

LCR131

Component Tester



- **Measures inductance, capacitance and resistance**
- **Dual display, dual parameter measurements**
- **Parallel/Series modes**
- **Relative mode for tolerance checking and select-on-test applications**
- **Real-time download to PC available**
- **0.5% basic accuracy**

DESCRIPTION

The LCR131 Component Tester is a portable instrument designed for quick, easy testing and analyzing of discrete electronic components in a broad range of applications. The unit will accurately measure values of inductance, capacitance and resistance at frequencies of 120 Hz and 1 kHz. The LCR131 provides a high 0.5% average accuracy and is capable of measuring electrolytic / ceramic capacitors, transformers, filter coils, speaker coils as well as standard LCR components. Additionally the instrument has many special features which have been included for a variety of differing applications.

Dual Display

The unique Dual Display allows the meter to simultaneously display both the numerical L/C/R values as well as D/Q (dissipation/quality) factor of any inductive or capacitive measurement. A secondary display can be set to show component values in terms of percentage when the tolerance mode is activated, as well as the status of Parallel or Series mode data.

Dual-Frequency

It is important for the user to test and evaluate components at similar measuring frequencies to the components' actual operating frequencies. The LCR131 Component Tester provides two of the most commonly used test frequencies 120 Hz and 1 kHz to simulate the actual component application condition. For example, a voice coil is generally rated at 1 kHz whereas power circuit applications are rated at 120 Hz.

Parallel/Series Mode

The LCR131 Component Tester is capable of showing all the measured values in series or parallel equivalent circuits. The parallel mode is the default for capacitance and resistance measurements and the series mode is the default for inductance measurement.

Tolerance Mode

The tolerance modes are 1%, 5% and 10% for the Inductance, Capacitance and Resistance functions. This feature has been designed for fast convenient component sorting, removing the necessity of the user having to take readings each time a new component is being measured. Once the tolerance mode has been selected, the meter will indicate a single "beep" for a component in tolerance and three consecutive "beeps" for components out of tolerance.

Static Recording

The Static Recording Function provides convenient statistical information when measuring bundles of components either in tape and reel or bulk packing. When testing a batch of similar components the values can automatically be stored into memory. Calculations are then performed in the static recording mode and the display will indicate the maximum value, the minimum value and the average value of the batch of components. An ideal feature when company quality procedures require routine or continuous testing of components during incoming goods inspection.

Calibration

This function is performed to calibrate the meter internally at both the upper and lower limits of each range. It will also calibrate externally to compensate for connector residues present whilst using test leads.

Relative Mode

This function is useful for value correlation and component comparison applications. By pressing the “REL” key the display will be set to zero, storing the present reading as the reference value. All subsequent readings in terms of their plus or minus value with comparison to the original stored value are then displayed.

APPLICATIONS

The instrument can be used in the Auto-range or Manual mode and is designed for measuring the value of discrete components. It is suited for use in field service applications and for laboratory or repair workshop requirements. Equally the advance features make it invaluable for batch checking of components in quality assurance and inspection situations. As well as measuring standard component parameters, the LCR131 can be used as a component analyzer for determining the Q and D factors.

Additionally, for use in varying applications, PC Software is available for real-time download of results into a spreadsheet.

SPECIFICATION**Features Include:**

Full auto-ranging, two major measuring methods: parallel and series mode, two selected frequencies, max/min/avg record, D/Q factor test mode, relative mode, calibration, tolerance mode, real-time download, auto power off.

Parameters Measurement

L.C.R and D/Q

Measurement Circuit Mode:

- 1) Capacitance/Resistance Measurement - Defaults to parallel mode for all ranges
- 2) Inductance Measurement - Defaults to series mode for all ranges. Both parallel and series mode data are available through simple key operation.

Display

4 $\frac{1}{2}$ digits (20000 count), dual parameter display

Ranging Mode

Auto and manual.

Test Frequency

1 kHz & 120 Hz.

Measurement Rate

1 measurement/second, normal.

Test Signal Level

1 measurement/second, normal.

Response Time

1 second/D/L/T (device under test) manual range

Power Supply

9 V Battery 6LF22 or equivalent.

Optional External Power Supply:

12 V d.c. (MIN)

15 V (MAX) load: 15 mA. double insulated for 250 V

Resistance Range

10 M Ω , 2 M Ω , 200 k Ω , 20 k Ω , 200 Ω , 20 Ω .

Accuracy

@ 10 M Ω \pm (2,0% +8 digits)

@ 2 M Ω \pm (0,5% +5 digits)

@ 200 k Ω \pm (0,5% +3 digits)

@ 20 k Ω \pm (0,5% +3 digits)

@ 2 k Ω \pm (0,5% +3 digits)

@ 200 Ω \pm (0,8% +5 digits)

@ 20 Ω \pm (1,2% +40 digits)

Inductance

Range 1000 H, 200 H, 20 H, 2 H, 200 mH, 20 mH, 2 mH

Accuracy

@ 1000 H	$\pm(1.0\% + (Lx/10000)\% + 5 \text{ digits})$ 120 Hz only
@ 200 H	$\pm(0.7\% + (Lx/10000)\% + 5 \text{ digits})$ 120 Hz
	$\pm(1.0\% + (Lx/10000)\% + 5 \text{ digits})$ 1 kHz
@ 20 H	$\pm(0.7\% + (Lx/10000)\% + 5 \text{ digits})$
@ 2 H	$\pm(0.7\% + (Lx/10000)\% + 5 \text{ digits})$
@ 200 mH	$\pm(1.0\% + (Lx/10000)\% + 5 \text{ digits})$ 120 Hz
	$\pm(0.7\% + (Lx/10000)\% + 5 \text{ digits})$ 1 kHz
@ 20 mH	$\pm(2.0\% + (Lx/10000)\% + 5 \text{ digits})$ 120 Hz
	$\pm(1.0\% + (Lx/10000)\% + 5 \text{ digits})$ 1 kHz
@ 2 mH	$\pm(2.0\% + (Lx/10000)\% + 5 \text{ digits})$ 1 kHz only

Capacitance

Range 10 mF, 1 mF, 200 μ F, 20 μ F, 2 μ F, 200 nF, 20 nF, 2 nF

Accuracy

@ 10 mF	$\pm(3.0\% + 5 \text{ digits})$ (DF < 0.1) 120 Hz only
@ 1 mF	$\pm(1.0\% + 5 \text{ digits})$ (DF < 0.1) 120 Hz
	$\pm(3.0\% + 5 \text{ digits})$ (DF < 0.1) 1 kHz
@ 200 μ F	$\pm(0.7\% + 3 \text{ digits})$ (DF < 0.5) 120 Hz
	$\pm(1.0\% + 5 \text{ digits})$ (DF < 0.1) 1 kHz
@ 20 μ F	$\pm(0.7\% + 3 \text{ digits})$ (DF < 0.5)
@ 2000 nF	$\pm(0.7\% + 3 \text{ digits})$ (DF < 0.5)
@ 200 nF	$\pm(0.7\% + 5 \text{ digits})$ (DF < 0.5) 120 Hz
	$\pm(0.7\% + 3 \text{ digits})$ (DF < 0.5) 1 kHz
@ 20 nF	$\pm(1.0\% + 5 \text{ digits})$ (DF < 0.1) 120 Hz
	$\pm(0.7\% + 5 \text{ digits})$ (DF < 0.5) 1 kHz
@ 2000 pF	$\pm(1.0\% + 5 \text{ digits})$ (DF < 0.1) 1 kHz only

Dimensions

184mm x 87mm x 41mm

Weight

330 gms

Safety

Meets IEC1010-1, instrument not intended to be used on live circuits.

EMC

In accordance with IEC 61326 including Amendment No.1.

ORDERING INFORMATION

Item (Qty)	Order No.
LCR131 Component Tester	LCR131-EN
Included Accessories	
Test lead with clips (150 mm)	
User guide	
Optional Accessories	
Download software	CP-09

UK
Archcliffe Road Dover
CT17 9EN England
T +44 (0) 1304 502101
F +44 (0) 1304 207342

UNITED STATES
4271 Bronze Way
Dallas TX 75237-1088 USA
T 800 723 2861 (USA only)
T +1 214 333 3201
F +1 214 331 7399

OTHER TECHNICAL SALES OFFICES
Norristown USA, Toronto CANADA,
Mumbai INDIA, Trappes FRANCE,
Sydney AUSTRALIA, Madrid SPAIN
and the Kingdom of BAHRAIN.

Registered to ISO 9001:2000 Reg no. Q 09290

Registered to ISO 14001 Reg no. EMS 61597

LCR131_DS_en_V01

www.megger.com
Megger is a registered trademark