

Model: Adonis-C1		Date: 26-Apr-00	No.: RA283002
Subject: ROM History (Adonis-C Fax Option)		Prepared by: M. Mano	
From: Technical Services Dept., GTS Division			
Classification:	<input type="checkbox"/> Troubleshooting <input type="checkbox"/> Part information <input type="checkbox"/> Action required <input type="checkbox"/> Mechanical <input type="checkbox"/> Electrical <input type="checkbox"/> Service manual revision <input type="checkbox"/> Paper path <input type="checkbox"/> Transmit/receive <input checked="" type="checkbox"/> Retrofit information <input type="checkbox"/> Other ()		

Firmware history for the Adonis-C Fax Option

A2855581	File No. (A285Uxxx)	Version	C.SUM	Production
A	001	16.01	91C6	1st Mass Prod.
B	002	18.00	ED65	April Prod. '00

Symptoms Corrected	USA
<i>When sending an original wider than the maximum paper width of the receiving machine (Auto-Reduction OFF / JBIG compression), the machine cuts the image to the smaller size but sends the left-most area of the image instead of the central area.</i>	B
<i>Even though the following bit switch settings should disable the File Retention function, the machine retains files for 24 hours: User Parameter switch 24 (swusr_18): (bit1, bit0) = (1, 0)</i>	B
<i>When bit 4 of Communication switch 07 is 1 (Fallback from G4 to G3 when G4 communication fails on the ISDN B-channel is enabled) and a G4 communication error occurs on the ISDN B-channel (ADF mode), the machine falls back to G3 and resumes transmission from the second page. This is because the first page has already fed out from the ADF.</i>	B

A2855581	A874-17
B	TBA~