


Synthesizer, SMT for RFID Covering all UHF Bands

M/A-COM Products
Rev. 2

Features

- Fully Integrated VCO, PLL, Loop Filter
- Includes TCXO with <10 PPM Stability
- Low Phase Noise
- High Performance, Low Cost
- Covers US, European and Japanese RFID Bands
- Lead-Free Land Grid Array Package
- Tape and Reel Packaging Available
- 260°C Reflow Compatible
- RoHS* Compliant

Functional Block Diagram



Ordering Information^{1, 4}

Model No.	Band	Frequency	Package
MASY-007028-0001TR	US	902 - 928 MHz	Tape and Reel
MASY-007028-000100	US	902 - 928 MHz	Bulk
MASY-007028-0001TB	US	902 - 928 MHz	Sample Board ²
MASY-007028-SW01TB	US	902 - 928 MHz	Sample Board ³
MASY-007028-0001TR	European	865 - 868 MHz	Tape and Reel
MASY-007028-000100	European	865 - 868 MHz	Bulk
MASY-007028-0001TB	European	865 - 868 MHz	Sample Board ²
MASY-007028-SW01TB	European	865 - 868 MHz	Sample Board ³
MASY-007028-0002TR	Japanese	950 - 956 MHz	Tape and Reel
MASY-007028-000200	Japanese	950 - 956 MHz	Bulk
MASY-007028-0002TB	Japanese	950 - 956 MHz	Sample Board ²
MASY-007028-SW02TB	Japanese	950 - 956 MHz	Sample Board ³

1. The US and European bands share the same part. The listings are separated to illustrate the different frequencies.
2. This is the synthesizer installed on a sample board. This does not include the evaluation software or the test cable.
3. This is the synthesizer installed on a sample board. It also includes software (including a brief manual on how to use the software), and a cable to interface with a Windows™ based PC having a parallel port.
4. Reference Application Note M513 for reel size information.

* Restrictions on Hazardous Substances, European Union Directive 2002/95/EC.

1

ADVANCED: Data Sheets contain information regarding a product M/A-COM is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.

- **North America** Tel: 800.366.2266 / Fax: 978.366.2266
- **Europe** Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- **Asia/Pacific** Tel: 81.44.844.8296 / Fax: 81.44.844.8298

Visit www.macom.com for additional data sheets and product information.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Electrical Specifications – US & European Bands⁵
T_A = +25°C, Z_o = 50 Ω, V_{DD1} = 3.3V, V_{DD2} = 3.3V

Parameter	Test Conditions	Units	Min	Typ	Max
Frequency Range	US Band European Band	MHz MHz	902 865	- -	928 868
Frequency Stability	Over T _{op} ⁶	ppm	-	-	10
RF Output Power	At 25°C Over T _{op} ⁶	dBm dBm	+4.0 +3.0	-	+6.2 +7.5
Phase Noise	SSB at 100 Hz offset from carrier SSB at 1 KHz offset from carrier SSB at 10 KHz offset from carrier SSB at 100 KHz offset from carrier SSB at 200 KHz offset from carrier SSB at 1 MHz offset from carrier SSB at 2 MHz offset from carrier SSB at 3 MHz offset from carrier	dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz	- - - - - - - -	-72 -75 -80 -112 -121 -135 -140 -142	- - - - - - - -
Phase Jitter	From 10 kHz to 100 kHz using brick wall filter	deg rms	-	0.34	-
Harmonic Suppression	2nd 3rd and higher 1.25 * F _o 1.5 * F _o Sub-harmonics	dBc dBc dBc dBc dBc	- - - - -	-35 -35 -80 -85 -80	-20 -25 -60 -60 -60
Spurious Suppression (Non-Harmonic)	Phase comparison frequency (± 50 KHz)	dBc	-	-65	-
Spurious Suppression (Non-Harmonic)	Reference breakthrough (± 16 MHz)	dBc	-	-80	-
Frequency Lock Time	Over F _{out} , PFD frequency = 50 KHz, Loop bandwidth = 5 KHz Measured to within ± 1 kHz Measured to within ± 10 Hz	us us	- -	700 800	- -
VDD1 ⁷	Recommended Operating Condition	V	+3.00	+3.30	+3.45
IDD1 ¹⁰	Recommended Operating Condition	mA	-	45	60
VDD2 ⁸	Recommended Operating Condition	V	+3.00	+3.30	+3.45
IDD2	Recommended Operating Condition	mA	-	25	35
RF Impedance	At RX_LO and TX_LO ⁹	Ω	-	50	-
Isolation	Between RX_LO and TX_LO	dB	-	20	-
Step Size	Over T _{op} ⁶	KHz	-	50	-
Output Frequencies	For US RFID readers, there are 50 equally spaced frequencies. The minimum and maximum frequencies are to the right. There are 49 steps with a step size of 500 KHz. For European RFID readers, there are 15 equally spaced frequencies. The minimum and maximum frequencies are to the right. There are 14 steps with a step size of 200 KHz	MHz MHz	902.750 865.100	- -	927.250 867.900
PLL Programming	3-wire serial CMOS in accordance with Analog Devices ADF4360-7.				

Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Electrical Specifications – Japanese Band⁵:
T_A = +25°C, Z_o = 50 Ω, V_{DD1} = 3.3V, V_{DD2} = 3.3V

Parameter	Test Conditions	Units	Min	Typ	Max
Frequency Range	Japanese Band	MHz	952	-	954
Frequency Stability	Over T _{op} ⁶	ppm	-	-	10
RF Output Power	At 25°C Over T _{op} ⁶	dBm dBm	+4.0 +3.0	-	+6.2 +7.5
Phase Noise	SSB at 100 Hz offset from carrier SSB at 1 KHz offset from carrier SSB at 10 KHz offset from carrier SSB at 100 KHz offset from carrier SSB at 200 KHz offset from carrier SSB at 1 MHz offset from carrier SSB at 2 MHz offset from carrier SSB at 3 MHz offset from carrier	dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz dBc/Hz	- - - - - - - - -	-74 -76 -81 -113 -120 -134 -136 -142	- - - - - - - - -
Phase Jitter	From 10 kHz to 100 kHz using brick wall filter	deg rms	-	0.34	-
Harmonic Suppression	2nd 3rd and higher 1.25 * F _o 1.5 * F _o Sub-harmonics	dBc dBc dBc dBc dBc	- - - - -	-35 -35 -80 -85 -80	-20 -25 -60 -60 -60
Spurious Suppression (Non-Harmonic)	Phase comparison frequency (± 200 KHz)	dBc	-	-75	-
Spurious Suppression (Non-Harmonic)	Reference breakthrough (± 16 MHz)	dBc	-	-80	-
Frequency Lock Time	Over F _{out} , PFD frequency = 200 KHz, Loop bandwidth = 5 KHz Measured to within ± 1 kHz Measured to within ± 10 Hz	us us	- -	700 800	-
VDD1 ⁷	Recommended Operating Condition	V	+3.00	+3.30	+3.45
IDD1 ¹⁰	Recommended Operating Condition	mA	-	45	60
VDD2 ⁸	Recommended Operating Condition	V	+3.00	+3.30	+3.45
IDD2	Recommended Operating Condition	mA	-	20	35
RF Impedance	At RX_LO and TX_LO ⁹	Ω	-	50	-
Isolation	Between RX_LO and TX_LO	dB	-	20	-
Step Size	Over T _{op} ⁶	KHz	-	200	-
Output Frequencies	For Japanese RFID readers, there are 9 equally spaced frequencies. The minimum and maximum frequencies are to the right. There are 8 steps with a step size of 200 KHz.	MHz	952.200	-	953.800
PLL Programming	3-wire serial CMOS in accordance with Analog Devices ADF4360-7.				

5. All specification limits are indicated values @ 25°C and apply over Fout unless otherwise indicated.
6. Top = -30°C to +70°C operating temperature.
7. VDD1 is the bias for the TCXO, VCO, and the synthesizer.
8. VDD2 is the bias for the amplifier.
9. Opposite port is terminated in 50 ohms.
10. IDD1 includes approximately 10 mA which drives an optional external Lock Detector LED.

**Synthesizer, SMT for RFID
Covering all UHF Bands**
**M/A-COM Products
Rev. 2**
Pin Configuration

Pin No.	Function	Pin No.	Function
1	GND	21	GND
2	GND	22	GND
3	GND	23	GND
4	GND	24	GND
5	RX_LO	25	CLK
6	GND	26	DATA
7	GND	27	LE
8	TX_LO	28	VDD1 ¹¹
9	GND	29	MUXOUT
10	GND	30	CE
11	VDD1 ¹¹	31	GND
12	GND	32	VDD1 ¹¹
13	GND	33	GND
14	GND	34	GND
15	GND	35	VDD2
16	GND	36	GND
17	GND	37	GND
18	GND	38	GND
19	GND	39	GND
20	GND	40	GND

11. Pins 11, 28, and 32 are not tied together on the synthesizer.
They all must be tied together on the PC Board

Absolute Maximum Ratings^{12,13}

Parameter	Absolute Maximum
VDD1 to GND	-0.3V to +3.9V
VDD2 to GND	-0.3V to +6.0V
CLK, DATA, LE, MUXOUT	-0.3V to VDD1 + 0.3V
Operating Temperature	-30°C to +70°C
Storage Temperature	-40°C to +125°C


12. Exceeding any one or combination of these limits may cause permanent damage to this device.
13. M/A-COM does not recommend sustained operation near these survivability limits.

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity

Silicon and Gallium Arsenide Integrated Circuits are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.

Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Recommended PCB Configuration^{14,15,16}



14. Corner locators are needed for manual placement and are strongly recommended.
15. Soldermask should be line to line with the pads on the bottom of the part.
16. Soldermask should be cleared 15 mils outside the corner locators. This ensures that they are easily visible.

Synthesizer, SMT for RFID Covering all UHF Bands


M/A-COM Products
Rev. 2

Typical Performance Curves


Output Power vs. Temperature: VDD1 & VDD2 = 3.3V
MASY-007028-000100, US Band




Output Power vs. Temperature: VDD1 & VDD2 = 3.3V
MASY-007028-000100, European Band




Output Power vs. Temperature: VDD1 & VDD2 = 3.0V
MASY-007028-000100, US Band




Output Power vs. Temperature: VDD1 & VDD2 = 3.0V
MASY-007028-000100, European Band



Output Power vs. Temperature: VDD1 & VDD2 = 3.45V
MASY-007028-000100, US Band



Output Power vs. Temperature: VDD1 & VDD2 = 3.45V
MASY-007028-000100, European Band



ADVANCED: Data Sheets contain information regarding a product M/A-COM is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.





PRELIMINARY: Data Sheets contain information regarding a product M/A-COM has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.





- **North America** Tel: 800.366.2266 / Fax: 978.366.2266
- **Europe** Tel: 44.1908.574.200 / Fax: 44.1908.574.300

• **Asia/Pacific** Tel: 81.44.844.8296 / Fax: 81.44.844.8298

Visit www.macom.com for additional data sheets and product information.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Typical Performance Curves
SSB Phase Noise
MASY-007028-000100, US & European Band

Harmonics vs. Frequency: VDD1 & VDD2 = 3.3V, 25°C
MASY-007028-000100, US Band

Harmonics vs. Frequency: VDD1 & VDD2 = 3.3V, 25°C
MASY-007028-000100, European Band

Output Power vs. Temperature: VDD1 & VDD2 = 3.3V
MASY-007028-000200, Japanese Band


Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Typical Performance Curves
Output Power vs. Temperature: VDD1 & VDD2 = 3.0V
MASY-007028-000200, Japanese Band

Output Power vs. Temperature: VDD1 & VDD2 = 3.45V
MASY-007028-000200, Japanese Band

SSB Phase Noise
MASY-007028-000200, Japanese Band

Harmonics vs. Frequency: VDD1 & VDD2 = 3.3V, 25°C
MASY-007028-000200, Japanese Band



Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Sample Board Pin Configuration
Pin Configuration J1


Pin No.	Function	Pin No.	Function
1	GND	6	VDD1
2	GND	7	LE
3	CE	8	VDD2
4	MUXOUT	9	J2-6 (D4)
5	SCOPE- TRIGGER ¹⁸	10	GND

Pin Configuration J2¹⁷


Pin No.	Function
1	NC
2	DATA
3	CLK
4	GND
5	TP1 (D5) ¹⁹
6	D4 ¹⁹
7	LE
8	SCOPE-TRIGGER
9	GND

17. J2 is Tyco Electronics P/N 5747840-5.
18. This signal is provided by the test software supplied with the sample boards. The signal comes in on the cable from the parallel port of the computer.
19. D4 and D5 are uncommitted PC Parallel Port data bits.



Synthesizer, SMT for RFID
Covering all UHF Bands
M/A-COM Products
Rev. 2
Sample Board Schematic and Bill of Material


Qty	Part Number	Description	Reference Designator
1		Resistor, 100 ohm, 1%, 1/16W, 0402	R4
3		Resistor, 10K, 1%, 1/16W, 0402	R1, R2, R3, R7
2		Capacitor, 1000pF, 10%, 50V, 0402, COG	C2, C4
2		Capacitor, 10 uF, 10%, 6.3V, 0805, X5R	C1, C3
1	1000026283-0000001	LED, 0603, Green (Ledtronics)	LED1
2	142-0701-801	Connector, SMA, End Launch Jack	J3, J4
1	5747840-5	Connector, 9P, 90 Deg, Plug, Through (Tycoelectronics)	J2
1	MASY-007028-000100	RFID Synthesizer (M/A-COM)	U1
2	RK73Z-1JT	Resistor, 0 ohm, 1.0A MAX, 0603	R5, R6
1	TSM-105-01-S-DV	Connector, Termstrip, 10P_2R, .230 Post Height	J1

**Synthesizer, SMT for RFID
Covering all UHF Bands**
**M/A-COM Products
Rev. 2**
Test Cable that is provided with MASY-007028-SWxxTB^{20,21}


20. Length is 72 inches
21. Connector pins are gold.

Wiring Chart

DB25M	DB9F
PIN 8	PIN 1
PIN 3	PIN 2
PIN 2	PIN 3
PIN 20	PIN 4
PIN 7	PIN 5
PIN 6	PIN 6
PIN 4	PIN 7
PIN 5	PIN 8
PIN 22	PIN 9
SHELL	SHELL

ADVANCED: Data Sheets contain information regarding a product M/A-COM is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.

- **North America** Tel: 800.366.2266 / Fax: 978.366.2266
- **Europe** Tel: 44.1908.574.200 / Fax: 44.1908.574.300

• **Asia/Pacific** Tel: 81.44.844.8296 / Fax: 81.44.844.8298



Visit www.macom.com for additional data sheets and product information.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Synthesizer, SMT for RFID Covering all UHF Bands

M/A-COM Products

Land Grid Array Outline Drawing[†]



The PC Board Configuration contains detailed pad sizes and locations.

[†] Reference Application Note M538 for lead-free solder reflow recommendations.

12

ADVANCED: Data Sheets contain information regarding a product M/A-COM is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume not guaranteed.

- **North America** Tel: 800.366.2266 / Fax: 978.366.2266
 - **Europe** Tel: 44.1908.574.200 / Fax: 44.1908.574.300
 - **Asia/Pacific** Tel: 81.14.844.8296 / Fax: 81.14.844.8298

Visit www.macom.com for additional data sheets and product information.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.