


Data Sheet

Tag-it™ HF-I

Transponder Inlay

Rectangle - Miniature



Specifications:

Part Number	RI-I03-112A
Supported Standard	ISO 15693-2,-3
Recommended Operating frequency	13.56 MHz
Passive Resonance Frequency (at +25°C)	13.86 MHz ± 300kHz (includes frequency offset to compensate further integration into paper or PVC)
Max. required activation field strength read (at +25°C)	109 dBμA/m (preliminary value)
Typ. required activation field strength write (at +25°C)	111 dBμA/m (preliminary value)
Factory programmed Read Only Number	64 bits
Memory (user programmable)	2k bits organized in 64 x 32-bit blocks
Typical programming cycles (at +25°C)	100,000
Data retention time (at +55°C)	> 10 years
Simultaneous Identification of Tags	Up to 50 tags per second (reader/antenna dependant)
Antenna size	22.5 mm x 38 mm (~0.89 x ~1.5 in)
Foil width	48 mm ± 0.5 mm (1.89 in ± 0.02 in)
Foil pitch	48 mm +0.1mm/-0.4mm (~1.89 in)
Thickness	Chip: 0.355mm (~0.014 in) Antenna: 0.085mm (~0.0033 in)
Base material	Substrate: PET (Polyethylenetherephthalate) Antenna: Aluminum
Smallest bending radius allowed	18 mm (~0.71 in)
Operating temperature	-25°C to +70°C
Storage temperature (single inlay)	-40°C to +85°C (warpage may occur with increasing temperature)
Storage temperature (on reel)	-40°C to +40°C
Delivery	Single row tape wound on cardboard reel with 500 mm diameter Reel width: approx. 60 mm (~2.36 in); inside 50 mm (~1.97 in) Hub diameter: 76.2 mm (3 in)
Typical quantity per reel	5,000

Note: For highest possible read-out coverage we recommend to operate readers at a modulation depth of 20% or higher

For more information, contact the sales office or distributor nearest you. This contact information can be found on our web site at: <http://www.ti-rfid.com>


Texas Instruments reserves the right to change its products and services at any time without notice. TI provides customer assistance in various technical areas, but does not have full access to data concerning the uses and applications of customers products. Therefore, TI assumes no responsibility for customer product design or for infringement of patents and/or the rights of third parties, which may result from assistance provided by TI.

Supported Command Set

		Request Mode				
Request	Request Code	Inventory.	Addressed.	Non-Addressed.	Select	AFI
ISO 15693 Mandatory and Optional Commands						
Inventory	0x01	✓	-	-	-	✓
Stay Quiet	0x02	-	✓	-	-	-
Read_Single_Block	0x20	✓	✓	✓	✓	✓
Write_Single_Block	0x21	-	✓	✓	✓	-
Lock_Block	0x22	-	✓	✓	✓	-
Read_Multi_Blocks	0x23	✓	✓	✓	✓	✓
Write_Multi_Blocks	0x24	-	-	-	-	-
Select Tag	0x25	-	✓	-	-	-
Reset to Ready	0x26	-	✓	-	✓	-
Write_AFI	0x27	-	✓	✓	✓	-
Lock_AFI	0x28	-	✓	✓	✓	-
Write_DSFD	0x29	-	✓	✓	✓	-
Lock_DSFD	0x2A	-	✓	✓	✓	-
Get_System_info	0x2B	✓	✓	✓	✓	✓
Get_M_Blk_Sec_St	0x2C	✓	✓	✓	✓	✓
TI Custom Commands						
Write_2_Blocks	0xA2	-	✓	✓	✓	-
Lock_2_Blocks	0xA3	-	✓	✓	✓	-

✓: Implemented
-: Not applicable

Memory Organization



Texas Instruments reserves the right to change its products and services at any time without notice. TI provides customer assistance in various technical areas, but does not have full access to data concerning the uses and applications of customers products. Therefore, TI assumes no responsibility for customer product design or for infringement of patents and/or the rights of third parties, which may result from assistance provided by TI.