



TOSLKF50A-40 Calibration Kit

Type K(f)
DC to 40 GHz, 50 Ω

This calibration kit has been designed to provide superior measurement results when used with precision instruments. It is designed for use in both field and lab environments. It is a high precision component and should be handled with proper care. Excessive shock, torque, or power should be avoided to prevent permanent damage.

Specifications for units within recommended calibration cycle are guaranteed under the following conditions:

1. Unit is operated within specified temperature range.
2. Unit has not been subjected to damage from mishandling.

Length, capacitance, and inductance are nominal values.

Through Return Loss and Insertion Loss and DC Resistance specifications are typical. Phase is measured as a deviation from the model defined by offset length and inductance or capacitance.

Operating Temperature Range	-10 °C to +55 °C (MIL-PRF-28800F, Class 2)
Storage Temperature Range	-51 °C to +71 °C (MIL-PRF-28800F, Class 2)
Recommended Calibration Interval	1 year

For the latest information, sales, or service, visit: www.anritsu.com

TOSLKF50A-40 Calibration Kit TDS
Copyright October 2013 Anritsu Company, USA
All Rights Reserved



11410-00744

® Anritsu All trademarks are registered trademarks of their respective companies.
Data subject to change without notice. Anritsu prints on recycled paper with
vegetable soybean oil ink.



A



TOSLKF50A-40 Calibration Kit Specifications

Through (Thru)	Spec	Open	Spec	Short	Spec	Load	Spec
Length	16.07 mm	Length	5.01 mm	Length	5.01 mm	DC Resistance	$50 \Omega \pm 0.25 \Omega$
Return Loss (DC to 10 GHz)	≥ 34 dB	C0 (1E-15) F	5.000	L0 (1E-12) H	8.000	Return Loss (DC to 10 GHz)	≥ 42 dB
Return Loss (10 to 20 GHz)	≥ 32 dB	C1 (1E-27) F/Hz	0.000	L1 (1E-24) H/Hz	-995.000	Return Loss (10 to 20 GHz)	≥ 36 dB
Return Loss (20 to 30 GHz)	≥ 30 dB	C2 (1E-36) F/Hz ²	1.500	L2 (1E-33) H/Hz ²	33.000	Return Loss (20 to 30 GHz)	≥ 32 dB
Return Loss (30 to 40 GHz)	≥ 30 dB	C3 (1E-45) F/Hz ³	0.100	L3 (1E-42) H/Hz ³	-0.290	Return Loss (30 to 40 GHz)	≥ 30 dB
Insertion Loss (DC to 40 GHz)	$\leq 0.025 \times \sqrt{f/\text{GHz}}$ dB	Phase (DC to 10 GHz)	$\leq \pm 1.5^\circ$	Phase (DC to 10 GHz)	$\leq \pm 1.5^\circ$	Max Power	0.5 W
		Phase (10 to 20 GHz)	$\leq \pm 3.0^\circ$	Phase (10 to 20 GHz)	$\leq \pm 2.5^\circ$		
		Phase (20 to 30 GHz)	$\leq \pm 4.5^\circ$	Phase (20 to 30 GHz)	$\leq \pm 4.0^\circ$		
		Phase (30 to 40 GHz)	$\leq \pm 6.0^\circ$	Phase (30 to 40 GHz)	$\leq \pm 5.5^\circ$		