

MAC2000 MANUAL CONTROLLER

FEATURES

- Direct Digital Synthesized sine wave
- Adjustable Volts & Current limit
- Fixed & adjustable frequency
- Three DMM displays
- Front panel or remote control



CONTROLLER WITH ADJUSTABLE VOLTS, FREQUENCY & CONSTANT CURRENT LIMIT

Behlman's MAC 2000 Manual Controller utilizes a Direct Digital Synthesizer to generate a precise sine wave to drive the power amplifiers. The MAC 2000 is available as either a (–1), single phase or (–3), three phase controller. The controller can set voltage, frequency, current limit, output on/off and correct for line-drop over distance. The controller can also make fundamental measurements on the output of the amplifier of volts, current and frequency and can be set manually via front panel controls or remotely using an analog (0-10 VDC) input.

SETTING CAPABILITY

Voltage:	Adjustable (0 to Full Scale) VAC, L-N, 1-phase or 3-phase
Frequency:	Three fixed frequencies of 50 Hz, 60 Hz and 400 Hz and adjustable frequency from 45 to 500 Hz
Constant Current Limit:	Adjustable from 0.5 A to full current. Overload automatically causes voltage fold-back to provide constant current without distorting output waveform.

MEASUREMENT and DISPLAY CAPABILITY

	Resolution	Accuracy
Voltage RMS	1.0 V	0.25% of FS +/- 1 V
Current RMS	0.1 A	0.5% of FS +/- 0.1 A
Frequency	1.0 Hz	+/- 0.1 Hz

CONTROLS and INDICATORS

Frequency select:	Four position switch for 50 Hz, 60 Hz, 400 Hz and variable frequency of 45 to 500 Hz
Meter:	Three DMM's; Frequency, True RMS Amps and True RMS Volts
Frequency adjust:	Ten-turn pot to adjust frequency
Phase select switch:	Four position switch for Phase A, B, C, volts and amps, & CC; constant current select
Constant current:	Recessed potentiometer and display, adjustable from 10% to full scale
Voltage adjust:	Ten-turn pot to adjust voltage
Indicators:	Overload Latch, Constant Current, Over Temp, Output On
Output On/Off:	Pushbutton switch
Line drop compensation:	Three recessed potentiometers for 10% adjustment of Phase A, B, C
Local remote:	Slide switch to select front panel or remote control
Reset	Reset to default condition

MECHANICAL & ENVIRONMENTAL

Dimensions	3.5"H X 17"W X 12"D, Rack Mount chassis
Weight	13 lbs.
Temperature	0° to 50° C
Connections	
Input (Line Power)	J1- IEC320-C20 receptacle
Phase B & C Meas.	J2- 9 pin D connector
Amplifier Interface	J3- 9 pin D connector
Phase A Meas.	
& Relay control	J4- 9 pin D connector
Remote Analog	J5- 9 pin D connector(with Option A only)



OPTIONS:

contact factory for additional options including custom input and output

A	Remote Analog Interface
WF	"Wild Frequency" range of 350 to 880 Hz

MODEL SELECTION GUIDE

MAC 2000-1 (single-phase) or -3 (three-phase) - Options

www.behlman.com

ORBIT POWER GROUP
Behlman Electronics

Headquarters:
80 Cabot Court, Hauppauge, NY 11788
631 435-0410 800 874-6727
Fax: 631 951-4341

2363 Teller Road, Suite 108
Newbury Park, CA 91320
805 375-7046 800 456-2006
Fax: 805 498-2147

sales@behlman.com