

## **Contents**

1	Checking Out Your Gateway 600	. 1
1	Front Left side Right side Back Bottom Keyboard area Identifying your model Gateway model number Gateway serial number Internal wireless label Microsoft Certificate of Authenticity Finding your specifications Accessories	. 2 . 3 . 6 . 8 . 10 . 12 . 12 . 13 . 13
_		
2	Getting Started	
	Connecting the AC adapter	
	Protecting from power source problems	
	Starting your notebook	
	Waking up your notebook	
	Turning off your notebook	
	Restarting (rebooting) your notebook	
	Status indicators	
	Key types	
	System key combinations	
	Multi-function buttons	
	Using the EZ Pad touchpad	
	Using the touchpad	
	Connecting the modem	36
	Connecting to a wired Ethernet network	
	Broadband Internet connections	
	Installing a printer, scanner, or other peripheral device	38
3	Getting Help	30
J	•	
	HelpSpot	
	Searching for a topic	
	HelpSpot videos Online help	
	- Othilie Help	-+4

	Gateway Web site	
	Using eSupport	.46
4	Windows Basics	.47
-	About the Windows environment	
	Using the desktop	
	Using the Start menu	
	Adding icons to the desktop	
	Identifying window items	
	Working with files and folders	
	Viewing drives	
	Creating folders	
	Copying and moving files and folders	
	Deleting files and folders	
	Browsing for files and folders	
	Searching for files	
	Using the Windows Search utility	.63
	Working with documents	
	Creating a new document	
	Saving a document	
	Opening a document	.67
	Printing a document	.68
	Shortcuts	.69
5	Using the Internet	71
J	•	
	Learning about the Internet	
	Setting up an Internet account	
	Accessing your Internet account	
	Using the World Wide Web	
	Connecting to a Web site	
	Downloading files	
	Using e-mail	
	Sending e-mail	
	Checking your e-mail	.79
6	Using Multimedia	.81
	Using the diskette drive	.82
	Using the DVD or recordable CD drive	
	Identifying drive types	
		.04
	Inserting a CD or DVD	.85

	Adjusting the volume in Windows 2000	
	Using Audio DJ	
	Audio DJ controls	
	Playing your play channels	
	Listening to CDs	
	Listening to CDs in Windows XP	
	Listening to CDs in Windows AF	
	Recording and playing audio	
	Playing audio and video files with the Windows Media Player	
	Using MusicMatch	
	Playing CDs	
	Creating MP3 music files	
	Editing track information	
	Building a music library	
	Changing the music library display settings	
	Listening to Internet radio	
	Using advanced features	
	Using a recordable CD drive	
	Creating data CDs	
	Creating music CDs	
	Copying CDs	
	Playing a DVD	
	Viewing the display on a television	128
		128
7	Viewing the display on a television	128 131
7	Viewing the display on a television	128 131 <b>133</b>
7	Viewing the display on a television	128 131 <b>133</b> 134
7	Viewing the display on a television	128 131 <b>133</b> 134 134
7	Viewing the display on a television	128 131 <b>133</b> 134 134 135
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes  Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows XP Sending a simple fax	128 131 <b>133</b> 134 134 135 137 139
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template	128 131 <b>133</b> 134 135 137 139 140
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes  Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs	128 131 <b>133</b> 134 135 137 139 140 141
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes  Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document	128 131 133 134 135 137 139 140 141 142
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes  Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax	128 131 133 134 135 137 139 140 141 142 142
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes  Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000  Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax	128 131 133 134 135 137 139 140 141 142 142 143
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax Automatically retry sending a fax in Windows XP	128 131 133 134 135 137 139 140 141 142 142 143 144
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes  Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000  Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax	128 131 133 134 135 137 139 140 141 142 142 143 144
	Viewing the display on a television Capturing video  Sending and Receiving Faxes Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax Automatically retry sending a fax in Windows XP Automatically cancelling a fax in Windows XP	128 131 133 134 135 137 139 140 141 142 143 144 145
7	Viewing the display on a television Capturing video  Sending and Receiving Faxes Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax Automatically retry sending a fax in Windows XP Automatically cancelling a fax in Windows XP  Managing Power	128 131 133 134 135 137 139 140 141 142 143 144 145
	Viewing the display on a television Capturing video  Sending and Receiving Faxes Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax Automatically retry sending a fax in Windows XP Automatically cancelling a fax in Windows XP  Managing Power  Monitoring the battery charge	128 131 133 134 135 137 139 140 141 142 143 144 145 <b>147</b>
	Viewing the display on a television Capturing video  Sending and Receiving Faxes Installing and configuring Fax Installing Fax in Windows XP Configuring Fax in Windows XP Configuring Fax in Windows 2000 Sending a simple fax Setting up your cover page template Faxing from programs Faxing a scanned document Receiving and viewing a fax Canceling a fax Automatically retry sending a fax in Windows XP Automatically cancelling a fax in Windows XP  Managing Power	128 131 133 134 135 137 139 140 141 142 143 144 145 <b>147</b>

	Recalibrating the battery	150
	Changing batteries	
	Replacing the main battery	
	Installing a secondary battery	
	Extending battery life	
	Conserving battery power	
	Using alternate power sources	
	Changing power modes	
	Changing power settings	
	Changing the power scheme	
	Changing alarm options	
	Changing advanced settings	
	Activating and using Hibernate mode	
	Changing SpeedStep settings	164
9	Travel Tips	167
9	•	
	Modem	
	Radio frequency wireless connections	
	Files	
	Power	
	Additional tips	
	Additional tips	/ .
10	Customizing Your Computer	173
	Adjusting the screen and desktop settings	
	Adjusting the color depth	
	Adjusting the screen resolution	
	Changing the colors on your Windows desktop	
	Changing the desktop background	
	Selecting a screen saver	
	Changing the touchpad settings	
	Adding and modifying user accounts	
11	Networking Your Computer	189
	Benefits of networking	190
	Sharing a single Internet connection	190
	Sharing drives	190
	Sharing peripheral devices	
	Streaming audio and video files	
	Playing multi-player games	
	Selecting a network connection	
	Wired Ethernet network	192

	Wireless Ethernet (IEEE 802.11a or IEEE 802.11b) network	
	Using a wired Ethernet network	
	Ethernet, Fast Ethernet, or Gigabit Ethernet	
	Example wired Ethernet network	
	Equipment you need for a wired Ethernet network	
	Using a wireless Ethernet network	
	Example access point wireless Ethernet network	
	Equipment you need for an access point wireless Ethernet network	
	Example peer-to-peer wireless Ethernet network	
	Equipment you need for a peer-to-peer wireless Ethernet network	
	For more information	
	Using your notebook on a network	
	Installing and configuring your notebook for Ethernet networking	
	Turning your wireless Ethernet on or off	. 201
12	Moving from Your Old Computer	. 203
	Using the Windows XP Files and Settings Transfer Wizard	. 204
	Transferring files	. 205
	Finding your files	. 205
	Transferring Internet settings	. 207
	Setting up your ISP	. 207
	Transferring your e-mail and address book	
	Transferring your Internet shortcuts	. 208
	Installing your old printer or scanner	. 208
	Installing a USB printer or scanner	. 208
	Installing a parallel port printer	. 209
	Installing your old programs	. 210
13	Maintaining Your Computer	. 211
	Caring for your computer	. 212
	Creating an emergency startup diskette	
	Protecting your computer from viruses	
	Managing hard drive space	
	Checking hard drive space	
	Using Disk Cleanup	
	Checking the hard drive for errors	
	Defragmenting the hard drive	
	Backing up files	
	Using the Scheduled Task Wizard	
	Cleaning your computer	
	Cleaning the exterior	
	Cleaning the keyboard	
	Cleaning the computer screen	

	Cleaning the mouse	.229
14	Restoring Software  Using the Restoration CDs  Reinstalling device drivers  Updating device drivers	.232 .233
	Reinstalling programs	
15	Upgrading Your Notebook	.243
	Adding and removing a PC Card	.244 .246 .249
	Replacing the main hard drive kit	
16	Using the Gateway 600 Port Replicator	250
	Front Back Connecting to the port replicator Attaching to the port replicator Disconnecting from the port replicator Securing your port replicator	.260 .261 .263 .263
17	Troubleshooting	.267
	Safety guidelines First steps Software support tools Troubleshooting CD or DVD drives Cleaning CDs or DVDs Device installation Diskette drive Display File management Hard drive Internet Keyboard	.268 .269 .270 .270 .272 .272 .273 .274 .275 .276
	Memory	
	Modem	.284

	Passwords	285
	PC Cards	286
	Power	286
	Printer	287
	Sound	289
	Touchpad	289
	Video	290
	Telephone support	291
	Before calling Gateway Technical Support	291
	Telephone numbers	292
	Tutoring and training	293
	Self-help	293
	Tutoring	293
	Training	294
_		
Α	Safety, Regulatory, and Legal Information	295
Ind	dex	307

## Checking Out Your Gateway 600

This chapter introduces you to the basic features of your notebook. Read this chapter to learn:

- How to identify the features of your Gateway notebook
- How to locate your notebook's model and serial number
- How to locate the Microsoft Certificate of Authenticity
- How to locate the specifications for your notebook
- What accessories are available for your notebook

#### **Tips & Tricks**




To access the contents of this guide while you are traveling, click **Start**, **All Programs**, then click **Gateway Utilities**. You can also download an electronic copy from <a href="https://www.gateway.com/support/manlib/">www.gateway.com/support/manlib/</a>.

Thank you for purchasing this Factory Service Manual CD/DVD from servicemanuals4u.com.

Please check out our eBay auctions for more great deals on Factory Service Manuals:

## servicemanuals4u

## **Front**



Component	Icon	Description
Audio DJ controls		Control the built-in .MP3 and audio CD player. The volume buttons control the volume level of the built-in speakers and headphones plugged into the headphone jack. The play/pause, back, next, and stop buttons may control multimedia programs such as Windows Media Player, Windows CD Player, MusicMatch, and the InterVideo DVD Player. For more information, see "Using Audio DJ" on page 91.
LCD panel release latch		Open the LCD panel by pressing the release latch.
Battery charge indicator	[ <del>+</del> )	The LED shows the battery activity and status.  LED green - battery is fully charged.  LED orange - battery is charging.  LED red - battery is malfunctioning.  This LED only lights up when the notebook is plugged in.
Power indicator	Ф	Lights up when the notebook is turned on and shows notebook power status.  LED on - power is on.  LED blinking - power is in Standby mode.  LED off - power is off.

### Left side



Component	Icon	Description	
PC Card eject buttons		Press one of the eject buttons to remove a PC Card from a PC Card slot. For more information, see "Adding and removing a PC Card" on page 244.	
PC Card slots		Insert one or two Type II, or one Type III PC Card into these slots. For more information, see "Adding and removing a PC Card" on page 244.	
Left-side modular bay	<b>Ū</b>	Use this bay for a DVD, CD-RW, or combination DVD/CD-RW drive, a diskette drive, or a second hard drive. For more information, see "Changing drives" on page 246.  To determine the type of drive in the modular bay, examine the drive tray's plastic cover and compare the logo to those listed in "Identifying drive types" on page 84.	
S/PDIF digital audio jack	<b>(</b> ]	Plug an optical (Toslink) AC-3 digital audio cable into this jack.	
Microphone jack	B	Plug a microphone into this jack. The built-in microphone is turned off when a microphone is plugged into this jack. For the location of your built-in microphone, see "Keyboard area" on page 10.	

3

Component	Icon	Description
Headphone jack		Plug amplified speakers or headphones into this jack. The built-in speakers are turned off when speakers or headphones are plugged into this jack.
		The headphone jack on the port replicator is turned off when headphones are plugged into this jack.
Line in jack	(( <del>&lt;))</del>	Connect an external audio input source (such as a stereo) to this jack so that you can record sound on your notebook or play sound through the notebook speakers.
IEEE 1394 port	N	Plug an IEEE 1394 (also known as Firewire <sup>®</sup> or i.Link <sup>®</sup> ) device (such as a digital camcorder) into this 4-pin IEEE 1394 port.


## Right side



Component	Icon	Description
Ventilation fan		Helps cool internal components. Do not block or insert objects into these slots.
Right-side modular bay	<b></b>	Use this bay for a secondary battery, a DVD, CD-RW, or combination DVD/CD-RW drive, a diskette drive, or a second hard drive. For more information, see "Changing drives" on page 246.
		To determine the type of drive in the modular bay, examine the drive tray's plastic cover and compare the logo to those listed in "Identifying drive types" on page 84.
USB ports	●~	Plug USB (Universal Serial Bus) devices (such as a USB lomega™ Zip™ drive, printer, scanner, camera, keyboard, or mouse) into these ports.
Kensington™ lock slot	K	Secure your computer to an object by connecting a Kensington cable lock to this slot.

5


## **Back**



Component	Icon	Description	
TV out jack	<b>-</b>	Plug a television into this jack so that you can view your display on a television using NTSC/PAL composite video. For more information, see "Viewing the display on a television" on page 128.	
Monitor port		Plug an analog VGA monitor into this port.	
Parallel port		Plug a parallel device (such as a printer) into this port.	
Ventilation fan		Cools internal components. Do not block or insert objects into these slots.	
Modem jack		Plug a modem cable into this jack. For more information, see "Connecting the modem" on page 36.	
Ethernet jack	盎	Plug a 10/100 Ethernet network cable into this jack. For more information, see "Connecting to a wired Ethernet network" on page 37 and "Networking Your Computer" on page 189.	

Component	Icon	Description	
Serial port		Plug a serial device (such as a digital camera) into this port.	
Power connector	===	Plug the AC adapter cable into this connector.	
PS/2 port	ጬ/	Plug a PS/2 device (such as a keyboard or mouse) into this port. Attaching a PS/2 mouse or keyboard to your notebook may deactivate the touchpad or built-in keyboard.	

## **Bottom**




Component	Icon	Description	
Docking port		Connect the port replicator to this port.  Warning! Power is passed through this port. This docking connection is certified to UL 1950 for use only with port replicators designed for your Gateway notebook.	
Mini PCI bay		The optional wireless Ethernet mini PCI card is located in this bay.	
System label		Includes the product model number. For more information, see "Identifying your model" on page 12.	
Reset hole	C	Insert a straightened paper clip into this hole to manually restart the notebook.	
Hard drive bay		The main hard drive kit is located in this bay. For more information, see "Replacing the main hard drive kit" on page 255.	

Component	Icon	Description	
Battery bay	I +)	Insert the main battery into this bay. For more information, see "Changing batteries" on page 151.	
Memory bay		Install as many as two memory modules into this bay. For more information, see "Adding or replacing memory" on page 251.	

## Keyboard area

For information on using your keyboard, see "Using the keyboard" on page 28.



Component	Icon	Description
Multi-function buttons		Press these buttons to open programs assigned to them. These buttons are set to open your default e-mail program, your default Web browser, online help, and the <i>My Computer</i> window. For more information, see "Multi-function buttons" on page 32.
Speakers		Provide audio output when headphones or amplified speakers are not plugged in.
Touchpad		Provides all the functionality of a mouse. For more information, see "Using the EZ Pad touchpad" on page 33.
Microphone	B	Record audio through this microphone. The built-in microphone is turned off while an external microphone is connected. For the location of your microphone jack, see "Left side" on page 3.
Keyboard		Provides all the features of a full-sized 86-key keyboard. For more information, see "Using the keyboard" on page 28.
Power button	Ф	Press to turn the power on or off. You can also configure the power button for Standby/Resume mode. For more information on configuring the power button mode, see "Changing power settings" on page 158.
Status indicators		Inform you when a drive is in use or when a button has been pressed that affects how the keyboard is used. For more information, see "Status indicators" on page 26.

## Identifying your model


#### **Important**



The labels shown in this section are for informational purposes only. Label information varies by model, features ordered, and location.

#### **Gateway model number**

The label on the bottom of your notebook contains information that identifies your notebook model and its features. Gateway Technical Support will need this information if you call for assistance.



#### **Gateway serial number**

You can locate the Gateway serial number:

- Printed on a white sticker on the bottom or back of your notebook.
- Printed on the customer invoice that came with your notebook. The invoice also contains your customer ID number.
- Displayed in HelpSpot in Windows XP. Click Start, Help and Support, then click View product serial number.

#### Internal wireless label

A label similar to the following indicates your computer contains a wireless communications device. The label is located on the bottom of your notebook.

IEEE 802.11b RLAN Approvals: FCC ID HFS9550015318 CANADA ID 1787104509A

#### **Microsoft Certificate of Authenticity**

The Microsoft Certificate of Authenticity label found on the bottom of your notebook includes the product key code for your operating system.




## Finding your specifications

For more information about your computer, such as memory size, memory type, and hard drive size, go to the **My Computer Info** link in *HelpSpot* or visit Gateway's *eSupport* page at <u>support.gateway.com</u>. The *eSupport* page also has links to additional Gateway documentation and detailed specifications.

In Windows XP, view your computer's serial number by clicking Start, Help and Support, then clicking View system serial number. Check your specifications by clicking Start, Help and Support, then clicking See your PC's configuration.



You can also find out more about your computer at the Gateway *eSupport* site. Visit <u>support.gateway.com</u>.



#### **Accessories**

Gateway offers accessories that can help you make the most of using your notebook. To order accessories, visit the Accessory Store at accessories.gateway.com.

#### Batteries and automobile/airplane power adapters

If you run your notebook on battery power for extended periods, you may want to buy an additional battery so that you can swap batteries when necessary. See "Changing batteries" on page 151 for more information about using an additional main battery and "Installing a secondary battery" on page 153 for more information about using a secondary battery in your notebook.

With an automobile/airplane power adapter, you can save battery power by plugging your notebook into an automobile cigarette lighter or an airplane in-flight power receptacle.

#### Carrying cases

Gateway has large-capacity carrying cases if you need additional space for accessories or supplies.

#### Port replicators

Although you can attach devices directly to your notebook, a port replicator lets you make all of those connections at one time. When you travel with your notebook, you merely disconnect from the port replicator instead of unplugging all the devices.

A port replicator also provides additional ports and other expansion features not included with your notebook. See "Using the Gateway 600 Port Replicator" on page 259 for more information about using a port replicator with your notebook.

#### Peripheral devices

You can attach devices (such as a keyboard, mouse, printer, or monitor) to your notebook or port replicator.

#### Memory

Large programs, such as multimedia games or graphics programs, use a lot of memory. If your programs are running more slowly than you think they should, try adding more memory. See "Adding or replacing memory" on page 251 for more information.

#### **Printers**

You can attach almost any type of printer to your notebook. The most common types are inkjet and laser printers, which print in color or black and white. See "Installing a printer, scanner, or other peripheral device" on page 38 for more information about attaching a printer to your notebook.

Inkjet printers and cartridges are relatively inexpensive, but they are slower than laser printers. Using an inkjet color printer, you can print pictures, banners, and greeting cards, as well as documents.

Laser printers and cartridges are more expensive, but they print much faster than inkjet printers. Laser printers are better than inkjet printers when you are printing large documents.

# Getting Started 2

This chapter provides basic information about your Gateway notebook. Read this chapter to find out how to:

- Connect the AC adapter
- Start and turn off your notebook
- Identify the status indicators
- Use the keyboard
- Use the EZ Pad touchpad
- Connect the modem
- Connect to an Ethernet network
- Install peripheral devices

## Connecting the AC adapter


You can run your notebook using an AC adapter or the notebook battery. The battery was shipped to you partially charged. You should use the AC adapter right away to fully charge the battery. Allow 24 hours for the battery to fully charge.

#### **Important**



If the battery is not fully charged before you use your notebook on battery power for the first time, the battery life may be much shorter than you expect. If the battery life seems short even after being charged for 24 hours, the battery may need to be recalibrated. For information, see "Recalibrating the battery" on page 150.

- To connect the AC adapter:
  - 1 Connect the power cord to the AC adapter.



#### Warning



Make sure that you use the AC adapter that came with your notebook.

Replace the power cord if it becomes damaged. The replacement cord must be of the same type and voltage rating as the original cord or your notebook may be damaged.

**2** Connect the AC adapter to your notebook's power connector.



**3** Plug the power cord into a wall outlet.

The battery charge indicator turns on (see "Front" on page 2 for the location of the battery charge indicator). If the battery charge indicator does not turn on, unplug the adapter from your notebook, then plug it back in.

- 4 When you finish using your notebook for the first time, turn your notebook off and leave your notebook connected to AC power for at least 24 hours. The battery charge meters may not show a charge for several hours. For more information about the battery charge meter on your model, see "Monitoring the battery charge" on page 148.
- 5 If the battery charge meters do not show a full charge after 24 hours, contact Gateway Technical Support at <a href="https://www.gateway.com/support/contact">www.gateway.com/support/contact</a>.

#### Warning



Do not attempt to disassemble the AC adapter. The AC adapter has no user-replaceable or user-serviceable parts inside. The AC adapter has dangerous voltages that can cause serious injury or death. Contact Gateway about returning defective AC adapters.



#### **Protecting from power source problems**

During a power surge, the voltage level of electricity coming into your notebook can increase to far above normal levels and cause data loss or system damage. Protect your notebook and peripheral devices by connecting them to a *surge protector*, which absorbs voltage surges and prevents them from reaching your notebook.


#### Warning



High voltages can enter your notebook through both the power cord and the modem connection. Protect your notebook by using a surge protector. If you have a telephone modem, use a surge protector that has a modem jack. If you have a cable modem, use a surge protector that has an antenna/cable TV jack. During an electrical storm, unplug both the surge protector and the modem.

## Starting your notebook

- To start your notebook:
  - 1 Open your notebook by pressing the latch on the front of your notebook and lifting the LCD panel.
  - **2** Press the power button located above the keyboard.



The power button is preset to On/Off mode. However, you can also set it to function in Standby/Resume mode. For instructions on changing the power button mode, see "Changing power settings" on page 158.

**3** If you are starting your notebook for the first time, follow the on-screen instructions to set up your notebook.



#### Waking up your notebook

When you have not used your notebook for several minutes, it may enter a power-saving mode called *Standby*. While in Standby, the power indicator flashes. If your notebook is in Standby mode, "wake" it up by pressing the power button. For more information on changing power-saving settings, see "Changing power settings" on page 158.

## Turning off your notebook

- To turn off your notebook in Windows XP:
  - 1 Click Start, then click Turn Off Computer. The *Turn Off Computer* dialog box opens.
  - **2** Click **Turn Off**. Windows shuts down and turns off your notebook.

#### **Important**



If for some reason you cannot use the Turn Off Computer option in Windows to turn off your notebook, press and hold the power button for about five seconds, then release it.



- To turn off your notebook in Windows 2000:
  - 1 Click Start, then click Shut Down. The Shut Down Windows dialog box opens.
  - 2 Click the arrow button to open the What do you want your computer to do list, then click Shut down.
  - **3** Click **OK**. Windows shuts down and turns off your notebook.

#### **Important**



If for some reason you cannot use the Shut Down option in Windows to turn off your notebook, press and hold the power button for about five seconds, then release it.



## Restarting (rebooting) your notebook

If your notebook does not respond to keyboard or touchpad input, you may have to close programs that are not responding. If closing unresponsive programs does not restore your notebook to normal operation, you may have to restart (reboot) your notebook.

- To close unresponsive programs and restart your notebook:
  - 1 Press CTRL+ALT+DEL. A window opens that lets you close a program that is not responding.
  - **2** Click the program that is not responding.
  - **3** Close the program by clicking **End Task**.
  - 4 If your notebook does not respond, turn it off, wait ten seconds and turn it on again.

#### **Important**



If your notebook does not turn off immediately, complete the following steps until the notebook turns off:


- 1 Press and hold the power button for about five seconds, then release it.
- 2 Insert a straightened paper clip into the reset hole on the bottom of your notebook.
- 3 Remove AC power and the batteries for more than 10 seconds.

As a part of the regular startup process, a program to check the disk status runs automatically. When the checks are finished, Windows starts.



# **Status indicators**

Status indicators inform you when a drive is being used or when a button has been pressed that affects how the keyboard is used.




Indicator	Icon	Description	
Hard drive		The hard drive is in use.	
Left-side modular drive	<del>-</del>	<ul> <li>Indicator Blinking Green - The modular drive is in use.</li> <li>Indicator Solid Green - The module is ready to swap.</li> </ul>	

Indicator	Icon	Description		
Right-side modular drive	<b></b>	<ul><li>Indicator Blinking Green - The modular drive is in use.</li><li>Indicator Solid Green - The module is ready to swap.</li></ul>		
Caps Lock		Caps Lock is turned on.		
Scroll Lock	$\bigcirc$	Scroll Lock is turned on. For more information, see "System key combinations" on page 30.		
Pad Lock	1	Numeric keypad is turned on. For more information, see "System key combinations" on page 30.		

# Using the keyboard

Your notebook features a full-size keyboard that functions the same as a desktop computer keyboard. Many of the keys have been assigned alternate functions, including shortcut keys for Windows, function keys for specific system operations, and the Pad Lock keys for the numeric keypad.

You can attach an external keyboard to the notebook using a USB or PS/2 port. You do not need to shut down the notebook to connect a USB keyboard. Attaching a PS/2 keyboard to your notebook or port replicator may turn off the built-in keyboard.



### **Key types**

The keyboard has several different types of keys. Some keys perform specific actions when pressed alone and other actions when pressed in combination with another key.

Key type	Icon	Description	
Function keys		Press these keys labeled <b>F1</b> to <b>F12</b> to perform actions in programs. For example, pressing <b>F1</b> may open help.	
		Each program uses different function keys for different purposes. See the program documentation to find out more about the function key actions.	
System keys		Press these colored keys in combination with the ${f FN}$ key to perform specific actions.	
Navigation keys		Press these keys to move the cursor to the beginning of a line, to the end of a line, up the page, down the page, to the beginning of a document, or to the end of a document.	
FN key		Press the <b>FN</b> key in combination with a colored system key (such as <b>STATUS</b> , <b>STANDBY</b> , or <b>PAUSE</b> ) to perform a specific action.	
Windows key	B	Press this key to open the Windows <b>Start</b> menu. This key can also be used in combination with other keys to open utilities like ${\bf F}$ (Search utility), ${\bf R}$ (Run utility), and ${\bf E}$ (Explorer utility).	
Numeric keypad		Use these keys to type numbers when the numeric keypad is turned on. Press $F_{N+PAD}\ Lock$ to turn on the numeric keypad.	
Application key	$\overline{\Sigma}$	Press this key for quick access to shortcut menus and help assistants in Windows.	
Arrow keys		Press these keys to move the cursor up, down, right, or left.	
LCD brightness keys		Press these colored keys in combination with the ${\bf F}{\bf N}$ key to control the screen brightness.	

### System key combinations

When you press an **F**N key and a system key at the same time, your notebook performs the action identified by the colored text or icon on the key.

Press and hold FN while pressing this system key	To
F2 Status	Display the power status box in the upper-left corner of your display. The box shows the battery charge level, the BIOS version, and whether the AC adapter is being used. Press the key combination again to close this box.
F3 LCD/CRT	Toggle the notebook display between the LCD, an external monitor, or both displays at the same time. A monitor must be plugged into the monitor port on your notebook or port replicator.
F4 Standby	Enter Standby mode. Press the power button to leave Standby mode. For more information, see "Changing power modes" on page 157.
F9 Pad Lock	Turn on Pad Lock so you can use the numeric keypad. Press this key combination again to turn off Pad Lock. The Pad Lock status indicator appears when this function is turned on.
F10 Scroll Lock	Pause the text scrolling in a DOS screen. Press this key combination again to continue scrolling. The Scroll Lock status indicator appears when this function is turned on. (This function is only available in some programs.)
F11 Pause	Pause execution of a DOS program. (This function is only available in some programs.)
F12 Break	Stop the currently running DOS program. (This function is only available in some programs.)

Press and hold FN while pressing this system key...

To...




Increase the brightness of the display.



Decrease the brightness of the display.

# **Multi-function buttons**


Press the multi-function buttons to open the programs associated with them.



Button	Icon	Press to	
E-mail	$\bowtie$	Open your default e-mail program.	
Internet	4 <b>9</b> 5	Open your default Web browser.	
Help	?	Open online help.	
My Computer		Open the My Computer window.	

# Using the EZ Pad touchpad

The EZ  $Pad^{\text{TM}}$  consists of a touchpad, two buttons, and a rocker switch.



When you move your finger on the touchpad, the *pointer* (arrow) on the screen moves in the same direction.





You can use the EZ-Pad *left* and *right buttons* below the touchpad to select objects.

You can assign a function to the *rocker switch* between the touchpad buttons. This function can be to scroll up or down, maximize or minimize the active window, or open and close the Start menu. For more information about programming the rocker switch, see "Changing the touchpad settings" on page 185.

**Important** 




Attaching a PS/2 mouse to your notebook or port replicator may turn off the touchpad.

### Using the touchpad

To... Do this...


Move the pointer on the screen.



Move your finger around on the touchpad. If you run out of space and need to move the pointer farther, lift your finger, move it to the middle of the touchpad, then continue moving your finger.


### To... Do this...

Select an object on the screen.




Position the pointer over the object. Quickly press and release the left button once. This action is called *clicking*.

Start a program or open a file or folder.




Position the pointer over the object. Press the left button twice in rapid succession. This action is called *double-clicking*.

Access a shortcut menu or find more information about an object on the screen.



Position the pointer over the object. Quickly press and release the right button once. This action is called *right-clicking*.

Move an object on the screen.



Position the pointer over the object. Press the left button and hold it down, then use the touchpad to move (drag) the object to the appropriate part of the screen. Release the button to drop the object where you want it.

For instructions on how to adjust the double-click speed, pointer speed, right-hand or left-hand configuration, and other touchpad settings, see "Changing the touchpad settings" on page 185.

# Connecting the modem

Your notebook has a built-in 56K modem that you can use to connect to a standard telephone line.

### Caution



To reduce the risk of fire, use only No. 26 AWG or larger telecommunications line cord.

### To connect the modem:

1 Insert one end of the modem cable into the modem jack on the back of your notebook.



- **2** Insert the other end of the modem cable into a telephone wall jack. The modem will not work with digital or PBX telephone lines.
- **3** Start your notebook, then start your communications program.



# Connecting to a wired Ethernet network


Your notebook has a network jack that you can use to connect to a 10/100 wired Ethernet network.

### **Important**



Your notebook may be equipped with built-in wireless Ethernet or you may have a wireless Ethernet PC Card. For information about connecting to a wired or wireless Ethernet network, see "Networking Your Computer" on page 189. For information about installing a wireless Ethernet PC Card, see "Adding and removing a PC Card" on page 244.

- To connect to a wired Ethernet network:
  - 1 Insert one end of the network cable into the network jack 📮 on the back of your notebook.



**2** Insert the other end of the network cable into a network jack. Ask your network administrator to help you select the correct network jack.



### **Broadband Internet connections**

You can use your notebook's Ethernet jack for more than just networking. Many broadband Internet connections, such as cable modems and DSL modems, connect to your notebook's Ethernet jack. For more information, see "Using the Internet" on page 71 and "Networking Your Computer" on page 189.

# Installing a printer, scanner, or other peripheral device

### **Important**



Before you install a printer, scanner, or other peripheral device, see the device documentation and installation instructions.

Your computer has one or more of the following ports: IEEE 1394 (also known as Firewire  $^{\circledR}$  or i.Link  $^{\circledR}$ ), Universal Serial Bus (USB), serial, and parallel. You use these ports to connect peripheral devices such as printers, scanners, and digital cameras to your computer. For more information about port locations, see "Checking Out Your Gateway 600" on page 1 and "Using the Gateway 600 Port Replicator" on page 259.

IEEE 1394 and USB ports support *plug-and-play* and *hot swapping*, which means that your computer will usually recognize such a device whenever you plug it into the appropriate port. When you use an IEEE 1394 or USB device for the first time, your computer will prompt you to install any software the device needs. After doing this, you can disconnect and reconnect the device at any time.

Parallel and serial port devices are not plug-and-play. See the device documentation for detailed information and installation instructions.

## Help and Support



For more information about installing peripheral devices in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **installing devices** in the HelpSpot **Search** box **Search** , then click the arrow.

# Getting Help 3

This chapter tells you about additional information resources available to help you use your computer. Read this chapter to learn how to access:

- HelpSpot<sup>TM</sup>
- Online help
- Gateway Web site

# **HelpSpot**

Your computer may include  $HelpSpot^{TM}$ , an easily accessible collection of help information, troubleshooters, instructional videos, and automated support. Use HelpSpot to answer questions about Windows and to help you quickly discover and use the many features of your Gateway computer. HelpSpot also has an area called *Contact Gateway* that helps you find the right resource at Gateway to answer your questions or help solve your problems.

### To start HelpSpot:


■ Click Start, then click Help and Support. HelpSpot opens.



If this is the first time you have started HelpSpot, you may experience a brief wait while HelpSpot builds the help database, then HelpSpot displays an introductory video.




You can find help information by clicking a link, performing a search, or browsing the index. To learn about using your Gateway computer, your touchpad, and other tasks, click the **Using your computer** link on the HelpSpot main page.



### Searching for a topic

To search for a topic in HelpSpot, type a word or phrase (keyword) in the **Search** box located at the top of any HelpSpot screen, then click the arrow button.



For each search, you receive the following search result types:

- Suggested Topics These topics are located in HelpSpot and are relevant to your search topic.
- Full-text Search Matches These topics are located in HelpSpot and contain the words you entered in the Search box.
- Microsoft Knowledge Base These topics are located on the Microsoft Web site and contain the words you entered in the **Search** box. You must be connected to the Internet to search for and access these topics.
- Gateway.com Search These topics are located on the Gateway Web site and contain the words you entered in the Search box. You must be connected to the Internet to search for and access these topics.

To view a list of your search results, click the results header for the type of results you want to view.

To view a topic, click the topic name in the Search Results list.

### **HelpSpot videos**

HelpSpot contains several short videos to help introduce you to new concepts or show you how to perform various tasks.


- To play a HelpSpot video:
  - To watch a video in HelpSpot, click **Video Tutorials** on the HelpSpot home page, then click a video title. The video plays.





# **Online help**

Many programs provide information online so you can research a topic or learn how to perform a task while you are using the program. You can access most online help information by selecting a topic from a **Help** menu or by clicking a **Help** button.




You can search for information by viewing the help contents, checking the index, searching for a topic or keyword, or browsing through the online help.



# **Gateway Web site**

Gateway's online support is available 24 hours per day, 7 days per week and provides the most current drivers, product specifications, tutorials and personalized information about your system. Visit the Gateway eSupport Web site at <a href="support.gateway.com">support.gateway.com</a>. For more information about connecting to the Internet, see "Using the Internet" on page 71.



### **Using eSupport**

The eSupport site is divided into four major areas:

- **■** Support Home
- Downloads
- Contact Us
- Account Info

Each of these areas is represented by a tab across the top of the Web page.

### **Support Home tab**

To get specific information about your computer, type your serial number into the *My System Information* box, then click **GO**, or click **Look up my serial number for me**. For more information, see "Finding your specifications" on page 14.

The *Support Information* link lets you access product documentation, specifications, and manuals. By entering your serial number, you get specific documents related to your system. You can also browse through the reference area to locate an article specific to the question you have.

The *Tutorials* link lets you access an extensive library of how-to articles and videos on topics such as making audio CDs and installing a hard drive.

### Downloads tab

The *Downloads* tab provides the latest software updates for BIOS and driver upgrades. By entering your serial number you get drivers specific to your system. Click All Downloads to walk through a step-by-step wizard to locate your drivers. For more information, see "Updating device drivers" on page 235.

### **Contact Us tab**

The *Contact Us* tab contains links to technical support with a live technician, including chat and e-mail. Click **Call Us** to get a list of Gateway telephone numbers for both sales and support. For more information, see "Telephone support" on page 291.

### Account Info tab

The *Account Info* tab contains support for non-technical issues, like the status of your order or changing your account address.

# Windows Basics 4

Read this chapter to learn how to:

- Use the Windows desktop
- Manage files and folders
- Work with documents
- **■** Use shortcuts

### **About the Windows environment**

After your computer starts, the first screen you see is the Windows *desktop*. The desktop is like the top of a real desk. Think of the desktop as your personalized work space where you open programs and perform other tasks.

Your desktop may be different from this example, depending on how your computer is set up.

Help and Support




For more information about the Windows XP desktop, click **Start**, then click **Help and Support**.

Type the keyword **Windows desktop** in the HelpSpot **Search** box <sub>Search</sub>, then click the arrow.



# Using the desktop

The desktop contains the taskbar, the Start button, and the Recycle Bin icon.



### **Using the Start menu**

You can start programs, open files, customize your system, get help, search for files and folders, and more using the Start menu.




### To use the Start menu:

- 1 Click the **Start** button on the lower left of the Windows desktop. The Start menu opens showing you the first level of menu items.
- **2** Click **All Programs** or **Programs** to see all programs and files in the Start menu. When you move the mouse pointer over any menu item that has an arrow next to it, another menu, called a *submenu*, opens and reveals related files, programs, or commands.



### **3** Click a file or program to open it.





# Help and Support



For more information about the Windows XP Start menu, click **Start**, then click **Help and Support**.

Type the keyword **Windows Start menu** in the HelpSpot **Search** box Search , then click the arrow.

### Adding icons to the desktop

You may want to add an icon (shortcut) to the desktop for a program that you use frequently.

- To add icons to the desktop:
  - 1 Click Start, then click All Programs.
  - **2** Right-click (press the right touchpad button) the program that you want to add to the desktop.
  - **3** Click **Send To**, then click **Desktop (create shortcut)**. A shortcut icon for that program appears on the desktop.



Help and Support




For more information about desktop icons in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **desktop icons** in the HelpSpot **Search** box Search , then click the arrow.

# **Identifying window items**

When you double-click the icon for a drive, folder, file, or program, a *window* opens on the desktop. This example shows the Local Disk (C:) window, which opens after you double-click the **Local Disk (C:)** icon in the *My Computer* window.



Every program window looks a little different because each has its own menus, icons, and controls. Most windows include these items:

Window item	Description	
😂 Local Disk (C:)	The <i>title bar</i> is the horizontal bar at the top of a window that shows the window title.	
	Clicking the <i>minimize button</i> reduces the active window to a button on the taskbar. Clicking the program button in the taskbar opens the window again.	
	Clicking the <i>maximize button</i> expands the active window to fit the entire computer display. Clicking the maximize button again restores the window to its former size.	

Window item				Description		
	X					Clicking the <i>close button</i> closes the active window or program.
File	Edit	View	Favorites	Tools	Help	Clicking an item on the <i>menu bar</i> starts an action such as Print or Save.

# Help and Support



For more information about windows in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **window** in the HelpSpot **Search** box Search , then click the arrow.

# Working with files and folders


You can organize your files and programs to suit your preferences much like you would store information in a file cabinet. You can store these files in folders and copy, move, and delete the information just as you would reorganize and throw away information in a file cabinet.

### Viewing drives

*Drives* are like file cabinets because they hold files and folders. A computer almost always has more than one drive. Each drive has a letter, usually Local Disk (C:) for the hard drive and 3½ Floppy (A:) for the diskette drive. You may also have more drives such as a DVD or recordable CD drive.

- To view the drives on your computer:
  - In Windows XP, click Start, then click My Computer on the Start menu.
    - OR -


In Windows 2000, double-click the My Computer icon on the desktop.





- To see the files and folders on a drive:
  - Double-click the drive icon. If you do not see the contents of a drive after you double-click its icon, click Show the contents of this drive.






### **Creating folders**

*Folders* are much like the folders in a file cabinet. They can contain files and other folders.

*Files* are much like paper documents—letters, spreadsheets, and pictures—that you keep on your computer. In fact, all information on a computer is stored in files.





### To create a folder:

- 1 In Windows XP, click Start, then click My Computer on the Start menu.
  - OR -

In Windows 2000, double-click the My Computer icon on the desktop.

- **2** Double-click the drive where you want to put the new folder. Typically, Local Disk (C:) is your hard drive and 3½ Floppy (A:) is your diskette drive. If you do not see the contents of the drive, click **Show the contents of this drive**.
- 3 If you want to create a new folder inside an existing folder, double-click the existing folder. If you do not see the contents of the folder, click Show the contents of this drive or Show the contents of this folder.
- 4 Click File. New, then click Folder. The new folder is created.
- **5** Type a name for the folder, then press **ENTER**. The new folder name appears by the folder icon.



# Help and Support



For more information about creating files and folders in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword creating files and folders in the HelpSpot Search box  $_{\text{Search}}$   $_{\text{Lin}}$ , then click the arrow.

For information about renaming folders, see "Shortcuts" on page 69.

### Copying and moving files and folders

The skills you need to copy and move files are called copying, cutting, and pasting.

When you *copy and paste* a file or folder, you place a *copy* of the file or folder on the Windows *clipboard*, which temporarily stores it. Then, when you decide what folder you want the copy to go in (the *destination* folder), you *paste* it there.

When you *cut and paste* a file or folder, you remove the file or folder from its original location and place the file or folder on the Windows clipboard. When you decide where you want the file or folder to go, you paste it there.

### **Important**



The clipboard stores whatever you cut or copy until you cut or copy again. Then the clipboard contains the new information only. Therefore, you can paste copies of a file or folder into more than one place, but as soon as you copy or cut a different file or folder, the original file or folder is deleted from the clipboard.

- To copy a file or folder to another folder:
  - 1 Locate the file or folder you want to copy. For more information, see "Viewing drives" on page 54 and "Searching for files" on page 62.
  - **2** Right-click (press the right touchpad button) the file or folder that you want to copy. A pop-up menu opens on the desktop.
  - **3** Click **Copy** on the pop-up menu.
  - **4** Open the destination folder.
  - **5** With the pointer inside the destination folder, right-click.
  - **6** Click **Paste**. A copy of the file or folder appears in the new location.





### To move a file or folder to another folder:

- 1 Locate the file or folder you want to move. For more information, see "Viewing drives" on page 54 and "Searching for files" on page 62.
- **2** Right-click (press the right touchpad button) the file or folder that you want to move. A pop-up menu opens on the desktop.
- **3** Click **Cut** on the pop-up menu.
- **4** Open the destination folder.
- **5** With the pointer inside the destination folder, right-click.
- **6** Click **Paste**. The file or folder you moved appears in its new location and is removed from its old location.



# Help and Support



For more information about copying files and folders or moving files and folders in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword copying files and folders or moving files and folders in the HelpSpot Search box

### **Deleting files and folders**

When you throw away paper files and folders, you take them from the file cabinet and put them in a trash can. Eventually the trash can is emptied.

In Windows, you throw away files and folders by first moving them to the Windows trash can, called the *Recycle Bin*, where they remain until you decide to empty the bin.

You can recover any file in the Recycle Bin as long as the bin has not been emptied.

- To delete files or folders:
  - 1 In My Computer or Windows Explorer, click the files or folders that you want to delete. For instructions on how to select multiple files and folders, see "Shortcuts" on page 69.
    - If you cannot find the file you want to delete, see "Searching for files" on page 62.
  - **2** Click **File**, then click **Delete**. Windows moves the files and folders to the Recycle Bin.



# Help and Support



For more information about deleting files and folders in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **deleting files and folders** in the HelpSpot **Search** box Search , then click the arrow.

- To recover files or folders from the Recycle Bin:
  - 1 Double-click the Recycle Bin icon. The *Recycle Bin* window opens and lists the files and folders you have thrown away since you last emptied it.
  - **2** Click the files or folders that you want to restore. For instructions on how to select multiple files and folders, see "Shortcuts" on page 69.
  - **3** Click **File**, then click **Restore**. Windows returns the deleted files or folders to their original locations.



### To empty the Recycle Bin:

### Caution



Emptying the Recycle Bin permanently erases any files or folders in the bin. These files cannot be restored.

- 1 Double-click the Recycle Bin icon on the desktop. The *Recycle Bin* window opens.
- **2** Click File, then click Empty Recycle Bin. Windows asks you if you are sure that you want to empty the bin.
- 3 Click Yes. Windows permanently deletes all files in the Recycle Bin.



## Help and Support



For more information about emptying the Recycle Bin in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **emptying Recycle Bin** in the HelpSpot **Search** box Search [ ], then click the arrow.

### Browsing for files and folders

A file or folder that you need is rarely right on top of your Windows desktop. It is usually on a drive inside a folder that may be inside yet another folder, and so on.


Windows drives, folders, and files are organized in the same way as a real file cabinet in that they may have many levels (usually many more levels than a file cabinet, in fact). So you usually will have to search through levels of folders to find the file or folder that you need. This is called *browsing*.

### To browse for a file:

- 1 In Windows XP, click **Start**, then click **My Computer**. The *My Computer* window opens.
  - OR -

In Windows 2000, double-click the **My Computer** icon on the desktop. The *My Computer* window opens.

2 Double-click the drive or folder that you think contains the file or folder that you want to find. If you do not see the contents of a folder, click Show the contents of this drive or Show the contents of this folder.



**3** Continue double-clicking folders and their subfolders until you find the file or folder you want.



# Help and Support



For more information about browsing for files and folders in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **files and folders** in the HelpSpot **Search** box **Search**, then click the arrow.

## Searching for files

If you are looking for a particular file or folder or a set of files or folders that have characteristics in common, but you do not remember where they are stored on your hard drive, you can use the Search utility to search by:

- Name or part of a name
- Creation date
- Modification date
- File type
- Text contained in the file
- Time period in which it was created or modified

You can also combine search criteria to refine searches.

Files and folders found using this utility can be opened, copied, cut, renamed, or deleted directly from the list in the results window.

#### **Using the Windows Search utility**

- To find files and folders using the Search utility:
  - 1 In Windows XP, click Start, then click Search. The Search Results window opens. Click All files and folders.
    - OR -


In Windows 2000, click Start, Search, then click For Files or Folders. The *Search Results* window opens.



- **2** If you want to search by file or folder name, type in all or part of the file or folder name in the name box in the left pane of the window.
  - If you type all of the name, Search will list all files and folders of that name.
  - If you type part of the name, Search will list all of the file and folder names containing the letters you typed.



**3** Click **Search** or **Search Now**. When the search is completed, Windows lists the files and folders whose names contain the text that you searched for.



4 Open a file, folder, or program by double-clicking the name in the list.



#### Help and Support



For more information about searching for files and folders in Windows XP, click **Start**, then click **Help and Support**. Type the keyword **searching** in the HelpSpot **Search** box

Search , then click the arrow.

#### Using advanced search options

Search can find files meeting more criteria than file name. You can narrow your search by selecting the search options that you want. You can search by the:

- Date the file was created or modified.
- Size of the file.
- Type of file, such as a program or a text document.

## **Working with documents**


Computer documents include word processing files, spreadsheet files, or other similar files. The basic methods of creating, saving, opening, and printing a document apply to most of these types of files.

The following examples show how to create, save, open, and print a document using Microsoft® WordPad. Similar procedures apply to other programs such as WordPerfect, Microsoft Word, and Microsoft Excel.

For more information about using a program, click Help on its menu bar.

#### Creating a new document

- To create a new document:
  - 1 Click Start, All Programs, Accessories, then click WordPad. Microsoft WordPad starts and a blank document opens.




**2** Begin composing your document. Use the menus and toolbar buttons at the top of the window to format the document.



#### Saving a document

After you create a document, you need to save it if you want to use it later.

- To save a document:
  - 1 Click File, then click Save. The Save As dialog box opens.



- **2** Click the arrow button to open the **Save** in list, then click the folder where you want to save the file. If you do not see the folder you want, browse through the folders listed below the *Save* in list.
- **3** Type a new file name in the File name box.
- 4 Click Save.








For more information about saving documents in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **saving** in the HelpSpot **Search** box Search , then click the arrow.

#### **Opening a document**

To view, revise, or print an existing document, first you need to open it. Open the document in the program that it was created in.

- To open a document:
  - 1 Start the program.
  - 2 Click File, then click Open.
  - **3** Click the arrow button to open the **Look** in list, then click the folder you want to open. If you do not see the folder you want, browse through the folders listed below the *Look* in list.



4 Double-click the document file name. The document opens.



Help and Support



For more information about opening documents in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **opening files** in the HelpSpot **Search** box Search , then click the arrow.

#### **Printing a document**

To print a document, you must have a printer connected to your computer or have access to a network printer. For more information about installing or using your printer, see the printer documentation.

- To print a document:
  - 1 Make sure that the printer is turned on and loaded with paper.
  - **2** Start the program and open the document.
  - **3** Click File, then click Print. The *Print* dialog box opens.
  - **4** Set the print options, then click **OK**. The document prints.



Help and Support



For more information about printing documents in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **printing** in the HelpSpot **Search** box Search , then click the arrow.

#### **Shortcuts**

The following table shows a few shortcuts that you can use in Windows and almost all programs that run in Windows. For more information on Windows shortcuts, see your Windows or program documentation.

To	Do this
Copy a file, folder, text, or graphic	Click the item, then press CTRL + C.
Cut a file, folder, text, or graphic	Click the item, then press CTRL + X.
Paste a file, folder, text, or graphic	Click inside the folder or window where you want to paste the object, then press ${f CTRL}$ + ${f V}$ .
Select multiple items in a list or window	Click the first item, press and hold down the $\mathbf{CTRL}$ key, then click each of the remaining items.
Select multiple adjacent items in a list or window	Click the first item in the list, press and hold down the <b>SHIFT</b> key, then click the last item in the list.
Permanently delete a file or folder	Click the file or folder, then press <b>SHIFT + DELETE</b> . The file or folder is permanently deleted. The file or folder is <b>not</b> stored in the Recycle Bin.
Rename a file or folder	Click the file or folder, press ${\bf F2}$ , type the new name, then press ${\bf ENTER}$ .
Close the active window or program	Press ALT + F4.
Switch to a different file, folder, or running program	Press ALT + TAB.

Help and Support



For more information about Windows keyboard shortcuts in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **Windows keyboard shortcuts** in the HelpSpot **Search** box Search , then click the arrow.

# Using the Internet 5


This chapter provides information about the Internet and the World Wide Web. Read this chapter to learn how to:

- Set up and access an Internet account using America Online®
- Connect to a Web site using a browser
- Download files from the Internet
- Send and receive e-mail using America Online

## Learning about the Internet

The *Internet* is a worldwide network of computers linked together to provide information to people everywhere. The two most popular services on the Internet are e-mail and the World Wide Web. You can access this network by connecting your computer to a telephone, DSL (Digital Subscriber Line), or cable line and signing up with an Internet service provider (ISP).

Cable and DSL modems, a connection known as broadband, use your TV cable or special telephone lines to connect to your ISP and access the Internet. Cable and DSL modems connect to your computer through an Ethernet jack and provide a faster connection speed than a standard telephone modem.



If you want to access the Internet you need:

- A **modem** a device that connects your computer to other computers or servers using a telephone, DSL, or cable line.
- An **Internet service provider** a company that provides access to the Internet through an ISP server. When you connect to an ISP, the ISP server lets you access the Internet and your e-mail messages.
- A Web browser a program that displays information from the World Wide Web.
- An e-mail program a program that lets you create, send, and receive e-mail messages over the Internet.

## Setting up an Internet account

Before you can view the information on the World Wide Web, you need to set up an Internet account with an Internet service provider (ISP). If you have chosen America Online as an ISP, follow these instructions to set up and connect to your account. To set up a different ISP service or to transfer an existing account to this computer, contact the ISP directly.

If you set up an account with America Online, an Internet e-mail address is created for you. After completing the setup, you are ready to access the Internet.

- To set up an Internet account with America Online:
  - 1 Click Start, All Programs, then click America Online.
  - **2** Follow the on-screen instructions. After setting up your account, you can connect to the Internet and access your e-mail services.



#### **Accessing your Internet account**

- To connect to your America Online Internet account:
  - 1 Click Start, All Programs, then click America Online.
  - **2** Complete the member name and password information, then click **Connect**. Your computer dials the Internet account telephone number. After connecting, the *Welcome* window opens.



If you are using a service other than America Online, check with your ISP for the correct procedure for connecting.

- To disconnect from your America Online Internet account:
  - Click X in the top-right corner of the America Online window. Your computer disconnects from the Internet.

#### **Important**



Make sure that your computer disconnects correctly from your Internet account. If you do not have an "unlimited hours" ISP account, you may have to pay for the time that you are connected, even if you are not at your computer.



If you are using a service other than America Online, check with your ISP for the correct procedure for disconnecting.

#### Help and Support



For general information about using Internet accounts in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **ISP** in the HelpSpot **Search** box Search , then click the arrow.

## **Using the World Wide Web**

The World Wide Web is a multimedia window to the Internet that gives you access to millions of information sources.

Information on the Web comes to you on *Web pages*, which are electronic documents that you view using a Web page display program called a *browser*. You can use any of the commercially available Web browsers, like Microsoft Internet Explorer (which comes installed on your new computer), Netscape Navigator, or the browser built into America Online.

Web pages can contain text, animations, music, and other multimedia features. A group of related Web pages is called a *Web site*. You can access Web sites to shop, track investments, read the news, download programs, and much more.

You can explore a Web site or visit other Web sites by clicking areas on a Web page called *links* or *hyperlinks*. A link may be colored or underlined text, a picture, or an animated image. You can identify a link by moving the mouse pointer over it. If the pointer changes to a hand, the item is a link.

To learn more about using the Web browser features, click Help in the menu bar.



#### Connecting to a Web site

After you set up an account with an Internet service provider (ISP) such as America Online, you can access the many information sources on the World Wide Web.

- To connect to a Web site:
  - 1 Connect to your Internet account. After your computer connects, a default opening page or welcome screen opens.
  - **2** To go to a different Web site, type the *address* (called a *URL* for "Universal Resource Locator") in the browser address bar (for example **www.gateway.com**), then click **GO** on the browser address bar.



- OR -

On the current Web page, click a link to a Web site.

The Web browser locates the server computer on the Internet, *downloads* (transfers) data to your computer, and displays the page on the site that you requested.



#### Help and Support



For more information about connecting to a Web site in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **connecting to Web site** in the HelpSpot **Search** box Search , then click the arrow.

Sometimes Web pages display slowly. The speed that a Web page displays on your screen depends on the complexity of the Web page and other Internet conditions. Additionally, the speed of your connection will determine how fast Web pages display.

#### **Downloading files**

*Downloading* is the process of transferring files from a computer on the Internet to your computer.

To protect your computer against viruses, make sure that you scan the files you download. For more information, see "Protecting your computer from viruses" on page 216.

- To download files or programs from a Web site:
  - 1 Connect to your Internet account.
  - 2 In the address bar, type the address of the Web site that contains the file or program you want to download, then click **GO** on the browser address bar.
    - OR -

Click a link on a Web page to navigate to the Web site containing the file that you want to download.

- **3** Create or locate the folder where you want to store the file on your computer. For more information, see "Working with files and folders" on page 54.
- **4** Click the link on the Web page for the file that you want to download.
- 5 Follow the on-screen instructions for saving the file in the folder that you want. A copy of the file is downloaded to your computer. The time that it takes to transfer the file to your computer depends on file size and Internet conditions.
- **6** Open the folder that you created.
- **7** Install or view the downloaded file by double-clicking it. If applicable, follow the instructions provided on the Web site to run or install the program.



Help and Support



For more information about downloading files in Windows XP, click **Start**, then click **Help and Support**.


Type the keyword **downloading files** in the HelpSpot **Search** box **Search**, then click the arrow.

## **Using e-mail**

*E-mail* (electronic mail) lets you send messages to anyone who has an Internet connection and e-mail address. E-mail is usually a free service of your Internet account.

The Internet never closes, so you can send e-mail messages at any time. Your e-mail messages arrive at most e-mail addresses in minutes.

An *e-mail address* consists of a user name, the @ symbol, and the Internet *domain name* of the Internet service provider (ISP) or company that "hosts" that user. Your e-mail address is assigned when you sign up for an account with an ISP. For example, a person with an account with America Online might have an e-mail address that is similar to this one:



#### Sending e-mail

- To send e-mail using America Online:
  - 1 Connect to your America Online account.
  - 2 Click Write.
  - **3** Type the e-mail address of the recipient you want to send e-mail to in the **Send To** box.
  - **4** Type the subject of your e-mail in the **Subject** box.
  - **5** Type the e-mail message.
  - **6** When finished, click **Send Now**. Your e-mail is sent over the Internet to the e-mail address you specified.



#### **Checking your e-mail**

- To check your e-mail using America Online:
  - 1 Connect to your America Online account.
  - 2 Click Read.
  - 3 Double-click the message you want to read.



For more information about managing and organizing your e-mail messages, see the online help in your e-mail program.

Help and Support



For general information about using e-mail in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **e-mail** in the HelpSpot **Search** box Search , then click the arrow.

Chapter 5: Using the Internet

## Using Multimedia 6

This chapter provides information on using the multimedia capabilities of your notebook. Read this chapter to learn how to:

- Use the diskette drive
- Use a DVD or recordable CD drive
- Adjust the volume
- Use Audio DJ
- Play CDs
- Record and play audio files
- Use Windows Media Player
- Use MusicMatch
- Use a recordable CD drive to create CDs
- Play DVDs
- View the display on a television
- Capture video using the IEEE 1394 (also known as Firewire or i.Link) port


## Using the diskette drive

The diskette drive uses 3.5-inch diskettes (sometimes called *floppy disks*). Diskettes are useful for storing files or transferring files to another computer.

#### Warning



Do not expose diskettes to water or magnetic fields. Exposure could damage the data on the diskette.



#### To use a diskette:

1 Insert the diskette into the diskette drive with the label facing up.

#### **Important**



If the diskette drive is not in the right-side modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246. The diskette drive will not work in the left-side modular bay.

- **2** To access a file on the diskette in Windows XP, click **Start**, then click **My Computer**. Double-click the drive letter (for example, the A: drive), then double-click the file name.
  - OR -

To access a file on the diskette in Windows 2000, double-click the My Computer icon, the drive letter (for example, the A: drive), then double-click the file name.

**3** To remove the diskette, make sure that the modular drive status indicator is off (see "Status indicators" on page 26), then press the diskette eject button.



## Using the DVD or recordable CD drive

You can use your computer to enjoy a wide variety of multimedia features.

#### Identifying drive types

Your Gateway computer may contain one of the following drive types. Look on the front of the drive for one of the following logos:

CD-RW drive



Use a CD-RW drive for installing programs, playing audio CDs, accessing data, and creating CDs.

You cannot use this drive to play DVDs.

You can only write to a CD-R disc once. You can write to and erase CD-RW discs multiple times. For more information, see "Using a recordable CD drive" on page 112.

DVD drive



Use a DVD drive for installing programs, playing audio CDs, playing DVDs, and accessing data.

You cannot use this drive to create CDs.


Combination DVD/CD-RW drive





Use a combination DVD/CD-RW drive for installing programs, playing audio CDs, playing DVDs, accessing data, and recording music and data to CD-R or CD-RW discs. For more information, see "Using a recordable CD drive" on page 112.

#### Inserting a CD or DVD



**Important** 



Some music CDs have copy protection software. You may not be able to play these CDs on your computer.

#### To insert a CD or DVD:

1 Press the eject button on the DVD or recordable CD drive. After the tray opens slightly, pull the disc tray completely open.

**Important** 



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.



2 Place the disc in the tray with the label facing up, then press down carefully on the disc until it snaps into place.

Important



When you place a single-sided disc in the tray, make sure that the label side is facing up. If the disc has two playable sides, place the disc so that the name of the side you want to play is facing up.

**3** Push the tray in until it is closed.



#### Adjusting the volume

#### Adjusting the volume in Windows XP

You can use the volume controls to adjust the overall volume and the volume of specific sound devices in your computer.

- To adjust the overall volume level using hardware controls:
  - If you are using external speakers, turn the knob on the front of the speakers.

-OR-

Use the mute and volume control buttons on the Audio DJ control panel. For more information, see "Audio DJ controls" on page 92.



- To adjust the overall volume level from Windows:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Sounds, Speech, and Audio Devices.
  - **2** Click/Double-click the Adjust the system volume or Sounds and Audio Devices. The Sounds and Audio Devices Properties dialog box opens.
  - **3** Click the **Volume** tab.



4 Drag the Device Volume slider to change the volume or click to select the Mute check box, then click OK.



Help and Support



For more information about adjusting volume in Windows XP, click **Start**, then click **Help and Support**. Type the keyword **adjusting volume** in the HelpSpot **Search** box **Search**, then click the arrow.

- To adjust specific volume levels:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Sounds, Speech, and Audio Devices.
  - **2** Click/Double-click the Adjust the system volume or Sounds and Audio Devices. The Sounds and Audio Devices Properties dialog box opens.
  - **3** Click the **Volume** tab.



4 Click Advanced in the Device volume area.



If the device you want to adjust does not appear in the window, click **Options**, **Properties**, the check box next to the audio device you want to adjust, then click **OK**.

- **5** Drag the volume level and balance sliders for the device you want to adjust. For more information about the volume controls, click **Help** in the window.
- **6** Click **X** in the top-right corner of the window to close it.



#### Adjusting the volume in Windows 2000

You can use the volume controls to adjust the overall volume and the volume of specific sound devices in your computer.

- To adjust overall volume level using hardware controls:
  - If you are using external speakers, turn the knob on the front of the speakers.

-OR-

Use the mute and volume control buttons on the Audio DJ control panel. For more information, see "Audio DJ controls" on page 92.




- To adjust overall volume level from Windows:
  - Click the speaker icon on the taskbar, then drag the slider to change the volume or click to select the **Mute** check box.





- To adjust specific volume levels:
  - 1 Double-click the speaker icon on the taskbar. The *Volume Control* window opens.



If the device you want to adjust does not appear in the *Volume Control* window, click **Options**, **Properties**, the audio device you want to adjust, then click **OK**.

- **2** Drag the volume level and balance sliders for the device you want to adjust. For more information about the volume controls, click **Help** in the *Volume Control* window.
- $\mathbf{3}$  Click  $\mathbf{X}$  in the top-right corner of the window to close it.



## **Using Audio DJ**

Audio DJ plays audio CDs in your DVD or recordable CD drive or .MP3 files (stored either on your hard drive or on a CD) using your notebook's speakers or headphones plugged into the headphone jack. The Audio DJ can be used only while the notebook is turned off. While using Audio DJ, the LCD panel can be open or closed. When the LCD panel is open, the display will turn off approximately 30 seconds after Audio DJ is started. Press any key on the keyboard to turn the display back on.

Audio DJ operates in the following modes:

- Play a song is playing
- Pause song play has been paused
- Stop song play has been stopped
- Playlist select a different play channel (see "Assigning music to play channels" on page 93)


#### **Important**



If you leave Audio DJ in Playlist mode for longer than a few minutes, Audio DJ will turn off. You will need to turn Audio DJ on again to use it.

#### **Audio DJ controls**

The controls for Audio DJ are located on the front of the notebook.



Component	Icon	Description
Power indicator		Indicates the current Audio DJ status:
		<ul> <li>LED blinking green - Audio DJ is turned on. While the Audio DJ LED is blinking, the notebook's power indicator will also be green.</li> <li>LED off - Audio DJ is turned off.</li> </ul>
Power button	•	Press the button to turn the Audio DJ on or off. The button works only when the notebook is turned off.
Back		In play, pause, or stop mode: Skip back one song in the channel. In playlist mode: Skip back one channel.
Play/Pause	<b>)</b> /	In playlist, pause, or stop mode: Start playing your current channel. In play mode: Pause playing.

Component	Icon	Description
Stop		In play, pause, or playlist mode: Enter stop mode. In stop mode: Enter playlist mode.
Next	<b>&gt;&gt;</b>	In play, pause, or stop mode: Skip ahead one song in the channel.  In playlist mode: Skip ahead one channel.
Volume down	Щ)	Press to decrease the volume.
Volume up	山))	Press to increase the volume.
Mute		Press the volume down and volume up buttons to mute the sound. Press the button combination again to restore the sound. Mute is not available when you are playing a file or CD with Audio DJ.

#### **Important**



The volume buttons control the volume level of the built-in speakers and headphones plugged into the headphone jack. The play/pause, back, next, and stop buttons may control multimedia programs such as Windows Media Player, Windows CD Player, MusicMatch, and the InterVideo DVD Player.


#### Assigning music to play channels

Before you can play music with Audio DJ, you need to assign music to at least one play channel. There are nine play channels available and each can contain either a folder of .MP3 files, an audio CD in your DVD or recordable CD drive, or a playlist created in another music playing program such as MusicMatch or Windows Media Player.

- To assign music to play channels:
  - 1 With your notebook turned on and running Windows, click Start, All Programs, O2Micro, then click Play List Editor. The *Music Wizard* window opens.



**2** Click add, then click either folder or play list. The *Select files for playlist* dialog box opens.



- 3 Click one of the following to add it to your Audio DJ play channel:
  - A folder containing .MP3 files
  - A playlist created in Windows Media Player or MusicMatch
  - An audio CD in your DVD or recordable CD drive
- 4 Click Select.
- 5 Click OK.
- 6 Repeat Step 2 through Step 5 to assign music to other play channels. Your Audio DJ can play up to nine play channels.



#### Playing your play channels

- To play your Audio DJ channels:
  - 1 Open the LCD panel (optional). If you use the notebook's speakers while using Audio DJ, open the LCD panel for best sound quality.
  - **2** With the notebook turned off (not in Standby or Hibernate mode), press the Audio DJ power button. The Audio DJ starts.
  - 3 Press the ▶ (play) button to play the first song in your first channel -OR-

Press the ■ (stop) button to put Audio DJ into playlist mode to select another channel using the back button or next button.

**Important** 



Pressing the notebook's power button while Audio DJ is running will turn off Audio DJ.

4 Press the Audio DJ power button again to turn off Audio DJ.



## **Listening to CDs**

You can use the DVD or recordable CD drive on your computer to listen to music CDs.

**Important** 



Some music CDs have copy protection software. You may not be able to play these CDs on your computer.

#### Listening to CDs in Windows XP

Use the Windows Media Player to listen to CDs in Windows XP. For more information about the using the Windows Media Player, click Help. You can also use MusicMatch to listen to CDs. For more information, see "Using MusicMatch" on page 103.



#### To play a CD:

1 Insert a CD into the DVD or recordable CD drive.

**Important** 





If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

**2** If a dialog box opens with a list of CD players, click **Windows Media Player**. The Windows Media Player opens.

- OR -

If a dialog box does not open with a list of CD players, click **Start**, then click **Windows Media Player**. The Windows Media Player opens.





If you do not hear audio or you want to change the volume, see "Adjusting the volume in Windows XP" on page 86.



#### Help and Support



For more information about playing CDs in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **playing CDs** in the HelpSpot **Search** box Search [ ], then click the arrow.

## **Listening to CDs in Windows 2000**

Use the Windows CD Player to play an audio CD. You can also use MusicMatch to listen to CDs. For more information, see "Using MusicMatch" on page 103.

## To play a CD:

■ Insert a CD into the DVD or recordable CD drive. The CD Player opens and the CD plays.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

- OR -

If the CD does not start playing automatically, click **Start**, **Programs**, **Accessories**, **Entertainment**, then click **CD Player**. When the CD Player opens, click ▶ (play).




If you do not hear audio or you want to change the volume, see "Adjusting the volume in Windows 2000" on page 89.



## Recording and playing audio

Use the following instructions to make an audio recording by speaking into the built-in microphone or an optional external microphone.

- To make an audio recording:
  - 1 If you want to use an external microphone, plug a microphone into the Microphone jack on your computer. For the location of the Microphone jack, see "Left side" on page 3.
  - 2 Click Start, All Programs, Accessories, Entertainment, then click Sound Recorder. The Sound Recorder opens.



- **3** Click (record), then speak into the microphone.
- **4** When you finish recording, click  $\blacksquare$  (stop).
- **5** Click **File**, then click **Save As**. The *Save As* dialog box opens.
- 6 Name the recording, specify the location where you want to save the recording, then click **Save**. The recording is saved.



- To play an audio recording in Sound Recorder:
  - 1 Open the Sound Recorder.
  - **2** Click File, then click Open. The *Open* dialog box opens.
  - 3 Click the file you want to play, then click Open.
  - **4** Play the file by clicking ▶ (play), then stop playing the file by clicking (stop).



## Help and Support



For more information about making or playing an audio recording in Windows XP, click **Start**, then click **Help and Support**.


Type the keyword **recording audio** or **playing audio** in the HelpSpot **Search** box Search the normal search the search se

## Playing audio and video files with the Windows Media Player

The Windows Media Player can play several types of audio and video files, including WAV, MIDI, MP3, AU, AVI, and MPEG formats. For more information about the using the Windows Media Player, click **Help**.

- To play a file using the Windows Media Player:
  - 1 In Windows XP, click Start, All Programs, then click Windows Media Player. The Windows Media Player opens.
    - OR -

In Windows 2000, click Start, Programs, Accessories, Entertainment, then click Windows Media Player. The Windows Media Player opens.





2 Click File, then click Open. The Open dialog box opens.

#### **Important**



If the menu bar does not appear, click the show menu bar button.

- 3 Click the file you want to play, then click Open.
- **4** Play the file by clicking ▶ (play), then stop playing the file by clicking (stop).



## Help and Support



For more information about playing audio and video using the Windows Media Player in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **Media Player** in the HelpSpot **Search** box Search , then click the arrow.

## **Using MusicMatch**

Using MusicMatch™, you can:

- Play music CDs
- Create MP3 music files from your music CDs
- Edit music track information
- Use your music files to build a music library
- Listen to Internet Radio

For more information on using MusicMatch, see its online help.

## **Playing CDs**

You can use the MusicMatch program to play music CDs.

**Important** 



Some music CDs have copy protection software. You may not be able to play these CDs on your computer.


- To play a music CD in Windows XP:
  - 1 Insert the music CD into the DVD or recordable CD drive on your computer.

**Important** 



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.







**2** Click Play Audio CD using MUSICMATCH Jukebox, then click OK. MusicMatch opens, the CD begins playing, and the names of the music tracks appear in the playlist area.





- To play a music CD in Windows 2000:
  - 1 Double-click the **musicmatch JUKEBOX** icon on your desktop. MusicMatch opens.
  - **2** Insert the music CD into the DVD or recordable CD drive on your computer.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

3 Click the **CD** tab in the *MusicMatch* window. The names of the music tracks appear in the playlist area.



4 Click ▶ (play).



## **Creating MP3 music files**

Using MusicMatch, you can copy the tracks from a music CD to your computer's hard drive as MP3 files. *MP3* (MPEG Layer 3) is a standard for digitally compressing high-fidelity music into compact files without noticeably sacrificing quality. MP3 files end in the file extension .**MP3**.

#### **Important**



Some music CDs have copy protection software. You cannot copy tracks from these CDs.



#### To create (rip) MP3 files:

1 Insert a music CD into your DVD or recordable CD drive.

#### **Important**




If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

- **2** If an *Audio CD* dialog box opens, click **Play Audio CD** using **MUSICMATCH Jukebox**, then click **OK**. The *MusicMatch* window opens.
  - OR -

If a dialog box does not open, click **Start**, **All Programs**, **MusicMatch**, then click **MusicMatch Jukebox**. The *MusicMatch* window opens.



**3** Click the record button. The *Recorder* window opens.



- 4 Click to clear the check box for any track you do not want to record (rip).
- 5 Click REC.
- **6** When a message appears that tells you the recordable CD drive needs to be configured, click **OK**.



## **Editing track information**

After you add a CD track as an MP3 file to your music library, you can edit the track's information.

- To edit track information:
  - 1 In MusicMatch, click My Library. The library window opens.
  - 2 In the library window, right-click the file, then click Edit Track Tag(s). The Edit Track Tag dialog box opens.



- **3** Enter information such as track title, lead artist, album, and genre.
- **4** Click **OK**. The new track information appears in the MusicMatch playlist, music library, and recorder window.



## **Building a music library**

Use MusicMatch to build a music library. You can organize your music tracks by categories, find a track quickly by using the sort features, and add information to a music file.

You can add music tracks to your music library by:

- **Creating MP3 files** When you create MP3 files from the tracks on your music CD, MusicMatch automatically adds these files to your music library.
- **Dragging and Dropping** Drag and drop files from Windows Explorer or your desktop to the music library.
- **Downloading files from the Internet** When you are connected to the Internet, MP3 files that you download are automatically added to your music library.


#### Caution



During the download process, MP3 files may become corrupt. If you are having trouble listening to, or working with, a downloaded file, try downloading the file again.

## Changing the music library display settings

- To change the music library display settings:
  - 1 In MusicMatch, click **Options**, then click **Settings**. The *Settings* dialog box opens.
  - **2** Click the Music Library tab.



**3** Click the categories that you want to display in the columns, then click **OK**.



## **Listening to Internet radio**

- To listen to an Internet radio station:
  - 1 Connect to the Internet, then open MusicMatch.



**2** Click Radio Stations. The *Radio* window opens.



- **3** To select one of the MusicMatch Internet radio stations, click one of the Popular Stations. MusicMatch connects to the station and plays the audio.
  - OR -

To play another Internet radio station, click **Broadcast Stations**, the appropriate category in the *Station Selector*, the radio station, then click  $\blacktriangleright$  (play). MusicMatch connects to the station and plays the audio.



## **Using advanced features**

You can also use MusicMatch to create your own music CDs and to download MP3 files to your portable MP3 player. For more information, see the MusicMatch online help.

## Using a recordable CD drive

You can use your CD-RW or DVD/CD-RW drive to create data CDs, music CDs, or copies of CDs. For more information about your drive's capabilities, see "Identifying drive types" on page 84.

## **Creating data CDs**

Use Roxio Easy CD Creator to create **data** CDs. Data CDs are ideal for backing up important files such as tax records, letters, MP3s, digital movies, or photos. For information on creating **music** CDs, see "Creating music CDs" on page 116.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

#### **Important**



We recommend that you do not use your computer for other tasks while creating CDs.


#### **Important**



If you record copyrighted material on a CD, you need permission from the copyright owner. Otherwise, you may be violating copyright law and be subject to payment of damages and other remedies. If you are uncertain about your rights, contact your legal advisor.

- To create a data CD:
  - 1 Insert a blank, writable CD into your recordable CD drive.
  - **2** If a *CD Drive* dialog box opens, click **Create** a **CD** using Roxio Easy **CD** Creator, then click **OK**. The *Select a Project* window opens.
    - OR -


If a dialog box does not open, click **Start**, **All Programs**, **Roxio Easy CD Creator**, then click **Project Selector**. The *Select a Project* window opens.



make a data CD dataCD project



**3** Move your pointer over make a data CD, then click dataCD project. The *Easy CD Creator* window opens.




4 Click the arrow button to open the **Select Source Files** list, then click the drive or folder where the files you want to add to the writable CD are located. If you do not see the folder you want, browse through the folders in the *Source* pane.

**5** Click the file you want to record (hold down the **CTRL** or **SHIFT** key when you click to select multiple files) in the *Source* pane, then click **Add**.



**6** After you have added all of your files, click **record**. The *Record CD Setup* dialog box opens.





#### 7 Click Start Recording.



## Help and Support



For more information about creating CDs in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **creating CDs** in the HelpSpot **Search** box Search , then click the arrow.

## **Creating music CDs**

Use Roxio Easy CD Creator to create **music** CDs from other music CDs or MP3 files. For information on creating **data** CDs, see "Creating data CDs" on page 112.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

#### **Important**



We recommend that you do not use your computer for other tasks while creating CDs.

#### **Important**



If you record copyrighted material on a CD, you need permission from the copyright owner. Otherwise, you may be violating copyright law and be subject to payment of damages and other remedies. If you are uncertain about your rights, contact your legal advisor.

#### **Important**



Some CDs have copy protection software. You cannot create MP3 files from these CDs and you may not be able to listen to these CDs on your computer.

## To create music CDs:

1 Insert a blank, writable CD into your recordable CD drive.


**Tips & Tricks** 



Most home and car stereos can read CD-R discs, but do not read CD-RW discs. To make sure that the CD that you create will play on home and car CD players, use a CD-R disc.

- **2** If a *CD Drive* dialog box opens, click **Create** a **CD** using **Roxio Easy CD Creator**, then click **OK**. The *Select a Project* window opens.
  - OR -

If a dialog box does not open, click **Start**, **All Programs**, **Roxio Easy CD Creator**, then click **Project Selector**. The *Select a Project* window opens.




make a music CD

musicCD project



**3** Move your pointer over **make a music CD**, then click **musicCD project**. The *Easy CD Creator* window opens.

#### Select Source Files




4 Click the arrow button to open the Select Source Files list, then click the drive or folder where the music files that you want to add to the writable CD are located. If you do not see the folder you want, browse through the folders in the *Source* pane.

**5** Click the file you want to record (hold down the **CTRL** or **SHIFT** key when you click to select multiple files) in the *Source* pane, then click **Add**.

**Tips & Tricks** 



You can add any combination of music tracks or MP3 files to a music CD project. You can add up to 99 tracks and files, or up to 650 MB (74-minute CD) or 700 MB (80-minute CD) of tracks and files to a music CD project.





**6** After you have added all of your tracks and files, click **record**. The *Record CD Setup* dialog box opens.



7 Click Start Recording. When the recording is complete, you may see a *Record Complete* dialog box. Select the appropriate option.



## Help and Support



For more information about creating CDs in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **creating CDs** in the HelpSpot **Search** box Search . , then click the arrow.

## **Copying CDs**

CD Copier can make backup copies of almost any type of CD.

#### Important



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

#### Important



We recommend that you do not use your computer for other tasks while creating a CD.

#### **Important**



If you record copyrighted material on a CD, you need permission from the copyright owner. Otherwise, you may be violating copyright law and be subject to payment of damages and other remedies. If you are uncertain about your rights, contact your legal advisor.

If you have only one drive and it is a recordable CD drive, go to "To copy a CD using one drive:" on page 121.

-OR-


If you have two drives and one of the drives is a recordable CD drive, go to "To copy a CD using two drives:" on page 123.

- To copy a CD using one drive:
  - 1 Insert the CD you want to copy into your recordable CD drive.
  - **2** If a dialog box opens, click **Take no action**.



- **3** If a *CD Drive* dialog box opens, click **Create a CD using Roxio Easy CD Creator**, then click **OK**. The *Select a Project* window opens.
  - OR -

If a dialog box does not open, click **Start**, **All Programs**, **Roxio Easy CD Creator**, then click **Project Selector**. The *Select a Project* window opens.



122

**4** Move your pointer over **CD copier**, then click **CD copier**. The *CD Copier* window opens.



- **5** On the **Source and Destination** tab, click the arrow button to open the **Copy from** list, then click the recordable CD drive.
- **6** Click the arrow button to open the **Record to** list, then click the recordable CD drive.
- **7** Click **Copy**. CD Copier copies the information on the source CD to your hard drive, prompts you to insert the blank CD, then copies the information from the hard drive to the blank CD.




- To copy a CD using two drives:
  - 1 Insert the CD you want to copy into your DVD or secondary recordable CD drive.
  - **2** If a dialog box opens, click **Take no action**.
  - 3 Insert a blank, writable CD into your primary recordable CD drive.




- 4 If a *CD Drive* dialog box opens, click **Create a CD using Roxio Easy CD Creator**, then click **OK**. The *Select a Project* window opens.
  - OR -

If a dialog box does not open, click **Start**, **All Programs**, **Roxio Easy CD Creator**, then click **Project Selector**. The *Select a Project* window opens.



CD copier CD copier

**5** Move your pointer over **CD copier**, then click **CD copier**. The *CD Copier* window opens.



- 6 On the Source and Destination tab, click the arrow button to open the Copy from list, then click the drive that contains the source CD.
- **7** Click the arrow button to open the **Record to** list, then click the drive that contains the blank CD (this is your primary recordable CD drive).
- **8** Click **Copy**. The information on the source CD is copied automatically to your blank CD.



## Help and Support



For more information about copying CDs in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **copying CDs** in the HelpSpot **Search** box Search , then click the arrow.

## Playing a DVD

A Digital Versatile Disc (DVD) is similar to a standard CD but has greater data capacity. Because of this increased capacity, full-length movies, several albums of music, or several gigabytes of data can fit on a single disc. If your computer has a DVD drive, you can play DVDs with the InterVideo DVD Player program or Windows Media Player. For more information about playing DVDs, click Help in the DVD player program.

#### To play a DVD:

- 1 Make sure that the speakers are turned on or headphones are plugged in and that the volume is turned up.
- **2** Turn off your screen saver and standby timers.
- **3** To play a DVD using InterVideo DVD, click **Start**, **All Programs**, **DVD**, then click **DVD Player**. The InterVideo DVD Player video screen and control panel open.

-OR-

To play a DVD using Windows Media Player in Windows XP, click **Start**, **All Programs**, then click **Windows Media Player**. The Windows Media Player opens.

- OR -

To play a DVD using Windows Media Player in Windows 2000, click Start, Programs, Accessories, Entertainment, then click Windows Media Player. The Windows Media Player opens.

#### **Important**



If the InterVideo DVD player is not on your Start menu, or if Windows Media Player cannot play a DVD, you will need to install the InterVideo DVD program. To install the InterVideo program, insert the InterVideo DVD Software disc into your DVD drive and follow the on-screen instructions.

**4** Insert a DVD into the DVD drive, then click ▶ (play). The DVD plays.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

**5** To specifically control the DVD or adjust the volume, use the controls in the DVD player. For more information on using the DVD player, see its online help.



## Help and Support



For more information about playing DVDs in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **playing DVDs** in the HelpSpot **Search** box Search , then click the arrow.

## Viewing the display on a television

The TV out (NTSC/PAL Composite Video) jack on your notebook lets you view your notebook display on a television screen using a standard RCA video cable. The S-Video out jack on your port replicator lets you view your notebook display on a television screen using a standard S-Video cable.

#### **Important**



To turn on external video by default, connect the television (or other external video device) before starting your notebook.

#### **Important**



Audio is not transmitted through the TV out jack. Use the built-in speakers, a set of headphones or external powered speakers, or connect your notebook to a stereo system to hear sound while playing a DVD. DVD playback to a VCR will be scrambled by copyright protection technology.

#### To view your notebook display on a television:

- 1 With your notebook off, connect one end of a standard RCA video cable to the TV out (Composite Video) jack on your notebook. For the location of the TV out jack on your notebook, see "Back" on page 6.
  - OR -

With your notebook off, connect one end of a standard S-Video cable to the S-Video out jack on your port replicator. For the location of the S-Video out jack on your port replicator, see "Back" on page 261.

- **2** Connect the other end of the cable to the Video in jack on your television or VCR.
- **3** Turn on the television or VCR.
- 4 Start your notebook.


- **5** In Windows XP, click **Start**, then click **Control Panel**. The *Control Panel* window opens. If your Control Panel is in Category View, click **Appearance** and **Themes**.
  - -OR-
  - In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.
- **6** Click/Double-click the **Display** icon. The *Display Properties* dialog box opens.
- **7** Click the **Settings** tab.



8 Click Advanced. The *Default Monitor and MOBILITY M9 Properties* dialog box opens.



#### **9** Click the **Displays** tab.



- **10** Click the Enable TV button if it is not already enabled.
- 11 Click TV to make any adjustments to the TV settings.
- 12 Click Apply.
- **13** Click **OK** to close the *Default Monitor and MOBILITY M9 Properties* dialog box.
- 14 Click OK to close the *Display Properties* dialog box.
- **15** Click **X** to close the *Control Panel* window.



## **Capturing video**

Pinnacle Expression is a video capture program that lets you capture and edit full-motion video, single images, and audio through the IEEE 1394 (also known as Firewire or i.Link) port. To find the location of the IEEE 1394 port, see "Left side" on page 3.

- To use Pinnacle Expression:
  - 1 Connect one end of the IEEE 1394 cable to your external source, such as a video camera, and connect the other end of the cable to the IEEE 1394 port // on the side of your notebook.



**2** Click Start, All Programs, Pinnacle Expression, then click Pinnacle Expression. The program starts.

#### **Important**



If Pinnacle Expression is not on your Start menu, install it from the Pinnacle Expression CD. Insert the CD into your DVD or recordable CD drive and follow the instructions in the setup wizard. For more information on using Pinnacle Expression, see its online help and the online guide located on the program CD.



# Sending and Receiving Faxes

Microsoft Fax lets you send and receive faxes using the modem. Read this chapter to learn how to:

- Install and configure Fax
- Create and send a new fax
- Set up a fax cover page template
- Fax a document you scanned or created in another program
- Receive, view, and print a fax

#### **Important**



Your modem cable must be installed before you can send and receive faxes. You cannot use your standard telephone modem to connect to the Internet while sending and receiving faxes.

#### Help and Support



For more information about sending and receiving faxes in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **Fax** in the HelpSpot **Search** box <sub>Search</sub> , then click the arrow.

## Installing and configuring Fax

If you are using Windows XP, complete the following instructions for installing and configuring Fax. If you are using Windows 2000, go to "Configuring Fax in Windows 2000" on page 137.

## **Installing Fax in Windows XP**

Microsoft Fax lets you send and receive faxes using your modem. When Windows XP was originally installed on your computer, Fax was not installed. You need to install Fax from your blue *Operating System* CD.

### To install Fax:

- 1 Place the blue *Operating System* CD in your DVD or recordable CD drive.
- **2** If the *Welcome to Microsoft Windows XP* dialog box opens, click **Install optional Windows components**. The Windows Components Wizard opens.

-OR-

If the *Welcome to Microsoft Windows XP* dialog box does not open, click **Start**, then click **Control Panel**. The *Control Panel* window opens. Click/Double-click **Add and Remove Programs**. The *Add or Remove Programs* dialog box opens. Click **Add/Remove Windows Components**. The Windows Components Wizard opens.

- 3 Click Fax Services, then click Next.
- **4** Click Finish to exit the Windows Components Wizard.
- 5 Click Exit to close the Welcome to Microsoft Windows XP dialog box.

-OR-

Click Close to close the Add or Remove Programs dialog box.



## **Configuring Fax in Windows XP**

Before you send your first fax, you need to set up your user information. Your fax cover sheets and fax headers contain this information, some of which is required by law. The Fax Configuration Wizard opens the first time you try to send a fax.

#### **Important**



The first time you run the Fax Configuration Wizard, you may need to provide information in the *Location Information* and the *Phone and Modem Options* dialog boxes.

#### To configure Microsoft Fax:

- 1 Click Start, All Programs, Accessories, Communications, Fax, then click Fax Console. The Fax Configuration Wizard opens.
- **2** On the *Welcome to Fax Configuration Wizard* screen, click **Next**. The *Sender Information* screen opens.



**3** Enter the information about yourself that you want to appear on your fax cover page, then click **Next**. The *Select Device for Sending or Receiving Faxes* screen opens.




- **4** Click the arrow to open the **Please select the fax device** list, then click the modem you are using to send and receive faxes.
- 5 If you want the modem to automatically answer the telephone in order to receive faxes, click the **Enable Receive** check box.
- 6 Click Next. The Transmitting Subscriber Identification (TSID) screen opens.
- 7 Enter the transmitting fax identifier information. This identifier information is required by law. You can enter up to 20 characters in the text box. We suggest using eight characters for your identifier name, followed by 12 characters for your telephone number.

#### Important



Some fax machines cannot use special characters such as hyphens. We suggest using spaces instead of hyphens in telephone and fax numbers.



- 8 Click Next.
- **9** If you set up your computer to receive faxes, enter the receiving fax identifier information, then click **Next**. This identifier information is required by law and can be the same identifier that you entered in Step 7. The *Routing Options* screen opens.

- **10** If you set up your computer to receive faxes, select a folder you want to store receive faxes in and a printer you want to print received faxes on, then click **Next**. The *Configuration Summary* screen opens.
- 11 Click Finish.



## **Configuring Fax in Windows 2000**

Before you send your first fax, you need to set up your user information. Your fax cover sheets and fax headers contain this information, some of which is required by law.

- To configure Microsoft Fax:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Double-click the **Fax** icon. The *Fax Properties* dialog box opens.
  - 3 Click the User Information tab.
  - **4** Enter the information about yourself that you want to appear on the fax cover page.
  - 5 Click the Advanced Options tab.
  - 6 Click Open Fax Service Management Console. The Fax Service Management window opens.
  - 7 Click **Devices** in the left column.
  - **8** Double-click the name of your modem. The *Modem Properties* dialog box opens.
  - 9 Click Enable send.



10 Enter the transmitting fax identifier information. This identifier information is required by law. You can enter up to 20 characters in the text box. We suggest using eight characters for your identifier name, followed by 12 characters for your telephone number.

#### Important



Some fax machines cannot use special characters such as hyphens. We suggest using spaces instead of hyphens in telephone and fax numbers

11 If you want to receive faxes, click **Enable receive**.

-OR-

If you do not want to receive faxes, go to Step 14.

- **12** Enter the receiving fax identifier information. This identifier information is required by law and can be the same identifier that you entered in Step 10.
- 13 Click the Received Faxes tab and select a folder you want to store received faxes in.
- 14 Click OK.
- **15** Click the **X** in the top-right corner to close the *Fax Service Management* window.
- 16 Click OK.



## Sending a simple fax

You can use the Send Fax Wizard to send a simple one-page fax to one or more recipients.

- To send a simple fax:
  - 1 In Windows XP, click Start, All Programs, Accessories, Communications, Fax, then click Send a Fax. The Send Fax Wizard opens.
    - OR -

In Windows 2000, click Start, Programs, Accessories, Communications, Fax, then click Send Cover Page Fax. The Send Fax Wizard opens.

- 2 On the *Welcome to Fax Configuration Wizard* screen, click **Next**. The *Recipient Information* screen opens.
- **3** Enter the name and fax number of the recipient of your fax.
- 4 If you need to enter the area code for your recipient, click **Use dialing rules** to enter the full ten-digit fax number.
- 5 If you want to send your fax to more than one recipient, click Add and enter the name and fax number of the next recipient.





- **6** When you have entered all your recipients, click **Next**. The *Preparing the Cover Page* screen opens.
- **7** Click the arrow to open the **Cover page template**, then click the cover page template you want to use.
- **8** Type the subject text in the **Subject line** area.
- **9** Type the message text in the **Note** area, then click **Next**. The *Schedule* screen opens.
- **10** Select when you want to send the fax and a priority for the fax, then click **Next**. The *Completing the Send Fax Wizard* screen opens.
- 11 Click Finish.



# Setting up your cover page template

You can create your own cover page template that you can use in place of the cover page templates that Microsoft Fax provides for you. To create a cover page template, you use the Fax Cover Page Editor. On this template, you insert information fields that automatically import values you enter in both the Send Fax Wizard and the Fax Configuration Wizard (Windows XP) or Fax Properties User Information tab (Windows 2000) when you send your fax.



1 In Windows XP, click Start, All Programs, Accessories, Communications, Fax, then click Fax Cover Page Editor. The Cover Page-Fax Cover Page Editor opens. If the *Cover Page Editor Tips* dialog box opens, click OK.

-OR-

In Windows 2000, click Start, Settings, then click Control Panel. The *Control Panel* window opens. Double-click the Fax icon. The *Fax Properties* dialog box opens. Click the Cover Pages tab. Click New. The Cover Page-Fax Cover Page Editor opens.

- 2 If you want to include fields that are imported from either the Send Fax Wizard or the Fax Configuration Wizard (such as To or From), add them to the page by using the Insert menu, then move them to the appropriate place on your template. You can also use the Insert menu to include information that is automatically calculated (such as number of pages or date and time sent).
- **3** If you want to include text that always appears on your cover page (such as a letterhead or address), draw a box using the text box tool, enter your text inside of it, then move the box to the appropriate place on your template.
- **4** If you want to include a logo that appears on your cover page, copy it to the Windows clipboard, then paste it into the Cover Page Editor and move it to the appropriate place on your template.
- **5** To save your cover page template, click **File**, then click **Save As**. The *Save As* dialog box opens with your personal cover pages folder already in the **Save** in list.
- **6** Type the new cover page template name.
- 7 Click Save.



## **Faxing from programs**

- To fax a document directly from most programs:
  - 1 Open your document in the program it was created in.
  - **2** Click File, then click Print. The *Print* dialog box opens.
  - 3 Click the arrow button to open the Name list, then click the Fax printer.
  - 4 Click Print or OK. The Send Fax Wizard opens.
  - **5** Complete the wizard by following the instructions in "Sending a simple fax" on page 139.



## Faxing a scanned document

- To fax a document that you have scanned:
  - 1 Scan the document using the program for your scanner.
  - **2** With the scanned file open, click **File**, then click **Print**. The *Print* dialog box opens.
  - 3 Click the arrow button to open the Name list, then click the Fax printer.
  - 4 Click Print or OK. The Send Fax Wizard opens.
  - **5** Complete the wizard by following the instructions in "Sending a simple fax" on page 139.



## Receiving and viewing a fax

- To receive and view a fax in Windows XP:
  - 1 Click Start, All Programs, Accessories, Communications, Fax, then click Fax Console. The Fax Console opens. When the Fax Console is open, it detects incoming faxes and stores them in the Inbox.
  - **2** To view a fax, click **Inbox**, then double-click the fax you want to view. The fax viewer opens, where you can view and print the fax.



- To receive and view a fax in Windows 2000:
  - 1 Click Start, Programs, Accessories, Communications, Fax, then click My Faxes. The My Faxes folder opens.
  - **2** To view a fax, double-click **Received Faxes**, then double-click the fax you want to view. The fax viewer opens, where you can view and print the fax.



## Canceling a fax

You can cancel a fax that you have set up to send at a time in the future.

- To cancel a fax that has not been sent in Windows XP:
  - 1 If Fax is not open, click Start, All Programs, Accessories, Communications, Fax, then click Fax Console. The Fax Console opens.
  - **2** Click **Outbox**, then right-click the fax you want to cancel.
  - 3 Click **Delete** to cancel the fax.
  - 4 Click Yes.



- To cancel a fax that has not been sent in Windows 2000:
  - 1 If Fax is not open, click Start, Programs, Accessories, Communications, Fax, then click Fax Queue. The Fax Queue opens.
  - 2 Right-click the fax you want to cancel.
  - 3 Click Cancel.



## Automatically retry sending a fax in Windows XP

You can set up Fax so that it continues to try sending your fax if the receiving fax machine is busy.

Important



Fax is automatically set up to retry three times at ten minute intervals.

- To automatically retry sending a fax:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens.
  - 2 If your Control Panel is in Category View, click Printers and Other Hardware. Click View installed printers or fax printers. The *Printers and Faxes* window opens.

-OR-

If your Control Panel is in Classic View, double-click the **Printers and Faxes** icon. The *Printers and Faxes* window opens.

- **3** Right-click **Fax**, then click **Properties**. The *Fax Properties* dialog box opens.
- 4 Click the Devices tab, then click Properties. The *Modem* dialog box opens.
- **5** Specify the number of retries and the amount of time between retries.
- 6 Click OK.



# Automatically cancelling a fax in Windows XP

If your computer tried to send a fax and failed to connect to a fax machine, you can automatically cancel a failed fax.

- To automatically cancel a failed fax:
  - 1 Click Start, then click Control Panel. The Control Panel window opens.
  - 2 If your Control Panel is in Category View, click Printers and Other Hardware. Click View installed printers or fax printers. The *Printers and Faxes* window opens.

-OR-

If your Control Panel is in Classic View, double-click the **Printers and Faxes** icon. The *Printers and Faxes* window opens.

- **3** Right-click **Fax**, then click **Properties**. The *Fax Properties* dialog box opens.
- **4** Click the **Devices** tab, then click **Properties**. The *Modem* dialog box opens.
- 5 Click the Cleanup tab.
- 6 Click to select the Automatically delete failed faxes after check box and specify the number of days.
- 7 Click OK.



Chapter 7: Sending and Receiving Faxes

# Managing Power 8

While your notebook is running on battery power, you should manage power consumption to get the most use out of the battery. Read this chapter to learn how to:

- Check and recharge the battery
- Recalibrate the battery
- Change batteries
- Extend the life of the battery by conserving battery power and using alternate power sources
- **■** Change power-saving settings

## Monitoring the battery charge

Closely monitor the battery charge. When the battery charge gets low, change the battery or connect to AC power immediately to prevent losing any unsaved work.

Monitor the battery charge by:

■ Double-clicking the power cord icon **\** or battery icon **\** in the taskbar. The *Power Meter* dialog box opens.

#### Important



If the power cord or battery icon does not appear on the taskbar, click the show hidden icons **()** button.

- Pressing FN+STATUS to view the power status box, which opens in the upper-left corner of the screen. The power status box shows the current power source, the battery charge level, and the power management mode.
- Looking at the battery charge indicator:
  - LED green battery is fully charged.
  - LED orange battery is charging.
  - LED red battery is malfunctioning.

#### **Important**



This LED only lights up when the notebook is connected to AC power. For the location of the battery charge indicator, see "Front" on page 2.

■ Pressing the battery meter buttons on the main battery and optional secondary battery. The battery meter lights indicate the percentage of battery charge remaining.



■ Waiting for a Low Battery warning message to appear.

If your battery charge indicator displays what looks like an inaccurate charge, you may need to recalibrate the battery. For more information, see "Recalibrating the battery" on page 150.

## Recharging the battery

Both the main and the optional secondary batteries recharge while they are installed and your notebook is connected to AC power. While the batteries are recharging, the battery charge indicator turns orange and the battery icon in the taskbar has a lightning bolt ...

**Important** 



If the power cord or battery icon does not appear on the taskbar, click the show hidden icons 6 button.

## Recalibrating the battery

If your notebook unexpectedly goes into Standby mode while you are using it but the battery charge is not low, you may need to recalibrate your battery. You should also recalibrate the battery periodically to maintain the accuracy of the battery gauge.

- To recalibrate the battery:
  - 1 Connect the AC adapter, then turn on your notebook.
  - **2** As soon as it starts and you see a startup screen, press **F2**. The BIOS Setup utility opens.
  - **3** Open the **Advanced** menu.
  - 4 Highlight Battery Auto Learning, then select Enabled by pressing the spacebar.
  - 5 Open the Exit menu, then highlight Exit Saving Changes and press ENTER.
  - 6 Select Yes, then press ENTER.

The battery recalibration process begins and a screen opens showing you the progress. The entire process will take several hours.

#### **Important**



Do not interrupt the battery recalibration process. If recalibration is interrupted, you must start the process over again.

When the recalibration has finished, the message "Press [Esc] key to exit" appears.

**7** Press **Esc**. The battery meter now displays an accurate battery charge. If the battery meter does not show an accurate charge, contact Gateway Technical Support.



## **Changing batteries**

If your notebook is plugged into an AC outlet or if it has a charged secondary battery installed, you can change the main battery while the notebook is turned on. If your notebook has only one battery and it is not plugged into an AC outlet, you must turn the notebook off while changing the batteries.

#### Warning



Danger of explosion if battery is incorrectly replaced.

Replace only with a Gateway 600YG2 battery. Discard used batteries according to the manufacturer's instructions.

The battery used in this device may present a fire or chemical burn hazard if mishandled. Do not disassemble, heat above 212°F (100°C), or incinerate. Dispose of used battery promptly. Keep away from children.

## Replacing the main battery

- To replace the main battery:
  - 1 If your notebook is on and is plugged into an AC outlet or has a charged secondary battery installed, go to Step 2.


-OR-

If your notebook is on and is not plugged into an AC outlet and does not have a charged secondary battery installed, save your work and turn off the notebook.


- **2** Close the LCD panel.
- **3** Disconnect your notebook from the optional port replicator (see "Disconnecting from the port replicator" on page 264).
- 4 Turn your notebook over so that the bottom is facing up.



#### Slide the battery release latch.



6 Lift the battery out of the bay.



- Place a recharged battery into the bay and press down until it snaps into place.
- Turn your notebook over and reattach the optional port replicator.
- Open the LCD panel and press the power button.



## Installing a secondary battery

Your notebook's right-side modular bay accepts a secondary battery. The secondary battery charges when the notebook is connected to AC power.

#### Warning



Danger of explosion if battery is incorrectly replaced.

Replace only with a Gateway 600YG2 secondary battery. Discard used batteries according to the manufacturer's instructions.


The battery used in this device may present a fire or chemical burn hazard if mishandled. Do not disassemble, heat above 212°F (100°C), or incinerate. Dispose of used battery promptly. Keep away from children.

#### To install a secondary battery:


- 1 If you are removing a DVD, recordable CD, or diskette drive, make sure that the drive is empty.
- **2** Make sure that your notebook is off (not in Standby or Hibernate mode).
- **3** Close the LCD panel.
- **4** Disconnect your notebook from the optional port replicator (see "Disconnecting from the port replicator" on page 264).
- 5 Turn your notebook over so that the bottom is facing up.



**6** Slide and hold the bay module latch and press the bay module release button. The module moves out slightly.



- **7** Slide the bay module out.
- **8** Firmly push the secondary battery straight into the bay until the latch clicks into place.



- Turn your notebook over.
- Reattach the optional port replicator.
- Open the LCD panel and press the power button.



## **Extending battery life**

## **Conserving battery power**

While using the battery to power your notebook, conserve power by:

- Dimming the display as low as is comfortable.
- Removing PC Cards when you do not need them. Many PC Cards use a small amount of power while inserted, even if they are not being used.
- Modifying the power management settings for maximum power savings. For more information, see "Changing power settings" on page 158.
- Closing the LCD panel to turn off the display while you are not using your notebook. The display stays off until you open the panel again.
- Using Hibernate mode for maximum power savings while your notebook is not in use. For more information, see "Activating and using Hibernate mode" on page 162.
- Using the DVD or recordable CD drive only when necessary. These drives use a large amount of power.
- Recharge the battery often, take an extra battery, and fully recharge the batteries before traveling. For more information, see "Recharging the battery" on page 149 and "Changing batteries" on page 151.

## Using alternate power sources

To extend battery life, use alternate power sources whenever possible.

- If traveling internationally, take electrical adapters. Save the battery for times when you cannot use a power adapter. If you plan on taking your AC power adapter, also take a single-plug surge protector.
- If you will have access to an EmPower<sup>™</sup> in-flight power receptacle or an automobile cigarette lighter, use an airplane/automobile power adapter. Save the battery for times when you cannot use a power adapter.
- To find AC power outlets in airports, look for them next to support pillars, in large areas such as boarding gates, and under banks of telephones.

## **Changing power modes**

You can use the following power modes to lengthen the life of your notebook's battery:

- *Standby* while your notebook is in Standby, it switches to a low power state where devices, such as the display and drives, turn off.
- *Hibernate* (also called *save to disk*) writes all current memory (RAM) information to the hard drive, then turns your notebook completely off. The next time you turn on your notebook, it reads the memory information from the hard drive and opens the programs and documents that were open when you activated Hibernate mode. For more information on using Hibernate mode, see "Activating and using Hibernate mode" on page 162.

#### Using power saving modes

Always save your work before using Standby mode. In Standby mode, your notebook reduces or turns off the power to most devices except memory. However, the information in memory is not saved to the hard drive. If power is interrupted, the information is lost.

When in Hibernate mode, your computer saves all memory information to the hard drive, then turns the power completely off.

If your computer is	and you want to	then
On	Enter Standby mode	Press Fn+STANDBY.
On	Enter Hibernate mode (must be enabled)	In Windows XP, click Start, then click Turn Off Computer. Press and hold SHIFT, then click Hibernate.  OR - In Windows 2000, click Start, then click Shut Down. Click the arrow button to open the What do you want your computer to do list, then click Hibernate. Click OK.
In Standby or Hibernate mode	Exit Standby or Hibernate mode	Press the power button.

## **Changing power settings**

You can change the function of the power button, Standby system key, and power-saving timers by changing power settings on your notebook.

You can customize power settings from the Windows Control Panel by selecting power schemes, setting power alarms, adjusting advanced power settings, and activating Hibernate mode.

*Power schemes* (groups of power settings) let you change power saving options such as when the display or hard drive is automatically turned off. You can select one of the defined power schemes or create a custom power scheme.

Alarms can alert you when the battery charge is low.

Advanced power settings let you assign different power saving modes to the power button and Standby system key. You can also select which power saving mode is activated when you close the LCD panel.

## Changing the power scheme



To change the power scheme

- 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Performance and Maintenance.
  - OR -

In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.

**2** Click/Double-click the **Power Options** or **Power Management** icon. The *Power Options Properties* dialog box opens.



- **3** Click the arrow button to open the **Power Schemes** list, then click the power scheme you want.
  - OR -

Set the timers, then save your custom power scheme by clicking **Save As** and typing a name for the scheme.

4 Click OK.



## Help and Support



For more information about changing the power scheme in Windows XP, click **Start**, then click **Help and Support**.


Type the keyword **power scheme** in the HelpSpot **Search** box Search [ ], then click the arrow.

## **Changing alarm options**

- To change the alarm options:
  - 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Performance and Maintenance.
    - OR -

In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.

- **2** Click/Double-click the **Power Options** or **Power Management** icon. The *Power Options Properties* dialog box opens.
- **3** Click the Alarms tab.



- **4** Adjust the alarm settings.
- 5 Click OK.



## Help and Support



For more information about changing the alarm options in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **alarm options** in the HelpSpot **Search** box Search , then click the arrow.

## **Changing advanced settings**

- To change advanced power management settings:
  - 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Performance and Maintenance.
    - OR -
    - In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.
  - **2** Click/Double-click the **Power Options** or **Power Management** icon. The *Power Options Properties* dialog box opens.
  - 3 Click the Advanced tab.





- **4** Click the arrow button to open a **Power buttons** list, then click the power setting mode you want to use.
- 5 Click OK.



Help and Support



For more information about changing the power management settings in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **power management** in the HelpSpot **Search** box Search [ ], then click the arrow.


## **Activating and using Hibernate mode**

- To activate Hibernate mode:
  - 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Performance and Maintenance.
    - OR -

In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.

**2** Click/Double-click the **Power Options** or **Power Management** icon. The *Power Options Properties* dialog box opens.

3 Click the Hibernate tab.



4 Click the **Enable hibernation** check box, then click **Apply**. *Hibernate* mode is now an option you can select on the Advanced tab in the *Power Options Properties* dialog box and in the *Turn Off Computer* or *Shut Down Windows* dialog box.



- To use Hibernate mode:
  - As an automatic power savings mode:

Open the *Power Options Properties* dialog box, then click the **Power Schemes** tab. Click the arrow button to open a **System hibernates** list, then click the time you want to use.

-OR-

Open the *Power Options Properties* dialog box, then click the **Advanced** tab. Hibernate is now an option in the **Power buttons** lists.



■ As a manually-selected power savings mode:

In Windows XP, click Start, then click Turn Off Computer. Press and hold SHIFT, then click Hibernate.

-OR-

In Windows 2000, click Start, then click Shut Down. Click the arrow button to open the What do you want your computer to do list, then click Hibernate. Click OK.



## Help and Support



For more information about using Hibernate mode in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **hibernate** in the HelpSpot **Search** box Search , then click the arrow.

## **Changing SpeedStep settings**

The processor installed in your notebook may use  $Intel^{\circledR}$  SpeedStep<sup>TM</sup> technology to conserve battery power. A SpeedStep-equipped processor can change its operating speed according to the power source. Your notebook's default settings operate the processor at full speed while connected to AC power and at reduced speed (which uses less power) while using battery power. If you are using Windows XP, you can change the Intel SpeedStep settings in the BIOS Setup utility. If you are using Windows 2000, you can change the SpeedStep settings in Windows.

- To change SpeedStep settings in Windows XP:
  - 1 Turn on your notebook.
  - **2** As soon as it starts and you see a startup screen, press **F2**. The BIOS Setup utility opens.
  - **3** Open the **Advanced** menu.
  - **4** Highlight In Battery only, then change the value by pressing the + key.
  - **5** Highlight In AC mode, then change the value by pressing the + key.

- 6 Open the Exit menu, highlight Exit Saving Changes, then press ENTER.
- **7** Select **Yes**, then press **ENTER**.



- To change SpeedStep settings in Windows 2000:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Double-click the **Power Management** icon. The *Power Options Properties* dialog box opens.
  - 3 Click the Intel SpeedStep technology tab.





#### **4** Change any of the following settings:

- To run the processor at full speed regardless of the power source, click the arrow button to open the Running on batteries list, then click Maximum Performance.
- To run the processor at reduced speed (using less power) regardless of the power source, click the arrow button to open the Plugged in list, then click Battery Optimized Performance.
- To turn off the SpeedStep technology control, click the Advanced tab, click the Disable Intel SpeedStep technology control check box, then click Apply.
- To remove the SpeedStep icon from the taskbar, click the Advanced tab, click the Remove icon from taskbar check box, then click Apply.

#### 5 Click OK.



# Travel Tips 9

These tips can make traveling with your notebook more convenient and trouble-free. Read this chapter to learn about:

- Using the modem
- Using your radio frequency wireless connections
- Transferring files
- Protecting your notebook from loss and theft
- Managing your notebook's power efficiently

#### **Tips & Tricks**



To access the contents of this guide while you are traveling, click **Start**, **All Programs**, then click **Gateway Utilities**. You can also download an electronic copy from <a href="https://www.gateway.com/support/manlib/">www.gateway.com/support/manlib/</a>.

## Modem

- Take a telephone cord to connect the modem to telephone jacks. If you are traveling internationally, take telephone jack adapters or an acoustic handset coupler.
- Take a telephone line protector.
- Take a telephone line tester to check for unsafe lines, especially if you are traveling internationally.
- Take remote access information with you so you can connect to your ISP while outside of your usual calling area. A list of country dialing codes may be especially useful if you are traveling internationally.

# Radio frequency wireless connections

- Every country has different restrictions on the use of wireless devices. If your notebook is equipped with a wireless device, check with the local radio approval authorities prior to your trip for any restrictions on the use of a wireless device in the destination country.
- If your notebook came equipped with an internal embedded wireless device, see "Safety, Regulatory, and Legal Information" on page 295 for general wireless regulatory guidelines.
- Wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. IEEE 802.11b (also known as wireless Ethernet or Wifi) and Bluetooth communication devices are examples of devices which use wireless to communicate. For instructions on how to turn off your wireless device, see "Turning your wireless Ethernet on or off" on page 201.

## **Files**

- Copy your working files from your desktop computer to your notebook before you travel.
- If you need to access your desktop computer files from your notebook while traveling, set up your desktop computer for remote access. Contact your network administrator for more information about remote access.
- Take extra diskettes or writable CDs for transferring files between computers and backing up files.

## **Security**

- Get a locking cable for your notebook so that you can attach a cable lock and leave your notebook in your hotel room while you are away.
- Always keep your notebook with you while waiting in airports, train stations, or bus terminals. Be ready to claim your notebook as soon as it passes through the x-ray machine in security checkpoints.
- Write down your notebook model number and serial number (see "Identifying your model" on page 12) in case of theft or loss, and keep the information in a safe place. Also, tape your business card or an address label to your notebook and accessories.
- Whoever sits next to you or behind you can see your notebook display. Avoid working with confidential files until you can be sure of privacy.
- Use a startup password to restrict access to your notebook.

#### **Important**



Use a password that you can remember, but that is difficult for someone else to guess. The password feature is very secure, with no easy way to recover a forgotten password. If you forget your password, you must return your notebook to Gateway for service. Call Gateway Technical Support for instructions.

#### To create a startup password:

- 1 Restart your notebook. As soon as you see a startup screen, press **F2**. The BIOS Setup utility opens.
- 2 Open the Security menu, highlight Set Supervisor Password, then press ENTER and follow the instructions. You must set the supervisor password in order to set the user (startup) password.
- **3** Highlight **Set User Password**, then press **ENTER** and follow the instructions. This is the password you need to enter at startup.
- 4 Highlight Password on boot, then press ENTER.
- 5 Highlight Enabled, then press ENTER.
- **6** To exit the BIOS Setup utility, open the **Exit** menu, then select **Exit Saving Changes**. When you start your computer, you are prompted to enter the user password you set in Step 3.



### **Power**

- Take your AC power adapter to recharge the battery. If you are traveling internationally, take power plug adapters.
- Take a portable surge protector to protect your notebook from power surges.
- To get the best performance from your notebook, avoid using the battery whenever possible, monitor the battery charge, and use the most efficient power management settings.
  - For information on conserving battery power, see "Conserving battery power" on page 156.
  - For information on using alternate power sources, see "Using alternate power sources" on page 156.
  - For information on monitoring the battery charge, see "Monitoring the battery charge" on page 148.

### **Additional tips**

- If you plan to use several USB peripheral devices, take a portable USB hub to provide additional USB ports.
- Take a network cable if you need to connect to a network. Some hotels provide Internet connectivity only through their networks.
- Take your *System Restoration CDs* in case you need to install an additional driver or software.

# Customizing 10 Your Computer

This chapter provides information about customizing your computer by changing settings in Windows. Read this chapter to learn how to:

- Change screen and display settings
- Change the background and screen saver
- Adjust the touchpad settings
- Add, change, and switch user accounts in Windows XP

# Adjusting the screen and desktop settings

Adjusting the color depth and screen area are two of the most basic display settings you may need to change. You can also adjust settings such as the screen background and screen saver.

### Adjusting the color depth

Color depth is the number of colors your screen displays. Various image types require various color depths for optimum appearance. For example, simple color drawings may appear adequately in 256 colors while color photographs need millions of colors to be displayed with optimum quality.

Windows lets you choose from several color depth settings. We recommend that you use the 32-bit True Color setting at all times.

If the color in your images seems "false" or "jumpy," especially after you have played a game or run a video-intensive program, check the color depth setting and return it to 32-bit True Color, if necessary.

### To change the color depth:

- 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Appearance and Themes.
  - OR -

In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.

**2** Click/Double-click the **Display** icon. The *Display Properties* dialog box opens.

### **3** Click the **Settings** tab.



- 4 Click the arrow button to open the Color quality or Colors list, then click the color depth you want.
- **5** To save your changes in Windows XP, click **OK**, then click **Yes**.
  - OR -

To save your changes in Windows 2000, click  $\mathbf{OK}$ , then click  $\mathbf{OK}$  again.



### Help and Support



For more information about adjusting display settings in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **changing display settings** in the HelpSpot **Search** box Search , then click the arrow.

### Adjusting the screen resolution

You can increase the screen resolution to fit more icons on your desktop, or you can decrease the resolution to make reading the display easier. The higher the resolution, the smaller individual components of the screen (such as icons and menu bars) appear.

- To adjust the screen resolution:
  - 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Appearance and Themes.
    - OR -
    - In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.
  - **2** Click/Double-click the **Display** icon. The *Display Properties* dialog box opens.
  - **3** Click the **Settings** tab.



4 Drag the Screen resolution or Screen area slider to the size you prefer.

**5** To save your changes in Windows XP, click **OK**, then click **Yes**.

- OR -

To save your changes in Windows 2000, click OK, then click OK again.



### Help and Support



For more information about adjusting screen resolution in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **changing screen resolution** in the HelpSpot **Search** box **Search ...**, then click the arrow.

# Changing the colors on your Windows desktop

You can change the colors of Windows desktop items, such as the background color and dialog box title bars.

- To change desktop colors in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Appearance and Themes.
  - **2** Click/Double-click the **Display** icon. The *Display Properties* dialog box opens.



### **3** Click the **Appearance** tab.



- 4 Click the arrow button to open the Color scheme list, click the color scheme you want, then click OK. The new colors appear on your desktop.
  - OR -

If you want to create a new color scheme as part of a desktop theme:

- **a** Click **Advanced**. The *Advanced Appearance* dialog box opens.
- **b** Click the arrow button to open the **Item** list, then click the item you want to change.
- **C** Change the color or font settings for the item.
- d Click OK, then click the Themes tab.
- **C**lick **Save As**, type a name for the new theme, then click **OK** twice. The new colors appear on your desktop.



- To change desktop colors in Windows 2000:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Double-click the **Display** icon. The *Display Properties* dialog box opens.
  - 3 Click the Appearance tab.



- 4 If you want to apply one of Windows' color schemes, click the arrow button to open the **Scheme** list, click the scheme you want, then click **OK**. The new scheme appears on your desktop.
  - OR -

If you want to create a new color scheme:

- **a** Click the arrow button to open the **Item** list, then click the item you want to change.
- **b** Change the color or font settings for the item.
- C Click Save As, type a name for the new scheme, then click OK.
- **d** Click **OK** again. The new colors appears on your desktop.



### Changing the desktop background

In Windows XP, you can change the Windows desktop background picture. Windows provides several backgrounds, or you can use pictures that you have created or retrieved from other sources.

In Windows 2000, you can change the Windows desktop background to a picture or an HTML document. Windows provides several background pictures. You can also use pictures or HTML documents that you have created or retrieved from other sources.

- To change the desktop background in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Appearance and Themes.
  - **2** Click/Double-click the **Display** icon. The *Display Properties* dialog box opens.
  - 3 Click the **Desktop** tab.



- 4 Click a background picture in the Background list.
  - OR -

Click Browse to select a background picture from another location.

- 5 If you want the picture you chose to cover the entire screen, click the arrow button to open the **Position** list, then click **Stretch** or **Tile**.
- **6** If the picture you chose does not cover the entire screen and you did not choose to stretch or tile the image in Step 5, you can change the solid color behind the picture by clicking the arrow button to open the **Color** list, then clicking a color.
- 7 Click OK.



### Help and Support




For more information about changing the desktop background in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **changing desktop background** in the HelpSpot **Search** box Search , then click the arrow.

- To change the desktop background in Windows 2000:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Double-click the **Display** icon. The *Display Properties* dialog box opens.



3 Click the Background tab.



- 4 Click a background picture in the Select a background picture or HTML document as Wallpaper list.
  - OR -

Click Browse to select a background picture from another location.

- 5 If you want the picture you chose to cover the entire screen, click the arrow button to open the Picture Display list, then click Tile.
- **6** If the picture you chose does not cover the entire screen and you did not choose to tile the image in Step 5, you can change the solid color behind the picture by clicking **Pattern**, clicking a pattern in the **Pattern** list, then clicking **OK**.
- 7 Click OK.



### Selecting a screen saver

You can use a screen saver to keep others from viewing your display while you are away from your computer. Windows supplies a variety of screen savers that you can choose from, and many more are available from the Internet and as commercial products.

### To select a screen saver:

- 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Appearance and Themes.
  - OR -
  - In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.
- **2** Click/Double-click the **Display** icon. The *Display Properties* dialog box opens.
- 3 Click the Screen Saver tab.





- 4 Click the arrow button to open the **Screen Saver** list, then click the screen saver you want. Windows previews the screen saver.
- 5 If you want to customize the screen saver, click **Settings**, then make your changes. If the Settings button is not available, you cannot customize the screen saver you selected.
- 6 In Windows XP, if you want to display the Welcome (Login) screen whenever you exit the screen saver, click the On resume, display Welcome screen check box.
- **7** If you want to change the time before the screen saver is activated, click the up or down arrows next to the **Wait** box.
- 8 Click OK.



Help and Support



For more information about selecting a screen saver in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **screen savers** in the HelpSpot **Search** box Search , then click the arrow.

## Changing the touchpad settings

You can adjust the double-click speed, pointer speed, left-hand or right-hand configuration, and other touchpad settings.

- To change your touchpad settings:
  - 1 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
    - OR -

In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.

**2** Click/Double-click the **Mouse** icon. The *Mouse Properties* dialog box opens.





- 3 Click the Advanced Features tab, then click Settings to change your touchpad settings.
- **4** To modify a touchpad setting, click the **+** in front of a setting, then modify the setting.



- **5** To assign a function to the rocker switch, click the **+** in front of **Button Actions**, click the up or down button, then click the action you want.
- 6 Click **OK** to save changes.



Help and Support



For more information about changing mouse settings in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **mouse settings** in the HelpSpot **Search** box Search [ ], then click the arrow.

# Adding and modifying user accounts

In Windows XP, you can create and customize a user account for each person who uses your computer. You can also *switch* (change) user accounts without turning off your computer.

### User account tips

- If you want to create an account for someone, but you do not want that user to have full access to your computer, be sure to make that account *limited*. Remember that limited accounts may not be able to install some older programs.
- If a program or peripheral device is installed in one account, it may not be available in other accounts. If this happens, install the program or device in the accounts that need it.
- Files created in one account are not accessible from other accounts unless the files are stored in the *Shared Documents* folder. The Shared Documents folder is accessible from all accounts on that computer and from other computers on the network.
- To add, delete, or modify user accounts in Windows XP:
  - 1 Click Start, then click Control Panel.
  - 2 Click/Double-click the User Accounts icon. The User Accounts window opens.
  - **3** Follow the on-screen instructions to add, delete, or modify a user account.



Help and Support



For more information about user accounts in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **user accounts** in the HelpSpot **Search** box Search [ ], then click the arrow.



To switch user accounts in Windows XP:

1 Click Start, then click Log Off. The Log Off Windows dialog box opens.



- **2** Click **Switch User**. The Windows *Welcome* screen opens.
- **3** Click the user account that you want to use. When you switch between user accounts, any programs that were running for the previous user continue to run.



# Networking Your Computer

Connecting your home, small office, or home office computers lets you share drives, printers, and a single Internet connection among the connected computers.

Read this chapter to learn about:

- Benefits of using a network in your home, small office, or home office
- Types of network connections
- Purchasing additional network equipment
- Installing and configuring your notebook for Ethernet networking
- Turning wireless Ethernet on and off

### Benefits of networking

A network lets you:

- Share a single Internet connection
- Share computer drives
- Share peripheral devices
- Stream audio and video files
- Play multi-player games

### **Sharing a single Internet connection**

Each computer that is connected to the network can share the same broadband connection or modem and telephone line and access the Internet at the same time. This saves on the cost of installing another telephone line for your second computer and paying for a second Internet service provider (ISP) account.

Help and Support



For more information about sharing an Internet connection in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **internet sharing** in the HelpSpot **Search** box Search , then click the arrow.

### **Sharing drives**

With a network, you can copy files from computer to computer by copying and pasting or dragging and dropping. You will no longer waste your time transferring files by using diskettes. In addition, you can *map* a drive on a networked computer to another computer, and access the files as if they were located on the hard drive of the computer you are using.

Help and Support



For more information about sharing network drives in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **sharing network drives** in the HelpSpot **Search** box Search , then click the arrow.

### **Sharing peripheral devices**

Each computer that is connected to the network can share the same peripheral devices, such as a printer. Select print from the computer you are currently using and your file is automatically printed on your printer no matter where it is located on your network.

Help and Support



For more information about sharing network devices in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **sharing** in the HelpSpot **Search** box Search , then click the arrow.

### Streaming audio and video files

With a network, you can store audio files (such as the popular .MP3 files) and video files on any networked computer, then play them on any of the other computers or devices connected to your network. This process is called *streaming*.

Help and Support



For more information about streaming files in Windows XP, click **Start**, then click **Help and Support**.

### Playing multi-player games

With a home network, you can play multi-player games. Load a game like *Microsoft Midtown Madness 2* on your computers, and in minutes, you and your friends can race in competing cars through the streets of San Francisco.

Help and Support



For more information about playing multi-player games in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **games** or **network games** in the HelpSpot **Search** box Search , then click the arrow.

### Selecting a network connection

The biggest decision you need to make when creating your network is what type of connection you will use. Gateway supports both wired and wireless Ethernet networks. Use the following criteria as a guide when selecting a network connection.

### Wired Ethernet network

Create a wired Ethernet network if:

- You are building a new home or your existing home already has Ethernet cable installed in each room that has a device you want to connect
- You are creating a network in an office or business where network speed is more important than moving about with your computer
- Your computer has an Ethernet jack for connecting to the network

# Wireless Ethernet (IEEE 802.11a or IEEE 802.11b) network

Create a wireless Ethernet network if:

- You are looking for an alternative to installing cable for connectivity
- The ability to move about with your computer is as important as network speed
- Your computer has wireless Ethernet (IEEE 802.11a or IEEE 802.11b) for networking

Help and Support



For more information about selecting network connections in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **networks** or **network types** in the HelpSpot **Search** box Search , then click the arrow.

## Using a wired Ethernet network

A wired Ethernet network consists of two or more computers connected together through an Ethernet cable. This connection type is commonly used in offices around the world and can be used to build computer networks in the home.

### **Ethernet, Fast Ethernet, or Gigabit Ethernet**

Ethernet is available at three different speeds. Standard Ethernet runs at 10 Mbps, Fast Ethernet runs at 100 Mbps, and Gigabit Ethernet runs at 1000 Mbps. Most home networks are built using Standard or Fast Ethernet components. Business networks are typically built using Fast or Gigabit Ethernet components.

To create a wired Ethernet network, you or your electrician must:

■ Install special Ethernet cables in your home or office

#### Important



Check local code requirements before installing Ethernet cable or other wiring in your home or office. Your municipality may require you to obtain a permit and hire a licensed installer.

- Install an Ethernet card in each of your desktop computers (if your computers do not already have built-in Ethernet jacks)
- Install an Ethernet PC Card in each of your notebooks (if your notebooks do not already have built-in Ethernet jacks)
- Install an Ethernet *router*, *switch*, or *hub*

Tips & Tricks



If you are connecting just two computers, you can eliminate the router, switch, or hub and use a special *crossover* cable.

### **Example wired Ethernet network**

The following is an example of a wired Ethernet network. The network is made up of a router, a cable or DSL modem, your computers, and cables connecting each of these components. The router is the central control point for the network. Attached to the router are all of your computers or Ethernet-ready devices. Also connected to the router is a cable or DSL modem that provides access to the Internet.



**Tips & Tricks** 



To add the ability to access a wireless Ethernet network to your wired Ethernet network, connect an access point to the router, switch, or hub. For more information about accessing a wireless Ethernet, see "Using a wireless Ethernet network" on page 196.

# Equipment you need for a wired Ethernet network

For a wired Ethernet network you need:

- An Ethernet jack on each desktop computer and notebook.
  - OR -

An Ethernet card installed in each desktop computer.

- OR -

An Ethernet PC Card installed in each notebook.

- An Ethernet router. Select a router that gives you the following features:
  - A jack for connecting to a cable or DSL modem.
  - The ability to assign IP addresses to your networked computers dynamically. This prevents intruders from seeing the computers over the Internet.
  - A built-in *firewall* to protect the computers on your network from intruders trying to access your data over the Internet.
  - Built-in switching (with enough ports for all computers and devices on the network) so that you will not have to purchase a hub or switch.
- If you did not purchase a router that includes built-in switching or if the router does not have enough ports to attach all your computers, an Ethernet hub or switch with enough ports for all computers and devices in the network.
- Ethernet cable going from each computer to the router, hub, or switch.

#### **Important**



For best results, all Ethernet components should be either standard Ethernet (10 Mbps), Fast Ethernet (100 Mbps or 10/100), or Gigabit Ethernet (1000 Mbps or 10/100/1000). A mixture of components rated at different speeds will result in your network running at the speed of the slowest rated component.

## Using a wireless Ethernet network

A wireless Ethernet network is ideal for creating a home or office network or adding mobility to an existing wired Ethernet.

#### Warning



Radio frequency wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. IEEE 802.11a and IEEE 802.11b communication devices are examples of devices that provide wireless communication. For instructions to turn wireless Ethernet on and off, see "Turning your wireless Ethernet on or off" on page 201.

#### **Important**



If your notebook came equipped with an internal radio frequency wireless device, see "Safety, Regulatory, and Legal Information" on page 295 for general wireless regulatory and safety guidelines. To find out if your notebook has an internal wireless device, check the label (see "Identifying your model" on page 12).

Wireless Ethernet is available at two different speeds. 802.11a wireless Ethernet runs at speeds up to 54 Mbps, or about half the speed of Fast Ethernet. 802.11b wireless Ethernet runs at speeds up to 11 Mbps, or approximately the same speed as standard wired Ethernet. This type of network allows you the freedom to move about your home or office with your notebook. For example, you can take your notebook from your home office to your patio without having an Ethernet jack available.

#### **Important**




The speed of a wireless network is related to signal strength. Signal strength is affected by the distance between your wireless network devices, by radio interference, and by interference from natural obstructions such as walls, floors, and doors.

The two most common types of wireless Ethernet networks are access point and peer-to-peer.

# Example access point wireless Ethernet network

By using an *access point*, you can join a wireless Ethernet network and access a wired Ethernet network. An access point also lets you access the Internet.

The following is an example of an access point wireless Ethernet network. The network is made up of an access point, a cable or DSL modem, and your computers. The access point is the central control point for the network. Attached to the access point is the cable or DSL modem that provides access to the Internet. Each of the computers or Ethernet-ready devices communicate with the access point using radio waves. If your computer does not have built-in wireless Ethernet capabilities, you need to add a wireless PCI card (desktop), PC card (notebook), or USB adapter.



**Tips & Tricks** 



If you want to access a wireless Ethernet network from your wired Ethernet network, connect an access point to the router, switch, or hub. For more information about accessing a wired Ethernet, see "Using a wired Ethernet network" on page 193.

# **Equipment you need for an access point wireless Ethernet network**

For an access point wireless Ethernet network you need:

- A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) PCI card installed in each desktop computer
  - OR -

A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) USB adapter attached to each desktop computer

- OR -

A notebook with wireless Ethernet (IEEE 802.11b) built-in

- OR -

A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) PC Card installed in each notebook that does not have wireless Ethernet built-in

■ A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) access point to connect your wireless Ethernet network to the Internet or a wired Ethernet network

#### **Important**



IEEE 802.11a and IEEE 802.11b use different radio frequencies. All wireless Ethernet components should use the same frequency. Some wireless devices can broadcast and receive signals on both frequencies. A combination of IEEE 802.11a and IEEE 802.11b components will not work.

# **Example peer-to-peer wireless Ethernet network**

Use a peer-to-peer (also known as ad hoc) wireless Ethernet network if you are setting up or joining a temporary computer-to-computer network. This type of network does not include access into a wired network or the Internet. You can create this type of network to quickly move files from one computer to another.



# Equipment you need for a peer-to-peer wireless Ethernet network

For a peer-to-peer wireless Ethernet network you need:

A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) PCI card installed in each desktop computer

- OR -

A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) USB adapter attached to each desktop computer

- OR -

A notebook with wireless Ethernet (IEEE 802.11b) built-in

- OR -

A wireless Ethernet (IEEE 802.11a or IEEE 802.11b) PC Card installed in each notebook that does not have wireless Ethernet built-in

### For more information

For more information about purchasing equipment for your home or office Ethernet network, discuss your particular needs with your Gateway store representative. In addition, several books and Internet sites are dedicated to networking. See these sources for more information about networking your home or office with wired or wireless Ethernet.

Help and Support



For more information about networking in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **networking** in the HelpSpot **Search** box Search , then click the arrow.

## Using your notebook on a network

### Installing and configuring your notebook for Ethernet networking

A guide in .PDF format has been included on your hard drive that provides instructions for installing and configuring both wired and wireless Ethernet networking on your notebook. To access this guide, click Start, All Programs, then click Gateway Utilities.

### **Turning your wireless Ethernet on or off**

#### Warning



Radio frequency wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. IEEE 802.11a and IEEE 802.11b communication devices are examples of devices that provide wireless communication.

- To turn wireless Ethernet on or off in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Network and Internet Connections. The *Network and Internet Connections* window opens.
  - 2 Click/Double-click Network Connections. The Network Connections window opens.
  - 3 Right-click Wireless Network Connection, then click Enable to turn on wireless Ethernet or click Disable to turn off wireless Ethernet.



- To turn wireless Ethernet on or off in Windows 2000:
  - 1 Right-click the ORiNOCO Client Manager icon on the taskbar. The ORiNOCO Wireless LAN menu opens.
  - 2 Click Enable Radio to turn on wireless Ethernet or click Disable Radio to turn off wireless Ethernet.



# Moving from Your 12

If your new computer is replacing an old computer, you may have personal data files, Internet settings, a printer or other peripheral devices, and other unique computer settings that you want to move from your old computer to your new one. Read this chapter to learn about:

- Using the Windows XP Files and Settings Transfer Wizard
- Transferring files
- Transferring Internet settings
- Installing your old printer or scanner
- Installing your old programs

## Using the Windows XP Files and Settings Transfer Wizard

If your new computer is running Windows XP, you can move your data files and personal settings, such as display, Internet, and e-mail settings, from your old computer to your new one by using the Files and Settings Transfer Wizard. The wizard also moves specific files or entire folders, such as My Documents, My Pictures, and Favorites.

- To open the Files and Settings Transfer Wizard:
  - Click Start, All Programs, Accessories, System Tools, then click Files and Settings Transfer Wizard.



Help and Support



For more information about using the Files and Settings Transfer Wizard in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **using transfer wizard** in the HelpSpot **Search** box <sub>Search</sub> , then click the arrow.

### **Transferring files**

You can manually transfer your personal data files by copying them to removable media, such as a diskette, writable CD, or Zip disk, or by using a home network. For more information, see "Using a recordable CD drive" on page 112, "Connecting to a wired Ethernet network" on page 37, and "Networking Your Computer" on page 189.

### Finding your files

Many programs automatically save your personal data files in the My Documents folder. Look in your old computer's My Documents folder for personal data files. Use Windows Find or Search to locate other personal data files. For more information, see "To find files using Find or Search:" on page 206, or see "Searching for files" on page 62.

- To find files in the My Documents folder:
  - 1 In Windows XP, click Start, then click My Documents. The *My Documents* window opens and displays many of your saved personal data files. Go to Step 4.
    - OR -

In Windows 98, Windows Me, or Windows 2000, double-click the **My Computer** icon on the desktop. Go to the next step.

- **2** Double-click the **C**:\ drive icon.
- **3** Double-click the **My Documents** folder. The *My Documents* window opens and displays many of your saved personal data files.
- **4** Copy your personal data files to removable media or to another computer on your network.



You can often identify different data file types by looking at the file's *extension* (the part of the file name following the last period). For example, a document file might have a .DOC extension and a spreadsheet file might have an .XLS extension.

File type	File usually ends in			
Documents	.DOC, .TXT, .RTF, .HTM, .HTML, .DOT			
Spreadsheets	.XLS, .XLT, .TXT			
Pictures	.JPG, .BMP, .GIF, .PDF, .PCT, .TIF, .PNG, .EPS			
Movies	.MPEG, .MPG, .AVI, .GIF, .MOV			
Sound and Music	.WAV, .CDA, .MP3, .MID, .MIDI, .WMA			

#### To find files using Find or Search:

- 1 In Windows XP, click Start, then click Search. The Search Results window opens.
  - OR -

In Windows 98, Windows Me, or Windows 2000, click Start, Find or Search, then click For Files or Folders. The *Search Results* window opens.

**2** Use Windows Find or Search to locate data files by file name or file type. For help on finding files, click **Help**, then click **Help and Support Center** or **Help Topics**. For more information, see "Searching for files" on page 62.



### Help and Support



For more information about finding files in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **searching for files** in the HelpSpot **Search** box <sub>Search</sub> , click the arrow, then click the **Full-text Search Matches** button.

## **Transferring Internet settings**

You can use different methods to transfer your Internet account from your old computer to your new one.

#### Setting up your ISP

- If your current Internet service provider (ISP) software came preinstalled on your new computer, run that setup program. If it asks to set up a new account or an existing one, choose to set up an existing account.
- If your current ISP software is not preinstalled on your new computer, locate the original Internet setup program provided by your local ISP, or contact your ISP to see if they have an updated version of their software, and install it on your new computer.
- If you use MSN as your ISP, or if you know your ISP settings, use the Windows Internet Connection Wizard.
- To use the Internet Connection Wizard:
  - 1 Click Start, All Programs, Accessories, Communications, then click New Connection Wizard. The New Connection wizard opens.
  - **2** Configure your Internet settings by following the on-screen instructions.



Help and Support



For more information about setting up an Internet connection in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **Internet connection** in the HelpSpot **Search** box <sub>Search</sub> , then click the arrow.

#### Transferring your e-mail and address book

See your old e-mail program's online help for information on *exporting* and *importing* e-mail messages and the address book. You can often export all of your old e-mail messages or address book to a diskette, then import them from the diskette into your new computer's e-mail program. Alternatively, you may want to consider printing the old information or using your old computer to send the e-mail messages to yourself, then using your new computer to retrieve the e-mail messages.

#### **Transferring your Internet shortcuts**

You can export and import your old Netscape Navigator bookmarks or Microsoft Internet Explorer favorites. For more information, see your Internet browser program's online help.

## Installing your old printer or scanner

Windows may have built-in support for older printers, scanners, or other peripheral devices. This means you do not need any additional software. Newer devices, however, usually require your original software installation CDs or diskettes.

If you have trouble after you install the software for your old devices, you can use System Restore to restore your computer's previous settings.

Help and Support



For information about restoring your computer's previous settings in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **System Restore** in the HelpSpot **Search** box Search , then click the arrow.

#### Installing a USB printer or scanner

USB devices may have special installation instructions. See your USB device's installation guide.

#### Installing a parallel port printer

You can usually install parallel port printers by following these steps.

- To install your old printer:
  - 1 Shut down and turn off your computer.
  - **2** Connect your parallel port printer.
  - **3** Turn on your printer, then turn on your computer.
  - **4** If Windows detects your printer, install your printer by following the on-screen instructions. You are finished.
    - OR -

If Windows does not detect the printer, go to the next step.

- 5 In Windows XP, click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
  - OR -

In Windows 2000, click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.

- 6 Click/Double-click the Printers and Faxes or Printers icon, then click Add a printer or Add Printer. The Add Printer wizard opens.
- 7 Install your printer by following the on-screen instructions.



## Help and Support



For more information about installing a printer in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **installing a printer** in the HelpSpot **Search** box <sub>Search</sub> . then click the arrow.

See your peripheral device's user guide for installation information and tips. Because most installation software is periodically updated, you should also check the manufacturer's Web site for software updates.

## Installing your old programs

You probably use some programs that did not come installed on your new computer, such as personal finance software, graphics programs, or games.

Spend some time going through your old computer's **Start** and **Programs** menus, making note of any programs you want to install on your new computer. Locate your original program installation CDs and installation guides. Your original CDs and guides should contain any serial numbers or product ID keys that may be required for program installation and registration. Remember to check the publisher's Web site for important program updates.

Tips & Tricks



If your new computer comes with a newer version of a program, it is usually better to use the newer version than to reinstall the old one.

If you have trouble after installing your old programs, you can restore your computer's previous settings using System Restore.

Help and Support



For more information about restoring your computer's previous settings in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **System Restore** in the HelpSpot **Search** box Search [ ], then click the arrow.

# Maintaining 13 Your Computer

This chapter provides basic information about maintaining your computer hardware and software. Read this chapter to learn how to:

- Care for your computer
- Create an emergency startup diskette
- Protect your computer from viruses
- Manage hard drive space
- Back up files
- Clean your computer

## Caring for your computer

To extend the life of your system:

- Be careful not to bump or drop your computer, and do not put any objects on top of it. The case, although strong, is not made to support extra weight.
- When transporting your computer, we recommend that you put it in a carrying case.
- Keep diskettes, modular drives, and your computer away from magnetic fields. Magnetic fields can erase data on both diskettes and hard drives.
- Never turn off your computer when the hard drive light is on because data on the hard drive could be lost or corrupted.
- Avoid subjecting your computer to extreme temperature changes. The case and LCD panel can become brittle and easy to break in cold temperatures and can melt or warp in high temperatures. Damage due to either extreme is not covered by your warranty. As a general rule, your computer is safest at temperatures that are comfortable for you.
- Keep all liquids away from your computer. When spilled onto computer components, almost any liquid can result in extremely expensive repairs that are not covered under your warranty.
- Avoid dusty or dirty work environments. Dust and dirt can clog the internal mechanisms.

Use the following table to set up a regular maintenance schedule.

Maintenance task	Immediately after purchase	Monthly	When needed	See
Create an emergency diskette	Х			page 214
Check for viruses		X	Χ	page 216
Manage hard drive space			Χ	page 219
Clean up hard drives		X	Χ	page 220
Scan hard drive for errors		X	Χ	page 221
Defragment hard drive		X	Χ	page 223
Back up files		X	Χ	page 225

Maintenance task	Immediately after purchase	Monthly	When needed	See
Recalibrate the battery			Х	page 150
Clean computer case			Χ	page 228
Clean keyboard			Χ	page 229
Clean computer screen			Χ	page 229
Clean mouse			Χ	page 229

## **Creating an emergency startup diskette**

An *emergency startup diskette* is a diskette that contains critical information that you need to start your computer if Windows fails to start. You should create a startup diskette as soon as you get your computer.



#### To create an emergency startup diskette in Windows XP:

1 Insert a blank diskette labeled **Startup** into the diskette drive.

#### Important




If the diskette drive is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

- 2 Click Start, then click My Computer. The My Computer window opens.
- **3** Right-click **3**½ **Floppy (A:)**, then click **Format**. The *Format 3*½ *Floppy (A:)* dialog box opens.



- 4 Click to select the Create an MS-DOS startup disk check box, then click Start. A message warns you that any information on the diskette will be erased.
- **5** When you see the warning message, click **OK**. Windows copies files to the emergency startup diskette.
- **6** When Windows finishes copying files, remove the diskette from the diskette drive.
- **7** Slide the write-protect tab up to prevent the diskette from being erased or infected by viruses.



**8** Store your emergency startup diskette in a safe place with your other backup software media.



## Protecting your computer from viruses

A *virus* is a program that attaches itself to a file on a computer, then spreads from one computer to another. Viruses can damage data or cause your computer to malfunction. Some viruses go undetected for a period of time because they are activated on a certain date.

Protect your computer from a virus by:

- Using the Norton<sup>®</sup> AntiVirus program to check files and programs that are on diskettes, attached to e-mail messages, or downloaded from the Internet.
- Checking all programs for viruses before installing them.
- Disabling macros on suspicious Microsoft Word and Excel files. These programs will warn you if a document that you are opening contains a macro that might have a virus.
- Periodically updating the Norton AntiVirus program to protect against the latest viruses.

Help and Support




For more information about protecting your computer against viruses in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **viruses** in the HelpSpot **Search** box Search , then click the arrow.

- To scan for viruses:
  - 1 Click Start, All Programs, Norton AntiVirus, then click Norton AntiVirus 2002. Norton AntiVirus opens.



2 Click Scan for Viruses.



**3** Click the type of scan you want to make in the Scan area, then under Actions, click **Scan**.



#### To remove a virus:

- 1 If Norton AntiVirus finds a virus, follow all on-screen instructions to remove the virus.
- **2** Turn off your computer and leave it off for at least 30 seconds.
- **3** Turn on your computer and rescan for the virus.



#### To update Norton AntiVirus:

- 1 Make sure that you are connected to the Internet.
- **2** Click Start, All Programs, Norton AntiVirus, then click LiveUpdate Norton AntiVirus. The LiveUpdate wizard opens.
- **3** Follow the on-screen instructions to update your Norton AntiVirus program with the latest virus protection files.
- 4 When the program has finished, click Finish.



## Managing hard drive space


Windows provides several utilities you can use to manage your hard drive.

#### Checking hard drive space

- To check hard drive space:
  - 1 In Windows XP, click **Start**, then click **My Computer**. The *My Computer* window opens.
    - OR -

In Windows 2000, double-click the **My Computer** icon. The *My Computer* window opens.

**2** Right-click the drive that you want to check for available file space, then click **Properties**. Drive space information appears.






#### **Using Disk Cleanup**

Delete unnecessary files, such as temporary Windows files, to free hard drive space.

- To use the Windows Disk Cleanup program:
  - 1 In Windows XP, click **Start**, then click **My Computer**. The *My Computer* window opens.
    - OR -

In Windows 2000, double-click the **My Computer** icon. The *My Computer* window opens.

**2** Right-click the hard drive that you want to delete files from, for example Local Disk (C:), then click **Properties**. The *Properties* dialog box opens at the General tab.



- 3 Click Disk Cleanup. The Disk Cleanup dialog box opens.
- **4** Make sure that the check box beside each file type you want to delete is selected. For more information about file types you can delete, read the descriptions in the *Disk Cleanup* dialog box.

5 Click OK, then click Yes.



## Help and Support



For more information about keeping the hard drive space free of unnecessary files in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **disk cleanup** in the HelpSpot **Search** box Search , then click the arrow.

#### Checking the hard drive for errors

The Error-checking program examines the hard drive for physical flaws and file and folder problems. This program corrects file and folder problems and marks flawed areas on the hard drive so that Windows does not use them.

If you use your computer several hours every day, you probably want to run Error-checking once a week. If you use your computer less frequently, once a month may be adequate. Also use Error-checking if you encounter hard drive problems.

- To check the hard drive for errors:
  - 1 In Windows XP, click Start, then click My Computer. The *My Computer* window opens.
    - OR -

In Windows 2000, double-click the My Computer icon. The My Computer window opens.

**2** Right-click the hard drive that you want to check for errors, for example Local Disk (C:), then click **Properties**. The *Properties* dialog box opens.



#### **3** Click the **Tools** tab.



- 4 Click Check Now.
- 5 Click the options you want to use, then click Start. For help, press F1. Windows checks the drive for errors. This process may take several minutes. After Windows has finished checking the drive for errors, it provides a summary of the problems that it found.
- **6** Correct any problems that are found by following the on-screen instructions.
- 7 Click OK.



Help and Support



For more information about checking the hard drive for errors in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **checking for disk errors** in the HelpSpot **Search** box Search , then click the arrow.

#### Defragmenting the hard drive

When working with files, sometimes Windows divides the file information into pieces and stores them in different places on the hard drive. This is called *fragmentation*, and it is normal. In order for your computer to use a file, Windows must search for the pieces of the file and put them back together. This process slows the hard drive performance.

The Disk Defragmenter program organizes the data on the drive so that each file is stored as one unit rather than as multiple pieces scattered across different areas of the drive. Defragmenting the information stored on the drive can improve hard drive performance.

While the Disk Defragmenter program is running, do not use your keyboard or touchpad because using them may continuously stop and restart the defragmenting process. Also, if you are connected to a network, log off before starting Disk Defragmenter. Network communication may stop the defragmentation process and cause it to start over.

#### To run Disk Defragmenter:

- 1 In Windows XP, click **Start**, then click **My Computer**. The *My Computer* window opens.
  - OR -
  - In Windows 2000, double-click the **My Computer** icon. The *My Computer* window opens.
- **2** Right-click the hard drive that you want to defragment, for example Local Disk (C:), then click **Properties**. The *Properties* dialog box opens.



#### **3** Click the **Tools** tab.



- 4 Click Defragment Now.
- 5 If Disk Defragmenter does not start automatically, click Defragment or Start.
  Disk Defragmenter shows its progress on the computer display. When finished, Disk Defragmenter asks if you want to quit the program.
- **6** Click **Close** or **Yes**, then click the **X** in the top-right corner to close the *Disk Defragmenter* window.



Help and Support



For more information about defragmenting the hard drive in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **defragmenting** in the HelpSpot **Search** box Search , then click the arrow.

#### **Backing up files**

Backing up files and removing them from the hard drive frees space for new files on the hard drive. It also protects you from losing important information if the hard drive fails or you accidentally delete files.

You should back up your files regularly to a writable CD (if you have a recordable CD drive) or to diskettes. Use a backup device, such as a recordable CD drive or Zip drive, to do a complete hard drive backup. For more information, see "Using a recordable CD drive" on page 112. If you do not have a high-capacity backup device and you want to purchase one, you can contact Gateway's Add-on Sales department or visit our Web site at <a href="https://www.gateway.com">www.gateway.com</a>.

Help and Support



For more information about backing up files in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **saving files** in the HelpSpot **Search** box **Search**, then click the arrow.

#### **Using the Scheduled Task Wizard**

The Scheduled Task Wizard lets you schedule maintenance tasks such as running Disk Defragmenter and Error-checking.

- To start the Scheduled Task Wizard:
  - 1 Click Start, All Programs, Accessories, System Tools, then click Scheduled Tasks. The *Scheduled Tasks* window opens.
  - **2** Double-click the **Add Scheduled Task** icon. The Scheduled Task Wizard opens.



**3** Click **Next**, then click the task or program you want to schedule and follow the on-screen instructions to customize the task.

# Important

Your computer must be on during scheduled tasks. If your computer is off, scheduled tasks will not run.

## Help and Support



For more information about using the Scheduled Tasks Wizard in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **Scheduled Task Wizard** in the HelpSpot **Search** box Search , then click the arrow.

## Cleaning your computer

Keeping your computer clean and the vents free from dust helps keep your system performing at its best. You may want to gather these items and put together a computer cleaning kit:

- A soft. lint-free cloth
- An aerosol can of air that has a narrow, straw-like extension
- Isopropyl alcohol
- Cotton swabs
- A CD or DVD drive cleaning kit

#### Cleaning the exterior

#### Warning



When you shut down your computer, the power turns off, but some electrical current still flows through your computer. To avoid possible injury from electrical shock, unplug the power cord and modem cable from the wall outlets.

Always turn off your computer and other peripherals, then remove the main and optional secondary batteries before cleaning any components.

Use a damp, lint-free cloth to clean your computer and other parts of your system. Do not use abrasive or solvent cleaners because they can damage the finish on components.

Your computer is cooled by air circulated through the vents on the case, so keep the vents free of dust. With your computer turned off and unplugged, brush the dust away from the vents with a damp cloth. Be careful not to drip any water into the vents. Do not attempt to clean dust from the inside your computer.

#### Cleaning the keyboard

You should clean the keyboard occasionally by using an aerosol can of air with a narrow, straw-like extension to remove dust and lint trapped under the keys.

If you spill liquid on the keyboard, turn off your computer and turn the unit upside down. Let the liquid drain, then let the keyboard dry before trying to use it again. If the keyboard does not work after it dries, you may need to replace it.

#### Cleaning the computer screen

Use a soft cloth and water to clean the computer screen. Squirt a little water on the cloth (never directly on the screen), and wipe the screen with the cloth.

#### Caution



The computer screen is made of specially coated glass and can be scratched or damaged by abrasive or ammonia-based glass cleaners.

#### Cleaning the mouse

If you have a mouse and the mouse pointer begins moving erratically across the computer screen or becomes difficult to control precisely, cleaning the mouse will likely improve its accuracy.

### Help and Support



For a video tutorial about cleaning the mouse in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **Video tutorials** in the HelpSpot **Search** box Search , then click the arrow.


Click Cleaning the mouse.

Clean your optical mouse by wiping the bottom of the mouse with a damp lint-free cloth.

- To clean your trackball mouse:
  - 1 Turn the mouse upside down.
  - **2** Rotate the retaining ring on the bottom of the mouse counter-clockwise, then remove the retaining ring and mouse ball.



- **3** Remove any dust, lint, or dirt from the mouse ball with a soft cloth.
- **4** Clean the mouse rollers with a cotton swab dipped in isopropyl alcohol.



**5** Replace the mouse ball and lock the retaining ring into place.



# Restoring 14 Software

Read this chapter to learn how to:

- Reinstall device drivers
- Update device drivers
- Reinstall programs
- Reinstall Windows

## **Using the Restoration CDs**

Use the Gateway *Restoration CDs* to reinstall device drivers, your operating system, and other programs that were preinstalled at the factory.

#### **Important**



Before you try to fix a problem by reinstalling software from your Gateway *Restoration CDs*, make sure that you have tried these steps first:

- Use the diagnostics and troubleshooting tools found in HelpSpot. For more information about diagnostics and troubleshooting tools in Windows XP, click Start, then click Help and Support.
  - Type the keyword **troubleshooting** in the HelpSpot **Search** box search , then click the arrow.
- See the Troubleshooting section of this guide.
  If these steps do not resolve the problem, use the Gateway
  Restoration CDs to reinstall device drivers or programs.

If reinstalling device drivers or programs does not resolve the problem, reinstall Windows.

## Reinstalling device drivers

Device drivers are programs that control devices such as the computer display, DVD or recordable CD drives, and modems. Drivers translate information between computer devices and programs.

Drivers for your original computer hardware are installed at Gateway. If you install a new device, you need to install the drivers provided by the device manufacturer.

You should reinstall device drivers:

- If directed to do so while troubleshooting
- If you see a message indicating that there is a problem with a device driver

If you need to reinstall device drivers because you are directed to do so while troubleshooting or if a message tells you that there is a problem with a device driver, reinstall the device drivers by completing the following task.

If you just reinstalled Windows XP or Windows 2000, the device drivers were automatically reinstalled.

If you are not comfortable with the procedures covered in this section, seek help from a more experienced computer user or a computer service technician.

#### To reinstall device drivers:

- 1 Insert the red Gateway CD into the DVD or recordable CD drive. If the program starts automatically, go to Step 5.
  - OR -

If the program does not start automatically, go to Step 2.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

2 Click Start, then click Run. The Run dialog box opens.



- **3** In the **Open** text box, type **d:\runmenu.exe** (where **d** is the drive letter of your DVD or recordable CD drive).
- 4 Click OK.
- 5 If this is the first time you have inserted the red Gateway CD, accept the End User License Agreement (EULA) by clicking Yes, I accept it, then clicking Continue. The Gateway Driver and Application Recovery program starts and the Drivers and Application Recovery tab appears.
- **6** Select a single device driver to reinstall.
  - OR -

Click **Automatic Installation**, then select multiple device drivers to reinstall. (Grayed out drivers are not available for Automatic Installation. To select these drivers, click **Manual Installation**.)

- 7 Click Install.
- **8** Follow any additional on-screen instructions. Depending on the device driver you are reinstalling, you may only need to restart your computer to complete the installation. However, if a setup wizard opens when you restart your computer, follow the on-screen instructions.



## Help and Support



For more information about reinstalling device drivers in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **drivers** in the HelpSpot **Search** box Search , then click the arrow.

## **Updating device drivers**

The *Restoration CDs* contain a device driver update utility that works over the Internet. If you do not have an Internet service provider, the update utility works by direct-dialing the device driver update service.

#### **Important**



If your system came equipped with a wireless device, only use the drivers approved for the country the device will be used in. See the red Gateway CD or the Gateway Technical Support Web site (<a href="www.gateway.com/support">www.gateway.com/support</a>).

If your system came equipped with an internal embedded wireless device, see "Safety, Regulatory, and Legal Information" on page 295 for general wireless regulatory and safety guidelines. To find out if your system has an internal wireless device, check the label (see "Identifying your model" on page 12).

#### To update device drivers:

- 1 Insert the red Gateway CD into the DVD or recordable CD drive. If the program starts automatically, go to Step 5.
  - OR -

If the program does not start automatically, go to Step 2.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

- 2 Click Start, then click Run. The Run dialog box opens.
- **3** In the **Open** text box, type **d:\runmenu.exe** (where **d** is the drive letter of the DVD or recordable CD drive).
- 4 Click OK.



- 5 If this is the first time you have inserted the red Gateway CD, accept the End User License Agreement (EULA) by clicking Yes, I accept it, then clicking Continue. The Gateway Driver and Application Recovery program starts and the Drivers and Application Recovery tab appears.
- 6 Click the Web Updates tab.
- 7 Click Check Now. The *Connect* window opens.
- 8 Install available updated device drivers by following the on-screen instructions. Depending on the device driver you are updating, you may only need to restart your computer to complete the installation. However, if a setup wizard opens when you restart your computer, follow the on-screen instructions.



## Help and Support



For more information about updating device drivers in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **updating drivers** in the HelpSpot **Search** box <sub>Search</sub> , then click the arrow.

## Reinstalling programs

If you have problems running a program or if you have reinstalled your operating system, you can reinstall programs from the red Gateway CD and other program CDs. If you are reinstalling programs from other program CDs, follow the installation instructions on each CD. If you want to **reinstall** a program, uninstall the old version first.

- To reinstall programs from the red Gateway CD:
  - **1** If you just reinstalled Windows, go to Step 4. Otherwise, go to the next step.
  - 2 In Windows XP, click Start, Control Panel, then click Add or Remove Programs.
    - OR -

In Windows 2000, click Start, Settings, Control Panel, then double-click the Add or Remove Programs icon.

- 3 In the *Currently Installed Programs* list, click the program you want to uninstall, then click **Change/Remove** and follow the on-screen instructions.
- **4** Insert the red Gateway CD into the DVD or recordable CD drive. If the program starts automatically, go to Step 8.
  - OR -

If the program does not start automatically, go to Step 5.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

- 5 Click Start, then click Run. The Run dialog box opens.
- **6** In the **Open** text box, type **d:\runmenu.exe** (where **d** is the drive letter of your DVD or recordable CD drive).
- 7 Click OK.



- 8 If this is the first time you have inserted the red Gateway CD, accept the End User License Agreement (EULA) by clicking Yes, I accept it, then clicking Continue. The Gateway Driver and Application Recovery program starts and the Drivers and Application Recovery tab appears.
- **9** Select a single program to reinstall.
  - OR -

Click **Automatic Installation**, then select multiple programs to reinstall. (Grayed out programs are not available for Automatic Installation. To select these programs, click **Manual Installation**.)

- 10 Click Install.
- 11 Follow any additional on-screen instructions. Depending on the programs you are reinstalling, you may only need to restart your computer to complete the installation. However, if a setup wizard opens when you restart your computer, follow the on-screen instructions.



#### Help and Support



For more information about reinstalling programs in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **installing programs** in the HelpSpot **Search** box **search**, then click the arrow.

- To reinstall Works Suite (including Word), games, or other programs from a CD:
  - **1** If you just reinstalled Windows, go to Step 4. Otherwise, go to the next step.
  - 2 In Windows XP, click Start, Control Panel, then click Add or Remove Programs.
    - OR -

In Windows 2000, click Start, Settings, Control Panel, then double-click the Add or Remove Programs icon.

**3** In the *Currently Installed Programs* list, click the program you want to uninstall, then click **Change/Remove** and follow the on-screen instructions.

**4** Insert the program CD into the DVD or recordable CD drive.

#### **Important**



If the drive you want to use is not in the modular bay, you need to swap modules. For more information about swapping modules, see "Changing drives" on page 246.

**5** Complete the program reinstallation by following the instructions included with the program CD.



## **Reinstalling Windows**

If your computer is not working correctly, try the following options to correct the problem:

- Troubleshooting. For more information, see "Troubleshooting" on page 267.
- Reinstalling device drivers. For more information, see "Reinstalling device drivers" on page 233.

If the options above do not correct the problem, you can use the *Restoration CDs* to reinstall Windows and other software.

The *Restoration CDs* step you through reinstalling Windows XP or Windows 2000. If you are reinstalling Windows XP or Windows 2000, the *Restoration CDs* automatically reinstall the hardware device drivers and some programs as well. You can install any remaining programs by using the program CDs that came with your computer. To reinstall your programs, follow the instructions in "Reinstalling programs" on page 237.

#### **Important**



If you are prompted for your Windows product key when you reinstall Windows, you can find the key on the *Microsoft Certificate of Authenticity* label located on the bottom of your computer case. For more information, see "Microsoft Certificate of Authenticity" on page 13.



#### Warning



Back up your personal files before you use this option.

All files on your computer will be deleted!

- 1 Insert the red Gateway CD into the DVD or recordable CD drive.
- **2** Restart your computer.
- 3 Select 2. Boot from CD-ROM.
- **4** Select a language option.
- 5 Select 1. Delete all files (Automated Fdisk/Format).
- 6 Select 1. Continue deleting all files and restart.

- **7** When prompted, press any key to continue.
- 8 Select 2. Boot from CD-ROM.
- **9** Select a language option.
- 10 Select 2. Automated installation of Windows (XP or 2000).
- 11 When prompted, remove the red Gateway CD and insert the blue *Operating System* CD into the DVD or recordable CD drive, then press any key to continue.
- 12 When prompted, accept the License Agreement by pressing Y.
- 13 Wait while the setup program copies files to your hard drive. When your computer restarts, do NOT press any key to boot from CD.
- 14 When prompted, insert the red Gateway CD, then click Continue. The Gateway Application Loader automatically installs your drivers and programs. Your computer restarts several times during this process. Do not press any keys or buttons during this process unless prompted to do so.
- **15** When the Gateway Application Loader has finished, go to the Windows desktop by clicking **OK**.
- **16** Install additional programs by following the instructions in "Reinstalling programs" on page 237.
- 17 Install other software, such as Microsoft Works Suite and gaming software, by following the instructions in "To reinstall Works Suite (including Word), games, or other programs from a CD:" on page 238.



Chapter 14: Restoring Software

# Upgrading Your 15 Notebook

This chapter provides information about adding hardware devices to your notebook. Read this chapter to learn how to:

- Add and remove PC Cards
- Swap a bay module (for example, a drive or a secondary battery)
- Add and replace memory
- Replace the hard drive kit


# Adding and removing a PC Card

Your notebook has a two PC Card slots (also known as a PCMCIA card slots). These slots accept two Type II cards or one Type III card.

You do not need to restart your notebook when changing most cards because your notebook supports *hot-swapping*. Hot-swapping means that you can insert a PC Card while your notebook is running. If your PC Card does not work after hot-swapping, see the PC Card manufacturer's documentation for further information.

#### To insert a PC Card:

■ Push the card firmly into the PC Card slot label-side up until the outer edge of the card is flush with the side of your notebook.





#### To remove a PC Card:

1 Click the remove hardware so icon in the taskbar, the PC Card name, then click **Stop**.

-OR-

Turn off your notebook.

**Important** 



If the remove hardware icon does not appear on the taskbar, click the show hidden icons 
 button.

- **2** Release the eject button by pressing the PC Card eject button once.
- **3** Eject the PC Card by pressing the eject button again.






# **Changing drives**

Your notebook's modular bays support different *bay modules*, such as a DVD drive, a recordable CD drive, a second hard drive, a diskette drive, or a secondary battery.

#### **Important**



The diskette drive and secondary battery can only be used in the right-side modular bay. All other drives can be used in either the left or right-side modular bay.



#### To change bay modules:

- 1 If you are removing a DVD, recordable CD, or diskette drive, make sure that the drive is empty.
- **2** Click the remove hardware sicon in the taskbar, the drive you are removing, then click **Stop**.

-OR-

Turn off your notebook (do not place it in Standby or Hibernate mode).

**Important** 



If the remove hardware icon does not appear on the taskbar, click the show hidden icons () button.


- **3** Close the LCD panel.
- **4** Disconnect your notebook from the optional port replicator (see "Disconnecting from the port replicator" on page 264).
- **5** Turn your notebook over so that the bottom is facing up.
- **6** Slide and hold the bay module latch and press the bay module release button. The module moves out slightly.



**7** Slide the bay module out.



**8** Firmly push the new bay module straight into the bay until the latch clicks into place.



- **9** Turn your notebook over, then open the LCD panel.
- **10** If your notebook is on, click **OK** to continue working on your notebook.
  - OR -

If your notebook is off, turn it on.



# Preventing static electricity discharge

The components inside your computer are extremely sensitive to static electricity, also known as *electrostatic discharge* (ESD).

#### Caution



ESD can permanently damage electrostatic discharge-sensitive components in your notebook. Prevent ESD damage by following ESD guidelines every time you install memory or replace the hard drive kit.

#### Warning



To avoid exposure to dangerous electrical voltages and moving parts, turn off your notebook and unplug the power cord and modem and network cable before opening the case.

Before installing memory or replacing the hard drive kit, follow these guidelines:

- Turn off your notebook.
- Wear a grounding wrist strap (available at most electronics stores) and attach it to a bare metal part of your workbench or other grounded connection.

#### Warning



To prevent risk of electric shock, do not insert any object into the vent holes of the notebook.


- Touch a bare metal surface on your workbench or other grounded object.
- Unplug the power cord and the modem and network cables.
- Remove the main battery (and secondary battery, if installed). For more information, see "Changing batteries" on page 151.
- Disconnect all peripheral devices and remove any PC Cards.

Before working with computer components, follow these guidelines:

- Avoid static-causing surfaces such as carpeted floors, plastic, and packing foam.
- Remove components from their antistatic bags only when you are ready to use them. Do not lay components on the outside of antistatic bags because only the inside of the bags provide electrostatic protection.
- Always hold components by their edges. Avoid touching the edge connectors. Never slide components over any surface.

# Adding or replacing memory

Your notebook uses memory modules called SO-DIMMs (Small Outline Dual Inline Memory Modules). The modules are available in various capacities and any module can be placed in any available slot. Use only memory modules designed for the Gateway 600YG2 for upgrading your memory.



- To add or replace memory modules:
  - 1 Follow the instructions under "Preventing static electricity discharge" on page 249.
  - **2** Turn off your notebook, disconnect the AC adapter and modem and network cables.
  - **3** Disconnect your notebook from the optional port replicator (see "Disconnecting from the port replicator" on page 264).
  - 4 Turn your notebook over so that the bottom is facing up.
  - **5** Remove the main and optional secondary batteries.



- **6** Loosen the memory bay cover screw, then remove the memory bay cover.
- **7** If you are removing a module, gently press outward on the clip at each end of the memory module until the module tilts upward.



**8** Pull the memory module out of the slot.




**9** Hold the new or replacement module at a 30-degree angle and press it into the empty memory slot. This module is keyed so that it can only be inserted in one direction. If the module does not fit, make sure that the notch in the module lines up with the tab in the memory bay.

#### Important



Use only memory modules designed for the Gateway 600YG2.






- **10** Gently push the module down until it clicks in place.
- 11 Replace the memory bay cover and tighten the cover screw.
- **12** Insert the batteries, then turn your notebook over.
- **13** Reconnect the optional port replicator.
- **14** Connect the power adapter and modem and network cables, then turn on your notebook.



# Replacing the main hard drive kit


If you would like more hard drive capacity, you can replace your original drive with a higher-capacity drive.




- To replace the main hard drive kit:
  - 1 Follow the instructions under "Preventing static electricity discharge" on page 249.
  - **2** Turn off your notebook, disconnect the AC adapter and modem and network cables.
  - **3** Disconnect from the optional port replicator (see "Disconnecting from the port replicator" on page 264).
  - **4** Turn your notebook over so that the bottom is facing up.
  - **5** Remove the main and optional secondary batteries (see "Changing batteries" on page 151).




**6** Loosen the hard drive bay cover screw, then remove the hard drive bay cover.



**7** Slide the hard drive kit away from the connector.



**8** Lift the end of the hard drive kit furthest from the connector, then remove the drive from the bay



- **9** Place the new hard drive kit in the bay and slide it into the connector.
- **10** Replace the hard drive bay cover and tighten the screw.
- 11 Insert the batteries and turn your notebook over.
- **12** Reconnect the optional port replicator.
- **13** Connect the power adapter and modem and network cables, then turn on your notebook.



# Using the Gateway 600 Port Replicator

The optional port replicator gives you a convenient way to attach external devices such as a monitor, a full-size keyboard, or an AC adapter.

Although devices can be attached directly to the ports on the notebook, the port replicator lets you make all of those connections in one step. The port replicator also gives you access to additional ports not found on the notebook.

#### Read this chapter to learn:


- Where ports and jacks are located
- How to connect and disconnect the port replicator
- How to secure the port replicator with a locking cable

# **Front**



Component	Icon	Description
Docking release latch		Press both release latches to release the notebook.
Docking port		Connect the notebook to this port.  Warning! Power is passed through this port. This docking connection is certified to UL 1950 for use only with notebooks designed for your Gateway port replicator.

# **Back**



Component	Icon	Description
USB ports	●<	Plug USB (Universal Serial Bus) devices (such as a USB lomega™ Zip™ drive, printer, scanner, camera, keyboard, or mouse) into these ports.
Headphone jack		Plug amplified speakers or headphones into this jack. The built-in speakers on the notebook are turned off when speakers or headphones are plugged into this jack. This jack is turned off when headphones are plugged into the notebook's headphone jack.
Line in jack	(( <del>&lt;))</del>	Connect an external audio input source (such as a stereo) to this jack so that you can record sound on your computer or play sound through the notebook speakers.
PS/2 mouse port	Ò	Plug a Personal System/2 (PS/2) mouse into this port. Attaching a PS/2 mouse to your port replicator may deactivate the touchpad.
PS/2 keyboard port	<u>::::::</u>	Plug a Personal System/2 (PS/2) keyboard into this port. Attaching a PS/2 keyboard to your port replicator may deactivate the built-in keyboard.

Component	Icon	Description
S-Video out jack	S- <b>▶</b>	Plug a standard S-Video cable into this jack and the jack on an S-Video device.
Monitor port		Plug an analog VGA monitor into this port.
Parallel port		Plug a parallel device (such as a printer) into this port.
Serial port	[0 0]	Plug a serial device (such as a digital camera) into this port.
Modem jack	ß	Plug a modem cable into this jack.
Ethernet jack	盎	Plug a 10/100 Ethernet network cable into this jack. For more information, see "Connecting to a wired Ethernet network" on page 37 and "Networking Your Computer" on page 189.
S/PDIF digital audio jack	<b>(</b>	Plug an optical (Toslink) AC-3 digital audio cable into this jack.
Power connector	===	Plug the AC adapter cable into this connector.

# Connecting to the port replicator

You can attach your notebook to the port replicator while your notebook is off, on, or in Standby mode.

#### Attaching to the port replicator

- To attach your notebook to the port replicator:
  - 1 Connect external devices to the ports on the port replicator.
  - **2** Align the connector holes on the bottom of your notebook with the docking posts on the port replicator.
  - 3 Press down on the notebook until it snaps into place.



Caution



Press down on the outside edges of the notebook. Do not press in the middle or you may damage the LCD screen.



#### **Important**



The notebook may detect additional devices and add drivers after being attached to the port replicator. This process must be completed for components to work correctly. Follow any on-screen instructions, if necessary.



## Disconnecting from the port replicator

You can separate your notebook from the port replicator while your notebook is off or on (not in Standby or Hibernate mode).

- To separate your notebook from the port replicator:
  - 1 If your notebook is off, go to Step 2.

-OR-

If your notebook is on and using Windows XP, click **Start**, then click **Undock Computer**. The Undock Computer menu item appears in the Start menu only while the notebook is docked.

-OR-

If your notebook is on and using Windows 2000, click **Start**, then click **Eject PC**. The Eject PC menu item appears in the Start menu only while the notebook is docked.

**2** Press down on both docking release latches. The notebook will spring up slightly.



**3** Lift the notebook off of the port replicator.



# Securing your port replicator

You can secure your notebook and port replicator to an object by using the security ring located on the right side of the port replicator and the Kensington lock slot located on the right side of your notebook.

- To secure your notebook and port replicator:
  - 1 Open the security ring on the port replicator.
  - **2** Attach your notebook to the port replicator.
  - 3 Secure one end of the Kensington cable to a solid object, then run the other end of the cable through the security ring and lock it into the slot provided on the right side of your notebook.



# Troubleshooting 17

This chapter provides some solutions to common notebook problems. Read this chapter to learn how to:

- Troubleshoot typical hardware and software problems
- Get telephone support
- Use automated troubleshooting systems
- Get tutoring and training

If the suggestions in this chapter do not correct the problem, see "Getting Help" on page 39 for more information about how to get help.

# Safety guidelines

While troubleshooting your notebook, follow these safety guidelines:

- Never remove the memory bay cover or hard drive kit while your notebook is turned on, while the batteries are installed, and while the modem cable, network cable, and AC power adapter are connected.
- Make sure that you are correctly grounded before accessing internal components. For more information about preventing damage from static electricity, see "Preventing static electricity discharge" on page 249.
- After you complete any maintenance tasks where you remove the memory bay or hard drive cover, make sure that you replace the cover, reinstall any screws, then replace the battery before you start your notebook.

#### Warning




Do not try to troubleshoot your problem if power cords or plugs are damaged, if your notebook was dropped, or if the case was damaged. Instead, unplug your notebook and contact a qualified computer technician.

# First steps

If you have problems with your notebook, try these things first:

- Make sure that the AC power adapter is connected to your notebook and an AC outlet and that the AC outlet is supplying power.
- If you use a power strip or surge protector, make sure that it is turned on.
- If a peripheral device (such as a keyboard or mouse) does not work, make sure that all connections are secure.
- Make sure that your hard drive is not full.
- If an error message appears on the screen, write down the exact message. The message may help Gateway Technical Support in diagnosing and fixing the problem.
- If you added or removed modules or peripheral devices, review the installation procedures you performed and make sure that you followed each instruction.
- If an error occurs in a program, see the program's printed documentation or the online help.



# Software support tools

Your notebook *may* include the following support tool to help you diagnose and fix problems:

 PC Doctor is a comprehensive hardware diagnostic and system information tool that can test your notebook and determine its configuration.
 PC Doctor provides 85 professional diagnostic tests directly from your notebook.

This support tool is available from HelpSpot or by clicking Start, All Programs, then clicking Gateway Utilities.

# **Troubleshooting**

#### **CD or DVD drives**

#### Your notebook does not recognize a disc or the drive

- The disc may not be seated correctly in the tray. When you place a disc on the tray, make sure that you press the disc firmly onto the spindle so that the retainers hold the disc in place.
- The modular drive may not be inserted completely into the modular bay. Press the module into the bay, then try to access the disc again.
- Make sure that the disc label is facing up, then try again.
- If you are trying to play a DVD, make sure that you have a DVD drive. See "Identifying drive types" on page 84 for more information.
- Try a different disc. Occasionally discs are flawed and cannot be read by the drive.
- Some music CDs have copy protection software. You may not be able to play these CDs on your notebook.
- Your notebook may be experiencing some temporary memory problems. Shut down and restart your notebook.
- Clean the disc. For more information, see "Cleaning CDs or DVDs" on page 272.

#### An audio CD does not produce sound

- Make sure that the CD label is facing up, then try again.
- Make sure that the volume control on your notebook is turned up. For more information, see "Audio DJ controls" on page 92.
- Make sure that the Windows volume control is turned up. For more information, see "Adjusting the volume in Windows XP" on page 86 and "Adjusting the volume in Windows 2000" on page 89.
- Make sure that Mute controls are turned off. For more information about the mute setting, see "Audio DJ controls" on page 92 or "Adjusting the volume in Windows XP" on page 86 and "Adjusting the volume in Windows 2000" on page 89.

- Make sure that headphones are not plugged into the headphone jack. For the location of the headphone jack, see "Left side" on page 3 and "Back" on page 261.
- If you are using powered speakers, make sure that they are plugged in and turned on.
- Clean the CD. For more information, see "Cleaning CDs or DVDs" on page 272.
- Your notebook may be experiencing some temporary memory problems. Shut down and restart your notebook.
- Reinstall the audio device drivers. For more information, see "Reinstalling device drivers" on page 233.

#### A DVD movie will not play

- Make sure that the label or side you want to play is facing up, then try again.
- Make sure that a DVD or DVD/CD-RW combination drive is inserted into the modular bay. See "Identifying drive types" on page 84 for more information.
- Shut down and restart your notebook.
- Clean the DVD. For more information, see "Cleaning CDs or DVDs" on page 272.
- DVD discs and drives contain *regional codes* that help control DVD title exports and help reduce illegal disc distribution. To be able to play a DVD, the disc's regional code and your DVD drive's regional code must match.
  - The regional code on your DVD drive is determined by your notebook's delivery address. The regional code for the United States and Canada is 1. The regional code for Mexico is 2. Your DVD drive's regional code must match the regional code of the disc. The regional code for the disc is on the disc, disc documentation, or packaging.
  - If the DVD movie does not play, the disc's regional code and your DVD drive's regional code may not match.
- Make sure that the InterVideo program has been installed on your notebook. See "Playing a DVD" on page 126 for more information.


#### A DVD does not produce sound on a TV

■ Audio is not transmitted through the TV out jack. Use the built-in speakers, a set of headphones or external powered speakers, or connect your notebook to a stereo system to hear sound while playing a DVD.

### Cleaning CDs or DVDs

Wipe from the center to the edge, not around in a circle, using a product made especially for the purpose.





#### **Device installation**

#### You have computer problems after adding a new device

Sometimes a new device, such as a PC Card, can cause a system resource (IRQ) conflict. Check IRQ usage to determine if there is an IRQ conflict.



#### To check IRQ usage in Windows XP:

- 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Performance and Maintenance.
- 2 Click/Double-click System, click the Hardware tab, then click Device Manager. The *Device Manager* window opens.
- 3 Click View, then click Resources by type. Double-click Interrupt request (IRQ). All IRQs and their hardware assignments are displayed.



#### Help and Support



For more information about IRQs in Windows XP, click Start, then click Help and Support.

Type the keyword **IRQs** in the HelpSpot **Search** box Search , then click the arrow.

- To check IRQ usage in Windows 2000:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Double-click the **System** icon, click the **Hardware** tab, then click **Device Manager**. The *Device Manager* window opens.
  - 3 Click View, then click Resources by type. Double-click Interrupt request (IRQ). All IRQs and their hardware assignments are displayed.



- To free IRQ resources for the new device:
  - 1 In the *Device Manager* window, check the device list for a resource conflict. A resource conflict appears as a black exclamation point in a yellow circle.
  - **2** Remove the device you are trying to install, then determine which one of the existing devices or ports you can disable.
  - 3 Right-click the device or port you want to disable, then click Disable. The device or port is disabled.



#### Diskette drive

#### The diskette drive is not recognized

- Shut down and restart your notebook.
- The modular drive may not be inserted completely into the modular bay. Press the module into the bay, then try to access the diskette again.

#### You see an "Access Denied" or "Write protect" error message

■ Move the write-protection tab in the upper-right corner of the diskette down (unprotected).

- The diskette may be full. Delete unnecessary files on the diskette and try again.
- Not all diskettes are IBM-compatible. Make sure that the diskette you are using is IBM-compatible.
- Try a different diskette. Occasionally diskettes are flawed and cannot be read by the diskette drive.

#### You see a "Disk is full" error message

- Delete unnecessary files on the diskette.
- Try a different diskette. Occasionally diskettes are flawed and cannot be read by the diskette drive.
- Run Error checking on the diskette. For more information, see "Checking the hard drive for errors" on page 221. If errors are detected and corrected, try using the diskette again.

# You see a "Non-system disk", "NTLDR is missing", or "Disk error" error message

- Eject the diskette from the diskette drive, then press ENTER.
- Make sure that the diskette you are using is IBM-compatible.

#### The modular drive status indicator is lit continuously

■ Remove the diskette from the drive. If the indicator stays on, try restarting your notebook.

#### **Display**

#### The screen is too dark

■ Adjust the brightness using the system keys. For more information, see "System key combinations" on page 30.

#### The screen resolution is not correct

■ Change the screen resolution from the *Display Properties* dialog box. For more information, see "Adjusting the screen resolution" on page 176.

#### Help and Support



For more information about changing the screen resolution in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **screen resolution** in the HelpSpot **Search** box <sub>Search</sub> , then click the arrow.

#### The text on the display is dim or difficult to read

- Adjust the brightness and contrast using the system keys. For more information, see "System key combinations" on page 30.
- Change the display settings. For more information, see "Adjusting the screen and desktop settings" on page 174.
- Move your notebook away from sources of electrical interference, such as televisions, unshielded speakers, microwaves, fluorescent lights, and metal beams or shelves.

#### The display has pixels that are always dark or too bright

■ This condition is normal and inherent in the TFT technology used in active-matrix LCD screens. Gateway's inspection standards keep these to a minimum. If you feel these pixels are unacceptably numerous or dense on your display, contact Gateway Technical Support to identify whether a repair or replacement is justified based on the number of pixels affected.

#### File management

#### A file was accidentally deleted

If a file was deleted at a DOS prompt or in Windows while holding down the **SHIFT** key, the file cannot be restored.



#### To restore deleted files:

- 1 Double-click the Recycle Bin icon.
- **2** Right-click the file you want to restore, then click **Restore**. The file is restored to the place where it was originally deleted from.

If the Recycle Bin was emptied before you tried to restore a file, the file cannot be restored.



# Help and Support



For more information about restoring deleted files in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **System Restore** in the HelpSpot **Search** box Search , then click the arrow.

#### Hard drive

#### You see an "Insufficient disk space" error message

- Delete unnecessary files from the hard drive using Disk Cleanup. For more information, see "Using Disk Cleanup" on page 220.
- Empty the Recycle Bin by right-clicking the Recycle Bin icon, then clicking Empty Recycle Bin.

#### Caution



All deleted files will be lost when you empty the Recycle Bin.

■ Save your files to a diskette or another drive. If the hard drive is full, copy any files not regularly used to diskettes or other backup media, then delete them from the hard drive.

## Help and Support



For more information about file management in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **file management** in the HelpSpot **Search** box **Search**, then click the arrow.

#### You see a "Data error" message

■ This may be the result of a defective area on the hard drive. To fix hard drive problems, run the Error checking program. For more information, see "Checking the hard drive for errors" on page 221.

# The hard drive cannot be accessed, or you see a "General failure reading drive C" error message

- If a diskette is in the diskette drive, eject it and restart your notebook.
- Make sure that the hard drive kit is installed correctly. Remove it, firmly reinsert it, then restart your notebook. For more information, see "Replacing the main hard drive kit" on page 255.

■ If your notebook has been subjected to static electricity or physical shock, you may need to reinstall the operating system.

# You see a "Non-system disk", "NTLDR is missing", or "disk" error message

■ Eject the diskette from the diskette drive, then press Enter.

#### The secondary hard drive is not recognized

■ The modular drive may not be inserted completely into the drive bay. Press the drive into the bay, then try to access the drive again.

#### Internet

#### You cannot connect to the Internet

- Make sure that the modem cable is plugged into the modem jack and not the Ethernet network jack. See "Back" on page 6 and "Back" on page 261 to make sure that the connections have been made correctly.
- Make sure that your notebook is connected to the telephone line and the telephone line has a dial tone.
- If you have the call waiting feature on your telephone line, make sure that it is disabled.
- Make sure that you are not using a digital, rollover, or PBX line. These lines do not work with your modem.
- Make sure that your account with your Internet service provider (ISP) is set up correctly. Contact your ISP technical support for help.
- Make sure that you do not have a problem with your modem. For more information, see "Modem" on page 279.

Help	and
Sup	oort



For more information about troubleshooting Internet connections in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **troubleshooting connections** in the HelpSpot **Search** box  $\underline{\mathbb{S}}$ , then click the arrow.

### You see an "Unable to locate host" message and are unable to browse the Internet

This problem can occur when you have typed a URL (Web address) incorrectly, you have lost your Internet connection, or your ISP is having technical difficulties.

Double-check the URL or try a different URL. If the error message still appears, disconnect from the ISP connection and close your browser, then reconnect and open the browser. If you still get the error, your ISP may be having technical difficulties.

### Connecting to a Web site takes too long

Many factors can affect Internet performance:

- The condition of the telephone lines in your residence or at your local telephone service
- The condition of the Internet computers to which you connect and the number of users accessing those computers
- The complexity of graphics and multimedia on Web pages
- Having multiple Web browsers open, performing multiple downloads, and having multiple programs open on your notebook

### People are sending you e-mail messages, but you have not received any mail

- Click the receive button in your e-mail program.
- Make sure that your account with your Internet service provider (ISP) is set up correctly. Contact your ISP for technical support.

### Keyboard

### The built-in keyboard does not work

■ Attaching a PS/2 keyboard to your notebook or port replicator while your notebook is running may deactivate the built-in keyboard.

### The external keyboard does not work

- Make sure that the keyboard cable is plugged in correctly.
- Remove all extension cables and switchboxes.
- Clean the keyboard by using an aerosol can of air with a narrow, straw-like extension to remove dust and lint trapped under the keys.

- Try a keyboard that you know works to make sure that the keyboard port works.
- If you spilled liquid in the keyboard, turn off your notebook and unplug the keyboard. Clean the keyboard and turn it upside down to drain it. Let the keyboard dry before using it again. If the keyboard does not work after it dries, you may need to replace it.

### A keyboard character keeps repeating or you see a "Keyboard stuck" or "Key failure" error message

- Make sure that nothing is resting on the keyboard.
- Make sure that a key is not stuck. Press each key to loosen a key that might be stuck, then restart your notebook.

### Memory

### You see a "Memory error" message

- Make sure that the memory modules are inserted correctly in the memory bay slot. For more information, see "Adding or replacing memory" on page 251.
- Use PC Doctor or a third-party diagnostic program to help determine if a memory module is failing. For more information, see "Adding or replacing memory" on page 251.

### You see a "Not enough memory" error message

■ Close all programs, then restart your notebook.

Help	and
Sup	port
_	_



lelp and	For more information about troubleshooting memory errors
Support	in Windows XP, click Start, then click Help and Support.
	Type the keyword <b>memory error</b> in the HelpSpot <b>Search</b> box Search, then click the arrow.

### Modem

#### Your modem does not dial or does not connect

■ Make sure that the modem cable is plugged into the modem jack and not the Ethernet network jack. See "Back" on page 6 and "Back" on page 261 to make sure that the connections have been made correctly.

- Make sure that your notebook is connected to the telephone line and the telephone line has a dial tone.
- Make sure that the modem cable is less than 6 feet (1.8 meters) long.
- Remove any line splitters or surge protectors from your telephone line, then check for a dial tone by plugging a working telephone into the telephone wall jack.
- If you have additional telephone services such as call waiting, call messaging, or voice mail, make sure that all messages are cleared and call waiting is disabled before using the modem. Contact your telephone service to get the correct code to temporarily disable the service. Also make sure that the modem dialing properties are set appropriately.
- To check the dialing properties in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
  - 2 Click/Double-click the Phone and Modem Options icon, then click the Dialing Rules tab.
  - 3 Click the location from which you are dialing, then click Edit.
  - **4** Make sure that all settings are correct.



### Help and Support



For more information about dialing properties in Windows XP, click **Start**, then click **Help and Support**. Type the keyword **dialing** in the HelpSpot **Search** box

lype the keyword **dialing** in the HelpSpot **Search** to the search to the

- To check the dialing properties in Windows 2000:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Click/Double-click the **Modems** icon, then click **Dialing Properties** tab. The *Dialing Properties* dialog box opens.

**3** Make sure that all settings are correct.



- Disconnect any answering machine, fax machine, or printer that is on the same line as the modem. Do not connect these devices to the same telephone line as the modem.
- Make sure that you are not using a digital, rollover, or PBX line. These lines do not work with your modem.
- Check for line noise (scratchy, crackling, or popping sounds). Line noise is a common problem that can cause the modem to connect at a slower rate, abort downloads, or even disconnect. The faster the modem, the less line noise it can tolerate and still work correctly.

Listen to the line using your telephone. Dial a single number (such as 1). When the dial tone stops, listen for line noise. Wiggle the modem cable to see if that makes a difference. Make sure that the connectors are free from corrosion and all screws in the wall or telephone wall jack are secure.

You can also call your telephone service and have the telephone line checked for noise or low line levels.

- Try another telephone line (either a different telephone number in your house or a telephone line at a different location). If you can connect on this line, call your telephone service.
- Try connecting with the modem at a lower connection speed. If reducing the connect speed lets you connect, call your telephone service. The telephone line may be too noisy.

#### You cannot connect to the Internet

- The ISP may be having technical difficulties. Contact your ISP for technical support.
- See if the modem works with a different communications program. The problem may be with just one program.

#### Your 56K modem does not connect at 56K

Current FCC regulations restrict actual data transfer rates over public telephone lines to 53K. Other factors, such as line noise, telephone service provider equipment, or ISP limitations, may lower the speed even further.

If your notebook has a v.90 modem, the speed at which you can upload (send) data is limited to 33.6K. If your notebook has a v.92 modem, the speed at which you can upload data is limited to 48K. Your ISP may not support 48K uploads.

You can check modem connection speeds and dial-up network (DUN) connections by accessing the *gateway.your.way dial-up server*. The server also contains drivers, patches, and updates for current Gateway hardware and software.

The server provides a secure connection and is a stand-alone server. You cannot use it to access the Internet. The server cannot be accessed Mondays from 8:00 a.m. to 12:00 p.m. CT.

- To access the gateway.your.way dial-up server:
  - 1 Insert the red Gateway CD into the DVD or recordable CD drive.
  - 2 Click Help, then click Support Web Site.
  - **3** To check your modem connection speed, click the **Direct Dial** option. After your modem connects, move the mouse pointer over the **Dial-Up Networking** icon (located next to the clock on your taskbar). Your modem connection speed appears.



### Your fax communications program only sends and receives faxes at 14,400 bps when you have a 56K modem

Current fax technology only supports a maximum send and receive rate of 14,400 bps.

### The modem is not recognized by your notebook

- Make sure that the line connected to the modem is working and plugged into the appropriate port on your notebook. See "Back" on page 6 and "Back" on page 261 to make sure that the connections have been made correctly.
- If the modem shares the telephone line with another device, make sure that the telephone line is not in use (for example, someone is on the telephone, or another modem is in use).
- Use the modem cable that came with your notebook. Some telephone cables do not meet required cable standards and may cause problems with the modem connection.
- Shut down and restart your notebook.
- Run Windows modem diagnostics.

### To run modem diagnostics in Windows XP:

- 1 Close all open programs.
- 2 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
- 3 Click/Double-click the Phone and Modem Options icon, then click the Modems tab.
- **4** Click your modem, then click **Properties**. The *Modem Properties* dialog box opens.
- 5 Click the Diagnostic tab, then click Query Modem. If information about the modem appears, the modem passed diagnostics. If no modem information is available, a white screen appears with no data, or if you get an error such as *port already open* or *the modem has failed to respond*, the modem did not pass diagnostics.



### Help and Support

For more information about modem troubleshooting in Windows XP, click **Start**, then click **Help and Support**.



Type the keyword **modem troubleshooting** in the HelpSpot **Search** box Search , then click the arrow.

### To run modem diagnostics in Windows 2000:

- 1 Close all open programs.
- **2** Click **Start**, **Settings**, then click **Control Panel**. The *Control Panel* window opens.
- **3** Double-click the **Modems** icon. The *Modems Properties* window opens.
- 4 Click the Diagnostic tab, click the COM port next to the name of the modem, then click More Info. The Modem Info dialog box opens. If information about the modem appears, the modem passed diagnostics. If no modem information is available, a white screen appears with no data, or if you get an error such as port already open or the modem has failed to respond, the modem did not pass diagnostics.



### The modem is noisy when it dials and connects

When your modem tries to connect to another modem, it begins *handshaking*. Handshaking is a digital "getting acquainted" conversation between the two modems that establishes connection speeds and communication protocols. You may hear unusual handshaking sounds when the modems first connect. If the handshaking sounds are too loud, you can turn down the modem volume.

- To turn down the modem volume in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
  - **2** Click/Double-click the **Phone and Modem Options** icon, then click the **Modems** tab.
  - 3 Click the modem you want to adjust, then click Properties.
  - 4 Click the Modem tab, then adjust the Speaker volume control.
  - **5** Click **OK** twice to close the *Phone and Modem Options* dialog box.



- To turn down the modem volume in Windows 2000:
  - 1 Click Start, Settings, then click Control Panel. The *Control Panel* window opens.
  - **2** Double-click the **Modems** icon. The *Modems Properties* dialog box opens.
  - 3 Click the General tab, click the modem you want to adjust, then click Properties.
  - 4 Adjust the Speaker volume control.
  - 5 Click OK.



### Mouse

### The external mouse does not work

■ Make sure that the mouse cable is plugged in correctly.

- Shut down and restart your notebook.
- Remove all extension cables and switch boxes.
- Try a mouse you know is working to make sure that the mouse port works.

### The external mouse works erratically

- Clean the mouse. For more information, see "Cleaning the mouse" on page 229.
- Use a mouse pad with an optical mouse. Optical mice do not work well on shiny surfaces.

# For a video tutorial about cleaning the mouse, click Start, then click Help and Support. Type the keyword mouse troubleshooting in the HelpSpot Search box Search 1, then click the arrow.

### **Networks**

### You cannot connect to your company network

■ Every network is unique. Contact your company computer department or network administrator for help.



### **Passwords**

### Your notebook does not accept your password

■ Make sure that CAPS LOCK and PAD LOCK are turned off, then retype the password.

### You forgot your startup password

■ The password feature (which is set in the BIOS Setup utility) is very secure, with no easy way to recover a forgotten password. You must return your notebook for repair. Call Gateway Technical Support for instructions.

### **PC Cards**

### You installed a PC Card and now your notebook is having problems

- Make sure that you have correctly installed required software for the PC Card. For more information, see your PC Card's documentation.
- Make sure that the PC Card you installed is not causing a system resource conflict. For more information on resource conflicts, see "Device installation" on page 272.

### **Power**

### Your notebook is not working on AC power

- Make sure that your AC power adapter is connected correctly to your notebook. For more information, see "Connecting the AC adapter" on page 20.
- If your notebook is plugged into a surge protector, make sure that the surge protector is connected securely to an electrical outlet, turned on, and working correctly. To test the outlet, plug a working device, such as a lamp, into the outlet and turn it on.
- Make sure that the AC power adapter cables are free from cuts or damage. Replace any damaged cables.

### Your notebook is not working on battery power

- Make sure that the main battery is installed correctly. For more information, see "Changing batteries" on page 151.
- Make sure that the optional secondary battery is installed correctly. For more information, see "Installing a secondary battery" on page 153.
- Make sure that the batteries are fully recharged. For more information, see "Recharging the battery" on page 149.
- Make sure that the battery is calibrated correctly. For more information, see "Recalibrating the battery" on page 150.

### Your notebook will not turn off, even after pressing the power button for five seconds

■ If your notebook has "frozen," and pressing the power button for five seconds does not turn it off, insert a straightened paper clip into the reset hole on the bottom of your notebook. For the location of the reset hole, see "Bottom" on page 8.

### **Printer**

### The printer will not turn on

- Make sure that the printer is online. Many printers have an online/offline button that you may need to press.
- Make sure that the power cable is plugged into an AC power source.

### The printer is on but will not print

- Check the cable between the printer and your notebook. Make sure that it is connected to the correct port.
- Make sure that the printer is online. Many printers have an online/offline button that you may need to press so that the printer can start printing. Press the button to put the printer online.
- Check the port and cable for bent or broken pins.
- If the printer you want to print to is not the default printer, make sure that you have selected it in the printer setup.
- To set a default printer in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
  - **2** Click/Double-click the **Printers and Faxes** icon. The *Printers and Faxes* window opens.
  - **3** Right-click the name of the printer you want to be the default printer, then click **Set as Default Printer**.



- To set a default printer in Windows 2000:
  - 1 Click Start, Settings, then click Printers.
  - **2** Right-click on the name of the printer you want to be the default printer, then click **Set as Default**.



■ Reinstall the printer driver. See the guide that came with your printer for instructions on installing the printer driver.

### You see a "Printer queue is full" error message

- Make sure that the printer is not set to work offline.
- To make sure that the printer is not set to work offline in Windows XP:
  - 1 Click Start, then click Control Panel. The *Control Panel* window opens. If your Control Panel is in Category View, click Printers and Other Hardware.
  - **2** Click/Double-click the **Printers and Faxes** icon. The *Printers and Faxes* window opens.
  - 3 Right-click the name of the printer you want to use. If the menu shows a check mark next to Use Printer Offline, click Use Printer Offline to clear the check mark.



### Help and Support



For more information about printer troubleshooting in Windows XP, click **Start**, then click **Help and Support**.

Type the keyword **printer troubleshooter** in the HelpSpot **Search** box **Search**, then click the arrow.

- To make sure that the printer is not set to work offline in Windows 2000:
  - 1 Click Start, Settings, then click Printers.
  - 2 Right-click the name of the printer you want to use. If the menu shows a check mark next to Use Printer Offline, click Use Printer Offline to clear the check mark.



- Wait until files have been printed before sending additional files to the printer.
- If you print large files or many files at one time, you may want to add additional memory to the printer. See the printer documentation for instructions for adding additional memory.


### You see a "Printer is out of paper" error message

■ After adding paper, make sure that the printer is online. Most printers have an online/offline button that you need to press after adding paper.

### Sound

### You are not getting sound from the built-in speakers

- Make sure that headphones are not plugged into the headphone jack. For the location of the headphone jack, see "Left side" on page 3 and "Back" on page 261.
- Make sure that the volume control on your notebook is turned up. For more information, see "Audio DJ controls" on page 92.
- Make sure that the Windows volume control is turned up. For more information, see "Adjusting the volume in Windows XP" on page 86 or "Adjusting the volume in Windows 2000" on page 89.
- Make sure that Mute controls are turned off. For more information, see "Audio DJ controls" on page 92 or "Adjusting the volume in Windows XP" on page 86 or "Adjusting the volume in Windows 2000" on page 89.



### You are not getting sound from headphones plugged into the port replicator

■ Make sure that headphones are not plugged into your notebook's headphone jack. For the location of the headphone jack, see "Left side" on page 3.

### **Touchpad**

### The touchpad does not work

Attaching a PS/2 mouse to your notebook or port replicator may deactivate the touchpad.

### Video

### The external monitor is not working

- Make sure that you have pressed FN+LCD/CRT to activate the external monitor option.
- Make sure that the monitor power is turned on and that the video cable is correctly connected.

### TV out is not working

- Make sure that you have activated TV out. For more information, see "Viewing the display on a television" on page 128.
- Make sure that the television is turned on and that the RCA video cable or S-Video cable is connected correctly.
- Televisions in different countries use different standards. If you are traveling, you may need to change the TV Out mode. For more information, see "Viewing the display on a television" on page 128.

### **Telephone support**

### **Before calling Gateway Technical Support**

If you have a technical problem with your notebook, follow these recommendations before contacting Gateway Technical Support:

- Make sure that your notebook is connected correctly to a grounded AC outlet that is supplying power. If you use a surge protector, make sure that it is turned on.
- If a peripheral device, such as a keyboard or mouse, does not appear to work, make sure that all cables are plugged in securely.
- If you have recently installed hardware or software, make sure that you have installed it according to the instructions provided with it. If you did not purchase the hardware or software from Gateway, see the manufacturer's documentation and technical support resources.
- If you have "how to" questions about using a program, see:
  - Online Help
  - Printed documentation
  - The Microsoft Windows documentation
  - The software publisher's Web site
- See the troubleshooting section of this chapter.

### Warning



To avoid bodily injury, do not attempt to troubleshoot your notebook problem if:

- Power cords or plugs are damaged
- Liquid has been spilled into your notebook
- Your notebook was dropped
- The case was damaged

Instead, unplug your notebook and contact a qualified computer technician.

- Have your customer ID, serial number, and order number available, along with a detailed description of your problem, including the exact text of any error messages, and the steps you have taken.
- Make sure that your notebook is nearby at the time of your call. The technician may have you follow troubleshooting steps.

### **Telephone numbers**

Gateway offers a wide range of customer service, technical support, and information services.

### **Automated troubleshooting system**

Service description	How to reach
Use an automated menu system and your telephone keypad to find answers to common problems.	800-846-2118 (US) 877-709-2945 (Canada)

### **Telephone numbers**

You can access the following services through your telephone to get answers to your questions:

Resource	Service description	How to reach
Fax on demand support	Order a catalog of documents on common problems, then order documents by document numbers. The documents will be faxed to you.	800-846-4526 (US) 877-709-2951 (Canada)
Gateway's fee-based software tutorial service	Get tutorial assistance for software issues billed by the minute.	800-229-1103 (charged to your credit card) 900-555-4695 (charged to your telephone bill)
Gateway Technical Support	Talk to a Gateway Technical Support representative about a non-tutorial technical support question. (See "Before calling Gateway Technical Support" on page 291 before calling.)  TDD Technical Support (for hearing impaired) is available:  Weekdays 6:00 a.m 8:00 p.m. Central Time Weekends 6:00 a.m 5:00 p.m. Central Time	800-846-2301 (US) 800-846-3609 (Canada and Puerto Rico) 605-232-2191 (all other countries) 800-846-1778 (TDD)
America Online	Get support for your America Online ISP account	800-827-6364 (US) 888-265-4357 (Canada)
CompuServe	Get support for your CompuServe ISP account	800-848-8990 (US)
Sales, accounting, and warranty	Get information about available systems, pricing, orders, billing statements, warranty service, or other non-technical issues.	800-846-2000 (US) 888-888-2037 (Canada)


### **Tutoring and training**

Gateway's Technical Support professionals cannot provide hardware and software training or tutorial services. Instead, Gateway recommends the following tutoring and training resources.

### Self-help

If you have *how-to* questions about using your Gateway-supplied hardware or software, see the following resources:

- The printed or online documentation that came with your hardware or software. In many cases, additional product information and online documentation for Gateway-supplied hardware can be found in our Web site's Documentation Library
- This user's guide
- The software publisher's Web site



### **Tutoring**

For help on using hardware or software that came with your Gateway notebook, contact Gateway's fee-based tutorial hotline:

- 800-229-1103 (rate charged per minute; charged to a major credit card)
- 900-555-4695 (rate charged per minute; charged to your telephone bill)

### **Training**

### Gateway provides the following in-person and computerized training:

Resource	Service description	For more information
In-Store Training at Gateway stores	Our friendly and knowledgeable software trainers can teach you how to use the Internet and the most popular software programs, including Microsoft Word, Excel, and PowerPoint.	www.gateway.com/country
Gateway Learning Libraries	A variety of courses and tutorials are available on CD. Select from several easy-to-use learning libraries.	www.gateway.com/training
Online Training from Learn@Gateway	More than 450 online courses are available from Learn@Gateway. All you have to do is go online and log in. You select the subject matter, and the learning format (self-paced tutorials or virtual classrooms), all from the comfort of your notebook.	www.learnatgateway.com/

# Safety, Regulatory, and Legal Information

# Important safety information

Your Gateway system is designed and tested to meet the latest standards for safety of information technology equipment. However, to ensure safe use of this product, it is important that the safety instructions marked on the product and in the documentation are followed.

#### Warning



Always follow these instructions to help guard against personal injury and damage to your Gateway system.

### Setting up your system

- Read and follow all instructions marked on the product and in the documentation before you operate your system. Retain all safety and operating instructions for future use.
- Do not use this product near water or a heat source such as a radiator.
- Set up the system on a stable work surface.
- The product should be operated only from the type of power source indicated on the rating label.
- If your computer has a voltage selector switch, make sure that the switch is in the proper position for your area. The voltage selector switch is set at the factory to the correct voltage.

- Openings in the computer case are provided for ventilation. Do not block or cover these openings. Make sure you provide adequate space, at least 6 inches (15 cm), around the system for ventilation when you set up your work area. Never insert objects of any kind into the computer ventilation openings.
- Some products are equipped with a three-wire power cord to make sure that the product is properly grounded when in use. The plug on this cord will fit only into a grounding-type outlet. This is a safety feature. If you are unable to insert the plug into an outlet, contact an electrician to install the appropriate outlet.
- If you use an extension cord with this system, make sure that the total ampere rating on the products plugged into the extension cord does not exceed the extension cord ampere rating.
- If your system is fitted with a TV Tuner, cable, or satellite receiver card, make sure that the
  antenna or cable system is electrically grounded to provide some protection against voltage
  surges and buildup of static charges.

### Care during use

- Do not walk on the power cord or allow anything to rest on it.
- Do not spill anything on the system. The best way to avoid spills is to avoid eating and drinking near your system.
- Some products have a replaceable CMOS battery on the system board. There is a danger of explosion if the CMOS battery is replaced incorrectly. Replace the battery with the same or equivalent type recommended by the manufacturer. Dispose of batteries according to the manufacturer's instructions.
- When the computer is turned off, a small amount of electrical current still flows through the computer. To avoid electrical shock, always unplug all power cables and modem cables from the wall outlets before cleaning the system.
- Unplug the system from the wall outlet and refer servicing to qualified personnel if:
  - The power cord or plug is damaged.
  - Liquid has been spilled into the system.
  - The system does not operate properly when the operating instructions are followed.
  - The system was dropped or the cabinet is damaged.
  - The system performance changes.

### Replacement parts and accessories

Use only replacement parts and accessories recommended by Gateway.

#### **Important**



Do not use Gateway products in areas classified as hazardous locations. Such areas include patient care areas of medical and dental facilities, oxygen-laden environments, or industrial facilities.

#### Caution



To reduce the risk of fire, use only No. 26 AWG or larger telecommunications line cord.

### Regulatory compliance statements

### Wireless Guidance

Low power, Radio LAN type devices (radio frequency (RF) wireless communication devices), operating in the 2.4 GHz Band, may be present (embedded) in your notebook system. The following section is a general overview of considerations while operating a wireless device.

Additional limitations, cautions, and concerns for specific countries are listed in the specific country sections (or country group sections). The wireless devices in your system are only qualified for use in the countries identified by the Radio Approval Marks on the system rating label. If the country you will be using the wireless device in, is not listed, please contact your local Radio Approval agency for requirements. Wireless devices are closely regulated and use may not be allowed.

The power output of the wireless device or devices that may be embedded in your notebook is well below the RF exposure limits as known at this time. Because the wireless devices (which may be embedded into your notebook) emit less energy than is allowed in radio frequency safety standards and recommendations, Gateway believes these devices are safe for use. Regardless of the power levels, care should be taken to minimize human contact during normal operation.

As a general guideline, a separation of 20 cm (8 inches) between the wireless device and the body, for use of a wireless device near the body (this does not include extremities) is typical. This device should be used more than 20 cm (8 inches) from the body when wireless devices are on and transmitting.

Some circumstances require restrictions on wireless devices. Examples of common restrictions are listed below:

#### Warning



Radio frequency wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. 802.11B (also known as wireless Ethernet or Wifi) and Bluetooth communication devices are examples of devices that provide wireless communication.

#### Warning



In environments where the risk of interference to other devices or services is harmful or perceived as harmful, the option to use a wireless device may be restricted or eliminated. Airports, Hospitals, and Oxygen or flammable gas laden atmospheres are limited examples where use of wireless devices may be restricted or eliminated. When in environments where you are uncertain of the sanction to use wireless devices, ask the applicable authority for authorization prior to use or turning on the wireless device.

#### Warning



Every country has different restrictions on the use of wireless devices. Since your system is equipped with a wireless device, when traveling between countries with your system, check with the local Radio Approval authorities prior to any move or trip for any restrictions on the use of a wireless device in the destination country.

#### Warning



If your system came equipped with an internal embedded wireless device, do not operate the wireless device unless all covers and shields are in place and the system is fully assembled.

#### Warning



Wireless devices are not user serviceable. Do not modify them in any way. Modification to a wireless device will void the authorization to use it. Please contact Gateway for service.

#### Warning



Only use drivers approved for the country in which the device will be used. See the Gateway System Restoration Kit, or contact Gateway Technical Support for additional information.

#### Warning



In order to comply with FCC requirements this transmitter must not be operated (or co-located) in conjunction with any other transmitter or antenna installed in the notebook.

### **United States of America**

### Federal Communications Commission (FCC) Intentional emitter per FCC Part 15

Low power, Radio LAN type devices (radio frequency (RF) wireless communication devices), operating in the 2.4 GHz Band, may be present (embedded) in your notebook system. This section is only applicable if these devices are present. Refer to the system label to verify the presence of wireless devices.

Wireless devices that may be in your system are only qualified for use in the United States of America if an FCC ID number is on the system label.

The FCC has set a general guideline of 20 cm (8 inches) separation between the device and the body, for use of a wireless device near the body (this does not include extremities). This device should be used more than 20 cm (8 inches) from the body when wireless devices are on. The power output of the wireless device (or devices), which may be embedded in your notebook, is well below the RF exposure limits as set by the FCC.

Operation of this device is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

#### Warning



Wireless devices are not user serviceable. Do not modify them in any way. Modification to a wireless device will void the authorization to use it. Contact Gateway for service.

#### **Unintentional emitter per FCC Part 15**

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio or television reception. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause interference to radio and television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the separation between the equipment and receiver
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help.

**Compliance Accessories**: The accessories associated with this equipment are: shielded video cable when an external monitor is connected. These accessories are required to be used in order to ensure compliance with FCC rules.

### FCC declaration of conformity

#### Responsible party:

Gateway Companies, Inc. 610 Gateway Drive, North Sioux City, SD 57049 (605) 232-2000 Fax: (605) 232-2023

#### Product:

■ Gateway 600YG2

This device complies with Part 15 of the FCC Rules. Operation of this product is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

#### Caution



Changes or modifications not expressly approved by Gateway could void the FCC compliance and negate your authority to operate the product.

### Telecommunications per FCC part 68 (applicable to products fitted with USA modems)

Your modem complies with Part 68 of the Federal Communications Commission (FCC) rules. On the computer or modem card is a label that contains the FCC registration number and Ringer Equivalence Number (REN) for this device. If requested, this information must be provided to the telephone company.

An FCC-compliant telephone line cord with a modular plug is required for use with this device. The modem is designed to be connected to the telephone network or premises wiring using a compatible modular jack which is Part 68-compliant. See installation instructions for details.

The Ringer Equivalence Number (REN) is used to determine the number of devices which may be connected to the telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company.

If this device causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. The telephone company may request that you disconnect the equipment until the problem is resolved.

The telephone company may make changes in its facilities, equipment, operations, or procedures that could affect the operation of this equipment. If this happens, the telephone company will provide advance notice in order for you to make necessary modifications to maintain uninterrupted service.

This equipment cannot be used on telephone company-provided coin service. Connection to party line service is subject to state tariffs. Contact the state public utility commission or public service commission for information.

When programming or making test calls to emergency numbers:

- Remain on the line and briefly explain to the dispatcher the reason for the call.
- Perform such activities in the off-peak hours such as early morning or late evenings.

The United States Telephone Consumer Protection Act of 1991 makes it unlawful for any person to use a computer or other electronic device to send any message via a telephone fax machine unless such message clearly contains, in a margin at the top or bottom of each transmitted page or on the first page of the transmission, the date and time it is sent, an identification of the business, other entity, or other individual sending the message, and the telephone number of the sending machine or such business, other entity, or individual. Refer to your fax communication software documentation for details on how to comply with the fax-branding requirement.

### Canada

### Industry Canada (IC) Intentional emitter per RSS 210

Low power, Radio LAN type devices (radio frequency (RF) wireless communication devices), operating in the 2.4 GHz Band, may be present (embedded) in your notebook system. This section is only applicable if these devices are present. Refer to the system label to verify the presence of wireless devices.

Wireless devices that may be in your system are only qualified for use in Canada if an Industry Canada ID number is on the system label.

As a general guideline, a separation of 20 cm (8 inches) between the wireless device and the body, for use of a wireless device near the body (this does not include extremities) is typical. This device should be used more than 20 cm (8 inches) from the body when wireless devices are on. The power output of the wireless device (or devices), which may be embedded in your notebook, is well below the RF exposure limits as set by Industry Canada.

Operation of this device is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

#### Warning



To prevent radio interference to licensed service, this device is intended to be operated indoors and away from windows to provide maximum shielding. Equipment (or its transmit antenna) that is installed outdoors is subject to licensing.

#### Warning



Wireless devices are not user serviceable. Do not modify them in any way. Modification to a wireless device will void the authorization to use it. Contact Gateway for service.

#### **Unintentional emitter per ICES-003**

This digital apparatus does not exceed the Class B limits for radio noise emissions from digital apparatus as set out in the radio interference regulations of Industry Canada.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de Classe B prescrites dans le règlement sur le brouillage radioélectrique édicté par Industrie Canada.

### Telecommunications per DOC notice (for products fitted with an IC-compliant modem)

The Industry Canada label identifies certified equipment. This certification means that the equipment meets certain telecommunications network protective, operation, and safety requirements. The Department does not guarantee the equipment will operate to the users' satisfaction.

Before installing this equipment, users should make sure that it is permissible to be connected to the facilities of the local telecommunications company. The equipment must also be installed using an acceptable method of connection. In some cases, the inside wiring associated with a single-line individual service may be extended by means of a certified connector assembly. The customer should be aware that compliance with the above conditions may not prevent degradation of service in some situations.

Repairs to certified equipment should be made by an authorized Canadian maintenance facility designated by the supplier. Any repairs or alterations made by the user to this equipment, or equipment malfunctions, may give the telecommunications company cause to request the user to disconnect the equipment.

Users should make sure, for their own protection, that the electrical ground connections of the power utility, telephone lines, and internal metallic water pipe system, if present, are connected together. This precaution may be particularly important in rural areas.

#### Warning



To avoid electrical shock or equipment malfunction do not attempt to make electrical ground connections by yourself. Contact the appropriate inspection authority or an electrician, as appropriate.

The **Ringer Equivalence Number** (REN) assigned to each terminal device provides an indication of the maximum number of terminals allowed to be connected to a telephone interface. The termination on an interface may consist of any combination of devices subject only to the requirement that the sum of the Ringer Equivalence Numbers of all the devices does not exceed 5.

### **Mexico**

### Intentional emitter

Low power, Radio LAN type devices (radio frequency (RF) wireless communication devices), operating in the 2.4 GHz Band, may be present (embedded) in your notebook system. This section is only applicable if these devices are present. Refer to the system label to verify the presence of wireless devices.

Wireless devices that may be in your system are only qualified for use in Mexico if a SCT ID is on the system label.

As a general guideline, a separation of 20 cm (8 inches) between the wireless device and the body, for use of a wireless device near the body (this does not include extremities) is typical. This device should be used more than 20 cm (8 inches) from the body when wireless devices are on. The power output of the wireless device (or devices), which may be embedded in your notebook, is well below the RF exposure limits as set by SCT.

#### **Unintentional emitter**

At this time there are no mandatory requirements for Unintentional Emitters. However, this device does comply with multiple requirements for other countries and regions as listed on the system label and in the user's manual.

### Laser safety statement

All Gateway systems equipped with CD and DVD drives comply with the appropriate safety standards, including IEC 825. The laser devices in these components are classified as "Class 1 Laser Products" under a US Department of Health and Human Services (DHHS) Radiation Performance Standard. Should the unit ever need servicing, contact an authorized service location.

#### Warning



Use of controls or adjustments or performance of procedures other than those specified in this manual may result in hazardous radiation exposure. To prevent exposure to laser beams, do not try to open the enclosure of a CD or DVD drive.

### **Notices**

Copyright © 2002 Gateway, Inc. All Rights Reserved 14303 Gateway Place Poway, CA 92064 USA

#### **All Rights Reserved**

This publication is protected by copyright and all rights are reserved. No part of it may be reproduced or transmitted by any means or in any form, without prior consent in writing from Gateway.

The information in this manual has been carefully checked and is believed to be accurate. However, changes are made periodically. These changes are incorporated in newer publication editions. Gateway may improve and/or change products described in this publication at any time. Due to continuing system improvements, Gateway is not responsible for inaccurate information which may appear in this manual. For the latest product updates, consult the Gateway Web site at <a href="https://www.gateway.com">www.gateway.com</a>. In no event will Gateway be liable for direct, indirect, special, exemplary, incidental, or consequential damages resulting from any defect or omission in this manual, even if advised of the possibility of such damages.

In the interest of continued product development, Gateway reserves the right to make improvements in this manual and the products it describes at any time, without notices or obligation.

#### **Trademark Acknowledgments**

1-800-GATEWAY, ActiveCPR, ALR, AnyKey, black-and-white spot design, CrystalScan, Destination, DestiVu, EZ Pad, EZ Point, Field Mouse, Gateway 2000, Gateway Country, gateway.net, Gateway stylized logo, Perfect Scholar, Solo, TelePath, Vivitron, stylized "G" design, and "You've got a friend in the business" slogan are registered trademarks and black-and-white spotted box logo, GATEWAY, Gateway Astro, Gateway @Work, Gateway Connected touch pad, Gateway Connected music player, Gateway Cyber:)Ware, Gateway Education:)Ware, Gateway Flex Case, Gateway Gaming:)Ware, Gateway GoBack, Gateway Gold, Gateway Learning:)Ware, Gateway Magazine, Gateway Micro Server, Gateway Money:)Ware, Gateway Music:)Ware, Gateway Networking Solutions, Gateway Online Network (O.N.) solution, Gateway Photo:)Ware, Gateway Professional PCs, Gateway Profile, Gateway Solo, green stylized GATEWAY, green stylized Gateway logo, Gateway Teacher:)Ware, Gateway Video:)Ware, HelpSpot, InforManager, Just click it!, Learn@Gateway, Kids BackPack, SERVE-TO-ORDER, Server Watchdog, SpotShop, Spotshop.com, and Your:)Ware are trademarks of Gateway, Inc. Intel, Intel Inside logo, and Pentium are registered trademarks and MMX is a trademark of Intel Corporation. Microsoft, MS, MS-DOS, and Windows are trademarks or registered trademarks of Microsoft Corporation. All other product names mentioned herein are used for identification purposes only, and may be the trademarks or registered trademarks of their respective companies.

### **Macrovision statement**

#### If your computer has a DVD drive and an analog TV Out port, the following paragraph applies:

This product incorporates copyright protection technology that is protected by method claims of certain U.S. patents and other intellectual property rights owned by Macrovision Corporation and other rights owners. Use of this copyright protection technology must be authorized by Macrovision Corporation, and is intended for home and other limited viewing uses only unless otherwise authorized by Macrovision Corporation. Reverse engineering or disassembly is prohibited.

### Index

A	inserting 85
AC adapter	playing 91, 96, 98, 103, 105
connecting 20	troubleshooting 270
connector 7, 262	Audio DJ
damaged 20	channels 93, 95
defective 21	controls 2, 92
international adapters 156	playing CD 91
AC-3 digital audio jack 3, 262	power indicator 92
access point 194, 197, 198	using 91
accessories 16	Audio DJ controls 2
safety precautions 296	back 92
accounts	next 93
America Online 73	pause 92
ISP 73	play 92
user 187	power button 92
ad hoc networking 199	stop 93
adding	volume down 93
icons to desktop 51	volume up 93
user accounts 187	audio file
See also installing	streaming 191
airplane power adapter 16, 156	automobile power adapter 16, 156
alarms 158, 160	AVI file 101
America Online 74	_
application key 29	В
arrow keys 29	background 180
AU file 101	backing up files 225
audio	battery 16
digital jack 3, 262	alarm options 158, 160
headphone jack 4, 261	bay 9, 151
microphone jack 3, 11	changing 151
muting 87, 89, 93	charge indicator 2, 21, 148
playing 96, 98, 99, 101	charge status 148
recording 99	conserving power 156
troubleshooting 289	installing main 151
audio CD	installing secondary 153
adding tracks to your library 109	managing power 156
cleaning 272	meter 21, 149
copying 121	monitoring charge 148
creating music CDs 112, 116	recalibrating 150
editing track information 108	recharging 20, 149

replacing 244
slots 3, 244
troubleshooting 286
carrying case 16
CD
adding tracks to your library 109
cleaning 272
copying 121
creating data CD 112
creating music CDs 112, 116
editing track information 108
inserting 85
playing music 91, 96, 98, 103, 105
troubleshooting 270
using 84
CD Copier 121
CD drive
See CD-RW drive
See recordable CD drive
CD Player 98
CD-RW
cleaning 272
copying CDs 121
creating data CDs 112
creating music CDs 116
troubleshooting 270
using 84
CD-RW drive 3, 5, 84, 156
identifying drive 84
modular drive status indicator 26,
27
replacing drive module 246
Certificate of Authenticity 13
changing bay modules 246
cleaning
audio CD 272
case 228
CD 272
component exteriors 228
computer screen 229
DVD 272
keyboard 229
mouse 229

screen 229	headphone 4, 261
clicking 35	i.Link 4, 38, 131
close button 53	IEEE 1394 4, 38, 131
closing	keyboard 5, 7, 38, 261
program 25, 53	line in 4, 261
window 53	microphone 3, 11, 99
color	modem 6, 36, 262
changing depth 174	monitor (VGA) 6, 262
changing desktop 177, 179	mouse 5, 7, 38, 261
changing number of 174	network 6, 37, 262
changing scheme 177, 179	NTSC/PAL 6
composite video (TV) out jack 6, 128	parallel 6, 38, 262
connecting	port replicator 8, 260
AC adapter 20	power 7, 20, 262
camera 38	printer 5, 6, 38, 261, 262
digital camera 38	PS/2 7, 261
digital video camera 38	PS/2 keyboard 7, 261
external keyboard 28	PS/2 mouse 7, 261
keyboard 28	S/PDIF 3, 262
modem 36	scanner 5, 38, 261
port replicator 263	serial 7, 38, 262
printer 38	speaker 4, 261
PS/2 keyboard 7, 261	S-Video out 128, 262
PS/2 mouse 7, 261	Toslink digital audio 3, 262
scanner 38	TV out 6
surge protector 22	USB 5, 38, 261
to Ethernet 37	VGA 6, 262
to Internet 38, 74	video camera 4, 38, 131
to network 37	video out 6
video camera 38, 131	Zip drive 5, 38, 261
connections	copying
AC-3 digital audio 3, 262	CDs 121
audio 3, 4, 262	files and folders 57, 69
composite video (TV) out 6	text and graphics 69
digital audio out 3, 262	copyright notice 306
digital camera 5, 7, 38, 261	creating
digital video camera 4, 38, 131	data CDs 112
docking 8, 260	documents 65
docking station 260	folders 55, 56
Ethernet 6, 37, 262	movies 131
external audio 4, 261	MP3 files 109
external speakers 4, 261	music CDs 116
Firewire 4, 38, 131	music files 105, 109
,,	

startup diskette 214	inserting 82
Customer Service 291	status indicator 26, 27, 83
Accounting 292	troubleshooting 273
Sales 292	using 82
Warranty 292	write-protect 215
customizing 173	diskette drive 3, 5, 82
cutting	eject button 82
files and folders 57, 69	replacing drive module 246
text and graphics 69	using 82
	display
D	settings 174
default printer 287	switching 30
defragmenting hard drive 223	troubleshooting 274
deleting files and folders 49, 59, 69,	docking port 8, 260
220	docking release latch 260
desktop 48	documentation
adding icons 51	Gateway Web site 45
adding shortcuts 51	help $4 ilde{0}$
adjusting settings 174	HelpSpot 40
changing background 180	online help 44
changing color depth 174	documents
changing color scheme 177, 179	creating 65
changing colors 177, 179	opening 67
changing number of colors 174	printing 68
changing resolution 176	saving 66
using 49	double-clicking 35
device drivers	downloading 77
See drivers	dragging 35
devices 16, 38	drivers 233
dialing codes 168	reinstalling 233
digital audio S/PDIF jack 3, 262	updating $\bar{2}35$
digital camera	drives 54
connecting 38	backing up files 225
serial port 7, 262	CD 3, 5, 156
USB port 5, 261	CD-RW 3, 5, 84, 156
digital video camera	changing modular drives 246
connecting 38	checking for errors on 221
IEEE 1394 port 4	checking for free space 219
directional keys 29	defragmenting 223
Disk Cleanup 220	deleting files 220
Disk Defragmenter 223	diskette 3, 5, 82
diskette	DVD 3, 5, 84, 156
creating startup 214	DVD/CD-RW 3, 5, 84, 156

hard drive 3, 5, 8, 255	EmPower power adapter 156
identifying drive types 84	Error-checking 221
replacing hard drive kit 255	eSupport 14, 15, 46
second hard drive 3, 5	Ethernet 192, 193
sharing 190	connecting 37
status indicators 26, 27	jack 6, 37, 262
troubleshooting 270, 273, 276	turning wireless Ethernet on or off
types 84	201
viewing contents 54	wired 193, 194
viewing files and folders 55	wireless 196, 197, 198, 199
DSL modem 38, 72, 194, 197	external audio jack 4, 261
DVD	external monitor 6, 30, 262
cleaning 272	EZ Pad touchpad 11, 33
inserting 85	F ,
playing 126, 128	F
troubleshooting 270	fan 5, 6
using 84	Fast Ethernet 192, 193, 195
DVD drive 3, 5, 84, 156	faxes 133
identifying drive 84	automatically canceling 144
modular drive status indicator 26,	canceling 143
27	configuring Fax 135, 137
replacing drive module 246	failed transmission 145
DVD/CD-RW	installing Fax 134
copying CDs 121	receiving and viewing 142
creating data CDs 112	retrying 144
creating music CDs 116	sending 139
troubleshooting 270	sending a scanned image 142
using 84	sending from a program 141
DVD/CD-RW drive 3, 5, 84, 156	setting up cover page template 140
identifying drive 84	troubleshooting 282
modular drive status indicator 26,	files 54, 55
27	backing up 225
replacing drive module 246	copying 57, 69
replacing universities and	cutting 69
E	deleting 49, 59, 69, 220
electrostatic discharge (ESD) 249	finding 60, 62
e-mail 73, 78	moving 57, 205
address 78	opening 35, 49
button 32	pasting 69
checking for messages 79	recovering 59
sending 78	renaming 69
transferring settings 208	searching for 60, 62
emergency startup diskette 214	transferring 169, 205
omene and a second	

troubleshooting 275	checking for errors on 221
types 206	checking for free space 219
viewing list 55	defragmenting 223
Files and Settings Transfer Wizard 204	installing 246
finding	scanning for errors on 221
files and folders 60, 62, 205	scheduling tasks 226
HelpSpot topics 42	second hard drive 3, 5
specifications 14	status indicator 26
Firewire port 4, 38, 131	troubleshooting 276
floppy disk	hard drive kit
See diskette	installing 255
Fn key 29, 30	replacing 255
folders 54, 55	headphone jack 4, 261
copying 57, 69	help
creating 56	button 32
cutting 69	online 44
deleting 49, 59, 69	using 40
finding 60, 62	HelpSpot 40
moving 57	playing a video 43
opening 35, 55	searching 42
pasting 69	starting 40
recovering 59	Using your computer link 41
renaming 69	Hibernate mode 156, 157, 162, 163
searching for 60, 62	home office network 190
viewing list 55	hot-swapping 244
fragmentation 223	hyperlinks 75
function keys 29	<i>J</i> 1
	I
G	i.Link port 4, 38, 131
game	IEEE 1394 port 4, 38, 131
multi-player 191	IEEE 802.11a 192, 196
Gateway	using while traveling 168
eSupport 14, 15, 46	IEEE 802.11b 192, 196
model number 8, 12	using while traveling 168
serial number 12, 14	indicators
Web address 45	See status indicators
Web site 45	inkjet printer 17
gateway.your.way dial-up server 282	installing
	battery 151
H	bay modules 246
hard drive	cards 244
backing up files 225	CD-RW drive 246
bay 8	device drivers 233

devices 38	J
digital camera 38	jacks
digital video camera 38	See connections
diskette drive 246	
drivers 233	K
drives 246	Kensington cable lock 169, 266
DVD drive 246	lock slot 5
DVD/CD-RW drive 246	port replicator 266
hard drive kit 255	key combinations 30
InterVideo DVD player 126	keyboard 10, 11
memory 251	buttons 28
Microsoft Fax 134	cleaning 229
PC Cards 244	connecting 28
peripheral devices 38, 208	features 28
printer 38, 208	PS/2 port 7, 261
programs 210, 237	shortcuts 69
recordable CD drive 246	troubleshooting 278
scanner 38, 208	USB port 5, 261
secondary battery 153, 246	keys
software 210, 237	application 29
Windows 240	arrow 29
Internal wireless label 13	battery status 30
Internet 72	Break 30
account 73	brightness 29, 31
broadband connection 38, 72, 190	directional 29
button 32	Fn 29, 30
connecting to 74	function 29
requirements to access 73	LCD brightness 29, 31
sharing access 190	LCD/CRT 30
transferring settings 207	navigation 29
troubleshooting 277	numeric keypad 29
Internet connection	Pad Lock 30
troubleshooting 277, 281	Pause 30
Internet radio 111	power status 30
Internet service provider (ISP) 73	Scroll Lock 30
connecting to 74	Standby 30
disconnecting from 74	Status 30
setting up an account 73	system 29
transferring settings 207	system key combinations 30
InterVideo DVD player 126	toggle display 30
IRQ conflicts 272	Windows 29

L	Media Player 96, 101
label	memory 16
internal wireless 13	adding 251
Microsoft Certificate of Authenticity	bay 9, 251
(COA) 13	installing 251
model number 8, 12	replacing 251
serial number 12	troubleshooting 279
wireless networking 13	upgrading 251
laser printer 17	menu bar 53
latch	messages
docking release 260	checking e-mail 79
LCD panel release 2	sending e-mail 78
LCD brightness system keys 29	microphone jack 3, 11
LCD panel	Microsoft Certificate of Authenticity
cleaning 229	(COA) 13
release latch 2	Microsoft Fax 133
troubleshooting 274	MIDI file 101
LCD/CRT system key 30	mini PCI bay 8
lights	minimize button 52
See status indicators	model number 12, 169
line in jack 4, 261	modem 72, 73
line protector 168	cable 38, 72, 194, 197
line tester 168	connecting 36
lock	connection speed 281
Kensington cable 5, 169	DSL 38, 72, 194, 197
Rensington cable 3, 103	international adapter 168
M	jack 6, 36, 262
maintenance 211	protecting from power surge 22
backing up files 225	troubleshooting 279
checking for drive errors 221	modular bay 3, 5
checking hard drive space 219	See also bays
cleaning case 228	modular drive indicator 26, 27
cleaning component exteriors 228	monitor (VGA) port 6, 262
cleaning computer display 229	switching display 30
cleaning keyboard 229	mouse
cleaning the mouse 230	cleaning 230
creating startup diskette 214	PS/2 port 7, 261
defragmenting 223	troubleshooting 284
	USB port 5, 261
deleting files 220 suggested schedule 212	See also touchpad
	moving
using Scheduled Task Wizard 226	files 57, 205
virus protection 216 maximize button 52	folders 57, 58
IIIAXIIIIZE DULLUII J&	1014015 01, 00

Internet settings 207	networking
pointer 34	access point 197, 198
screen objects 35	ad hoc 199, 200
MP3 file	data transfer speed 193, 196
creating 105	Ethernet 192, 193, 196
editing track information 108	games 191
playing 101	internal wireless label 13
streaming 191	peer-to-peer 199, 200
MPEG file 101	sharing devices 191
streaming 191	sharing drives 190
multi-function buttons 11, 32	sharing Internet connections 190
multimedia	sharing printers 191
adjusting volume 86, 89	signal strength 196
playing audio CD 96, 98	streaming audio 191
playing DVD 126	streaming video 191
recording audio 99	turning off wireless Ethernet 201
using diskette drive 82	turning on wireless Ethernet 201
using DVD drive 84	wired connections 193
using Windows Media Player 96,	wireless connections 196
101	non-technical support
multi-player game	Accounting 292
playing 191	Sales 292
music	Warranty 292
playing 96, 98, 103	Norton Antivirus 216, 217
music library	NTSC/PAL jack 6, 128
building 109	numeric keypad 29
changing settings 110	numeric keypad status indicator 27
MusicMatch	mamerie neg pau seucus maieuces 2.
building a music library 109	0
creating music files 105	online help 40, 44
editing track information 108	button 32
listening to Internet radio 111	opening
playing audio CD 103, 105	documents 67
muting 87, 89, 93	files 35, 49
My Computer button 32	folders 35, 55
Wy Computer Button on	LCD panel 2
N	notebook 2
navigation keys 29	programs 35, 49
network	shortcut menu 35
jack 6, 37, 262	option bays
troubleshooting 285	changing modules 246
network equipment shopping list 195,	changing modules 240
198, 200	

P	release latch 260
Pad Lock	separating notebook 264
indicator 27, 30	using 16, 259
system key 30	ports
parallel port 6, 38, 262	See connections
password 169, 285	power
pasting	AC adapter 20, 156
files and folders 57, 69	advanced settings 158, 161
text and graphics 69	alarms 158, 160
pause text scrolling 30	automobile/airplane adapter 156
PC Cards	battery 25, 148, 149, 150, 151,
adding 244	156
eject buttons 3, 245	button 11, 23, 30, 158
inserting 244	changing modes 157
installing 244	changing schemes 158
removing 245	changing settings 158
slots 3, 244	connector 7, 20, 262
troubleshooting 286	conserving battery power 156
PC Doctor 269	damaged cord 20, 21
PCMCIA Cards	EmPower adapter 156
See PC Cards	extending battery life 156
peer-to-peer 200	Hibernate mode 157, 162, 163
peer-to-peer networking 199	indicator 2
peripheral devices 16, 38	international adapter 170
Pinnacle Expression 131	management 147, 156, 170
playing	schemes 158
audio CD 96, 98	SpeedStep settings 164
audio CD with MusicMatch 103	Standby/Resume 23, 24, 30, 157,
audio file 100	158
DVD 126	status box 30
multimedia files 101	status indicator 2
music CD 96, 98, 103	surge protector 22
Windows Media Player file 101	troubleshooting 286
Plug and Play devices	turning on notebook 23
Firewire support for 38	power adapter
i.Link support for 38	airplane 16
IEEE 1394 support for 38	automobile 16
USB support for 38	printer 17
pointer 34	default 287
moving 34	inkjet 17
port replicator 16, 259	installing 38, 208
attaching notebook 263	laser 17
docking port 8, 260	parallel port 6, 209, 262

sharing 191	Windows 2000 240
troubleshooting 287	Windows XP 240
USB port 5, 38, 261	See also installing
printing documents 68	removing files and folders 49, 59, 69,
programs	220
closing 69	renaming files and folders 69
installing 210, 237	replacing
opening 35, 49	battery 151
reinstalling 210, 237	bay modules 246
PS/2 port 7, 261	CD drive 246
•	CD-RW drive 246
R	diskette drive 246
radio	DVD drive 246
listening with MusicMatch 111	DVD/CD-RW drive 246
radio approval authorities 168	hard drive kit 255
radio frequency wireless connections	memory 251
168	PC Card 244
RAM	secondary battery 153
See memory	reset hole 8, 286
reboot 25	resetting the computer 25
recalibrating the battery 150	resolution
recharging the battery 149	changing 176
recordable CD drive 156, 225	restart 25
copying CDs 121	Restoration CDs 232
creating data CDs 112	right-clicking 35
creating music CDs 116	rocker switch 33
identifying drive 84	changing settings 186
status indicator 26, 27	router 194
troubleshooting 270	Roxio Easy CD Creator 112, 116
using 84, 112	•
recording	S
audio file 99	S/PDIF digital audio jack 3, 262
CD tracks 105	safety
recovering files and folders 59	general precautions 295
Recycle Bin 49	guidelines for troubleshooting 268
deleting files and folders 59	static electricity 249
emptying 60	saving documents 66
recovering files and folders 59	ScanDisk 221
reinstalling	scanner
device drivers 233	installing 38
drivers 233	USB port 5, 38
programs 210, 237	scanning drive
software 210, 237	for errors 221

for viruses 216	deleting files and folders 69
Scheduled Tasks Wizard 226	keyboard 69
screen	opening menu 35
adjusting settings 174	pasting 69
changing color depth 174	renaming files and folders 69
changing number of colors 174	selecting items in list 69
changing resolution 176	selecting multiple adjacent items in
cleaning 229	list 69
saver 183	switching between files, folders, or
troubleshooting 274, 290	running programs 69
screen objects	shutting down computer 24
getting information 35	signal strength 196
moving 35	small office network 190
selecting 35	SO-DIMM 251
Scroll Lock	software
status indicator 27, 30	See programs
system key 30	sound
Search utility 63	adjusting 86, 89, 93
searching	controls 86, 89, 93
for files and folders 60, 62	muting 86, 87, 89, 93
in HelpSpot 42	troubleshooting 289
security features	See also audio
Kensington cable lock 5, 169	Sound Recorder
Kensington lock ring 266	making audio recordings 99
security while traveling 169	playing file 100
serial number 12, 14, 46, 169, 210	speakers
serial port 7, 38, 262	built-in 11
setting up	jack 4, 261
safety precautions 295	specifications 14
sharing	SpeedStep technology 164
devices 191	Standby mode 24, 30, 157
drives 190	Standby system key 30
Internet connection 190	Start button 49
printer 191	Start menu 49
shortcut menus	starting
accessing 35	notebook 23
shortcuts	programs 35, 49
adding to desktop 51	startup diskette 214
buttons 32	static electricity 249
closing programs 69	status indicators 11, 26
closing windows 69	battery charge 2, 21, 148
copying 69	Caps Lock 27
cutting 69	CD 26, 27

CD-RW 26, 27	setting up fax cover page template
diskette drive 26, 27	140
drive activity 26, 27	telephone support 291
DVD 26, 27	television
DVD/CD-RW 26, 27	playing DVD on 128
hard drive 26	TV out jack 6, 128
modular drive 26, 27	viewing display on 128
numeric keypad 27, 30	title bar 52
Pad Lock 27, 30	Toslink digital audio jack 3, 262
power 2	touchpad 11, 33
Scroll Lock 27, 30	buttons 33, 34
support tool	changing settings 185
PC Doctor 269	clicking 35
surge protector 22, 156, 170	double-clicking 35
Suspend 30	dragging objects 35
S-Video out jack 128, 262	moving pointer 34
system identification label 8, 12	moving screen objects 35
system key combinations 30	opening files, folders, and programs
system keys 29	35
	opening shortcut menu 35
T	right-clicking 35
taskbar 49	rocker switch 33, 34
Technical Support 292	selecting screen objects 35
technical support	training
automated troubleshooting 292	CD 294
eSupport 14, 15, 46	classroom 294
FaxBack support 292	Gateway Learning Libraries 294
resources 291	Learn@Gateway 294
Technical Support 292	transferring
tips before contacting 291	files 205
tutorial service 292	Internet settings 207
telephone	travel tips 167
automatically canceling a fax 144	troubleshooting
canceling a fax 143	audio 289
configuring Fax 135, 137	automated system 292
installing Fax 134	CD drive 270
line protector 168	CD-RW drive 270
line tester 168	cleaning CD 272
receiving and viewing faxes 142	cleaning DVD 272
retrying a fax 144	device installation 272
sending a fax 139	diskette drive 273
sending a scanned image fax 142	display 274
sending faxes from a program 141	DVD drive 270


DVD/CD-RW drive 270	adding in Windows XP 187
Error-checking 221	switching in Windows XP 188
faxed answers 292	G
faxes 282	V
files 275	video
gateway.your.way dial-up server 282	capture 131
general guidelines 269	composite video out jack 6
hard drive 276	playing 101, 126
Internet connection 277, 281	S-Video out jack 262
IRQ conflict 272	troubleshooting 290
keyboard 278	TV out jack 6
LCD panel 274	video camera
memory 279	connecting 38, 131
modem 279	video file
mouse 284	streaming 191
network 285	virus 216
passwords 285	protecting against 77, 216
PC Cards 286	removing with Norton AntiVirus
PC Doctor 269	217
power 286	volume
printer 287	adjusting 86, 89
safety guidelines 268	adjusting modem 284
screen 274, 290	controls 86, 89, 93
screen area 274	muting 86, 87, 89, 93
screen resolution 274	mating 00, 07, 00, 00
sound 289	W
support tool 269	waking up notebook 24
video 290	WAV file 101
Web site connection speed 278	Web browser 73, 75
turning off notebook 24	button 32
turning on notebook 23, 25	Web page 75
tutoring	Web site 75
fee-based 293	connecting to 76
	•
TV out jack 6, 128	Gateway 45 window 52
U	close button 53
undocking 264	closing 53, 69 maximize button 52
updating	menu bar 53
device drivers 235	minimize button 52
Norton AntiVirus 218	
upgrading 243	title bar 52
USB port 5, 38, 261	Windows
user accounts	desktop 48

installing 240 Product Key Code 13 reinstalling 240 reinstalling device drivers 233 updating device drivers 235 Windows key 29 Windows Media Player 96, 101, 126 wireless connections using while traveling 168 wireless Ethernet 192, 196 access point 197, 198 ad hoc 199, 200 data transfer speed 196 label 13 peer-to-peer 199, 200 signal strength 196 turning on or off 201 using while traveling 168 World Wide Web (WWW) 75 downloading files 77 write-protection for diskettes 215 Ζ Zip drive 225 USB port 5, 38

### **Before You Start!**

### Connect to AC power

- Connect the AC adapter to the notebook.
- Connect the AC adapter to the power cord and the power cord to an electrical outlet. You can use the notebook while the adapter is connected to AC power.



## **2** Connect the modem (optional)

Plug one end of the modem cable into the modem jack on the back of the notebook and the other end into the telephone jack.




**CAUTION!** To protect your computer during electrical storms, unplug both the computer and modem.

### **3** Start the notebook

Open the LCD panel and press the power button located on the panel above the keyboard.

After the notebook has started, follow the on-screen instructions to complete Windows setup.



MAN SYS 600 YG2 USR GDE R0 10/02

