

XL2 Input Keypad

for XL2 Audio and Acoustic Analyzer



The XL2 Input Keypad offers four keys to trigger an event recording or categorize noise during measurements. It is an accessory to the XL2 Audio and Acoustic Analyzer.

The XL2 Audio and Acoustic Analyzer features event recording. The accessory XL2 Input Keypad offers the basic interface to set markers and trigger the event recording. The requirements are:

- Installed optional Extended Acoustic Pack
- Firmware V2.30 or higher

Applications:

- Categorize annoying industrial noise.
- Mark events to exclude them from the measurement data during post-processing.
- Manually trigger the audio data and noise level recording, e.g. for neighborhood noise monitoring.

LED

The XL2 confirms a successful registered key press with the green confirmation LED.

Setting Markers

You may categorize the noise during measurements by pressing any key of the XL2 Input Keypad. This supports post-processing of the measurement data back in your office. For example, pressing key 1 adds the information, that marker 1 was pressed, into the log file. In this manner you can objectively differentiate between four independent noise categories.

Trigger Events

The XL2 Analyzer may be configured to record wav-files and additional noise level data only when triggered, instead of for the complete measurement duration. Events are triggered automatically by sound levels above/below a preset value or manually by external key press using the XL2 Input Keypad. Pressing any key initiates the following XL2 actions:

- Audio data may be recorded for a limited, user-defined time.
- The levels LAeq, LZeq and LCPeak are recorded for the event duration.
- Retrigger with every repeated key press within the event duration.

Specifications

Output / Input	<ul style="list-style-type: none"> • 2.5 mm jack mono at end of the connection cable <ul style="list-style-type: none"> » Cable length = 1.8 m (5.9 ft) » Termination: dip - Signal, ring - Common ground • Confirmation LED informs the XL2 Analyzer has recognized the key press.
Power Supply	<ul style="list-style-type: none"> • Self-powered by I/O interface of XL2 Analyzer • Confirmation LED <ul style="list-style-type: none"> » Powered by Lithium Battery 3V CR2032 » Typical battery life time: 250'000 key presses for 1 second.
Temperature	-10 °C to +50 °C (14° to 122 °F)
Humidity	< 90% RH, non-condensing
NTi Audio #	600 000 384



Find more information in the XL2 Operating Manual.

All information subject to change without notice.
XL2 Audio and Acoustic Analyzer is a trademark of NTi Audio.

NTi Audio AG
Im alten Riet 102
9494 Schaan
Liechtenstein, Europe
Phone +423 239 60 60
Fax +423 239 60 89
info@nti-audio.com

NTi Americas Inc.
PO Box 231027
97281 Tigard, Oregon
USA
Phone +1 503 684 7050
Fax +1 503 684 7051
americas@nti-audio.com

NTi China Ltd.
Room 722, 7F, Building 6-3A,
No 1388, Bin He Rd.
215000 Suzhou, China
Phone +86 512 6802 0075
Fax +86 512 6802 0097
china@nti-audio.com

NTi Japan Ltd.
Ryogokusakamoto Bldg. 1-8-4
Ryogoku, 130-0026 Sumida-ku
Tokyo, Japan
Phone +81 3 3634 6110
Fax +81 3 3634 6160
japan@nti-audio.com