

4210A RUBIDIUM FREQUENCY STANDARD

10MHz Rubidium Frequency Reference 100kHz Capability (with MOPS option) 1PPS Disciplining Input (standard) Ultra Low Phase Noise (-130dBc at 10Hz) RS 232 Monitor/Control Convenient 2U bench or 19" rack mount



The *ptf* 4210A Rubidium Frequency Standard is a unique solution for providing a highly stable, low phase noise, frequency reference for applications requiring atomic reference stability performance.

The instrument contains a high performance rubidium module, with an extended life design, and very low aging rate, with high quality OCXO o/p for low phase noise.

For even better long term stability the unit will accept a 1PPS input that can be derived from a reference such as caesium or GPS.

An ideal laboratory or system frequency reference, which includes a range of options are available to enhance the functionality of the unit.



4210A RUBIDIUM FREQUENCY STANDARD

SPECIFICATIONS

ELECTRICAL

Output Level (standard)

10MHz 0.5 vrms into 50Ω

1PPS 5 v CMOS ±20 mA sink/source

Output Level (w/MOPS Option)

1MHz 1.0 vrms into $50\Omega + 13dBm \pm 1dBm$

5MHz 1.0 vrms into $50\Omega + 13$ dBm ± 1 dBm

10MHz 1.0 vrms into 50 Ω +13dBm ±1dBm 1PPS 4.2 v CMOS into 50 Ω

Stability

Short-term: 1s 2E-11

10s 1E-11 100s 2E-12

Aging <5 E-11/month (after 30 days)

<5 E-10/year

Accuracy 5E-11 (at shipment)

Phase Noise, 1Hz b/w,

Offset from carrier Phase Noise (dBc)

10Hz -130 100Hz -140

Spurious -130 dBc (100kHz bw)

ENVIRONMENTAL & PHYSICAL

Power Requirements

AC Input (±15%) 90 - 264 VAC, <10W

DC Input (optional)

Dimensions

(HxWxD) 2U x 19" x 16"

Configuration Options

Option # Description
PPSI External 1 PPS

EXP4 4 ch. Expansion Module

MOPS Multiple RF Outputs (1, 5 & 10MHz)

RF01 1MHz Sinewave out (x4) 5MHz Sinewave out (x4) RF05 RF10 10MHz Sinewave out (x4) **PULS** Pulse Distribution (x4) High Performance OCXO OCXO ULNO Ultra Low Noise Output **FPOC** Front Panel Outputs **DCPS** DC Power Supply **RSLD** Mounted Rackslides



ptf 4210A rear view (w/MOPS option)