

VESTEL ELEKTRONİK A.Ş.			CHANGE BULLETIN (TCN)		CHANGE NO: 59-2 REF NO :-
AFFECTED MODELS: 110° MODELS WITH 11AK19B CHASSIS					
START DATE : 15.09.1999					
REASONS OF CHANGE: DELIVERY PROBLEMS OF MC44604AP SMPS CONTROLLER IC.					
OUT					
NO	PCB CODE	VESTEL CODE	COMPONENT NAME	POSITION NUMBER	QUANTITY
1	11AK19B-2	30000191	CAP CER 100PF 50V J SL	C803	1,000
2	“	30000342	CAP CER 820PF 50V K B	C806	1,000
3	“	30000074	CAP MKT 100NF 63V J	C807	1,000
4	“	30000283	CAP CER 1NF 50V K B	C808	2,000
5	“	30000353	CAP EL 100UF 25V M	C848	1,000
6	“	30000290	CAP CER 10NF 50V Z F	C853	1,000
7	“	30000283	CAP CER 1NF 50V K B	C855	2,000
8	“	30001307	DIODE BYW95A	D814	2,000
9	“	30001307	DIODE BYW95A	D815	2,000
10	“	30001503	IC CQY80NG (OPT.COUPLER)	IC801	1,000
11	“	30001499	IC MC44604P	IC802	1,000
12	“	30000554	RES CF 1/4W 180R J	R569	1,000
13	“	30002583	JUMPER WIRE 0.6MM	R802	0,875
14	“	30002583	JUMPER WIRE 0.6MM	R803	0,875
15	“	30000466	RES CF 1/4W 1K J	R809	2,000
16	“	30000594	RES CF 1/4W 22K J	R811	2,000
17	“	30000471	RES CF 1/4W 10K J	R813	3,000
18	“	30000706	RES CF 1/4W 47R J	R814	3,000
19	“	30000599	RES CF 1/4W 220K J	R821	1,000
20	“	30001129	RES MO 22K 3W J	R822	1,000
21	“	30000471	RES CF 1/4W 10K J	R831	3,000
22	“	30000718	RES CF 1/4W 4.7K J	R832	2,000
23	“	30000706	RES CF 1/4W 47R J	R833	3,000
24	“	30000815	RES CF 1/4W 8.2K J	R834	1,000
25	“	30000580	RES CF 1/4W 22R J	R835	1,000
26	“	30000706	RES CF 1/4W 47R J	R836	3,000
27	“	30000471	RES CF 1/4W 10K J	R844	3,000
28	“	30001159	RES MO 1W 0.33R J	R870	1,000
29	“	30000471	RES CF 1/4W 10K J	R871	1,000
30	“	30000718	RES CF 1/4W 4.7K J	R879	2,000
31	“	30000283	CAP CER 1NF 50V K B	C809	1,000
32	“	30000295	CAP CER 100NF 50V Z F	C830	1,000
33	“	30001318	DIODE BA159	D805	1,000
34	“	30001349	DIODE ZENER 11V	D819	1,000
35	“	30002583	JUMPER WIRE 0.6MM	D822	0,875
36	“	30002583	JUMPER WIRE 0.6MM	J801	0,875
37	“	30002583	JUMPER WIRE 0.6MM	J803	0,875
38	“	30000633	RES CF 1/4W 27K J	R805	1,000
39	“	30001128	RES MO 2W 22K J	R806	1,000
40	“	30000466	RES CF 1/4W 1K J	R807	2,000
41	“	30000837	RES CF 1/4W 9.1K J	R808	1,000
42	“	30000594	RES CF 1/4W 22K J	R810	2,000
43	“	30000519	RES CF 1/4W 150R J	R812	1,000
44	“	30000540	RES CF 1/2W 1.5M J (400V)	R816	1,000
45	“	30000531	RES CF 1/4W 15K J	R849	1,000
46	“	30000569	RES CF 1/4W 180K J	R850	1,000
47	“	30002823	RES CF 1/4W 3.3M J	R855	1,000
48	“	30000603	RES CF 1/2W 2.2M J (400V)	R860	1,000
49	“	30002583	JUMPER WIRE 0.6MM	S804	0,875
50	“	30002583	JUMPER WIRE 0.6MM	S805	0,875
51	“	30007878	PCB 11AK19B-1		1,000

## IN

NO	PCB CODE	VESTEL CODE	COMPONENT NAME	POSITION NUMBER	QUANTITY
1	11AK19E	30000300	CAP SMD 1.5NF 50V K	C803	1,000
2	"	30009206	CAP SMD 15NF 50V K R (0805)	C806	1,000
3	"	30000362	CAP EL 1UF 50V M	C807	1,000
4	"	30000321	CAP CER 3.3NF 50V K B	C808	1,000
5	"	30000400	CAP EL 47UF 50V M	C848	1,000
6	"	30000280	CAP SMD 820PF 50V J	C853	1,000
7	"	30000263	CAP SMD 56PF 50V J CH (0805)	C855	1,000
8	"	30009366	DIODE UF5402	D814	2,000
9	"	30009366	DIODE UF5402	D815	2,000
10	"	30007069	IC TCDT1102G	IC801	1,000
11	"	30007442	IC TDA16846 (4646)	IC802	1,000
12	"	30000622	RES CF 1/4W 270R J	R569	1,000
13	"	30001224	RES FUSE 1/2W 0.22R J	R802	2,000
14	"	30001224	RES FUSE 1/2W 0.22R J	R803	2,000
15	"	30000751	RES SMD 1/10W 5.6K J 0805	R809	1,000
16	"	30000824	RES CF 1/2W 820K J (400V)	R811	1,000
17	"	30000567	RES SMD 1/10W 18K J 0805	R813	1,000
18	"	30000808	RES CF 1/4W 82R J	R814	1,000
19	"	30000729	RES CF 1/4W 470K J	R821	2,000
20	"	30001086	RES MO 2W 10K J	R822	2,000
21	"	30000580	RES CF 1/4W 22R J	R831	1,000
22	"	30000735	RES SMD 1/10W 4.7R J (0805)	R832	4,000
23	"	30000735	RES SMD 1/10W 4.7R J (0805)	R833	4,000
24	"	30000735	RES SMD 1/10W 4.7R J (0805)	R834	4,000
25	"	30000683	RES CF 1/4W 390R J	R835	1,000
26	"	30000466	RES CF 1/4W 1K J	R836	2,000
27	"	30000723	RES CF 1/4W 47K J	R844	1,000
28	"	30001131	RES MO 1W 0.22R J	R870	1,000
29	"	30000590	RES CF 1/4W 2.2K J	R871	2,000
30	"	30000735	RES SMD 1/10W 4.7R J (0805)	R879	4,000
31	"	30000362	CAP EL 1UF 50V M	C834	2,000
32	"	30000362	CAP EL 1UF 50V M	C839	2,000
33	"	30000400	CAP EL 47UF 50V M	C883	1,000
34	"	30000294	CAP SMD 100NF 50V K (0805)	C891	1,000
35	"	30000284	CAP SMD 1NF 50V K R (0805)	C899	1,000
36	"	30001339	DIODE ZENER 3.9V	D820	1,000
37	"	30001284	DIODE 1N4148	D864	2,000
38	"	30001284	DIODE 1N4148	D869	2,000
39	"	30001351	DIODE ZENER 12V	D871	1,000
40	"	30001284	DIODE 1N4148	D890	2,000
41	"	30002583	JUMPER WIRE 0.6MM	J815	1,000
42	"	30002583	JUMPER WIRE 0.6MM	J816	1,000
43	"	30002583	JUMPER WIRE 0.6MM	J817	1,000
44	"	30002583	JUMPER WIRE 0.6MM	J818	1,000
45	"	30002583	JUMPER WIRE 0.6MM	J819	1,000
46	"	30002583	JUMPER WIRE 0.6MM	J820	1,000
47	"	30002583	JUMPER WIRE 0.6MM	J821	1,000
48	"	30001734	JUMPER SMD (0805)	J881	1,000
49	"	30001455	TR BC558B	Q833	2,000
50	"	30001455	TR BC558B	Q834	2,000
51	"	30001235	RES FUSE 1/2W 0.33R J	R640	2,000
52	"	30001235	RES FUSE 1/2W 0.33R J	R641	2,000
53	"	30000469	RES SMD 1/10W 1K J 0805	R815	1,000
54	"	30000729	RES CF 1/4W 470K J	R826	2,000
55	"	30000633	RES CF 1/4W 27K J	R859	1,000
56	"	30001235	RES FUSE 1/2W 0.33R J	R865	1,000
57	"	30001236	RES FUSE 1/4W 0.33R J	R866	2,000
58	"	30001236	RES FUSE 1/4W 0.33R J	R867	2,000
59	"	30001155	RES MO 33K 2W J	R880	1,000
60	"	30000563	RES SMD 1/10W 1.8K J (0805)	R883	1,000
61	"	30000524	RES SMD 1/10W 150R J (0805)	R884	1,000

62	“	30000475	RES SMD 1/10W 10K J 0805	R885	1,000
63	“	30000597	RES SMD 1/10W 22K J	R887	1,000
64	“	30002583	JUMPER WIRE 0.6MM	R888	1,000
65	“	30000710	RES SMD 1/10W 47R J (0805)	R889	1,000
66	“	30000603	RES CF 1/2W 2.2M J (400V)	R890	1,000
67	“	30000590	RES CF 1/4W 2.2K J	R891	2,000
68	“	30001086	RES MO 2W 10K J	R892	2,000
69	“	30000475	RES SMD 1/10W 10K J 0805	R895	1,000
70	“	30000466	RES CF 1/4W 1K J	R899	2,000
71	“	30009185	PCB 11AK19E		1,000
72	“	60000047	CCL 1220*1020*1.6 FR2 V0 351		0,084