A Database Publication

THE MICRO USER

Volume 4
Number 10
December 1986
£1.25

Top-selling guide to the BBC Micro!

MAKE YOUR MICRO TALK...

UTILITIES: Fast Flood Fill, Fast Scroller, Break Recovery

REVIEWS: Advanced 1770 DFS, Beeb Digitiser, ViewSpell, Max

THE MICRO USER NEWS
Disc drive prices: Big rises on way

EDUCATION MICRO USER
Classroom role for the Master Compact

BUSINESS MICRO USER
BBC Micro that runs a language centre



Festive Fun!
Help Santa load his sleigh . . . and test your powers of deduction . . . in our two great Christmas games

For the BBC MICRO ELECTRON

Ravenskull



The Eerie Loading Screen



The Elf escapes from a Ravenbee



Close-up of a Crystal Ball



The Adventurer collects a Treasure Chest

Ravenskull Castle — The Fortress of Doom

Your task is to save the village of Austburg from imminent devastation. You must enter Ravenskull Castle and retrieve the silver crucifix which the evil Baron Strieg has stolen. Only then will Austburg be safe from the Zombies who inhabit the swamp surrounding the medieval castle.

Ravenskull is a massive arcade-adventure featuring smooth 4-way screen scrolling over the 4 levels of play. Each level is 64 times the size of the screen, and there is an initially-bewildering variety of game characters including: acid pools, man-eating plants, time-doors, keys, pick-axes, scythes, spades, bows and arrows, dynamite, bells, food and wine (beware! it may be poisonous or have strange side-effects). There are also several magical scrolls and potions to be found. These may be good or evil; for example the strength scroll gives you the power to push wooden casks, whereas the lightning-strike scroll is fatal if used.

The guardians of the castle, the vicious Ravenbees have to be avoided or, in some cases, destroyed — but there is only one way to kill them; you must discover how as you venture through the dank passages of the castle. Your quest is not an easy one — only with time, experience and a little luck will you unravel all the mysteries within Ravenskull Castle.

PRIZE COMPETITION

If you are skilful enough to complete Ravenskull, you can enter our prize competition. The prizes include a £100 first-prize, with Superior Software T-shirts for runners-up.

PRICES

Electron cassette.....**£9.95**
BBC Micro cassette.....**£9.95**
BBC Micro disc (5¼")..... **£11.95**

Ravenskull is compatible with the BBC B, B+, Master

SUPERIOR SOFTWARE Limited

ACORNSOFT

The screen pictures above show the BBC Micro version of Ravenskull.

Dept. RS4, Regent House, Skinner Lane, Leeds LS7 1AX. Telephone: 0532 459453.


Access VISA

24 HOUR TELEPHONE ANSWERING SERVICE FOR ORDERS

OUR GUARANTEE

- All mail orders are despatched within 24 hours by first-class post.
- Postage and packing is free.
- Faulty cassettes and discs will be replaced immediately.

EVERY WILD IMAGINATION NEEDS A LITTLE SELF CONTROL.



As a BBC Micro user, you enjoy some pretty sophisticated equipment.

So it's a pity if you are still missing that sophisticated, positive control your equipment deserves.

There's not much joy in a joystick, and keyboards can be all fingers and thumbs. Frustrating, especially when your imagination is much faster than your fingers!

What you need is an AMX Mouse.

Already thousands of BBC Micro users have adopted an AMX Mouse and wouldn't be without it.

We didn't claim it was 'the best input device'. The press said it for us.

In fact it has received outstanding critical acclaim, and no wonder!

The AMX Mouse brings to BBC Model B, B+ and Master 128 users, the same freedom and versatility which has, up to now, been the exclusive province of much more expensive computers.

COMPATIBLE WITH MASTER 128



In fact, it's no surprise that nearly all the new 16 bit 'State of the Art' computers now come with a mouse as standard. Proof, if proof were needed, that the Mouse is here to stay.

The AMS range of Mouse software includes, AMX Art, AMX Utilities, AMX Pagemaker, AMX Super Art/Rom, AMX Paintpot, AMX Desk, AMX Data Base, AMX 3D Zicon, AMX XAM.

There is also a growing list of programs available from other leading software houses, which utilize the Mouse, including, Colour Art from Watford, Mini Office II from Database, Novocad from Technomatic, Icon Master from Beebug, Compas Starter CAD system from British Thornton, CAD Soft from CAD Soft, Solidesk from Solidisk, and Mode 7 Art from Tubelink and of course View and Wordwise are also compatible, many more titles will be available soon.

Now there are three great ways for you to get into a perfect Mouse Environment!

AMX Super Art & Super Rom (Mouse, Keyboard & Joystick compatible) £49.95.

AMX Mouse plus AMX Art/Rom £69.95.

TUBELINK on Prestel page *2582182# supports the AMX Mouse and ALL AMS software.

AMX Mouse plus AMX Super Art/Rom £89.95.

Both AMX Art in mono and Super Art in colour are ideal for true Epson compatible printers and AMX Super Art is also compatible with Integrex and Okimate colour printers.

Isn't it about time you trapped an AMX Mouse?

These superb packages are available from all good computer dealers or direct, using the FREEPOST order form below.



—BBC MASTER 128—
ALSO AVAILABLE FOR MICRO MODEL B and B+

☎ FOR INSTANT ACCESS/VISA ORDERS TELEPHONE (0925) 413501/2/3

PLEASE RUSH ME **POST FREE** THE FOLLOWING AMX BBC PACKAGES.

Quantity ☐ PLEASE TICK IF MASTER VERSION IS REQUIRED.

_____AMX SUPER ART & SUPER ROM @ £49.95 EACH, INCL. VAT & P&P

_____AMX MOUSE & AMX ART & ROM @ £69.95 EACH, INCL. VAT & P&P

_____AMX MOUSE & AMX SUPER ART ROM @ £89.95 EACH, INCL. VAT & P&P

I ENCLOSE CHEQUE/POSTAL ORDER FOR £ _____

OR DEBIT MY ACCESS ☐ OR VISA ☐ (tick as appropriate)

CARD No. | | | | | | | | | | | | | | | | |

EXPIRY DATE_____

SIGNATURE_____

NAME (Block Capitals Please)_____

ADDRESS_____

_____POSTCODE_____

☐ PLEASE SEND ME FURTHER DETAILED INFORMATION ON THE AMS RANGE OF PRODUCTS (Tick if appropriate)

AMX MOUSE

IMAGINATION AT YOUR FINGERTIPS

SEND TO: ADVANCED MEMORY SYSTEMS LTD., FREEPOST, WARRINGTON WA4 1BR.

ADVANCED MEMORY SYSTEMS LTD · 166/170 WILDERSPOOL CAUSEWAY · WARRINGTON WA4 6QA · TELEX: 628672 AMS G



Vol. 4. No. 10 December 1986

Managing Editor
Derek Meakin

Editor in Chief
Mike Bibby

Features Editor
Peter Davidson

Production Editor
Peter Glover

Art Editor
Heather Sheldrick

Associate Editor
Alan McLachlan

Reviews Editor
Christopher Payne

News Editor
Mike Cowley

Technical Editor
Mike Cook

Advertisement Manager
John Riding

Advertising Sales
Mike Hayes
Peter Babbage

Tel: 061-456 8835 (Editorial)
061-456 8383 (Admin.)
061-456 8500 Advertising)
061-480 0171 (Subscriptions)
Telecom Gold: 72:MAG001
Telex: 265871 MONREF G
Quoting Ref. MAG001
Prestel Mailbox: 614568383

Published by:
Database Publications Ltd,
Europa House, 68 Chester Road,
Hazel Grove, Stockport SK7 5NY.

Subscription rates for 12 issues, post free:
£15 – UK & Eire (Sterling only)
£25 – Europe
£42 – Rest of world (airmail)

ABC 59,727 Jan-June 1986

The Micro User welcomes program listings and articles for publication. Material should be typed or computer-printed, and preferably double-spaced. Program listings should be accompanied by cassette tape or disc. Please enclose a stamped, self-addressed envelope, otherwise the return of material cannot be guaranteed. Contributions accepted for publication will be on an all-rights basis.

© 1986 Database Publications Ltd. No material may be reproduced in whole or in part without written permission. While every care is taken, the publishers cannot be held legally responsible for any errors in articles, listings or advertisements.

The Micro User is an independent publication and neither the BBC nor Acorn Computers Ltd are responsible for any of the articles in this issue or for any of the opinions expressed.

News trade distribution: Diamond Europress Sales & Distribution, Unit 1, Burgess Road, Ivyhouse Lane, Hastings, East Sussex TN35 4NR. Tel: 0424 430422.

FEATURES

7 News

All the latest happenings in the ever changing world of your BBC Micro.

67 Begin Here

More on arrays. It's hands off programming experience as we READ all about DATA.

85 MicroLink News

A monthly progress report on the growth of Britain's nationwide online database for micros.

106 Machine Code

We investigate the use of the Carry flag and show how it all adds up.

109 Competition

£500 worth of Audiogenic software to be won in this easy to enter competition.

116 Body Building

Construct a hygrometer to add to your weather station or to use on its own.

128 Adventures

More advice for the novice and expert alike – with hints on chaining puzzles.

153 Micromail

The part of the magazine you write yourselves – your news, views, brainwaves and moans.

GAMES


105 Christmas Box

While away those winter evenings with this game of logic to test the old grey matter.

111 Santa's Sleigh

Game of the month

Help Santa in his gift warehouse – but watch out for the monster spider.



Contents

UTILITIES

71 Speech

A fascinating utility to get your micro to talk back to you – and there's not a speech chip in sight.

103 Scroller

Improve your animation with this machine code program to provide fast scrolling in any direction.

112 Flood Fill

This versatile fast fill routine will enable you to exploit your micro's graphics capabilites to the full.

127 Break Recover

Hang on to your variables! This effective utility will do just that even when Break is pressed.

REVIEWS

20 Software Scene

From Repton 3 to Rebel Planet and Trivial Pursuit – you'll find the latest software reviewed here.

65 Rom Roundup

Max from Advanced Memory Systems and Clares' Brom Plus are put through their paces.

124 Advanced 1770 DFS

An in-depth evaluation of Advanced Computer Products' alternative disc filing system.

BUSINESS MICRO USER

83 Application

How the BBC Micro came to the aid of both students and tutors alike, in Lydbury English Centre.

87 Type casting

A light-hearted look at some of the characters to be found in most business organisations.

93 Spreadsheets

More on using function keys as we learn how to avoid mistakes by locking cells.

97 ViewSpell

Need a good spelling checker? This package from Acornsoft may be just what you're looking for.


EDUCATION MICRO USER

31 Compact in school

We discuss the potential classroom role of Acorn's new Master Compact.

35 Tables

Learning can be fun with this short effective table tester.



37 Software

Our experts cast a critical eye over some of the latest educational releases for the BBC Micro.

40 Beeb Digitiser

Printer dumps for magazines – just one of the applications for this add-on from Watford.

43 Administration

The suite of programs reviewed here should be a boon to school administrators.

44 Letters

A selection from our mailbag reflecting your views on the BBC Micro's role in education.

G.P.D. SYSTEMS

31 ABBEY ROAD
BILLERICAY
ESSEX CM12 9NF
Tel: (02774) 51443



DISC DRIVES

	exc. VAT	inc. VAT
Mitsubishi 5.25" 2 year manufacturers's guarantee 40/80 switchable (switch at front of unit)		
Without PSU		
Single 400k DS	£96	£110.40
Dual 800k DS	£183	£210.45
With PSU		
Single 400k DS	£112	£128.80
Dual 800k DS	£205	£235.75
Dual 800k horizontally mounted in a monitor stand. Fits both the BBC and Master series.	£235	£270.25
Low cost 5.25" Hoshin drives 1 year guarantee		
Single 400k DS Without PSU	£85	£97.75
Dual 800k DS Without PSU	£168	£193.20
Single 400k DS With PSU	£101	£116.15
Megadisc		
A 20Mg byte hard disc for the BBC using the ADFS. Includes 20MgB hard disc, independent PSU and cooling fan, Winchester controller card and BBC host adapter card.	£499	£573.85

SPECIAL OFFER
5 free discs with every single drive
10 free discs with every dual drive

Offer ends 15th December 1986



PRINTERS

	exc. VAT	inc. VAT
Star NL10 30cps NLQ 120cps Draft	£225	£258.75
Taxan KP810 30cps NLQ 140 Draft	£214	£246.10
Shinwa CP80A 100cps Draft	£160	£184.00
Epson LX86 28cps NLQ 120cps Draft	£225	£258.75
Juki 6100 Daisywheel	£240	£276.00

SPECIAL OFFER

Quendata 1120 Daisywheel (includes spare ribbon worth £7)	£140	£161.00

MONITORS

	exc. VAT	inc. VAT
Philips 8533 medium resolution colour	£249	£286.35
Philips Monochrome green, anti-glare	£69	£79.35
Taxan 14" std res colour	£195	£224.25
Taxan Supervision III high res colour	£315	£362.25
Microvitec 1451 med res colour	£230	£264.50
Mitsubishi 1404 medium res	£210	£241.50
Ideal Xmas Gift		
Philips TV/Monitor, gives true monitor performance but with 10 pre select TV channels	£172	£197.80




COMPUTERS

	ex. VAT	inc. VAT
Master 'Compact' New BBC system with integral 3.5" disc and separate keyboard. 128k RAM. Comes complete with a wide range of software. View, Logotron Desk Top Utilities.		
Base unit (Computer + Single Drive)	£385	£442.74
Base unit + UHF modulator	£395	£454.25
Base unit + monochrome monitor	£465	£534.75
Base unit + colour monitor	£595	£684.25
Second 3.5" Disc Unit	£100	£115.00
B8C MASTER 128k with VIEW and other free software	£390	£448.50
B8C+ 64k (price subject to availability)	£350	£402.50
ADFS Upgrade with manual	£26	£29.90
Word Processing Package		
Master 128 with View and Viewsheet, Dual 800k Disc Drive, High Res Green Monitor, Daisywheel Printer, Paper, Discs and all cables	£787	£905.05
Master Compact with View, Single Drive, Colour Monitor and Daisywheel Printer	£705	£810.75



SPECIAL LATE NIGHT LINE
We have opened a special evening enquiry and order telephone line from 5.30pm to 9.00pm every evening
Phone at your leisure: 02774 55076



Mail Order Goods despatched within 24hrs.
Discounts available for quantity purchases.
Large selection of educational and business software.
Educational and official orders welcome.
Export orders welcome

Access VISA

All prices correct at time of going to press.

THE MICRO USER NEWS

December 1986

Disc drive prices are due to rocket

A WARNING has gone out to BBC Micro users that the price of disc drives is about "to go through the roof".

The message that is coming over loud and clear is: Buy now or pay more later.

A survey has shown that the current wholesale price of disc drives in the UK is around 40 per cent higher than at this time last year.

The main reason for this is the poor showing of the pound against the Japanese yen – a situation that is unlikely to improve in the immediate future.

"Last year saw 400k drives on sale for as little as £80, whereas now you're looking at an RRP of around the £120 mark", says Barry Rubery of Pace Micro Technology.

"The situation is now completely out of our control".

Spokesmen for several other disc drive suppliers told *The Micro User* that this was the case. "If BBC Micro owners want to buy a disc drive, they had better buy now", said a representative of Middlesex-based Twillstar.

However at least one dissenter could be found in the form of one of the leading suppliers in the market.

Watford Electronics has in fact shown an overall reduction in its disc drive price range of seven per cent since last year.

Nor has the firm any intention of imposing a price increase in the immediate future.

"We intend to keep our prices down as long as we possibly can", a Watford spokesman told *The Micro User*.

"Naturally we are subject to problems with the pound just like anyone else, so there is no way any price guarantees can be given.

"However we hope to stay ahead of the game as we normally do by buying at the right price. That's the key".

ALL GO AT THE SHOW

ONCE again the vast army of BBC Micro users north of Watford turned out in force to ensure the latest Manchester Electron & BBC Micro User Show was an enormous success.

Exhibitors too reported an extremely successful three days trading.

"The show proved to us that the northern BBC Micro user is as enthusiastic as ever", said Nick Pearson of AMS.

"We sold our entire supply of AMX Pagemaker on the first day and rushed back to base to re-stock".

Another happy man was Paul Beverley of Norwich Computer Services who unveiled three new Wordwise Plus support programs – Videoscript, Footnotes and Fractions.

Like the other two programs, Videoscript uses the Wordwise Plus segment programming language to manipulate text into columnar format.

"Up to three columns are supported and Videoscript allows Wordwise Plus users to easily create their own newspaper-style printouts", said Beverley.

As an aid to editors and students, Footnotes allows user-controlled insertion of margin and page notes into a Wordwise Plus text file – useful, for example, in English language and literature study courses, as well as an aide memoire for text file creation and editing.

Fractions is an easy-to-use patch routine for on-screen display and printing of fractions from within Wordwise Plus – symbols that are not normally available in Wordwise Plus files.

Videoscript sells for £12, Footnotes for £10 and Fractions for £8.

Care Electronics had several new cartridge rom products for the Master series on view.

Using a £10.81 cartridge extender, Master owners can plug the existing range of low profile rom cartridges from Care into their machines.

At £2 each the cartridges compare favour-

Turn to Page 9

Santa goes on-line

MESSAGES to Father Christmas need not be subjected to the vagaries of the postal service this year.

To ensure that it is possible for every child to contact him before the big day, the jolly old fellow has gone on-line up at the North Pole.

Equipped with a BBC Micro no less, Santa has electronically hooked himself up to a giant computer here in the UK.

Now all that kiddies – or their parents – have to do to contact him is to transmit their message via any home or office micro.

SantaLink is the latest service being offered to subscribers to MicroLink, the UK's fastest growing electronic mail service.

All they have to do is type SANTA at the prompt when they go on-line and then enter their message.

And Father Christmas is guaranteeing that each message he receives will get through – and be sent an answer – right up to Christmas Eve when he leaves to deliver the presents.

BOOST FOR COMPACT

THE windfall from profit-taking on TSB shares could be one reason why the new Compact is selling in such large quantities.

"The machine is doing very well in the shops", says Acorn marketing chief Bob Coates.

"There seems to be a lot of money around in the consumer market at the moment – a lot of it in the pockets of people who've taken a quick profit on their TSB share issue.

"This has been very good for us at a time when we are running an extensive and costly advertising campaign".

MICROMAN Computers

ACORN SPECIALIST COMPUTER CENTRE

All our prices include VAT.

APPOINTED WATFORD DEALER

Microman has been appointed a Watford Dealer. We are stocking a large range of Watford products, including the popular BEEB DIGITIZER, MAGAZINE MAKER, 32K SHADOW RAM CARD, RAM/ROM CARDS, DFS UPGRADES and many more available from our shop.

BBC MASTER SERIES

Master 128	475.00
Master Turbo Module	125.00
Master 512 Upgrade	399.00

MASTER ROM CARTRIDGES

ISO Pascal	69.00
Logo	69.00

BBC MASTER COMPACT SERIES

Master Compact + TV Modulator	458.85
Master Compact + Green Monitor	539.35
Master Compact + Colour Monitor	688.85
Compact Software	Phone for new list

ACORN PERIPHERALS

800K Dual Disc Drive + Stand	316.00
Teletext Receiver	99.00
Prestel Receiver	139.00
6502 2nd Processor	199.00
IEEE Interface	325.00

BBC B and B+ DISC INTERFACES

Acorn 8271 0.9 Disc Interface	59.80
Acorn DNFS ROM	20.60
Acorn 1770 Disc Interface	49.95
Acorn ADFS ROM	29.99
Watford Single Density DFS	62.10
Solidisk DDFS 2·2 Interface	35.00

RAM/ROM SHADOW EXPANSION

Watford Expansion Boards	Large range in stock
Aries B12 Sideways ROM Board	46.00
Aries B12c Adapter	5.75
Aries B32 RAM Extension Board	92.00
ATPL Sidewide ROM Board	43.70

EPROM PROGRAMMERS/ERASERS

Control Telemetry Eprom Prog.	109.25
Uviprom EPROM Prog.	20.95
Uviprom EPROM Prog. + ZIF	25.95
Uviprom 32k EPROM Prog. + ZIF	25.95
Uviprom ROM Software	5.00
Uviprom SWR Disc Software	2.00
Uvipac EPROM Eraser	20.95
Uvipac EPROM Eraser + Timer	25.95

EPROMS/RAM

Eproms 2764 8K	2.75
Eproms 27128 16K	3.45
27128 per 5 Eproms	16.50
RAM 6264LP-15 8K	3.95
27256 (12.5v)	5.95

MONITORS (inc BBC CABLE)

Microvitec 1431 Std/Metal	229.00
Microvitec 1451 Med/Metal	279.00
Philips 1114 TV/Monitor/CV	209.00
Philips CM8524 STL/RGB/CV	175.00
Philips CM8533 Med/RGB/CV	299.00
Philips Green 7502	85.00
Philips Amber 7522	89.00

MODEMS/COMMUNICATIONS

Pace Nightingale + Commstar	129.95
Pace Nightingale	113.85

PACE DISC DRIVE PRODUCTS

Pace PSD3 400K 40-80T	128.95
Pace PDD3 800K 40-80T	249.95
Pace PDS3P 400K 40-80T + PSU	154.95
Pace PDD3P 800K 40-80T + PSU	286.95

PRINTERS

Canon PW1080A	289.00
Star NL10 (No Interface)	239.00
Star NL10 + BBC/Cent Interface	278.00
Star SG15 Wide Carriage	389.00
Juki 6100 Daisywheel	299.00

PLOTTERS

Roland DXY-880A A3 Plotter	P.O.A.
Roland DXY-980A A3 Plotter	1207.50
Watanabe MP1000 A3 Plotter	P.O.A.
Epson HI80 Plotter (4 pen)	458.85
Hitachi A3 Plotter (4 pen)	495.00
Microman Plotter ROM	29.95

DIGITISERS

Graphpad II	75.50
Cherry Digitiser	632.50

BBC CAD SYSTEMS

Bitstik 1	375.00
Bitstik Multi-plotter Driver	79.00
Bitstik 2 (Master compatible)	799.00
Bitstik 2 Upgrade	460.00
Pineapple Diagram (40T Disc)	28.75
Pineapple Diagram (80T Disc)	28.75
Pineapple PCB Designer	97.75
Novacad Trackerball Compatible	113.85
Novacad Plotter Utilities	32.78

MITSUBISHI DISC DRIVES

OPUS 5802 400K 40/80T/DS

£109.95

OPUS 5802D 800K 40/80T/DS

£209.95

OPUS 5802D 800K 40/80T/DS including PSU

£239.95

Opus Challenger 256K — £179.95

Opus Challenger 512K — £199.95

MOUSE/TRACKERBALL PRODUCTS

AMX Mouse + Free Watford Art	79.95
AMX Mouse: Master Version	79.95
AMX Pagemaker	49.95
AMX Pagemaker: Master version	49.95
AMX Desk	24.95
AMX Utilities	14.95
AMX Max	19.95
AMX Super Art ROM	49.95
AMX 3D Zicon	24.95
AMX Database	24.95
AMX Xam	24.95
Fleet Street Editor	39.95
Fleet Street Editor Utilities	14.95
Trackerball RB2 + ICON Soft	69.95
Trackerball + Pointer (Master)	69.95
Pointer ROM	14.37
Trackerball/Mouse Interface	9.20

VIDEO DIGITISERS

Watford BEEB Video Digitiser	126.50
Watford Magazine Maker	148.35

WORD-PROCESSORS + UTILITIES

View 2.1 ROM	52.00
View 3.0 ROM	79.00
Viewspell ROM	39.95
Interword ROM	49.00
Wordwise Plus ROM	49.00
Watford Word-Aid	27.60

FONT/NLQ UTILITIES

Watford NLQ ROM for Epson	28.75
View Printer Driver for above	11.50
Hershey Font (Disc)	21.00
Clares Fontwise (Disc)	12.00
Clares Fontwise Plus (Disc)	20.00
Clares Fonteditor (Disc)	20.00
Fontaid ROM	30.00
Fontaid Utilities Disc A	15.00
Fontaid Utilities Disc B	15.00
Multi-Font NLQ	30.00

DATABASES + UTILITIES

Viewstore ROM	52.00
Acorn Database (Disc)	15.35
Masterfile II (Disc)	22.00
Betabase	25.00

SPREADSHEETS/CHARTS

Viewsheet ROM	52.00
Viewplot ROM	29.95
Ultracalc ROM	79.50
Intersheet ROM	49.95
Interchart ROM	33.95

PANASONIC KX-P1080 PRINTER

This well-built printer offers many advanced features. It provides both friction and tractor feed NLQ as well as draft modes and full Epson code compatibility. This special offer includes a BBC Cable. Further details on request.

£179.00

LANGUAGES

BCPL ROM	59.80
BCPL Calculations	34.50
BCPL Stand Alone Generator	49.90
ISO Pascal ROM	59.95
ISO Pascal Stand Alone Gen.	34.50
Comal ROM	49.85
Acorn LOGO ROM	69.00
Logotron LOGO ROM	69.00
Micro-Prolog ROM	79.95

UTILITIES

Acorn Basic Editor ROM	29.90
Acorn Termulator ROM	34.50
Acorn Graphics Ext. ROM	29.90
Computer Concepts	Full range
Beebug	Full range
Caretaker Basic Utility ROM	33.35
System ADE ROM	60.00
System SPY ROM	30.00
Slave Plus ROM	39.95
Floppywise Plus ROM	29.95
Proc-Kit (Disc)	10.95
Loc-Kit (Disc)	25.00
Vine Replay ROM's	35.00
Vine TD ROM	18.00
Clares Profile Disc	12.00
Clares BROM Plus	30.00
Clares Ramrod ROM	40.00
Watford The Investigator	23.00
Watford Dumpout 3 ROM	28.75
CJE Inform	20.00
Moviemaker ROM	29.90
Supergraph	28.75
Pineapple Compiler	28.75

VIGLEN PRODUCTS

Viglen Console	49.00
Viglen Printer Stand	19.95

PC SHOWROOM

With the launch of the Amstrad PC1512 and Opus PC II, we are opening a new showroom for the sales of PC compatible computers, add-on card, hard discs, printers and software. The showroom is adjacent to our existing shop and we welcome our existing and new customers to visit us and have an opportunity to see and use this new range of machines and software.

We will be stocking the range of Amstrad PC1512, Opus PC II and Tandon computers along with software titles such as VP Planner, VP Info, Executive Writer, Supercalc 3, Wordstar 1512, Word Junior and many more applications.

Opening times for the showroom will be 9-5 Mon.-Fri. and 9-12 Sat. Our shop times remain unchanged.

MAIL ORDER SALES

Access

PHONE 074488 5295

VISA

We accept both Access and Visa credit cards. Simply telephone your order, giving card number, expiry date, name and address, or send your order with cheque or postal order to the address opposite.

Carriage/Postage Charges: Computers/Printers/Disc Drives: Next day delivery, £8.00; Royal Mail Trackback, £4.00; ROM/Exp. Boards/Software: First class post, £1.00.

Our Mail Order Dept. will despatch your order within 24 hours (subject to availability).

ALL PRICES INCLUDE VAT


Government and Educational Orders accepted.

SHOP

SHOP OPENING

9-6 MONDAY TO SATURDAY

Unit 1A
Rainford Industrial Estate
Mill Lane, Rainford,
St Helens, Merseyside, WA11 8LS
Phone 074488 5242



The incredible shrinking Beeb



Mini powerpack – the Microbeeb

LATEST product from Cambridge Microprocessor Systems is a micro that Gulliver might have appreciated.

Innovative design and extensive use of surface mount technology combine to make Microbeeb the smallest and most versatile single board computer to date, the company claims.

A multi-layer board measuring just 3.5in by 2.5in, Microbeeb has three times as many surface mount components underneath the board as there are conventional components on top.

Functions supported include 6502 compatible processor, three independent fully programmable serial channels, RS422/423 serial interface and high speed synchronous serial interface.

It has two independent stepper motor outputs, four analogue input channels, 35 independent user definable input/output ports, liquid crystal display interface driver, six programmable counter timers, real time calendar timers and real time timers, real time calendar clock and pulse width modulation facility.

battery backed ram, from 2k to 3Mb of eprom, 8MHz clock, 5 volt power supply, watchdog facility, rom filing system and full multi tasking.

Microbeeb supports a complete 40/80 column full colour video processor which provides an enhanced character set including teletext, over 400 user definable characters, pixel graphics, underline, flashing, reverse video, and 32k of paged ram. Video drivers are provided.

It can be programmed in Basic, Forth, Pascal or any other high level language and can be networked to up to 126 remote stations.

The manufacturer says the unique compositon of Microbeeb makes it suitable for virtually any control/monitoring task, from simple switching to applications requiring a complex video display. Price £49.95.

Northern Show

From Page 7

ably with the official Acorn product.

As with most other BBC rom cartridges, the Care system only supports 16k roms. For the latest series of 32k rom programs Care has released its twin Master rom cartridge, available with three combinations of ZIF and plug-in rom sockets, from £11.50.

Care said it will be releasing a plug-in eprom blower for the Master's cartridge slot in time for Christmas.

With the falling cost of ram chips, Opus was selling its Challenger disc drive/ram disc for £149.95 for the 256k version – £30 cheaper than usual. Buyers got a BBC double density interface, 400k disc drive and 256k ram disc unit.

Upgrades to 512k ram are available from Opus by mail order for £30.

Lecturers all smiles thanks to Micro User

TWO Manchester Polytechnic lecturers have suddenly found themselves with a thriving part-time business on their hands – thanks to *The Micro User*.

Andy Verwer and Leonard Golten have seen the computer aided design software they developed as a teaching aid become a hot commercial property of late.

Customers for one package known as Codas – control system design and simulation – now include such prestigious names as British Aerospace, British Nuclear Fuels, Vickers and Lucas.

And the Royal Greenwich Observatory is currently using Codas on a BBC Micro to help with the design of giant telescopes for the Canary Islands.

The two lecturers, who first met when Andy Verwer was a student of Leonard Golten's at Manchester Poly, have also had success with a package called PCS.

Used to simulate process plant control systems, it is now being used to train process operators at Shell Chemicals and ICI Organics Division.

Other packages concerned with signal analysis and digital control systems are in the pipeline.

Yet the two lecturers readily admit that their part-time business venture would never have got off the ground without *The Micro User*.

"All our sales to date have come from one ad we placed in the magazine earlier this year", said Andy Verwer, "so that certainly speaks well for its pulling power".

Three year ago

ANOTHER look back at what *The Micro User* covered just 36 months ago. This was the issue for December 1983:

Encouraged by the huge sales of BBC Micros to the schools, new software companies have been proliferating – mostly set up by publishing houses. One of the most prestigious companies to enter the field is Cambridge University Press.

★★★

The coming BBC Micro User Show to be held at the Westminster Exhibition Centre will feature practical demonstrations of an inexpensive way to link up two micros. Also on show will be the BBC's recently-launched telesoftware service and the government-backed Micro Electronics Project will be displaying the latest in the world of educational computing.

★★★

Acorn pulls off Britain's largest chess sponsorship deal by backing the semi-finals of the world chess championships at a cost of £100,000. The deal is made in the face of rival bids from Holland and Austria and allows the British Chess Federation to stage the matches in London.



★★★

Two new pieces of hardware are released by Acorn. The first is the Bit Stik graphics system, an extremely sophisticated computer aided design package which allows the user to define a whole library of designs. Also on offer is an IEEE interface for the BBC Micro which makes the machine the first computer of its type to offer all of the standard I/O ports - RS423, Centronics and IEEE.

Software is a family affair . . .

NEW budget software house Code Masters is a real family affair.

Managing director is Jim Darling, head of A I Products when that company was responsible for writing Mastertronic software.

His partners are sons Richard, 18, and David, 20, award-winning programmers whose games have sold in excess of a million copies.

Their prodigious output includes The Last V8, Master of Magic and the highly successful Games Creator for Mirrorsoft.

"All Code Masters' releases will be top quality arcade action games, priced £1.99", promised Jim Darling.

"We see the BBC Micro market as a vital element in our strategy and will be publishing several titles for the BBC range before Christmas".



Partners David and Richard Darling

NEW MOUSE PACKAGE

MOUSE Pac from ATPL is a new AMX-compatible digital mouse-driven software package the company claims is "comparable if not better quality" than Super Art.

Consisting of mouse, two discs, and a rom containing mouse driver software, it runs on all BBC Micro and Master series.

The software includes a facility to select and save an AMX format screen from the larger Mouse Pac-generated picture.

Mouse Pac costs £48 complete, £29.95 for the mouse which can be used with AMX software, and £20 for the two discs and rom.

OFFICE PACKAGE IS No1

MINI Office II has followed its predecessor – the original Mini Office package – to the top of the best-selling charts.

It is now number one in the BBC Top Ten of the Gallup Chart which is published in Microscope and Popular Computing Weekly.

As such, it becomes only the second business package to achieve sales figures of sufficient volume to compete in the otherwise games-dominated league. The first was Mini Office.

A rom version of Mini Office II has recently been launched by Database Software for the BBC B, B+, Master and Compact.

Contained in four chips on one board, it allows immediate access to the six modules – word processor, database, spreadsheet, graphics, label printing and comms. The price is £59.95.

Does your BBC have a one track mind?



True multi-tasking will put you out of your misery!

Your BBC now has the true multi-tasking potential of much bigger machines.

CMS Soft have cracked it!

This module, packaged as a ready-to-fit sideways ROM, brings you a robust system that holds its own in the most demanding industrial and laboratory conditions.

And there is no interference with normal BASIC functions; Multi-Basic enhances the power, speed and readability of the best BASIC Interpreter there is.


Real time Programs now possible on the BBC Micro.

- A serious tool – not an 'evaluation package'
- No extra hardware required
- No modifications needed to your BBC Micro
- Faster than procedure driven tasks

So if you want:

- full MULTI-TASKING with up to 8 background tasks running concurrent with the main program
- BBC Basic CONTROL FEATURES powerfully enhanced
- the ability to run REAL TIME PROGRAMS
- control of PHYSICAL INPUT/OUTPUT
- 5 real-time COUNTER/TIMERS
- 8 real-time TASK INTERVAL TIMERS
- a COMPREHENSIVE MANUAL that describes each command in detail, with many practical examples

£39.95 incl. p+p



MULTI-BASIC is what you need

MULTI BASIC


CMS Soft Limited.
Unit 18, Industrial Estate
Chelmsford Road, Great Dunmow
Essex CM6 1XG
Telephone (0223) 324141

CMS SOFT

CODAS

Control System Design and Simulation

for the BBC




"CODAS" is a new, highly integrated, interactive and flexible suite of programs for designing and simulating a wide variety of linear dynamic systems. Transfer functions are typed in directly as they would appear on the written page. Transport delays can also be included. Single keystroke commands promote rapid design and simulation.

- Suitable for Teaching/ Professional Use
- Simple Entry of Transfer Functions
- Step, Ramp and Impulse Response
- Root Locus
- Open and Closed Loop Responses
- Print-out of Results
- Comprehensive Manual
- Easy to Use, Fast
- Separate Compensator
- Bode, Nichols and Nyquist Plots
- Optional Transport Delays
- Cursor to Extract Detailed Data
- Hard Copy of Graphic Displays
- Tutorial Session

Golten & Verwer Partners
33 Moseley Road
Cheadle Hulme
Cheshire SK8 5HJ
Tel: 061-485 5435

Supplied on 40 or 80 track disk with comprehensive manual

Price £190 inclusive



10 Mb back-up

LATEST product from Akhter is the Archive, a 1Mb floppy disc drive with a 10Mb tape streamer for back-up storage on the BBC Micro and Master series.


It is connected in the same way as a normal floppy disc drive.

This means it can be used in tandem with a Winchester connected to the 1MHz bus on the computer.

Not only can it back up a Winchester by making an identical copy of the entire disc, its hierarchical structure enables it to back up any individual directory or file.

For use as a normal disc drive, Archive includes a 40/80 track switchable floppy disc drive.

Price £866.



Integrated test

DESIGNED to provide a fast and flexible integrated circuit testing facility, Chiptester from Datapen Microtechnology works with all disc-based BBC Micros and the Master.

The product will handle all chip sizes up to 28 pin and widths from 0.3 to 0.6 in.

Both C-Mos and TTL families are catered for as well as other 5 volt technologies, and as the user can specify entirely new test sequences many unusual devices may also be tested.

Features include searching for an unknown device, loop testing until pass or failure occurs, and the display of voltage waveforms present on any of the pins during testing of the circuit.

Software could save thousands

SOFTWARE specially written for the BBC Micro is being used in a campaign which could save up to 20,000 lives a year in the UK.

Dr Peter Burridge, consultant anaesthetist at Birch Hill Hospital, Rochdale, wrote the program with the help of two colleagues.

It forms part of the resource material for the current Save a Life campaign which aims to teach everyone in the country what to do in a life-or-death emergency.

Each year in Britain about 60,000 people die suddenly, 80 per cent at home, and experts say one third of them could survive if they got proper attention right away.

As heart attacks are a major cause of sudden death, cardio pulmonary resuscitation forms an important part of the campaign's teaching.

Dr Burridge's program contains text instruction and multiple choice test questions aimed at teaching people how to keep heart attack victims alive during those vital minutes before the ambulance arrives.

It explains how to give emergency aid like mouth-to-mouth resuscitation techniques.

"The campaign is the basis for a BBC 1 television series and 2½ hour courses are being given all over the country", Dr Burridge told *The Micro User*.

"Our BBC Micro program aims to bring practical instruction to people who haven't seen the series or can't get to their local training centre. I am particularly concerned that it should get maximum exposure in schools.

"This is why we have left it unprotected and are supplying it on disc or tape for only £3".

'Robot' control in the home

AN add-on which puts the BBC Micro in charge of household appliances has been launched by General Information Systems.

The Red Box interface "represents the first significant step into home automation for the non-technically minded", says the company.


Red Boxes are programmed using the BBC Micro as a terminal to the system, which sends signals along the mains wiring of a house to control lighting, heating and other appliances powered from a 13 amp socket.

Detectors

The devices can also receive and react to signals from devices such as intruder and smoke detectors and temperature gauges.

Special wiring is not needed because all control information is transmitted along the standard domestic main.

Data modulates a mains-borne 129kHz carrier, a frequency set aside by the British Standards Institution for such applications.



Repton updated

AN updated version of the bestselling Repton games for the BBC Micro has been launched by Superior Software.

Repton 3 offers 24 screens and a host of new features allowing the user for the first time to design screens and monsters, even to re-define the existing characters.

Those lucky enough to complete the epic adventure will be able to enter a competition with a chance of winning more than £200.

Repton 3 is available for the BBC Micro on disc at £11.95 or cassette £9.95

Commstar upgrade launched

COMMSTAR II, the long-awaited successor to the acclaimed Commstar communications rom for the BBC Micro, has finally been launched by Pace Micro Technology.

After devoting most of the summer to improving the original, author Andy Hood claims the new version represents state of the art.

According to Hood the software differs from run of the mill terminal programs for the BBC Micro in that it offers AMX style pull down menus for user selection without leaving the on-line mode. It is also fully AMX Mouse compatible.

Commstar II comes as a 16k rom for the BBC Micro – twice the code used on the original – and retails for £24, the same price as Commstar I.

21st. Software

ACCESS HOTLINE
Ask for Jacqui
0625 528885
24hr Answer Service
(ELECTRON VERSIONS AVAILABLE)

PRESENTS A SELECTION OF HARDWARE, UTILITIES & SOFTWARE FOR THE BBC MICRO

NEW **SUPERIOR/ACORNSOFT**
COMPACT DISCS 3½"
REVS+ REVS 4 TRACKS RRP **£19.95** OUR PRICE **£18.65**
CITADEL/KARATE COMBAT/SPEECH
REPTON 2/GALAFORCE/THRUST
STRYKERS RUN
RRP **£14.95** each OUR PRICE **£13.45** each

SUPERIOR SOFTWARE'S
REPTON 3
Cas. **£9.95** OUR PRICE **£8.45**
Disc **£11.95** OUR PRICE **£10.65**
SUPERIOR'S RAVENSKULL
Cas. **£9.95** OUR PRICE **£8.45**
Disc **£11.95** OUR PRICE **£10.65**

NEW **TYNESOFT'S**
FUTURESHOCK (Arc/Adv)
Cass. **£6.50** Disc price **£10.65**
GOAL (Superb Football Game)
Cass. **£6.50** Disc price **£10.65**
JET SET WILLIE II
Cass. **£6.50** Disc price **£10.65**

GEMINI'S
OFFICE MATE
Cass. or Disc **£12.00** OUR PRICE **£11.00**
OFFICE MASTER
Cass. or Disc **£25.00** OUR PRICE **£22.50**
MONEY MANAGEMENT
Disc R.R.P. **£12.95** OUR PRICE **£11.65**

MINI OFFICE II

	R.R.P.	OUR PRICE
Cass.	£14.95	£12.95
5¼"	£16.95	£14.95
3"	£19.95	£17.95

ACORNSOFT'S
ELITE On Disc
(NEW VERSION)
RRP **£19.95**
OUR PRICE **£18.65**

SUPERIOR SOFTWARE
SUPER 3 PACK (BBC)
3 CASSETTES
MOON MISSION
BMX ON THE MOON
SPITFIRE COMMAND
GREAT VALUE ALL 3 FOR **JUST £4.95**

SPECIAL OFFERS
Majic Mushrooms
Cas. **£8.95** Disc **£10.95**
Maze Cas. **£6.95** Disc **£8.95**
Yie Ar Kung Fu Cas. **£6.95**
Pole Position Cas. **£5.95**
Robotlon Cas. **£5.95**
Ends 31st November

VINE MICROS ROM SOFTWARE
ADDCOM
R.R.P. **£28.00** OUR PRICE **£26.00**
REPLAY
R.R.P. **£35.00** OUR PRICE **£31.50**
Please state Op. system

US GOLD'S
IMPOSSIBLE MISSION
Cass. **£8.95** OUR PRICE **£7.45**
Disc **£14.95** OUR PRICE **£13.45**
CRYSTAL CASTLES
(Coin op. conversion)
Cass. **£9.99** OUR PRICE **£8.45**
Disc **£14.95** OUR PRICE **£13.45**

	R.R.P.	OUR PRICE
AARDVAAK SOFTWARE		
Zalaga	7.95	6.95
Frak	8.95	7.95
ACORNSOFT		
Viewspell Rom	39.95	35.55
Elite (cas.)	14.95	12.95
Revs (cas.)	14.95	12.95
Revs (disc)	17.95	15.85
Revs 4 tracks (cass)	9.95	8.95
Revs 4 tracks (disc)	12.95	11.65
Aviator (cas.)	14.95	13.25
Aviator (disc)	17.65	15.25
Firebug (cas.)	9.95	8.95
Firebug (disc)	11.50	10.45
Snooker (cas.)	9.95	8.95
Snooker (disc)	11.50	10.50
Labyrinth (cas.)	9.95	8.95
Gateway to Karos (cas.)	9.95	8.95
Kingdom of Hamil (cas.)	9.95	8.95
ACORNSOFT/BES		
Timeman One	8.95	7.95
Happy Numbers	8.95	7.95
Wordhang	8.95	7.95
Osprey	9.95	8.95
ACORN/LINKWORD		
German	14.95	12.95
French	14.95	12.95
Italian	14.95	12.95
Spanish	14.95	12.95
ADDICTIVE GAMES		
Football Manager	8.95	7.95
Boffin	9.95	8.95
ADVENTURE INT:		
Robin of Sherwood	7.95	6.95
ALLIGATA		
Decathlon (disc)	9.95	8.95
Who Dares Wins II (disc)	9.95	8.95
Quiz Quest (disc)	9.95	8.95
Son of Blagga	7.95	6.95
Contract Bridge	9.95	8.95
ATARISOFT		
Pole Position	9.95	8.95
Robotron	9.95	8.95
BBC PUBLICATIONS		
White Knight Mk 12 (cas.)	9.95	8.95
White Knight Mk 12 (disc)	19.95	18.65
BEEBUGSOFT		
Toolkit Plus (ROM)	39.00	35.25
Romit (ROM)	34.00	31.50
Studio Eight (cass)	17.00	15.25
Studio Eight (disc)	22.00	20.00
BUG BYTE		
Twin Kingdom Valley (cas.)		2.95
Tennis (cas.)		2.95
Jack Atac (cas.)		2.95
Savage Pond (cas.)		2.95
Robots		2.95
Cricket		2.95
Starforce 7		2.95
C.D.S.		
Birdie Barrage	7.95	6.95
Steve Davis Snooker (cas.)	8.95	7.95
Steve Davis Snooker (disc)	12.95	11.65
CLARES		
Profile disc)	12.00	11.00
Fontwise (disc)	12.00	11.00
Brom ROM	34.50	31.50
Brom (disc)	27.50	25.00
Replica III (disc)	15.00	13.50
Enhanced Beta Base (disc)	25.00	22.00
Beta Base Utilities (disc)	12.00	10.85
Macrom Rom	40.00	36.00
Macrom Disc	35.00	32.00
COMSOFT		
Playbox	4.95	3.95
S.A.S. Commando	4.95	3.95
DR. SOFT (* Disc 40T add £2)		
747 Flight Sim.*	7.95	6.95
Phanton Combat*	9.95	8.95
Double Phantom (disc)	19.95	17.95
D.A.C.C.		
Flight Sim 747 (DACC)	9.95	8.95
Bobby Charlton Soccer	11.95	10.95
DATABASE (Discs add £3)		
Red Arrows	8.95	7.95
Instant Mini Office (Roms on board)	59.95	54.95
DOMARK		
Trivial Pursuits (cas.)	14.95	13.45
Trivial Pursuits (disc)	£19.95	17.95
DURELL MARTECH (*Disc add £4)		
Tarzan*	8.95	7.45
Brian Jacks Superstars	7.95	6.95
Combat Lynx	8.95	7.95
Eddie Kidd Jump	7.95	6.95
Gisburne's Castle	7.95	6.95
Geoff Capes	8.95	7.95
ELITE		
Airwolf (cas.)	9.95	8.95
Airwolf (disc)	14.95	13.65
Commando (cas.)	9.95	8.95
Commando (disc)	14.95	13.65
EPIC SOFTWARE (Disc versions add £2)		
The Wheel of Fortune cas.	9.95	8.45
Castle Frankenstein cas.	7.95	6.55
The Quest of the Holy Grail cas.	7.95	6.55
Kingdom of Klein cas.	7.95	6.55
GILSOFT		
The Quill (cas.)	16.95	15.45
The Quill (disc)	22.95	20.45
GOLEM LTD (For disc version add £2)		
Education I	8.00	7.00
Education II	8.00	7.00
Fun with Words	8.00	7.00
Fun with Numbers	8.00	7.00
Jigsaw	8.00	7.00
HEWSON		
Heathrow A.T.C.	7.95	6.95
Fantasia Diamond	7.95	6.95
Southern Belle	7.95	6.95
ASL/ICON SOFTWARE		
Psycastria	7.95	6.75
Caveman Capers	7.95	6.95
Contraption	8.95	6.95
Bug Eyes II (cas.)	7.95	6.95
Frankenstein 2000	6.95	5.95
Int. Megasports/Genesis	8.95	7.95
Last of the Free	7.95	6.75
Thunderstruck	7.95	6.75
INCENTIVE		
Moon Cresta (cas.)	7.95	6.95
Moon Cresta (disc)	9.95	8.95
Graphic Adv. Creator (cas.)	22.95	20.45
Graphic Adv. Creator (disc)	27.95	25.00
IMAGINE		
Mikie	9.95	8.95
Wizardore	7.95	6.95
Yie Ar Kung Fu	9.95	8.95
Kung Fu (disc)	12.95	11.65
Hypersports (disc only)	12.95	11.65
KOSMOS SOFTWARE (Disc version add £1)		
French Mistress A or B*	8.95	7.95
German Master A or B*	8.95	7.95
Spanish Tutor A or B*	8.95	7.95
Answer Back Jun. or Sen.*	9.95	8.95
Answer Back Sport*	9.95	8.95
Identify Europe*	7.95	6.95
L.C.L. (Disc version same price)		
Micro Maths (24 progs '0' Level)	24.50	21.50
Micro English (24 progs '0' Level)	24.50	21.50
Mega Maths ('A' Level)	24.50	21.50
Micro French '0' Level	24.90	21.50
LONGMAN'S SOFTWARE		
First Moves (Chess 8+)	9.95	8.95
LEISURE GENIUS (Disc add £2)		
Scrabble	12.95	11.65
Monopoly	12.95	11.65
LEVEL 9		
Price of Magyck	9.95	8.95
Adventure Quest	9.95	8.95
Dungeon Adventure	9.95	8.95
Emerald Isle	6.95	5.95
Lords of Time	9.95	8.95
Return to Edan	9.95	8.95
Snowball	9.95	8.95
The Worm of Paradise	9.95	8.95
Red Moon	6.95	5.95
LLAMASOFT		
Colourspace (cas.)	7.95	6.95
MACSEN SOFT		
Treasure Hunt	9.95	8.95
Block Busters	7.95	6.95
Bulls Eye	8.95	7.95
Gold Run	8.95	7.95
MELBOURNE HOUSE		
Classic Adventure	6.95	5.95
Hampstead	6.95	5.95
Terromolinos	6.95	5.95
Hobbit (cas.)	14.95	13.45
Hobbit (disc)	17.95	16.25
Exploding Fist (cas.)	9.95	8.95
Exploding Fist (disc)	14.95	13.45
MICROPOWER (Disc version add £2)		
Dr Who/Terror Mines	18.95	17.25
Castle Quest	12.95	11.65
Ghouls	7.95	6.95
Swag	6.95	5.95
Chess	7.95	6.95
Killer Gorilla	7.95	6.95
Felix in Factory	7.95	6.95
Stock Car	6.95	5.95
MIRRORSOFT (Disc version add £3)		
Count with Oliver	7.95	6.95
First Steps	8.95	7.95
Here/There with Mr Men	7.95	6.95
Quick Thinking Plus	6.95	5.95
Starseeker	9.95	8.95
Harrier Strike Force	9.95	8.95
Word Games	9.95	8.95
M.C. LOTHLORIEN		
Redcats	6.95	5.95
Paras	6.95	5.95
Johnny Reb	6.95	5.95
Special Operations	6.95	5.95
Battlezone	6.95	5.95
Waterloo	9.95	8.95
MICROBYTE		
Er*Bert	4.95	3.95
Reversi	4.95	3.95
Pinball	4.95	3.95
MOSAIC (Disc add £3)		
Erik the Viking (cas. only)	7.95	6.95
Secret Diary of Adrian Mole*	9.95	8.95
OASIS		
Aces High	14.95	12.95
OCEAN		
Match Day	9.95	8.95
REDSHIFT		
English Civil War (Cass.)	9.95	5.95
ROBICO SOFTWARE (Disc version add £2)		
Banjax	9.95	8.95
Beeline	7.95	6.95
Enthar 7 (disc)	17.95	16.45
Island of Xaan	9.95	8.95
Rick Hanson	9.95	8.95
Project Thesius	9.95	8.65
Myorem	9.95	8.65
SHARDS (* Disc version add £3)		
Mystery of Java Star	7.95	6.95
Whoopsy	6.95	5.95
Woodbury End*	9.95	8.95
SHIELD		
O Level Maths Ex.	9.95	8.95
O Level Chemistry Ex.	9.95	8.95
O Level Physics Ex.	9.95	8.95
SOFTWARE INVASION (* Disc add £3)		
3D Bomb Alley	7.95	6.95
Gunsmoke	7.95	6.95
Blitzkreig*	7.95	6.95
Super Pool	7.95	6.95
Vortex	7.95	6.95
Jet Boat	7.95	6.95
3D Grand Prix*	9.95	8.95
Eagles Wing	7.95	6.95
Stairway to Hell*	12.95	9.95
SQUIRRELSOFT		
Supergolf	7.50	6.50
Trafalgar	8.00	7.00
SUPERIOR SOFTWARE (*Disc version add £2)		
Overdrive	7.95	6.95
Tempest*	9.95	8.95
Repton*	9.95	8.95
Death Star*	9.95	8.95
Repton 2*	9.95	8.95
Citadel*	9.95	8.95
Speech*	9.95	8.95
Karate Combat (cas.)	8.95	7.95
Karate Combat (disc)	11.95	10.95
Thrust (cas.)	7.95	6.95
Thrust (disc)	11.95	10.65
Strykers Run (cas.)	9.95	8.75
Strykers Run (disc)	11.95	10.65
Gala Force (cas.)	9.95	8.75
Gala Force (disc)	11.95	10.65
TYNESOFT (*Disc versions add £3)		
Commonwealth Games (cas.)	7.95	6.50
Commonwealth Games (disc)	11.95	10.65
US Drag Racing*	6.95	5.95
Vindaloo*	7.95	6.50
Ian Botham's Test*	7.95	6.95
Mousetrap*	6.95	5.95
Winter Olympics*	7.95	6.95
Jet Set Willy*	8.95	7.95
U.S. GOLD		
Spyhunter	9.95	8.45
Raid over Moscow	9.95	8.45
Beach Head	9.95	8.95
Bruce Lee	9.95	8.95
Dambusters (disc)	14.95	13.65
Bruce Lee (disc)	14.95	13.65
Tapper	9.95	8.95
Dambusters	9.95	8.95
Rebel Planet	7.95	6.95
ULTIMATE		
Atic Atac	7.95	6.95
Alien 8	9.95	8.95
Knightlore	9.95	8.95
Jetpac	7.95	6.95
Sabre Wulf	9.95	8.95
Nightshade	9.95	8.95

21st. Software Ltd. 15 Bridgefield Avenue, Wilmslow, Cheshire SK9 2JS. Tel: (0625) 528885
ALL PRICES ARE INCLUSIVE OF VAT AND CARRIAGE
OVERSEAS ORDERS PLEASE ADD £1.00 PER ITEM
We guarantee all titles are originals. We offer a quick and reliable service.

Please send me: Cas. ☐ Disc ☐ 40T ☐ 80T ☐

1. _____ £ _____
2. _____ £ _____
3. _____ £ _____
4. _____ £ _____

TOTAL £ _____

Please make cheques payable to:
21st Software Ltd.


Send orders to:
21st SOFTWARE LTD, Dept. MU
15 Bridgefield Avenue,
Wilmslow, Cheshire SK9 2JS
Tel: Wilmslow (0625) 528885

Name .....
Address .....
.....
.....
Post Code .....
Tel. No. .....

MAX

MAX WORKS WITH KEYBOARD JOYSTICK OR AMX MOUSE

A GEM OF A DESKTOP



Using the latest Window, Icon, Menu and Pointer techniques, Max provides an easy to use, graphic based, front end for your computer's disc filing system giving the look and advantages of the latest 16 bit 'State of the Art' micros such as the Macintosh, Amiga and Atari ST.

Max has many machine specific features to bring out the best in your micro – you'll wonder how you ever did without it.

Max is available from all good computer dealers or direct using the Freepost order form below.

AVAILABLE FOR	
BBC B, B+, MASTER128, COMPACT SUPPLIED ON 16K ROM	£19.95
AMSTRAD CPC 464, 664, 6128 SUPPLIED ON DISC	£19.95
COMMODORE 64, 64C, 128 SUPPLIED ON DISC	£14.95
SPECTRUM 48K, +, 128 SUPPLIED ON MICRODRIVE	£14.95

PLEASE SEND ME **POST FREE**

(Quantity) _____ BBC (ROM) @ £19.95 (Quantity) _____ AMSTRAD (DISC) @ £19.95

_____ C64 (DISC) @ £14.95 _____ SPECTRUM (MICRODRIVE) @ £14.95

ALL PRICES INCLUDE VAT AND POST AND PACKING

I ENCLOSE CHEQUE/POSTAL ORDER FOR £ _____

OR DEBIT MY ACCESS ☐ OR VISA ☐ (tick as appropriate)

CARD NO. | | | | | | | | | | | | | | | | |

EXPIRY DATE _____

SIGNATURE _____

NAME (Block Capitals Please) _____

ADDRESS _____

_____ POSTCODE _____

☐ PLEASE SEND ME FURTHER DETAILED INFORMATION ON THE AMS RANGE OF PRODUCTS (tick if appropriate)

MAX


IMAGINATION AT YOUR FINGERTIPS

SEND TO: ADVANCED MEMORY SYSTEMS LTD., FREEPOST, WARRINGTON WA4 1BR.

☎ FOR INSTANT ACCESS/VISA ORDERS TELEPHONE (0925) 413501/2/3

ADVANCED MEMORY SYSTEMS LTD · 166/170 WILDERSPOOL CAUSEWAY · WARRINGTON WA4 6QA · TELEX: 628672 AMS G


JOYSTICKS—
THE COMPLETE SOLUTION



Delta 3B Twin



Delta 14B



Delta 14B/1



Delta 3S and Delta 3B Single



Datapad 16B

DELTA 3B TWIN—BBC B or ELECTRON PLUS 1 **£19.95**
A direct but improved alternative for the original ACORN joysticks, with 2 joysticks wired to one plug. As with all our joysticks they have the fast action sprung to centre return of the steel shafted nylon covered joystick. The light action makes them ideal to hold and the 3 fire buttons allow left or right-handed use.

DELTA 3B SINGLE—BBC B or ELECTRON PLUS 1 **£12.00**
A single joystick that in some ways can act as two. The custom made special "low noise" potentiometers are wired so that it will work as a left hand or right hand joystick. It can even run some programs written for two joysticks and has the fire buttons of both.

DELTA 14B—BBC B **£14.95**
Our original ACORN/BBC handset. The same super light joystick, but the long life buttons, which have been video game tested for many years, increased to 14 in number. A DELTA 14B/1 is needed to run the keypad but a 14B on its own will work as a joystick and fire buttons, so you can always add the 14B/1 to it later.

DELTA 14B/1 for use with 1 or 2 DELTA 14Bs **£14.85**
DELTA DRIVER CASSETTE **£5.95**
The A/D/USER PORT interface box. This gives simultaneous access to both the analogue port, for the joystick part and the user port, for the keypad. Two handsets can be plugged into the box giving a total of 24 user definable keys.
Full instructions are provided to include the keypad in your own programs even in BASIC or for the non-programmer a DELTA DRIVER cassette is available with keyboard to joystick/keypad conversions and keypad set up programs.

DELTA 3S—ELECTRON with switch joystick interface £12.00
For an ELECTRON with a switched joystick interface (Not a PLUS 1) this gives you the same delightful light, fast action of the DELTA joysticks but fitted with a 9 way D plug as per Atari, Commodore, etc. and will run on First Byte interface or similar.

DELTA ASC not illustrated **£9.95**
This little box plugs in series with your analogue joystick to alter its characteristics simply by using a switch. In one set up the joystick will act like a switched joystick, i.e. a slight movement will act as if the joystick has been pushed hard over. In the other mode the joystick only covers the centre half of the A/D converter so that it takes twice as much movement to give the same effect. This makes it much easier to make delicate adjustments to programs like flight simulators.

DATAPAD 16B **£39.95**
A commercial spec. 16 way keypad. Full travel mechanical keys with double shot moulded keycaps mounted in a low profile metal case. The keys are marked with calculator legend, but the software included allows the pad to be defined as any keys, including function keys or single byte VDU commands such as PRINTER ON/OFF. No tampering with the computer as it fits onto the user port.

Access

Available from your dealer or direct from us

VISA

Voltmace Limited

Park Drive
Baldock
Herts
SG7 6EW
Telephone (0462) 894410

BEEBUG

BRITAIN'S LARGEST INDEPENDENT COMPUTER USER GROUP


FOR THE BBC MICRO & MASTER SERIES

3 GOOD REASONS TO JOIN BEEBUG NOW!



1 Regular Magazine Mailed FREE to members

Informative articles for beginner and expert, Workshops, Reviews, News, Hints & Tips; Programs such as Personal Diary Manager, Phone Book, Page Designer, Animation, Windows and Icons, Business Graphics etc (also on cassette and disc). All to help you make the most of your micro.



2 Substantial Discounts for BEEBUG members

25% Discount on BEEBUG's own range of professional software (Masterfile, Quickcalc, Design, Studio Eight for example). 5% Discount on all other computer products (computers, disc drives, printers, software, accessories etc) through our own showroom and by mail-order.



3 Services for BEEBUG members

Comprehensive Technical Support to answer your queries regarding the use of your system; Free Members' ads; Trade-in Scheme on your old BBC micro when upgrading to Master or Compact; Secondhand Beebs with three months warranty; Insurance and Repairs; and much more.

I would like to enrol as a member of BEEBUG for 1 year and receive the next 10 issues of BEEBUG magazine.

***SUBSCRIPTION RATES**

UK, Eire and BFPOs	£12.90
Rest of Europe	£19.00
Middle East	£22.00
America & Africa	£24.00
Elsewhere	£26.00

All payments MUST be in pounds sterling. Cheques MUST be drawn on a UK bank.

SURNAME _____ INITIALS _____ TITLE _____

ADDRESS _____

_____ POSTCODE _____

SIGNATURE _____

I enclose £ _____ (enter correct amount*) OR
Please debit my Access/Visa Account £ _____

Card Number | | | | | | | | | | | | | | | | Card Expiry Date __/__

EITHER Post today to BEEBUG, Dept. MU12, Dolphin Place, Holywell Hill, St. Albans, Herts AL1 1EX
OR Phone St. Albans (0727) 40303

FOR A FREE BEEBUG INFORMATION PACK PHONE 0727 40303


BEEBUG SHOWROOM AND MAIL ORDER

The products in this price list are available in our showroom in St. Albans and by mail order. Telephone your order on 0727 40303 or send the order form to the address below. Alternatively come along and see us. We are open 9 - 5.30 Mon -Sat, and there is ample parking at the rear at our premises.

5% DISCOUNT

CHECK OUR NEW PRICES
Beebug Members May Claim 5% Discount On Our Whole Range

If you are not yet a member, join now on the form overleaf and claim your 5% discount on the hardware/software that you need.



BEEBUG MAIL ORDER
Dolphin Place, Holywell Hill,
St. Albans, Herts AL1 1EX
Tel: 0727 40303 — Multi-lines

- **Computers**
- **Printers**
- **Monitors**
- **Disc Drives**
- **Budget Discs**
- **Software**

ALL OUR PRICES INCLUDE VAT

COMPUTERS

Code	Description	Price	Mem Price
0196G	Compact+Col. Monitor	688.85	654.40
0197G	Compact+Mono Monitor	539.35	512.38
0198G	Compact TV System	458.85	435.90
0199G	Compact Entry System	442.75	420.61
0200G	Master 128	489.00	464.55
0202G	Master ET	368.00	349.60
0230C	65C102 6502 "Turbo"	119.00	113.05
0231D	80186 Co-Proc	395.00	375.25
0232D	32016 Co-Proc	1288.00	1223.60
0234B	M128 Econet Module	48.87	46.43
0235B	M128 Eprom Cartridge	15.18	14.42
0240C	M128 Manual 1 ADJ22	14.95	14.20
0241C	M128 Manual 2 ADJ23	14.95	14.20
0242C	M128 Adv Ref Manual	19.00	18.05
0203F	'6502' 2nd Processor	207.00	196.65
0204F	'Z80' 2nd Processor	335.80	319.01
0205F	Acorn Prestel Adapt	138.00	131.10
0206F	Acorn Teletext Adapt	148.35	140.93
0237F	Acorn IEEE Interface	322.00	305.90
0217B	1770 Disc Interface	49.39	46.92
0218A	ADFS Upgrade 1770	29.33	27.86
0209A	1.2 DNFS Rom	19.78	18.79
0207A	Basic II Rom	21.85	20.76
0208A	1.2 Operating System	6.90	6.55

DISC DRIVES

Code	Description	Price	Mem Price
0600F	Cumana CSX100 40T	106.95	101.60
0610F	Cumana CS100 40T	126.50	120.18
0601G	Cumana CDX200 40T	215.00	204.25
0602F	Cumana CSX400 40/80T	142.60	135.47
0603F	Cumana CS400 40/80T	162.15	154.04
0604G	Cumana CD800S 40/80T	286.35	272.03
0614F	Cumana CS100E	118.45	112.53
0615F	Cumana CS400E	155.00	147.25
0222F	Disc Starter Pack	163.00	154.85
0611A	Cumana Disk Guide	1.90	1.80
0650B	Memorex DiscsSSDD 40	15.50	14.73
0651B	Memorex DiscsDSDD 80	25.50	24.22
0652A	Memorex Disc Cleaner	9.65	9.17
0653A	Disc Case 10 discs	2.25	2.14
0654C	Disc Box - up to 50	11.99	11.39
0656D	Lockable Disc Box 85	17.25	16.39

MONITORS

Code	Description	Price	Mem Price
0501H	Kaga KX1202 Monitor	116.00	110.20
0502H	Kaga KX1203 Monitor	116.00	110.20
0556A	Taxan 1201/2/3 BNC	3.90	3.70
0571D	Stand for KX Series	29.00	27.55
0503G	Zenith 123 12" Green	83.00	78.85
0504G	Zenith 122 12" Amber	87.00	82.65
0530H	Microvitec 1431 Mon.	212.75	202.11
0531H	Microvitec 1451 Mon.	269.10	255.65
0550A	1.0m Mon. Lead RGB	5.75	5.46
0535H	Supervision III RGB	379.50	360.52
0536H	Supervision II RGB	318.55	302.62
0555A	Supervision Mon. Lead	7.00	6.65
0570D	Stand for Supervision	29.00	27.55
0551E	Single Master Plinth	16.10	15.30
0552E	Single Plinth	12.65	12.02
0553F	Double Plinth	23.00	21.85
0554A	Memorex VDU Cleaner	4.65	4.41

PRINTERS

Code	Description	Price	Mem Price
0299G	Panasonic KX-P1080	170.20	161.69
0311G	Kaga KP 810	251.85	239.26
0316G	Taxan KP910 15"	410.37	389.85
0319G	Epson FX85 NLQ	368.00	349.60
0320D	FX85 Tractor Feed	32.20	30.59
0321D	FX85 Sheet Feeder	130.00	123.50
0300G	Brother HR15XL Para	350.75	333.21
0301G	Brother HR15XL Ser.	350.75	333.21
0310G	Juki 6100 Daisywheel	362.25	344.14
0309F	Ibico LTR1 NLQ	105.16	99.90
0303G	Canon PJ1080A col.	520.00	494.00
0308G	Epson JX 80 colour	520.00	494.00
0318G	Epson HI 80 Plotter	368.00	349.60

0400A	Platten Cleaner Kit	6.44	6.12
0401A	2M Printer Lead	8.00	7.60
0402A	Epson FX/RX80 Ribbon	4.00	3.80
0403A	Epson FX/RX100 Ribbon	5.00	4.75
0408A	Canon/Taxan Ribbon	5.63	5.35
0409A	Black Cart PJ1080A	7.19	6.83
0410A	Colour Cart PJ1080A	9.99	9.49
0413A	LX 80 Ribbon	4.60	4.37
0414A	Ibico Ink Roller	4.60	4.37
0415A	Epson JX80 Ribbon	16.22	15.40
0418A	Juki 6100 S/S Ribbon	1.55	1.47
0406D	11" *9.5" Paper 2000	14.03	13.33
0453G	2-part NCR Paper	23.00	21.85
0407C	3.5" *1 7/16" Labels	5.63	5.35
0416A	Dust Cover KP810	5.45	5.18

AMX MOUSE

Code	Description	Price	Mem Price
0703B	AMX Mouse	74.75	71.01
1150B	AMX Desk Disc	19.00	18.05
1151B	AMX 3D Zicon Disc	19.00	18.05
1152B	AMX Database Disc	19.00	18.05
1153B	AMX XAM	19.00	18.05
1154C	AMX Pagemaker Plus	40.00	38.00
1155B	AMX Superart Rom	40.00	38.00
1156B	AMX Paint Pot Disc	10.99	10.44
1157C	AMX Mind Games Disc	14.50	13.78
1158A	AMX Zap Zone Cass	4.90	4.65
1160B	AMX Utilities	10.99	10.44

WATFORD HARDWARE

Code	Description	Price	Mem Price
0213A	Watford DFS Rom+Man	27.48	26.11
0214B	Watford DDFS Kit	56.35	53.53
0216A	Watford DFS Manual	6.95	6.60
0219B	Watford 1.43 DFS Kit	62.10	59.00
0702A	Watford 32K RAM Card	67.28	63.91
0709D	Watford Eprom Eraser	33.35	31.68
0717A	Watford Sideways ZIF	17.83	16.93
0736A	Watford 12 Rom Board	36.80	34.96
0737A	Watford Battery	4.37	4.15
0750B	Watford S/State 16K	32.20	30.59
0751B	Watford 16K Module	30.59	21.85
0752B	Watford Diagnostic	23.00	21.85
0753B	Rom/Ram Board 64K	67.85	64.46
0754B	Rom/Ram Board 128K	102.35	97.23
0755A	Write Protect Mk12	2.76	2.62
1120B	Watford TD Rom (SD)	28.75	27.31
1121B	Watford TD Rom (DD)	28.75	27.31

OTHER HARDWARE

Code	Description	Price	Mem Price
0701A	Aries B32 RAM Card	93.15	88.49
0704A	ATPL ROM Board BBC	39.67	37.69
0735A	ATPL Battery Backup	17.37	16.50
0740B	Aries B12 Rom Board	46.00	43.70
0749A	Aries B12C Adaptor	5.87	5.57
0705A	2764 8K Eprom	2.64	2.51
0706A	27128 16K Eprom	3.33	3.17
0707A	6264 8K Ram	3.68	3.50
0708A	Eprom Extractor Tool	3.45	3.28
0710B	Spotlife Rom Blower	75.90	72.11
0713A	Phone 2 in 1 Adaptor	6.30	5.99
0714A	BBkey Lables	2.09	1.99
0715A	Dust Cover BBC B/B+	3.45	3.28
0734A	Dust Cover Master	4.60	4.37
0716F	Music 500	86.32	82.00
0718B	Voltmace 3B Single	9.99	9.49
0719B	Voltmace 3B Twin	17.00	16.15
0720B	Voltmace Delta 14B	12.50	11.88
0721B	Voltmace Delta 14B/1	13.00	12.35
0762E	Beebug Magic Modem	95.00	90.25
0763E	Beebug Modem+ S'ware	109.00	103.55
0810D	BBC Keyboard	52.90	50.26
0811A	Video ULA Chip	17.25	16.39
0812A	A to D D7002C Chip	5.29	5.03
0814A	Keyboard Connector	5.75	5.46
0815A	65C02 CPU	13.80	13.11

COMPUTER CONCEPTS

Code	Description	Price	Mem Price
1100C	Wordwise Plus	46.00	43.70
1101A	WW+ Progbook & Disc	20.00	19.00
1102A	Wordwise	28.75	27.31
1103B	C.C. Graphics ROM	24.73	23.49
1104B	Printmaster (Epson)	28.00	26.60
1105B	Printmaster (Star)	28.00	26.60
1106B	Accelerator	56.01	53.20
1107B	Speech ROM	28.00	26.60
1109B	Disc Doctor	27.00	25.65
1110B	Intersheet	44.85	42.61
1111A	Hi Intersheet Disc	5.75	5.46
1112A	Hi Wordwise+ Disc	5.75	5.46
1113B	Caretaker Rom	28.75	27.31
1114B	Interchart	29.90	28.41
1115B	Speech System TTS	30.99	29.44
1116B	Interbase	67.85	64.46
1117B	Interword	50.03	47.52

ACORNSOFT

Code	Description	Price	Mem Price
1000B	Acornsoft View	44.28	42.06
1022C	View 3.0 Rom	66.70	63.36
1002B	Acornsoft Hi-View	44.28	42.06
1013B	View Print/Drive T.	8.62	8.19
1014B	View Print/Drive Disc	9.77	9.29
1043B	Acorn Viewspell Rom	34.02	32.32
1021A	Acorn Viewindex Disc	14.37	13.66
1019B	Acorns Viewstore Rom	44.28	42.06
1030B	Acornsoft ViewPlot	25.30	24.03
1001B	Acornsoft View Sheet	44.28	42.06
0243A	Master Lisp C.ROM	59.69	56.70
1003A	Acornsoft Lisp Rom	41.40	39.33
1025B	Acornsoft Lisp Cass	10.35	9.83

Trade in your Beeb for a Master 128 or Compact

One of the services that we are now able to offer to Beebug members is the opportunity to trade in your BBC Micro towards the purchase of a new Master.

Depending upon the age of your computer, we will allow a trade-in discount of up to £225 off the price of a new BBC Master 128 or Compact computer. This would bring the purchase price of a Master 128 down from £464.55 to £239.55.

The discounts are as follows:

BBC Micro issue 4 or older without DFS £125

BBC Micro issue 4 or older with DFS £175

BBC Micro issue 7 or newer without DFS £175

BBC Micro issue 7 or newer with DFS £225

By DFS we mean an Acorn or Watford single density DFS. Computers must obviously be in good working condition to qualify for this offer.

If you wish to take advantage of this service please write to us or telephone the number below. Do not just send your machine, as we are only able to accept orders subject to availability.

If you are not yet a member please phone and ask for an application form.

Second Hand BBC Micros For Sale

As a result of this service we will also be able to offer a number of second hand BBC Micros for sale.

Machines are thoroughly serviced and offered for sale with 3 months guarantee, from £180 upwards. Please write or phone to discuss your requirements.

Beebug Retail, Dolphin Place, Holywell Hill, St. Albans, Herts, AL1 1EX
Telephone: 0727 40303

Dynamic Discs from Beebug

Our range of top quality 5¼" blank discs for the BBC Micro and Master 128 are now available at unbeatable prices.

These discs are from the UK's leading disc manufacturer, individually tested and guaranteed for life. They are specially produced and boxed for Beebug. Don't settle for anything less than the best.

Beebug members may claim a 5% discount on the price. If you are not yet a member please phone for an application form.

NEW LOW PRICES!



48 TPI DOUBLE DENSITY

		Price	Members Price			Price	Members Price
10	S/S	£9.90	£9.40	10	D/S	£10.42	£9.90
25	S/S	£23.00	£21.85	25	D/S	£26.47	£25.15
50	S/S	£48.00	£45.60	50	D/S	£50.00	£47.50

ALL PRICES INLCUDE VAT AND STORAGE BOX

UK Carriage.
Please add £1.00 for 10 and £3.75 for 25 or 50



96 TPI QUAD DENSITY

		Price	Members Price			Price	Members Price
10	S/S	£10.42	£9.90	10	D/S	£10.90	10.35
25	S/S	£26.47	£25.15	25	D/S	£29.00	£27.55
50	S/S	£50.00	£47.50	50	D/S	£53.00	£50.35

1041B	Acornsoft Forth Rom	38.53	36.60
1042B	Acornsoft Forth Disc	19.00	18.05
1027C	Micro PROLOG	74.75	71.01
1033B	Microtext Disc	55.20	52.44
1034C	Microtext Plus Rom	240.00	228.00
1035B	6502 Dev. Pack	45.00	42.75
1004B	Acornsoft BCPL	50.03	47.52
1026B	BCPL Generator	43.57	41.39
1005B	Acornsoft Comal	41.97	39.88
1006B	Acornsoft Logo	50.71	48.18
0244A	Master PASCAL C.ROM	67.85	64.46
1007C	Acornsoft ISO Pascal	50.71	48.18
1028B	Pascal Generator	32.78	31.14
1031B	Acorn Termulator Rom	31.05	29.50
1008B	Acornsoft Basic Ed	28.00	26.60
1040C	Micros Business Disc	47.27	44.90
1037B	Database Cassette	11.50	10.93
1038B	Database Disc	14.50	13.78
1017B	Acornsoft GXR B	25.43	24.16
1018B	Acornsoft GXR B+	25.43	24.16
1039B	Creative Sound Disc	19.00	18.05
1015B	Acornsoft Revs Disc	17.08	16.22
1029A	Revs 4 Tracks Disc	11.95	11.35
1024B	Acornsoft Revs Cass	14.00	13.30
1032B	Revs 4 Tracks Tape	9.32	8.85
1016B	Acorn Aviator Disc	17.08	16.22
1044B	Acorn Aviator Cass	14.00	13.30
1036B	Elite Disc All'vers	19.95	18.95
1124A	Citadel 40/80	11.95	11.35
1125A	White Knight Disc	18.63	17.70
1126B	White Knight Cass	9.89	9.40
1127A	White Knight 1770	18.63	17.70
1128B	Movie Maker	20.95	19.91
1129A	THRUST	11.95	11.35
1130A	REPTON2	11.95	11.35
1170D	Fleet Street 40T	37.95	36.05
1171D	Fleet Street 80T	37.95	36.05
1172A	Mini Office II Cass	14.50	13.78
1173A	Mini Office II 40T	16.50	15.68
1174A	Mini Office II 80T	16.50	15.68
1175A	Clares Replica II	15.00	14.25
1011B	BBCsoft UltraCalc 2	70.00	66.50

OTHER SOFTWARE

Code	Description	Price	Mem Price
1123A	SPEECH! Disc 40/80T	11.95	11.35

CARRIAGE

Carriage is denoted by the letter contained in the stockcode, A-50p, B-£1, C-£2, D-£3, E-£3.75, F-£5.50, G-£7.

When ordering several items, use the highest price code plus half of each subsequent code, up to a maximum of £7. For courier delivery use code G.

***Overseas** customers please follow the above instructions. The VAT covers the extra postage and insurance.*

***BFPO** customers deduct VAT from the goods purchased and add above postage.*

ALL PRICES INCLUDE VAT

ORDER FORM

Beebug Mail Order, Dolphin Place, Holywell Hill, St.Albans, Herts. AL1 1EX
0727 40303

To claim members 5% discount please quote membership no. . . . . or add £12.90 for 1 years subscription (UK).

CODE	QUANTITY	DESCRIPTION	UNIT PRICE	TOTAL

NAME:

ADDRESS:

POSTCODE:

SUB TOTAL	£
CARRIAGE	£
TOTAL	£

ACCESS/BARCLAYCARD NO:

In accordance with our competitive pricing structure prices are subject to alteration at any time.

MICRO MEDIA Computer Supplies

0707 52698 or 0707 50913

Dept. MU Rydal Mount, Baker Street, Potters Bar, Herts EN6 2BP

Printer Ribbons


Mixed types for quantity breaks

	2+	5+	12+
Acorn AP 80	2.70	2.30	2.10
AP 100	2.70	2.30	2.10
Ink Jet Cartridge	7.50 per pack of four		
Brother M1009	3.50	3.00	2.80
Red Brown Blue Green	4.95	4.65	4.25
HR 15 MS	3.30	2.90	2.60
HR 15 Fabric	3.40	3.00	2.70
Canon PW1156/1080	3.20	2.70	2.50
Red Brown Blue Green	4.70	4.20	3.90
Centronics GLP	3.50	3.00	2.80
Red Brown Blue Green	4.95	4.65	4.25
Daisystep 2000 M/S	2.90	2.40	2.20
Fabric	4.10	3.80	3.50
Epson FX/MX/RX 80	2.80	2.40	2.20
Red Brown Blue Green	4.00	3.30	3.10
LX 80	2.80	2.40	2.20
Red Brown Blue Green	4.00	3.30	3.10
Juki 5510	2.80	2.40	2.20
Red Brown Blue Green	4.00	3.30	3.10
6100 MS	2.30	1.90	1.70
6100 SS	1.40	1.10	1.00
Corr Red Brown Blue	2.50	2.10	1.90
2200 Fabric	3.60	3.30	3.10
2200 SS	3.00	2.60	2.40
2200 Corr	3.90	3.50	3.30
Kaga KP 810/910	3.20	2.70	2.50
Red Brown Blue Green	4.70	4.20	3.90
M/Tally MT 80 M/S	3.80	3.00	2.80
NEC PC 8023	3.60	3.00	2.80
Oki 80/82	1.50	1.20	1.10
Red Brown Blue Green	2.40	2.00	1.80
Panasonic KXP 110	3.90	3.40	2.90
Quendata 2000 MS	2.90	2.40	2.20
Fabric	4.10	3.80	3.50
Seikosha GP80	2.70	2.30	2.10
GP100/250	2.70	2.30	2.10
GP500	3.70	3.10	2.90
Red Broiwn Blue Green	4.90	4.60	4.20
Shinwa CP80 M/S	3.80	3.00	2.80
Smith Corona			
D100/200	4.90	4.50	4.00
EL1000/2000 M/S	8.30	7.70	7.00
Fabric	3.70	3.40	3.30
Corr	4.80	4.50	4.30
Star Gemini 10x 15x	1.50	1.20	1.10
Red Brown Blue Green	2.40	2.00	1.80
NL 10	5.50	4.80	4.50
Walters WM80 M/S	3.80	3.00	2.80
2000	3.70	3.30	2.90

If the ribbon you require is not listed ring 0707 52698 and let us quote

Swivel Bases

for Monitors



Pan tilt revolves around 360°
12.5° tiltable up and down
adjustable by front mechanism.

12" Monitors **£12.00**
14" Monitors **£15.00**

Adjustable Copy Holders



A4 Adjustable desk clamping. Magnifying cursor line paper height adjustable clip, paper thickness adjustment.

£19.80



A4 Adjustable desk clamping. Plate positioned 360°.

£13.90

Micro Media Brand Universal 5¼" Discs

Reversible with 2 notches and index holes. Lifetime guarantee, hub rings, envelopes, labels. Suitable for 40 or 80 track. Packed in plastic library case.

10+	30+	50+
9.40	**8.90**	**8.50**

Unbranded 5¼" Discs

Certified lifetime warranty
hub rings, envelopes, labels

Prices per 10 Discs

	10+	30+	50+
SS/DD 40	6.50	6.00	5.50
DS/DD 40	7.50	7.00	6.50
DS/DD 80	8.50	8.00	7.50

Unbranded 3½" Discs

Lifetime Guarantee/label sets

SS/DD	17.00	16.00	15.00
DS/DD	19.00	18.00	17.00

3M 5¼" Lifetime Guarantee

SS/DD 40	10.80	10.40	10.00
DS/DD 40	12.80	12.40	12.00
DS/DD 80	17.70	17.00	16.50

3M 3½" Lifetime Guarantee

SS/DD	20.50	20.00	19.00
DS/DD	27.50	27.00	26.00

Verbatim Datalife 5¼"

SS/DD 40	11.70	11.40	11.10
DS/DD 40	14.70	14.40	14.10
DS/DD 80	19.70	19.40	19.10

Computer Labels

Continuous fanfold, sprocket fed

Price per 1000	1,000	2,000
70 x 36	4.20	3.80
89 x 36	4.30	3.90
89 x 49	5.90	5.30
102 x 36	4.50	4.20

Please state no. of labels across the sheet (1, 2 or 3).

9½" Backing Sheet for Fixed Tractor

	1,000	2,000
70 x 36 3 across	4.20	3.80
89 x 36 2 across	6.60	6.30
102 x 36 2 across	6.70	6.40

Computer paper

Plain fanfold, micro perf edges

Size	Weight gsm	1000's per box	Price per box 1 box	2 bxs+
11x9½	60	2	12.50	11.80
	80	2	15.50	14.20
EXACT A4				
11⅔ x 9¼	70	2	20.90	18.50
	90	1	13.20	11.00

A4 Fixed tractor paper available

Head Cleaners

Discs with 15ml cleaning solution

5¼" Head Cleaner	4.00
3½" Head Cleaner	5.00

Printer Leads

Centronics lead to connect BBC to Epson Kaga Canon etc.

1 MTR 6.30 2 MTR 8.50

Printout Binders

Adjustable hardback ring binder for 11x9½ to 12x9½ cont paper 40mm paper capacity


BLUE RED or BLACK	£4.90 each
set of 5 indexes	£2.30

Disc Mailers


	Price each	50+	100+
Rigid Cardboard holds up to 3 discs		40p	28p

Printer Stands


5mm clear perspex
405 x 325 x 100mm



80 column printers	£17.90
132 column printers	£24.90



MM100
Lift off lid



MD100



MM50
Lift off lid



MD50



MM40

Disc Boxes

	1	3+
MM 100 5¼ x100	11.70	10.00
MD 100 5¼ x100	11.70	10.00
MM 50 5¼ x50	8.70	7.90
MD 50 5¼ x50	8.70	7.90
MM 40 3½ x40	8.50	7.40
Rexel Mini Disc Box	5.00	
Plastic Library Case	1.50	

All MM boxes anti-static with lock

● Educational and HMG orders accepted. ● Trade enquires. ● Personal callers welcome. ● Open Sat 10am - 4pm

Orders despatched. 24 hrs. Please allow 5 days for delivery. For next day delivery please ring for details. Postage covers UK only.

ALL PRICES INCLUSIVE OF POSTAGE & PACKING

Please add VAT at 15%

24-Hour Credit Card Orders

0707 52698

-MICRO MEDIA-MICRO MEDIA-MICRO MEDIA-MICRO MEDIA-

Question master?

Program: Trivial Pursuit
Price: £14.95 (cassette), £19.95 (disc)
Supplier: Domark, 204 Worple Road, London SW20 8PN.
Tel: 01-947 5624.

If you are part of the "in crowd" then you will have spent many an evening wracking your brains playing Trivial Pursuit, rather than getting tiddly down at the Dog and Duck. Now a computerised version has been released by Domark.

After loading, you are requested to enter the names of between one and six players. A comprehensive options menu allows you to alter several of the game's features. A timer can be used to limit the time taken by a player to answer a question, and you have the option of using a dwarf called TP as question master.

You may also load a new question file from this menu. There are eight such files containing over 3,000 questions in total, many of which are taken directly from the board game.

When the game commences a crude representation of the Trivial Pursuit board is displayed. Instead of rolling a die TP throws a dart at the numbers one to six and all possible moves are then highlighted on the board. You move your token to your chosen square and one of the six subject categories will be illuminated.

The scene now changes to TP's study where it's time to put your thinking cap on. Questions can be of three types: A straight forward written question as in the board game, a picture question for which a projection screen is lowered to display an image, or a musical question for which TP turns on his cassette player to play a tune. Answers are not typed into the computer but spoken out



loud, and you press the fire button or spacebar to reveal the correct answer. You are then required to enter whether or not you got it right.

The BBC Micro version of Trivial Pursuit is embarrassingly inferior to its Amstrad and Commodore counterparts. Make sure you try it out for yourself before handing over any money.

Carol Barrow

Sound	7
Graphics	6
Playability	7
Value for money	5
Overall	6

Coming up trumps

Program: Bridge Mentor II
Price: £17.50 (disc), £19.50 (3½in disc for Compact)
Supplier: Minic Business Services, 12 Woburn Close, Bushey, Herts WD2 3XA
Tel: 01-950 9413

Bridge Mentor II is the third reincarnation of a program first released in 1984 and, as a confirmed player myself, I was a little wary of introducing it to several of my non-computer owning Bridge club friends.

The program comes up trumps, or perhaps I should say no-trumps in the case of Bridge, in the user-friendly stakes. Clear, easy to use menus guide you through the considerable number of keyboard entries necessary to set up a new game.

You can play out the existing archive of deals in the game library which comes with the program, but for true creativity and learning the facility to produce your own deal archives wins me over to Bridge Mentor II hands down.

Sixty deals are contained in the library and range from simple house rules conventions to the more complex conventions used in the Bridge-playing world.


Unlike several other games of its genre, Bridge Mentor II is the product of several programmers' minds – this is obvious by the several conventions used in different playing deals. Since every self-confessed Bridge expert is only "expert" in at best two playing conventions, the program will appeal to all types of player – from the beginner through to the professional.

Once a pre-programmed or self-programmed deal has been set up play commences with a nice on-screen graphical representation of the card table.

Since the program concentrates on hand analysis, each deal is not truly random since Bridge has defied the so-called logical analysis required for expert game systems.

Bridge Mentor II guides you through a series of logical menu choices, based upon an increasing amount of minimal information appearing, so that the ideal gameplay can be achieved.

In the event of a deviation from the programmed gameplay, the program



does not simply browbeat you into accepting its play. Instead, a fresh sequence is created and, based on the human player's judgement, the fresh gameplay may be played right through.

If the playing of that deal turns out to be memorable, the option of saving the played-out deal to a new library archive is offered.

This is one of the best serious games programs I have yet come across. It can cope with many variations and, within the not-inconsiderable limitations imposed by the BBC Micro's memory constraints, proves more than a match for any serious Bridge player.

Steve Gold

Sound	5
Graphics	9
Playability	10
Value for money	10
Overall	9

Nasty newcomers



Program: Repton 3
Price: £9.95 (cassette) £11.95 (disc)
Supplier: Superior Software, Regent House, Skinner Lane, Leeds LS7 1AX
Tel: 0532 459453

JUST when you thought it was safe to go back down the mine, Superior Software has released Repton 3.

The game features all the characters and graphics from Repton 2, but is closer to the original Repton in gameplay and objectives. It comes with 24 individual levels to complete, stored on tape or disc as three separate files.

On successful completion of each level you are given the password for the next, which means that when you play the game on subsequent occasions you don't have to wade your way through it all again.

Repton 3 doesn't suffer from as much screen edge flicker as did Repton 2, and the animation is noticeably faster – our little green skinned buddy really tears around the screen under your control.

Only a small section of the overall map is visible at any one time. Each level is laid out like a maze, constructed from boulders, earth, diamonds, giant eggs and many other devilish things. To complete a level you must kill every monster and collect all of the diamonds and a golden crown before a time bomb explodes.

The problems begin as you burrow your way beneath the boulders. As soon as the supporting earth has been removed the boulder falls, killing you or changing the shape of the maze by blocking off a passageway.

For this reason your route through the maze must be very carefully planned – one badly placed rock and you might as well start again. As in Repton, you can call up a detailed map of the whole level to help you choose the correct path through a maze.

When I first played the game I thought the monsters were pretty tricky to deal with as they have to be lured beneath a precariously balanced boulder and then squashed.

One nasty newcomer to the Repton scene is the creeping fungus. As time passes this poisonous growth will spread around the maze. Your only hope is to block its way with a few well placed boulders.


Not only does Superior Software give you one of the best games of 1986 it also supplies a maze-editing utility. You can design your own fiendish mazes, save them to cassette or disc, and pass them on to your friends for them to solve.

I can say with complete confidence that Repton 3 will outsell every other game for the BBC Micro this Christmas.

James Riddell

Sound	*8*
Graphics	*9*
Playability	*10*
Value for money	*10*
Overall	*10*

Big and bright



Program: Thunderstruck
Price: £7.95
Supplier: Audiogenic, 12 Chiltern Enterprise Centre, Station Road, Theale, Berks RG7 4AA
Tel: 0734 303663

WHILE doing your rounds as a cosmic dustbin man you are struck by a space/time thunder storm. As a result of this you find yourself trapped in an eerie medieval castle. All you want to do is get back to Myrtle and the kids before your dinner gets cold.

The multi-storey castle has eight floors which can be accessed in any order once you have located the castle's lift room. Using the cursor keys you can select a floor, then set the mechanism in motion and ascend or descend to a new level.

You will discover many objects, most of which have a specific function. If you are to escape from the castle you must use each object correctly, but due to the restraints of your bulky spacesuit you can only carry one object at a time.

One of the easier puzzles can be found the basement. When trying to access this level you find that the screen goes blank. Wishing to throw a little light on the problem you collect the candle which you saw on a higher level, but you are informed that it is not lit.

I spent a long time burning my fingers on the flaming torches trying to light the candle until I explored the other levels and found a suitable match. Returning to the basement I was greeted by a whole new floor.

One of the bigger puzzles involves lowering the drawbridge. On your travels you will see several large letters, and when you pick them up you are told that they operate the drawbridge. The letters D O and N are easily located, but I have yet to find a W to complete the sequence.

You have only one life, which you lose when your energy reserve is reduced to zero. This energy is lost through contact with flames and the castle's inhabitants, the most deadly being your own droids. They blame you for their incarceration and are fatal to the touch.

The game's graphics are big and brightly coloured, the puzzles varied in their levels of difficulty. Thunderstruck is a fun game and a good example of an arcade adventure.

Carol Barrow

Sound	*6*
Graphics	*8*
Playability	*8*
Value for money	*7*
Overall	*8*

Save the galaxy

Product: Rebel Planet
Price: £9.95 (cassette), £14.95 (disc)
Supplier: US Gold, Unit 2/3, Holford Way, Holford, Birmingham B6 7AX.
Tel: 021-356 3388

IN this text adventure your task is to save the galaxy from the nasty Arcadian Empire by penetrating the building housing the queen computer and destroying it before it destroys you.

The pressure is on from the word go. Firstly there is a move-counter ticking away (disguised as a pre-programmed flight plan for your ship Caydia). Secondly, it is a game where some sort of a puzzle is to be found at almost every move.

Be warned, it is essential that you save your position at regular intervals as you make the preliminary exploration of the scene.

You will rapidly find out, as I did, that you have left undone those things that you ought to have done! I spent almost as much time backtracking as I did going forwards into the game. You *must* examine every item you meet, as there is nearly always a clue to its use in the way it is described.


The first maze you come across can be mapped by noting the exit directions – but the authors are good at twisting the tails of adventurers.

The background and playing details are well set-out on the insert with clear information for the newcomer to adventures. A clue sheet is also on offer.

Rebel Planet uses the split screen method of display and different colours for location descriptions and objects found. However at least once in the ship an essential item is "hidden" in a location description. As the authors say: "We don't want to make things too easy, now do we?"

To help you disembark, I'll give you a clue. Make sure that you take an inventory at the start. SS means Ship's Status, PS means Personal Status, IH means Inner Hatch and OH is Outer Hatch.

Good humour, tricky puzzles and sensible back-up assistance make this a



good, workmanlike adventure that is well worth buying. If I were to give it a general rating, then I would classify it as well towards the top of Division Two.

It should particularly appeal to those who like a combination of science fiction and occasional deft humour. I have no hesitation in recommending it.

Mad Hatter

Atmosphere	7
Complexity	7
Presentation	8
Value for money	8
Overall	8

Cowboys and indians

Program: Kane
Price: £1.99 (cassette)
Supplier: Mastertronic, 8-10 Paul Street, London EC2A 4JH
Tel: 01-377 6880

KANE is a man with problems. As sheriff he must make peace with the indians and pump the town's bandits full of lead.

Stage one involves Kane shooting birds with a bow and arrow. You fire the bow by moving the cursor to the desired impact point and pressing Return.

The skill lies in judging how far in front of the bird to fire, which depends on the bird's altitude, distance and velocity. A direct hit results in the bird plummeting earthwards.

You begin with 10 arrows, and every time you kill a bird you get your arrow back. You also receive an extra life for every three birds shot. The carnage takes place against a pretty mountain scene. Sound effects are very good – the arrows fly with a nice thwap and dead birds hit the deck with a realistic thud.

The instructions say that the next stage involves a race across the desert on horseback, jumping over bushes. Not in my version it doesn't – the program went straight to scene three.

Standing at one end of the main street you stare at the buildings, scrutinising every doorway for tell-tale signs of movement. A hand appears at the saloon door, you run across the street, move your cursor into position, and Black Jake bites the dust. Before you know what's happening the buildings are buzzing with bandits.

Whatever you do you must keep moving. If you stand still for too long you'll end up an ex-sheriff. You can re-load your pistol by running off the right side of the screen, but you must choose your time to return carefully.

Everybody knows where you are going to appear, so you need to wait until there are only a few baddies on the screen before returning. Having shot 10



bad guys you can proceed to scene four. What! no scene four! Come on Mastertronic what are you playing at? The instructions say that scene four consists of racing to stop a hijacked train. It's a pity that the programmer didn't read them.

The game may cost only £1.99 but I can't help feeling that Mastertronic will receive a few letters of complaint about this one.

Jon Revis

Sound	6
Graphics	7
Playability	4
Value for money	6
Overall	6

Freedom of the press.

WORKS WITH KEYBOARD JOYSTICK OR AMX MOUSE

AMX Pagemaker puts you right at the heart of the desktop publishing revolution.

At long last you can produce newspapers, posters, leaflets, notices and handouts in your own school, home or office.

We're not talking about amateurish results, but extraordinarily professional work with crisp text and exciting graphics.

It's the sort of 21st Century technology that's turned Fleet Street upside down and is part of the most exciting advance in publishing since Guttenburg and Caxton.

You can type directly onto your screen with a choice of 16 typefaces or, if you really want to be creative, you can design your own typefaces, and, just like the most advanced computer setting, you can centre, range right, left or choose literal justification. You can even have full pixel control over character size and spacing.

Alternatively, you can load in 'wordwise' and 'view' files with fully automatic on-screen text formatting.

EXTRA! EXTRA!

Using the patterns supplied, you have outstanding graphics facilities for drawing, spraying and painting, or you can achieve some incredible results, using your own pattern designs.


The cut and paste options include copying, moving, rotating, stretching plus a fantastic zoom facility.




DIGITISED PICTURES SUPPLIED BY KEN WARWICK, PARKSIDE DEVELOPMENTS · 01-500 5701.
MAGAZINE MAKER INCLUDES AMX PAGEMAKER AND VIDEO DIGITISER WHICH IS OBTAINABLE FROM WATFORD ELECTRONICS · 0923 37774/40688.



— PROCESSOR —



— PREVIEWER —



— FONT DEFINER —

A complete mode conversion program is included, allowing you to load in drawings and digitised pictures from all BBC graphic modes.

HOLD THE FRONT PAGE

The 'Previewer' gives you total quality control over your work, allowing you to view three pages at any time before your work is output to the printer. And there's a wide range of printers, including Epson FX/RX/LX/LQ, Canon PW1080, Kaga KP810, Mannesman Tally MT-80+, Seikosha SP 1000A, Star Delta and Star SG10.

AMX Pagemaker consists of two Roms with two discs or just three discs on Master 128.

Coming complete with a comprehensive manual, AMX Pagemaker costs a mere £49.95 and is available from all good computer dealers or direct from the address below.

AMX Pagemaker – your opportunity to publish and be damned!

☎ FOR INSTANT ACCESS/VISA ORDERS TELEPHONE 0925-413501/2/3

PLEASE RUSH ME **POST FREE** _____(Quantity) AMX PAGEMAKER PACKAGE/S AT £49.95 each INCLUDING VAT AND P & P

I ENCLOSE CHEQUE/POSTAL ORDER FOR £_____

OR DEBIT MY ACCESS ☐ OR VISA ☐ (tick as appropriate)

CARD No. | | | | | | | | | | | | | | | | |

EXPIRY DATE_____

SIGNATURE_____

NAME (Block Capitals Please)_____

ADDRESS_____

_____ POSTCODE_____

AMX PAGEMAKER

IMAGINATION AT YOUR FINGERTIPS

SEND TO: ADVANCED MEMORY SYSTEMS LTD., FREEPOST, WARRINGTON WA4 1BR.

ADVANCED MEMORY SYSTEMS LTD · 166/170 WILDERSPOOL CAUSEWAY · WARRINGTON WA4 6QA · TELEX: 628672 AMS G

SOLIDISK SUMMER SPECIAL OFFERS

£40.00 Cash Allowance for your old ROM Expansion Board when you trade in for the Fourmeg 256K

or £10.00 reduction if you already have Solidisk DFS

The memory limit on the BBC Micro can now definitely be a thing of the past. The new Solidisk Fourmeg 256 board offers all you could wish for.
It has 256K of extra RAM, a superfast 4MHz CMOS processor, sophisticated memory management, sockets for high capacity ROMs and 48K of software in ROM.
In fact, it contains even more devices than the BBC itself. It is compatible with most hardware add-ons — except Sideways ROM expansion, which explains why this special offer.
Fitting it is easy. You remove the existing processor from its socket and plug the new board in its place, push on three colour-coded wires, clip on two mini-hooks and it's ready. Switch on the computer and you will immediately see the difference.
The message "Solidisk 256K expansion (4MHz)" announces the new memory size and speed.
A switch at the back lets you select between the old (2MHz) and the new (4MHz) speed.
The BBC Micro at 4MHz easily surpasses the new MASTER 128K on benchmarks.
For example, it runs the benchmark using Basic 4 in only half the time taken on the MASTER 128K.
If you have too many ROMs to plug in at once, the Fourmeg 256 offers TWO ways out. First, it includes additional high capacity (and fast) ROM sockets. Moreover, two or four normal ROM images can be stored in one high capacity ROM chip (by "Vertical Paging") — so more can be made immediately available at your fingertips.
Secondly, ROM images can be stored on discs and loaded into any one of the eight Sideways RAM banks available.
If you need more room in "languages" such as VIEW or BASIC, you may use any of the eight SHADOW RAM banks. No user memory is then lost to the screen, whatever the screen mode (while machine coded programs can access RAM right up to &FC00!).
Two frequent uses of the extra memory are as a RAMDISK or a printer buffer.
Star commands in the ROM can turn the extra RAM into a silicon DISK of 200K, compatible with both the Solidisk DFS and ADFS formats. The RAMDISK is at least 10 times faster than physical disc drives as it has no moving parts.
The printer buffer saves you time, it lets you use the computer while feeding your printer in the background.
In addition, the MANAGER ROM offers over 30 star command utilities to save time and effort using the computer.
To complement such a powerful product, Solidisk has arranged with Computer Concepts to bundle the famous WORDWISE PLUS wordprocessor ROM and manuals. This excellent product, worth £45.00 on its own, became the best selling wordprocessor for the BBC computer last year.
All in all, the Solidisk Fourmeg 256 offers an unmatched combination of speed, power and built-in facilities, while still having room for even further expansion. It is the most logical next step for the owners of any Sideways ROM board or of Solidisk Sideways RAM, who can trade in their present boards for the excellent Fourmeg 256.

Yes! I want to take you up on your special summer offer

"I will pay only: (delete if not applicable)

☑ £135.00 instead of the normal price (175), I will send you my old ROM board when I have been satisfied with your Fourmeg 256.

☑ £165.00 instead of the normal price, I already have your DFS installed in my BBC.

☑ I also allow £3.00 for First Class Post.

If for any reason I am not entirely satisfied with your product, I will return it before 15 days and have all my money back (except postage if applicable)".

Name .....

Address .....

.....

Access/Visa Account : : : : : : : : : : : : : : : : : :

Send to:

Solidisk Technology Ltd
17 Sweyne Avenue, Southend-on-Sea
Essex SS2 6JQ

We reserve the right to change prices and specifications without notice for improvement.



SOLIDISK has products to expand your BBC Micro inside out, so why hesitate, pick up the phone and ring this number:


SOUTHEND (0702) 354 674

ASK FOR A BROCHURE

SOLIDISK NEW DEVELOPMENTS

SOLIDISK NEW DEVELOPMENTS


Shadow, Sideways ROM and Sideways RAM All-In-One for £50:



This board, the TWOMEG-32K, is specifically designed with the SCHOOL BEEB in mind so that one could have everything one wanted on a single, compact and extremely easy to install unit. All the necessary software is in a MANAGER ROM (supplied).
The top row of FIVE ROM sockets will take software ROMs, up to 32K each such as used on the BBC Plus and MASTER 128.
The middle row contains 32K of additional CMOS, low power RAM, acting as SHADOW RAM or as two banks of SIDEWAYS RAM.
The empty 40 pin socket will receive either the normal 2MHz CPU or the optional enhanced, faster 4MHz CMOS 65C02 (the board will be then called the FOURMEG-32K).
The TWOMEG-32K combined the usual functions of a Sideways ROM board — offering storage for up to 160K on board and 64K on the Beeb itself (a total 224K out of 256K possible) and a SHADOW RAM compatible with major 'language ROMs' such as BASIC, VIEW, WORDWISE, INTERWORD, VIEW-SHEET, VIEW-STORE etc.
When Shadow RAM is in use, a small 8K of Sideways RAM is available for loading ROM images or a small printer buffer. When SHADOW RAM is not in use, the entire 32K additional RAM can be used as TWO banks of SIDEWAYS RAM or as a RAM DISC (available only with Solidisk DFS or ADFS).
The MANAGER ROM also contains a powerful TOOLKIT to assist PROGRAMMING IN BASIC.
The attraction of the TWOMEG-32K board comes from its versatility, its convenient software in ROM and its low price tag. Furthermore, the board can be fitted with a CMOS 65C02 capable for example of running the new BASIC 4 (some 30% faster than BASIC 2 and also more accurate) or upgraded to FOURMEG speed, comparable to the TURBO board on the MASTER.

TWOMEG-32K £50.00
65C02 (2MHz) for the above £10.00
Or upgrade to FOURMEG £25.00
FOURMEG-32K £70.00

Real Time Clock & Desk:



The Real Time Clock and Calendar (RTC) can be plugged into any ROM socket on the BBC Model B with absolutely no other connection to make.
The Real Time Clock is powered by a rechargeable battery which should keep the RTC active throughout the Summer Holidays.
Apart from giving the Time and Date, through *TIME or TIME$ (BASIC 4), the RTC has many of the AUTO-CONFIGURE features of the MASTER 128K with the same command syntax, a friendly DESKTOP program for use with the AMX MOUSE, a DIARY and a Calculator.
Many additional commands are background commands, leaving your computer free to run your program. They set the time, display the clock in any screen mode, bleep at specified time, interrupt and show a message when you have an appointment, perform a specified task at specified time etc.
You can even 'Clock Boot' your computer directly into the DESKTOP, using the MOUSE you can operate the computer without touching the keyboard (ATARI-ST style) until you 'click' on a language ROM or an application program. You can pop down the pocket size calculator, change the time and edit your DIARY (instead of using a word processor).
The Real Time Clock will add fun and convenience to the every day use of your BEEB.

Order as CLOCK £29.00


In Brief:

The range of Solidisk Add-Ons for the Beeb is quite extensive. For example: TWOMEG-32K . . . £50.00, FOURMEG-32K . . . £70.00, SWR64 with S/W pack 1 . . . £60.00, SWR128 (new style) with S/W pack 1 . . . £80.00, FOURMEG-256K with WORDWISE PLUS . . . £175.00, DDFS (1770) . . . £35.00, DFDC (1770+8271) . . . £40.00, DFS 2.2 ROM . . . £15.00, ADFS 2.1 ROM set . . . £30.00, 3½ inch (80 track double sided) drive . . . £90.00, 5¼ inch drive . . . £109.00, 20MB Winchester with PSU . . . £745, Linemaster communication ROM . . . £10.00, Insight intelligent disassembler ROM . . . £15.00, Solimon machine code monitor ROM . . . £10.00, Toolkit ROM . . . £10.00, S/W pack (1 to 3) of 5 discs . . . £10.00, 2764 EPROM . . . £1.00 each, 27128 . . . £3.00, 27256 . . . £6.00, EPROM programmer for 2764/27128 . . . £19.00, EPROM programmer for 27256 . . . £21.00, EPROM Eraser . . . £20.00.

SOLIDISK TECHNOLOGY LIMITED, 17 SWEYNE AVE, SOUTHEND-ON-SEA, ESSEX SS2 6JQ. TEL. SOUTHEND (0702) 354674 (16 lines).

SOLIDISK BUDGET DISC SYSTEMS


Double density disc interface



Solidisk very popular Double Density Disc Filing System (DDFS) is based on the WD-1770 floppy disc controller, the same chip used on the Beeb-Plus and the Master series, totally hardware compatible with Acorn 1770 DFS and ADFS ROMs. The DDFS is suitable for virtually any type of floppy disc drives, 3½" and 5¼", 40 track and 80 track, single and double-sided with or without power supply unit. New low price without DFS ROM £35.00
(order as XR/DDFS)


1770+8271, dual floppy disc controller interface

Solidisk DFDC (1770+8271) is the best seller in disc upgrades for Model B's already fitted with an INTEL 8271 chip (Acorn, Watford, Pace, Viglen, Cumana etc). It plugs into the 8271 socket with the latter relocated on the DFDC itself. This is the most convenient way of adding the modern and powerful 1770 without sacrificing the 8271 chip. The DFDC is fully hardware compatible with both Acorn DNFS 1.2 and ADFS ROMs, as well as Solidisk DFS 2.2 and ADFS 2.1 ROMs. The Acorn DNFS 1.2 is recommended for use jointly with the Solidisk ADFS 2.1 as both systems 'self-frugalise' to keep PAGE at the lowest value. We recommend the DFS 2.2 ROM alone if ADFS is not required. New low price without DFS ROM £40.00
(order as XR/DFDC)



Low cost 3 ½ inch disc drives

The new generation of THIRD HEIGHT 3 and a half inch Floppy Disc Drives offers unprecedented value for money. They feature Double-sided, 80 track per side mechanism offering up to 640K per disc in double density and ADFS. Low power, large capacity, extremely quiet mechanism, robust media and LOWER PRICE than 5 and ¼ drives make them irresistable. They are also the newly adopted Acorn disc standard. Cased, all leads. One year guarantee.
Order as 3.5 INCH-DRIVE (80 track/Double-sided) £90.00
FREE demonstration diskett (double sided) in DFS format while stock lasts (containing a Database, a Word-processor and a selection of games and disc utilities). Separate power supply for BBC Model B, issue 2 or Electron is available at £25.00.
Order as 3.5/PSU.




Special leads

A Special set of leads to connect TWO drives in ANY combination of 5¼ and 3½ drives is available separately at only £15.00 or only £8.00 surcharge if supplied in lieu of standard leads. Order as SPECIAL LEADS.

Advanced disc filing system ROM-set (two 16k EPROMS) version 2.1

The finest product yet for any BBC computer fitted with the 1770 Floppy Disc Controller (Model B, Plus and Master 128K and Electron) encompassing many Master 128K specifications. The list of features is so extensive that it would require a lot more space to describe it. In brief, it has ALL the features of the 2.2 DFS ROM except device drivers for the INTEL-8271 chip, full ADFS implementation comparable to the MASTER 128K. Plus ADFS-FORMAT (FORM40, FORM80 and FORM160) and VERIFY. Plus MVDFS and MVADFS to transfer files between DFS and ADFS formats with automatic PAUSE for disc change rendering possible to operate with a single drive. Low PAGE value. Compatible with 6502, Z80, 32016, 80186 (Master version) Second Processor. Two manuals.
Normally £30.00 but if order with DDFS or DFDC only £20.00
Please mention computer model when ordering. Order as ROMS2.1S. Also available on a single 32K EPROM as ROM2.1/32.




Single and double density disc filing system ROM version 2.2

The most powerful and versatile DFS ROM available for the BBC model B, the BBC Plus and the Master 128K. Suitable for both 8271 and 1770 Floppy Disc Controller. Double density allows up to 60% increase over conventional format or 640K storage per (80 track double-sided) disc. Extensive features include 40 and 80 track software switch, unlimited filenames in catalogue (as opposed to Acorn 31), automatic Read after Write. It works with Z80, 6502 second processors and Econet and also is very fast on comparative review benchmarks. Built-in commands include FORMAT (F40 and F80), VERIFY, DZAP, MZAP, RECOVER, RESTORE, WORD, RTRACK, WTRACK etc... Also, ENABLE M allows IBM PC discs to be read or written to. Extensive User Manual covers many technical details. Supplied on 16K EPROM.
Normally £15.00 but if order with DDFS or DFDC only £10.00
Please mention computer model when ordering. Order as ROM2.2.



Unbeatable quality 5 and ¼ inch disc drives

Also available are NEC or MITSUBISHI 5 and ¼ inch, 80 track, double-sided drives at a very attractive price. Cased in matching cream colour, all leads. Only £109.00




Free bridge unit for twin drive systems

If you pay for two drives on a single order, we will offer you, absolutely FREE this practical BRIDGE unit. Solid steel construction, suitable for all Models of BBC and Master 128K.

SOLIDISK TECHNOLOGY LIMITED, 17 SWEYNE AVE, SOUTHEND-ON-SEA, ESSEX SS2 6JQ. TEL. SOUTHEND (0702) 354674 (16 lines).


Electron Disc Interface:

This unit (EFS) plugs into the PLUS-1 Expansion and allows connection of a twin disc drive system and a Winchester. The Disc Interface is based on the same WD1770 chip as used on the Beeb.
The Electron Disc Filing System software in ROM (32K) is a version of the Solidisk ADFS 2.1 thus offers a large degree of compatibility with Beeb software. The system is capable of both Beeb DFS format (single and double density) and ADFS format as used on the Acorn PLUS-3.
The unit also has a 16K of Sideways RAM which can be used to load ROM images. The unit is guaranteed for one full year but we warn the users that the built-in Sideways RAM is UNRELIABLE hence the reduced price of only:
..... £50.00.
Use a disc system with built-in power supply unit.




Old Style SWR32 and 128K:

This exceedingly popular system (30,000 plus units sold) enables the Beeb user to load one or two ROM images into the Beeb, make a 16K printer buffer, use DFS with PAGE at &E00, play games, run bigger BASIC, store music and inumerable other uses as supported by a library of 15 software diskettes.
The SWR32 system consists of a BASE UNIT which plugs into the rightmost ROM socket on the BBC board and a (exchangeable) RAM CARD. The RAM CARD also has extension socket for a piggy-back memory board capable of bringing the extra memory to 128K bytes of RAM.
This system is now superseded by the new FOURMEG series and therefore offered at a knock-down price of ONLY £20.00 for a complete unit, excluding software. The 96k add-on piggy-back memory board is also greatly reduced.
Order as SWR32 ..... £20.00
Order as SWR128 (SWR32 with 96K extension) . £50.00
NB: Manual supplied but software (not strictly required) not included.
The supportive software is a series of 15 diskettes, available on either 40 or 80 track DFS diskettes. You can buy any number of VOLUMES although we recommend you buy by PACK of FIVE volumes. PACK 1 (volumes 1 to 5) contains general applications such as MENU, PRINTER, DFS0E00, SILEXICON etc. PACK 2 contains programming applications (SOLIMON, SOLITRACE, TELETEXT EDITOR, SPRITES, DFS and ADFS etc). PACK 3 contains exclusively computer games. Each diskette is priced at only £2.00, software PACK is £10.00 for 5 diskettes.
Order as VOL. XX £2.00
Order as SOFT/PACK 1 or 2 or 3 ..... £10.00



Secondhand Refurbished Beebs:

As a result of the Solidisk MASTERPLAN, we have to dispose regularly of SECONDHAND, refurbished, complete with Double Density DISC INTERFACE, thoroughly checked and fully guaranteed (Labour only) BBC Model B's. Price vary with issues and ages, commencing from £150.00. Please ring for brochure.



In Brief:

The range of Solidisk Add-Ons for the Beeb is quite extensive. For example: TWOMEG-32K . . . £50.00, FOURMEG-32K . . . £70.00, SWR64 with S/W pack 1 . . . £60.00, SWR128 (new style) with S/W pack 1 . . . £80.00, FOURMEG-256K with WORDWISE PLUS . . . £175.00, DDFS (1770) . . . £35.00, DFDC (1770+8271) . . . £40.00, DFS 2.2 ROM . . . £15.00, ADFS 2.1 ROM set . . . £30.00, 3½ inch (80 track double sided) drive . . . £90.00, 5¼ inch drive . . . £109.00, 20MB Winchester with PSU . . . £745.00, Linemaster communication ROM . . . £10.00, Insight intelligent disassembler ROM . . . £15.00, Solimon machine code monitor ROM . . . £10.00, Toolkit ROM . . . £10.00, S/W pack (1 to 3) of 5 discs . . . £10.00, 2764 EPROM . . . £1.00 each, 27128 . . . £3.00, 27256 . . . £6.00, EPROM programmer for 2764/27128 . . . £19.00, EPROM programmer for 27256 . . . £21.00, EPROM Eraser . . . £20.00.

Order Form

ITEM **PRICE**

1) .....

2) .....

3) .....

ADD post and packing £2.00
(£3.00 for disc drive)

TOTAL:

Name .....

Address .....

.....

Access/Visa Account : : : : : : : : : : : : : : : : : : :

Send to:

Solidisk Technology Ltd
17 Sweyne Avenue, Southend-on-Sea
Essex SS2 6JQ

We reserve the right to change prices and specifications without notice for improvement.


SOLIDISK AUTUMN SALE

SOLIDISK SHOP IN ESSEX

System One: COMPACT

A Master COMPACT 128K, two 80-track, double-sided (1.3 MB) 3.5 inch disc drives (a must even for copying ADFS file to another disc), a choice of Mono or Colour monitor, free Solidisk Double Density DFS Master Version ROM to run thousands of BBC programs, free DATABASE and SPELLING CHECKER disc.

As illustrated with Acorn Mono monitor **£598.00**
With Acorn Colour monitor **£749.00**
MP165 printer if bought together **£220.00**



System Three: MASTER 512K with 80186

A MASTER 128K internally upgraded with the 512K-80186 co-processor, twin 1.3 Megabyte disc drives, 20 MB Solidisk Hard Disc and special ADFS/Double Density DFS ROM, GEM and MASTER software packages.

As illustrated (without monitor) **£1600**
With MP165 NLQ printer **£1800**
With Juki 6100 Daisy Wheel printer **£1880**



Pick any of these Four, and you are sure to get every penny's worth. You'll get more than just the lowest ever prices: a flexible trade-in scheme, free telephone support and free software are in the packs."

System Two: MASTER

A fully blown MASTER 128K, twin 80-track, double-sided 1.3 Megabyte Disc Drives in a bridge unit doubling as a monitor stand, free MEGAGAMES, DATABASE and SPELLING CHECKER in 5 discs.

As illustrated (without monitor) **£660.00**
With MP 165 printer, 165 cps, NLQ, EPSON compatible (even the ribbon) **£880.00**



System Four: 520 STM

ATARI slogan is 'Power without the Price'. This is specially true with this 520-STM computer, 16 bit 8MHz-68000 CPU and 512K of RAM, hard disc connector, RS232, Midi interface, printer port and Mouse. The bundled software includes GEM (as on the MASTER 512), word-processor, Basic, Logo and CPM emulator. More information is available on request. Two 80 track, double sided 3.5 inch drives (1.5 Megabytes) complete this system.

As illustrated (without monitor), you use your own TV set **£540.00**
Special price for MP165 NLQ printer and lead **£240.00**
Special low price on 20 MB ATARI ST Hard Disc ..... **POA**



SOLIDISK TECHNOLOGY LIMITED, 17 SWEYNE AVE, SOUTHEND-ON-SEA, ESSEX SS2 6JQ. TEL. SOUTHEND (0702) 354674 (16 lines).

Printers

Code	Description	Price
P101	EPSON LX80 + 2 M printer lead	220.00
P101TF	LX80 Tractor Feed	21.30
P101SF	LX80 Cut Sheet Feeder	53.53
P102	EPSON FX85 NLQ + 2M printer lead	350.00
P102TF	FX85 Tractor Feed	30.59
P102SF	FX85 Cut Sheet Feeder	123.50
P103	MP165 — 165 cps + NLQ + 2M printer lead star buy*	260.00
P103R	Black ribbon for LX80, FX85 and MP165	4.60
P104	JUKI 6100 Daisy Wheel + 2 M printerlead star buy*	340.00
P104R	JUKI 6100 black vinyl printer ribbon	2.30
P105	Panasonic KX-P1080 + 2 M printer lead	165.00
P106	Kaga KP 810 + 2 M printer lead	240.00
P100P	2000 sheets cont. paper, A4 size 11"×9.5"	14.00

Monitors

Code	Description	Price
M101	12" Phillips BM7502 hi-res green screen, BNC lead	85.00
M102	12" Phillips BM7522 amber, BNC lead star buy*	86.00
M103	12" TAXAN Supervision 3, hi-res RGB RGB lead	375.00
M104	12" TAXAN Supervision 2, hi-res RGB RGB lead	315.00
M105	14" Mitsubishi XC1404, RGB lead star buy*	260.00

Diskettes

Code	Description	Price
C100	5¼" low cost VEREX for all drives	12.00
C101	5¼" hi-rel MD557, Verbatim DSDD 96 tpi	25.00
C102	3.5" low cost Verbatim for all drives	20.00
C103	3.5" hi-rel 90097M Verbatim DSDD 135 tpi	28.00
C104	3" CF2/MSOFT for all Amstrad drives	39.00

Acorn Co-processors

Code	Description	Price
C110	Master Turbo	113.00
C111	Master 512K-80186 and software bundle	375.00
C112	32016, 6MHz, 8MHz and 10MHz	POA
C112A	Solidisk ADFS ROM for 6MHz-32016	20.00
C120	M128K Econet Module	46.50

Order form

All prices are inclusive of VAT at 15% but excluding delivery. We reserve the right to change without notice.

: ..... System ..... Price

Add delivery £10.00 per system

TOTAL

Name: .....

Address: .....

.....

.....

Visa/Access .....

Send to:
Solidisk, 17 Sweyne Ave, Southend-on-Sea, Essex SS2 6JQ

"If you have a good working BBC Model B already expanded with Solidisk DFS, or Disc Drives or Sideways RAMs, then this "MASTER PLAN" is designed for you"


The Solidisk MASTERPLAN is specifically set up to reduce financial burdens to all Solidisk loyal customers, as much as possible.
Fill in carefully the coupon below and send it to us. We will immediately send you a personalized quotation for upgrading your BBC B to the Master which we are sure you will find really hard to refuse . . .

MASTERPLAN COUPON

Please tell us about your BBC Computer:
1) Issue and Age .....
2)Upgrades fitted inside:
a) .....date .....by .....
b) .....date .....by .....
c) .....date .....by .....
d) .....date .....by .....
3) Service history:
a) has never gone wrong (tick box) : :
b) Serviced as follows:
: .....
: .....
: .....

Please fill in your name and address using the order form printed opposite. Send the complete Order Form — Masterplan Reply coupon to Solidisk. Allow 3 working days for your quotation.

Come and See Us



We are open 9-5.30 PM, Monday to Friday. Our Telephone Number is: Southend-on-Sea

SOUTHEND (0702) 354 674

COMPUTERS AT X

Announcing a Great New Deal for all Primary and Secondary Schools

INTRODUCING

LINEAR GRAPHICS EDUCATIONAL SUPPORT SCHEME


SUBSTANTIAL REDUCTIONS ON ALL PLOTTERS

Plotmate is recognised by many educationalists as one of the most sophisticated and practical plotters available at its price.

Now Primary and Secondary schools throughout the UK can reap the many benefits obtained by using PLOTMATE as an aid to computer based teaching at a cost which is lower than ever before.

This tremendous offer comes about as a result of the unique LINEAR GRAPHICS' EDUCATION SUPPORT SCHEME (ESS).

ESS has been devised and launched by Linear Graphics in order to provide the educational environment with the best possible value for money when purchasing this highly versatile extension to their computer graphics systems.



Under the ESS the following features become available:

- **SAVINGS of up to 30% on normal prices**
- **FREE training available.**
- **SUBSTANTIAL discount on all Linear Graphics Software packages**
- **FULL support and service from the manufacturer.**
- **TWELVE months warranty.**

COMPARE THESE PRICES!

PLOTMATE A4	**£224**	a saving of **25%**
PLOTMATE A4M	**£299**	a saving of **25%**
PLOTMATE A3 (with free Cadlink Disk and Plotmate ROM)	**£299**	a saving of **30%**
PLOTMATE A3M	**£426**	a saving of **25%**
SCANNER	**£120**	a saving of **20%**
UPGRADE KIT A3 TO A3M	**£150**	

PLUS save 20%-25% on all plotting accessories.

All prices are ex VAT.

ESS HOTLINE
For immediate attention and further information on ESS call
0702 541663/4/5

PLOTMATE Graphics Plotters are British manufactured products and approved by ILEA.

PLOTMATE

LINEAR GRAPHICS LTD

28 Purdeys Way Rochford Essex SS4 1NE
Tel 0702 541663/4/5 Telex 995701

Please rush me information on Linear Graphics' Educational Support Scheme. I am particularly interested in (please indicate).

NAME_____

POSITION_____

SCHOOL/AUTHORITY_____

ADDRESS_____

TELEPHONE_____ MU12

EDUCATION MICRO USER

New Masters in the classroom

Philip Andrews assesses the potential of the Compact

ONLY months after the BBC Master was launched, the new Master Compact has arrived, advertised as a machine suitable for home or school use. A review appeared in the October edition of *The Micro User* and the concensus was that it is a super machine.

The Master Compact has some advantages over the Master for use as a general educational computer. But I do believe that Acorn has produced another Electron – a design that is so nearly right but misses the mark by just enough to make the machine unacceptable for classroom use.

First let's look at the differences between the 128k Master and the Compact which could affect its use in school.

- It comes complete with single 80 track double-sided 3.5in disc drive. The discs for this are much more robust than their 5.25in floppy equivalents. Also they can store 640k of data whereas a standard 40 track DFS disc will only hold 100k. (A 5.25in 80 track disc can also store 640k in ADFS format.) The price – just over twice that of 5.25in discs – should reduce with popularity, especially now that IBM has gone over to this size for its desktop computers. A useful feature of the 3.5in disc is that it has a sliding plastic switch instead of the dreadful write-protect sticker. My only problem is that I can never remember which way the switch should be set. Why on earth can't this information be moulded in the plastic of the disc itself?
- The Compact only has the ADFS, although Acorn says that it will supply the standard DFS as an extra rom. The ADFS takes a little more understanding than a normal DFS system, especially when requiring data discs for a word processor or database. But the advantage of the ADFS is that far more files can be held on a disc and it will store over six times as much information as a normal 40 track BBC Micro disc.
- The printer socket is different but this is a nuisance rather than a serious problem, needing another cable.
- The keyboard has changed. It is now concave and of a membrane type, the feel being somewhat different although not unpleasant. The @ key is now above the 0, and a new function on this key enables extra symbols to be obtained more easily. This could be useful for special symbols and the characters required in modern languages.
- No user or analog port, Tube or 1MHz bus are fitted. These are seldom used in school, but the lack of a user port may cause problems because devices such as the Concept keyboard use it. There is an expansion port on the side of the Compact, and already add-ons are available for it.
- A new Atari-style joystick/mouse port has been fitted, giving PB0-PB4, CB1 and CB2, and +5 volt lines which are equivalent to part of the user port. The use of a mouse or other input device with this new port together with the WIMPs could reduce the usefulness of the Concept keyboard. For example, instead of using the Concept keyboard with a list of words the child can press, the mouse could be used to point to them on the screen. This would be much cheaper and allow much greater flexibility.
- There is no low voltage power socket, which means that devices such as a standard Jessop turtle requiring a power take off point will not work without modification.
- It should be possible to connect a standard

→



Poynders Gardens Estate ... the reality belies the name

Computer project is fighting crime

A BBC Micro is being used as the key weapon in the fight against juvenile crime on one of London's most notorious housing estates.

On the boundary of Brixton, the Poynders Gardens Estate has such a violent reputation that the police's shock troops – the Special Patrol Group – had to be called in to deal with the local villains.

Now the streets are becoming safer thanks to a computer project being run by the local Anglican church.

For Arthur McBryan, the community worker at St. Stephen's Parish Church, has persuaded some of the tough tearaways to get to grips with the BBC Micro.

Donated by a member of the parish, the machine is opening up new horizons for the youngsters.

And it is helping to solve a problem which is estimated to

→

affect close to 50 per cent of all the area's children – illiteracy.


A survey has shown that some 30 per cent are semi-literate and a further 20 per cent are totally unable to read and write. "We know of one whole family – a mother, father and four children – who fall into this category", said Arthur McBryan. "From this situation is born a real sense of frustration. And frustration in the case of youngsters can often lead to violence".

The community worker is well aware of how a locality can degenerate as a result of crime.

He spent some time looking after sick hippies in Afghanistan before returning to the UK to run a drug rehabilitation centre.

However the Poynders Gardens Estate was to prove an eye opener even for him.

Built shortly before the Second World War, it is now a



Arthur McBryan points the way for a willing pupil

nightmare maze of blocks of depressing flats.

Racial tension has become rife in recent years as the percentage of black families has increased.

The police have made themselves unpopular by maintaining a high profile in order to stamp out drug taking.

Faced with it becoming a no-man's land, the church decided to act.

"The estate was deteriorating so rapidly that we had to do something fast", said McBryan. "And fortunately the BBC Micro has provided us with at least part of the answer".

Why has the machine had such an impact in the church project, when computers in the local schools have apparently failed?

"First of all the kids around here play truant so regularly that

From Page 31

5.25in disc drive into the disc socket of the Compact, although the connector is different to the Master's IDC socket. Usefully, both connections have the same function and are in the same order as the IDC socket, so it is possible to clamp a 25 way D-type connector on to a standard disc drive cable. It will then plug directly into a Compact and can still be used with other BBC Micros. A similar ruse can be used with the printer cable.

- There are no cartridge sockets on the Compact but this is no great loss because, at the time of writing, these cartridges have only just become available and have not yet really been exploited. On the Compact there are four spare rom sockets. This is about as many as you would really need, especially with all the sideways ram available, software for this being saved on disc and quickly loaded.
- The Compact comes with more educationally useful software than does the Master: Desk Top, Timpaint, Logotron Logo, View, ABC and a range of utilities and demonstrations. The desktop contains a clock, card index and calculator, all using WIMPs. There are also sprite and PWFS roms which I suspect are connected with the WIMPs. Once Acorn documents these roms they should become a familiar sight on the Compact.
- A useful feature is the built-in ADFS disc formatter. On the Master this is only available on the Welcome disc.
- The WIMPs supplied with the Compact will not work on the Master because of the organisation of the CMOS ram. This could cause compatibility problems for software designed for both.
- The Compact has less components than the Master and few of them are socketed so the computer should be very reliable. Shorting the power supply connector produces a nice clicking noise from the power supply, so it is clearly protected against such misuse. The one part which I am sure will cause reliability problems is the power socket on the circuit board. This type of socket is not noted for its robustness and can easily be damaged by misuse. These sockets have a maximum rating of 2 amps which the Compact keyboard unit is stated to use.
- The Master Compact is about £70 cheaper than a Master together with a 40 track disc drive.

These differences on balance favour the Master Compact, but the most critical problem for schools is the different disc format. The lack of a DFS and the change in disc size mean that schools would have to live with both formats together which would cause tremendous problems. To convert programs from a BBC Micro to the Compact they must first be converted to ADFS format and the easiest way to do this is with a Master. The disc formats can be converted using the Copyfiles utility on the Master Welcome disc if a hybrid twin disc drive is available. It should be possible to copy any unprotected disc and I suspect that most programs that will run on the Master will run quite happily on the Compact.

This is certainly not a job most schools will want to undertake as they would need a Master and a hybrid disc drive. Perhaps these are items that could be made available in teachers' centres, where the discs could be taken for conversion. But this becomes inconvenient if not impossible when you want to take data files and use them on either format. The only other solution, equally unacceptable, is for schools to buy software in both formats. I believe advising schools to buy the Master Compact instead of a Master will lead to many problems, unless the school is able to identify a use for it quite separate from any other computer activities undertaken.

Acorn believes it has a captive market in education, and up to now it had. LEAs have never had much support from Acorn in any direction so that more and more are beginning to wonder whether a change of machine is perhaps advisable.

I would suggest, for both education's and Acorn's sake, they start supporting those who have supported them so loyally for the last 5 years, and start to sell a different version of the Compact for schools with the following changes:

- Supply just the keyboard together with a Master or BBC Micro power supply packaged on its own. This would give the auxiliary power output to run a disc drive and so on. The keyboard contains the full computer with a mouse, printer and disc drive socket, so this would involve no redesign work by Acorn.
- Fit a DFS rom as well as an ADFS and supply the Compact software on a 5.25in ADFS disc.

I estimate that the price of this machine could be well under £300 to schools if some of the dealer discount is passed on to LEAs. This is then about £100 cheaper than a Master, and a complete system would cost under £500. Schools would be free to use whichever disc drive they wanted, 3.5in or 5.25in. Indeed with a switchable 80 track 5.25in disc drive you would have all the capabilities of the Compact's disc system.

Also, what happens when the existing BBC Micros reach the end of their useful life? Many schools may have just bought a disc drive or monitor and would expect either or both to outlive the computer. Thus replacement costs for a school could be spread out over the years instead of having a large single outlay.

With such a machine on the market I suspect that the low cost and the useful software supplied with it would greatly increase sales. Once sufficient machines have been sold I believe that writers will start designing software that makes the best use of some of the new features to be found on the Master and Compact. You would then have a machine which should satisfy the needs for a basic educational computer for several years to come, and continue to provide the stability in educational computing that is essential for the effective integration of computers into the classroom.

Christmas Crackers

These are just the kind of crackers any BBC Micro user would love to find in his Christmas stocking – packed with party games that make full use of the computer's power!

And all for just £6.95 (tape), £9.95 (5¼" disc) or £11.95 (3" disc).


It's the best buy you'll make this Christmas!

6 GREAT GAMES


Pull the Cracker. *Just like the real thing – and there's even a prize at the end.*
Jet Set Santa. *Guide him on his jet pack to collect and deliver the presents.*
Snowplough. *Clear the snow – but watch out for dangerous rocks and flying snowballs.*
Snap. *Colourful family fun in this seasonal variation of an old favourite.*
Name the Carol. *Quick-fire answers win the game. Or you can just listen to the music.*
Candle Light. *A classic game updated in this "light the Christmas tree" challenge.*







Put some sparkle into your Christmas!




TO ORDER TURN TO THE FORM ON PAGE 167

AT LAST A BRIGHT IDEA IN COMPUTER WORKSTATIONS

For only £79.50.





FREE with every workstation ordered this Plug/Tidy basket will accommodate a 4 socket in-line distribution block.

The Klick colourframe workstation is designed to provide a highly efficient way of organising your micro system. This fully mobile unit runs on silent glide rubber tyred wheels and is ideal for use in the domestic or office environment.

Manufactured from heavy duty steel, the framework is finished in a choice of 5 stylish colours and the high quality melamine faced chipboard shelves are available in either White or Teak effect.

This unit will accommodate your monitor, computer, printer, disk drive or cassette recorder and is suitable for use with most leading micro systems including Amstrad, BBC Acorn, Commodore and Sinclair.

This offer is available to UK Mainland residents only.

Buttercup Yellow

Leaf Green

Marine Blue

Mahogany Brown

Overall assembled dimensions are: 845mm (33¼") high, 810mm (31⅞") wide and 610mm (24") deep.

To Store Stock Systems Ltd, FREEPOST Manchester M23 9BH

Please send me _____ (quantity) of units at £79.50 inc. VAT & carriage

I enclose a cheque for £_____ made payable to Store Stock Systems Ltd or debit my ACCESS/VISA

Card No. | | | | | | | | | | | | | | | |

Card expiry date_____ Signature_____

Name_____

Address_____

_____ Postcode_____

(BLOCK LETTERS PLEASE)

Please write the number of units required in the boxes provided

Frame colour	Shelf colour	
	White	Teak
Poppy Red		
Buttercup Yellow		
Leaf Green		
Marine Blue		
Mahogany Brown		

M1

Klick

ADDING COLOUR TO COMPUTER FURNITURE

Access VISA

(Please allow 28 days for delivery)

they are unlikely to have come face to face with the classroom micro on a regular basis", claims the community worker.

"And we offer a friendly environment where many local teachers adopt the hard line tactics of clipping kids round the ear".

Though the church project has been considered a success to date – "The police tell us it is safer around here" – McBryan is concerned that lack of software will cause them to lose the initiative, for they are having to rely entirely on donations from sympathetic organisations.

"We can't get any help from the ILEA because they insist the club should be covered by insurance", says McBryan, and even if we could get it round here – which is doubtful – we couldn't afford it.

"So we are desperately in need of entertaining programs that offer basic inttroductions to reading and writing".

Companies or individuals who wish to help should contact Arthur McBryan at 252 Poynders Gardens, Clapham Park, London SW4 8PQ.

Toolbox on rom

SCHOOLS will welcome the Econet compatible rom versions of Toolbox 1 and 2. Offering the most useful routines from each, they will be released by BBC Enterprises early next year.

Routines include the symbolic disassembler, single step monitor, relocator, and Basic bad program fix.

The Basic utilities work across the Tube and the roms are compatible with all BBC Micros including the Master series.

The roms will cost about £12.95 each.

Assembler instruction on-line

BBC Telesoftware has announced a major new feature for BBC Micro users wishing to venture into assembly language and machine code programming.

Starting the second week in January, BBC Micro owners

Testing, testing, 1×2×3

By PETER DAVIDSON

HOW often have you been busy and your child or a pupil in your class has asked you to test him or her on some recently learnt topic?

This program aims to test children on their tables, giving the time taken, to add a challenge to those who already know them and just want to become more proficient.

Before the test starts you will be asked whether you want the questions in numerical order or mixed up. By opting for questions in numerical order you can learn your tables by adding to the last answer, while random questions give you the chance to prove that the tables have been thoroughly learnt.

Each response is marked with a tick or cross and when the test has been completed you can have the correct answers printed alongside yours, allowing you to see where you went wrong.

Now just type in the program and see how well you know your tables.

```
  10 REM TABLES TEST
  20 REM By Peter Davidson
  30 REM (c) The Micro User
  40 ONERROR IF ERR=17 RUN ELSE MODE
7:REPORT:PRINTERL:END
  50 DIMN(13)
  60 MODE7:PRINT:S=0
  70 PRINTSPC(10);:PROCprword("TABLE
S TEST"):PRINT'''
  80 VDU28,0,24,39,3
  90 PROCprword("What is your name?
"):PROCinput:PRINT'''':name$=word$
 100 PROCprword("Hello "+name$):PRIN
T'''
 110 PROCprword("Do you want your ta
bles in order or"):PRINT'':PROCprword
("mixed up? PRESS O or M ")
 120 C$=GET$:IFC$<>"O"ANDC$<>"o"ANDC
$<>"M"ANDC$<"m"THEN120
 130 PROCprword(C$)
 140 IFC$="M"ORC$="m" C=1 ELSE C=0
 150 PRINT'''':PROCprword("Which tabl
e (0 - 12)? "):PROCinput:table=VALwor
d$:IFtable<0 OR table>12 THEN VDU11,1
1,11,7:GOTO150
 160 CLS
 170 FORI=0TO12:N(I)=I:NEXT
 180 TIME=0
 190 FORquesloop=0 TO 12
 200 IFC=0 THEN ques=quesloop ELSE r
nd=RND(13-quesloop)-1:ques=N(rnd):FOR
I=rnd TO 11-quesloop:N(I)=N(I+1):NEXT
 210 PRINTTAB(3,1);:PROCprword(CHR$(
RND(7)+128)+STR$(ques)+" X "+STR$(tab
le)+" = "):PROCinput
 220 PRINTTAB(3,1);:PROCprword(STRIN
G$(20," "))
 230 answer=VAL(word$):IFanswer=ques
*table THEN S=S+1:M$=CHR$130+"/" ELSE
 M$=CHR$129+"x"+CHR$7
 240 PRINTTAB(24,ques+3)CHR$(RND(7)+
128)STR$(ques)" X "STR$(table)" = "ST
R$(answer)TAB(38,ques+3)M$
 250 NEXT
 260 PRINTTAB(0,17);:PROCprword(name
$+", you got "+STR$(S)+" out of 13.")
 270 PRINTTAB(0,20);:PROCprword("You
 took "+STR$((TIME DIV 6000))+" minut
es "+STR$((TIME DIV 100)MOD 60)+" sec
onds.")
 280 PRINTTAB(0,8)CHR$134CHR$136"Pre
ss Space for"CHR$137SPC5'CHR$134CHR$1
36"another go."CHR$137SPC(5)''CHR$133
CHR$136"Press C for correct"CHR$137'C
HR$133CHR$136"answers."CHR$137:REPEAT
 reply=GET: UNTIL reply=32 OR (reply
OR 32)=99
 290 IF(reply OR 32)=67 FORques=0 TO
 12:PRINTTAB(0,ques+3)SPC(5)CHR$(RND(
7)+128)STR$(ques)" X "STR$(table)" =
"STR$(ques*table)SPC(5):NEXT:PRINTTAB
(2,1)CHR$133CHR$136"Press Space for a
nother go."CHR$137:REPEAT reply=GET:
UNTIL reply=32
 300 RUN
 310 DEFPROCinput
 320 word$=""
 330 REPEAT
 340 letter$=GET$
 350 word$=word$+letter$
 360 IFASCword$=13 word$="":letter$=
"":GOTO390
 370 PROCprlet(letter$)
 380 IF ASCletter$=127 AND LEN(word$
)>0 THEN word$=LEFT$(word$,(LEN(word$
)-2))
 390 UNTILletter$=CHR$13
 400 word$=LEFT$(word$,(LEN(word$)-1))
 410 ENDPROC
 420 DEFPROCprlet(letter$)
 430 IFASCletter$=127 AND LEN(word$)
>1 VDU8,32,8,10,32,8,11 ELSE IFASClet
ter$<>127 PRINTletter$CHR$8CHR$10lett
er$CHR$11;
 440 ENDPROC
 450 DEFPROCprword(word$)
 460 rnd=RND(6)+127
 470 PROCprlet(CHR$141):PROCprlet(CH
R$rnd)
 480 FORI=1TOLEN(word$):PROCprlet(MI
D$(word$,I,1)):NEXT
 490 ENDPROC
```

Mass Data Storage


-The Complete Solution

With more experience than any other company in the provision of hard disc storage for BBC users, Amcom can supply a range of ADFS compatible winchester drives, second to none.

With storage capacities of up to 600 megabytes, Amcom winchesters are designed for use in demanding environments like schools, colleges, and universities as well as for industrial applications.

Connection of an Amcom winchester couldn't be simpler as it connects directly to the 1MHz bus socket of the computer by a 34-way cable. Plug in, switch on, and that's all there is to it.

Used in conjunction with or to replace conventional floppy disc drives, Amcom hard disc systems are totally compatible with all ADFS software as well as the BBC Master Series computers.



Amcom for the complete mass-storage solution.

Amcom

For further information on Winchester hard discs, Educational Networking Systems or Tapestreamers, contact:

Amcom Software Ltd. 35, Carters Lane, Kiln Farm,
Milton Keynes. MK11 3HL. Telephone (0908) 569212

Canals program tends to spring a leak

Program: Canal Builder
Price: £12
Supplier: AVP Computing, Hocker Hill House, Chepstow, Gwent NP6 5ER.
Tel: 02912 5439

THE idea behind Canal Builder is excellent. You have to construct a canal between Xchester, a large industrial town, and Yboro, a market town, as profitably as possible.

To complicate matters there's an existing road network, a coal mine to service and a quarry that, once reached, supplies cheap building materials for the rest of your canal.

There's also a large hill between the two towns, shown in contours. You have to decide whether to tackle this via locks or tunnels, with varying costs.

To help defray this expenditure there's the traffic the canal carries between the towns, mines, quarries and a bordering farming area. The route you take is up to you, though you must bear in mind the economics of the situation. It comes to a trade-off, cost of construction versus revenue from traffic.

All in all, an intriguing simulation you may think, with lots of spin-offs for economic history and geography studies. However Canal Builder is flawed. For a start, it's restricted to only one case. Each time you run it you are presented with the same situation. There is no scope for pupils to apply the strategies they've learned to new situations. Arcade games can have multiple screens, so why not educational programs?

And there's a distinct lack of analysis of the results. I managed to get knighted after making a substantial profit, but was unsure as to how exactly I made it. The accompanying rather sparse teachers' notes don't illuminate much, either.

Another drawback is that the ideal solution seems to be programmed in. You can construct branch canals quite safely provided you're sticking to the obvious solutions. Creative deviation soon has the program worried, though. In fact the implementation of the program leaves a lot to be desired. You build your canal by steering it via the cursor keys, a far from friendly procedure. Rubber banding or use of the joystick would be far better.

In addition colours are used rather poorly. For instance, each contour is in a different colour, for no good reason. It would probably have been better to write the program in Mode 1 rather than Mode 2 as at present. The on-screen prompts would certainly have been far tidier that way.

Also construction of bridges and canal basins is a sloppy procedure. You can find yourself blocked from further progress for no reason other than, frankly, amateurish programming.

Canal Builder is a good idea, and could be used by skilled teachers as an initial stimulus to related work. However the realisation of the idea is rather limited, both educationally and practically.

Verdict: Could do better.

Michael Noels

INVALUABLE AID FOR SERVO SYSTEM USE

Program: Codas
Price: £190
Supplier: Golten and Verwer Partners, 33 Moseley Road, Cheadle Hulme, Cheshire SK8 5HJ
Tel: 061-485 8435

CODAS stands for Control System Design and Simulation and is not one, but a suite of programs for the simulation of servo systems. This package will deal with the single input/output systems most commonly found.

Conventionally the treatment of this subject is very heavily mathematical and consequently is considered a difficult topic. However, understanding its principles should be considerably easier with the aid of this package.

Unfortunately I cannot describe all the features of a control system in this review – I doubt that I could if they gave me the whole magazine. But for those of you who have not come across feedback control systems before let me give you a simple example.

Suppose you wanted to move a TV aerial with a motor to point at another station. To get some idea of where the aerial is pointing you would attach a potentiometer to the aerial shaft. Therefore the resistance would be proportional to position.

A simple control scheme might be to drive the motor at full speed until the desired direction is achieved and then turn it off. However, what would happen is that due to the momentum of the aerial it would

→

with a teletext adapter will be able to receive – free of charge – a series called Osbits which is designed to help people master the micro's built-in assembler.

The series of 26 parts aims to provide an introduction to machine code programming and the machine's operating system.

Each part will be accompanied by associated software, available for downloading at any time during the week of transmission.

Osbits goes beyond most course work by dealing with interrupts, events, vector interception, sideways roms and floating point arithmetic.

The series is intended to perform as a guide rather than a teacher in leading users through machine level programming.

Telesoftware is broadcast using the normal teletext service, and can be found on BBC2 Ceefax starting on page 700.

Language programs

NEW software from BBC Enterprises includes two language learning programs.

A Vous La France is a complete introductory package for French language learning.

No prior knowledge is assumed and the level achieved after using all the material is a workable conversational ability – about fourth-year O-level standard.

The software can be used in conjunction with the A Vous La France book and audio cassettes, with other French teaching materials or alone. Although designed for adults it is suitable for children from about 11 years of age.

The 45 programs in the package offer a variety of interesting ways to improve the user's French grammar and vocabulary.

Proven educational methods such as cloze testing (for missing words and letters), diagrams and sentence build-up are included, together with new approaches like street map reading with graphics, clock reading, a phrases fruit machine and even an adventure game.

The package runs on the BBC Micro, BBC B Plus, Master 128 and Electron. It is supplied on cassette, unprotected, with full instructions for transfer to disc.

→

When transferred the package occupies six 40-track discs. The software will also work on Econet. Price £19.95.

Deutsch Direkt! specialises in German vocabulary. It can be used with the Deutsch Direkt! course book and audio cassettes, other German teaching material or alone.

Suitable for adults and children from 12 years of age, the software consists of five activities, each of which can be used with any group of words in the disc dictionary provided.

There are two practice activities where the user works through the words, paying particular attention to capital letters, special characters and umlauts.

Three game-type exercises provide further stimulation to learn.

Included is a manual and an audio cassette containing pronunciations of every word in the dictionary.

The software comes on 5.25in 40/80 track disc and will work on the BBC Micro, BBC B Plus, Master 128 and Econet. Price £22.95.

From the same source comes Figures of Fun, a compilation of BBC Soft's educational packs for primary age children – Maths With A Story, 1 & 2 and Number Games.

There are 14 learning games on the 3.5in disc which comes with a manual and costs £19.95.

Electronic papers

ELECTRONIC publishing has become a major focus for the activities of Lincolnshire's microelectronics education development unit.

The central concept is that two "competing" papers are produced with real news in real time, and with a heavy reliance on electronic media.

The papers are staffed by equal numbers of pupils and teachers and served by a number of small "agencies" which are small scale simulations in their own right.

At the core is the news agency which draws its information from a variety of sources. Other agencies provide pictures and generate advertisements.

The latest MEDU newspaper project is using a remote news

From Page 37

overshoot and be pointing slightly too far round. The motor would then set off in the other direction in order to achieve the desired direction and would overshoot again and this constant oscillation would continue.


What is needed is some system that slows down the motor as the correct position is approached then there would be no oscillation and the system would work as rapidly as possible. You don't have to build a system like this to see how it will behave. You can model its behaviour precisely with mathematics, and this is known as a control or servo system.

A system is described by an overall gain constant and its transfer function. This is represented in complex number form as a polynomial or "pole/zero" pair. If some part of the output to the system is fed back into the input we say we have a closed loop system, otherwise we have an open loop system.

If we suddenly disturb the system it will respond in a certain way known as the transient response. There is also a response to constant signals known as the frequency response. It is also important that we know how stable a system is so that it will not break out into wild oscillations.

The package consists of several programs that share a common data file. A description of the system can be typed in using free form input and is easily edited. You can draw the transient response of the open or closed loop system. The root locus can be found using the branch following method and finally the frequency response can be plotted as a Niquist diagram or a Bode gain and phase plot.

It is possible to obtain a screen dump of all



Response of a suspension system to a sudden shock

plots on an Epson printer. A useful feature for those who own some other make of printer is that the machine code program to do the dumping is held in a file which can be simply substituted by one of your own.

I must admit that my control theory was a little rusty as I hadn't touched any since I took my degree, but on using this package it all came flooding back. I was able to set up a system and look at the gain margin, step response and even the effects of adding compensators. The band width and transport delay were also easily gleaned.

It is very heartening to see the BBC Micro attracting this calibre of software. It was easy to use and did what you wanted. It is not a teaching package as such but an invaluable aid to anyone learning about or using servo control systems. Its price might rule it out for individuals to purchase but I would strongly advise that all those institutions involved in teaching control systems take a very close look at it.

You will not be disappointed.

Mike Cook

Stimulating simulation

Program: Raft Away River
Price: £19.95 (disc)
Supplier: John Wiley and Sons, Baffins Lane, Chichester, West Sussex PO19 1UD
Tel: 0243 784531

RAFT-AWAY RIVER is an adventure simulation game for two to six players, designed to improve communication skills and encourage cooperative behaviour, careful planning and problem solving within a group. It also involves reading comprehension and the interpretation of pictorial information.

Initially the players are stranded on the west bank of a river in a remote wilderness area after a boating calamity. To reach safety they must build a raft. Unfortunately, there is insufficient timber on the west bank, so they must find some means of getting to the forest on the other river bank. They are constantly threatened by hunger, illness and floods.

Each player types in his name and is given two tools from the four available, a fishing line, rope, matches and an axe. For example, one may get matches and an axe while another gets a fishing line and rope. This obviously affects the work they can perform. They have a range of jobs in common, but one of them can light fires and chop wood while the other can fish for food and build a bridge or raft. These restrictions make cooperation essential if they are to succeed in their task.

The on-screen map is effective and colourful. Each child is represented by a stick figure which moves between the locations as instructed. Players are named in turn and told where they are and what they are carrying. They choose from 21 single key entry action commands which are set out clearly on the back of the student's guide. For example, pressing Q will print "Put wood from the pile on to the fire". If they are in the wrong place or have the wrong tools to carry out a chosen action the computer informs them of their mistake and they miss their go.

The guides set the scene and stimulate the imagination, though the operating instructions looked cluttered. Nevertheless this is excellent software that certainly achieves its aims and is ideal for a wide range of ages and abilities. Most eight-year-olds succeeded at the easy level in about an hour, but a group of adults found the very difficult level to be almost impossible. Thoroughly recommended.

Jim McHugh

THE MICRO USER MAIL ORDER OFFERS

Learning CAN be fun

- **Use your BBC Micro to teach and amuse your children at the same time.**
- **Three packages crammed full of educational programs – and so easy to use!**
- **Each program has been educationally approved after extensive testing in the classroom.**


Reduced prices!
£3.95 tape
£4.95 5¼" disc
£6.95 3" disc



B+ ✓
M ✗

Ages 2-5

Alphabet
Colours
Counting
House
Magic Garden
Matchmaker
Numbers
Pelican
Seaside
Snap




PELICAN
Teach your children to cross the road safely at a Pelican crossing



HOUSE
Select the colours to draw a house – hours of creative entertainment

Ages 5-8

Balance
Castle
Derrick
Fred's Words
Hilo
Maths Test
Mouser
Number Signs
Seawall
Super Spell




NUMBER SIGNS
Provide the correct arithmetic sign and aim to score ten out of ten



BALANCE
Learn maths the fun way. Type in the answer to balance the scales

Ages 8-12

Anagram
Codebreaker
Dog Duck Corn
Guessing
Hangman
Maths Hike
Nim
Odd Man Out
Pelmanism
Towers of Hanoi



HANGMAN
Improve your child's spelling with this fun version of the popular game



ODD MAN OUT
Find the word that does not fit – before your time runs out

TO ORDER TURN TO THE FORM ON PAGE 167

agency provided by TTNS from London.

This draws news from The Times computer, World Reporter and special correspondents in Australia, Austria and the USA.

Material is sent by electronic mail to the Lincoln "agency" and processed there by the two newspapers.

A "technology bus" sponsored by local firms is acting as a mobile public opinion agency, conducting polls in Lincoln on behalf of the newspapers.

Results of these vox populi exercises are relayed via modem to the "editorial offices" of the papers.

Linear Graphics has provided the project with a Plotmate plotter with scanner and some pages are being faxed and sent to London and Australia.

Curriculum development officer and simulation organiser Derek Maxted told *The Micro User:* "We are planning a joint simulation next March involving four schools in Gainsborough, with the bus as news agency and a repeat of the TTNS exercise.

"Also a joint simulation between several regional computer centres in the summer, and an intercontinental exercise later in the year".

Lincolnshire MEDU provides in-service training, back-up support and implementation of government funded initiatives for educational establishments in the county.

The technology bus provides mobile in-service facilities for information technology and control design and technology.

Apart from regular courses for teachers, MEDU is developing primary "host schools" – 15 local in-service training centres, each serving a small cluster of schools.

And it produces a county-wide educational computing magazine called Micro Lincs.

Classic releases

A NEW range of text adventures based on classic novels is to be released for the BBC Micro by Riverdale Software.

The first is a version of Charles Dickens' A Christmas Carol in which the player takes the part of Scrooge.

The second is another Dickens favourite Oliver Twist, and again the player takes the

Pictures worth a thousand words

Mike Cannon looks at a promising new video digitiser

THE Watford Beeb Video Digitiser is another challenge to the creative computer user. It consists of a neat, lightweight grey plastic box measuring only 140 × 100 × 50mm.

The top face has two switches, one to select the graphics mode (the digitiser will only function in Modes 0, 1 or 2), and the other – an auto/manual switch – to adjust the black and white levels.

The unit has a connecting ribbon which fits into the user port. Unless you have a lot of peripherals drawing power from the computer you should not experience overloading problems. It is important that the plug is inserted the right way.

The video signal is fed through a BNC connector at the back of the digitiser and can come from a camera, videotape or television receiver. Clear connecting details are given in the accompanying leaflet and should cause no problems. The cable has to be bought separately and it is worthwhile spending extra to ensure that you get a good quality, well-shielded lead.

A normal sideways rom is also supplied, together with a slim operating manual which is adequate for most users. All the essential software is included on this rom and is accessed using star commands.

A useful one is *IMSAVE which saves the screen image to disc in compacted form, enabling you to store more pictures on one disc than would normally be possible. Remember though that you will need the digitiser rom installed to reload a screen saved in this way.


Other commands include ones to obtain the image from the digitiser, and to dump screens to various printers. A short Basic program is useful to tie these commands together, and examples are given in the manual.

Of course, once the display is on the screen it is held in memory and can be controlled using ordinary Basic commands quite independently of the rom software.

It is this flexibility of use which I feel makes the digitiser such a potentially powerful tool for creating graphics for self-produced magazines, newsletters or anything requiring a distinctive image. I wondered about the possibility of producing a personalised sports achievement certificate complete with a picture of the record-breaker.

At Levenshulme High School for girls, Manchester, the Watford Digitiser created a great deal of interest among staff and children. It was quite simple to use and producing a good image in poorish light conditions was achieved with ease when using our portable videocamera, the Panasonic A2.

We tried using a videotape as the input to the digitiser and the quality of the pictures



obtained was good despite the warnings in the manual. We obtained similar results using the video recorder's tuner on all channels.

Mode 0 seemed the easiest to control and predict the quality of the printout from the image on the screen. There was a little difficulty with the smaller image obtained on the printout compared with the picture size on the screen but in all cases the quality of the printout was better than that of the picture on-screen.

Just as important, recovering saved images at a later date was a simple independent operation.

As with many screen dumps, the physical operation of printing out the images produced with the digitiser is very wearing on the printer ribbon and excessive use may take the unit outside the normal budget of the ordinary classroom teacher.

Dumping images to the printer took considerably longer than would be acceptable if, for example, it was used during a normal 35 minute lesson.

Some school subjects might only have one teaching period per week so the whole impact of a lesson might be lost if the material was processed after the lesson and examined next time the class met.

The manual, which appeared to have been compiled by a technical writer, was alright for people who were familiar with computers and the language style of computer handbooks, but the kind of teacher who might want to use the digitiser would be unlikely to come from that background.

Watford needs to produce a much more detailed instruction booklet containing plenty of example programs and possibly a series of exercises to help the user familiarise himself with the equipment. Ideally these exercises should be available on tape or disc.

Examples of such use might include extra-curricular activities, perhaps connected with use of the video camera in art, processing diagrams and so on. It could also be used in school or class magazines or work sheets, or as an optional module of instruction within a wider course such as drama or information technology.

The advent of GCSE and the present intensive pressure on schools to adopt a modular approach to the curriculum give enterprising firms the opportunity to produce and present modules which use various items of their equipment with special emphasis on its vocational use.

The digitiser would form an ideal part of such a module involving exercises in the organisation and setting up of the equipment together with examples taken from a vocational background in which the equipment is used in real life.

The real versatility of the digitiser becomes apparent when it is teamed up with packages such as Mirrorsoft's Fleet Street Editor or AMX Pagemaker. More advanced micro users are recommended to examine the pack consisting of Pagemaker and digitiser which is very properly called Magazine Maker.

It is clear that an effort has been made to present the unit in a helpful way. However, the technically inept – though curious – teacher would soon become disinterested and the ordinary classroom teacher would not even attempt to unravel the mysteries.

I anticipate that these teachers could feel that in buying the digitiser the school had not got value for money. This would be sad because it is not the case.

The digitiser is an excellent product with wide appeal but it is let down by an inadequate manual. If Watford can rectify this it will have a product which would make an important contribution to any school resource room. ■

Product: Beeb Video Digitiser
Price: £110
Supplier: Watford Electronics, Jessa House, 250 Lower High Street, Watford
Tel: 0923 37774



part of the main character.

Because of the length of the adventures they will come in four parts on one tape.

Both titles cost £4 each.

Computer dictionary

CAMBRIDGE University Press and Acorn Computers have collaborated to publish Acorn Cambridge Illustrated Dictionary for Young Computer Users by Arthur Godman and Tim Tregear.

This up-to-date dictionary, which includes all the latest developments in technology, is easy to follow and suitable for use with all computers. It has simple explanations of computer jargon and, where possible, these are put into context. Many full colour illustrations are used throughout the book to aid understanding.

The dictionary also features a brief history of computers and a general description of the machines. There is a quick reference section explaining computer abbreviations, a Basic glossary and a table of the Ascii codes.

Hard covers: £5.95 net.

New language

A NEW computing language from High-level Algorithms called Halcien has been launched for the BBC range of micros.

Its features include a high level algorithmic format with modular program construction and efficient use of program memory space.

Halcien can automatically edit – under program control – a text file held in ram, supported by nearly 50 language keywords.

Programs have easy read and write access to textual data in the file.

It also includes an advanced graphics package allowing structured image drawing in both two and three dimensions.

Position, size and rotation of image components – icons – are controlled via a dedicated set of Halcien language keywords.

The package comprises a 16k eprom, user guide, function key strip and utility disc of demonstration programs and useful program components. Price £49.95.

Cut-Price Disks — Lowest Yet!

from only £14.99 for 25 disks delivered to your door



Cash 'n Carry prices on disks from Direct Disk Supplies

Offer 1 — 5.25" 'Universal' Hlgrade disks

to suit all drives SSSD, SSDD, SSDD, DSDD & DSQD 48 or 96tpi (40/80)

Disks are packed in 25's, complete with envelopes, label sets and write protect tabs. Nothing wasted on fancy brand names, just plain good value you can rely on!

£ 14.99 – 25 disks	★ Full spec Hlgrade disks, made to 60% clipping level
£ 26.99 – 50 disks	★ Life-time no quibble warranty
£ 49.99 – 100 disks	★ Hub-rings on 5.25" disks
£ 96.99 – 200 disks	★ Label sets & envelopes included
£119.99 – 250 disks	★ No extras – VAT & delivery included.
£219.99 – 500 disks	

ALL PRICES INCLUDE VAT & DELIVERY TO YOUR DOOR! – NO HIDDEN EXTRAS

Coloured 'Universal' disks at lowest prices!

Hlgrade Rainbow Coloured disks

Use coloured disks to code your files. Buy our rainbow pack of 5 different coloured 'Universal' disks. Without doubt the best value in quality and price.

£ 18.99 –	25 disks
£ 35.99 –	50 disks
£ 69.99 –	100 disks
£129.99 –	200 disks
£149.99 –	250 disks
£279.99 –	500 disks

Offer 2 — 3.5" Hlgrade disks

(single or double sided 135tpi) Life-time Warranty & fully certified

Single sided	or Double sided	Qty
£ 39.99	£ 49.99	25 disks
£ 75.99	£ 85.99	50 disks
£139.99	£159.99	100 disks
£259.99	£299.99	200 disks
£319.99	£365.99	250 disks

Bargain Box Offer 5 — Mitsubishi branded disks

at trade prices.

SSDD-48	20 disks	£11.99
SSDD-96	20 disks	£16.99
DSDD-48	20 disks	£16.99
DSDD-96	20 disks	£19.99

Get 20 disks for the normal price of ten 5.25".

Offer 4 — Save money by using both sides Reversible Media Life

floppy disks complete with 2 notches and two index holes. Again, packed in complete sets of 25 disks.

£ 18.99 –	25 disks
£ 35.99 –	50 disks
£ 69.99 –	100 disks
£129.99 –	200 disks
£149.99 –	250 disks
£279.99 –	500 disks

Same day despatch – at no extra cost

****We've moved! ****
Please note our new address

Owing to continued growth we've moved to larger premises. Callers are still very welcome between 9.30am and 5.00pm.

3M — The BRAND leaders

at CASH 'N CARRY prices

Offer 6 – If it's quality, reliability and security then it's 3M. Direct Disk Supplies always give the best price. In fact it's so special that the minimum quantity is 20 disks, and the offer will close on the 30th November 1986.

SSDD-48tpi	744	20 disks	£24.99
DSDD-48tpi	745	20 disks	£28.99
DSDD-96tpi	747	20 disks	£35.99

Remember VAT & Delivery are included – No extras from DDS

How to Order

1. DIAL-A-DISK on 01-979 7811, and give your ACCESS or VISA number and expiry date.
2. Send your cheque etc. to Direct Disk Supplies Ltd. at the new address below.
3. Official Orders. Bona-fide orders from Universities, Colleges, Schools, Charities, etc. are very welcome.

Show Guide to even more special bargains!!

Visit Direct Disk Supplies at the following shows:-

Micro-User	7-9	November – Stand 101
Commodore Horizons	21-23	November – Stand 144
Atari	28-30	November – Stand 101
ZX Microfair	13	December

Access VISA

DDS UK

DIAL-A-DISK
01-979 7811
Answering service for out of hours orders

Direct Disk Supplies Ltd., FREEPOST, 129 High Street, Hampton Hill, Middlesex TW12 1NJ

School admin on the BBC Micro

John Northwood reviews a package that takes the drudgery out of management

A COMPREHENSIVE school may contain over 1,500 pupils, more than 150 teachers and other staff and have a turnover approaching £100,000 per year. Any organisation of this size should clearly be able to benefit from using some form of computer-aided administration.

It is not surprising therefore that there has been no shortage of so-called school administration software in recent years. However much of what is on offer is either an adaptation of some commercial package which fails to take into account the special requirements of schools and often requires hardware generally not available in most or, if it runs on a school's existing hardware it seldom covers all the admin tasks.

This results in the user ending up with a number of different packages to accommodate all the necessary jobs, many of which require the input of the same data.

This system, School Administration System for the BBC Micro, by Alan Dean is a well thought out integrated package for the BBC Micro written specifically for the small to medium secondary school. The author is a full time teacher of computer science with extensive school administration experience and this is reflected by the wide range of administrative tasks covered by the software.

The system requires a dual disc drive, and the 40 track version reviewed here comprises five discs, one of which contains some example data files to enable you to experiment with most parts of the package without first having to enter large amounts of data.

A version using 80 track double sided discs is available which virtually eliminates the need to swap discs when using different sections of the program.

The currently active files are held in memory which makes for faster use than accessing the backing store, but at the expense of data volume. The main limitations, and hence the restriction of the package's use to medium size schools, is a maximum of 74 teachers and 240 pupils per year group.


These restrictions will be lifted when the package is rewritten for later machines such as the BBC+ and the Master.

The full suite of programs may appear overwhelming to the first time user but everything is menu-controlled. Once into the system data input is easy and straightforward with good error detection as you establish the various parameters. Like most computer administration programs it relies on codes for subjects and teachers and many schools will find the allocation of two characters for these to be rather restrictive.


A major problem with many school admin programs is that they assume all schools to be the same and leave little freedom for individual preferences. This package clearly reflects the author's experience of the education system. He overcomes the major problem of just about every school having its own unique set of pupil data by splitting it into three areas.

The primary data includes pupils' names, sex and date of birth, while the secondary data includes six option subjects, examination entry or results data, and up to three user-defined items. Facilities in the additional pupil data entry allow for a further maximum of 40 data fields with a combined total of 256 bytes and up to 50 bytes on any one field. This should be ample freedom to meet the requirements of any school.

Characteristic of the thought that has gone into the package is the section for providing cover for absent staff. This is an area fraught with problems with virtually every school, applying different criteria for appointing non-teaching staff to cover lessons for absent colleagues with the consequent loss of their non-teaching time. The program considers six factors, and seventeen parameters apply weightings of various degrees to these factors, all of which you can modify to your own



The main menu



Main menu of the Info-Cal system

CAL package

A COMPUTER operated learning package that needs no programming is now available from communications consultancy Information Transfer.

Called Infro-Cal, it enables CAL programs to be written with the flexibility to create varied and interesting material, but without writing a single line of programming.

The authoring system, which loads itself, allows you to create six types of frame – information, multiple choice, missing word, true or false, matching lists and multiple response.

The originator chooses the kind of question to be included and types in the text as though using a word processor.

Info-Cal also has built-in formal testing, where the computer makes a random selection from a bank of questions each time the test is given.

The learner is then awarded a percentage score to enable the trainer to monitor performance.

Designed for use on the BBC Micro, B Plus and Master series, Info-Cal comes on disc with a comprehensive user guide. Price £240.

YTS running viewdata system

MIDDLESEX Training Centre has started its own public viewdata system.

Called HITeC, it is originated and maintained by YTS trainees and supervisors.

Subject matter ranges from local Hillingdon area information, through computer news to details about the Training Centre's activities. The Hilling-

don database includes a what's new feature, lists of local organisations and articles about the Borough.

There is a wide range of machine specific databases and a games review section.

As well as providing information, HITeC aims to entertain with joke pages, quizzes, "Did you know?" and gallery sections, some of which are contributed by users.

Interaction is one of the main features of the database. Most sections encourage response in the form of letters sent via the mailbox.

This is an electronic mail system which allows users to type in a page of text or graphics and send it to the HITeC host computer in Uxbridge.

The HITeC host runs on a BBC Micro, with twin 80 track double sided disc drives using CommuniTel software.

It is a Prestel look-alike viewdata system. Any terminal capable of accessing Prestel can log on to HITeC.

The system is on-line 24 hours a day, 365 days a year, on 089559842. Sysop is David Hook.

From Page 43

particular circumstances.

There are more than 50 output options covering just about every type of list ever required in a school. These include lists of forms, sets, options, grades, marks, examination entry, examination results analysis, staff cover and sports leagues lists. There are options for parents' evenings timetables, as well as room, staff and pupil timetables.

In addition the package provides for general purpose searches and production of fourth year option block fitting, D.E.S form 7 statistics production, curriculum analysis and a variety of other useful statistics that someone, sooner or later, will require in most schools. It even produces data files for use with Inform, the data retrieval package.

The only main school administration tasks not available are full school timetable construction and requisition type activities. Cheaper packages are available that provide some of these functions, but the main benefit and value of this integrated suite is that it all runs off the same set of data, thereby avoiding the errors and time in setting up new databases for each separate program.

The accompanying documentation is very good, consisting of a 164 page A5 spiral bound manual, but many users would find a larger format more useful. The easy-to-follow text is largely free from jargon and liberally illustrated with examples of typical printouts.

In addition to instructions on using the programs, the documentation includes useful information on backing up discs and the Data Protection Act. To the author's credit he provides an appendix that gives full details and parameters of the various files and discs for the computer buff in every school who will want to modify the system. However he also wisely advises that no support can be given when any system has been modified.

A computer administrative system should not require a detailed understanding of computers by the user. This package of programs is very user-friendly and was found to be particularly robust. It should be able to cope with the most perverse of operators, although non-computer minded admin staff may need some initial help in setting up printer parameters and in copying and backing up discs.

Although not cheap, at £120 this suite of programs represents very good value for money and once you became fully aware of its power, the package would quickly repay this cost in saved time.

Product: School Administration System
Price: £120 (40/80 track disc)
Supplier: A.J. Dean, 6 Birkland Drive, Edwinstowe, Notts NG21 9LU

EDUCATION SOFTWARE

THE *"LEARN EASY"* RANGE

from

PTARMIGAN SOFTWARE

Mathematics 1 age 5-12yrs
Addition 1
Subtraction 1
Shapes
Times table 1
Times table 2

	BBC		Electron
	Disk	Tape	Tape
	£9.95	£6.95	£6.95

Mathematics 2 age 9 upwards
Addition 2
Subtraction 2
Multiplication 1
Division 1
Number Signs

	BBC		Electron
	Disk	Tape	Tape
	£9.95	£6.95	£6.95

These programs have been developed with the aid of teachers and have been tested in Essex Schools and homes. The programs actually teach the concepts of Borrow, Carry & Payback.

NOT ANOTHER DEMONSTRATION PROGRAM!

Actually **teaches** and **corrects** with full on screen explanations.
Designed as a stand alone teaching aid.
All prices inclusive of Post and Packing.
Equal Addition OR Decomposition Methods Available.

Please state requirements with order (or phone)
DISKS: *Please state 40 or 80 track with order.*

PTARMIGAN SOFTWARE
5 ANSON CHASE, SHOEBURYNESS
ESSEX SS3 9RW
Phone: 03708 2429

Discounts available to Education Establishments
Dealer Enquiries Welcome
Watch this space for more Quality Education Software

Leigh Computer Systems

Authorised Acorn Service Centre. ACT and Ferranti Computer Dealer

COMPUTERS
BBC Master £499.00
Amstrad PC ..... POA
Opus PC II range ..... £499-£999
Plus Atari ST, ACT, Olivetti etc.

DISC DRIVES
OPUS 5802 ..... POA
5802SD ..... POA
5802D ..... POA
Challenger ..... POA
Opus DDFS ..... POA
Plus many others
Cumana 10Mb Hard Disc £699.00
Cumana 20Mb Hard Disc £799.00
OS9 Interface £695.00

PRINTERS
MT80 ..... £179.00
Epson LX86 +Tractor £269.00
Epson GX80 ..... £245.00
Epson FX85 ..... POA
Epson FX105 ..... POA
Epson LX86 ..... POA
Plus rest of Epson range
Canon 1080A ... £269.00
Canon A55 ..... £399.00
Star NL10 ..... POA
Special Offer
Kaga Taxan £259.00

DAISYWHEEL PRINTERS
Epson DX100 ..... £379.00
Juki 6000 ..... £209.00
Juki 6100 ..... £369.00
Juki 6300 ..... £899.00
QuenData £175.00
Plus Silver Reed range

MONITORS
Microvitec 1431 .. £199.00
Microvitec 1451 ... £269.00
Microvitec 1441 ... £399.00
Philips 7502 green .. £84.00
Philips 7522 amber . £89.00

EPROMS
27128 ..... £2.95
8271 ..... £39.00

Plus Full Range of Add-Ons, ROM software etc.
Prices subject to variation.
Phone for latest prices.

EDUCATIONAL ORDERS SUPPLIED
– Price list available on application –
P&P **80p** small items. **£7** large items
All Prices include VAT

75 CROSS STREET
SALE
MANCHESTER
Telephone: 061-905 2144 or 0455 612139

Keep your letters coming in – the education pages are here to reflect your interests. We want to hear your tips, ideas, experiences and suggestions. Send your contributions to:
Peter Davidson, Education Editor, The Micro User, Europa House, 68 Chester Road, Hazel Grove, Stockport, SK7 5NY.

Text file recovery

ONE of my pupils accidentally pressed Break while using Wordwise. She then answered no to the prompt Old text? (Y/N) *thus losing a whole lesson's work.*

If this ever happens again, how can I recover the text? – **S.Collins, Manchester.**

● If this sort of problem occurs with a word processor there is a good chance that the text is still in memory so don't switch off. The text will be somewhere between PAGE and HIMEM, so save all the memory between these points. Recovery from tape is tricky, and we haven't room to cover it here, but if you are using a disc system use:

```
*SAVE TEXT 1900 7BFF
```

Now type the following, pressing Control + N before Return:

```
*DUMP TEXT
```

Press Shift until you recognise the start of your text as in this example:

```
01F8 00 00 00 00 00 00 00 00 ........
0200 00 81 53 74 61 72 74 0D ..Start.
0208 FF 54 68 69 73 20 69 73 .This is
0210 20 61 20 64 65 6D 6F 6E  a demon
0218 73 74 72 61 74 69 6F 6E stration
0220 20 66 69 6C 65 20 74 6F  file to
0228 20 73 68 6F 77 20 74 68  show th
0230 65 20 72 65 63 6F 76 65 e recove
0238 72 79 20 6F 66 20 77 6F ry of wo
0240 72 64 20 70 72 6F 63 65 rd proce
0248 73 73 6F 72 20 74 65 78 ssor tex
0250 74 20 73 74 69 6C 6C 20 t still
0258 69 6E 20 6D 65 6D 6F 72 in memor
0260 79 2E 0D 00 00 00 00 00 y.......
0268 00 00 00 00 00 00 00 00 ........
0270 00 00 00 00 00 00 00 00 ........
```

Make a note of the number XXXX on the left of that line (0208 in our example). Press Shift again until you recognise the end of your text and make a note of the number YYYY on the next line (0268 in the example).

Now press Control + Break and do the following, substituting your own numbers:

```
PRINT ~&1900 + &XXXX
```

and make a note of the result SSSS (1B08 in the example). Then enter:

```
PRINT ~&1900 + &YYYY
```

and note the result EEEE (1B68).

Now just:

```
*SAVE RECOVER SSSS EEEE
```

or in the example:

```
*SAVE RECOVER 1B08 1B68
```

You should now have the majority of your text back in a file called *RECOVER*.

There may be some corruption so you will have to edit it – but that should be easier than typing the whole file in.

If this method fails, you have the file *TEXT* containing your work, so do not destroy it. Unfortunately, in this case, recovery is more complex and would need a whole article to explain it.

Working party aids disabled

IN response to Mr March's letter in the September edition of The Micro User, *I felt that I should write something about the type of work myself and my colleagues have been carrying out for the past three years, with regard to our work with less able, visually handicapped pupils.*

I teach at Condover Hall School in Shropshire. Run by the RNIB, this is a school for pupils of secondary school age who are not only visually impaired but also have additional disabilities, including intellectual, physical, auditory and behaviour problems.

The introduction of the BBC Micro provided a challenge to myself and the rest of the staff in learning how to use it.

More importantly, there was a challenge in how to get the best from it in terms of pupil interaction, bearing in mind the diversity of problems experienced by our pupils.

Fortunately, I was invited to join a working party run by the Research Centre for the Education of the Visually Handicapped in Birmingham. The members were drawn from a variety of educational establishments, mainly concerned with the visually impaired, but also some from schools for pupils with severe learning difficulties, and schools for the physically handicapped.

The group meets once or twice a term at venues around the country in an attempt to review the latest developments and exchange ideas. From the collective experiences of the members of the group, everyone was able to gain much needed information with regard to their successes and failures in using a wide range of hardware and software.

We were also fortunate in having a programmer, Paul Blenkhorn, who was a Research Fellow at the RCEVH. His expertise proved to be invaluable in customising the software to the needs of our pupils.

The work carried out by the working party covers several areas. The first and most basic point concerned screen presentation. It was felt that there should ideally be a choice of foreground/background colours, but failing this, the background should always be black. Also, general screen presentation needs to be as clear and

→

French with fears

A PROGRAM which tests French comprehension and vocabulary against a background of life-or-death drama has been released by Database Software.

French on the Run uses multi-choice questions with randomised distractors, all carefully chosen to illustrate linguistic points or those concerning things French.

It is meant for individual assessment, but can be used effectively for classroom work.

What makes it so different is that the user is cast in the role of an RAF pilot shot down over occupied France in 1943.

The only way to get back to Britain is to pose as a Frenchman, making use of information collected along the way while avoiding traps laid by the Gestapo and other enemies.

There are four escape routes and the language problems get harder with each one attempted.

Historically and geographically accurate, the program tests grammar, vocabulary and linguistic points and also the user's knowledge of France and the French way of life.

The standard of French required is generally about O level, but rises to just below A level in the final test.

Software releases

EDUCATIONAL software house Chalksoft has brought out six new titles for the BBC Micro, Master 128 and Compact.

In Movaword five on-screen pictures are supplied – a house, a beach scene, a garden scene, and two "maths" pictures – and the aim of the activity is to move a word around the selected picture until its initial letter rests on the object it names.

After all the teacher-chosen words have been correctly positioned, the scene "comes alive". Price of £13 includes colouring sheets.

Numbers & Pictures provides structured work on number recognition, counting to, and counting back from 9, using BBC Micro sprite graphics. Price, including teacher guide and black-line photocopy colouring pictures, is £13.

First Filer allows young

→


BBC INDEPENDENT POWER SUPPLY

We have designed this Independent Power Supply for those of you who use disc drives powered from the BBC power supply and are concerned that with the addition of Sideways ROM boards etc., the psu is being overloaded. The Pace independent power supply unit plugs directly into the mains and has four power output sockets of the type used on the BBC. This means that you can plug your unpowered disc drives, buggies etc., directly into this unit thus removing the strain from the BBC Power Supply.

Technically speaking, the Pace Independent PSU takes 240V AC mains and gives out regulated +5V & +12V DC (±2%) and OV power through 4 parallel sockets. These sockets are of the same type as provided at the Auxilliary power output socket of the BBC microcomputer. Push connectors are also provided for all three voltage levels.

The unit is capable of supplying two single disc drives or one dual disc drive plus one or two other devices, such as Eprom programmers, which draw less current. The maximum current available is approximately 1.5A @ +5V and 1.2A @ +12V.

£39 plus VAT



Available from good quality dealers throughout the country or direct from Pace.

Pace Micro Technology

Allerton Road, Bradford BD15 7AG
Tel. 0274 488211 Telex 51338 PACE G
Telecom Gold Mailbox No. 79:PCE 001 Prestel Mailbox No. 274729306

We welcome Access
BARCLAYCARD VISA

PACE


VISION SOFTWARE

OR LEARN YOUR LESSON THE HARD WAY

In our competitive world, it has never been more important to study — for success in exams or continuous assessment.
VISION SOFTWARE is an exciting range of software which allows students to help themselves — at their own pace.
It's easy for any pupil aged between 11-16 to use, as well as those studying for CSE, GCE, 16-plus or GCSE examinations.
Each subject in the range is covered in depth and presented as a complete course in a choice of separate units. So each syllabus can be met precisely.
To help the learning process, the software provides extra information, hints or clues. It gives the encouragement which is so essential.
VISION SOFTWARE was developed by teachers and has been proven in the classroom. Rely on it with confidence!
VISION SOFTWARE is available by mail order for use on these microcomputers:
Amstrad 464, 664 and 6128 · BBC B, B + and Master Series Electron · Spectrum 48K, 128K and Spectrum-plus.

Each pack contains a 3" or 5¼" disk or **TWO** cassettes, plus necessary study diagrams and a comprehensive user guide.

For a free catalogue: simply complete the coupon and send it to Disney Limited, FREEPOST, Sutton Coldfield, West Midlands B72 1BR. (No stamp required)



Please send my **FREE** catalogue of Vision Software and **FREE £3 value VOUCHER** for use with my first software purchase.

Name _____

Address _____

_____

_____

Post code _____

Amstrad ☐ BBC ☐

Electron ☐ Spectrum 48K ☐

Subjects of interest and microcomputers are:

Chemistry ☐ Physics ☐

Biology ☐ Computer Science ☐

History ☐ Geography ☐

French ☐ German ☐

Information Processing ☐ Other _____

_____

Other _____

MU 11/86

From Page 45

uncluttered as possible.

Another essential was the provision of some form of synthetic speech to provide prompts and/or reinforcement. Again ideally, this should be an option, enabling the teacher to switch it off or on as applicable.

Due to the type of user the group was dealing with, the type of synthetic speech initially decided upon was the Acorn Speech chip. Despite its obvious drawback of limited vocabulary, it was felt that this was more than offset by the quality of the speech, as compared to a text to speech system.

However, this theory has since been partly disproved, with the majority of the group's users appearing to quickly come to terms with the robotic voice of a text to speech synthesizer. Therefore most of the software has since been modified to operate from either the chip or a synthesizer.

Input devices were considered by the group so that the micro could be made available to as many of our users as possible. Because of the diversity of additional problems experienced by our users, mainly physical, motor control and coordination, the standard keyboard presented the majority with yet another handicap and somewhat restricted the micro's use and effectiveness.

The main solution to this problem was to utilise a variety of input devices, suited to the individual's needs and abilities. These include the Concept Keyboard, MicroMike, lightpen, Micrex Box (with a variety of appropriate switches), modified Perkins Brailler, and touch screen (both the Cheyne Scribbler and the Microvitec Touchtec 501).

The need for variety brought with it an additional problem in that most software is usually written to run by means of only one input device. It was therefore necessary to duplicate some of the modified materials to operate by some of these devices, and to stipulate the need for the option of device to be incorporated in any software being specifically written.

Certain group members and their establishments have also been involved in some additional development of specific aspects. For example Dave Mitchell (Alexander Patterson School) has helped in the development of a switch control box, aptly named BORIS (Box Of Really Interesting Switches!).

This is basically an enhanced Micrex Box, enabling four inputs and four outputs to be utilised. Dave has also done a tremendous amount of work in creating examples for the touch screen programs and the "Touch and Listen" discs produced by the RCEVH.

Condover Hall has been mainly involved in assisting in the modification of non-copyright software and additional examples for the touch screen programs.

A wide range of software is now available covering topics such as help for those users who are non-literate and have severe learning difficulties, reinforcment of the work being done by pre-braillists (both writing and reading), early visual perception training and pre-reading skills, pre and early number skills and typing and simple word processing skills.

Because of the difficulties experienced by teachers embarking into the field of using the micro with the less able and/or visually handicapped, the group is now attempting to produce information and guideline leaflets. The next stage, just being started, is for specific topics for discussion to be included in each meeting.

The outcome of these discussions will be the production of a paper on that topic which will then be available to anyone, through the RCEVH. Topics such as Controlling and Enhancing Sound Output, Communications, Mobility, Multi-Handicapped Users and Totally blind, non-literate users, have already been suggested.

If you have any more ideas please let us know. One major, on-going project similar to those mentioned above, which has come about from the working party, is the production of a visual assessment package.

The group as a whole, and Dave Mitchell in particular, has also been instrumental in the production of an information booklet which is available from the RCEVH at Selly Wick House, 59 Selly Wick Road, Edgbaston, Birmingham.

This booklet is intended for anyone just starting to use a BBC Micro with the less able and visually handicapped. It draws on the group's collective experiences and provides a basic outline of suggestions.

These are primarily aimed at hardware, software and peripheral equipment which group members have found to be most satisfactory. Also available are a termly newsletter, a comprehensive list of suppliers and a list of software developed at the RCEVH.

I hope this letter has been of some benefit to Mr. March and others alike.

The working party welcomes any new members or inquiries regarding the work they are doing. Should anyone require further details, they can obtain them from me. – **Chris Painter, Condover Hall School, Condover, Shrewsbury, Salop SY3 5HU.**

Machine code for knitters

I WAS interested to read the article on computer control by Philip Andrews on page 41 of the October issue of The Micro User.

In the article Philip mentions an unusual software package for knitters. My wife is a keen machine knitter and the software mentioned may well be useful in persuading her that computers can be useful.

Could you please let me have details of the supplier? – **F.J. Lovelady, Litherland, Liverpool.**

● We hope to publish a review of this software in a future issue. Details can be obtained from: Newsnight Ltd, Reliance House, 340 Clapham Road, London SW9. Tel: 01-627 3149

Catering for Any Questions

HOW do I get Any Questions, which was in the September issue of The Micro User, *to work on a Master? Pressing D for disc filing results in an error message. Does this also mean it will not work on a 1770 DFS upgrade?*

Are you interested in a file of questions and answers on catering? – **I. R. Sykes, Birmingham.**

● Any Questions works on a 1770 DFS. The problem on the Master is caused by *D. commands in lines 1390 and 1470. *DISC was not used because some disc filing systems report an error with *DISC (they need *DISK).

The only change you need to make for Any Questions to work on a Master is to alter the following lines:

```
1390 *DISC
1470 *DISC
```

We are interested in questions on most subjects and at all levels.

children to create and use small databases with the minimum of help, and can even be a valuable aid for the small school which wants to computerise its record-keeping systems. Price £17.35.

Transform is a mathematics program designed to simplify the investigation of transformations and coordinate geometry from upper junior to sixth form work and beyond.

Transformations of shapes defined by coordinates are instantly displayed on screen and can be retransformed at will.

Mistakes are easily rectified and images may be saved in calculator-like memories. Price £17.35.

Keyboard Player is a complete computer assisted learning course designed to introduce the absolute beginner to electronic – piano/organ – keyboards.

The computer introduces the keyboard with the help of a game called Sequences then teaches correct use of your hands.

The user learns to play a graded sequence of exercises and melodies along with the computer.

Additional exercises and melodies are provided – some in printed form – and advice is given on future progress. Price £17.35.

Arthur – The Legend is the title of Chalksoft's first multi-media topic pack.

It features a disc-based graphics adventure involving the search for the Holy Grail, stories on two audio tapes, slides, detailed teacher background booklet, open-ended work booklets for children, and many research and topic ideas. Price £29.95.

Upbeat drum

AN improved version of its drum machine add-on for the BBC Micro has been released by Rice Computers.

The software now allows 32 steps in a bar and tempo in the range 1 to 255. And it has been made compatible with the Master series.

People who already own an 8 bit D/A converter, or a sampler with an 8 bit D/A converter, can buy the program separately.

Software costs £19.95 on cassette, £22.95 on disc. BBC Micro and Master versions with the drum unit cost £45 on cassette, £47.50 on disc.

Two things your

Good old Teddy will always have great sentimental value.

The BBC Master Compact, on the other hand, will be valued for more practical reasons. No doubt your child is already familiar with BBC micros from the classroom.

With the BBC Master Compact at home, they will soon feel completely comfortable using computers.

From then on, learning becomes that much easier.

Parents will quickly spot the value of this new BBC micro for themselves.

Once your child is safely tucked up with Ted, you might use the Master Compact to do the dreaded VAT returns.

Accountancy Age has already acclaimed our micro's spreadsheet package* as 'the most sophisticated yet produced for a small micro'.

The BBC Master Compact comes as a complete, easy to use package. This includes colour monitor, processor, disc drive and enough software to keep you and your children occupied indefinitely.

Have a chat with your local dealer or specialist retailer about the computer that equips your child for life.

Like a Teddy Bear, it can be justified as an essential purchase.



THE MASTER COMPACT 128K RAM, 3.5" DISC DRIVE, PRINTER AND JOYSTICK INTERFACE. SOFTWARE INCLUDES VIEW WORD PROCESSOR, ABC, CARD INDEX, LOGOTRON LOGO, WINDOW-DRIVEN DESKTOP SYSTEM, ADVANCED DISC FILING SYSTEM, 14 PROGRAM WELCOME PACK AND 4 TUTORIALS, *SPREADSHEET EXTRA AT £52. BASIC PRICE £399 WITH MONOCHROME MONITOR £469, WITH HIGH RESOLUTION (0.42 PITCH) COLOUR MONITOR (AS ABOVE) £599. ALL PRICES PLUS VAT. FULL DETAILS FROM BOB COATES, DEPT. [MU3], ACORN COMPUTERS LTD., CAMBRIDGE TECHNOPARK, 645 NEWMARKET ROAD, CAMBRIDGE CB5 8PD.

compact
BRITISH BROADCASTING CORPORATION
MASTER SERIES MICROCOMPUTER

The BBC Master Comp qu

ur five year old will still value at twenty-one.



ompaquips your child for life.

Acorn
The choice of experience.

The only truly integrated suite of ROMs

This unique system allows all ROM-LINK compatible ROMs to be fully integrated. Up to 16 'packages' can be held in memory at once, so for example you could have a spreadsheet and a chart and a document in the word processor all being worked on at the same time. The ROM-LINK system also allows any data to be transferred directly from any package to anyother. For example spreadsheet data could be imported into the word processor, and then back again into the spread-sheet, then into INTER-CHART to plot a graph.









* TO BE RELEASED SOON

FOR THE BBC MICRO

Computer Concepts

The Master Comp
Compatible

INTER-WORD

The latest word processor from the same stable as WORDWISE and WORDWISE PLUS, the most successful programs ever written for the BBC Micro computer. With years of experience and feedback from users, the authors of INTER-WORD have ensured that it suits everyone's needs. A great deal of attention has been paid to ensuring that INTER-WORD is fast, efficient and above all simple to use. Being menu operated the newcomer does not need to remember strange key combinations or command names. The menus are not a burden to the experienced user since there are shortcuts to access many of the features.

REVIEWS

"the most significant program since WORDWISE." ... "INTER-WORD on the BBC Micro compares favourably with word processors costing five or ten times as much on the IBM PC and the like." ... "INTER-WORD is a real pleasure ... a truly worthy successor to WORDWISE"
Gordon Taylor A&B Computing

"Rulers can be used to manipulate text to your satisfaction. This is a joy to use."
"INTER-WORD is certainly an advance on most other word processor packages."
Popular Computing Weekly, July '86

Technically, too, the program is astounding ..."
"... quite stunning handling characteristics"
Viewfax Tubelink—August '86

"INTER-WORD is the most powerful and comprehensive word processor available for the Beeb today. It is more powerful and flexible than View and still retains much of the friendliness and ease of use of Wordwise. Inter-Word looks set to become the standard word processor for the BBC Micro."
Beebug, Aug/Sept '86

Some of its special features are:

•Automatic re-formatting
This enables the user to just type - no keys to press to re-format the paragraph after changes to the text or margins have been made; the margins on the rulers can simply be dragged, all text being instantly re-formatted to the new settings.

•Multiple documents in memory.
Most people do not work on one document at a time. INTER-WORD allows up to 16 documents to be stored in memory at once, and text to be transferred from one to another.


•Multi column
Built in facilities for printing text in up to 5 columns.

• Pull down menu operation
Simple and fast selection of all INTER-WORD options and page layout.

20% discount

Available to all WORDWISE PLUS owners. Simply quote you serial number, name and address when ordering direct. Discount price;
£39.20 + VAT (£45.08 incl.)

THE NEW WORDPROCESSOR FOR THE BBC MICRO




•Multi-file operation
Very large documents can be handled with ease. INTER-WORD's unique multi-file mode puts virtually no limits on document size and allows simple and fast movement to any point in the document.

•Block operations
These are common to most word processors, but with INTER-WORD any part of the text can be marked and then instantly moved, copied, deleted, printed, saved, underlined etc. There is no limit to the amount that can be marked.

•Specific page printing
Any page or range of pages may be printed, even in multi-file mode, with any number of copies.

•File selector
The file selector displays a list of all files - move to one and select it. You will never have to type or remember filenames again.




£49.00+vat(£56.35)

Computer Concepts

Gaddesden Place, Hemel Hempstead, Herts. HP2 6EX, England.
Telephone (0442) 63933

•On screen style changes
Underline, bold and a special 'dotted' style are shown on screen exactly as they would appear on the final printout. Also left, centred and right justified text is shown on screen as you edit. What you see on screen is really what you get on the printout.

•On screen page breaks
You need never lose your place on the page. Top and bottom spaces, with any associated headings, footings or page numbers etc. are shown at all times. Like most features in INTER-WORD, a menu option lets you turn paging off.



•Integrated spelling checker
To be made available soon, this entirely ROM based spelling checker allows text to be checked as it is typed or after typing, at over 9000 words per minute.

•40,53,80 and 106 column screen modes
•Mail merge
•Integrates with all other parts of INTER family
•Automatic page numbering, with headers and footers
•Very fast and smooth scrolling
•Powerful search and replace facilities including wildcards, upper/lower case sensitivity, stored search and replace strings for instant re-use.
•Automatic word count
•Fast simple cursor movement to any point
•Easily tailored to any printer
•Line numbering
•Selectable screen colours
•Compatible with the B, B+ and Master; Solidisk, Aries and Watford shadow RAM boards.

Software is now more important than the hardware, especially with todays falling hardware prices.

INTER-WORD is the most sophisticated and professional word processing package available for the BBC Microcomputer.

MONEY-BACK
Guarantee
Buy INTER-WORD—if you don't like it—send it back for a full refund!
(Available when purchasing direct from Computer Concepts)

Watford Electronics

Jessa House, 250 Lower High Street, Watford WD1 2AN, England
Tel: Watford (0923) 37774/40588 Tlx: 8956095 WATFRD Fax: 01 950 8989

All prices exclusive of VAT; subject to change without notice & available on request.

Credit Card Orders (ACCESS & VISA) Tel: (0923) 33383 or 50234 (24 Hours)

BBC MASTER 128K Micro		**£395**
BBC MASTER TURBO 4MHz		**£493**
512K Processor Add on Board		**£335**
Turbo 65C102 Add-on Module		**£99**
BBC MASTER ET (Econet Terminal)		**£320**
Econet Module for the Master		**£43**
ROM Cartridges for Master		**£13**
Reference Manual I	(No VAT)	**£15**
Reference Manual II	(No VAT)	**£15**
Advance Ref. Manual	(No VAT)	**£19**
64K Upgrade Kit for B+		**£32**
Acorn 1770 DFS Upgrade Kit		**£42**
ECONET Upgrade Kit for BBC		**£42**
ALL ECONET UPGRADES Available		

SPECIAL OFFER

FREE with every BBC Master purchased from us, Software Packages worth

£80

Comprising of: Computer Concepts New **INTERWORD,** *wordprocessor Rom, OFFICE MATE & OFFICE MASTER Softwares on Disc consisting of Database, Spreadsheet, Beebplot Graphics, Wordprocessor, Accounts Packs: (Cashbook, Final Accounts, Mailist, Easiledger, Invoice & Statements, Stock Control.*

6502 Acorn 2nd Processor package	**£172**
Z80 Acorn 2nd Processor package	**£319**
32016 Co-Processor	**£999**
Cambridge Workstation	**£3450**
ARIES IEEE Interface	**£238**
Acorn IEEE Interface Complete	**£280**
Acorn Teletext Adaptor	**£125**
Acorn Prestel Receiver	**£115**
Acorn Bitstick I	**£299**
Robocom Bitstick II	**£759**
Upgrade for Bitstick I to II	**£450**
Bitstick Multiplotter Driver	**£65**

(Securicor carriage £7)

By popular demand our retail shop is now open until 8.00pm. every Thursday.

VARIOUS PRINTERS

● EPSON FX85 Printer	**£315**
● EPSON FX105 Printer	**£435**
● EPSON JX-80 Colour Printer	**£420**
● EPSON Hi-80 Printer Plotter	**£319**
● EPSON Paper Roll Holder	**£17**
● EPSON LX86 Printer	**£229**
● BROTHER M1409 Printer	**£285**
● SEIKOSHA GP50A & GP50S	**£49**
● Centronics Printer Cable to interface all the above Printers to BBC	**£6**

(Securicor carriage charge on printers £7)

RX & FX PRINTER INTERFACES

Epson interfaces fit inside the printer to allow connection using techniques other than Centronics.

RS232	**£27**	RS232 + 2K Buffer	**£55**
IEEE 488	**£65**	RS232 + 8K Buffer	**£75**

Compact

COMPACT without monitor	**£385**
COMPACT with green monitor	**£469**
COMPACT with colour monitor	**£599**

INTRODUCTORY OFFER
As an introductory offer, we are offering the Computer Concept's INTERWORD ROM and Gemini's OFFICE MATE and OFFICE MASTER software packages (worth £80) ABSOLUTELY FREE with every COMPACT bought from us in November.

Securicor £7

WHY SHOULD I BUY A MASTER COMPACT?

Acorn Computers have sold over 1,000,000 computers to the home, education, business and research markets over the last six years, and so are a well established contender in the market.
Originating, and still very compatible with, the original BBC design from over 5 years ago, the Master Compact features many enhancements to the specifications of a Model B. The Operating System has doubled in size, the amount of memory installed has quadrupled, an advanced disc filing system is included as standard, and an even faster and more expanded version of the famous BBC Basic is installed.

Using a special 'front panel' program, you can configure the Compact to power up according to your requirements. The disc drives for the Compact are housed in a separate box, which contains the power supply and doubles as a monitor stand. Thanks to this box, the Compact normally only requires one mains socket.

RGB (colour) and composite video (monochrome) connections are provided as standard, along with a phono socket to permit external amplification of the 4 voice sound synthesis system. An 'Atari' style digital joystick port permits a wide range of joysticks to be used.

The Compact is supplied with a massive amount of bundled software, making it ideal for home, business and educational use. A single 3.5" disc drive is supplied as standard, with a second drive optionally available later. You can purchase the Compact with either a bundled colour or monochrome monitor, or choose from one of our popular range of colour and monochrome monitors. A UHF modulator will be available shortly for use with TVs. An Econet kit will soon be released, as will an RS232 kit.

There is already a lot of software available on 3.5" disc format (with much more to follow), but we can supply converted 5.25" disc drives, should these be required. A 50 way expansion bus guarantees future expansion.

Bundled software includes: Basic 4 (1986), View 3 (latest version), Printer drivers for View, Logotron Logo, ABC Word Processor, ADFS (latest version), Disc Utilities, Arcade style game, Adventure game, Range of tutorial programs, Desktop environment software, Notepad, calculator and clock for desktop, TimPaint drawing package, Card Index System, Character Definer.

Official ACORN Distributor

CENTRONICS GLP & Brother M1009 (NLQ) Printers

A major price break-through in NLQ Printers from Watford.

At last, a full feature NLQ printer at a price that everyone can afford. Due to Watford's bulk purchasing power and low margins we can now offer this incredible printer deal direct from the manufacturers to our customers.

The Centronics GLP printer which is manufactured by BROTHER (and also marketed by them under their own brand name M1009), features a Near Letter Quality (NLQ) mode using a 23 by 18 dot matrix for each NLQ character (this is the same as is used by the very popular Kaga Taxan printers). The NLQ Font Rom supplied is Watford's own Professional NLQ ROM for the GLP/M1009.

Single, double and quadruple density graphics modes as well as four character widths and super/sub script printing are also supported, along with many other facilities normally found on printers costing twice as much.

Handles upto 9" wide paper. Friction feed standard, tractor feed optional extra.

GLP is bidirectional logic seeking. Has a 9 needle print head. 50 CPS. Parallel interface only.

Special Offer **£95** *(carr £5)*
Tractor Feed Attachment **£7**

Centronics GLP Mk2 (Brother M1109) NLQ Printer

100 CPS, (25 in NLQ mode), Bi-directional, logic seeking, Friction feed, tractor feed optional extra, 2K Buffer. Has both Centronics parallel and RS232 both as standard. Simply at the flick of a DIP switch, the Mk2 printer swaps between full IBM or Epson compatibility.

Launch Price: **£139** (carr. £5)
Tractor Feed Attachment **£5**

BROTHER HR-15XL

(NEW IMPROVED FAST HR-15XL)
The new improved Brother HR15XL is a very high quality and very fast daisy-wheel printer for serious use. Notable features of this printer include a 3k buffer, 20cps, bi-directional proportional spacing, Centronics interface standard, (RS232 optional).

ONLY **£295** (carr. £7)

TRACTOR FEED Attachment	**£84**
Ribbon Cartridges:	
Fabric **£3;** Carbon **£3;** Multistrike	**£5**
DAISYWHEELS (various typefaces)	**£18**

PRINTER SHARERS

(Ideal for School environment)

Connect 3 BBC Micros to 1 Printer	**£60**
Connect 6 BBC Micros to 1 Printer	**£129**

PRINTER CHANGER

Connects 3 Printers to 1 Micro	**£65**

(Cables extra)

HITACHI 672 PLOTTER
Only: £450 (Carr £6)

SPECIAL OFFER
EPROMs for BBC's Sideways ROMs.

2764-250nS £2.00
27128-250nS £2.40

RAMs (Low power) for ATPL, WATFORD, etc., Sideways ROM Boards

6264LP (8K) £3.00
2 × 6264LP (16K) £5.90

KAGA KP810
NLQ PRINTER

This rugged printer is made by Canon of Japan and is the same as Canon PW1080. It is fully Epson FX80 compatible and offers superb NLQ printing.

Our Price: ONLY ***£215*** (£7 carr.)

Kaga RS232 Interface	**£49**
Kaga RS232 Interface + 2K Buffer	**£69**
Kaga RS232 Interface + 16K Buffer	**£95**

KAGA KP910 Printer

Similar to the KP810 but has 17" wide carriage for wide print. Gives 156 columns of normal print or 256 columns in condensed mode. Ideal for printing out spreadsheets.

ONLY **£375** (£7 carr.)

PRINTER LEAD

Centronics lead to connect BBC micro to EPSON, KAGA, SEIKOSHA, NEC, STAR, JUKI, BROTHER, SHINWA etc. printers.

Standard length (4 feet long)	**£6**
Extra long (6 feet long)	**£8**
Compact's Special Centronics Lead	**£9**
RS232 Cable	**P.O.A.**
IBM Parallel 1 meter Cable	**£12**

PRINTER RIBBONS & VARIOUS DUST COVERS

Type	Ribbons	Dust Covers
BBC Micro	–	**£3.50**
BBC Master	–	**£4.00**
FX100	**£7.00**	**£5.25**
FX80/MX80/FX85	**£4.50**	**£4.95**
RX80	**£4.50**	**£4.50**
LX80	**£4.00**	**£4.50**
GP80	**£4.50**	**£4.00**
GP100/GP250	**£5.95**	**£3.95**
Centronics GLP	**£4.00**	**£3.75**
KAGA KP810	**£5.25**	**£4.75**
CANON PW1080	**£5.25**	**£4.75**
Panasonic KX1080	**£7.75**	**£4.75**
Microvitec Metal Monitors	–	**£5.50**

Our attractive Dust Covers are manufactured from translucent PVC. The seams are stitched and edges are taped to prevent splitting due to continuous use.

Listing Paper (Perforated)

1,000 Sheets 9½" × 11" Fanfold Paper	**£7**
2,000 Sheets 9½" × 11" Fanfold Paper	**£12**
1,000 Sheets 15" × 11" Fanfold Paper	**£9**
Teleprinter Roll (Econo paper)	**£4**

Carriage on 1,000 Sheets £1.50

PRINTER LABELS
(On continuous fanfold backing sheet)

1,000 90×36mm (Single Row)	**£5.00**
1,000 90 ×36mm (Twin Row)	**£4.90**
1,000 90×49mm (Twin Row)	**£7.50**
1,000 102×36mm (Twin Row)	**£6.25**

Carriage on 1,000 Labels £1.00

Acorn/Olivetti JP101 Spark Jet Printer

One of the main problems with most printers is that they are hopelessly noisy. How often have you wanted to print something late at night but not done so for fear of waking the children? Also ideal for those working in quiet environments such as libraries, etc. Silence the complaints with the serious solution from Watford at the amazing cost of only

£65

Pack of 4 refills **£10**

FREE Spark Dump ROM WORTH £15 for each JP101 purchased this month

JP101 Sparkjet Dump Rom £15



We stock a range of monitors to suit all needs. Choice of a monitor is a matter of personal taste so we recommend that whenever possible, you ask for a demonstration at our shop. All Monitors are supplied complete with connecting lead.

MICROVITEC 14"

- 1431 – Medium resolution as used on the BBC television computer programme **£172**
- 1451 – High resolution, suitable for word processing in mode 0 ..... **£225**
- 1441 – High res, exceeds the capabilities of the BBC micro **£365**
- 1431AP RGB + PAL and AUDIO **£199**
- 1451AP RGB + PAL and AUDIO **£259**
- **TOUCHTEC** Touch Screen Pack **£250**
- Dust Cover for Microvitecs **£5.50**

KAGA/TAXAN 12"

- KAGA KX1201G Hi-res Green Monitor **£90**
- KAGA KX1202G Long persistance Hi-Res Green Monitor **£98**
- KAGA KX1203A Ultra-Hi-Res Amber Monitor **£98**
- **KAGA Super Vision 3,** Ultra Hi-res, RGB Colour; Text mode switch allows monochrome text display in Green, Amber, White reverse or White on Blue **£320**

STAR BUY

- PHILIPS 14" Hi-Res, dark-glass, attractively finished Colour Monitor – supplied complete with RGB, SKART and Audio/Phono connectors. A push-button switch toggles between Hi-Res monochrome green text mode and full colour display.

ONLY £199

ZENITH

12" high resolution monochrome monitor. Ideal for word processing as its green or amber screen is very restful to read. (These are the same professional quality, stylishly finished monitors as used in the larger Zenith Micro Systems.)

Green (New Design) Hi-res	**£69**
Amber (New Design) Hi-res	**£76**

LEADS

BNC Lead for Zenith or Philips	**£3**
Skart Monitor Lead	**£5**
RGB lead for KAGA	**£3**

N.B. Carriage on Monitors **£7** (securicor)


SWIVEL BASES
for Video Monitors

By placing your monitor on one of our superb swivel bases, you gain the freedom to adjust the monitor viewing angle to suit your needs. By doing this, you alleviate eye strain and reduce back stress.

for 12" Monitors **£12** (carr. £2.50)
for 14" Monitors **£16** (carr. £2.50)

Panasonic KX-P1080

FREE BBC Micro Cable



From the prodigious Japanese Stable of Panasonic comes this fabulous new NLQ Dot Matrix Printer

Available NOW at a superbly realistic price, the KX-P1080 perfectly balances features, quality of construction and Value for Money to produce the printer of tomorrow, here today, ready to sweep the current generation of machines away.

Ingenious innovation in terms of software control codes permits great flexibility when it comes to defining the print style. A nippy 100 cps of clear Draft text backs up the crisp 20 cps Near Letter Quality text mode, with upto 40 superbly useful downloadable characters. A delightful range of assorted character widths is efficiently supported, with sizes ranging from a broad 5 cpi to petite 17 cpi, EVEN in NLQ mode. Some of the extensive support for serious use includes specialised functions to perform justification, centering and even left and right ranging. Proportional spacing permit even greater freedom when it comes to advanced use. Not only is the full Epson RX control code set implemented, but extra codes have also been added to cater for the NLQ options, etc.

A full 96 ASCII character set is supported, with an extended set of 32 international characters A 1K Print Buffer alleviates much of the wait time normally associated with printing, whilst the bi-directional logic seeking print head takes the quickest route to print as required.

The draft text is implemented with a 9 × 9 matrix, with Near Letter Quality effected by means of an 18 × 18 matrix.

FREE with every KX-P1080 printer purchased this month, 1000 sheets of fanfold paper, printer cable for a BBC micro and our sophisticated Dump Out 3 screen dump ROM.

Introductory Price: **£155** (carr. £7)

NEW LAUNCH

A few months ago, we introduced the KX-P1080 to our large and discerning customer base. As a result of the enthusiastic and overwhelming reaction to this versatile dot matrix printer (see above for details), we are now extremely pleased to be able to bring you details of the fabulous KX-P313 Daisywheel Printer, also from Panasonic. The KX-P3131 printer is the ideal printer for the home user wishing to produce clear, immaculate letters or reports.

Ideally suited to the pocket of the home user, costing not much more than a pair of disc drives, this daisywheel printer delivers flawless text at 10, 12 or 15 characters per inch. It also supports proportional print mode.

Printing at a respectable 17 characters per second, the KX-P3131 features a capacious 6 kilobytes printer buffer to swallow most printing requirements with ease. For the more demanding user, there is a 32 kilobytes printer buffer option available. Taking paper up to 13.5" wide, the KX-P3131 prints with bidirectional logic seeking, ensuring the minumum time to print your text.

Continued ——→

MARK 2 LIGHT PEN

You no longer have to fiddle with the brilliance control or work in the shade as this NEW Mark II Light Pen is totally insensitive to local lighting conditions It only operates on high frequency light from the TV or Monitor.
The red LED Indicator on the Mk II pen, lights up when valid video data is available. Your program can have access to this signal allowing computer verification of target for high res drawing. The conveniently located switch on the pen body allows the computer to ignore any stray signals. Supplied complete with the sophisticated PEN-PAL Software on Cassette or Disc. Please specify.

Special Offer Price: £15

THE EPSON RX/FX/KAGA PRINTER COMMANDS REVEALED (BOOK)

So you bought yourself a new printer, because the salesman in the shop showed you how clever it is and impressed you with all sorts of printouts to show its capabilities – he may even have offered you a special price.

However, now that you have got it home and connected it to your BBC microcomputer, you are wondering how to make it perform these magical tasks. The manual seems to give no clues, and when you type in the example programs, the computer throws the LPRINT statements back in your face.

Now what do you do, when this £400 piece of high technology refuses even to move its head, and you have stayed up until 2 in the morning with copious supplies of coffee, desperately trying to print something out. Once again, Watford Electronics comes to your help with our new book entitled 'THE EPSON FX/KAGA PRINTER COMMANDS REVEALED'.

This book describes in plain, easy to understand English, how to use and make the most of your KP810, Canon PW1080A or any Epson FX80 compatible Printer with the BBC Micro, both from Basic and Wordwise.

It describes in detail how to obtain the maximum in graphics capability from your printer and includes full indexes allowing you to cross index the numerous commands. Every command is explained in detail, with an accompanying BBC Basic program and an example of its use from Wordwise.

Superb Value at **£5.95** (No VAT)

WATFORD TOPS THE DFS CHART

Watford's Ultimate DFS has scored highest points in ACORN USER's unbiased DFS's Review of July 1985.
In concluding, the reviewer writes "It must be said that Watford's DFS certainly offers a comprehensive range of facilities at a very attractive price". (Please write in for comprehensive details.)

WATFORD's & ACORN's SINGLE DENSITY DFS

Watford's popular and widely acclaimed DFS has now been available for three years, and has gained a large following amongst serious users of the BBC Micro. Owners of Acorn or any other standard DFS can upgrade to our "Ultimate" DFS merely by replacing their DFS ROM. See below for this upgrade. (P.S. Watford's highly sophisticated DFS is fully compatible with Acorn DFS).

PRICES

- *Complete Disc Interface Kit incl. DFS ROM & fitting instructions* **£58**
- *Acorn's 0.90 DFS Kit complete* **£52**
- *DFS Manual (Comprehensive)* *(no VAT)* **£6.95**
  (P.S. Our comprehensive DFS Manual covers both Acorn & Watford DFSs)
- *Watford's sophisticated DFS ROM only* **£16**
- *We will exchange your existing DFS ROM for Watford's Ultimate DFS ROM for only* **£12**
- *DNFS ROM only* **£17** ● *ADFS ROM only* **£25**
- *Watford's DFS is exclusively available from Watford Electronics. Every ROM carries a special label with our LOGO and serial number.*

WATFORD's DOUBLE DENSITY DFS INTERFACE

The DDFS from Watford Electronics represents a new standard in DFSs for the BBC micro. This is a double density version of our popular single density DFS, and combines all the features of this powerful DFS with the advantages of a system that gives 80% more storage per disc in double density mode. P.S. – Please note that not all DDFSs are capable of providing either the full 80% storage increase, or of allowing a file the full size of the disc – Ours allows both of these! Operates both in Single & Double Density modes.

The typical piece of games software these days is provided upon a protected disc. In order to work on any double density system (including the others on the market) a protected piece of software needs to make calls through the OSWORD &7F routines. To ensure compatibility, the Watford DDFS features probably the most comprehensive and powerful 8271 emulation ever written for a double density system.

PRICES

- *Complete DDFS Kit incl. fitting instructions* **£46**
- *DDFS Manual* *(no VAT)* **£6.95**
- *We will exchange your existing Single Density DFS Kit for our DDFS Unit at* **£35**

CHRISTMAS GIFT VOUCHERS

Following numerous requests from you the customers, we have at last introduced our GIFT VOUCHER service. The Vouchers are available in £5; £10 & £15 demominations and are an ideal answer when faced with that problem of what to give for that special Birthday/Christmas gift. Simply send your credit card number or your cheque for the amount of Vouchers you require and we shall send you these attractive Vouchers. (There is a 50p handling charge on any amount.)

MYSTERIES OF DISC DRIVES & DFS REVEALED (BOOK)

Are you tired of faulty cassettes, and lengthy loading times? Do you want to upgrade your BBC micro to take discs but you get tied up in the plethora of jargon surrounding the choice and use of these systems.


For instance, what is the difference between single and double density formats, how can you use a 40 track disc on an 80 track disc drive? What is the difference between a DFS and disc interface kit? Should you acquire a single Disc drive or twin? What does 48 TPI and 96 TPI discs mean? These are just a few of the questions you may have asked yourself and never found the answer or maybe you have yet to encounter these questions.

Now the mystery of buying a suitable interface and disc drive for your BBC micro is revealed in Watford's new book entitled 'MYSTERIES of DISC DRIVES & DFS REVEALED'. It describes in fine detail, yet remaining very readable to the beginner, how disc drives operate, the type of interfaces available, which type of discs to use on a disc drive and how data is stored on the discs.

£5.95 (Book No VAT)

DISC ALBUMS £4

Attractively finished in antique brown leather look vinyl. Stores upto 20 Discs. Each disc can be seen through the clear view pocket.



STAK-PAK

The unique computer program filing and storage system. Made of tough black plastic, these compact drawer sections hold two cassettes each and lock together vertically to form miniature cabinets of any height. Each drawer section has two C12 Data Cassettes with labels plus external index card.


Five twin Packs incl.
10 Cassettes Only: **£5**

FLOPPY HEAD CLEANER KIT

The heads in floppy drives are precision made and very sensitive to dirt. The use of a cleaner Kit is a sensible precaution against losing valuable data. It is recommended to clean the drive head once a week. It is very simple to use.


£8

LOCKABLE DISC STORAGE UNITS



Strong plastic case that afford real protection to your discs. The smoked top locks down. Dividers and adhesive title strips are supplied for efficient filing of discs.

- M35 - holds upto 50 discs **£8**
- M85 – holds upto 95 discs **£11**



PLASTIC LIBRARY CASES

FOR 5¼" DISC STORAGE
holds 10 Discs. **£2.00**

DUST COVERS (For our Disc Drives)

Single CLS (without PSU) **£3.20** Twin CLD (without PSU) **£3.85**
Single CS (with PSU) **£3.95** Twin CD (with PSU) **£3.90**

Quality Disc Drives from Watford

To help you decide which drive is the most suitable for your needs (and your pocket!), we have produced the table below.

The first capacity given in the first column indicates the single density capacity. The double density storage capacity is second one, (that within the brackets). All disc Drive type numbers start with the prefix "C".

The tinting on some of the boxes is used to indicate which Drives are 40 track (non-tinted) and which are 80 track (tinted). All our drives are of Japanese manufacture. All our 80 track drives are already fitted with a 40-80 select switch.


All our Disc Drives are Double Sided and will operate in both Single and Double Density modes. *Extensive experience of the usage of disc drives suggests that the JAPANESE drives currently represent about the best in terms of speed, reliability and overall "elegance" available for the BBC Micro.*


Various other "manufacturers" of disc drives for the BBC micro (more accurately, "packages" label other manufacturers drives with their own name). We buy the high quality JVC and Mitsubishi drives in large quantities directly from the manufacturers, package them and sell them at "dealer" prices direct to the public.

If you look around the popular BBC micro press, you will find that the prices we quote for the top quality, new slimline disc drives are, virtually without exception, some of the best around. These prices, coupled with the backup of one of the country's largest distributors of BBC peripherals provides a superb deal.

Unless you anticipate using dual drives in a fully expanded BBC system for long periods of time with little ventilation, then we suggest that our range of "CL" disc drives without the PSU (Power Supply Unit) would be quite adequate: extensive tests within our workshops have confirmed this. All drives are supplied complete with a SPECIAL UTILITIES Disc, Cables and Plugs. The Drives with power supply have a mains moulded plug for safety purposes. Ideal for Schools & Colleges. We are now able to supply all single disc drives in Power Supply, in either single or dual case. (Dual case has a twin data cable and a power supply capable of driving two disc drives; allows easy expansion to a dual drive unit, at a later date. Prices stated in the pricing boxes below for single drives is for a single drive in a standard single case. Single drive in a dual case cost an extra £5. (At Watford we anticipate your needs of tomorrow, not just today)!

When using a BBC Micro, most people find themselves short of space. The Watford's BBC Micro plinths form an ideal way of recovering some of this precious space; your BBC, Disc Drive and Monitor can all occupy the same vertical footprint and still be comfortably situated. With the Watford Double plinth, your Disc Drive is mounted vertically at one side, leaving a very valuable area directly in front of you for such useful items as spare discs, pen, paper, reference manuals, etc. Follow the trend with Watford plinth. (Turn to the 10th page of our advert for the Plinths).
P.S. All our 5¼" Disc Drives are compatible with the Compact Micro. All you require is the special Compact Disc Drive Cables designed by us.





Capacity	Drives without P.S.U.		Drives with P.S.U.	
	Single	Twin	Single	Twin
200K (360K)	CLS 200 £89		CS 200 £99	
400K (720K)	CLS400S £97	CLD400 £165	CS 400S £110	CD400 £189
800K (1.44M)		CLD 800S £183		CD 800S £205

● TWIN Disc Drive Case, complete with Power Supply & Cables **£35**
Securicor carriage on Disc Drives £5 to £6

Prefix **C** = *Cased Drive*
L = *Less PSU*
S = *Single*
D = *Double*

Suffix **S** = *40/80 Switchable*

e.g. CLS400S = Cased drive, Less power supply unit, Single 400K, Switchable (40/80 track).

3M – DISKETTES

Top quality 3M – SCOTCH Diskettes from Watford Electronics (Your 3M Appointed Distributors). All our discs carry a lifetime warranty. These discs are quiet in operation and insert positively with their reinforced hub rings. Boxes of 10 supplied complete with self stick disc labels and write protect tabs.

- *10 × 5¼" S/S D/D 40 Track Diskettes* **£10**
- *10 × 5¼" D/S D/D 40 Track Diskettes* **£12**
- *10 × 5¼" S/S D/D 80 Track Diskettes* **£17**
- *10 × 5¼" D/S D/D 80 Track Diskettes* **£17**
- *Hi-Density 1.6M D/S D/D for IBM* **£32**

- *10 × 3½" S/S D/D 40/80 track Discs* **£20**
- *10 × 3½" D/D D/D 40/80 track Discs* **£27**

TOP QUALITY 5¼" DISKETTES

To complement the range of quality discs and disc drives that WE already sell, WE are now supplying some special offer packs of 10 high quality discs. Each Disc has a reinforced hub ring and carries a lifetime guarantee. These are supplied complete with selfstick labels and packaged in an attractive plastic library disc box to protect them from damage. We strongly recommend these Discs.

DON'T SETTLE FOR LESS, BUY THE BEST

- *10 ×* **M4** *S-S D/D 40 Track Discs* **£9**
- *10 ×* **M5** *D/S D/D 40 Track Discs* **£11**
- *10 ×* **M7** *D/S D/D 80 Track Discs* **£15**

- **3"** *Double Sided Discs* **£4** *each*

Special BULK OFFER on 5¼" DISCS

(Supplied packed in plastic storage Units)
(Lifetime warranty on Discs)

BULK PACK DISCS in lots of 100

Type	S/S 80T	D/S 80T
● Without Sleeves	£49	£74
● With Sleeves	£50	£75

ACORN WINCHESTER DRIVES

Suitable for direct connection, via the 1MHz bus, to any BBC running ADFS. These Acorn Winchester disc drives are fast and extremely reliable. Each Winchester comes complete with the Level III Econet File Server software.

10 Megabytes **£1050;** 30 Megabytes **£1549**


WATFORD's WINCHESTER DRIVES

- 20 Megabytes with ADFS **£635**
- 40 Megabytes with ADFS **£999**

WINCHESTER WORKSTATION

20 Megabyte Winchester, plus a Tape Streamer and a 400K Floppy Drive all housed in a plinth with cooling fan **£1499**

CDP 800S **CDPM 800S**



Twin 800K Double sided 40/80 track switchable disc drives mounted in an attractively finished Beige colour plinth for the BBC Micro. Supplied complete with integral power supply, cables and Utilities disc. The switches are mounted on the front panel for ease of use.

CDP 800S for BBC Micro £235

CDPM 800S for Master £245
(Securicor Carr. £7)



Harness the full potentials of your Epson RX & FX Printers. Impress your friends and business colleagues with the quality of your letters and printed material with Watford's very simple to use EPSON NLQ! (Near Letter Quality) ROM. Suitable for FX80, RX80, RX80F/T, FX100.

Look at the features:
- Simply type *NLQ80/100 and a single VDU code to use NLQ print.
- NLQ is then available without any modifications from BASIC, WORDWISE, VIEW (with NLQ DRIVER) or virtually any other program or language.
- Single codes select PROPORTIONAL type (yes even on the RX80); ENLARGED type; UNDERLINED type. These features can be used seperately or in any combination.
- Full UK character set; Standard 'pica size'; Proportional spacing; Enlarged; Underlined; Normal type.

The NLQ ROM is supplied complete with comprehensive manual.

P.S. NLQ ROM is compatible with the Torch Z80 system and can be used from within the Perfect Writer software.

Only: £25

VIEW PRINTER DRIVER for NLQ ROM

This specially written printer driver has been designed to allow View access to the full features of our NLQ ROM.
A must for all VIEW and NLQ ROM users.

£7.00
(Hi-View compatible)

THE NLQ DESIGNER

(The First & still the Best)

KAGA KP810/910 and Canon PW1080 are two superb printers, as our many thousands of satisfied customers would surely attest to. One of it's particularly strong points is the NLQ option that it offers; perhaps one of the more weaker points is the effort required to design your own custom NLQ font.

Well the solution is here NOW in the shape of Watford's NLQ DESIGNER ROM! For the BBC Micro. This powerful piece of software allows easy design and entry of a full NLQ font, with further fonts recallable from disc. Once a font has been programmed with the versatile NLQ DESIGNER, it can be saved to disc, downloaded to your Kaga (or Canon) printer, or even programmed into an EPROM (given the appropriate hardware) and then plugged directly into your printer so that it is available immediately when you turn it on. Downloadable Fonts require 6264 RAM chip fitted. Now BBC Master compatible.


A 40 or 80 track (please specify) FONT Disc containing 9 Fonts, (Italic, Courier, Courier Italic, Script, Copper Plate, Shadow, Bold, Double Print, Gothic and Greek is now supplied FREE with every package.

(P.S. This ROM is not suitable for Epson printers.)

- NLQ Designer ROM & FONT Disc **£25**
- Kaga Individual FONT ROMs **£15**

(Write in for further details).

DUMPOUT 3



A highly sophisticated screen dump ROM. This has to be the most flexible and powerful screen dump ROM yet produced for the BBC micro. It will put on paper anything you see on the screen, including all Mode 7 facilities etc. We have to admit that there is one facility that we cannot replicate – if anyone can supply flashing ink we would like to know!
The ROM also provides window setting utilities and two new OSWORD calls that allow mode 7 graphics pixels to be read and plotted using the standard graphic co-ordinate system. The latest version includes a graphic dump trigger for dumping screens from games whilst they are running.
Two commands are used to operate the dump routines:
*GIMAGE – This provides a full graphics dump of any graphics mode, plus modes 7 and '8'. There are many optional parameters but you need only specify the parameters you wish to change.

Features available include:

- Vertical and horizontal scaling through all the graphic modes and mode 7
- Rotation of the image produced through 90, 180 and 270 degrees
- Left hand indentation setting
- Screen dump window definition
- Colour grey scaling
- Two tone fast dump
- Special colour mask
- Mode 7 contrast expansion
- Mode 7 contiguous dump
- Key triggered dumps
- User port switched dumps

What does the independent press say!

Practical Electronics, May 1985
"The Dump Out 3 ROM from Watford Electronics represents one of the most sophisticated types of printer dump utilities available for the BBC Micro . . .".

"an extremely sophisticated and powerful dump utility".

"VERDICT – Dump Out 3 ROM has all the facilities which you are ever likely to need for producing printer dumps. The facilities available work extremely well and if printer dumps are something which you require, then this ROM can be recommended to help you to get the best out of your dot matrix printer".

The Micro User Feb. 1985.
"Well, here is that winner"!

"provide(s) some rather sophisticated screen dumps. Producing high resolution paper copies of graphic screens in any (graphics) mode will be the major reason for buying this ROM, and this is where Dump Out 3 performs PAR EXCELLENCE". (Our capitals for their italics.)

"The versatility of *GIMAGE (the graphics dump command) when using these parameters is amazing. Pictures of almost any size, shape, contrast or distortion may be produced without the need for a reducing photocopier or trick photography".


"Without reservation I wholeheartedly recommend the Dump Out 3 ROM as the ultimate screen dump facility for the BBC micro. It is easy to use yet highly versatile, and caters for all BBC screen modes in multitone high resolution printing. Whole, partial, rotated and scaled screens may be dumped to almost any BBC compatible dot matrix printer (see our list at the end of this advert). At £25 it must represent excellent value for money and surely cannot be beaten".

Designed for use with the following printers:

GLP, GP80/100/250, CANNON, STAR, KAGA/TAXAN, NEC, SHINWA CP80, GEMINI, EPSON MX/RX/FX, M1009, NEC PC8023, DMP100/200/400, Mannesman Tally etc.
Price including comprehensive manual

£25

ROM MANAGER




Probably the most powerful way of expanding the BBC micro is from the use of Sideways ROMs. One problem faced by the avid ROM collector is that of ROM command clashes. The solution is very simple in the form of the ROM that "Provides comprehensive management of all your installed ROMs". (Quote from BEEBUG November '84.)

Basically, ROM Manager offers you the ability to turn off any installed ROM, or to send any * command to any specific installed ROM. It is said that imitation is the sincerest form of flattery – Acorn's BBC Plus features many of the abilities of this powerful ROM.

Many more facilities available.

SPECIAL OFFER £18

THE AMX MOUSE



Now supplied with the NEW SUPERART Software ROM & Disc at no extra cost.

ONLY: £65 (carr £1.50)

We are giving away, absolutely **FREE,** our popular Colour Art software package worth **£15** with every AMX Mouse package purchased from us.

AMX DESK Package	**£19.00**
AMX UTILITY Package	**£11.00**
AMX SUPERART Package	**£42**
AMX PAGE-MAKER Pack Best desk-top publishing software. Works with keyboard, joystick and AMX Mouse	**£39**
AMX 3D ZICON Disc	**£20**
AMX Database Disc	**£20**
AMX XAM Educational	**£20**
AMX MAX: A gem of desktop (ROM)	**£17**

RB2 MARCONI TRACKER BALL


This popular unit is supplied complete with software. Price: **£50**

FLEET STREET EDITOR

Software pack **£35**

TRANSFEROM

(Tape to Disc Utility)



Not compatible with 1770 DFS.

This advanced and sophisticated utility ROM for the BBC Micro has the following features:


- Fully menu driven for ease of use
- Copes with locked programs
- A very comprehensive built in copying features
- Copies very long adventure games
- Supplied with comprehensive manual

TRANSFEROM is now available in BOTH single and double density versions. The single density version works with both the Acorn and Watford single density DFSs. The double density version works with the Watford DDFS system only.

TRANSFEROM takes your software on tape and saves them onto disc. TRANSFEROM does not stop when one disc is full; you just insert another disc in and carry on with that one! Surely this is the most valuable investment you could make if you have tape software that you wish to transfer to disc! Please specify version required – Single or Double Density.

£25.00

DIAGNOSTICS DISC



The BBC micro is a very complex machine and thus diagnosing a fault can be very difficult. Until now, the only way to discover the nature of a fault was either to find a competent friend with a large degree of patience or to find your nearest dealer and pay him to find out what is wrong.

At Watford Electronics, we realise how difficult it can be when faced with a problem, finding yourself a long way from your nearest dealer, or even just uncertain about your Beeb's health, but not wanting to waste time and money taking it to be looked at.

The solution to these problems is here now, in the form of the Watford's Diagnostics Disc. This excellent utility is specially designed to test out the following areas of your Beeb:

RAMs, ROMs, ULAs, Sound, Keyboard, Disc, RS423, ADC, User Port, Printer Port, Cassette, Joysticks, Speech, Disc Drives, 6502 and Z80 2nd Processors.

This utility is an invaluable aid for all those who take the reliability of their system seriously. A comprehensive manual provides full operating details and a list of possible causes and remedies for any faults that you may find along the way. The package also enables a permanent equipment and service record to be maintained.

Only £20.00

NEW LAUNCH

THE BBC PLUS ROM BOARD

Specially designed for all BBC Plus users, this board sits in an external box, and will accept either 10 off 16k EPROMs, OR 10 off 32k EPROMs.

With the 32k EPROMs, only 5 can be 'online' at once (that's all the B+ can address, as each chip 'holds' two normal sockets worth), but you can swap between the two banks if necessary. With the 16k EPROMs, you can obviously address them all at once. An extra card can be added to permit 2 banks of 10 EPROMs to be used (again with only one bank available at once).

The ROM box, which has its own mains power supply, and connects to the BBC Plus via a specially designed card (which is a buffered card for your peace of mind) permits easy access to the EPROMs via the hinged lid. NO soldering is required for this board.

ROMAS

THE CROSS ASSEMBLER AND MACRO EDITOR FOR SERIOUS PROGRAMMERS!

ROMAS is a carefully designed, sophisticated yet simple to use, development system for serious assembly language programmers. Using the BBC as the development system, you can choose your target system from the following processors:

6502, 65C02, Z80, 8085, 8041, 6809 and Z8
P.S. This includes the Acorn 6502 & Z80.

A give away at . . . **Only £29**

Please specify 40 or 80 track disc when ordering.

ROM-SPELL

"way ahead of any competition"



ROM-SPELL is probably THE most advanced and fastest spelling checker available for the BBC Micro. Printed below are some extracts from a recent independent review (A&B Computing Nov. '85), which we feel sure will convince you that this is THE only spelling checker worth considering.

"The editing system is very neat and simple, instead of replying to queries and beeps all of the time . . ."

"The other feature which places ROM-SPELL way in front of any competition is the ability to examine the user dictionary, so any spelling mistakes that have found themselves on the disc can be examined and taken out if necessary".

". . . that it is compatible with many of the popular word processors on the market is a good indication that ROM-SPELL is going to be a very popular product indeed".

". . . ROM-SPELL is by far the best spelling checker for the unexpanded BBC B (with or without word processor). It boasts features which are hard to find on conventional spellcheckers on CP/M and MSDOS, namely Spellstar and has a speed/performance ratio of roughly the same as its CP/M cousin. The difference is that the CP/M version would cost the best part of £500".

". . . and with such vital house keeping features as an ambiguous word checker, the ability to edit the user dictionary, a comprehensive manual that is both easy to read and actually ENJOYABLE to learn from, . . . I feel confident that ROM-SPELL will woo the word processing public with no problems at all".

Compatible with: View, Wordwise & Wordwise +.

Don't settle for less, Buy the best.

£25

(Not compatible with 1770 DFS)
(Please state 40 or 80 track disc)

BBC MICRO BUSINESS/ WORD-PROCESSING PACKAGE


A complete word-processing package (which can be heavily modified to your requirements, maintaining the large discount). We supply everything you need to get a BBC micro running as a word-processor. Please call in at our retail shop to discuss your particular requirement and a demonstration.

EXAMPLE PACKAGE

BBC Master 128K Micro, View wordprocessor, Viewsheet, Basic Editor, Terminal Emulator, Twin 800K 40/80 track double sided Disc Drives, Zenith Hi-Res green monitor, Brother HR15XL professional quality Daisy Wheel printer, Gemini Database, Spreadsheet, Beebplot Graphics, Cashbook, Final Accounts, Mailist, Easiledger, Invoice & Statements, and Stock Control packages on disc with manuals.

Only £949

COPY HOLDERS



How often have you been about to type hand written notes into your computer when you find that there's nowhere to rest the paper or that your notes are resting at the wrong angle to read the type? Whether the notes be your latest program or the draft of a new trilogy, the new Manuscript Holders from Watford are superb for holding your paper at the ideal height and angle to allow you read and type in ease and comfort.

Available in desk resting and shelf clamping versions, these two units hold your paper firmly by means of a magnetic ruler and a clip grip.

Mounting to a convenient flat surface, the two joint anglepoise Manuscript Holder allows the paper to be positioned at virtually any convenient angle whilst only taking up a fraction of the surface area that the paper being held does.

The smaller desk resting Manuscript Holder is useful for the more organised desk where the problem is simply holding the paper at the right angle.

Whatever desk arrangement you use, surely you deserve a Watford Manuscript Holder!

Amazing value at only
Desk Top **£10** (carr. £2)
Angle poise **£14** *(carr. £3)*

All prices in this advert are exclusive of VAT.


REPLICA 3

This new improved REPLICA 3 from Clares is a very powerful disc based TAPE to DISC Utility. It now transfers even more programs than ever before. Replica 3 will not work with all programs but then neither will anything else. 30,000 Replicas have been sold to date. It has to be good.

£13 (40 or 80 track)

Continued ——→

SIDEWAYS ZIF SOCKET



Allows you to change your ROMs quickly and efficiently, without opening the lid. The ZERO INSERTION FORCE (ZIF) socket is located into the ROM Cartridge's position.

- Very simple to install. NO SOLDERING required. The ZIF (Zero Insertion Force) eliminates the possibility of damage to your ROM pins when inserting & extracting.
- The low profile of the socket allows unrestricted access to the Keyboard.
- All data and address lines are correctly terminated to ensure correct operation of suitable ROMs with the BBC micro. We also supply a purpose designed see-through storage container with anti-static lining, allowing you to store up to 12 ROMs, protecting them from mechanical and static damage.
- This versatile hardware solves the problem of running out of socket space. Simply lift the ROM from the ZIF & insert a different one (No pulling or pushing of Cartridges. It is a must for all professionals and Hobbyists alike.)
- BBC, B+ and Master compatible.

ONLY **£15** (carr £2)

Low Profile CARTRIDGE SYSTEM

Complete System consists of: Low profile ROM Cartridge, Socket housing, Cable assembly, 5 labels and a library storage rack.

Complete System	**£12**
Spare Cartridges	**£2.50**
Spare Rack	**£1.50**

16K Sideways RAM Modules


This is it! The revolutionary design RAM Module you've been waiting for. Complete with such features as read and write protection, these new modules from Watford Electronics are ideal for the hobbyist, software developer and ROM collector.
Key points to note about this new addition to the Watford range of products are:

- Write protection (useful in a variety of circumstances).
- Read protection (allows recovery from ROM crashes).
- Compact construction.
- May be fitted in systems even with a ROM board.
- Multiple units may be fitted, even with a ROM board.
- No overheating or overloading problems.
- Free utilities disc supplied.
- Can be used as a 16K PRINTER BUFFER.
- Ideal for professional software development.
- Supplied with utilities software disc.

Only: **£29** (carr £2)

Optional extras

READ and WRITE protect Switches **£2** each
Battery for Battery Backup **£3**




This is the RAM you've been waiting for!! This battery backed up, write protectable 16K sideways RAM board allows you to run from disk every sideways ROM available. Beware of other sideways RAM boards which are not backed up as certain ROMs will not run in these boards even though the RAM can be write protected. The Battery Backup facility allows retention of DATA after power off. On switch on the Micro will think the WATFORD DISC RAM is a ROM. Features available are:


- No soldering or modifications to BBC micro necessary.
- Plugs into normal ROM socket fitting neatly under the keyboard allowing room for other add-ons.
- Easy to use. Comes with disk based software to SAVE and LOAD ROMs. Allows you to make backup copies of your ROMs.
- Disk software can be copied onto other discs when disc is full.
- No messy plugging and unplugging of your ROMs. Simply Load the one you want into DISC RAM.
- Ideal for Professional users to develop ROMs. Backup facility allows testing of final versions without using EPROMs.
- The switch provided allows backup and write protection to be switched off externally.
- Can also be used as 16K printer buffer RAM in conjunction with our Buffer & Backup ROM.

New Low Price: £32 (carr £2)

P.S. 16K DISC RAM Board is not designed to work in conjunction with a Sideways ROM Board.

SOLID STATE 16K SIDEWAYS RAM





This new unit from Watford, which utilises the latest in Static RAM technology, offers 16k of easy-fit sideways RAM in a very compact unit with a footprint no larger than a standard 28pin EPROM. With only a single flying lead terminating in a mini hook-on probe, to fit, (no soldering required) this compact unit works with any BBC Micro with or without a ROM board. ***Compatible with BBC B Plus.*** Like our other 16K RAM Modules, this unit is very simple to fit.


Only **£28** (carr 2)
Supplied complete with comprehensive software on Disc, Operating and fitting instructions.

Do you find the 16K Sideways RAM Units confusing? If so, we have compiled this quick questionnaire to help YOU decide which is the best one for you. If the answer to any of the questions is yes, then use the index number to select from the boards below. Options in brackets indicate possible secondary choices.
Do you require:

- Sideways RAM for a BBC B? Choose 1, 2 or 3.
- Sideways RAM for the B+? Choose 3.
- A small, basic module? Choose 3.
- A sideways RAM module for a ROM board? Choose 1 or 3.
- An easy to use utilities disc? Choose 1, 2 or 3.
- More than one module installed at once? Choose 1 or 3.
- To use sideways RAM as a printer buffer? Choose 1 or 3.
- Battery Backup? Choose (1) or 2.
- Write protect for RAM (makes ROM look like RAM)? Choose (1) or 2.
- Read protect (allows recovery from crashes)? Choose 1.

Key:
1) 16k Sideways RAM Module
2) 16k Disc RAM
3) Solid State 16k Sideways RAM

SOLDERLESS SIDEWAYS ROM SOCKET BOARD



In the May 1986 Micro User's independent review, the writer concludes, "The board has been well laid out. Its position is much better than others – not over the HOT RAM chips and further away from the disc controller area". "I give the solderless ROM board the thumbs up and wish it success".

This brand new board from Watford Electronics is designed specifically for those wishing to add a ROM board to their own BBC without the need to perform any soldering.

This new board expands the total possible number of ROMs in a BBC from 4 to 16.


Unlike our competitors inferior boards, the ONLY upgrade required for fitting battery backup to the Watford Solderless ROM board (all Watford ROM boards, actually) is the fitting of the battery itself. (No other expensive components are required.)

- The key features of this new, no fuss, easy to install quality product from BBC leaders Watford Electronics are as follows:
- Increase your BBCs capacity for ROMs from 4 to 16.
- **No soldering required.**
- Very low power consumption.
- Minimal space required.
- Compatible with Torch, DDFS, RAM Card, 2nd Processor, etc.
- Socket 14 takes two 6264 RAM chips.
- Read protect to make RAM "Vanish"; allows recovety from ROM crashes.
- Battery backup option for RAM chips.
- Supplied ready to fit with comprehensive instructions.

Price: Only £34
Battery backup fitted **£36**
(carriage £2)

Watford ROM/RAM CARD

A must for all serious users



Watford Electronics announced the first ever commercial ROM board for the BBC micro, the Watford Electronics 13 ROM Socket Board 3 years ago. Following the success of this board, we have designed what probably represents the ultimate in expansion boards, the new Watford Electronics ROM/RAM board. This highly versatile and sophisticated board represents the latest in "2nd generation" sideways ROM technology for the BBC micro, designed to satisfy the serious BBC user.

- NO SOLDERING required to fit the board.
- NO overheating problems.
- No User Port corruption (avoids problems with the mouse, modems, Eprom Programmers, etc.)
- Fully buffered for peace of mind.
- Firm mounting in BBC micro.
- Compatible with all BBC micros (not BBC+ or Master).
- Total number of ROMs increased from 4 to 8.
- Up to 8 banks of sideways RAM (dynamic).
- Option for 16k of Battery backed CMOS RAM (CMOS RAM needs one ROM socket).
- Software Write protect for ALL RAM.
- Read protect for CMOS RAM (ALLEVIATES crashes during ROM development).
- Separate RAM write register (&FF30 to &FF3F).
- Automatic write to currently selected RAM socket for convenience.
- Accepts any ROM.
- FREE utilities disc packed with software.
- Compatible with our DDFS board, 32k RAM Card, Delta Card, sideways ZIF, etc.
- Large printer buffer.
- UNIQUE Fully implemented RAM FILING SYSTEM (similar to the popular Watford DFS).
- ROM to RAM load and save facilities.

The SFS (Silicon Filing System) can utilise up to the full 128k of RAM (with the SFS in any paged RAM) as a SILICON DISC. This behaves as a disc drive, with all the normal Watford DFS features (including OSWORD &7F for ROM-SPELL, etc.) to provide an environment that looks like a disc but loads and saves MUCH faster.

The ROM/RAM Board plugs into the 6502 CPU socket. This leaves free all the existing ROM sockets, which can still be used normally.

Any ROM that can be plugged into the BBC micro's own ROM sockets may be used in the ROM/RAM Board.

The ROM/RAM Board is supplied with all ordered options fitted as standard. Upgrade kits (with full instructions) are available for all of the options, for later.

Please write in for further details.

INTRODUCTORY PRICES:

- *ROM/RAM card with 32k dynamic RAM **£43***
- *ROM/RAM card with 64k dynamic RAM **£59***
- *ROM/RAM card with a massive 128k dynamic RAM **£89***

(carriage on ROM/RAM Card £3)

OPTIONAL EXTRAS:

- *16k plug-in Static RAM kit **£6***
- *16k Dynamic RAM for Upgrade **£7.50***
- *Battery backup **£3***
- *Read and Write protect switches ..... **£2** each*

*Complete ROM/RAM board (all options installed) **£99***

Le Modem



The MODEM from Watford

At last a professional MODEM for the BBC Micro. Unlike other 'Modem packages' this is a complete package there are no extra software costs to get 'up and running'. Of course Le MODEM is multi-standard, i.e. 300/300, 1200/75 & 75/1200 UK and BELL (USA) are all supported.

The features that make Le MODEM such good value are:

- *A complete communications terminal that transforms your BBC Micro into a very powerful World/wide data transfer system.*
- *Auto Dials, Auto answers, and is completely controlled by your micro. There are no external controls!*
- *Allows you to access PRESTEL, B.T. GOLD, THE SOURCE, MICROLINK, MICRONET, MICROWEB, THE TIMES NETWORK, MICRO LIVE (BBC TV database), CITY BB and more.*
- *Designed to be SIMPLE but SOPHISTICATED. To LOGON to a data base all you have to know is its TELEPHONE NUMBER, Le MODEM does the rest.*
- *Supplied with a comprehensive telecomms package in a 16K sideways ROM which includes a FULL PRESTEL terminal allowing TELESOFTWARE to be downloaded.*
- *A comprehensive 80 column terminal. This includes XMODEM error checked transfer protocol, to allow error free data transfer anywhere in the world!*
- *FULLY controlled by simple '*COMMANDS allowing you to control it from your own BASIC programs. To get you started we supply a FREE disc of bundled software!*
- *Connects to the 1MHz bus. A *AUDIO ON/OFF command allows you to actually hear the telephone line through your BBC micro loudspeaker.*
- *Completely self contained with internal mains power supply. (Even a free mains plug is fitted!) A *TEST facility gives ON SCREEN indication that Le MODEM is working correctly.*
- *Packaged in such as way that you need nothing else except a BBC Micro to communicate with computers all over the world.*
- *FREE 3 months subscription to MicroLink.*
- *BT Approval applied for.*

SPECIAL OFFER

Price: **£79** (carr £3)

PROHIBITED from direct or indirect connection to any telecommunication system run by British Telecommunications. Action may be taken against anyone re-connecting this apparatus.

(Price includes, Le Modem, Software ROM, Cables & Comprehensive Manual)
(Write in for further details)

Nightingale Modem

SPECIAL PRICE to our Customers

£99 (carr £3)

APPROVED

(Price includes: Nightingale Modem, Commstar ROM pack, Cables & Comprehensive manual)

Nightingale Modem without software	**Only £87**
COMMSTAR ROM package only (P&P on modem £2.00)	**£29**
Auto Dial/Auto Answer Board (non BABT)	**£48**
Auto Dial Utilities Disc	**£9.50**
OBBS Bulletin Software	**£20.00**

APOLLO

APPROVED

The NEW Modem from Watford

Following numerous requests from you, our discerning customers for an APPROVED, Low Cost – High Performance modem with Auto Dial & Auto Answer facilities as standard; we bring you the versatile APOLLO Modem. Just compare the features and look at the price (which incidentally includes the cost of the Software, manual and BBC connecting cable). We are sure you will agree that Watford Electronics in their traditional way are giving you a super 'value for money' deal.

Just look at these features:

- V21 for Bulletin boards, Microlink, Telecom Gold, etc.
- V23 for Prestel, Home Banking, and other Viewdata services.
- Reverse V23 allows User run Viewdata service.
- 1200/1200 half duplex for communications.
- XMODEM, HEX and ASCII file transmission.
- Auto Dial of given 'phone number.
- Auto Answer for User's Bulletin Board.
- 80 column terminal with split screen facility.
- Prestel text screen dump.
- Fully BABT approved.


The Apollo is attractively finished in matt black. It opens the doors to world communication to both, the Hobbyist and the Professionals alike. With baud rates varying from 300/300 Originate and Answer, 1200/75 and 75/1200 full duplex and 1200/1200 half duplex, virtually all the popular tele-services can be accessed. A comprehensive Comms ROM oversees the use of the APOLLO, providing simple commands for all the software controlled facilities. APOLLO is an ideal modem for both the first time buyer and the seasoned user. Join the Telecommunications Revolution – Buy a Watford APOLLO!

Special Launch Price: **£75**
(Carr £3)
(Write in for full specification)

BT TELEPHONE CONNECTORS

LJU	1/4A Mini Line Master	**£4.50**
LJU	1/6A Mini Line Slave	**£3.00**
LJU	2/4A Line Master	**£4.00**
LJU	2/6A Line Slave	**£2.50**
LJU	3/4A Flush Master	**£3.95**
LJU	3/6A Flush Slave	**£2.75**
LJU	10/3A Dual Splitter	**£5.50**
	4 Way BT Plug	**£0.75**

Versatile **BEEB SPEECH SYNTHESISER** Unit



The Watford Speech Synthesiser is a very flexible speech synthesis unit based upon the powerful phonemes system. This system stores the building blocks of speech (called phonemes) and allows you to combine them quickly and easily to form virtually any word imaginable.

Supplied with an advanced ROM, you are provided with a 500 word dictionary to get you started. These can easily be added to by following the notes given in the comprehensive manual.

SPECIAL PRICE £32 (carr £2)

Continued

COMPUTER CONCEPT'S ROMS

ACCELERATOR	£48
CARETAKER Basic Utility	£27
Graphics ROM	£23
Disc Doctor ROM	£24
TERMI	£27
COMMUNICATOR	£49
SPEECH ROM	£26
Printmaster	£24

Wordwise £25

Wordwise plus

£40

We are giving away absolutely **FREE,** the superb Word-Aid ROM worth £24, with every WORDWISE PLUS package bought from us.

Word-Aid

The most comprehensive utilities ROM for Wordwise-Plus

Extend the power of your Wordwise Plus word processor with this most advanced ROM from Watford. By utilising the powerful Wordwise Plus programming language, WordAid provides a whole host of extra features, all accessed via a special new menu option. This ROM has been personally approved by Mr Charles Moir, the author of WORDWISE PLUS.

- Alphabetical sorting of names and addresses.
- Text transfer options.
- Chapter marker.
- Epson printer codes function key option.
- Search and display in preview mode.
- Embedded command removal.
- Print Multiple copies of a document.
- Multiple file options for print and preview.
- Address finder.
- Label printer.
- Mail-merger.
- Number/delete/renumber.
- Clear text/segment area.
- BBC B, B+ and Master compatible.

Only **£24**

(N.B. Word Aid requires a Disc Interface in your Micro)

HI-WORDWISE-PLUS

Supplied on disc. This version requires a WORDWISE-PLUS ROM to be present in the machine. It gives up to 44k of text space on the 6502 2nd processor.

£5

Inter SHEET £40

INTER·CHART ONLY: £26

Inter-WORD

Only: £46

Special Discount price for the existing Wordwise Plus owners. Simply quote your reg. number and pay.


Only: **£39**

All Prices Exclusive of VAT

32K

SHADOW RAM- Printer Buffer

Expansion Board



A MUST FOR WORD PROCESSING

Watford Electronics now brings you the latest state-of-the-art MEMORY EXPANSION BOARD for your BBC microcomputer. Don't throw away your BBC B for a BBC B+ or BBC Master. Just plug the ribbon cable into the 6502 processor socket, and fit the compact board inside the computer. Immediately you will gain not 16K or even 20K, but a massive 32K of extra RAM!!!

- IMPROVE your WORD PROCESSING system, whether disc or cassette based. Don't wait for a slow printer – type in text while printing. TWO JOBS DONE SIMULTANEOUSLY and £100+ saved on a printer buffer.
- "VIEW" Wordprocessor users can now type in letters in 80 columns and have up to 28,000 bytes free – 5 times as much as normal.
- In WORDWISE (or WORDWISE-PLUS), preview in 80 columns with the full 24K of text in memory. This product is recommended as an ideal complement by Computer Concepts.
- Combine GOOD GRAPHICS and LONG PROGRAMS. Use the top 20K of the expansion RAM as the screen display memory, leaving all the standard BBC RAM free for programs. Benefit from MODE 0/1/2 graphics and 28K of program space.
- Use the FULL 32K or the bottom 12K of the expansion RAM as a PRINTER buffer for PARALLEL or SERIAL printers, sound channels, RS423 etc. Print large text files while running long graphics programs, and have all your buffer options available as well (*FX15,21,138,145,ADVAL etc). Please note only a 12K printer buffer can be used with Wordwise or Wordwise-Plus, due to the way they are written.
- Ensure COMPATIBILITY with a vast range of hardware (including our ROM board, the ATPL ROM boards, double density boards, second processors), and software (including BASIC, TOOLKIT, VIEW, WORDWISE (1.20+), WORDWISE-PLUS, Music 500's AMPLE). This is because our board, unlike those of our competitors, is connected to the computer by a ribbon cable and has the power consumption of a couple of ROMs!
- Achieve EASY OPERATION with ROM based software. A large range of commands is available for machine code and BASIC users, including some useful *HELP messages, and a comprehensive manual is supplied free.
- Unique facility to turn ROMs off and on again. Unlike all other ROM managers, this feature does not use 'unofficial' memory. Two bytes of normally user-inaccessible memory on the RAM card are used to ensure ROMs are disabled WHERE OTHER ROMS FAIL.

Only: £59 (carr £2)

(Price includes a comprehensive manual and the ROM)

SPECIAL OFFER

Acorn's Speech Synthesiser Package

Complete with manual in its original packaging

Clearance price Only: **£19**

INCREDIBLE WORD PROCESSING DEAL ! ! !

Watford Electronics, already renowned for quality products at discount prices, are offering, the truly spectacular BARGAIN OF THE YEAR!

A Watford's 32K Shadow RAM Card – Printer Buffer and the much sought after, Computer Concepts' Inter-WORD, (a very powerful package) All this at an astounding price of:

Only £79 (carr £2)

DATAGEM

Gemini's popular Database package

Only: £34

VIEW

VIEW WORDPROCESSOR 2.1 ..... **£37**

VIEW 3.0 ROM

Price: Only **£56**

HI-VIEW

A special version of VIEW designed for use with 6502 2nd Processor. Available on disc, it offers 47K of text memory.

£36

VIEWSHEET (Acornsoft)	**£37**
VIEWSTORE	**£37**
VIEWSPELL with 80 track disc	**£29**
VIEWPLOT Disc	**£22**
VIEW-INDEX	**£14**

Watford's own Sophisticated VIEW PRINTER DRIVER for Epson FX80 & KAGA KP

Only £10

VIEW DRIVERS FOR JUKI & BROTHER HR15 PRINTERS

Only £10

VIEW/VIEW SHEET PRINTER DRIVER for SILVER REED

(Officially approved by Silver Reed)

Only: £10

MINI OFFICE II (tape) £14.50

ARIES CORNER

Aries B-32 Shadow RAM Card

18 months of intensive research and development have produced a worthy successor to the widely acclaimed Aries-B20; the revolutionary Aries-B32. This 'second generation' expansion board features 32k of RAM and a 16k ROM socket.

Like the BBC B+, the B32 provides 20k of shadow screen RAM and 12k of sideways RAM. Unlike the B+, the B32 has simple software commands which allow the user to reconfigure the RAM as 16k of shadow RAM and 16k of sideways RAM, or all 32k as sideways RAM.

With the B32, the programmer gets up to 28k of RAM available for Basic, Logo, Comal, Forth, Lisp and BCPL programs in any screen mode. The business user gets extra memory for View, ViewSheet, Wordwise Plus and many othr applications. For advanced applications, the scientific user gets access to a massive 47k of data storage using the Acorn approved *FX call.

Sideways RAM enables you to load sideways ROM images from disc, allowing you to have a large library of sideways ROMs (subject to the copyright holder's permission) stored on disc. The B32's sideways RAM can also be used to extend any operating system buffer (such as the printer buffer) or to load tape programs into a disc system.

The B32 simply plugs into the processor socket on your BBC micro – no flying leads to connect and no soldering. Provision of the on-board ROM socket means that the Aries-B32 control ROM does not use up one of your existing ROM sockets.

Price: B-32 **£80** (carr. £2)

Aries B-12 Sideways ROM Board

This board is extremely well made, simple to install, reliable when fully loaded and compatible with the Aries B-20 and the Aries B-32. For the business user or educationalist, the compact and secure internal fitting is ideal, with the ROM board tucked neatly inside the lid where it will not cause overheating problems. The serious software developer and the hobbyist may prefer to mount the board externally, giving instant access to the sockets for experimental purposes. A zero-insertion force (ZIF) socket may be fitted to the board to enhance this mode of operation.

The B12 provides a total of twelve sideways ROM sockets (the four in the original machine are replaced by the twelve on the board), all fully accessible by the MOS sideways ROM system. In addition, there are two sockets for sideways RAM, giving up to 16k of RAM using 6264 static RAM chips.

The B12 system consists of two parts: a large detachable 'mother board' which carries the extension ROM sockets and a small 'base board' on a short ribbon cable, which plugs into the existing sideways ROM sockets. This two-board design eliminates the reliability problems previously associated with some other ribbon-cable based systems.

If you do not have an B32 or B20, a small adaptor module (the Aries B-12C) is available at a nominal cost. The 6264 static RAM chips used to provide the sideways RAM are advertised elsewhere in our advert.

Price:
Aries B-12 **£40.** Aries B-12C **£5**

GRAPH PAD 2

Supplied complete with Software
£60 (Carr. £3)

ARIES B-488 IEEE-488 INTERFACE UNIT

The Aries-B488 is an interface unit to enable the BBC micro to control and monitor IEEE-488 bus systems. The IEEE-488 bus (also known as the 'GPIB' or 'HP-IB') is the standard method of interconnecting programmable laboratory instruments and control equipment. Using the B488, up to 15 devices may be connected in a single high-speed data network.

Aries B-488 Unit: **£238** (Carr £3)

THE ARIES RANGE HARDWARE REQUIREMENTS

Aries B-32 – BBC B, MOS 1.20, hardware plugs into CPU socket.
Aries B-12 – BBC B, MOS 1.20, hardware plugs into all four sideways ROM sockets and connects to the B32 or the B20. The adaptor Aries B-12C module is necessary where these are not fitted.
Aries B-488 BBC B, MOS 1.20, Hardware plugs into 1MHz Bus.

BEEBMON

The most powerful machine code monitor for the BBC Micro **£24.**

DISASSEMBLER ROM

ONLY **£16**

THE INVESTIGATOR

This sophisticated Utility program on disc, enables you to make security back-up copies of most of your valuable Disc Software. Makes full use of all 8271 (will not run with double density DFSs) facilities to discover the precise format of your protected disc so that an exact copy can be produced. Supplied with detailed instructions. Please specify 40 or 80 track disc when ordering.

Only **£20**

CREDIT CARD 24 HOUR
Ansaphone Hot Lines
(0923) 50234/33383

النور

ARABIC ROM for the BBC Micro

The ALNOOR ARABIC ROM converts your BBC into a bilingual computer. New keytops provide both English and Arabic symbols. Two sets of Arabic symbols are provided for use in either context sensitive or insensitive operation.


20, 40 and 80 column operation. Compatible with ASMO (449). English/Arabic printer interface software. Numeric entry from either left or right of number. Communications software to send or receive 7 or 8 bit data.

Different shapes of Vowels (e.g. Shadda, Fatha, etc). Different shapes of Hamza. Full English and Arabic character sets with all special characters.

£85

(Price includes Alnoor ROM, Operating Manuals & a full set of Arabic/English Keytops)

PLINTHS FOR BBC MICRO, MASTER & PRINTERS



Protect your computer from the weight and heat of your monitor. The BBC micro plinths have slots for maximum ventilation. The single plinth is suitable for a BBC and monitor, whilst the double height version provides enough room for our stacked or side-by-side dual disc drives or TORCH Disc pack, to be placed in the centre section. If you use our stacked drives, the remaining space can be used for further peripherals e.g. Speech Synthesizer, EPROM programmer or simply stationery. The computer slides neatly in to the lower section allowing easy access to remove the lid. The printer plinth is equally sturdy but without the cooling slots. It allows for access to the paper from the front as well as from the rear, (a facility not often thought of in similar products) if the paper is located beneath the plinth. This is a very convenient way to work especially if your work area is not deep enough to take the printer and paper separately.

SINGLE BBC PLINTH ..... **£11** (carr. £1.50)
DOUBLE BBC PLINTH ..... **£20** (carr. £2.00)
PRINTER PLINTH ..... **£10** (carr. £1.50)
SINGLE MASTER PLINTH ..... **£14** (carr £1.50)
DOUBLE MASTER PLINTH ..... **£25** (carr £2.00)

OFFICE MATE

The popular Database, Spreadsheet, Beebplot and Wordprocessor on Disc
£10

OFFICE MASTER

The popular Cashbook, Final Accounts, Mailist, Easiledger, Invoice & Statements and Stock Control
£21

Money Management

This disc based software allows individual transactions to be stored and retrieved for upto 5 Bank a/c and 5 Loan accounts.

Price: Only **£11**

L.B.O. Rom
Life & Business Organiser

Use LBO to organise your life from today until 1999! It can handle literally hundreds of multi-line messages, as many as you are ever likely to need. Despite the very wide range of facilities offered, this professional program is VERY easy to use and requires absolutely NO knowledge of computers. A vital aid to your everyday life, LBO is GREAT FUN TO USE!

Price only: £17

D D D Suite
Integrated Software System


-BASE **£12**
-CALC **£12**
-PLOT **£12**
COMBO PACK All 3 together **£26**

Continued ——→

BOOKS (No VAT on Books)

30 Hour BASIC (BBC Micro) £7.95
40 Best machine Code Routines £7.95
6502 Assembly Language Program £19.95
6502 Application £11.95
6502 Assembly Lang. Subroutines ... £19.95
6502 Development System £7.50
6502 Machine Code for Humans £7.95
68000 Assembly Lang. Programming .. £19.95
68000 Machine Code Programming £13.00
68000 Programming the £22.95
6809, Programming the £16.95
A User Guide to Wordwise Plus £9.95
A Young persons Guide to BBC Basic £5.95
Advanced Disc User Guide £16.95
Advanced BASIC ROM User Guide £9.95
Advanced Machine Code Technique for BBC £7.95
Advanced Programming for BBC £6.95
Advanced User Guide for BBC £15.95
Advanced Graphics with BBC £9.95
Assembly Language Programming on BBC Micro £11.50
Advanced Programming Techniques for the BBC Micro £8.95
Adventure into BBC BASIC £6.95
Applied Assembly Lang. for BBC £9.95
Assembler Routines for the 6502 ..... £7.95
Assembly Language Programming FOR the BBC Micro £8.95
Assembly Language Programming on the BBC & Electron £8.95
Basic Programming on the BBC Micro £6.95
Basic ROM User Guide £11.95
Basic User Guide for BBC Micro £10.00
BBC B+ User Guide £14.95
BBC BASIC £5.95
BBC Forth £7.50
BBC Hardware Projects £8.95
BBC Machine Code Portfolio £7.95
BBC MAster 128 High Flyer £10.95
BBC Micro Advanced Ref. Guide £10.95
BBC Micro Advanced Programming £10.00
BBC Micro Book BASIC Sound & Graphics £7.95
BBC Micro ROM Book £9.95
BBC Micro Disc Companion £8.95
BBC User Guide £10.00
BCPL User Guide £14
Complete FORTH £6.95
CP/M - 86 User's Guide £19.95
CP/M Bible £16.50
CP/M Handbook with MPM £9.95
CP/M Plus Handbook £13.95
CP/M Soul of £16.50
CP/M The software BUS £8.95
Creative Animation & Graphics £7.95
Creative graphics on BBC Micro £7.50
Disc Drive Projects for Micros £5.45
DISC FILING SYSTEM (DFS) Operating Manual for BBC £6.95
Disc Programming Techniques £9.95
Discovering BBC Micro Machine Code £6.95
Disc System for the BBC Micro £6.95
Exploring FORTH £6.95
FORTH on the BBC Micro £7.50
Functional Forth for the BBC Micro £5.95
Games BBC Micro Play £6.95
Graphs & Charts on BBC Micro £7.50
Hackers Handbook £4.95
Hackers Handbook - New £6.95
Handbook of Procedure & Functions for the BBC Micro £6.95
Interfacing & Robotics on BBC £15.95
Interfacing Your BBC Micro £8.95
Into View £4.50
Introduction to COMAL £9.50
Introduction to LOGO £6.95
Introducing 'C' £9.95
Introducing CP/M on the BBC Micro Z80 2nd Processor £9.95
Introducing LOGO £5.95
Introduction to FORTH £8.95
Introduction to PASCAL £17.95
ISO -PASCAL Reference Manual £9.95
Let your BBC teach u to program £5.45
LISP 2nd Edition £14.95
LISP, A Beginners Guide to £10.95
LISP the Language of Artificial Intelligence £9.95
Logo Programming £9.95
Mysteries of DISC DRIVES and DFS REVEALED £5.95
Mastering CP/M £17.95
Mastering the Disc Drive £7.95
Master Advance Reference Manual .. £19.95
Master Reference Manual Part 1 ..... £14.95
Master Reference Manual Part 2 ..... £14.95
Micronet Handbook £6.95
Programming the 6502 ..... £16.95
Programming the Z80 ..... £19.95
Sensing & Control Projects for BBC £5.95
S-PASCAL on BBC Micro £7.50
Structured Basic £7.95
Structured Prog. with BBC BASIC £6.50
Termulator Manual £4.95
The Complete FORTH £6.95
The Complete Programmer £5.95
The Epson FX/KAGA PRINTER Commands REVEALED £5.95
Turtle Graphics on BBC Micro £7.50
Using Floppy Discs with BBC Micro £5.95
View 3.0 User Guide £10
View Guide £4.50
Viewsheet User Guide £10
Viewstore User Guide £10
Using BBC Basic £4.95
Wordprocessing BBC Beginners Guide ... £7.95
Wordstar & CP/M made easy £7.45
Wordwise Plus Guide £9.95
Z80 Applications £15.95
Z80 Assembly Language Programming £19.95
Z80 Reference Guide £9.95

EPROM PROGRAMMER



The Watford Electronics' EPROM programmer for the BBC micro is a high quality self contained package. Programs all popular EPROMs from 2K to 16K: 2716, 2516, 2532, 2564, 2764 and 27128. All manufacturers' specifications have been followed to program EPROMs at the correct speed – wrong timings could destroy your EPROMs. The unit has its own power supply so does not put heavy loads on the BBC power supply as do some other units. Connects directly to the 1MHz bus following all Acorn recommendations on addressing and bus loadings.

SOFTWARE PACKAGE
The software is supplied on an EPROM which plugs into the Micro and is instantly available with a single command (no time wasting as on Cassette/disc loading). It is a fully purpose designed and ingegrated package to simplify ROM development. The system is menu driven with many prompts to avoid any accidents.

Software facilities include:
Load File – Save File – Down Load EPROM – Program EPROM – Verify – Blank Check – Editing of memory contents prior to programming.
Also included is an automatic system to allow Basic programs to be put in EPROM and accessed through the *ROM filing system. More than one program may be put in an EPROM. All these facilities and more are explained in the comprehensive and clear 15 page manual.


SPECIAL OFFER £69 (£3 carr.)

TEX EPROM ERASERS

EPROMs need careful treatment if they are to survive their expected lifetime. Over erasure of EPROMs very rapidly turns them into ROMs! The TEX erasers operate following the manufacturers specifications to give the maximum possible working life by not erasing too fast. We use these erasers for all our own erasing work.

- **ERASER EB** – Standard version erases up to 16 chips. **£28** (carr £2)
- **ERASER GT** – Deluxe version erases up to 18 chips. Has automatic safety cut-off to switch off the UV lamp when opened. **£30** (carr £2)
- Spare UV tubes. **£9**

BEEB VIDEO DIGITISER



Using any source of composite video (colour or monochrome) and the Watford Beeb Video Digitiser, you can convert an image from your camera into a graphics screen on the BBC Micro.

This uses the full graphics capacity of the BBC micro in modes 0, 1 or 2. The video source may be a camera, video recorder or television, and is connected via the video output socket.

Images produced can be compressed, stored to disc, printed on an Epson compatible printer, directly used to generate graphics, analysed for scientific and educational use or converted to other formats e.g. Slow Scan TV or receiving a picture from a remote camera using a modem.

The output from the digitiser exactly matches the graphics capability in each mode, with up to 8 levels of grey in mode 2. The unit connects into the User Port and automatically scans a complete picture in 1.6 seconds.

Both the black and white levels can be adjusted manually for the optimum picture, or switched to automatic for unattended use. The image produced can be reversed if necessary.

Full controlling software is supplied on a normal sideways ROM and this is easily accessed via additional * commands. The package is designed to allow easy input of complex screens and give full access of the data to the user. Once on the screen, the image can be used as a normal graphics screen, allowing any of the usual graphics commands in BASIC or other ROM's to work on it.

A special print dump routine is included with the driver programs. This is specially designed to produce a fast, correctly proportioned picture, with reduced "contouring", resulting in an accurate reproduction of the original image.

Detailed examples of driving this unit from BASIC or other languages are all provided in the extensive manual supplied.

£110 (Carr. £3)

(Price includes: Digitiser Unit, Software in ROM & a Comprehensive Manual)
(BBC B+ and Master compatible, except Master with Econet)

Magazine Maker

(As seen on TV)
A combination of the AMX Pagemaker and Watford's Beeb Video Digitiser.

Using any video that provides a composite signal and the digitiser, images from a camera or TV can be converted into a graphics screen on the BBC Micro.

They can then be used within AMX Pagemaker to illustrate magazines or newsletters – in fact anything that needs to be created on A4 size paper.

With Pagemaker's many features, a variety of pictures can be composed – the only limit being the imagination.

Pictures can be doctored using Pagemaker's graphics option to produce any number of effects.

Text can be formatted around the digitised photo on screen using the facilities available, which include 16 typefaces, character and pattern definer, text formatting and the ability to load in wordwise and viewfiles plus much more.

Once created the picture can be printed out.

The Magazine Maker is suitable for any use that requires illustrated documents.

Complete Package **£129.00** (carr. £3)

VOLTMACE JOYSTICKS

Delta 3B Single Joystick	£10
Delta 3B Twin Joysticks	£16
Delta 14B Single Joystick	£12
Delta 14B/1 Adaptor Module	£12
Transfer Software Disc/Tape	£7

ROM EXTRACTION TOOL

This extremely useful tool allows you trouble free chip removal from your computer by distributing the removal force over the whole body of any 24 or 28 pin chip.

Price: **£2**

SURGE PROTECTOR Plug

Fitted in place of your normal mains plug, this device protects your equipment against mains surges. Nearby lightning strikes, thermostats switching and many other sources which put high voltage transient spikes on to the mains. This can lead to data corruption in memory and on disc and can result in spuriously crashing machines. A must for every computer user.

Protection for only **£6.99**

ATTACHE CARRYING CASE for BBC Micro

The Attache carrying case is attractively finished in mottled antique brown leatherette. The case is made of tough plywood, providing a very solid and safe way to carry your BBC micro. There is room provided to fit all the leads necessary behind the computer and manuals in the front.

Locks supplied with two keys. Price **£13** (£2 carr.)

28 pin ZIF SOCKET (Textool) **£6.95**

28pin DIL HEADER PLUG

SOLDER type	£1.50
IDC CRIMP type	£1.95

SPARES for BBC Micro

Keyboard	£46	Keystrip	£2
UHF Modulator	£4	Case	£25
Speaker Grill	£1	Speaker	£2
Power Supply	£59	Keyswitch	£1.50

Replacement FLEXIBLE KEYBOARD CONNECTOR

£3

8way DIP SWITCH **£0.85**

CONNECTING LEADS

(All ready made and tested)

CASSETTE LEADS 7 pin DIN Plug to 5 pin DIN Plug + 1 Jack Plug	£2.00
to 3 pin DIN Plug + 1 Jack Plug	£2.00
to 7 pin DIN Plug	£2.50
to 3 Jack Plugs	£2.00
6 pin DIN to 6 pin DIN Plug (RGB)	£2.50

DISC DRIVE POWER LEADS
Supply from BBC power supply to standard Disc Drive connector.
Single **£3.00** Dual **£3.75**

DISC DRIVE INTERFACE LEADS
BBC to Disc Drives Ribbon Cable
Single **£4** Twin **£6**

MISCELLANEOUS CONNECTORS

	Plugs	Sockets
RGB (6 PIN DIN)	30p	45p
RS423 (5 pin Domino)	40p	50p
Cassette (7 pin DIN)	25p	65p
ECONET (5 pin DIN)	20p	30p
Paddles (15 pin 'D')	80p	200p
BBC Power Plug 6 way	80p	–
Disc Drive Plug 4 way	75p	–
6 way Power Connector		95p

Watford Electronics' Dealer's List

UNITED KINGDOM

AKHTER INSTRUMENTS LTD,
Akhter House, Perry Road, HARLOW, Essex

Beebug Retail, Dolphin Place, Holywell Hill, St. Albans.

Cirkit Distribution Ltd,
Park Lane, Broxbourne, Herts.

C.J.E. Micros, 78 Brighton Road, Worthing, West Sussex. Tel: 0903 213361.

Gemini Marketing Ltd,
Exmouth, Devon

HCCS, 575/583 Durham Road, Low Fell, Gateshead, Nr. Newcastle Upon Tyne.
Tel. 091 4870760.

Mancomp Ltd, Printworks Lane, Levenshulme, Manchester. Tel: 061-224 1888/9888.

Microman Computers, Rainford Industrial Estate, Mill Lane, Rainford, St. Helens

Peartree Computers Ltd, St. Georges Street, Huntingdon Cambs.

Verospeed Ltd, Boyatt Wood, Eastleigh, Hants.

OVERSEAS DEALERS

Absolute Electronics, Rewal House, 208-210 La Trobe Street, Melbourne, 3000, Victoria, Australia. Tel: (03) 663 2411.

Alpha Computer Co, Shop 314 Chi Fu Commercial Centre, Chi Fu Fa Yuen, Hong Kong. Tel: 5-506592.

Computer Distribution Company, Parklaan, 47, B09300 Aalst, Belgium.

Lendac Data Systems, Unit 31, IDA Enterprise Centre, Pearce Street, Dublin 12. Tel: 710796.

Scientex P.V.B.S., Zilversmidstraat 2, B-2000 Antwerpen, Belgium, Tel: 03 233 59 06

Techno-matic Data, Holbergsgade 19, 1057 Kobenhavn K, Denmark

Velobyte, Scheaedyksadyk 5a-6a, 3011 EB Rotterdam, Holland, Tel: (010) 413 8197/414 5171.


Viking Tecno, Vestergade 12.1, 9620 Aalestrup, Denmark, Tel: 08 642522

Viglen Console Unit

Enhance the appearance and convenience of your BBC Micro with the Viglen console unit.

£42 (carr. £4)

4 WAY MAINS DISTRIBUTION SOCKET



4 way top quality mains trailing sockets. Supplied wired up with mains plug ready for use. Can be screwed to floor or wall if required. Very useful for tidying up all the mains leads from your peripherals. Allows the whole system to be switched on from one plug. **£9.50** (carr £1.50)

ACORN MUSIC 500

BBC B, B+ & Master Compatible.

Now available, a limited number of Music 500s at give away prices. For under half the normal cost of the Music 5000 (which is, basically, the same hardware) you can receive the music package that has already thrilled thousands.

CHRISTMAS PRICE £66

(carr £4)

Software Disc 'Mu-500' has 13 tunes **Only: £6**

CHIP SHOP

8271	£36	Acorn BCPL	£42
DS3691	£3.50	BCPL Calc Pack	£15
DS88LS120	£5.25	BCPL Stand Alone Generator	£36
LM324	£0.45	Basic Editor	£25
SN76489	£5.50	BROM	£28
SAA5050	£8.75	Buffer & Backup	£20
UPD7002	£4.40	Beebmon	£22
2764-250nS	£2.00	Beebfont	£25
27128-250nS	£2.50	Acorn COMAL	£36
27512	£18	Acorn FORTH	£32
4013	60p	Acorn Graphics	£25
4020	£0.90	Graphics Extension Rom	
4464	£8	GXR-B	£21
4816 RAM	£1.75	GXR-B+	£22
6264LP-8K RAM	£3.00	Acorn LISP	£35
6502A CPU	£5	Acorn LOGO	£42
65C02 3M	£9.75	ISO Pascal	£42
65C12	£9	ISO-Pascal Stand Alone Generator	£30
6512A	£10.00	ICON Master	£28
6522	£3.40	Logotron LOGO	£52
6522A	£5.00	Micro Prolog	£62
6845SP	£6.00	Microtext ROM	£48
7438	40p	ROMIT	£29
74LS00	25p	Serial ULA	£13
74LS04	25p	Video ULA	£15
74LS10	25p	TERMULATOR	£25
74LS123	80p	MUROM	£21
74LS163	70p	SLEUTH ROM	£24
74LS244	80p	STUDIO 8 Disc	£18
74LS245	£1.00	Toolkit Plus	£31
74LS373	£1.00	Communicator	£49
74LS393	£1.00	Disassembler	£16
75453	70p	Help II	£27
		View 2.1	£37
		View 3.0	£56
		Hi-View	£36
		Viewsheet	£37
		Viewstore	£37
		Viewspell	£29
		Viewplot Disc	£25
		Datagem (Gemini)	£34

ASSORTED ROMS

ACORN BASIC 2	£19
ACORN ADFS	£25
ACORN DNFS	£17
Acorn OS 1.2	£6
Acorn OS B+	£25

Prices subject to change without notice and available on request. ALL OFFERS subject to availibility.
Mail Order and RETAIL SHOP. Trade and Export inquiries welcome.
Government and Educational Establishments' OFFICIAL ORDERS Accepted.
Shop Hours: 9.00am to 6.00pm. Monday to Saturday. Thursdays 9am to 8pm. (Free Customer's Car Park)
VAT: UK customers please add 15% VAT to cost incl. Carriage.
CARRIAGE: Unless stated otherwise, minimum £1 on all orders. £2 on Larger items. On bulkier items, £7 Securicor charge applies. Overseas orders, carriage is charged at cost.
Specifications of all products are given in good faith but is subject to change without notice. Some items vary in their availability. Please ring for latest delivery situation.

Watford Electronics

JESSA HOUSE, 250, Lower High Street, WATFORD, ENGLAND
Telephone: (0923) 37774; Telex: 8956095; FAX: 01 950 8989

3½" 'COMPACT' versions of CJE software available £2 extra.

CJEmicro's

ENHANCED!

ALL CJE MICRO'S SOFTWARE IS B, B PLUS, MASTER & MASTER COMPACT COMPATIBLE.

Multi-Font NLQ

NEW

Converts most printers to NEAR LETTER QUALITY in user definable Fonts.

For EPSON & EPSON Compatibles, including MX/RX/FX/LX/80/100, STAR DP510/Gemini 10X/SG10/NL10 & Citizen 120D.

Simple to use, standard EPSON codes for Underline and Doublewidth used.

After initialising Multi-Font NLQ with a '*MFNLQ', Multi-Font NLQ is normally transparent to the user. Multi-Font does claim some memory for workspace and storing font data.
Multi-Font NLQ comprises of MFNLQ ROM for the BBC, and utility disc containing the FONT definer, ten fonts, BASIC demonstration program, VIEW demo text file and Driver.
Multi-Font NLQ is compatible with nearly all software, including most BASIC programs, VIEW, WORDWISE & InterWORD (SCRIBE & Printer Buffer software currently not supported).

Ten fonts are supplied or create your own using the font definer supplied.

Fonts included are:-
Standard NLQ, Courier, Italic, Gothic, CompTS, Bold, Shadow, Outline, Broadway E, Theatre

Additional Font Disc MF 'B' contains:-
Hand, Script, Stencil, Broadway, Caps, Italic-Plain, Meccano, Plain, STD large, Wire', Greek/Maths and Inverse.

For Canon & Taxan Kaga users we recommend FONTAID in preference to Multi-Font NLQ.

Multi-Font NLQ (ROM and 40/80 Disc)	**£30.00**
Additional font disc 'MF-B' (12 fonts)	**£15.00**
Additional font disc 'MF-C' (15 fonts)	**£15.00**
P & P on MFNLQ	**£ 1.00**

NEW

MASTER Write Protect and ROM select switch.
Two switches set to RAM slots to be:-
Internal ROM or RAM Read and Write or RAM Read only.
£12.00 inc. VAT. P & P £1.00.

```
This is Standard
This is COURIER
This is ITALIC
This is GOTHIC
This is COMPTS
This is BOLD
This is SHADOW
This is OUTLINE
This is BROWAYE
This is THEATRE
```

EXAMPLE OF MFNLQ FONTS

FONTAID

NLQ Definer for Canon & Taxan Kaga NLQ Printers.

Design your own NLQ Fonts or 'download' one of our 40+ predefined fonts.

Fonts can be downloaded within Wordwise, Inter Word or VIEW Documents allowing different fonts to be used for different paragraphs, or even individual lines of text. During downloading your Program or Text will not be corrupted.

On the FONTAID standard font Disk are the following eight fonts:- Square, Outline, Italic, Gothic, Computer Type Style, Bold, Shadow, and Broadway Engraved.

Additional disc 'A' gives an extra 11 fonts including:-
Greek/Maths, Plain, Hand & (Elite, Condensed, & Super Condensed).

Now included is a facility to issue '*' commands within a VIEW document.
To download new fonts within VIEW documents, the FONTAID ROM needs to be fitted in the BBC. (All other FONTAID facilities are available on both the FONTAID ROM & DISC). Fonts are always downloaded from Disc.

Fontaid is recommended to Canon & Taxan Kaga owners in preference to Multi-Font NLQ. As downloadable NLQ is a built-in facility of the Printer, full access to all the printers control codes is still allowed. The resolution of the FONTAID NLQ is also slightly higher than that of Multi-Font NLQ.

FONTAID requires 6264 RAM chip in printer.

FONTAID ROM & STD Font disc	(40 or 80 track)	**£30.00**
FONTAID ROM & STD Font disc with 6264 RAM	(40 or 80 track)	**£36.00**
FONTAID Additional Font DISC 'A' (11 fonts)	(40 Or 80 track)	**£15.00**
FONTAID Additional Font DISC 'B' (13 fonts)	(40 or 80 track)	**£15.00**
FONTAID Additional Font DISC 'C' (15 fonts)	(40 or 80 track)	**£15.00**
FONT ROMS of individual fonts are available eg "Square".		**£18.00**
P & P on FONTAID		**£ 1.00**

INFORM

A UNIQUE NEW POWERFUL USE FOR SIDEWAYS RAM

NEW

INFORM has been developed specifically to take full advantage of the Sideways RAM facility that many BBC micro users now have. Inform is compatible with most SIDEWAYS RAM units including ATPL Sidewise with RAM, Solidisc SWR, BBC B PLUS 128K & BBC MASTER series (not SDL256).

INFORM is a very powerful facility, which allows the user to display text information, of any kind, from Sideways RAM. This information can be readily accessed by using '*' commands from the keyboard or from application programs. In this way, much information can be displayed on the screen without stopping the current task, such as entering text in WORDWISE or VIEW.

The information in the RAM can be changed dynamically at any time.

Some of the possible applications for INFORM are:—

An on screen help manual can be created for your application, so that a reminder about more obscure points can be displayed at the users request. Information on your program or datafile contents, can remind you of their purpose.

Address and/or telephone numbers can be held and displayed quickly even while other applications are running. Very useful if you need to quickly display information about a client while he is hanging on the end of a phone!

Current prices for your products or stock position can be recalled instantly and readily modified using a wordprocessor. Similar files may be created from most databases such as VIEWSTORE.

In fact, any information to which you frequently refer can be displayed immediately without running another program. Your use of INFORM is only limited by your imagination, as they say!
There are three Inform Data Files (I.D.F.), of often used information, supplied on the disk to give an indication of the use of INFORM.

To use INFORM you must have Sideways RAM.

INFORM on 40/80 track disc. P & P on INFORM £1.00 **£20.00**

PRINTERS

NOW **FREE DELIVERY** on PRINTERS (by courier)

Ring for sample printouts, full specification and latest prices.

Near Letter Quality Printers all with Centronics interface, Friction and Tractor feed.

Canon 1080/Taxan KP810	**£270.00**
Canon PW1156A (15")	**£414.00**
Citizen 120D	**£190.00**
JUKI 5510	**£300.00**
JUKI 5510 + colour kit fitted	**£420.00**
Letter Quality Printer	
JUKI 6100 Daisywheel	**£280.00**
BBC Cable	**£ 8.00**

Inclusive of VAT & Delivery
Ring for latest prices.

CJE BBC Printer PACKS include:-
CABLE to BBC 1.25M, M/C two tone screen dump, Screen text dump, Function key set up program, Function key label printing program, VIEW driver, Character defining program for downloadable character set (draft mode), 100 sheets of paper, Mains plug with 3AMP Fuse, Booklet giving instruction on pack software and general details of using the printer with a BBC.
C.J.E. BBC Printer Packs are £15.00 cassette (£16.00 disc) (e.g. CANON PW1080A with Printer pack £270 + £15 = £285 everything included)

TRADE & EXPORT ORDERS WELCOME please inquire for delivery cost.

PRICES INCLUDE VAT Phone/Credit Card and Offical Orders welcome.

Full range of Printer, BBC, AMSTRAD & ATARI accessories available. **Offical ACORN approved Dealer.**

C.J.E. MICRO'S (Dept MU12) 78 Brighton Road
Worthing W. Sussex BN11 2EN (0903) 213361

CJEmicro's

Toolkit gets a new lease of life

Product: Brom Plus
Price: £34.50
Supplier: Clares Micro Supplies, 98 Middlewich Road, Northwich, Cheshire CW9 7DA
Tel: 0606 48511

By MIKE MAHON

THE original Brom, a programmer's Basic toolkit rom from Clares, was reviewed in *The Micro User* in August 1985 when 8k sideways roms were all the rage.

Since then a number of toolkit producers have moved on to the now equally cheap 16k eproms and produced packages possessing more and advanced utilities. The questions now are: Does Brom Plus make up for the deficiencies of Brom? Is it just another toolkit or a potential market leader?

As a reminder the original 8k Brom had 21 well implemented star commands covering features such as string search and replace, program editing and shrinking, and rom switch off and it came with a well produced 36 page manual.

Its best utility was the excellent interactive full screen Basic program editor. On the minus side I did point out in my previous review that "It is rather lacking, however, in facilities for memory information, roms listing, partial renumbering, cross-referencing and tracing, and has a poor pack routine."

Brom Plus is a 16k eprom with 36 star commands and a nicely bound 62 page manual selling for around the same price as the original, which it has now replaced.

It is a service rom only and does not signature its presence at switch-on or after a Break, nor does it alter PAGE. The version reviewed – 1.02 – was tested on a BBC model B and is also fully compatible with the BBC B+, Master 128 and Compact.

The commands, shown below are grouped into three areas – general purpose and rom editing, Basic toolkit and Disc utilities. Only the commands *ONEKEY and *NORMKEY – the Electron emulators – have been removed from the original and 17 new commands, indicated by *N* in the lists, have been added.

As with the earlier version all commands may be prefixed with a Z to avoid clashes between utilities with similar names from other roms. Only the disc commands and the non-memory editing general commands worked with the 6502 second processor.

The additional rom-associated commands, allowing you to check which roms are present and which have been switched off, are an essential facility for any BBC Micro toolkit worth its salt.

The new memory editor – *MEDIT – presents the screen in a coloured Mode 7 format and has a very fast scroll facility.

However these features are not as well implemented or as comprehensive as those found on some other general purpose "super-roms", although Clares has recently announced a companion rom – Ramrod – which is complementary to Brom Plus and has a number of versatile shadow ram and Tube memory editing features.

Among the extra Basic programmer's utilities the cross referencer – *XREF –

→

GENERAL COMMANDS

	*CASE	Forces upper or lower case keyboard entry.
	*FNKEY	Gives function key information.
N	*MEDIT	Enables the display end editing of memory.
N	*MFIND	Searches memory for a specified string.
N	*ROMLIST	Lists sideways roms and indicates status.
	*ROMOFF	Turns off a rom and survives Control+Break
	*ROMON	Reactivates a switched off rom.

DISC COMMANDS

	*COMPARE	Verifies program on disc against one in memory.
N	*DEDIT	Enters disc sector editor.
N	*DFIND	Locates track and sector containing a specified string
N	*DGET	Loads selected tracks into memory.
N	*DPUT	Writes to selected tracks on disc.
N	*FORM	Flexible disc formatter.
N	*MENU	Automatic program loader.
N	*UPDATE	Produces an information file on disc.
N	*SHUT	Closes all files.
N	*VERIFY	Verifies disc as readable.
N	*XCOPY	Copies multiple files.
N	*XDEL	Deletes multiple files.

BASIC COMMANDS

	*EDIT	Enters the Basic full screen editor.
	*ERR ON	Gives enhanced error messages.
	*ERR OFF	Returns to normal error messages.
	*FIND	String and keyword search utility.
	*CHANGE	Alters a string or keyword
	*SCHANGE	Allows selective alteration of strings or keywords.
	*FLIST	Produces neat listings and splits multi-statement lines.
	*FLUSH	Clears resident integer variables.
	*LCOPY	Copies lines within a program.
	*LMOVE	Moves lines within a program.
N	*LFIND	Lists lines containing a specified string.
	*LIMIT	Selects the range of lines to be edited and so on.
	*LVAR	Lists the contents of variables.
	*PACK	Removes REMs and spaces and forms multi-statement lines.
	*PAGE	Moves a program to a specified page in memory.
N	*RENUM	Performs a full or partial renumbering.
N	*XREF	Cross-references lines containing variables, procedures and functions.

From Page 65

is a useful and fairly well implemented feature, although its one major omission is that it does not cross reference line numbers.

*RENUM does, however, adequately perform partial renumbering – a useful feature missing from Brom. In addition the "pretty format" listing facility (*FLIST) now operates correctly for printouts.

There have also been some improvements to the already excellent full screen Basic program editor. Control+D deletes a line from memory without having to press Control+U and Return. Control+S has also been added and reverses the case of a letter as with the similar Wordwise command.

Now you can also move backwards or forwards one screen at a time with Shift + f0 and Shift + f1 respectively, though unfortunately there is still no trace facility to allow you to display program lines or step through a program in action.

Except for *COMPARE all the disc commands are new. They provide a flexible formatting routine – *FORM, enabling a partial reformat and specification of track offsets, separate format verification – *VERIFY – and closing of all open files – *SHUT.

Individual tracks may also be written to or loaded with the *DPUT and *DGET routines and are useful for repairing corrupted disc data. The inevitable disc sector editor and string search routines are also present on Brom Plus and worked well.

In particular the disc editor can be entered directly at any sector – for example, using *DEDIT 30,4,2 for sector four on track 30 of drive two. Two unique features I found especially useful were the commands for deleting or copying multiple files at once – *XDEL and *XCOPY.

The supposedly simplified loading routine – *MENU – was not as useful as it first seemed because each disc program has to be in the & directory to be recognised by the special Brom menu facility.

Associated with the latter feature is *UPDATE which allows you to tag information on each disc file to a special file labelled %.%%%%%%%%, which can be displayed when required from the Menu facility.

Brom Plus has certainly corrected most of the omissions from the original versions although it still lacks decent memory usage information, including the status of @%, major *FX commands and peripheral ports. It also has no trace, single step or rom memory viewing facilities.

Except for the full screen editor, Brom Plus offers nothing particularly exciting – we have come to expect far more from a 16k rom these days.

Perhaps combined with Ramrod in a 32k rom – when the price of these devices comes down and a little more sparkle has been added – Clares' programmer's aids could beat the other super-roms for the coveted toolkit rom slot on the BBC Micro.

Finally Brom Plus is also offered on disc at £30 for loading directly into sideways ram on the Master. Although there is no upgrade facility available owners of the original Brom can take advantage of a discount offer should they desire to buy the new version. ■

QUAL-SOFT **THOUGHTWARE** Sports simulations

ADJUDGED JOINT NUMBER ONE SOCCER SIMULATION FOR ALL HOME COMPUTERS

The June and July issues of COMPUTER GAMER magazine reviewed 16 soccer simulations, including Ocean's MATCHDAY and INTERNATIONAL MATCHDAY (128k SP), Addictive's FOOTBALL MANAGER, Artic's WORLD CUP and WORLD CUP 2, US Gold's WORLD CUP CARNIVAL, Virgin's FA CUP, etc etc. MEXICO '86 was given a NOVA overall rating and 5 "planets" from 5 for Value for Money. Only one other game could equal this, Commodore's classic INTERNATIONAL SOCCER.

ARE YOU STILL PLAYING THE SECOND RATERS?

Tape 1 (Qualifiers) + **Tape 2** (Finals) + 20 Page Booklet **£9.95**

MEXICO '86

DISC Qualifiers + Finals + 20 Page Booklet **£12.95**

A WORLD CUP MANAGEMENT SIMULATION

On June 22nd 1986, England's bid to become World Champions for the next 4 years came to an end in the Azteca stadium, Mexico City. How well did Bobby Robson do? Can YOU outperform him? MEXICO '86 gives YOU charge of the England team 2 years before the start of the Mexico finals. You must experiment with a demoralised squad who failed to qualify for the European Nations' Cup, drafting in players as you see fit, and nurse the team through the Qualifying stages of the World Cup. If you qualify, you must choose your squad for Mexico, play through Phase 1, the groups of four, into the last 16. Can you now take England two stages further than Bobby Robson and then win the big one? It takes a thorough understanding of International football to win in MEXICO '86.

MASTER COMPACT 3½" DISC VERSION: £12.95

ENGLAND'S GAMES: FULL PITCH, 22 MAN, 3D GRAPHICS & SOUND EFFECTS

QUAL-SOFT comments: With 5 levels of play, 12 depths of sophistication, and "fun" graphics, this game can be enjoyed by an 8 year old youngster as a "fun" game, and by the most sophisticated as a tactical/strategy challenge of the highest order.

QUALSOFT GUARANTEE: We will send your package by 1st class letter post on the day we receive your order with PO, cheque or ACCESS card authorisation. Programs are IN STOCK because we manufacture them!

TAPES and 5¼" DISC versions compatible with BBC "B", "B+", 128 and MASTER.

QUAL-SOFT, Dept. MU
18 HAZLEMERE ROAD STEVENAGE SG2 8RX.
Tel: 0438 721936

Please supply for:
ELECTRON ☐
COMPACT 3½" ☐
BBC ☐ ☐ ☐ (T 40 80)

Name: .....
Address: .....
.....
Access No. (if applicable) .....

Arrays: Entering a new dimension



By PETE BIBBY

BY now you should be fairly familiar with arrays, so Program I should cause you no problems.

The action starts at line 20 which sets aside memory space for two arrays, *name$()* and *age()*. Each of these arrays has five elements, but as is my usual, wasteful practice I'll ignore the first element of each. Hence there's no reference to *name$(0)* or *age(0)* in Program I.

```
  10 REM Program I
  20 DIM name$(4),age(4)
  30 FOR loop=1 TO 4
  40 PRINT "Give me a name"
  50 INPUT name$(loop)
  60 PRINT "Give me "name$(loop)"'s
age"
  70 INPUT age(loop)
  80 NEXT loop
  90 PRINT "Give me a pointer 1-4"
 100 INPUT pointer
 110 PRINT "You picked "name$(pointe
r)" whose age is ";age(pointer)
```

Program I

Once the two arrays have been set up the FOR . . . NEXT loop between lines 30 and 80 gets to work filling them.

Or rather it gets you to do the work by giving you the prompts and accepting your input. For each pass of the loop a name and an age is taken from the keyboard. In all, four names and four ages are requested.

Name	Age
Pete	36
Noreen	21
Colin	42
John	30

Table I: Names and ages

Suppose the data entered was taken from Table I. The first time round the loop, *loop* has the value 1, so the reply to the prompt of line 40 is stored in *name$(1)*. Hence *name$(1)* holds Pete.

The next prompt asks for my age, and so 36 is placed in *age(1)*. (I look years younger.) You can see that as the loop cycles, and you enter the data from Table I, so the arrays are filled.

You should also see that these are parallel arrays. It's no coincidence that there are two of them, *name$()* and *age()*, and they are there for the reason that they have something in common.

Because of the way the data has been entered, the respective elements of the arrays contain information about the same thing, or *entity* as it's sometimes known. In the case of the first element of each array the entity is me, with *name$(1)* holding my name and *age(1)* my age.

Similarly the second element of each array holds information on the same subject. *name$(2)* tells us that it's Noreen and *age(2)* that she is 21. (Again.)

Because of the fact that the arrays are parallel we can use the subscript of each element as a pointer. This can then be used to retrieve the element of each array containing the information about a particular entity. This is what Program I goes on to do in its last three lines.

Line 90 asks you for a pointer in the range 1 to 4 and stores it in *pointer*. Line 110 then uses this value as the subscript in both arrays, teasing out the information required. So if you reply 3 to the prompt of line 90, *pointer* takes the value 3 and line 110 uses *name$(3)* and *age(3)*.

Can you guess what happens if you give *pointer* a value outside the indicated range, say 11? Try it and see. Your micro is the best teacher you're likely to have. It tells you when you've made a mistake but won't tell anyone else you've made one. And it doesn't clip you across the ear, though some of the error messages it gives can be just as hurtful.

In this case the program is so simple as to be unnecessary in practice. With a more practical program it shouldn't strain your imagination to see that you could end up with lots of parallel arrays containing details of height, weight, and so on. And the ability to extract all the relevant information from a set of arrays with just one pointer is a valuable technique that will add power to your programs.

The trouble is that with the present method of entering data from the keyboard, filling a set of parallel arrays every time we run a program would take ages. There must be better methods. There are – and Program II shows one of them in action.

If you run the program you'll find that it just produces a list of the four names in Table I. Nothing unusual there, you're probably seeing them in your sleep. What is interesting is that you don't have to type in the names in response to a prompt as we've always done previously. Look no hands! Let's examine the program in more detail and see how this is done.

If you don't know that line 10 is a REMark which the computer ignores then I strongly suggest you're reading the wrong article. Line 20 is familiar enough, it dimensions the array *name$*. And, apart from line 40, the following FOR . . . NEXT loop is simple enough, it just cycles four times.

Similarly the second loop, between

→

```
 10 REM Program II
 20 DIM name$(4)
 30 FOR loop=1 TO 4
 40 READ name$(loop)
 50 NEXT loop
 60 PRINT "The names are:"
 70 FOR loop=1 TO 4
 80 PRINT name$(loop)
 90 NEXT loop
100 DATA Pete,Noreen,Colin,John
```

Program II

Computers by Post

LOWEST U.K. PRICES GUARANTEED

PRINTER RIBBONS

		2+	5+	12+
ACORN	AP80	£2.95	£2.40	£2.30
	AP100	£2.95	£2.40	£2.30
AMSTRAD	DMP1	£3.90	£3.30	£3.10
	DMP2000/3000	£4.60	£4.30	£4.20
	PCW8256/8512	£5.20	£4.60	£4.50
BROTHER	HR5	£3.00	£2.80	£2.60
	HR15 Corr	£2.90	£2.50	£2.30
	HR15 FAB	£3.60	£3.10	£2.90
	HR15 MS	£3.50	£3.00	£2.80
	HR15 also for HR25/HR35			
	EP44	£2.90	£2.50	£2.30
	M1009	£3.70	£3.20	£3.00
CANON	PW1080A Black	£3.40	£2.90	£2.70
	PW1080A Red or Blue	£5.30	£4.70	£4.40
	PJ1080 Ink Jet Colour. One Off			£10.90
	PJ1080 Ink Jet Black. One Off			£8.90
CBM	1515	£2.95	£2.40	£2.30
	1525	£2.95	£2.40	£2.30
	MPS801	£3.90	£3.30	£3.10
	802/1526	£4.00	£3.20	£3.00
	803	£3.70	£3.20	£3.00
	MPS1000	£3.00	£2.60	£2.40
	4022	£3.00	£2.60	£2.40
	MSC801 Colour. One Off			£18.50
	DPS1101 SS	£1.60	£1.30	£1.20
	DPS1101 MS	£2.50	£2.10	£2.00
	DPS1101 Corr	£1.80	£1.50	£1.40
CENTRONICS	GLP	£3.70	£3.20	£3.00
CITIZEN	120D	£5.00	£4.60	£4.30
DAISYSTEP	2000 MS	£3.10	£2.60	£2.40
	2000 FAB	£4.90	£4.20	£4.00
EPSON	MX/FX/RX80 Black	£3.00	£2.60	£2.40
	MX/FX/RX80 Red or Blue	£4.20	£3.50	£3.30
	100 Series	£5.00	£4.60	£4.30
	LX80/LX86	£3.00	£2.60	£2.40
	JX80 Colour. One Off			£18.50
	LQ800	£3.90	£3.50	£3.30
	LQ1500	£4.50	£3.90	£3.60
JUKI	6000/2200 FAB	£3.70	£3.40	£3.20
	6000/2200 Corr	£4.00	£3.60	£3.40
	6000/2200 SS	£3.10	£2.70	£2.50
	6100 MS	£2.50	£2.10	£2.00
	6100 SS	£1.60	£1.30	£1.20
	6100 Corr	£1.80	£1.50	£1.40
KAGA	KP810 Black	£3.40	£2.90	£2.70
	KP810 Red or Blue	£5.30	£4.70	£4.40
M/TALLY	MT80	£4.00	£3.20	£3.00
OKI	80/82	£1.60	£1.30	£1.20
	84	£3.90	£3.40	£3.20
	Mate 20 Colour	£7.00	£6.50	£6.20
	Mate 20 Black	£6.60	£6.20	£6.00
PANASONIC	KX1091/2	£5.00	£4.60	£4.30
QUENDATA	DWP1120 MS	£3.10	£2.60	£2.40
	DWP1120 FAB	£4.90	£4.20	£4.00
QUME	Sprint 7/9 MS	£3.10	£2.60	£2.40
	Sprint 7/9 FAB	£4.90	£4.20	£4.00
SEIKOSHA	GP50	£6.00	£5.50	£5.20
	GP80	£2.95	£2.40	£2.30
	GP100/250	£2.95	£2.40	£2.30
	GP500/550	£3.90	£3.30	£3.10
	GP700 Colour. One Off			£18.50
	SP1000	£6.00	£5.50	£5.20
SHINWA	CP80	£4.00	£3.20	£3.00
SMITH CORONA	TPI M/S	£8.50	£7.90	£7.20
	TPI Fabric	£3.90	£3.60	£3.40
	TPI Corr	£5.00	£4.70	£4.50
	D100/200	£9.00	£8.50	£8.20
	D300	£6.00	£5.50	£5.30
STAR	DP/GEMINI/SG	£1.60	£1.30	£1.20
	SR15	£4.90	£4.50	£4.30
	NL10	£5.60	£4.90	£4.60

FLOPPY DISKS

5¼"		BOXES OF 10 DISKS 1-2	3-9	10+
JVC inc Plastic Case				
MD-1D	S/side D/dens 40TR	£9.99	£9.50	£9.25
MD-2D	D/side D/dens 40TR	£11.99	£11.50	£11.25
MD-2DD	D/side Q/dens 80TR	£15.99	£15.50	£15.25
MD-2HD	D/side H/dens 1.6MB	£26.99	£25.99	£25.49
VERBATIM – DATALIFE				
MD525	S/side D/dens 40TR	£11.99	£11.75	£11.49
MD550	D/side D/dens 40TR	£14.99	£14.75	£14.49
MD577	S/side Q/dens 80TR	£14.99	£14.75	£14.49
MD557	D/side Q/dens 80TR	£19.99	£18.99	£18.50
MD HD	D/side H/dens 1.6MB	£27.99	£26.99	£25.99
SONY	S/side D/dens 40TR	£12.49	£11.99	£11.75
	D/side D/dens 40TR	£15.49	£14.99	£14.75
	D/side Q/dens 80TR	£20.49	£19.99	£19.75
3½"		BOXES OF 10 DISKS		
JVC	S/side D/dens	£17.99	£17.25	£16.99
SONY	S/side D/dens	£18.99	£18.25	£17.99
SONY	D/side D/dens	£27.99	£27.50	£26.99

BULK 3½" D/SIDE D/DENS DISKS BY SONY

10 x Disks	£1.99 each £19.90 pack
20 x Disks	£1.89 each £37.80 pack
50 x Disks	£1.79 each £89.00 pack

3" DISKS

CF2 5 Disks	£3.25 each £16.25 pack
CF2 10 Disks	£2.99 each £29.90 pack

ENVELOPES

	PRICE PER BOXED	BOX
110mm x 220mm White Self Seal 90gsm	500	£11.50
110mm x 220mm Manilla Banker Gummed 70gsm	500	£9.50
324mm x 229mm Manilla Self Seal 90gsm	250	£17.90

DISK STORAGE

LOCKABLE DISK BOXES

MODEL	SIZE	CAPACITY	PRICE
DD40L	3"/3.5"	40	£8.90
MD60T	3"/3.5"	60	£12.50
DD50	5¼"	50	£8.90
DD70	5¼"	70	£10.90
DX85	5¼"	90	£12.90
DD100	5¼"	100	£13.90
LIBRARY CASE	5¼"	10	£1.50
NON-LOCKABLE DISK BOXES			
MD12/30	3"/3.5"	24	£7.20
MF50	5¼"	50	£8.00
MICRODRIVE HOLDERS			
WALLET		4	£1.75
WALLET		20	£4.50

PRINTER CABLES & INTERFACES

AMSTRAD	Parallel	£8.90
ATARI ST	Parallel	£14.50
BBC	Parallel	£6.50
IBM	Parallel	£14.50
MSX	Parallel	£10.90
CBM 64/128	Parallel I/F	£59.90
SINCLAIR QL/SPEC 128	Parallel I/F	£26.50
SINCLAIR SPECTRUM	Parallel I/F	£32.50
AMSTRAD PCW	Parallel/Serial I/F	£49.90

COMPUTER STATIONERY

PLAIN WHITE WITH MICRO-PERF EDGES SIZE	GSM	QUANTITY	PRICE 1 BOX	2 BOXES
11 x 9½	60	2000	£12.90	£12.00
11 x 9½	70	2000	£15.90	£14.50
EXACT A4	70	2000	£21.50	£18.75
11⅞ x 9¼	90	1000	£13.50	£11.25

COMPUTER LABELS

	PRICE PER THOUSAND 1000	2000+
70 x 36mm	£4.40	£4.00
89 x 36mm	£4.50	£4.10
89 x 49mm 3 across only	£6.20	£5.70
102 x 36mm	£4.70	£4.40

Please state number of labels across sheets (1, 2 or 3).

PRINTERS

Epson LX86	£209.95
Epson FX85	£334.95
Epson FX105	£435.95
Epson EX800	£386.95
Epson LQ800	£454.95
Epson LQ1000	£607.95
Citizen 120D	£155.95
Amstrad DMP2000	£139.95
Amstrad DMP3000	£152.95
Brother 1509	£416.95
Oki-mate 20 Colour	£169.95
Micro P MP165	£199.95
Seikosha SP1000A	£199.95
Seikosha MP1300A	£349.95
Star NL10 inc I/F	£199.95
Star SG15	£299.95
Star SD10	£299.95
Star SD15	£429.95
Star Powertype Daisywheel	£199.95
Juki 6100	£249.95

COMPUTERS

Acorn BBC Master	£399.95
Acorn BBC Master Compact	P.O.A.
Amstrad PCW8256	£389.95
Amstrad PCW8512	£489.95
Amstrad CPC464 Green	£169.95
Amstrad CPC464 Colour	£254.95
Amstrad CPC6128	£254.95
Amstrad CPC6128 Colour	£339.95
Atari 520STM + 500K D. drive	£369.95
Atari other models	P.O.A.
Commodore C64	£139.95
Commodore C64C compend.	£204.95
Commodore C128D	£429.95
CBM 1541C Disk Drive	£168.95
CBM Amiga	P.O.A.
Sinclair Spectrum 128K + 2	£128.95

CF2 3" Disks Box of 10 **£29.90**	**Maxwell 5¼" MD1D** S/side D/dens 40TR Box of 10 (min. 2 boxes) **£9.99**	**TDK 5¼"** S/side D/dens 40TR Box of 10 (min. 2 boxes) **£8.99**
BASF 5¼" 2D/96 D/side Q/dens 80TR Box of 10 (min. 2 boxes) **£11.99**	**SONY 3½"** D/side D/dens Box of 10 **£27.99**	**INTERWORD WORD PROCESSOR FOR BBC** **£39.95**

DELIVERY ALL CONSUMABLES AND SOFTWARE POST FREE
Hardware £5 + VAT 4 Day Delivery · £9 + VAT 24 Hour Delivery

GALASET GUARANTEE If after buying any of the hardware or software in this advertisement, you find the same item offered at a lower price locally within one week, Galaset will refund the difference.

All prices exclude VAT

CREDIT CARD HOT-LINE

01-760 0014

Galaset Ltd, 30 Bayford Road, Littlehampton, West Sussex.

Export Enquiries Welcome

To: **Galaset Ltd, 30 Bayford Road, Littlehampton, West Sussex.**

I wish to order_____

My computer is_____

I enclose cheque/PO for £_____ inc VAT
or charge my Access/Visa No:

Name_____

Signature_____

Address_____

Postcode_____ Tel No:_____

From Page 67

lines 70 and 90, should cause you no intellectual suffering. It just cycles four times using the varying values of *loop* as a pointer to successive elements of *name$()*. Line 100 is definitely new material. So what do our mystery lines do?

In effect the READ of line 40 and the DATA of line 100 form a pair of commands that allow you to avoid a lot of the typing you've done previously. The READ replaces the INPUT and the DATA replaces all those names.

What happens is that when the micro comes across the keyword READ, it knows that it is to place a value or string into the variable it finds following that READ. But where does it get that value from?

The answer is that it comes from the line marked DATA. As soon as the computer hits the READ it searches down the program for the first line beginning with DATA. It then takes the first item from the list after the DATA and puts this into the variable following READ.

It also remembers its position so that next time the program executes a READ, it knows where the next data item is to come from without having to search for it. This is done automatically. All the programmer sees is that the READ reads successsive items from the list following DATA.

In the case of Program II, the micro originally comes across the READ during the first cycle of the initial FOR . . . NEXT loop. As at this point *loop* is 1, this means that line 40 is attempting to read a value into *name$(1)*. The micro now looks through the program listing until it finds the first line beginning with DATA. In this case it's line 100. It then takes the first name it finds in the data list (the items after the DATA, separated by commas). In this case it's Pete, so *name$(1)* duly becomes Pete.

The second time round the loop, *loop* has the value 2. This means that line 40 is attempting to read a value from the data list into *name$(2)*. The micro has kept track of where it was up to and the result is that Noreen is read into *name$(2)*.

The program carries on in this way until the loop has cycled four times. When this has finished *name$()* is filled with the name in the data list. The subsequent loop proves this by printing out the contents of the array.

While Program II has used READ and DATA to put strings into a string array we're not just stuck to strings. We can use our new keywords to enter values into a numeric array as Program III shows.

```
10 REM Program III
20 DIM age(4)
30 FOR loop=1 TO 4
40 READ age(loop)
50 NEXT loop
60 PRINT "The ages are:"
70 FOR loop=1 TO 4
80 PRINT age(loop)
90 NEXT loop
100 DATA 36,21,42,30
```

Program III

This is much the same as Program II except that now we're dealing with the array that holds the ages, *age()*. Reflecting this line 100, the one beginning with DATA, contains the ages from Table I. Notice again that they're separated by commas. Try leaving one out or putting it in the wrong place and see what happens.

Let's sum up what we've learnt so far. We've seen how we can use our keyword READ to take in data from a line marked DATA. And this data can be either strings – like Noreen – or numbers – such as 21.

It's a nice way of getting information into an array and saves a lot of typing. And it's quite flexible. For example, should we want to change the names in Program II to Bodger, Spot, Nelson and Ginger then we can leave the program more or less intact. All we do is add a new line 100:

```
DATA Bodger,Spot,Nelson,Ginger
```

Try it and see for yourself. And when you've done that have a look at Program IV which uses one READ to get values for two arrays.

Line 20 dimensions these two arrays, our old friends *name$()* and *age()*. Next comes the seemingly obligatory

```
10 REM Program IV
20 DIM name$(4),age(4)
30 FOR loop=1 TO 4
40 READ name$(loop),age(loop)
50 NEXT loop
60 FOR loop=1 TO 4
70 PRINT name$(loop),age(loop)
80 NEXT loop
90 DATA Pete,36,Noreen,21
100 DATA Colin,42,John,30
```

Program IV

FOR...NEXT loop which cycles four times. Each time it cycles line 40 is obeyed. And line 40 is rather different from our other line 40s.

This difference lies in the fact tht the READ now has two variable names following it, *name$(loop)* and *age(loop)*. Really this should come as no surprise. After all, we've already used Basic keywords to do two things at once as you'll see if you look at the DIM of line 20. The micro isn't bothered, it just searches out the DATA list, starts at its beginning and works its way along it, item by item.

The first time round the loop, *loop* is 1 and so the READ of line 40 is searching out content for *name$(1)* and *age(1)*. To do this it looks down to the data list starting at line 90 and takes its information from there. The first item it finds, Pete, is duly stored in *name$(1)* while the second, 36, finds its way into *age(1)*. The second time round the loop, the next pair of data items are copied into *name$(2)* and *age(2)*. In this way all the data items are entered into the arrays and the final FOR . . . NEXT loop displays the results as a way of proving this.

Simple isn't it? Well it is, but there are a couple of points to pay attention to. Notice that instead of having our data items all on one line, as in the previous programs, now they are spread over two.

I didn't have to do this, but it seemed neater and I've learnt that a neat layout can help make programs more readable and so easier to understand and debug. So long as the lines begin with DATA the micro isn't bothered.

The second point is that the items in the data line have to be in the right order. Lines like:

```
90 DATA Pete,Noreen,Colin,John
100 DATA 36,21,42,30
```

or:

```
90 DATA 36,Pete,21,Noreen
100 DATA 42,Colin,30,John
```

won't work. Try it and see.

As an exercise can you alter Program IV so that it will accept the last two DATA lines? Have a look at line 40. And then see if you can alter the program so that it uses a pointer to pick out a name and age rather like it did in Program I.

● *That should give you something to do until next month when we'll be READing a lot more about DATA.*

NEW BBC PRODUCTS FROM CLARES

Enhanced BETA-BASE £25

40 80 3"

SPECIFICATION

1) Random Access	- disc based, single or dual drives
2) File Size	- max 65,000 records
3) Record Size	- up to 2048 characters and 200 fields
4) Field Size	- up to 254 characters
5) Holds	- approx 1200 ADDRESS records per 100k
6) Search	- 5 search fields using powerful options
7) Sort	- 500 records on 3 fields in 60 seconds.

SYSTEM FEATURES

*CALCULATE - using any valid expression
*PRINTOUT - Powerful options
*REDEFINE - Titles, fields etc.
*TRANSFER - From one file to another
*GLOBAL ENTRY - of repetitive data
*SEARCH LISTS - Allow creation of sub Databases within main Database
*SPOOLER - enables you to create spooled files that are compatible with Wordwise, View etc.
*INPUT - is a routine included on the disc which will allow you to write your own utilities for accessing your data. Many of the programs on the utilities disc were written using this procedure

BETA-BASE UTILITIES £12.00

40 80 3"

Extend the power of Beta-Base with the extra facilities provided on this disc.

*MAIL MERGE
*LABEL PRINTER
*DISC SORT
*EXTENDED SEARCH
*FREE FORMAT TRANSFER
*FAST PACK
*STATUS

The MAIL MERGE alone is worth £12 so you get a real bargain with this disc. The features are so numerous that we cannot mention them all here.

Ask for our UTILITIES DATA SHEET if you want more information.

40 80 3" _____ DISC
40 _____ 40 TRACK
80 _____ 80 TRACK
3 _____ 3" DISC - ADD £3
_____ EPROM

Send for detailed newsletter.
All prices inclusive of VAT & Carriage - NO EXTRAS! Please state 40 or 80 track disc and state D.F.S. you use.

FONTWISE PLUS £20.00


40 80 3"

FONTWISE PLUS is now compatible with VIEW, MINI OFFICE II, EDWORD 2 and INTERWORD as well as WORDWISE and WORDWISE+!

Now you can have PROPORTIONAL and JUSTIFIED text in 12 different fonts, all within the same document if required. In addition to the standard facilities like line and page length, pagination, left margin etc. we have now added

- Enlarged, standard & condensed fonts
- Tabs
- Temporary indent
- User definable line feed
- User definable character spacing
- Non proportional fonts
- Now with 12 fonts
- Plus many more features

If you are not convinced ask us to send you a sample printout and you will be amazed at the quality - requires an EPSON compatible printer capable of single, double and quad density graphics but you do not require any RAM in your printer to use FONTWISE PLUS.



MACROM £40 £35 DISC

40 80 3"

MACROM is a fast full featured MACRO ASSEMBLER ROM that allows the use of macros, which are loaded from a macro library stored on disc. Assembly can be from disc to memory, disc to disc, memory to memory or memory to disc, thus allowing the use of very long source code up to the length of your disc. MACROM source code is tokenized and thus takes up far less room in memory or on disc than most assemblers.

- Operate in any mode
- Tokenized source code
- Assembles 6502 & 65C02 codes
- Automatically loads macros from library on disc
- Automatically loads subroutines from disc
- Macro library supplied plus demo files
- Chain program sections into main code
- Many different assembly options
- Converts BBC assembler code into MACROM source code
- Very fast & very flexible

In a comparison with ADE, MACROM was able to assemble a program to disc in 1 min 24 secs compared to 5 minutes with ADE and the source code took up 30% less room on the disc.
Ask for a data sheet today

RAMROD £40 ROM £35 DISC

40 80 3"

RAMROD is the ultimate in toolkit ROMs and is fully compatible with the whole BBC range from Model B through to the MASTER 128 and including both 6502 and TURBO co-processors. RAMROD adds 54 new commands to your computer. Areas covered are DISC (DFS & ADFS), GENERAL (memory commands etc.), ROM (including sideways RAM) and TUBE.

RAMROD provides commands to dump memory or a disassembly of memory to a printer. Editors can display the screen in 40 or 80 column mode.

DISC
Edit discs and search for ASCII or HEX sequences.

GENERAL
Edit, search, disassemble, compare, dump to printer and relocate ANY area of memory including the SHADOW screen. List vectors in use, load and save function keys even on MASTER etc.

In addition to the above you can move between ROM/RAM banks using (CTRL) Cursor Keys when in either memory or disassembly mode PLUS you can switch between memory editor and disassembler by pressing (CTRL)(TAB).

ROM
Includes commands for listing, loading, saving, wiping, swapping, ROM images. PLUS formatting and titling RAM banks for the ROM filing system and saving programs in RFS format.

TUBE
Provides the same memory commands as GENERAL plus SHIFT and COMPARE memory across the TUBE both ways.

We cannot do justice to RAMROD in the space here so please ask us to send you a fuller data sheet - RING NOW!

NEW PRODUCTS
Watch out for a fabulous new product which will be released during SEPTEMBER for the MASTER and its compatibles.

This is a high quality art package called ARTROOM but it offers many features not provided elsewhere. It is a full screen package and is written by the authors of FLEET STREET EDITOR so you know that it will be good.

Ask for a data sheet NOW!

Clares
MICRO SUPPLIES

**98 Middlewich Rd.,
Northwich, Cheshire CW9 7DA.
Tel: 0606 48511
Open 9—5pm Monday—Friday
LUNCH 12.30—1.30**

A word in your ear–and it's all in software

By IAN McLEOD

THERE are two or three speech synthesiser systems available for the BBC Micro. Excepting Superior Software's system, they all require additional hardware in the computer and they are not compatible. If you wish to include speech in your programs they can only be used by someone else with the same system.

This article describes how to reproduce speech, or any sound, without additional hardware and how to record sound with a simple and cheap interface (shown in Figure I).

One word can be stored in roughly 1k of memory, so it should be possible to include a few words in your games or educational programs.

Digitised audio is stored in memory and reproduced by using the in-built sound chip as a digital to analog convertor (DAC). To do this it is necessary to control the sound chip from machine code.

The three tone generators of the sound chip are set to a frequency of 31kHz which is beyond the range of human hearing. The audio data is used to control the level of the 31kHz tone using the sound chips' programmable attenuators.

Because the tone generator output is a filtered square wave the output waveform looks something like a chopped version of the audio, and the sound is heard in the loudspeaker.

The programmable attenuators in the sound chip give a logarithmic law. This would severely distort the sound and so it is corrected by using a look-up table to find the control word values to pass to the chip.

The sound chip in the BBC Micro is the Texas Instruments 76489. Full details of it can be found in the Texas Instruments data sheet published in The Hardware Guide to the BBC Microcomputer. It contains three tone generators which can be programmed for frequency and level.

The frequency of each generator is controlled by a 10 bit data word and it can be calculated by frequency = 4MHz/32*F, where F is the 10 bit binary number F0 to F9. F0 is the LSB.

The output attenuator of each generator is controlled by a four bit data word and can be calculated as follows:

Attenuation = –2*A dB, where A is the 4 bit binary number A0 to A3, except that when A=15 the channel is off.

The chip also contains a noise generator which can be programmed for frequency and attentuation. The noise quality and frequency are controlled by a three bit data word. When the bit FB is set to 0 periodic noise is generated. When it is set to 1 white noise is generated.

The two bits N1 and N0 control the




Figure I: ADC circuit

From Page 71

noise generator frequency.

N1	No	Frequency
0	0	high
0	1	med
1	0	low
1	1	tone generator 3 frequency

Noise generator frequency

The chip has eight registers which are used to control the tone generators and the noise source. During all data transfers to the chip the first byte contains a three bit address which selects the destination register. Frequency control requires a two byte transfer while attenuation and noise control require only one.


R2	R1	R0	Register
0	0	0	Tone1 frequency
0	0	1	Tone1 attenuation
0	1	0	Tone2 frequency
0	1	1	Tone2 attenuation
1	0	0	Tone3 frequency
1	0	1	Tone3 attenuation
1	1	0	Noise control
1	1	1	Noise attenuation

Register address field

In the BBC Micro the slow data bus is used to communicate with the sound chip, the speech chip and the keyboard. Data to be sent to the sound chip is put on to the slow data bus and the chip write enable line set low for a minimum of eight microseconds, then set high again.

The slow databus is register A of the system VIA at address &FE4F. The sound chip write enable line is selected by 0 in bits 0 to 2 of register B of the system VIA at address &FE40. The bit to be sent is in bit 3.

As a demonstration Program I sets



Data format

generator 1 to a frequency of 1kHz at half level.

Audio data is read into the computer from a very simple four bit analog to digital converter (ADC).

The in-built ADC has a conversion time of 4ms. This would allow a sampling rate of only 250Hz which is too low for audio. The ADC described here achieves a sampling rate of 5.5kHz which is adequate for intelligible speech. With two samples per byte approximately eight seconds of audio can be stored in 22kbytes of memory or roughly one word per k.

The user port is set up so that Pb0 to Pb6 are outputs and Pb7 is an input. Bits 0 to 3 are connected to the four most significant bits of the ZN425E DAC. The DAC output is connected to one input of the analog comparator.

The other input to the comparator is the audio signal which is DC biased to half the maximum DAC output voltage. The LM3302 comparator is slightly unusual in that its comparison range includes the negative supply rail, so only a single five volt supply rail is needed and this is obtained from the user port

```
  10 FOR PASS=0 TO 3 STEP3
  20 P%=&C00
  30 [OPT PASS
  40 .tone
  50 SEI                  \ disable in
terupts
  60 LDA#&FF:STA&FE43     \ set all re
gister A lines as outputs
  70 LDA#&8D:JSR sound    \ chan1 firs
t freq byte
  80 LDA#&07:JSR sound    \ second fre
q byte
  90 LDA#&93:JSR sound    \ chan1 atte
nuator
 100 CLI:RTS              \ enable int
erupts and exit
 110 .sound               \ sound subr
outine
 120 STA&FE4F             \ send byte
to register A
 130 LDA#0:STA&FE40       \ set write
enable low
 140 NOP:NOP:NOP:NOP      \ wait
 150 NOP:NOP
 160 LDA#8:STA&FE40       \ set write
enable high
 170 RTS
 180 ]:NEXT
 190 CALL tone
```

Program I

connector.

The computer counts down from 15 and looks at Pb7 to test if the DAC output is higher than the audio. The count is stored when the DAC output goes lower than the audio level but the count continues to zero, so that the time between samples is constant.

The maximum output voltage of the DAC is 2.4 volts and this is the peak to peak audio voltage required. This level can easily be obtained from the earphone or speaker output of a cassette recorder.

The machine code is assembled at address &C00. This should work for both disc and tape users. It could be relocated in any convenient block of 256 bytes of memory by altering line 120.

When Program II is run, assuming there are no assembly errors, the computer is left in direct mode. The function keys f1 and f2 are programmed to call the machine code to record and playback. The high byte of the data memory start and end addresses can be changed by altering locations &75 and &76.

This facility can be used to record a

PROBLEM

I WAS wondering, now there is a RS423 interface available for the Electron would it be possible to use it as extra memory or a second processor for a BBC Micro? If so could you load rom software from the Plus 1 into the BBC? – G.P. Hawkins, Chippenham.

SOLVED

The answer to these questions is always "yes but it's not worth it". You would need some communication software in each machine to send data and messages back and forth. By the time that is written and installed you would not have much memory left. The extra memory would only be of use for data and not program storage.

As to rom software, you could transfer it to the BBC Micro providing you had some sideways ram to put it in. The extra software needed would have to transfer the data and you would have to arrange some protocols to signify start and finish.

```
 10 REM Speech without a chip
 20 REM By Ian McLeod
 30 REM (c) The Micro User
 40 REM
 50 *KEY1 CALL rec!M
 60 *KEY2 CALL play!M
 70 ?&74=35:REM play speed
 80 ?&75=&22:REM memory start
 90 ?&76=&7B:REM memory end
100 VDU15
110 FOR PASS=0 TO 3 STEP3
120 P%=&C00
130 [OPT PASS
140 .rec SEI
150 LDA#0:STA&70
160 LDA&75:STA&71
170 LDA#&7F:STA&FE62
180 LDY#0
190 \ main loop, stores bytes
200 .rec1 JSR nib
210 STA(&70),Y
220 INC &70:BNE rec1
230 INC &71
240 LDA&71:CMP&76:BNE rec1
250 CLI:RTS
260 \ Pack 2*4 bit samples per byte
270 .nib
280 LDA#2:STA&72:LDA#0:STA&73
290 .nib1 JSR read
300 DEC&72:BEQ nib2
310 LDX#10
320 .nib3 DEX:BNE nib3
330 STA&73:JMP nib1
340 .nib2 ASLA:ASLA:ASLA:ASLA
350 ORA&73
360 RTS
370 \ Read 4 bit sample from ADC
380 .read
390 LDX#&10
400 .read1 DEX:BEQ read3
410 STX&FE60
420 LDA&FE60:BMI read1
430 TXA
440 .read2 DEX
450 NOP:NOP:NOP:NOP:NOP:NOP
460 BNE read2:RTS
470 .read3 TXA:RTS
480 \
490 \ Playback
500 .play SEI
510 LDA#&FF:STA&FE43
520 LDA#&84:JSR sound
530 LDA#0:JSR sound
540 LDA#&A4:JSR sound
550 LDA#0:JSR sound
560 LDA#&C4:JSR sound
570 LDA#0:JSR sound
580 LDA#0:STA&70
590 LDA&75:STA&71
600 .play1 LDY#0
610 LDA(&70),Y:AND#&0F
620 JSR fog
630 LDY#4
640 .loop DEY:BNE loop
650 LDA(&70),Y:AND#&F0
660 LSRA:LSRA:LSRA:LSRA
670 JSR fog
680 INC&70:BNE play1
690 INC&71
700 LDA&71:CMP&76:BNE play1
710 LDA#&0F:JSR fog
720 CLI:RTS
730 \ Send byte to sound chip
740 .sound
750 STA&FE4F
760 LDY#0:STY&FE40
770 NOP:NOP:NOP:NOP
780 NOP:NOP
790 LDY#8:STY&FE40
800 RTS
810 \ Look up atten values, send to
3 chans
820 .fog TAY:LDA table,Y
830 ORA#&90:JSR sound
840 ORA#&20:JSR sound
850 EOR#&60:JSR sound
860 LDY&74
870 .del DEY:BNE del
880 RTS
890 .table:]
900 NEXT
910 !table=&01010000:table!4=&03020
201
920 table!8=&07060504:table!12=&0F0
C0908
930 CLS:FOR A=0 TO 1
940 VDU131,157,132,141:PRINT"     T
he talking computer."
950 NEXT
960 PRINTTAB(6,6)" Press f1 to reco
rd."
970 PRINTTAB(6,8)" Press f2 to play
back."
980 END
```

Program II

short piece of sound or to find a particular word in a longer piece and then save that section of memory to disc or tape. The initial value for start is &22 and for end is &7B.

For example to playback then save a word found between say &3000 and &3500 enter:

```
?&75=&30
?&76=&35
```

Then press f2.

```
*SAVE"WORD"3000 3500
```

The word saved on disc or tape can be loaded and played back by:

```
*LOAD"WORD"2200
?&75=&22
?&76=&27
```

Then press f2.

The playback speed can be varied by changing the contents of location &74.

PROGRAM STRUCTURE

70-90	Set up initial values for speed, memory, start and end.
110-130	Set up assembler parameters, listing and report errors.
150-160	Set up memory start.
170	Sets up user port.
190-250	Main loop for record, stores data bytes and increments memory pointer.
240	Tests memory end.
260-360	Pack two samples into a single byte.
370-470	Read a 4 bit sample from the ADC. Start from 15, decrement count and output it to user port. If bit 7 of user port is low store the count, continue till zero.
510-570	Set all three tone generators to 31kHz.
580-590	Set up memory start.
600-690	Main play loop. Splits a byte into two samples.
700	Tests for memory end.
740-800	Send a byte to the sound chip.
820-880	Look up the values to send to sound chip attenuator control, send this value to the three generators.
860-880	Delay to set playback speed.
910-920	Use the ! operator to store the look-up table in memory.

BBC COMPUTER & ECONET REFERRAL CENTRE
ESTABLISHED OVER 15 YEARS

TECHNOMATIC

17 Burnley Road, London NW10 1ED Tel: 01-208 1177
305 Edgware Road, London W2 Tel: 01-723 0233

BBC MASTER SERIES

AMB15 MASTER
Foundation 128K. **£434 (a)**

AMB12 MASTER ET
(ANFS only)128K **£334 (a)**

AMCO6 Turbo 65C02 Module **£99 (b)**

ADC08 512 Processor **£329 (b)**

ADF13 ROM Cartridge	£13 (d)	ADJ23 Ref Manual Part II	£14 (c)
ADF10 Econet Module	£41 (c)		
ADJ22 Ref Manual Part I	£14 (c)	ADJ24 Adv Ref Manual	£19.50 (c)
BBC MASTER Dust Cover	£4.75 (d)	View User Guide	£10 (d)
		Viewsheet User Guide	£10 (d)

BBC MASTER COMPACT

A free packet of ten 3.5" DS Discs with each COMPACT"

See page 5 for details

SYSTEM 1
128K, Single 640K Drive & bundled software. **£385 (a)**

SYSTEM 2
System 1 with a 12" Hi Res Monochrome Monitor. **£469 (a)**

SYSTEM 3
System 1 with a 14" Med Res RGB Monitor. **£599 (a)**

Second Drive Kit. **£99 (c)**

Extension cable for external 5.25" Drive. **£10 (d)**

UPGRADE KITS

1.2 OS ROM	£15 (d)	ADFS ROM	£26 (d)
DNFS ROM	£17.50 (d)	1770 DFS Kit	£43.50 (d)
BASIC II ROM	£22.50 (d)	Econet Kit	£55 (d)

ECONET ACCESSORIES

Econet Starter Kit	£85 (b)	Econet Bridge	£174 (b)
Econet Socket Set	£29 (c)	Printer Server Rom	£41 (d)
File Server Level II	£125 (b)	10 Station Lead Set	£26 (d)
Ad Econet User Guide	£10 (d)	Econet Manager's Guide	£10 (d)

32016 CO PROCESSOR

For full specification see page 5 **£1,099 (a)**

CAMBRIDGE W/STATION

For full specification see page 5 **£3,450 (a)**

PANOS/PANDORA Upgrade incl 32000 BASIC FP. **£29 (d)**
Co-Processor upgrade to 10 MHz operation (to enable use of ADFS with floppy drives). **£POA (d)**
32016 Instruction Set Manual. **£25 (c)**

WINCHESTER DRIVES

Acorn 30 Mbyte Winchester with File Server Level III and ADFS hierarchical filing System. **£1,549 (a)**

P20HD TECHNOMATIC 20 Mbyte Winchester Drive fully compatible with Acorn ADFS and FS III. Includes ADFS Rom. **£635 (a)**

P204HP TECHNOMATIC 20 Mbyte Winchester and a 80T DS floppy Drive built in a monitor stand. Includes ADFS Rom. **£849 (a)**

P2041HT As P204HP but also with a 10 Mbyte tape streamer backup unit and backup utilities. Includes ADFS Rom. **£1,499 (a)**

TS10 10 Mbyte Tape Streamer Backup unit with utilities. **£695 (a)**

TFC10 10 Mbyte Pre-formatted Cartridge for use with P2041HT and TS10. **£19 (d)**

WINCHESTER Drive Multiplexer
A unique way of allowing two to four computers to share the large storage capacity of Winchester drives for saving and loading data.
TWM2 for two computers. **£99 (b)**
TWM4 for four Computers. **£159 (b)**
Details on Technomatic Winchesters and accessories on page 6

SECOND PROCESSORS

ACORN 6502 2nd Processor **£173 (b)**
TORCH ZEP100 **£229 (a)**

MULTIFORM Z80
TECHNOMATICs multi format Z80 system includes a FREE Pocket Wordstar. **£299 (b)**
MS/DOS Read/Write Utility. **£49 (d)**
See page 7 for details.

ACORN IEEE INTERFACE

Allows BBC computer to control any scientific and technical equipment that conforms to the IEEE488 standard. The interface can link upto 14 compatible devices. Typical applications are in experimental work in academic and industrial labs. **£265 (a)**

TELETEXT ADAPTOR

Converts your computer into a teletext receiver. **£119 (b)**

BBC Publications rom for enhanced Teletext Utilities. **£7.95 (d)**

ROBOCOM BITSTICK

BITSTICK II **£755 (a)**
Upgrade for Bitstick I to II **£415 (a)**
Epson FX80 Dump for Bitstick I/II **£25 (d)**

PRINTERS

EPSON LX86
120 cps, variety of fonts including NLQ, bit image graphics, IBM char/graphics compatible, centronics interface standard. **£209 (a)**

EPSON LX80/86 Tractor Feed **£20 (c)**

EPSON LX80/86 Sheet Feeder **£49 (c)**

EPSON FX85
160cps, 80 col, 8K buffer, NLQ, IBM compatible graphics Variety of fonts, multiple density bit image mode. **£315 (a)**

EPSON FX105
As FX85 but with wide carriage for 136 col **£435 (a)**

EPSON EX800
See specification on page 5 **£409 (a)**

EPSON LQ800
See specification on page 5 **£439 (a)**

EPSON LQ1000
As LQ800 but wider carriage for 136 columns **£619 (a)**

TAXAN KP810
140 cps, 80 col, NLQ, 2K buffer, variety of fonts, quad density hi res bit image graphics, centronics interface standard **£215 (a)**

TAXAN KP910
As KP810 but with wide carriage for 156 col **£349 (**

NATIONAL PANASONIC KX P1080 **£149 (**
See specification on page 5.

STAR NL 10 (Parallel Interface) **£239 (**

STAR NL 10 (Serial Interface) **£279 (**

EPSON JX80 colour printer **£420 (**

INTEGREX Multicolour Inkjet printer. **£549 (**
Ideally suited for high res colour VDU screen dumps. Quiteness & consistent output are major characteristics. **£525 (**
BBC Screen dump for Integrex. **£15 (**

CANON PJ1080A printer **£409 (**
4 Colours.

BROTHER HR20
A new attractively styled printer from Brother with unusually quiet operation, host of new features, including option to copy current document. 8K buffer standard expandable to 16K. Parallel & Serial ports as standard. **£329 (**

JUKI 6100 Daisy wheel printer
15 cps, 2K buffer, switchable 10/12/15 cpi proportional spacing, underlining. Parallel interface. **£279 (**

PLOTTERS

See details on page 5.

EPSON HI 80 PLOTTER **£319 (**
HITACHI 672 PLOTTER **£459 (**
GRAPHICS WORKSTATION **£599 (**
LINEAR GRAPHICS
A4 PLOTMATE **£224 (**
A4M PLOTMATE **£299 (**
A3M PLOTMATE **£426 (**

PRINTER SHARERS & BUFFERS

BUFFALO 32K
32K parallel buffer for internal fitting to most EPSON/Epson compatible printers. **£75 (**

TECHNO SHARER BUFFER
A unique sharer/buffer connects upto 3 computers to a single printer with auto scan and switching to computer outputting the data. Printer PAUSE, COPY and CLEAR facility. Mains powered, two buffer sizes 64K & 256K

TSB 64 **£199 (**

TSB 256 **£275 (**

PERIPHERAL & COMPUTER SHARER
High quality switches to allow the user to swit between computers, printers, modems etc. Fu shielded metal cases. all lines fully switched.

		Parallel		Seri
3 Computers to 1 Printer	36v36-3	£69 (c)	25v25-3	£65(
4 Computers to 1 Printer	36v36-4	£85 (c)	25v25-4	£75(
2 computers/2 Printers X-over	36v36-x	£69 (c)	25v25-x	£65(
BBC Cable set 3 to 1 (1m ea)		£32 (d)		£34(
BBC Cable set 4 to 1 (1m ea)		£39 (d)		£41(

BBC Computer Sharer: TCS26
1 computer to 2 printers fitted with BBC cable **£22.00 (**

ICHNOLINE
24 hr viewdata system)
el: 01-450 9764

AIL ORDER
Burnley Road
ndon NW10 1ED
lex: 922800

RETAIL SHOPS
15 Burnley Road, London NW10 1ED
Tel: 01-208 1177 Telex: 922800
(close to Dollis Hill ⊖)

West End Branch
305 Edgware Road, London W2
Tel: 01-723 0233
(near Edgware Road ⊖)

For fast delivery telephone your order on 01-208 1177 using VISA/Access Card

Orders welcome from government depts & educational establishments.

All prices ex VAT. Prices are subject to change without notice.

Please add carriage
(a) £8.00 (Datapost)
(b) £2.50
(c) £1.50
(d) £1.00

DISC DRIVES

Full details on page 6.

5.25" Single Drives 40/50 switchable:

TS400 400K/640K — **£114 (b)**

PS400 400K/640K with integral mains power supply — **£129 (b)**

5.25" Dual Drives 0/80 switchable:

TD800 800K/128OK — **£226 (a)**

PD800 800K/1280K with integral mains power supply — **£229 (a)**

PD800P 800K/1280K with integral mainspower supply and monitor stand — **£249 (a)**

3.5" 80T DS Drives:

TS351 single 400K/640K — **£99 (b)**

PS351 single 400K/640K with integral mains power supply — **£119 (b)**

TD352 Dual 800K/1280K — **£170 (b)**

PD352 Dual 800K/1280K with integral mains power supply — **£187 (b)**

DISC DRIVE MULTIPLEXER

Full specification on page 6.

TDM2
Dual Unit: 2 computers/one drive unit — **£75 (b)**

TDM4
Quad Unit: 4 computers/one drive unit — **£135 (b)**

3M FLOPPY DISCS

5.25" Discs in packs of 10

744 40T SS DD — **£10.00 (d)**
745 40T DS DD — **£12.00 (d)**
746 80T SS DD — **£14.50 (d)**
747 80T DS DD — **£16.00 (d)**

(Add £1 for library case packing)

3.5" Discs in packs of 10

40T SS DD — **£20 (d)**
80T DS DD — **£25 (d)**

BULK DISCS

High quality unlabelled discs supplied in packs of 50 in a storage box. The 5.25" discs have the reinforcing hub rings. These discs are guaranteed for life.

5.25" 40 T single sided discs in lockable box. — **£35 (b)**

5.25" 80T double sided discs in lockable box. — **£45 (b)**

3.5" 80T double sided discs in lockable box. — **£95 (b)**

FLOPPICLENE DRIVE HEAD CLEANING KIT

5.25" Kit with 20 disposable discs — **£12.50 (d)**

3.5" Kit with 20 disposable discs — **£14.00 (d)**

DISC STORAGE BOXES

CB530 Non Lockable 30 x 5.25" — **£6.00 (c)**
CB340 Lockable 40 x 3.5" — **£8.50 (c)**
CB550 Lockable 50 x 5.25" — **£9.00 (c)**
CB570 Lockable 70 x 5.25" — **£11.00 (c)**
CB5100 Lockable 100 x 5.25" — **£13.00 (c)**

MONITORS

BBC lead incl with all monitors

MICROVITEC 14" RGB Monitors
Please specify plastic or metal case.

Microvitec 1431
Standard Resolution 453 pixels — **£179 (a)**

Microvitec 1431AP
As 1431 + composite video and sound input — **£199 (a)**

Microvitec 1451
Medium Resolution 653 pixels — **£225 (a)**

Microvitec 1451AP
As 1451 + composite video and sound input — **£259 (a)**

Microvitec 1441
High Resolution 895 pixels — **£365 (a)**

Microvitec 20" RGB/PAL/ Audio Monitors

Microvitec 2030CS
Standard Resolution RGB/Comp Video — **£380 (a)**

Microvitec 2040CS
High Resolution RGB/Comp Video — **£685 (a)**

TOUCHTEC-501
Brings genuine touch screen operation on metal cased Microvitec monitors, incl utilities disc with starter and development programs — **£219 (b)**

PHILIPS 8501
RGB Standard Resolution — **£139 (a)**

TAXAN SUPER VISION II
12" Hi Res/Hi Contrast
Option to switch to green/amber
BBC/IBM Compatible — **£279 (a)**

TAXAN SUPER VISION III
12" Super Hi Res and contrast RGB Monitor with option to switch to mono BBC/IBM compatible. — **£319 (a)**

MITSUBISHI XC1404
14" Med Res RGB Monitor
Etched dark screen brilliance and contrast control, BBC/IBM compatible — **£219 (a)**

12" MONOCHROME MONITORS

TAXAN KX1201G
Hi Res green etched screen — **£90 (a)**

TAXAN KX1202G
Hi Res Long Persistence (P39) — **£95 (a)**

TAXAN KX1203A
Hi Res amber etched screen — **£95 (a)**

PHILIPS BM 7502
Hi Res green screen — **£75 (a)**

PHILIPS BM7522
Hi Res amber screen — **£79 (a)**

HANTAREX HX12 — **£69 (a)**

MONITOR ACCESSORIES

Microvitec Swivel Base (14" plastic monitors) — **£20 (c)**
Philips Swivel Base — **£14 (c)**
Monitor Stand Models B & B+ — **£10 (c)**
Monitor Stand Master — **£13 (c)**
Double Tier stand Models B, B+ or Master — **£24 (b)**
Taxan RGB Lead — **£5 (d)**
Microvitec Lead — **£3.50 (d)**
Monochrome BNC/Phono Lead — **£3.50 (d)**

RAM/ROM EXPANSION

ATPL Board for Model B. Simple to instal, no soldering. Allows expansion to 15 Roms + 28K Rams — **£37 (b)**

ATPL Battery backup kit — **£18 (b)**

RAMROM 15 for Model B. External board in an attractive case — easy access to sockets. 6502 Processor signals for development work. — **£69 (b)**

Low Profile Cartridge Module
Module + 1 cartridge — **£12 (d)**
Spare Cartridge — **£2.50 (d)**
Cartridge rack — **£1.50 (d)**

TIME WARP
Real Time Clock. Plugs into the user port, battery back up as standard, includes manual, demo software including a diary/planner application program — **£31 (d)**

MODEMS

(All modems are BABT approved)
See page 7 for modem specifications

MIRACLE WS2000V21/23 & BELL stds — **£102 (c)**
WS2000 Auto Dial Card — **£27 (d)**
WS2000 Auto Answer Card — **£27 (d)**
WS2000 SK1 Kit — **£5 (d)**
WS2000 DS1 disc — **£10 (d)**
WS2000 Data Cable for BBC — **£6 (d)**

MIRACLE WS4000 V21/23 — **£149 (b)**

MIRACLE WS3000 V21/23 — **£295 (b)**

MIRACLE WS3000 V22 — **£495 (b)**

MIRACLE WS3000 V22 bis — **£650 (b)**

WS3022 1200/1200 fd NEW — **£395 (b)**

WS3024 2400/2400 fd — **£570 (b)**

BBC Data Cable for WS3000 — **£7 (d)**

GEC DATACHAT Modem V23
1200/75, 75/1200 & 1200/1200 pseudo f.d. line powered, complete with software suitable for connecting to Prestel, Micronet, Telecom Gold and many bbs. **Special offer price** — **£39 (b)**

PROGRAMMING ACCESSORIES/SOFTWARE

See page 8 for detailed specification

Compatible with B, B+ and Master

EPROMER II with disc based software and rom image — **£99 (b)**

MPROMER — **£49 (c)**

META ASSEMBLER — **£145 (b)**

PORTAL EPROM EMULATOR 128K — **£185 (b)**

PORTAL EPROM EMULATOR 512K — **£285 (b)**

TEAM Disassembler — **£145 (b)**

EPROM ERASERS

UV1B 6 eproms, safety cutout — **£47 (b)**

UV1T 6 eproms, timer, safety cutout — **£59 (b)**

CAD/DRAWING PACKAGES

NOVACAD CAD Package for B, B+ & MASTER (See page 9 for specification)

BBC COMPUTER & ECONET REFERRAL CENTRE
ESTABLISHED OVER 15 YEARS

TECHNOMATIC

17 Burnley Road, London NW10 1ED Tel: 01-208 1177
305 Edgware Road, London W2 Tel: 01-723 0233

BASIC Version	£79 (d)
Tracker Ball/Mouse Version (TM)	£99 (d)
TM Version plus Tracker Ball	£129 (c)
TM Version plus Mouse	£115 (c)
Plotter Driver Generator	£28 (d)
MOUSE	
AMX MOUSE with SUPER ART (pse specify B, B+ or Master)	£67 (d)
Super Art	£43 (d)
PAGEMAKER	£39 (d)
3D ZICON	£21 (d)
PAINTPOT	£21 (d)
DATABASE	£21 (d)
RB2 TRACKER BALL RB2 Tracker Ball with Icon Master (for B, B+ & Master)	£52 (c)
RB2 Tracker Ball with Cursor Control Rom (for Master only)	£52 (c)
RB2 Tracker Ball 'Stand Alone' for use with NOVACAD & other software)	£47 (c)
Cursor Control Rom for Master	£12.50 (d)
MIRRORSOFT FLEET STREET EDITOR incl VAT	£39.50 (d)

SOFTWARE CP/M SOFTWARE

for Acorn, Torch & Multiform Z80 Processors

MICROPRO's Wordstar Professional	£310 (a)
ASHTON TATE's DBASE II	£310 (a)
SUPERCALC II	£195 (a)

Send for details on our full range of CP/M & PC DOS packages for Business, Communications & High Level Languages.

BBC SOFTWARE/ FIRMWARE

DATABASE MANAGEMENT SYSTEMS

VIEWSTORE
Acorn's database with display in any mode in spreadsheet or user defined card format and powerful sort facilities.Max file size 4Mb — £37 (d)

STARdataBASE
A fast machine code, true random access database. Upto 4000 records/file, 69 fields. Fully menu driven, user defined record layout, very fast searches thru keysearch facility. Mailmerging from VIEW and WW. — £49 (d)

MASTERFILE II
Highly popular economically priced database. 17 fields per record, file size limited by drive capacity only. (40T or 80T) — £17 (d)

WORD PROCESSORS

VIEW 2.1 — £37 (d)

VIEW 3.0
New version of VIEW compatible with B+ complete with a printer driver generator. — £56 (c)

Hi-VIEW
Disc based version of VIEW 2.1 for use with 6502 2nd processor allowing upto 47K of memory for text. — £36 (d)

VIEWSPELL
Acorn's new rom based spelling checking utility with a 70,000 word dictionary on 80T disc. Additional/specialised dictionaries can be created. Facilities also include wild card search for words. — £29 (d)

VIEW INDEX — £12 (d)

VIEW PRINTER DRIVER GENERATOR
A utility to generate a View printer driver to suit any printer. Screen driver allows viewing of text exactly as it will appear on paper. — £9 (d)

DOT PRINT PLUS
Full details on page 5 NLQ rom for Epson FX/RX, MX and GLP. — £28 (d)

WORDWISE — £24 (d)

WORDWISE PLUS — £38 (d)

INTERWORD
(If you own a WW+ then quote your reg number and pay £39). — £46 (d)

WORDEASE
A 16K rom based utility for WW+ — £24 (d)

SPELLCHECK III
A 16K rom based spellcheck program for View and WW. Contains 2000 words on the rom and 6000 (expandable to 17000) words on a disc. — £31 (d)

EDWORD II — £43 (c)

SPREADSHEETS

VIEWSHEET
Acorn's spreadsheet provides 255 cols and 255 rows and will operate in any mode. Fully compatible with VIEW and 6502 2nd processor. — £37 (d)

VIEWPLOT
A disc based plotting program. (To be released soon). — £22 (d)

INTERSHEET
The new spreadsheet from Computer Concepts with many advanced features like 105 col mode, holding several spreadsheets in memory at a time etc. — £39 (d)

INTERCHART
Graphics package for Intersheet — £27 (d)

ULTRACALC
BBC Publications very popular and well proven spreadsheet rom includes graphics utility disc. — £52 (d)

QUICKCALC
A disc based economically priced spreadsheet package (40 or 80T Disc). — £14.50(d)

MINI OFFICE II
A suite of inexpensive but extensive word processor, database and spreadsheet packages. (40T or 80T) — £14.75(d)

LANGUAGES

META ASSEMBLER
Multi processor Assembler full details on page 8 — £145 (c)

TEAM DISASSEMBLER — £145 (b)

ACORN 6502 DEV. PACKAGE
A macro assembler with utilities for developing large programs in assy lang. Requires 6502 2nd processor. — £43 (d)

MACROM
A very fast full featured macro assembler rom from 6502 and 65C02 codes, allows use of macros from library disc. Assembly can be disc to memory, memory to memory, memory to disc and disc to disc thus allowing very long source code upto the length of disc in use. About 3 times as fast as ADE and 30% more economical in memory. — £33 (d)

ACORN MICRO PROLOG
Logic programming language used extensively in the artificial intelligence field. A simple 'front end' is supplied to make syntax more friendly. — £62 (d)

ISO-PASCAL
Acorn's full implementation of International Std Pascal on 2x16K roms.

ISO PASCAL STAND ALONE GENERATOR

OXFORD PASCAL
A fast P-code compiler and stand alone utility (40 or 80T).

BCPL

BCPL CALCULATIONS
Supports floating point, fixed point and fast integer calculations on BCPL — £17.50

BCPL STAND ALONE GENERATOR

ACORN LOGO

LOGOTRON LOGO

BBC PUBLICATIONS OPEN LOGO

ACORN LISP ROM

ACORN FORTH ROM

ACORN COMAL ROM

MICROTEXT
A frame based authoring system from NPL for interactive computer tutoring. Disc based

MICROTEXT PLUS
Extended Features incl extra memory, control of external devices etc. Rom based. — £22

COMMUNICATIONS

TERMULATOR
Advanced terminal emulator which includes VT52/100, Tektronics 4010, teletype emulations. — £25

COMMSTAR
A highly popular communication rom suitable for all general purpose applications (specify B or Master) — £28

COMMUNICATOR
A full 80 col VT100 emulation program with easy to follow screen menus. — £4

DATABEEB
A variety of facilities for use with WS2000 Modem — £2

DS1 DISC
Special utilities for use with WS2000 — £1

UTILITIES

ACCELERATOR — £4

ACORN BASIC EDITOR — £2

MONITOR (BBC Pub) — £3

BROM PLUS — £26.5

SLEUTH — £2

TOOLKIT PLUS — £3

TOOLBOX 2 (BBC Pub) Manual Cassette — £9.5

EXMON II — £2

HELP II — £2

ACORN GXR GRAPHICS ROM specify B or B+ — £2

PRINTMASTER — £2

DUMPMASTER supports about 40 printers — £2

FONTWISE PLUS — £1

HERSHEY FONT CHARACTER GENERATOR — £1

ICON MASTER — £2

BILLBOARD — £1

STUDIO EIGHT — £1

MOVIE MAKER
Two Roms + Cassette — £2

CC SPEECH ROM — £2

CC SPEECH ROM to Text Rom — £3

ACORN SPEECH ROM — £1

ADV TELETEXT UTILITIES ROM — £7.9

CHNOLINE
hr viewdata system)
01-450 9764

IL ORDER
Burnley Road
ndon NW10 1ED
x: 922800

RETAIL SHOPS
15 Burnley Road, London NW10 1ED
Tel: 01-208 1177 Telex: 922800
(close to Dollis Hill ⊖)

West End Branch
305 Edgware Road, London W2
Tel: 01-723 0233
(near Edgware Road ⊖)

For fast delivery telephone your order on 01-208 1177 using VISA/Access Card

Orders welcome from government depts & educational establishments.

All prices ex VAT.
Prices are subject to change without notice.

Please add carriage
(a) £8.00 (Datapost)
(b) £2.50
(c) £1.50
(d) £1.00

BBC PUBLICATIONS EDUCATIONAL SOFTWARE

eries of programs developed in many cases along- Radio & TV programmes by BBC's Education partment which supplement the classroom studies moving and colourful displays helping in clear erstanding of a variety of subjects. Some packages include audio cassettes.

RIMARY EDUCATION

TRONOMY:
2 years. Phases of moon, eclipses, ons etc. Includes a game. Disc £11 (d)

MPUTERS AT WORK:
Work Game illustrates two of the t important computer applications: otics & IT. Incl. a database prog, d processing tutorial and a robotic rol prog. Aud/EC/disc £16 (c)

TURE CRAFT
nexhaustible, versatile and flexible e of programs to design shapes & erns, paint them and convert them pictures, puzzles and games. Disc £17 (d)

AWSTICK
ar upwards for creating pictures, rs, maps etc. Pictures created can used in your own programs. iciently sophisticated for use by rs. Cass £8 (d)

TRODUCING GEOGRAPHY
8 years. Four exciting graphical ntures include river navigation, g, mountain climbing and desert sing. Disc £16 (d)

THS WITH A STORY 1
r primary level programs incl metry, co-ordinates and prob- y for children of wide ranging ries. Cass £8 (d)

THS WITH A STORY 2
lar programs as 1 but covered n a different angle. Cass £8 (d)

MBER GAMES:
ograms designed to stimulate the t of an active child of 8 years and rd. Cass/EC £7.50(d)

NG YOUR COMPUTER
years. Introduction to computers synchronised audio techniques. l of 80mins of audio & 14 progs. Cass £24 (c)

RD PLAY
legant but simple introduction to t processing using animal shapes diting functions. Fun manual for hildren. Cass £10 (d)

RD MOVER
mple text editor. Cass £8 (d)

CONDARY LEARNING

ANCED LEVEL

DIES: STATISTICS
gs covering central concepts and ples. Topics include Discrete & Binomial Distribution. Eont. & Normal Data Distribution. thesis Testing & Confidence vals, Central Limit theorem & ation, Simulations, Correlations egressions. Disc £23 (d)

ANCED STUDIES: GRAPHY
gs covering social geography: ic & Town planning, drainage & management and planning for try. Cass £10 (d)

DE INFORMATION
ned to introduce IT to adults. Suitable for use schools, ITeCs & Adult Centres. Prog Cass £10 (d)
Audio Cass £5 (d)
Book £8 (d)

OPEN LOGO
Open University Logo incl two 16K roms and two manuals. £55 (c)

SCIENCE TOPICS (ST)

S.T.: WAVES
A Physics program allows display of waveforms and shows changes caused by different parameters. Disc £14 (d)

S.T.: RELATIONSHIPS
A Biology program giving a sophisticated simulation exercise based on data from W.H.O. Disc £14 (d)

S.T.: BONDING
A Chemistry program to reinforce & strengthen the concept of bonding of elements. Transfer and sharing of electrons are both shown graphically. Disc £14 (d)

S.T.: ELECTROMAGNETIC SPECTRUM
A graphical adventure prog to test your knowledge of the electromagnetic spectrum. Disc £14 (d)

S.T.: ELECTRONICS IN ACTION
Program about using computers for control. Control is achieved by using 6502 assy lang. Prog editor is supplied. Disc £14 (d)

S.T.: NEWTON & THE SHUTTLE
A interactive prog in 3 parts covering launch to recapture of a satellite to test the knowledge of Newtonian mech. Disc £19 (d)

S.T.: ECOLOGY
Simulation program managing a nature reserve to meet a host of individual needs. Disc/EC £19 (d)

S.T.: POLYMERS
Students run a manufacturing co. and have to choose best materials for their products and compete with a rival co. run by the computer. Disc/EC £19 (d)

S.T.: CLASSIFICATION & PERIODIC TABLE
A database program for producing different classifications of chemical information and presented in any format. Disc £20 (d)

S.T.: FOOD & POPULATION
Simulation in space of biological aspects of nutrition and food production logistics. Disc £20 (d)

SEC. SCIENCE: MICROTECHNOLOGY
Fundamental concepts of electronics Logic & Resistor Tutors, Servo Cct simulation & a cct design program. Cass £7 (d)

SEC. SCIENCE: THE MOLE CONCEPT
A computer sync. audio program explains definitions of atomic & molecular masses and depicts molar equations. Disc/Aud/EC £16 (c)

SEC. SC.: UNIFORMLY ACCELERATED MOTION:
Illustrates basic eqns., uniform accln, under gravity and an idea of terminal velocity. Disc/AUD/EC £16 (d)

VU-TYPE
The popular 'Sight & Sound' touch typing tutor with alterable settings. Disc/EC £15 (d)

GENERAL

GAME CORE
Provides information and intelligence routines for writing board games. Cass £9 (d)

VU TYPE PROFESSIONAL
An enhanced and expanded version of Vu Type with 63 Pitman approved exercise. Disc £19 (d)

WHITE KNIGHT MK II Disc £16 (d)
(Specify if for Master).

BATTLEFIELDS Cass £8.50 (d)

DEUTSCH DIREKT
Disc based vocabulary learning prog with audio cassette to help with pronounciation. Disc/aud/EC £16 (c)
Book £5.95 (d)

A VOUS LA FRANCE
A home study aid for anyone learning French. Cass/EC £12 (d)
Book £5.25 (d)

Cassette based programs listed above can be supplied on disc at an extra charge of £1.50 per disc and please specify the format required 40 or 80T.

PRINTER ACCESSORIES

EPSON ACCESSORIES:
Interfaces:
8143 RS232 £28 (d)
8148 + RS232 + 8K £75 (d)
8165 IEEE + Cable £65 (d)
8148 RS232 + 2K £57 (d)
8132 Apple II £60 (d)
8177P NLQ for FX80 + /FX100 + £99 (d)
Parallel & Serial Buffers of various size also available.
FX80/80 + /85 Tractor Attachment £37 (c)
FX80/80 + Paper Roll Holder £17 (c)
LX80 Tractor Feed £20 (d)
LQ800 Tractor Feed £44 (b)
LQ1000 Tractor Feed £49 (b)

SHEET FEEDERS:
8338 LX80 £49 (b)
8333 FX100 + /105 £169 (a)
8331 FX80 + /85 £129 (b)
8330 RX80 + £129 (b)
LQ800 £129 (b)
LQ1000 £159 (b)

Ribbons:
RX/FX100/100 +, FX105 £10 (d)
RX/FX80/80 +, FX85 £5 (d)
LX80 £4.50 (d)
LQ800 £8.50 (d)
LQ1000 £10 (d)
H180 Pen Set (Aqueous/Ball point) £7.50 (d)

Dust Covers:
FX80 £5.50 (d)
TAXAN/Canon KP810 £6 (d)
FX100 £7.50 (d) KP910 £7 (d)

HITACHI 672 Plotter
Aqueous Pen Set six pens £18.50 (d)
Oil Based Pen Set six pens £25.00 (d)

TAXAN CANON Accessories:
RS232 + 2K buffer £78 (d)
Ribbon £6 (d)

JUKI 6100
RS232 Interfaces £65 (d)
Tractor Feed £129 (a)
Ribbon (Carbon) £2.00 (d)
Spare Daisy Wheel £14 (d)
Sheet Feeder £182 (a)

BROTHER HR15
Daisy Wheel £18 (d)
Tractor Feed £90 (a)
Ribbon (Carbon/Nylon) £3.00 (d)
Sheet Feeder £182 (d)
Keyboard £135 (a)

Printer Leads:
BBC Parallel Lead (1.2m) £10 (d)
BBC Serial Lead (1.2m) £6 (d)

Other lengths can be supplied on order:
IBM Parallel Lead (2m) £12 (d)

PAPER & LABELS
Plain Fanfold paper with micro perforations:
2000 sheets 9½" × 11" £13 (b)
2000 sheets 14½" × 11" £18.50 (£4.50)
Labels/1000:
Single Row 3½ × 1 7/16" £5.25 (d)
Triple Row 27/16" × 17/16" £5 (d)

BBC SPARE PARTS
All Prices are Retail ex-VAT carriage code (d).

BBC & Misc:
Keyboards £52 (b)
Powers Supply £52 (b)
Keyswitch £1.75
Video ULA £18
Serial ULA £14
DNFS £18
UHF MOD £4.50
6502A CPU £6.50
65CO2 CPU £12
6522 VIA £3.50
6522A VIA £5.50
LM324 £0.45
74ALS 245 £5
88LS120 £3.00
BBC PLUS:
PAL16REN £13.50
64K × 4 DRAM £8.50
6512A £12.50
SAA5050 £9.00
6845SP £6.50
UPD7002 £5.00
DS3691 £3.50
7438 £0.40
74LSOO £0.24
74LSO4 £0.24
74LS10 £0.24
74LS123 £0.80
74LS163 £0.75
74LS244 £0.80
74LS245 £1.10
74LS373 £0.90
74LS393 £1.00
BBC MASTER:
1-Mbit ROM £39
MSI CHROMA IC £13.50
65SC12P-2 £12.50

BBC COMPUTER & ECONET REFERRAL CENTRE
ESTABLISHED OVER 15 YEARS

TECHNOMATIC

17 Burnley Road, London NW10 1ED Tel: 01-208 1177
305 Edgware Road, London W2 Tel: 01-723 0233

ACW443 CAMBRIDGE WORKSTATION

A complete self-contained workstation with:.

* NS32016 8MHz Main Processor & 32081 FP processor.
* 20 Mbyte Winchester and one 80T Ds floppy drive.
* A detachable keyboard Hi Res RGB Monitor.
* 4Mbyte of on board Ram as standard.
* Languages supplied include: Fortran 77, Pascal, C, Cambridge LISP, 32016 Assembler & 32bit BASIC.
* Utilities on the operating system to cross link programs between different languages, utilities for porting programs to mainframes.
* **Phone for detailed leaflet.**

32016 CO-PROCESSOR

A second processor that brings genuine 'Mainframe' power to the BBC Computer.

* Interfaces with the BBC through the tube connector.
* NS32016 6MHz CPU & 32081 FP processor.
* 1Mbyte Ram as standard.
* Packaged software includes all the languages and utilities supplied with the ACW Work Station.
* **Phone for detailed leaflet.**

CPU/FP Upgrade Kit (non-Acorn) for the Co Processor for 8Mhz operation to enable use of ADFS with the floppy drives is available. It can be fitted at no extra charge if ordered with the Co Processor.

A list of software available for the 32 bit processors is available on request.

512 CO-PROCESSOR

Brings professional software to the BBC Master.

* 10 Mhz 80186 *DOS PLUS.
* GEM Write & GEM Draw.
* 'WIMP' Environment with high quality Mouse.
* Runs many 'IBM' programs — even 'Flight Simulator'!
* Convert to/from IBM/BBC data.

DOTPRINT PLUS

A uniquely versatile NLQ ROM for the BBC Micro.

* Built-in character font generator.
* Built-in view printer driver.
* Supports microspacing for professional justification in View & with disc in Wordwise/Plus.
* True bold print as well as double width.
* 12 character pitch as standard.
* Fully variable pitch and line spacing.
* Suitable for fully **'EPSON'** compatible printers with quad-density graphics.
* **DOTPRINT PLUS** for EPSON FX/RX and compatibles.
* **DOTPRINT DUAL** for EPSON MX range.

MICROJUSTIFIED TEXT

homes of a ruling class whose right to rule was based on the ownership of land. Large estates produced money; perhaps even more important, they supplied people to fight for their

NORMALLY JUSTIFIED TEXT

homes of a ruling class whose right to rule was based on the ownership of land. Large estates produced money; perhaps even more important, they supplied people to fight for their

Notice how MICROJUSTIFICATION eliminates 'stretched' spaces between words.



For price details see page 1.

compact
BRITISH BROADCASTING CORPORATI
MASTER SERIES MICROCOMPUTER

THE FAMILY COMPUTER

Now available from stock

This low cost high tech computer h developed specially as a computer f home use.

SPECIFICATION

128K RAM, ADFS Filing syste BBC Basic version 4, MASTER st keyboard, a single 640K 3.5" dou sided drive. RGB/Mono Monitor an optional extra.

Bundled software pack includes: Desk Top Prog with note pad calculator, VIEW 3.0, Card Index LOGOTRON. A set of excit games and graphic demos.

IMPORTANT NOTICE

We would like to advise all our customers who purchased the BBC Master Computer from us between January to June 1986 to ensure that the ram batteries are replaced. The replacement kits are available free of charge.

EPSON LQ800/1000

Uses top quality 24 pin dot-matrix technology.

* Superb 'letter quality' at 67cps.
* Fast clear draft quality at 200cps.
* LQ/Draft modes selectable from front panel.
* Variety of fonts, usable in both draft & LQmodes.
* Optional 'personality' modules for Diablo and IBM emulation.
* Optional Font modules.
* Friction feed.
* Hi Res bit image graphics with hex density.
* 7K buffer, both serial and parallel interfaces as standard.

EPSON HI-80

* A4 with 4 colour precision plotting.
* Low cost while maintaining precision.
* Variety of pens available.
* Ideal for overhead transparencies.
* Powerful software commands allow complex plots.
* Superb line/bar/pie charts simply produced.

EPSON EX800

A new addition to the EPSON range provi faster printing speeds to offer versatility in volu printing. This 80 column printer prints at 300 in 12 cpi mode, 250 cps in 10 cpi and 50 cps letter quality mode. Four built in fonts, includ two letter quality fonts can be printed in a vari of typestyles. Full graphics facilities are includ Most selection from the front panel. Parallel a serial interfaces and tractor and friction feeds standard. Four colour printing option available.

NAT. PANASONIC KX P108


A high performance low cost printer with f character pitch feature 10, 12, 15 & 17 cpi and p portional spacing in both draft and NLQ mode. column, 100 cps draft and 20 cps in NLQ. Para interface and Friction and Tractor feeds standard. Epson Compatible Graphics.

HITACHI 672

* A3 four colour precision plotter.
* Serial and parallel ports as standard.
* Produces 'OHP' transparencies as well a plain paper.
* 'HP' graphics language or single characte commands.

GRAPHICS WORKSTATION

A A3 pen plotter with 0.1mm resolution allows graphs, charts, architectural drawings to be plotted using the 9 predefined plotting instructions or by using a CAD package. The pen mount allows a variety of pen types including drawing pens to be used or the following range of accessories to be fitted.



OPTICAL SENSOR

This converts the plotter into a input device a offers a new range of applications: Scan or digiti a picture or a drawing to display or store. Traver mazes and investigate methods of artifici intelligence. Reliably read bar codes.

DRILL/ROUTER

This will drill holes, machine moulds and c complex 3-D shapes in a range of suitab materials to a depth of 16mm. Driver software supplied on disc and an optional applicati program is available to interface the drill/router our NOVACAD package.

SCRIBER

The sharp pointed scriber may be used to etch fi line drawings on surfaces such as scraperboa wax coated copper etc. Full details on request. S page 1 for price.

All accessories available separately if required.

CHNOLINE
hr viewdata system)
: 01-450 9764

IL ORDER
Burnley Road
ndon NW10 1ED
x: 922800

RETAIL SHOPS
15 Burnley Road, London NW10 1ED
Tel: 01-208 1177 Telex: 922800
(close to Dollis Hill ⊖)

West End Branch
305 Edgware Road, London W2
Tel: 01-723 0233
(near Edgware Road ⊖)

For fast delivery telephone your order on 01-208 1177 using VISA/Access Card


Orders welcome from government depts & educational establishments.

All prices ex VAT.
Prices are subject to change without notice.

Please add carriage
(a) £8.00 (Datapost)
(b) £2.50
(c) £1.50
(d) £1.00



TS 400



PD 800



PD 800 P



P2041 HT

DISC DRIVES

TECHNOMATIC offers a wide range of high quality, high performance drives to meet all needs of BBC micro users. Please see our detailed and competitive price list on page 2.

*All drives are fitted with high quality slim line ultra low power mechanisms capable of single and double density operation and offering very fast track access and head settling times.

*5.25" floppy drives are fitted with 40/80 track switches as standard at no extra cost. The switches are located in the front and clearly marked to indicate the status at a glance.

*The mechanisms are set inside attractively styled, sturdy metal casings painted in BBC beige colour.

*The plinth version drives provide for a neat and compact system installation giving it a more professional look.

*All drives fitted with all necessary leads and are ready for operation on unpacking. The drives with the mains power supply are supplied with a mains lead fitted with suitably fused 13A moulded plug.

WINCHESTER DRIVES

Mass storage 20 Mbyte drives are available in the following versions:


* P20HD Stand alone.
* P204HP With a single floppy housed in a plinth version case.
* P214TS Top of the range with a 10 Mbyte back up streamer and a single floppy housed in a plinth type casing and supplied with backup utilities.
* TS10 A stand alone 10Mbyte streamer for those who are already equipped with a Winchester and a floppy drive. Utilities for backup can only be loaded from a floppy.

All models are fully compatible with Acorn's ADFS system and include a mains psu and the necessary cable connections.

ALL TECHNOMATIC DRIVES NOW CARRY A TWO YEAR WARRANTY

DISC DRIVE MULTIPLEXER

The cost-effective alternative to networking! A self-contained unit that enables up to four computers to be connected to one single or dual disc drive. No hardware modifications — simply plugs into the computers disc interface connectors. No ROMs or other software needed. All DFS commands work as normal. The switching of drives between computers is totally automatic and completely invisible to the user. This unit is ideal for installing in classrooms and other situations, where networking is not planned or necessary, or where costs must be kept low. In many cases software needs to be shared, although full networking complexity and cost is not needed. Several of these units can be connected in series to allow more computers to access the same discs, i.e. two quads connected together will allow 7 computers to share 1 drive. Units are supplied with 5' of cable per outlet as standard. Mains powered.



TDM4 Quad Unit (up to 4 computers)
TDM2 Dual Unit (2 computers)

WINCHESTER DRIVE MULTIPLEXER

A unique addition to our hardware range that allows the sharing of a Winchester between a number of computers. The principle of operation is the same as our highiy popular disc drive multiplexers and there is no need for any additional software or hardware modifications. The Multiplexers are available in two versions, a dual unit for two computers and a quad unit for four computers to share a Winchester. Multiplexers are particularly useful for accessing common software and transferring data between the computers. (Not recommended for use with randon access files).

3M FLOPPY DISCS

FREE Clock/calculator with every 5 boxes of 3M discs purchased.



Every single 3M Floppy Disc carries a written lifetime guarantee that it will perform reliably. Not only do 3M offer a highest quality product but also a very competitive price. Please see page 2 for details. 3M Floppy Discs are supplied in sturdy storage boxes each containing 10 discs. **While offer lasts discs will be supplied at specially reduced prices.**

FLOPPICLENE Disc Drive Cleaning Kit

Floppiclene introduces a positive concept in ensuring continuous high performance of the disc drives by providing an easy and efficient method of keeping the drive heads clean. Use of disposable cleaning discs eliminates the risk always present in reuseable discs of recontamination and abrasion of the sensitive drive heads. Available for both 5.25" and 3.5" drives. Please see page 2 for prices.

BBC COMPUTER & ECONET REFERRAL CENTRE
ESTABLISHED OVER 15 YEARS

TECHNOMATIC

17 Burnley Road, London NW10 1ED Tel: 01-208 1177
305 Edgware Road, London W2 Tel: 01-723 0233

MODEMS


MIRACLE WS4000

* A cost effective intelligent modem that offers the best value for money bringing the world of data communication within easy reach.
* Plain English commands make it simple to use, even for the first time user.
* Latest Hayes-type protocol commands, auto dial, auto answer, auto speed seeking.
* Equalisation model in V23 for line-noise filtering.
* Many other options including upgrading to V22 and V22 bis.

MIRACLE WS2000

* A comprehensive manually switched 'World Standard' modem.
* Competitively price with a capability to be upgraded for various options.
* BT approved for V21/V23, 300/300, 1200/75 and 1200/1200 half duplex.
* Includes BEL103/113/108 standards for use outside UK.

Optional extras include (Not BT approved).
* SK1 chip set for computer control.
* User port cable.
* Auto dial Board.
* Auto Answer Board.
* DS1 disc for auto dial facilities on Commstar.



WS 3000 Range

Miracle have introduced two new models in the WS3000 series for users who require a modem for a specific use. Model WS3022 provides 1200/1200 baud full duplex operation whilst only WS3024 provides 2400/2400 baud fd only.

Please see page 2 for prices

MIRACLE WS3000 RANG

* A professional range of intelligent mod with full BABT approval.
* Auto Answer and Auto Dial facil installed as standard.
* HAYES protocols implemented.
* Pulse or DTMF 'tone' dialing.
* Plain English command structure sim fies the use of the modem.
* Integral parallel printer port fitted standard configurable for both input output for process control application
* A line sharing facility to differen between data and voice calls.
* Intelligent speed buffering conv 1200/1200 terminals to 1200/75
* Equalisation mode for line noise filter
* Internal battery back up for storing names, numbers and default settings.
* Upgrade path for 1200/1200 2400/2400 and security encryption.
* Applications in the field of graphics text access, high speed telex, user to u and user to main frame.

SPECIFICATIONS


WS4000 V2123:	*CCITT V21/V23. *300/300, 600 and 1200 duplex, 1200/75.
WS3000 V2123:	*CCITT V21/V23/Bell 1 300/300, 600 and 1200/7
WS3000 V22:	*As V2123 and 1200/1200 full duplex.
WS3000 V22 bis:	*As V22 and also 2400/2

MULTIFORM Z80

includes a FREE Pocket Wordstar package

A unique Z80 2nd Processor with a 'MULTI FORMAT' capability.

"A wide selection of programs were installed and tested without problems. The task of transfering and installing the programs for the system was greatly eased by the flexibility of the multiformat approach and the implementation of the terminal emulators. *Ed Brown Acorn User Oct 86.*"



Please see page 1 for prices

* It is capable of running most CP/M 2.2 format applications programs on the BBC.
* Connects to the BBC via 1MHz bus, no restriction on the cable length. OS/M operating system on rom.
* Integral mains psu and 64K on board ram.
* 28 different formats including Acorn Z80, RML 380Z & 480Z, EPSON QX, Amstrad, Osborne etc, supplied on the library disc with the utility to create additional formats.
* Emulates the two of the most commonly used CP/M terminals, HAZELTINE 1500 and ADM-3a in addition to the Acorn VDU making installation of most of the software packages easy.
* Utility to inter convert ASCII text wordprocessed on a standard BBC and under OS/M or CP/M .
* Multiform is fully compatible with Acorn's 8271 and 1770 DFS on models B, B plus and the Master.
* Single density dfs allows single density CP/M format use Double density dfs allows both single and double den CP/M formats to be used.
* Single or dual, single sided or double sided and 40 or 80 tr drives can be used provided that they match the CP/M s ware format to be run.
* Dual drive will allow two separate formats to ope simultaneously for data transfer making it ideal for us environment where machines with different formats are use.
* Utility to read and write on IBM PC DOS discs available a optional extra. Utility will also format a PC DOS disc.
* Multiform Z80 is supplied with a OS/M operating sys rom, System disc and a Library disc. Please specify the type and the drive format when ordering.

CHNOLINE
hr viewdata system)
: 01-450 9764

AIL ORDER
Burnley Road
ndon NW10 1ED
ex: 922800

RETAIL SHOPS
15 Burnley Road, London NW10 1ED
Tel: 01-208 1177 Telex: 922800
(close to Dollis Hill ⊖)

West End Branch
305 Edgware Road, London W2
Tel: 01-723 0233
(near Edgware Road ⊖)

For fast delivery telephone your order on 01-208 1177 using VISA/Access Card

Orders welcome from government depts & educational establishments.

All prices ex VAT. Prices are subject to change without notice.

Please add carriage
(a) £8.00 (Datapost)
(b) £2.50
(c) £1.50
(d) £1.00

EPROMER III Eprom Programmer

n enhanced version of the highly successful EPROMER II providing added phistication to the eprom programming applications on the BBC computer range. e new software also utilises the extra facilities of the BBC Master computer. The ogramming methods are 'state of the art' of programming technology for fast, ficient and cost effective operation.

The single rail eproms handled by the EPROMER III are:

● 2716 2732 2764 27128 27256 27512 27513
2516 2532 (NMOS & CMOS)
● One time eproms P27XXX, 87CXXX etc.
● Also A suffix eproms such as 27XXXA

e software is menu driven, many operations being single key. On screen help rifying the operation being carried out. Will make the programming process very ple and easy for both specialists and novices alike.

The main features of the programming software are:

* Device, function and voltage selection from the computer keyboard.
* Continuous display of the options selected.
* All eproms upto 27512 (64K) programmed in single pass.
* Automatic Intelligent identifier support for eproms able to respond.
* Selectable programming voltage 25/21/12.5V
* 3 programming methods: Normal, Intelligent & Pulse (20 sec for a 27128).
* Serial port protocols supported.
* Intel HEX, Motorola S, HEX and ASCII protocols supported.
* DFS/ADFS and Rom Filing System Supported.
* BASIC/Machine Code programming using RFS.
* Powerful editor with input in HEX or ASCII.
* Block move of data within the address range.
* User can select any section of the eprom from single byte to the full address range to blank check/burn/verify. Facility to program single bytes makes program development/amendment simpler.
* Software interface provided for users own application (alternate byte program etc)

EPROMER III interfaces with the BBC through the 1 MHz bus, has a mains integral mains power supply and is fitted with a 3M TEXTOOL ZIF socket to provide consistent and reliable service for a long period.

META Version III

"All the good features you would expect to find in a good source code editor are esent . . . Meta assembler lives in a different world. It is structured to work th any new processor . . . as new instruction sets can be added . . . as needed . . has a well featured editor with colour highlighting, a sound modular proach." **Acorn User October 1986**

- Assembles for over 30 popular processors, including Z80, 6800/01/02/04/05/09/11 etc — and 68000 — using native mnemonics for each processor, eg. LD A, (HL) for Z80 and MOV AO, $1000 for 68000 etc.
- Fully integrated Editor: four field, all search, search/replace, block copy, delete, move, marked save, load etc.
- Compatible with Portal Eprom Emulators and Team Disassemblers.
- Send object code in Intel Hex, S-Record, straight binary etc. down to discs, RS232, parallel port, Eprom Emulators etc — all **during Assembly.**
- Over 50 directives included as standard: handling nestable macros, conditional assembly and twenty types of table definition directives.
- 32 bit labels; 31 character names. Arithmetic and Boolean arithmetic to 32 bits.
- Modular source code with numeric and string parameter passing.
- Serial communicator area with eight options lines: echo, control code trap, LF supression/addition etc.
- Over 500 in use throughout the world in universities and many different industries.
- Two 16K Roms, two 80 track discs, A4 ring-band manual, function-key strip.

PORTAL EPROM EMULATORS

- Emulates 2716, 2732, 2764, 27128, 27256, 27512 eproms at 150ns Access time.
- Load at 4Kbytes/second — No "erase" time.
- 28 pin header plugs into Eprom socket on target system — status monitored on 13 Leds.
- Fully software controlled from Meta Assembler.
- 100 times faster than standard EPROM program/erase cycle.
- Fully CMOS compatible; draws no power from target system.
- Four portals may be independently programmed off same user-post cable.
- Complete with all cables, manual and disc.

ORTAL 128 (2716, 2732, 2764, 27128):
ORTAL 512 (2716, 2732, 2764, 27128, 27256, 27512).

MICROPROMER

An add on unit for Epromer II enabling the user to program 8741, 8748 and 8749 single chip microcontrollers. Now with the aid of cross assemblers such as META, the user can write code for the above devices and then with the aid of Micro-promer program the device.

* Simple menu structure with on screen help. i.e. select a function and on the screen will appear details of the function being performed.
* Comprehensive error reporting and checking.
* Read, verify, blank check, program from 1 to the maximum byte count for the device being used at any address location.
* Support for DFS, ADFS and cassette filing systems.
* Edit data in Hex or ASCII.
* Total control via software, no switches to worry about.
* Supplied with user manual and software on diskette.
* MPROMER simply plugs into the EPROMER II ZIF socket.

TEAM DISSASSEMBLER

The third part of the Universal Development System: a Meta labelling dissassembler.

Supports 1802, 8080, 8085, HD64180, Z80, 65XX (includes 65 col, 6511 etc), 68XX (includes 00, 01, 02, 03, 08 etc): updates soon for most of Meta processors.

- Up to 64K of object code translated back into META compatible source code modules: labels automatically inserted on all jump targets, memory references etc.
- Pre-editing stage allows marking of object code areas as byte, string, word, long word etc, tables. These areas dis-assembled into appropriate directives instead of garbage mnemonics.
- Reconstituted source code ready for immediate re-assembly by META.
- Omniversal search/replace for re-naming arbitary label names with meaningful ones.

OOKS
VAT Carriage Code (c)

NGUAGES
Assy Lang Prog.....£19.95
Programming.....£13.95
Book.....£23.95
rn BCPL User Guide.....£15.00
rn FORTH.....£7.50
rn LISP.....£7.50
rn ISO Pascal Ref Manual.£10.00
to COMAL.....£10.00
to LOGO.....£7.50
o Prolog Ref Manual.....£10.00
oduction to Turbo Pascal..£14.95

Prog the Micro with Pascal.....£8.50
The UNIX Book.....£7.50
Unix User Guide.....£19.95
Understanding Unix.....£18.45

BBC MICRO GUIDE BOOKS
BBC User Guide Acorn.....£15.00
BBC Plus User Guide.....£15.00
Drawing your Own BBC Programs.....£6.95
Inside Information.....£8.95
Math Prog in BBC Basic.....£7.95
Toolbox 2.....£10.95
VIA 6522 Book.....£4.50

PROGRAMMING/UTILITY
Advanced Sidewise Ram User Guide.....£9.95
Advanced User Guide (BBC)...£15.95
Advanced User Guide.....£12.50
Applied Ass./Lang on the BBC.£9.95
BBC Micro Sideways ROM's RAM's.....£9.95
Guide to the BBC ROM.....£9.95
Beginners Guide to W.P.....£7.95
View 3.0 User Guide.....£10.00
Viewstore.....£10.00
Viewsheet.....£10.00
Wordwise Plus.....£9.95

SOUND & GRAPHICS:
Mastering Music.....£6.95
DISC DRIVE SYSTEMS:
Advanced Disc User Guide.....£16.95
Disc Book.....£3.50
Disc Programming Techniques..£7.95
Disc Systems.....£6.95
File Handling on the BBC.....£6.95
Discovering Disc Drives.....£POA
APPLICATIONS:
Interfacing Proj for BBC.....£6.95
BBC and Small Business.....£5.75
PROFESSIONAL SOFTWARE
Wordstar made easy.....£16.95

Introduction to Wordstar.....£17.95
Wordstar Handbook.....£11.95
dBase-II for the first time user.£16.95
Understanding dBase-III.....£22.95
Multiplan Made Easy.....£18.95
Multimate Complete Guide.....£16.95
ABC of LOTUS 123.....£17.45
1-2-3 for Business.....£16.95
Adv Tech in dBase II/III.....£22.95
Mastering CP/M.....£17.95
CP/M Bible.....£16.50
Introducing CP/M on BBC & Z80.....£9.95
MS/PC DOS Prompt.....£10.95

TECHNOLINE
(24 hr viewdata system)
Tel: 01-450 9764

MAIL ORDER
17 Burnley Road
London NW10 1ED
Telex: 922800

RETAIL SHOPS
15 Burnley Road, London NW10 1ED
Tel: 01-208 1177 Telex: 922800
(close to Dollis Hill ⊖)

West End Branch
305 Edgware Road, London W2
Tel: 01-723 0233
(near Edgware Road ⊖)

For fast delivery telephone your order on 01-208 1177 using VISA/Access Card

Orders welcome from government depts & educational establishments.

All prices ex VAT. Prices are subject to change without no

Please add carriage
(a) £8.00 (Datapost)
(b) £2.50
(c) £1.50
(d) £1.00

NOVACAD


Computer Aided Draughting for the BBC Micro

" The Novacad system is a thoughtfully designed piece of software requiring a minimum of manual bashing so that real results are possible with just a few hours work. "

" Novacad is a professional package, well worth the £90 for the ROM and disc and is expandable to suit your own particular requirements. I would have no reservations if I heard Novacad called, "the best on the market". " **A&B Computing August 1986**


A sophisticated CAD package with unique facilities which are generally confined to the professional CAD packages costing thousands of pounds.


NOVACAD is being used in widely differing fields ranging from leading British industries for producing engineering drawings to Accountants' offices for producing flow charts. Architects, engineers, plumbers, kitchen planners and many other professions requiring easy to use facilities for producing professional quality output are making extensive use of NOVACAD's unique features. NOVACAD is proving to be a invaluable teaching aid in technical schools and colleges simply because of the ease with which it can be used.





The major features of NOVACAD are:

* Simple and easy to use with logical command sequence.
* A large drawing area (approx 15 screens).
* The ability to create complex icons (upto 500 lines instead of the usual 15 to 20 pixels), store them in a library and recall them at different scales and orientations.
* A zoom facility allowing magnification of up to 20 times to insert finer details.
* Block copy of shapes on the screen for repetitive use.
* Text entry at any 90° orientation at any position on the screen.
* Create multi layer drawing with 8 levels available.
* Full compatibility with the BBC range with minimal hardware requirements yet having the capability of exploiting the potential of the extra shadow memory or the second processor's memory and speed.
* Printer routine for Epson 80 and 136 column printers.
* A unique facility to output to any BBC compatible plotter.









MINIMUM HARDWARE REQUIREMENTS

- **Any BBC range computer with Acorn DFS.**
- **40 Track single sided single drive.**
- **Epson compatible dot matrix printer.**

With basic BBC B, NOVACAD operates in mode 4 allowing use of any 2 colours. With shadow memory of the BBC+ or the Master, it can also operate in mode 0 for higher resolution or mode 1 for allowing use of any 4 colours, and it will provide additional user memory for more complex drawings.
6502 second processor or the Turbo on the Master will also increase the drawing speed considerably.

NOVACAD is available in two versions

*BASIC version for cursor control from the keyboard.

*T/M version for cursor control from the keyboard, Tracker Ball or a Mouse.


OPTIONAL EXTRAS

Plotter driver generator is available as an optional extra to configure a plotter routine for any BBC compatible plotter. Pre-configured programs for the popular plotters like **Epson HI 80, Hitachi 672, Plotmate, Penman** and **HP GL.** This program allows the drawing to be scaled to the maximum plotter size thus enabling drawing of A2 and A3 sizes to be produced with equal ease. The zoom facility will enable inaccuracies of drawing on the screen to be eliminated.

ROUTCAD, an optional software package for our Graphics Workstation allows for production of shapes drawn using NOVACAD in 3D on suitable material and is ideal for a range of applications including template making and model building.

NOVACAD package includes a 16K ROM, Utility disc and a comprehensive manual.

BUSINESS MICRO USER



Principal Duncan Baker in the office at Lydbury English Centre

From submarines to business, via the BBC Micro

By TONY LEAH

AFTER a career as a Royal Navy officer, followed by eight years in the diplomatic service, Duncan Baker decided it was time to drop anchor.

Equipped with a BBC Micro that had accompanied them on their travels, plus plenty of optimism and energy, Duncan and his wife Rita ploughed their savings into a business venture.

Not for them the safe harbour of a post office, boutique or pub – they wanted to create something of their own from scratch.

The question being, just what were a submarine navigation officer and a housewife-cum-mother-of-four qualified to do in the world of commerce?

They found the answer in their respective backgrounds.

Rita had previously been a teacher for 14 years, with post graduate qualifications in teaching English as a foreign language. Duncan knows exactly what it is like to be immersed in language training, having spent 15 months studying Arabic for a Foreign Office posting.

It was this combination that decided them to buy a rambling old vicarage in the Shropshire countryside and open the Lydbury English Centre – offering residential language courses to foreign businessmen and government officials.

The business itself, and the teaching of English as a foreign language, are conducted on BBC Micros.

Up to a dozen students are accommodated at one time, assimilated into the life of the Bakers and their children, even to the extent of taking their main meals with the family. They are taught in groups of three or four. "From my own experience I know one-to-one is too intensive", says Duncan Baker, "and big classes lack individual attention".

Two BBC Micros are installed in the Centre's largest tutorial room, each with a 100k single disc drive and monitor. "Our software is very largely Mr T and *The Micro User* educational material, with the vocabularies altered where possible for foreign learner use", says Duncan.

"Some of the material is not directly educational, but we use it for relaxation and light relief from studies. Both students' micros are also fixed up with sideways ram capsules. I use these to run some simulated rom software, and I'm trying to adapt some of our programs to run with Superior Software's Speech to help one of our students who is blind".

The office BBC Micro is used almost exclusively for word processing and communications.

With the help of an Epson and Fontwise, the Bakers produced "quite acceptable" camera-ready proofs for their prospectus and various other bits of copy. "It has saved us a good deal on printing bills and some degree of effort in proofreading", says Duncan.

"We have sent out more than 1,400 copies of our brochure, each one with an individual letter, thanks to Wordwise Plus, Wordaid and our Juki.

"I have now stored set Wordwise forms for invoices, replies to enquiries, receipts and so on, and this saves me a lot of time and effort".

The other main use of the machine is communications. The Centre subscribes to Prestel Education Service, advertising on Page 21171, and also uses the system often for travel information, educational software, "and generally keeping in touch with the world of education", adds Duncan.

"But our main asset has to be MicroLink. Our students and potential students come almost entirely

→

From Page 83

from the world's business communities and from government service, so we have to be able to communicate and receive messages quickly, reliably and accurately.

"Initially we took out a subscription to MicroLink for its telex facilities – telex being, from my experience, a far more reliable means of communicating between countries than mail or even telephone.

"The bonus with MicroLink is the electronic mail and bulletin board facilities. Through these we have made more friends, established new overseas contacts, and received more enquiries than any other means – direct mail and print advertising included. This was not foreseen, but may well make a big difference to the amount of business we shall do in our first year or so".

Duncan and Rita bought their first BBC Micro for entertainment and to fill gaps in their children's education while on overseas postings.

"Had I known we would eventually use the machine for business I would have bought larger capacity drives", Duncan says. However, I do find the 100k disc capacity useful in some ways, in that I rarely fill the catalog and I can keep separate discs for separate subjects without feeling I'm wasting capacity.

"The twin drives I regard as virtually essential and I continue to be glad I stood up to the salesman who tried to convince me to buy a single double-sided 80 track drive instead.

"I feel it is very valuable to be able to keep my utilities disc in drive 0. This contains various function key parameters for my favourite Wordwise Plus embedded commands and standard page set-ups for letterheads, invoices and so on. Drive 1 is then kept clear for whichever working disc I am on. I find this works well and also shares the load better between the two drives – I don't want one to wear out before the other".

The BBC Micro-based system now used in the Centre's office is basically the same as the one the Bakers bought for their children. They have added an ATPL board with 16k of sideways ram, a shadow ram board – virtually essential with the amount of word processing done – and a second printer with NLQ facility.


Other additions are a screen dump for Prestel, Disc Doctor and Caretaker for onboard formatting, single key and squashing facilities, and Rom Master "for seeing what's going on inside the micro and to give our student records password security".

There's also Commstar, which Duncan says does everything he needs on Prestel and, with Mini Office II, covers his bulletin board and communications needs. Wordaid is used for mailshotting the Wordwise Plus output, and Spellcheck for proofing.

The Centre also uses teletext, mainly for travel and TV information.

Duncan has a green screen for word processing and a colour monitor "for Prestel's pretty pictures and for student programs".

The original BBC Micro itself and the disc drives



Abdullah Al-Shahari from Yemen working in his study at the Centre

removed from their shells are now in a Viglen PC lookalike. "If any one product has to be regarded as my best buy this is it", enthuses Duncan. "I think being able to hold a light, liberated keyboard on my lap and sit at a comfortable distance from the screen is essential.

"The unit also allows me to slide back to the desk where I do the accounts and still use the same computer. Think of the money I've saved!"

A WS2000 modem serves comms requirements, while the original Epson – replaced by a Juki 5510 for sheet fed NLQ mailshotting – now handles program listings, telex and Email printouts, and envelope labels.

A "very efficient" switch allows Duncan to change printers without problem – and without dread memories of recorder leads. "In fact I don't have to go under or behind the computer at all except when software authors force a switch-off before Wordwise Plus will work again", says Duncan.

For the future, he plans to buy a 1200 baud duplex modem – "just to save time on-line" – and maybe a hard disc for the office. "Our accounts are still done manually – there just isn't any BBC Micro time left to do it all", says Duncan. "So when we have sorted ourselves out a bit more I shall start thinking about computerising them".

A Master for the office? Maybe, he says, and perhaps another one or two BBC Micros for the students "Though we'll have to see how next year's bookings look first". The Centre will almost certainly have a network for the students if more BBC Micros are obtained.

After all their initial hard work during this year and the latter part of 1985, Duncan and Rita now have an established and growing business on target for its break even point.

"More by luck than by judgement – and helped a good deal by *The Micro User* – we have managed to avoid making any expensive mistakes", says Duncan.

"But we shall need some expert advice before we go any further.

"However, I'm convinced we would not have been able to set up such a well-equipped Centre and offer such an individual and comprehensive approach to English language teaching had it not been for our BBC Micros, both in the office and in the tutorial rooms".

MicroLink
in association with
TELECOM GOLD

NEWSBEAT

Books and bookmen

BUYING and selling rare and out-of-print books isn't as fusty a business as it may sound – even for a firm founded when Robert Peel was prime minister.

Antiquarian bookseller Wheldon & Wesley has been trading since 1843, but is bang up-to-date when it comes to communications thanks to MicroLink.

Speed is important in locating rare publications, then buying and selling them at the right price.

And as 60 per cent of the firm's business involves dealing with people in countries all over the world, MicroLink's telex and other messaging services are proving invaluable.

"Although we specialise in natural history, we're very willing to search for any rare books other people are looking for", says director Tony Swann, a member of the family which has been running Wheldon & Wesley since the 1920s.

"And where great distances are involved, MicroLink is often the fastest and most economical means of doing the job.

"Our clients are universities, museums and libraries, private collectors and fellow dealers – and two-thirds of them are abroad.

"At present most of our business with the United States is done by telephone, but we should soon have an efficient transatlantic mailbox system via MicroLink – and perhaps even a special interest database as well".

Best foot forward

STOCK control procedures at a fast-expanding chain of footwear specialists in London used to be rather a marathon slog.

Now the system is more like a sprint – thanks to MicroLink.

Cobra Sports Shoe Shops has blossomed into an eight-store chain in as many years, selling to top international athletes as well as spare-time joggers.

It all adds up to a mountain of shoe leather – or rather spikes and rubber.

Before MicroLink, daily stock reports were written by hand and the sheets sent by next available delivery van to the firm's head office, sometimes two or three days later.

Now the information from each shop goes directly every night onto Cobra's MicroLink mailbox for retrieval next morning and processing on the firm's IBM computer. Up-to-the-minute stock control has been achieved without great expense – instead of a micro each store uses a Psion Organiser.

"This gives us simple one-button operations that are easy for the staff to pick up", says Cobra systems manager Daniel Brown.

"And I've successfully written an autodial file-sending procedure in OPL on my Psion which speeds up the process even more".

Link grows

MICROLINK subscribers can now communicate directly with two more countries through the world's biggest electronic mail and messaging network Dialcom.

Italy and Japan have joined the system, bringing to 14 the number of countries offering this global service.

More free software

MICROLINK'S telesoftware library is being reorganised and considerably extended.

The programs run on five types of computer – BBC Micro, Apple, Electron, Atari and Amstrad.

There are now nearly 150 free programs in the MicroLink telesoftware library and this number will be substantially increased during the next few months.

Going with a bang

HAVING survived his childhood hobby of making fireworks – "somewhat luckily", he says – Jon Culverhouse went on to other things.

But he never lost his fascination for colourful explosions and now, with a little help from MicroLink, he's creating them all over the country.

As boss of Fantastic Fireworks, Jon was responsible for something like 65,000 "bangs" around Britain this November 5th.

For the past two years Jon has been selling fireworks imported from places like Germany, Spain – and even China where pyrotechnics originated.

He keeps in touch with his suppliers via MicroLink's telex facilities and uses electronic mail to publicise his services.

These include packaged displays costing from £80 for a family bonfire party to £5,000 for, say, a town's Royal Wedding celebrations.

"I've found that sending information via MicroLink is the most effective method of getting publicity for my company in the media", says Jon.

"My displays have already been featured on Saturday Superstore and Pebble Mill at One as a result".

Fly me...

THE Official Airline Guide database available on MicroLink includes information about nearly 30,000 hotels as well as flight and fare details for more than 750 airlines.

The coverage spans 17,000 hotels and motels in North America, more than 9,000 in Europe and more than 2,500 in the Far East and Pacific area.

Details displayed include the full postal address, telephone and telex numbers, and the range of rates, plus an official classification in most cases.

YOUR chance to join MicroLink – Page 91

p&h electronics Ltd

5 THE PARADE · YATELEY
HANTS
TEL: 0252 877222

24 HR SALES LINE
0252 878107

22/24 GUILDFORD ROAD
BAGSHOT · SURREY
TEL: BAGSHOT 0276 74533

MICRO CENTRES TELEPHONE OR VISIT

ACORN COMPUTER

ALL PRICES INCLUDE VAT PRICES ARE SUBJECT TO CHANGE WITHOUT NOTICE

FAST PHONE/MAIL SERVICE – 48 HOUR DESPATCH ON ITEMS IN STOCK
SUPPLIERS TO SCIENTIFIC AND EDUCATION AUTHORITIES

ACORN

Master 128K	£475.00
Master Turbo Upgrade	£120.00
Master 512 Upgrade	£375.00
Master Econet Terminal	£375.00
Master Econet Module	£47.00
Master Compact Basic	£389.00
Master Compact + Green Monitor	£455.00
Master Compact + Colour Monitor	£575.00
Eprom Cartridge	£14.95
64K Upgrade Kit for BBC B Plus	£39.95
Z80 2nd Processor + Business Software	£380.00
6502 2nd Processor	£187.00
Electron Plus 1	£59.00
1770 Upgrade	£46.00
ADFS ROM	£28.00

MONITORS

MONO

Philips BM7502 Green High Res	£79.00
Philips BM7522 Amber High Res	£85.00
Philips BM7542 Paper White High Res	£85.00
Philips BM7542 White High Res	£93.00
Taxan KX1202 Green High Res	£120.00
Taxan KX1203 Amber High Res	£120.00

COLOUR

Microvitec 1451 Medium Res	£285.00
Philips 8501 RGB Std Res + Sound	£199.00
Philips 8533 RGB Med Res + Comp Vid + Sound. Also switches to Mono	£285.00
Philips CM8500 Comp Vid Med Res	£199.00
Taxan Supervision III Ultra High Res	£365.00

TELEVISION/MONITORS

Ferguson MC05 14in CTV + RGB (new)	£215.00
Philips 1114 14in CTV + RGB (new Super!)	£190.00
BBC – Monitor leads to suit	**£4.50**

PRINTERS

DOT MATRIX

Tally MT80 + 100cps	£195.00
Tally MT85 with NLQ	£375.00
Epson LX86 with NLQ (replaces LX80) 120cps	£269.00
Epson LX86/LX80 Tractor Unit	£22.00
Epson LX86/LX80 Sheet Feeder	£55.00
Epson FX85	£365.00
Kaga Taxan 810 with NLQ	£269.00
Kaga Taxan 910 with NLQ	£449.00

DAISYWHEEL

Juki 6100	£359.00
Juki 6000	£199.00
BBC – Printer leads to suit	**£12.00**

DISK DRIVES

CUMANA

CSX100 100k S/S 40T	£105.00
CS100 100K S/S 40T with P.S.	£135.00
CSX400 400k D/S 40/80T	£145.00
CS400 400k D/S 40/80T with P.S.	£170.00
CD800S Dual 400k with P.S.	£315.00
Opus Challenger	£245.00
Pace PSD1 100K S/S 40T	£105.00
Pace PSD3 400K D/S 40/80T	£135.00
Pace PDD3 Dual 400K	£259.00
Pace PDD3 Dual 400K with PS	£289.00

ACCESSORIES

Data Recorder	£29.00
Data Recorder – BBC Lead	£4.00
Full Proportional Joy Stick	£12.50
Full Proportional Joy Stick Pair	£20.00
Voltmace 14b Joystick	£14.50
AMX Mouse – with Super Art	£75.00
AMX Utilities Software	£13.50
AMX Desk	£22.00
AMX Paintbox	£13.50
AMX 3D Zicon	£22.00
AMX Page Maker	£47.00
AMX Data Base	£22.00
AMX Xam	£22.00
AMX Super Art	£47.00
Modem Nightingale with Commstar	£149.00
Modem Auto Answer Board + Software	£75.00
Sideways ROM Board (ATPL)	£43.00
Computer Desk Double Width	£69.00
Disc Storage Box (70)	£16.95
Disc Storage Box (100)	£19.95
5¼in Discs 10 in Library Case DS/DD	£18.00
TV Aerial/Computer Switch	£2.50
BBC Key Function Key Mask	£2.50
Giant Reference Card for BBC	£3.00
Computer Covers Soft	£5.50
Computer Covers Hard	£10.00
Printer Covers – State Type	£6.50
Disc Drive Covers – State Type	£5.00
Analogue Mouse (by NIDD)	£33.00
Digital Mouse (by NIDD)	£33.00

ACORNSOFT-VIEW

View – Wordprocessor ROM	£49.00
View 3 inc. Printer Drivers	£79.00
Hi-View – For 2nd 6502 Processor	£50.00
Viewsheet – Spreadsheet ROM	£50.00
View Index Disc	£15.00
View Store – Database ROM	£49.00
Viewspell	£35.00
Viewplot to be released	£35.00
Printer Driver Generator – Cassette	£10.00
Printer Driver Generator – Disc	£11.50

ACORNSOFT BOOKS

Creative Graphics	£7.50
Graphs and Charts	£7.50
Lisp Manual	£7.50
Forth manual	£7.50
Comal Manual	£11.50
BCPL Manual	£15.00
ISO Pascal Manual	£15.00
View Guide	£10.00
Viewsheet Guide	£10.00
Viewstore Manual	£10.00
Master Reference Manual Part 1	£14.95
Master Reference Manual Part 2	£14.95
Master Advanced Reference Manual	£19.95
Logo Manual	£7.50
Microtext Manual	£10.00

ACORNSOFT

Forth ROM	£47.00
Lisp ROM	£47.00
ISO - Pascal ROM	£62.00
BCPL ROM	£95.00
Comal ROM	£47.00
Logo ROM	£65.00
Turtle Graphics Cassette	£16.50
Graphics Extension ROM	£28.00
Graphics Extension ROM for B Plus	£28.00
Microtext Cassette	£47.00
Microtext Disc	£55.00
Creative Graphics Cassette	£9.50
Graphs and Charts Cassette	£9.50
French for Electron Also	£14.50
Italian for Electron Also	£14.50
Spanish for Electron also	£14.50
German for Electron also	£14.50
Basic Editor	£28.00
Database Disc	£16.50
Micro Prolog	£76.00
ISO Pascal Stand Alone Generator	£34.00

ROMS/UTILITIES

Wordwise Plus	Rom	£46.00
Intersheet	Rom	£50.00
Interword		£49.00
Interbase to be released		POA
Interchart	Rom	£34.00
Disc Doctor	Rom	£26.00
Printmaster	Rom	£26.00
Graphics	Rom	£26.00
Toolkit Plus	Rom	£36.00
Exmon II	Rom	£30.00
Murom (Music)	Rom	£28.00
Help II	Rom	£29.00
Sleuth	Rom	£28.00
Spellcheck III (View + W/W)	Rom	£33.00
Hershey Characters	Disc	£19.00
Hershey Characters	Cassette	£11.00
Logo (LCSI)	Rom	£59.00
Replica III 40/80	Disc	£14.00
Beta Base 40/80	Disc	£23.00
Vine Replay (State Disc I/F)	Rom	£33.00
Vine Tape to Disc	Rom	£18.00
Island Logic Music	Cassette 1	£13.50
Island Logic Music	Cassette 2	£13.50
Island Logic Music	Disc	£27.00
Wordease	2 Roms	£27.00
Studio Eight	Cass £15.50 Disc	£20.00
Icon Master	Rom	£31.00
Romit	Rom	£32.00
Dumpmaster II	Rom	£29.00
Fleet Street Editor	Disc	£38.00
Spelling Checker (Comp Con)	Rom	POA

TOP GAMES

Doctor Who Cass+ROM	£17.00
Doctor Who Disc+ROM	£18.00
Elite (Master/BBC Disc soon)	Cas. £13.50
Revs	Cas. £13.50 Disc £16.50
Revs II	(4 Track) Disc £11.50
Aviator	Cas £13.50 Disc £16.50
Castle Quest	Cas. £11.00 Disc £13.00
Scrabble	Cas. £12.50 Disc £17.00
Whiteknight 12 Chess	Cas. £9.50 Disc £18.50
Snooker	Cas. £9.50 Disc £11.00
Repton II	Cas. £8.50 Disc £10.50
Monopoly	Cas. £12.50 Disc £17.00
Red Arrows	Cas. £8.00 Disc £10.50
Jump Jet	Cas. £9.00 Disc £10.50
Lord of the Rings Part I	£14.50
Citadel	Cas. £8.50 Disc £10.50
Exploding Fist	Cas. £8.50 Disc £13.50
Phantom Combat	Cas. £9.50 Disc £14.50
Strike Force Harrier	Cas. £9.50 Disc £14.50
Nightshade	Cas. £9.50
Karate Combat	Cas. £8.50 Disc £10.50
Yie Ar Kung Fu	Cas. £8.50 Disc £10.50
Hypersports	Disc £11.50
Commando	Cas. £9.50 Disc £12.50
Phantom Combat	(for 2B's) Disc £19.00
Treasure Hunt	Cas. £9.50
Rebel Plant	Cas. £9.50
Winter Olympics	Cas. £6.50
Ian Botham's Test Match	Cas. £7.50
Bounty Bob Strikes Back	Cas. £9.50
Jet Pack	Cas. £9.50
Power Play	Disc £14.50
Moon Cresta	Disc £9.50
Thrust	Cas. £9.50 Disc £11.50
Waterloo	Cas. £9.50 Disc £12.00
Ian Botham Test Cricket	Cas. £7.50 Disc £11.00
Trivial Pursuit	Cas. £13.50 Disc £18.00
Galaforce	Cas. £7.50 Disc £11.00
Airwolf	Cas. £9.50 Disc £14.00
Psyclastria	Cas. £7.50 Disc £11.00
Mikie	Cas. £6.50
Bombjack	Cas. £9.50
Cosmic Battlestations	Cas. £9.50
Raid Over Moscow	Cas. £9.50
Spyhunter	Cas. £9.50
Commonwealth Games	Cas. £7.50
US Drag Racing	Cas. £6.50
Jet Set Willy	Cas. £7.50
Beach Head	Cas. £9.50
Dambusters	Cas. £9.50
Southern Belle	Cas. £7.50
Bruce Lee	Disc £14.95

COMPUTER BOOKS

BBC User Guide Binder	£3.95
Advanced User Guide	£12.95
Advanced User Guide Binder	£3.95
Advanced Basic ROM BBC	£7.95
Advanced Graphics with the BBC	£9.95
Applied Assembly Language BBC	£9.95
30 Hour Basic	£6.95
Basic ROM User Guide	£11.95
BBC Micro Disc Companion	£8.95
Disc Programming Technics for BBC	£7.95
The BBC Micro ROM Book	£10.95
6502 Applications	£13.95
6502 Assembly Language Programming	£19.95
6502 Assembly Language Subroutines	£19.95
Word Star and CPM Made Easy	£7.45
Word Star Made Easy	£16.95
Introduction CPM Z80 2nd Proc (new)	£9.95
Wordwise Plus	£9.95
Making Most of your BBC Disc System	£5.95
Assembly Language Programming on BBC	£8.95
Advanced Disc User Guide	£14.95
Advanced Machine Code Tech for BBC	£7.95
Art of Micro Graphics BBC/Electron	£14.95
BBC Micro Advanced Programming	£9.95
Beginners Guide Word Processing on BBC	£7.95
Beyond Basic	£7.25
Mastering Assembly Code on BBC (BBC Pub)	£8.95
Mastering Music on BBC (BBC Pub)	£6.95
Mastering the Disc on BBC (BBC Pub)	£7.95
Mathematical Prog in BBC Basic	£7.95
Structured Basic	£7.25
The Super Users BBC Micro Book	£10.95
6502 Reference Guide	£9.95
Programming the 6502	£16.95
The BBC Master 128 for High Flyers (new)	£10.95

SPECIAL
Convert your monitor to a TV with the new Philips Tuner unit.
OUR PRICE ONLY **£65.00**

MAIL ORDER COUPON

P&H ELECTRONICS LIMITED
22/24 GUILDFORD ROAD · BAGSHOT · SURREY GU19 5JN

Please send me: (or order by letter)

1 _____ at £_____ P&P_____

2 _____ at £_____ P&P_____

3 _____ at £_____ P&P_____

I enclose cheque/PO for £_____

Or please debit my Access/Barclaycard/Visa* *(delete as applicable)*

Card Number _____ Expiry Date_____ Telephone _____

FAST VAT FREE EXPORT SERVICE ON ORDERS OVER £15 NETT
PLEASE ALLOW FOR CARRIAGE COSTS OR REQUEST CARRIAGE QUOTATION

CARRIAGE COSTS – Micros – Monitors – Disc Drives – Printers – Desks – 2nd Processors: £7
Cassette Decks: £3. – Books: £1 per book – Software – Leads £1. per item.


BARCLAYCARD VISA

ACCESS/BARCLAYCARD/VISA ORDERS WELCOME
CREDIT FACILITIES Instant credit up to £1,000, deposit 10%
PLEASE STATE; DISK FORMAT 40 OR 80 TRACK

Name _____

Address _____

MU 12 86



What kind of user are YOU?

JO STORK takes a light-hearted look at stereotypes – and draws some useful conclusions

THE other day I was asked to give a lecture to the directors and senior management of a company with approximately £60 million turnover. Because of the nature of its business it has an unusually large and diverse number of computers. The subject of the lecture itself does not concern us here, nor does the equipment the company uses.

What is of interest is that as usual I asked for a brief background on my audience. The actual question I put to the seminar organiser was, "What sort of users are they?"

Perhaps I had not made my meaning clear since instead of the two line thumb nail sketches I was expecting, (job title, age, computer experience), on each of the 22 members in my audience I received virtually complete curriculum vitae.

These set me thinking, because there were five clearly defined groups with a couple of minor sub-classifications, all of which would have quite differing requirements.

The more I thought about my audience, the more I realised that the same classifications are universal for any computer users. This has nothing whatsoever to do with experience or knowledge, but is solely down to the way a person operates.

Readers of *The Micro User* would therefore be well advised to identify the group they belong in, for the kind of user they are will govern their style of working and hence the efficiency or otherwise of their eventual system.

The classifications below are in no particular order and the names I have given them are my own.

The Fidgets

These are the sort of people who are totally incapable of finishing a system. Alternatively, if they have a ready made system obtained from some other source, they are equally incapable of leaving well alone. Examine their disc files and you will find a mass of half-finished routines and modules. The reason for this style of working is quite simple. They constantly have ideas of the, "Wouldn't it be nice if . . ." variety and immediately start to work on them. It is of no importance to them if the previous piece of work is not yet finished.


These people are potentially extremely dangerous since they are frequently highly capable and knowledgable in computing matters. Consequently, less aware persons are very likely to ask them to produce systems. The outcome is that when the deadline for the system has long since passed and the requestor is jumping up and down like a demented pogo-stick in a desperate attempt to get even part of it delivered, Fidgets will stay up all night to produce a half-baked pilot version without documentation.

Since the system is clearly unsatisfactory they then proceed to adjust, tune, enhance and generally titivate it. Even so only a very small number of the modifications required to make the system meet its original specification are ever produced. Nevertheless by then the coding has taken on the appearance of the classic rat's nest.

Newcomers can also become Fidgets, since as they learn more they discover better ways of carrying out the same task. This tempts them to adopt the newly acquired knowledge. During this early stage of

→

ADVANCED TECHNOLOGICAL RESEARCH



Data Protection Act

Have you Registered that Your Data, is Secure in Accordance with 'the Data Protection Act 1986'? Whether YES or No, You need Lock-Tight from ATR. If any of Your Data Escapes, You can get in Big Trouble with the Law. So Lock-Up Your Data NOW with Lock-Tight from ATR Before it Gets Out. You can be Heavily Fined if Data is Insecure.

LOCK-TIGHT the BBC CYPHER CONTROL SYSTEM

LOCK-TIGHT is a 'Do-it Once' security system. Lock-Tight provides a 'Locked Area' around Data (or Software). Once the simple supervisor Menu Set-Up has been completed, only Users with Authority have Access, and then only to the options you have given them. If No Valid Password is used No Access is Given, and the Computer is Completely Disabled.

***** The MAIN FEATURES of LOCK-TIGHT *****

(1) One Pass Encoding of Data for High Speed.
(2) Menu Driven for both Supervisor and Users.
(3) Master Key-Code for Supervisor System Control.
(4) User Security Via User Name and Password.
(5) User Remembers Only One Password.
(6) Users Password Determines their Options.
(7) Works with Single or Double Density DFS Interfaces.
(8) Encoded Disk Copy Routine for Fast Disk Backup.
(9) Protects Data, Floppy/Hard Disks and Networks.
(10) Disk Sector Editors Will Only Show You Garbage.

LOCK-TIGHT is available on DISK or ROM

Product Code		DISK	ROM
(LT1)	Lock-Tight Version 1	£39.95	£44.95

All Prices Excl VAT, but include Postage and Package

Site, Network and Corporate Licences are Available on Request.
Dealer and Trade Inquiries Welcomed, normal discounts given.

ADVANCED TECHNOLOGICAL RESEARCH Telephone 01-206 1529
Telex 8953931

508 KINGSBURY ROAD, KINGSBURY, LONDON NW9 9HE, ENGLAND

Supply LOCK-TIGHT. Qty.....

Name _____ Tel _____

Please Tick Box	DISK	ROM
LT1 – Version 1	☐	☐

Address _____

I Enclose Cash / Cheque (payable to ATR) £ _____ which includes 15% VAT

SNOWFAX Ltd trading as ADVANCED TECHNOLOGICAL RESEARCH (C) 1986

From Page 87

computing development they are naturally forever discovering newer and better ways of performing some task with the consequence that they do not complete any.

The Magnates

Repeatedly, when I was still only 30 years old the Magnates would argue along the lines of, "How can a young whipper-snapper like you know?" or alternatively, "I was doing... when you were still chewing rusks." Now that I am considerably older they are still making my life difficult. The reason is that these types are traditionally workaholic self-made men who developed their organisations on their own.

The problem is that they are now almost incapable of taking any advice, since their maxim is, "No-one can tell us anything new about our business." If they believe they need a Gizzmo 256k then it is no use suggesting they require a Wonderbyte 512. If you tell them they should not put their payroll on to a computer and they think otherwise, be prepared for them to dump you for someone who will install payroll on the Gizzmo.

In fairness to them, if you do get the Magnates to agree to something, they throw the full force of their considerable personality behind the project and drive it for you. When this happens be prepared to rein in their gung-ho enthusiasm. Before you can say, "Bit!", they will be asking you if you can do this, add that or produce the other. Because of the personality you are matched against it is not easy to turn down the requests, since the Magnates will still expect the original time-scale to be adhered to. If you agree to all their requests and do not adjust the project time-table, you are in grave danger of being forced to become a Fidget.

Nonetheless if you can stand up to the bluster and come to some working relationship, working with a Magnate can be a highly satisfying experience resulting in rapid completion of many fine systems.

The Neurotics

These know that the time is long gone since they needed to computerise their organisation, but having heard all the war stories of the saloon bar experts, they are fearful as to whether they will ever handle the silicon monster or cope with the changes it will bring. They keep putting off the evil day, rationalising that they need to study further what systems are available. Only if the present system is dead on its feet will they actually take the plunge.

They share something with the Magnates, since they also resent the "young upstart" they have to work with. This time it is not a superiority complex but fear that their position will be undermined. They worry that their technological inadequacies will become widely known within the organisation and jeopardise any further advancement within it.

Neurotics frequently appear to be interested and knowledgeable in data processing, which can prove highly misleading to the unwary. Look in their desks and you will find a large number of system proposals, advertising literature, brochures from exhibitions and the like plus in many cases their reports on the same. The latter all give "valid reasons" why the organisation they work for is unique and nothing suitable and cost-effective is available on the market.

Neurotics are always interesting people to work with. They usually have all the capabilities needed and only lack the confidence to use them. I have met people who can calculate the stresses on a major bridge using only a slide-rule and the back of an envelope, but who quail at the thought of using a standard computer program to do the same thing in a tenth of the time. Similarly I have met people who can add lengthy columns of figures with complete accuracy in far less time than an able operator can enter them at a keyboard. They consequently resist on the basis that there is a greater likelihood of data being input incorrectly than there is of their getting the mental arithmetic wrong.

If Neurotics maintain their positions long enough they can become very well informed about all aspects of configuration, specification, analysis and design. Studying all the tenders and writing the reports gives them a feeling of great confidence and they are therefore often regarded as the fount of all knowledge by their peers. What is more, they can claim in absolute truth that they have never made a mistake. How could they? After all they never took a decision.

The Technocrats

These types are the virtual opposite of the Neurotics. Their attitude is, "If it's new it must be good." They are first cousins to the Collectors, whose principle is, "If it's new we must have it", and half-brothers of the Tsars whose maxim is "If it's bigger it must be better."

The problem they cause is that all three are for ever throwing out the commercial baby with the cybernetic bathwater. No sooner is a system working properly, the operators and staff familiar with its functions and the results starting to pour from it than they get restless, believing it must be out of date and need replacing. If a system has a life-expectancy of five years, they are looking to change it within two.

To the battle-cry of "We can't let the competition get the jump on us!", all three disrupt the organisation's work with more surveys, feasibility studies, progress meetings and training courses. They too acquire drawers full of brochures, reports, course documentation and so on, but unlike the Neurotics, installation does occur. The clue to their thinking is plain to see on top of their desks. They were the first members of their Chamber of Commerce to use a mouse, Email, have hard discs, fit all the go-faster chippery and use multi-colour high-resolution graphics. Alongside the terminal on their desk you will also find the most modern telephone handset, op-art desk ornamentation and other executive toys.

Technocrats do have a one massive virtue. If you are a youngster starting in the computing industry, then try and find yourself a manager who is in this group. You may well feel harrassed by the constant chopping and changing but you will learn faster than in any other

→

From Page 89

environment. Technocrats will take you to the forefront of computing and make sure you stay there. You will gain skills at a rate which will accelerate your career in fine style.

The Accountants

Do not confuse these with the Neurotics. They are unnaturally reluctant to take decisions because they will not make any move until every single cost and benefit has been calculated to a considerable number of decimal places. As the proposals arrive, every penny of the charges is analysed and each claimed benefit is considered. Queries and replies flow back and forth as the Accountants endeavour to determine if the magic cost benefit ratio of 1:1.5 has been reached.

At least a decision can eventually be made. If, after studying the mathematical entrails, the figures read right then the proposal is usually accepted. Unfortunately whether the system even works is a secondary factor, always assuming it is even considered. The omissions in many proposals are as informative as the inclusions. The Accountants more than any others are likely to have overlooked something fundamental such as whether the double micro system chosen can share files.

The money aspects of a system are naturally vital, but many of the factors are hard to quantify, such as the benefit gained from sending invoices out sooner versus the cost of decreased staff efficiency during the period of familiarisation. Nevertheless the Accountants will try. At the same time, if there is an element of the wheeler-dealer in the user, they will start to haggle over discounts and so forth. This is marvellous in principle until another basic issue such as user-friendliness is ignored. The Accountants show little interest in topics such as these, since they are the last to sully their lily-white hands by touching a keyboard, flowcharting template or coding sheet.

A further by-product of this thinking is that almost invariably the information which the chosen system presents will be financial. They find it very easy to overlook the possibilities of using others for such things as Computer Aided Design (CAD). I well remember a client in light engineering who called me in after the retirement of one of this group. The financial system would have done credit to a clearing bank, but the production and design side of the business was being handled with techniques which would have seemed antique to Noah building his ark.

Now that we have looked at these stereotypes, I hope you will recognise yourself in at least one of them. I have purposely chosen extremes in my descriptions, but there should have been sufficient indication for you to know what your attitude to data processing is. I stress that I fully accept that it is impossible to change your personality once past a certain age. Consequently I hope that what follows will be regarded as harnessing the advantages which your stereotype brings to computing, rather than trying to make you act in a manner wholly foreign to your natural style.

To the Fidgets, might I suggest that they regard the project time-table as the be-all and end-all of their task. By all means they should use completed and fully tested versions of their half-written modules, if they can be incorporated in the system. Develop more if they need to, since I do not wish to deprive them of all their fun. Nonetheless they should try to integrate all the various bits and pieces into just one worthwhile system. As a guideline I would suggest that no further un-related activities be entered into once 50 per cent of the project time-scale has passed.

The Magnates would do well to think about the days when they were new at their trade. They did not get where they were without seeking and using advice in their early days. If you are the Magnate type then consider the following. Just because you are a master of one skill it is unrealistic to assume that you are as expert in others, such as data processing. Remember that even the experts are still learning about a fast moving field therefore set your many talents to searching out the best advice you can get, in the same way as you did in the past.

Of all five groups, the Neurotics have the greatest internal conflicts to overcome. An organisation needs stability and direction, therefore sometimes the best decision is to take no decision at all. Nevertheless when acting becomes inevitable, delay is totally counter-productive. If you believe that the task is beyond you then give up responsibility for it and hand it over to someone who can handle it. If your organisation is large enough, what is so wrong with passing it to another member of staff? As a manager I was far happier to have juniors express their doubts rather than have them keep their concerns to themselves and then produce a pig's ear. If you have insufficient staff then give the problem to someone who can provide you with a turnkey system.


To the Technocrats the problem is an easy one. Just start working out a Cost : Benefit ratio of what you plan to do. If you discover it does not come to 1:1.5 and can not control your excessive zeal, then you are a lost cause. If the ratio is on the right side, be happy. Enjoy life, safe in the knowledge that you can purchase your new toy and still show a profit.

Finally I come to the Accountants. If you are one of these, then might I suggest that you try and split your time into three equal portions. The two new ones for you are analysing the system design and assessing new uses to which computer equipment may be put. When you get twitchy about carrying out such excessively radical activities, you can always return to your beloved costings.

I may have taken a light-hearted look at your working style, but it should now be obvious that each type has much to offer the other. If only it were possible, I would like nothing more than to operate on Mondays as a Fidget, on Tuesday as a Magnate and so on through the week finishing on Friday as an Accountant – working in this fashion I would reap the benefits of each.

If you do not recognise yourself in any of the above, then please write and tell me how such perfection was achieved. With such a paragon for competition I will concede you are my superior, bow down before such a master and happily hand over this column to you. ■

Use your BBC Micro to talk to the world!



MicroLink

in association with TELECOM GOLD

Join MicroLink – and use your micro to send and receive electronic mail, telexes, telemessages, go teleshopping, book theatre and rail tickets, read the latest micro news, form your own exclusive closed user group ... even go via satellite to the USA to chat in real time to other users with similar interests as yourself. And it's all as easy as making a phone call!
All you need to access MicroLink with your micro is a modem, appropriate software and a telephone.

How much does it cost?

● Standing charge of £3 a month. ● Connect charges of 3.5p a minute (between 7pm and 8am weekdays and all Saturday and Sunday), or 11p a minute during office hours. ● Cost of local phone call (London area) or cheap-rate PSS (extra 25p a minute).

These are basic charges. Most MicroLink facilities are free, including sending messages to other people on the system. Extras are:

Telex: 5.5p per 100 characters (UK), 11p per 100 (Europe), 18p per 100 (N. America), £1.25 per 400 (rest of the world), £2.75p per 400 (ships at sea). Plus a once-only telex registration fee of £10.

Telemessages: £1.45 for up to 350 words. An illustrated greetings card (for weddings, birthdays, etc) costs an extra 75p. Delivered anywhere in Britain first post the following day.

Overseas mail: 20p (Germany, Denmark), 30p (USA, Canada, Australia, Singapore, Hong Kong, Israel) for first 2,048 characters. For additional 1,024 characters, 10p and 15p.

To join MicroLink simply fill in and return the form below. Within days you will receive your personal mailbox number and password, an easy-to-understand Quick Guide to MicroLink, and the phone number of the Helpline where you can get additional assistance should you require it.

Your personal passport to the wide world of communications

Application Form

Name
Position
Company
Address
Postcode Daytime tel:

Commencement of Service
Please indicate month of commencement 19
Allow 7 days for validation of mailbox

Date of first payment to be on 15th of month following commencement. Please complete billing authorisation form A, B or C.

* *Telecom Gold is a trademark of British Telecommunications plc.*

I/We hereby apply to join MicroLink
(✓)☐ I enclose my cheque for £5 payable to Database Publications as registration fee to MicroLink.
(✓)☐ I also wish to use Telex. I authorise you to charge an additional £10 to my initial bill for validation.
☐ I confirm that I am over 18 years of age.
☐ I confirm that I accept the terms and conditions for the time being in force, copies of which are available on request

I intend to use the following computer model _____

Signature _____
Date _____

A. Direct Debiting Instruction *(Enter full postal address of UK Bank Branch) to:*

I/We authorise you until further notice in writing to charge to my/our account with you on or immediately after 15th day of each month unspecified amounts which may be deited thereto at the instance of Database Publications Ltd – MicroLink by Direct Debit. Bills are issued 10 days before debit is processed.

Name of Account to be debited
Account Number Sort Code

B. Please debit my/our Access/Mastercard/Visa/ *American Express No.
**Overseas subscribers only*

I/We authorise you until further notice in writing to charge to my/our account with you on or immediately after 15th day of each month unspecified amounts which may be debited thereto at the instance of Database Publications Ltd – MicroLink. Bills are issued 10 days before charge is applied to your account.

Signature _____ Date

C. Please invoice the company/authority.
(✓)☐ If you select this option, which is ONLY AVAILABLE to government establishments and Public Limited Companies, we will require an OFFICIAL ORDER to accept unspecified amounts.

Send to: **MicroLink, Database Publications, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 5NY.**

FOR OFFICE USE ONLY:
Mailbox assigned _____
Start date _____
Password _____

MU12


CARE ELECTRONICS

CARE ELECTRONICS

OPEN
9am-5pm Mon-Thu
9am-4pm Fri-Sat

800 ST ALBANS ROAD, GARSTON, WATFORD, HERTS. WD2 6NL.
Tel: 0923 672102

See us on Stand 31 at the November Micro User Show



NEW PRODUCT AVAILABLE
MASTER EPROM PROGRAMMER
£57.50C

DOT MATRIX PRINTERS

Kaga Taxan 810 with NLQ	£253.00a
Kaga Taxan 910 with NLQ	£419.75a
Printer Cable (BBC to Centronic) 1mt	£6.90c
Printer Cable (BBC to Centronic) 1.5mt	£8.05c
Ribbon Hi-Sec KP-R	£6.90c
Printer Stand	£16.56d

FLOPPY DISCS

3.5" D/S D/D (each)	£2.76c
3.5" D/S D/D (per 10)	£25.30c
5.25" S/S D/D (per 10)	£12.65c
5.25" D/S D/D (per 10)	£13.80c
5.25" Disc Storage Box Lockable	£11.50c

SEMICONDUCTORS

SN74LS10n	£0.28c
SN74LS123N	£0.92c
SN74LS393N	£1.15c
C'Mos 4013	£0.46c
C'Mos 4020	£0.69c
P8271 Floppy disc controller	£40.25c
Eprom 2764 250n/s 8k	£2.53c
Eprom 27128 250n/s 16k	£3.45c
Acorn DNFS Interface kit	£69.00c

Plus wide range of other Semiconductors.

MONITORS (Price incl lead)

Philips Monitors	
BM7502 Green Hi-Res	£89.70a
BM7522 Amber Hi-Res	£92.00a
CM8533 Colour Med-Res	£289.80a
Hantarex Monitors	
HX-12 Green Hi-Res	£79.50a
CT9000 Colour Med-Res	£199.50a

TV/MONITORS (Price incl lead)

Philips CF1114 14"	£180.55a
Philips CT2016 16"	£276.00a
Philips CT2216 16" Remote	£310.50a

POWER SUPPLIES

For use with disc drives.	
Single BBC Outlet	£28.75b
Dual BBC or D/D Outlets	£29.90b
For use with most peripherals	
Quad BBC Outlets	£36.80b

MASTER SERIES CORNER

CARTRIDGES FOR MASTER SERIES

Coming soon!
Non Volatile Battery backed 32k RAM Cartridge

CARE MASTER ROM EXTENDER:

Designed to enable owners of CARE or Viglen BBC Model B Cartridges. To now use them on the master series micros. The extender is capable of taking one 8k, 16k or 32k Eprom Cartridge.

CARE MASTER ROM CARTRIDGES:

Designed by CARE Electronics to Acorn Specifications. Capable of taking up to two x 16K Eproms, including Interword. The CARE Master Cartridges offer three options for maximum user flexibility.
Option 1: Standard Cartridge with two 28pin I.C. sockets.
Option 2: Single Zif version with one 28pin Zif and one 28pin I.C. sockets.
Option 3: Dual Zif version with two 28pin Zif sockets.

MASTER EPROM PROGRAMMER:

All hardware & software contained within a CARE Master cartridge. Ready to plug into either of your Master ROM slots (no wires, no need to open your Master). Capable of programming 8, 16, 32 and 64k Eproms.
Quality software by MORLEY ELECTRONICS.
Quality hardware by CARE ELECTRONICS.

Master 128k Micro	£460.00a
Reference Manual I	No VAT £15.00c
Reference Manual II	No VAT £15.00c
Master Eprom Programmer (Special offer price)	£57.50c
CARE Master ROM Extender	£9.20c
CARE BBC Model B Cartridge	£2.30c
Acorn Master ROM Cartridge	£14.95c
CARE Master ROM Cartridge	£11.50c
ZIF Socket Versions	
CARE Master ROM Cartridge (1xZif)	£17.25c
CARE Master ROM Cartridge (2xZif)	£21.85c
Master Monitor Stand	£16.56d
Master Monitor Stand with 5.25" Disc Housing	£32.20b
Master Monitor Stand with 3.5" Disc Housing	£32.20b

Wanted for Master Series
Hardware & Software Designs
Please contact above for details.

ACCESS

VISA

RGB CONVERSION

Philips/Pye & Ferguson TX	
Conversion Kit (DIY)	£46.00d
Factory Conversion	£69.00a

CONNECTORS

BBC Power plug 6 way (including crimps)	£0.92c
BBC Power socket 6 way (including crimps)	£00.92c
Card edge 34 way	£2.53c
Centronics 34 way	£4.60c
Disc Drive plug 4 way (including crimps)	£0.82c
Disc Drive socket 4 way (including crimps)	£0.82c
Domino plug 5 way RS423	£0.46c
Domino Socket 5 way RS423	£0.46c
DIN plug 5 way Econet	£0.36c
DIN plug 6 way RGB	£0.36c
DIN socket 6 way RGB	£0.36c
DIN plug 7 way Ferguson/Hitachi	£0.36c
DIP Header IDC plug 28 way	£1.38c
Scart plug (Euro) (including crimps)	£1.38c
Zif Socket 28 way	£5.75c

Plus wide range of IDC and other connectors.

VARIOUS CABLE

6 way screened cable price per metre	£0.69
15 way screened cable	£1.84c
20 way ribbon cable price per metre	£0.69c
26 way ribbon cable price per metre	£0.92c
34 way ribbon cable price per metre	£1.15c

READYMADE LEADS

Centronics to Centronics 1.5 mt	£11.50c
Disc Drive Data (Single) 1.2 mt	£5.75c
Disc Drive Data (Dual) 1.5 mt	£8.05c
Disc Drive Power (Single) 1.2 mt	£3.45c
Disc Drive Power (Dual) 1.5 mt	£4.60c
Phono to BNC	£4.60c
Phono to Phono	£2.99c
Phono to UHF	£2.60
RGB 6-6 pin DIN 1.2 mt	£3.45c
RGB 6-7 pin DIN (Hitachi) 1.2 mt	£4.60c
RGB 6-7 pin DIN (Ferguson) 1.2 mt	£4.60c
RGB 6 pin to SCART (Euro) 1.2 mt	£8.05c
User Port Extension Socket to Plug .5 mt	£9.20c
1MZ Bus Extension Socket to Plug .25 mt	£10.35c

Many other types available please telephone or write for details.

ROMS EXPANSION BBC Model B & B+

BBC Model B & B+
The original and best selling.

Low Profile System	£11.50d
Care BBC Model B Cartridge	£2.30c
Zif Socket Cartridge	£8.05c
Library Rack (Holds 6 Cart)	£1.84c

OTHERS: MORLEY ELECTRONICS PRODUCTS

Teletext Adaptor inc. software on ROM	£99.36d
Teletext Adaptor inc. software on DISC	£98.90d
Eprom Programmer – software on ROM	£29.21d
Eprom Programmer – software on DISC	£28.75d
Eprom Programmer – software on CARTRIDGE	£36.80d

SWITCHING UNITS

BBC Printer 2 to 1 (Inc Lead)	£34.50d
BBC Printer 6 to 1	£80.50d
Centronics 4 to 1	£80.50d
Printer 2 to 2 'CPX2 Fully Buffered'	£57.50b
User Port 2 way & Off Posn (Inc Lead)	£37.95d
User Port 6 way & Off Posn (Inc Lead)	£80.50d
RS423 2 to 1	£23.00d
RS232C 2 to 1 'T' (All lines)	£57.50d
RS232C 4 to 1 (All lines)	£80.50d
RS232C 2 to 2 'X' (8 lines)	£69.00d

SOFTWARE SECTION

The Computer Game.

Trivial Pursuit 5.25" Disc Version	£19.95c
Trivial Pursuit – Cassette Version	£14.95c

* Over 3000 Question of no vital importance!
* No typing is necessary.

Without music, graphics and sound the board game has become the most popular in the world. Now it has them.

MONOPOLY By Leisure	5.25" Disc	£14.95c
SCRABBLE By Genius	5.25" Disc	£14.95c

HOW TO ORDER: All prices inclusive of VAT. By Post. Enclose your cheque/PO made payable to CARE Electronics. Or use your ACCESS/VISA. Please allow 7 days for delivery. Please add carriage.
a = £9.99 b = £5.00 c = £1.00 d = £2.00

Shift and Control on red alert

In Part 8 of his series on spreadsheets NIGEL PETERS continues his exploration of the function keys used in Mini Office II

LAST month we explored some of the red function keys and saw the effect they had on our Mini Office II spreadsheets. This time we'll continue our journey, looking at the results of combining these keys with Shift and Control.

We ignored two of the keys last month, *f4* and *f7*. We'll continue to ignore *f4* for the moment and see what *f7* does, which is to allow you to correct your errors.

Have you ever made a mistake when you've been typing in one of the example spreadsheets? It can be really frustrating when you enter a number in a cell and then realise that you've put it in the wrong one. Of course there's no problem about putting the number in the correct cell but what about the cell where you made the mistake? This probably contained something and owing to your carelessness it's gone, overwritten, lost. It's so frustrating.

Happily it's gone but not forgotten. So long as you haven't made another cell active and entered something, pressing *f7* will bring back the value you've carelessly overwritten. It gives fallible people like you and me a second chance to get things right.

Of course it would be nice to have avoided the mistake in the first place and spreadsheets have an error avoidance method, that of locking cells. To explore this, try entering the spreadsheet shown in Figure I. Cells A1 and B1 are labels, while cells A2 and B2 hold the values 1 and 2 respectively. The rest of column A just increases the value of the cell above by 1, while in column B the previous cell is multiplied by 2.

It's an obvious case for the application of formulae and relative copying. I'll leave you to figure out how to do it and just point out that the whole thing shows the value of the powers of 2 from 1 to 5. (2 to the power 2 is 2*2, 2 to the power 3 is 2*2*2 and so on.)

Once you've got the spreadsheet on your micro, let's have a go at protecting it from accidental damage.

Suppose that you decided that the value 2.00 in cell A3 was so important you didn't want to change it inadvertantly. What you do is to make A3 the active cell and then press the Shift and *f0* keys at the same time. This "locks" cell A3 as is shown by:

```
(LOCKED)
```

appearing in the status area. Now try as you like, you can't enter anything into A3. If you do you just get a rather nasty beep and another message:

```
Locked
```

in case you missed the first one!

```
.......A.......B.......C.......D
1   Power  2 to P
2    1.00    2.00
3    2.00    4.00
4    3.00    8.00
5    4.00   16.00
6    5.00   32.00
7
8
```

Figure I: Entering initial data

Of course, human beings being the fickle brutes that we are, we're bound to change our mind and want to put something in A3 after we've locked it. So we need a way to unlock the cell and this is done by making A3 active and then pressing Control and *f0* simultaneously. We can now enter new data. While it may seem a bit silly to be able to undo our locking so easily, the fact that we have to do it does act as a brake, making sure that we think before we overwrite a cell's contents.

Often we don't just want to protect just one cell, we want to lock a whole column or row of cells. This can be done using two more of the function keys.

Say we wanted to lock column A of our spreadsheet. All we do is move the cursor to any cell in column A and then press Shift + *f1*. The result is that all the cells in that column are locked. You'll see this if you move the cursor up and down the column, the status area solemnly telling you that each cell is locked. If you don't believe it try entering a value into, say, A5 and see what you get for your pains.

Similarly you can lock a whole row. You just make one of the cells in that row active and then press Shift + *f2*. The result is that all the cells in the row containing the active cell are locked.

And when you want to change your mind and alter cells in a locked row or column, you're allowed to unlock them. Pressing Control + *f1* lets you tamper with a previously-locked column, Control + *f2* with a row.

Now we come to the *f4* key we ignored earlier. By now you're probably used to the ripple effect you get when you change a number in a cell. Suppose you changed B2 in our spreadsheet to 3 – assuming that it's

→

MANCOMP LTD

(Dept MU12) PRINTWORKS LANE, LEVENSHULME, MANCHESTER M19 3JP.
Tel 061-224 1888 or 061-224 9888

NOW AN AMSTRAD APPROVED SERVICE CENTRE!

APPOINTED WATFORD DEALER

Mancomp are now the main Northern Distributors for Watford Electronics and will be stocking all of Watford's popular range of hardware and software – all at Watford's prices.

Phone first for availability.

MANCOMP ARE MOVING

In line with our extensive expansion programme, we are moving to larger premises – with ample parking and only 2 minutes from the city centre.

Please call for details.

DISCS

Double-sided 96TPI
£7.50 for 10
Incl. **FREE** library case!
25 for £14.95

MODEMS

B.T. Approved
Modem complete with software
£99.95
300, 1200 & Prestel Auto Dial
Modem alone – £89.95
Software – £39.95

PRINT-AID

Printer Control Rom
ONLY £17.00
The Utility Rom to take the trouble out of getting the most out of your printer. (Specify Printer Type when ordering.)

SPECIAL PRINTER OFFER

BROTHER M1009
£145.00 incl. VAT

All our prices include VAT Please add carriage
£5.50 for Printers & Drives £1.50 for other items

Many other Hardware and Software items available

EXRESS SPECTRUM, BBC, COMMODORE & AMSTRAD REPAIRS!

SEND S.A.E.
for price list
Trade enquiries welcome

FIRST–
To provide 'While-U-Wait' Service.

FIRST–
With International repairs and discounts for Schools, Hospitals and H.M. Forces.

FIRST–
To provide Insured/Recorded Delivery on return journey.

FIRST–
With ***LOW CHARGES*** (e.g. £9 for keyboard faults).

FIRST–
For ***PROFESSIONALISM*** . . . "Of all the repair companies 'Sinclair User' spoke to, ***MANCOMP*** seemed the most professional when it came to advice and a helpful attitude". AUGUST 1985.

FIRST–
For ***SPEED*** . . . "One firm, at least, can usually effect any necessary repair. Based in Manchester, ***MANCOMP*** can offer what is arguably the fastest turnaround in the business, to personal callers".
'CRASH' Magazine, JUNE 1985.

FIRST–
For ***ADVICE & HELP*** . . . "I have come across a firm that will be more than willing to advise you as to how to remedy your problem. They are called ***MANCOMP*** and as well as repairing faulty Spectrums, are also quite willing to discuss your problems with you, and offer reasonably cheap and (more importantly) CORRECT cures". Phil Rogers, 'POPULAR COMPUTING WEEKLY', JANUARY 1985.

FIRST–
For ***LOW PRICES*** . . . "My Spectrum blew recently. I took it to ***MANCOMP,*** who fixed it in 8 mins. and for less than £10. they are local, 'clued-up', and blindingly efficient!" COMPUTER COLUMN, '4 HEATONS DIGEST', (Vol. 1, No. 11.).

FIRST–
For ***HONESTY*** . . .Call in and watch your computer being tested and repaired . Our engineers don't disappear into a back room.
If there is nothing wrong, we will tell you!

FIRST–
For ***REPUTATION*** . . . We have a reputation built on 2½ years of successful Spectrum, BBC, Commodore, Apple and IBM repairs.

AMSTRAD REPAIRS BETWEEN £14 and £55

SPECTRUM REPAIRS BETWEEN £9 and £20

COMMODORE REPAIRS BETWEEN £14 and £35

BBC REPAIRS BETWEEN £14 and £45

ESTIMATES GIVEN ON PRINTERS/DISK DRIVES ETC.

(Terms and conditions available on request.)

MANCOMP GUARANTEE
If the same fault occurs within 90 days of our repair, we will repair it FREE of charge AND refund the postage.
*Terms and Conditions available on request.

From Page 93

unlocked. I doubt if it will shock you to see that the other values in column B also change. We're used to this automatic updating of the spreadsheet. However we don't always want this, at times we want to change values without having consequences all over the place.

This automatic update is the default condition of the spreadsheet, the condition that applies at the start. In fact that's what the:

```
Auto
```

in the status area has been trying to tell us. Now we can switch this off by pressing Shift + *f4*. A glance at the status area shows us that we've done this, the message now being:

```
Manual
```

Confirm this by putting another value in B2, say 4. You'll see that the auto-update no longer occurs. There's no ripple through effect, the rest of the values in the column remain stubbornly the same even though they're all interlinked by formulae.

Once again the spreadsheet program allows us to change our mind and we can force an update, even when in manual mode. This is done using our previously neglected *f4* key. Press this and you'll see the spreadsheet change as the various formulae take account of the avalanche of new values started by changing B2.

And when you decide to switch on the automatic updating again, all you have to do is press Shift + *f4* again. This toggles between automatic and manual modes.

While we're using the *f4* function key, let's see what pressing Control + *f4* does. When you do this you'll see the message:

```
Enter column size:
```

appear in that status area. From this you should guess that pressing Control + *f4* allows us to change the width of our column. Now we've already been able to do this from the spreadsheet's menus so you may think that this is a bit wasteful. However, Control + *f4* only applies to one column, that containing the active cell. Previously we've only been able to change the width of all the columns.

So if the active cell is in column B, say B4, by replying 2 to the prompt and pressing Return you get a column B two characters wide. And as before you don't lose any information. All the contents you've previously put in the cell may not appear on-screen, but they are still there. If you don't believe me try using Control + *f4* again and this time request a column width of 7. All the old information re-appears.

By now your spreadsheet probably looks nothing like Figure I but unless you've gone really wild they will have one thing in common. They will be quite cramped. To look at Figure I, you can see that it's all numbers and labels. It would be much better if there were a few gaps in it. This would not only make it look better but it can also help understanding of the spreadsheet by isolating similar groups of cells.

Of course I've always harped on about planning and you should really have the layout sorted out before you start entering values. However, that's the counsel of perfection and we all change our minds. And, happily, spreadsheets usually allow for this. With Mini Office II the remedy lies in the *f3* key. Pressing Shift + *f3* allows us to insert a blank row or column into the spreadsheet. Let's try it on the spreadsheet in Figure I and see what happens.

```
.......A.......B.......C.......D
1           Power  2 to P
2
3             1.00    2.00
4             2.00    4.00
5             3.00    8.00
6             4.00   16.00
7             5.00   32.00
8
```

Figure II: The extra row and column

It would be nice to have a blank row between the labels and the figures, so let's do this. First move the cursor to any cell in row 2. Now pressing Shift + *f3* results in the message:

```
Insert row/column (R/C):
```

appearing in the status area. And replying with R for row gives us a blank row, the row containing the previously active cell and any subsequent rows all being moved down one to make room.

In pursuit of a neater layout we might also want to have the first column blank. This is done by making a cell in column A active and then using Shift + *f3* and replying C to the prompt. Column A is now blank with all the other columns being moved to the right to make space for it. The result should be something like Figure II – the figures may be different depending on what you've done previously.

Notice that no information is lost, it's just shuffled to the right or down to make room. And the blank row or column is always inserted where the active cell is.

And of course now we've got this facility to add a row or column to a spreadsheet we'll also want to be able to delete it. No prizes for guessing that this is done with Control + *f3*.

As before we move the cursor to the row or column we want to deal with. Pressing Control + *f3* results in the prompt:

```
Delete row/column (R/C):
```

and replying R or C deletes that row or column as required.

Knowing this it should be no trouble to re-create the spreadsheet of Figure I from Figure II's spreadsheet. Be wary though! Whereas adding a column or row doesn't lose information from the spreadsheet, deleting does. Delete column C of Figure II and it's gone for good. Hence it's always wise to lock columns and rows and so avoid tragedies.

● *And one more tragedy is that this is where we end for this month. More next time as we finish our exploration of the function keys.*

Season's Greetings FROM ATPL Advanced Technology Products Limited

B.U.5. Station Road, Clowne,
Chesterfield, S43 4AB. ☎ (0246) 811585 (4 lines)

SIDEWISE

Market No.1 Leader

SIDEWISE, ROM/RAM EXPANSION FOR THE BBC MICRO

- ★ Full Sideways ROM Expansion to a total of 16 ROMS.
- ★ 16K Battery backed CMOS RAM Option - Ram is treated as ROM no 15 on read.
- ★ Software for Sideways ROMS may be down loaded and run in RAM under true Sideways environment. See below for details of software packages available.
- ★ An ideal tool for Sideways ROM program development with the addition of RAM.
- ★ Plug-in-and go construction mounts neatly inside the BBC.
- ★ No soldering required to fit Sidewise.
- ★ Full buffering of address and data busses - prevents data bus loading problems assocaited with unbuffered boards.

Join the 10's of thousands of happy users.

£38.00 + £1.00 P&P + VAT

OPTIONS FOR SIDEWISE

Battery back up kit

£17.00 + 50p P&P + VAT

CMOS RAM 8K Bytes

£5.00 + 50p P&P + VAT

Buy 2 for £8.00 + 50p P&P + VAT

SIDEWISE PLUS

The Sideways ROM Board for the new BBC B+ Computer

- ★ Full Sideways expansion to a total of 10 x 16K ROMS.
- ★ Mounts neatly over the Sideways area inside BBC+ Micro.
- ★ No soldering required to fit Sidewise Plus.
- ★ Fully buffered board.

£32.95 + £1.00 P&P + VAT

SOFTWARE PACKAGES

A range of software specifically designed to enhance and extend the use of Sideways RAM on ATPL Sidewise and other products.

★ **SPOOLIT** Allows the Sideways RAM to be used as an 8K or 16K printer buffer.

£10.00 + 50p P&P + VAT

★ **DFS SHIFT** Moves the user RAM workspace required by the DFS into Sideways RAM. Allows memory recovery to & 0E00. Works with Acorn 0.9 DFS only.

£10.00 + 50p P&P + VAT

★ **SIDESWIPE** Allows you to save Sideways ROM onto disc and load Sideways ROMS from disc into RAM.

£10.00 + 50p P&P + VAT

★ **TURBOPROM - 1-2** Uses a fast programming algorithm to greatly reduce programming time of EPROMS (14 mins = 2 mins). Used with Autoprom available on disc or Sideways ROM.

£15.00 + 50p P&P + VAT

NEW **CUSTOM RAM/ROM WRITER** Utility to produce a ROM image for AUTOPROM or SIDEWISE RAM to automatically download and run a BASIC programme, and/or your utilities on power up. Several utilities supplied with this package. please specify 40T, 80T, disk or cassette.

£14.95 + 50p P&P + VAT

CAD SYSTEMS

ROBO SYSTEMS


Distributor

Professional CAD packages for IBM, Sperry, BBC and Apple computers

- ★ Over 10,000 users worldwide comprising: Electrical, electronic, mechanical, chemical, planning engineers, architects and educational establishments.
- ★ Complete systems supplied comprising: Computers, monitors, plotters and software.

Please contact Dale Atkins for further details.

DEALERS ENQUIRIES WELCOME ON ALL OUR PRODUCTS –PLEASE CALL



NEW **ATPL HOTLINE** For technical queries on ATPL products phone **(0246) 811585** between 3-5 p.m. Mon to Fri.

WE OFFER A DESIGN DEVELOPMENT AND MANUFACTURING SERVICE

INSIDEOUT

INSIDEOUT is designed to make a sideways ROM socket available outside the BBC computer, to allow for easy exchange of Sideways ROM's.

- ★ Can be used from BBC model B or expansion board sockets.
- ★ Supplied with low insertion force socket for ease of use-no costly cartridge packing.
- ★ EPROM plug in and go.
- ★ Not limited to one device.
- ★ Socket rated at 100's of insertions mounted outside the BBC. Easily removed and refitted.
- ★ Can be mounted in user defined location — not fitting in an illegal position.

ONLY £13.00 + 50p P&P + VAT

MOUSE PAC

MOUSE PAC IS AMX COMPATIBLE

Advanced software for the BBC Computer, available in the following combinations.

NEW **Mouse & Software** .....usually £48·00 + £1.50 P&P + VAT

On all orders recieved on or before 15th December. SPECIAL Christmas Price **£44·00**

NEW **Colour Stick + Software** ..... **£34.95** + £1.00 P&P + VAT

NEW **Mouse only** ..... **£29.90** + £1.50 P&P + VAT

NEW **Software only** ..... **£20.00** + £1.00 P&P + VAT

- ★ Comprehensive manual.
- ★ Drawing facilities include: Multi point rubber banding, 4 colour shapes for circles, squares, rectangles, elipses, arcs and sectors at any angle and size.
- ★ Drag drawing and air brush facilities with unique area masking.
- ★ Colour fill in any of 4 solid colours and a choice of 120 textured colours.
- ★ Screen printer dumps to Epson printer.
- ★ Utilities to use mouse or light pen in your own programs.
- ★ Colour stick fits analogue port, mouse fits to user port and needs 40 or 80 track disc drive.
- ★ Text can be entered in various sizes, fonts and colours.
- ★ Save and load screens to and from disc.

Please state 40 or 80 track disc.

BREAK LOCK

EVER HIT YOUR 'BREAK' KEY WHEN YOU DIDN'T MEAN TO?

FOR THE BBC MICRO

Fit ATPL 'BREAK LOCK' to your BBC Micro and avoid disaster where inadvertant use of 'BREAK' will cause loss of data and/or programmes.

ATPL 'BREAK LOCK' is a 2 position key-switch that will:

- ★ Prevent accidental or unauthorised use of the 'BREAK' key.
- ★ Act as a security device to prevent unauthorised use of your system more effectively and cheaper than security ROMs.
- ★ Easily and neatly fit in the 'Ash-tray'.
- ★ Render demonstration machines tamper-proof.

£8.53 + 50p P&P + VAT

AUTOPROM

Professional EPROM Programmer for the BBC computer and Acorn type Systems.

- ★ Capable of programming all 27 series EPROMS up to 27256 and most 25 series EPROMS.
- ★ Tape or disc based software, including fast program algorithm (27128 in 2 mins) and comprehensive manual.
- ★ Unique facility to run users own basic or machine code programs at Switch on or Reset.

£98.00 + £2.00 P&P + VAT

CONDITIONS OF SALE & DELIVERY

Cheques made payable to Advanced Technology Products Ltd. Please allow 28 days for delivery. Cost of carriage or postage refer to each section. Quantity orders and overseas carriage charged at cost. Condition of sales available on request.

ACCESS/VISA accepted. Carriage to be added to advertised price, then add VAT to the total. In accordance with our policy of progressive development, we reserve the right to modify specifications without prior notice.

A panacea for poor spellers

JIM NOTMAN looks into Acornsoft's much awaited ViewSpell, and gives it a definite thumbs up

ACORNSOFT has long promised a spelling checker for its View word processor. It has finally arrived with a package consisting of an 8k eprom, 80 track disc with the master dictionary, 41 page user guide and a reference card.

The package seems rather complicated at first, but is really straightforward. The reference card has a diagram showing which commands can be performed and in what order.

Once the software has been initialised in familiar View fashion with *SPELL the screen displays in the top left hand corner the title, number of bytes free, source file, number of words present and the current screen mode.

To check some text you first need to load it into memory. ViewSpell will then make a list of all the unique words, giving you the total word count and how many unique words there are in the file. As the list is being compiled any upper case letters are converted to lower case.

This can take some time, so to show that something is still happening a series of dots are printed on the screen. Once compiled the list is then checked against the master dictionary. This again takes some time, to the accompaniment of more dots.

The dictionary is larger than any other supplied with a spell checker. It fills most of an 80 track disc with a 175k file of 74,099 words stored in a compacted form, which apart from compressing the file also makes it easier and quicker to check.

Although this sounds like a huge number remember that each one may have a number of closely related words with different endings. For example, with the word yacht there is also yachting and yachts, but no yachtsman.

The words, supplied by Longman and based on its Concise English Dictionary, provide a wide ranging vocabulary. As you might expect there are a number of computing words present including byte and microcomputer. However there was no rom or eprom.

Crossword and Scrabble addicts will really like the facility to scan through the directory to look for the word they want. This task is helped by wildcards. All the words in the dictionary can be displayed or printed out with SEARCH *, where the star stands for any sequence of letters.

The ? character will stand for any single letter. For example, SEARCH *ing will display all words ending in "ing" and SEARCH ?a? will display all three letter words which have "a" as the middle letter.

Once the words from the original text list have been checked only those that have not been found in the dictionary remain. The checked list may be displayed on the screen or the words may be displayed in the context of the original text.

More usefully another file can be produced in which all the words not found by the dictionary are marked so that they may be easily found and edited in View.

By default the marker is !, but this may be changed. A marker may also be placed after the word. It is possible to change the markers to highlight characters so that, for example, all the marked text is underlined when printed out.

Just because a word is not in the master dictionary

ADD	Add selected words to a user dictionary, from a list in memory.
AW	Add words (typed in from the keyboard) to a user dictionary.
CHECK	Checks words against the dictionaries.
CMARK	Makes a text file with unfound words marked – on a single disc drive.
CONTEXT	Shows unfound words in the context of the original file.
CREATE	Creates a user dictionary.
DW	Deletes words from a user dictionary.
LIST	Lists the words in memory.
LOAD	Loads a text file retaining only a list of unique words.
MARK	Makes a text file with unfound words marked.
MARKER	Changes the characters used as markers.
MODE	Sets the screen mode.
NAME	Changes the source filename.
NEW	Clears all words but leaves prefixes and current user dictionary.
PREFIX	Specifies drives and directories for dictionaries and text files.
READ	Reads in words from other text files.
SAVE	Saves the word list to disc.
SCREEN	Displays the original text file.
SEARCH	Locates and displays words from the dictionary.
USER	Specifies a current user dictionary.

Table I: Viewspell commands

From Page 97

does not necessarily mean that it is incorrectly spelt. It could be an abbreviation, proper noun, word with an apostrophe or a specialist term.

Words that you use often, but are not in the master dictionary may be put into user dictionaries. Words may be added from the list of unfound words or typed directly into the dictionary.

Before they are added they are checked to see if they are already included. Words may be up to 32 characters long and the user dictionary up to 130,000 bytes long. Unwanted words can be deleted from the dictionary.

The PREFIX command tells ViewSpell on which drives the text and dictionaries are, and the USER command names of any user dictionaries. It is possible to set up a *EXEC file to enter ViewSpell, load and check text, produce marked text, then switch into View and start searching for the markers.

Although designed for View, ViewSpell can also be used with other word processors such as Wordwise and Mini Office II. Usually text files from word processors contain embedded control codes which could confuse ViewSpell. Therefore an Ascii file should be spooled for checking.

I did come across one problem with a couple of my View files which caused the system to crash when producing a marked text file.

This seemed to be due to three highlight characters appearing together for bold printing because when they were removed – and only these – there was no problem. The strange thing was that it then worked with other files with similar highlight commands.

This is the most flexible and easy to use spell checker I've come across so far. The documentation is up to Acornsoft's high standard with a 41 page manual. It is clearly illustrated using the example file supplied on the disc. My only quibble is this package has taken so long to appear. The only danger with ViewSpell is that once you start using it you'll find that you can't do without it. ■

Product: ViewSpell
Price: £39.95
Supplier: Acornsoft, Cambridge Technopark, 645 Newmarket Road, Cambridge. CB5 8PD

contex computing

BANK MANAGER (for disc systems only)
The most advanced and versatile personal bank account management program available for all BBC computers. Consistently acclaimed!
"data entry is a delight . . . professional . . . excellent product" **Micro User April 86**
Enter cheques and receipts. Standing orders any frequency. Automatic date sequencing. Reconcile statements. Search, amend and delete. Unreconcile. Move forwards or backwards. Analyse expenditure. Forward cash flow forecast. Up to 36 simultaneous 'bank' (bank, credit cards, savings, cash) accounts online simultaneously, inter-account transfers, 9999 standing orders, 99 analysis categories, 12 actual and 12 budgets per category, over 4,000 postings on an 80tk disc. Reports to screen or printer. Graphics. Foreign currency support. Password. File recovery. Auto exec. file. Field editing. Itemised look ahead. Programmable report writer.
Standard Bank Manager for the BBC B, B+ £17.50

BANK MANAGER MASTER (for disc systems only)
Version 2 now available. Includes all of the facilities of the standard Bank Manager plus ADFS file system support, shadow screens, uses sideways RAM, 40 or 80 column screen reports, improved graphics, m/c windows, function key support and onscreen labels, additional functions added to the already extensive report facilities.
Bank Manager Master for the MASTER and MASTER COMPACT £22.50
Upgrade from standard, return original disc and £6.00

BANK MANAGER BUSINESS UTILITIES (for disc systems only)
For the 'professional' who also uses the BANK MANAGER to control the business accounts the BUSINESS UTILITIES add double entry trial balance and programmable spreadsheet analysis reports. Generated from cheque and cash transactions keyed into BANK MANAGER. Just pass the reports to your accountant! Use with either standard or master/compact version.
Bank Manager Business Utility Pack 1 £12.00

TYPING TUTOR
Quickly learn to touch type. Over 90 smoothly graded lessons graduate you from the basic home keys to complete keyboard mastery. Unique word scan line checking. Target WPM and percentage correct. You may revise the targets or lessons as required. Audio key click for positive key depression. Establish a typing rhythm using the automatic metronome. Free format option. Recommended.
for BBC B, B+, Master and Compact; Cassette £9.50, Disc £12.50
ALL PRICES FULLY INCLUSIVE. FREE POSTAGE WITHIN UK. Enquiries and Access credit card orders telephone 023 03 347
CONTEX COMPUTING, 15 Woodlands Close, Cople, Bedford MK44 3UE

Please rush me ..... for BBC: ☐ B ☐ B+ ☐ Master ☐ Compact
☐ Cass ☐ 5.25" ☐ 3.5" ☐ 40tk ☐ 80tk ☐ DFS ☐ ADFS
Enclosed £ or debit my Access card no. .....
Name .....
Address .....
.....
MU
FAST DELIVERY


EPROMS – 8271 – MEMORY DRIVES – DISCS – MODEMS
Incl. VAT – LOW LOW PRICES – Incl. VAT

5¼" 40/80 TRACK D/SIDED DRIVES
– new switched cased drives with BBC leads.
SINGLE (400k) ● £99.00
DOUBLE (800k) £195.00
POWER SUPPLY ..... POA
Also **Teac 55F** £119.50 £239.00
Mitsubishi £115.50 £231.00

DFS KIT – 8271 DFS KIT Complete with ACORN DNFS £53.50
1770 DFS Kit (Inc. Acorn ROM) £44.95
1770 Compatible board + 7438's £34.90
Acorn ADFS with utilities £27.50

3M BRANDED 5¼" DISCS
Boxes of 10 40T SS DD £10.95
80T DS DD £17.95

TTL-DFS CHIPS ETC
7438 ..... £0.35
74LS10 ..... £0.25
74LS123 ..... £0.55
74LS136 ..... £0.35
74LS163 ..... £0.55
74LS174 ..... £0.55
74LS244 ..... £0.70
74LS245 ..... £0.85
74LS393 ..... £0.70
CD4013B £0.45
CD4020B £0.55
SPECIAL OFFER – Deduct 5% for 2 or more products. Except drives & 8271.

WINCHESTERS – Affordable compatible drives

INTRODUCTORY OFFER
Own power supply & fan – Plug in & go! (B+ requires ADFS, B requires 1770 + ADFS)
10MB £549.00
20MB £679.00

CONTROLLERS, CPU'S, ETC
8271 ..... £36.95
WD1770/72 ..... £14.80
6502A CPU £4.90
65C02 Low Power CPU £8.20
6522 VIA £3.60


MEMORIES
6264 LP-15 ..... £3.40
4416-15NL (TMS or NEC) £2.85
41254-12 (Solidisk) £6.20
41416-15 (Watford 48416) £2.60

EPROMS *VPP 12.5V
2764 - 250ns £2.35
27128 - 250ns £2.80
27256 - 250ns* £5.35
27C256 - 250ns* £6.95

MODEM HOUSE
Voyager 7 Modem ..... £88.95 inc.
+Comsoft ROM & Lead ..... £99.95 inc.

Mail order only to:
Prices incl. of VAT - Post & Ins. add 65p or for Drives add £3.60 (1) or £4.60 (2) £9.00 (Winch'r)
● State if 2nd Drive (DR1)
Postal queries answered promptly. (Enclose daytime & evening tel. no.)
Cp microsystems
32-34, Surbiton Road, Kingston upon Thames, Surrey KT1 2HX.
Local Auth. Orders accepted

INSTANT



Now on a power-packed ROM board – the BBC Micro's top-selling 6-in-1 package. Included in it are all the highly-acclaimed features of Mini Office II . . . plus many exciting extras.

INSTANT

WORD PROCESSOR

Memory can hold up to 3,600 extra words. Text can be entered in 20 (enlarged), 40 or 80 column modes. New embedded commands for Epson compatible printers.

INSTANT

DATABASE

Room for an additional 150 average-sized records in RAM. Total capacity only limited by disc space.

INSTANT

SPREADSHEET

Provides 3000 extra cells, plus many more maths functions. Can run 40 or 80 column format.

INSTANT

COMMUNICATIONS

Bigger buffer capacity means much longer text files can occupy the BBC Micro's memory for uploading or downloading text.

INSTANT

GRAPHICS


Speedier switching to and from spreadsheet to create or amend bar charts, line graphs and pie charts with ease.

INSTANT

LABEL PRINTER

Labels prepared in the database can be quickly output in any format onto sticky labels

The original Mini Office II is still available on tape and disc. Existing owners of tape or disc versions can exchange them for Instant Mini Office and save £8. See the coupon alongside.



- Four 32k ROMs packed with 128k of super fast machine code – together on one easy to fit board.
- Simply key *MINI for the main menu, or speed directly to each program by keying *WP, *SP, *DB and so on.
- Switch from one application to another in a split second.
- Frees valuable RAM space for much more data.
- No need to swap discs if you've only one drive.
- Easy to install – slots into any sideways RAM socket.
- Works with Aries or Watford shadow RAM board.
- Compatible with BBC B, B+, Master and Compact.
- Compatible with all filing systems: tape, DFS, ADFS, and ECONET – and many third party DFSs.

ONLY £59.95

Order Form

			£ p
☐ Instant Mini Office	£59.95	*2372*	
☐ Upgrade Mini Office II to Instant Mini Office *I enclose full tape/disc pack*	£51.95	*2375*	
☐ Mini Office II cassette	£14.95	*2368*	
☐ 5.25" disc 40T	£16.95	*2369*	
☐ 5.25" disc 80T	£16.95	*2370*	
☐ 3" disc	£19.95	*2371*	

Add £3 for Europe; £8 for Overseas

☐ Cheque enclosed made payable to Database Publications Ltd.

☐ Please debit my Access/Visa credit card account.

Please allow 28 days for delivery.

Post to: ***Database Software, FREEPOST, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 5NY***

PHONE ORDERS: 061-429 7931 (24 hours)
ENQUIRIES: 061-480 0171 (9am-5pm)
PRESTEL ORDERS: Key *89 then 614568383
MICROLINK ORDERS: Mailbox 72:MAG001

Name _____

Address _____

_____

_____

Post Code _____ Tel: _____

Signed _____

Please quote credit card number and full address + Ref MU 12

LASEROM
MASTER YOUR BBC

***BACK UP**	Inbuilt disk to disk copier — kills the disk swop problems.
***MEDIT**	Lightning memory editor — ASCII or HEX of course.
***DEDIT**	Lightning disk editor by tracks or sectors ASCII or HEX.
***PMEM**	Memory dump to printer for given address range.
***PDISK**	Disk sector dump to printer.
***MSEARCH**	Lightning string/byte set memory search, locating centre screen in ***MEDIT**.
***DSEARCH**	Lightning string-byte set disk search, locating centre screen in ***DEDIT**.
***RETRIEVE**	Reeds selected disk sectors to specified memory areas.
***REPLACE**	Writes selected memory area to specified disk track & sector.
***DIS**	At last — an ultra intelligent disassembler follows jump or branch instructions AND returns, at users request.
***BDIS**	Memory disassembler for selected address range, saving to disk which may then be *EXECed into a basic program.
***SKEYS**	Saves user-defined function keys to disk with chosen or default filename.
***LKEYS**	Loads user-defined function keys from disk with chosen or default filename.
***BYTE**	Fills memory for the specified range with a given byte.
***RELOCATE**	Moves a block of memory from one address to another coping with overlaps.
***UCODE**	Executes user code at the given address, from within other programs offering *COMMAND facilities.
***VDU**	Sends the given bytes to the printer, useful for changing print fonts from within other programs.
***CLOCK**	Continuously prints current time during your applications.
***COLOUR**	Changes foreground & background colours in all modes (except 7) for super text definition during applications in 80 column modes.

DISKING INTERNATIONAL, HINDHEAD, SURREY GU26 6BR
TEL: (0428) 722563

LASEROM is a trademark of, & is designed & manufactured by Proteus Software.
Prices & specification correct at time of going to press.
We reserve the right to improve without notice.

ONLY £25.00
exc. VAT
(£28.75 inc. VAT)
(P&P £1.00 inc. VAT)

Please rush me____ for the BBC MASTER Computer

Name_____

Address_____

_____

_____ Tel:_____

I enclose cheque payable to **DISKING**, or please

debit my ACCESS/VISA card No:_____

To order by 'phone (24hrs) call **(0428) 722563** RETAIL
Trade enquiries welcome — call
(0428) 722840 WHOLESALE

DISKING, FREEPOST,
Hindhead, Surrey GU26 6BR

LASEROM

·BANANA ·STOCKISTS

CAMBRIDGESHIRE
WISBECH COMPUTER SERVICES LTD
11 HILL STREET
WISBECH
CAMBRIDGESHIRE PE13 1BA
TEL: (0945) 64146
CONTACT: IAN DUFFY

CUMBRIA
CUMBRIA SOFTWARE SYSTEMS
13 BURNRIGG
HEADS NOOK
CARLISLE
CUMBRIA CA4 9BH
TEL: (0228) 60842

DORSET
TIGER SOFTWARE
66 ST. MICHAELS LANE
BRIDPORT
DORSET DT6 3RB
TEL: (0308) 27691
CONTACT: TERRY GILBERT

GLOUCESTERSHIRE
ENTHUSINET
UPPER SPRINGFIELD ROAD
UPLANDS
STROUD
GLOUCESTER GL5 1SN
TEL: (04536) 4310
CONTACT: JOHN S. CHURCHILL

HERTFORDSHIRE
MELMARK MICROSYSTEMS
WARREN PLACE
RAILWAY STREET
HERTFORD
HERTS SG14 1BA
TEL: (0992) 554469
CONTACT: N. J. TOBIN

KENT
CANTERBURY COMPUTER CENTRE
56-57 PALACE STREET
CANTERBURY
KENT CT1 2DY
TEL: (0227) 462101
CONTACT: DAVID JONES

COMPUTERS PLUS
65 HIGH STREET
SITTINBOURNE
KENT ME10 4AW
TEL: (0795) 25677
CONTACT: MR. A. FRANCIS

LONDON
WILDA SOFTWARE LTD
2 NICHOLAS GARDENS
LONDON W5 5HY
TEL: 01-567 6941
CONTACT: TONY WILLIAMS

MICRO ANVIKA
220A TOTTENHAM COURT RD
LONDON W1P 9AF
TEL: 01-636 2547
CONTACT: A. GOHIL

MIDLANDS
MR. DISK
11-12 THREE SHIRES OAK RD
BEARWOOD
WALEY
WEST MIDLANDS B67 5BA
TEL: 021 420 1360
CONTACT: J. GUEST

NORFOLK
COMPUTER PLUS (KINGS LYNN)
40 NEW CONDUIT STREET
KINGS LYNN
NORFOLK PE30 1DL
TEL: 0553 774550
CONTACT: D. J. FARROW

COMPUTER GAMES SHOP
3 ROYAL OAK BUILDINGS
WATERLOO ROAD
BLACKPOOL
LANCS FYA 2AQ
TEL: (0253) 48738
CONTACT: JIM McEVOY

OXFORD
OXFORD COMPUTER SUPPLIES
P.O. BOX 133
OXFORD OX4 3NB
TEL: (0865) 716137
CONTACT: TERRY J. CUMMINGS

SURREY
STATACOM COMPUTERS LTD
20 GROVE ROAD
SUTTON
SURREY SM1 1BG
TEL: 01-661 2266

SUSSEX
THE DATA STORE
19 STATION ROAD
HAILSHAM
SUSSEX BN27 2BH
TEL: (0323) 846777
CONTACT: MIKE CLAPHAM

banana
REVERSIBLE MINIDISKS

GRAVESEND COMPUTER CENTRE
39 THE TERRACE
GRAVESEND
KENT DA12 2BA
TEL: (0474) 323871
CONTACT: LYNNE BAXTER

LANCASHIRE
CASTLE COMPUTERS LTD.
5 FRANCES PASSAGE
LANCASTER
LANCS LA1 1UG
TEL: (0524) 61133
CONTACT: DAVE SMITH/GAIL

C.J.E. MICROS
78 BRIGHTON ROAD
WORTHING
WEST SUSSEX BN11 2EN
TEL: (0903) 213361

YORKSHIRE
WISE OWL SOFTWARE LTD
23 STATION STREET
SWINTON
MEXBOROUGH
SOUTH YORKSHIRE S64 8AU
TEL: (0302) 781625

BANANAS ARE RAPIDLY SPREADING THROUGHOUT THE U.K. AND EUROPE. IF YOU WISH TO MAKE MONEY SERVING YOUR LOCAL COMMUNITY WITH RIPE BANANAS CONTACT US FOR A DEALER PACK ON **(0428) 722840** (WHOLESALE).

DISKING, FREEPOST, HINDHEAD, SURREY W26 6BR. (0428) 722563 (24 HRS).

BANANAS SUIT VIRTUALLY ALL COMPUTERS WITH 5¼" DRIVES. SINGLE OR DOUBLE SIDED, 40 OR 80 TRACK SINGLE SIDED DRIVES HAVE TWICE THE STORAGE AS BANANAS CAN BE FLIPPED OVER. BANANAS HAVE:– HUB RINGS – 2 NOTCHES – 2 INDEX HOLES – TABS & LABELS. ALL CERTIFIED WITH A LIFETIME WARRANTY.

SOMETHING YOU WON'T SLIP ON



banana

REVERSIBLE MINIDISKS

EXCLUDING VAT, A TEN PACK IS

ONLY £8·65

GROWN EXCLUSIVELY BY
DISKING INTERNATIONAL
HINDHEAD, SURREY GU26 6TD

TEL: (0428) 722563

Official Government orders are welcome.
FREE 'Bananas' badge with every ten-pack.
All orders despatched in 4 hours.

POST to:—
DISKING, FREEPOST, Hindhead, Surrey GU26 6BR. Tel: (0428 722563)
Please rush me ____ boxes of Bananas at £9.95 per box plus P & P at £1.09 per box. Total £11.04 per box inc. VAT. P & P is 86p/box for 3-5 boxes, 69p/box for 6-9 boxes. Ten boxes or more are POST FREE.
I enclose cheque payable to DISKING, or please debit my ACESS/VISA card No:—

.....

Name .....

Address .....

.....

Tel No. .....

Try us for quality, service and prices

ROCKFORT

A Trading Division of Vignesh Ltd.

Manufacturer and distributor of Rockfort disk storage systems

DISK STORAGE




M.F. 50 Floppy Disk Box
Holds 50 - 5¼" Disks
£9.50



M.F. 10 Floppy Disk Box
Holds 10 - 5¼" Disks
£2.75

REG. DESIGN

NEW



MD 10/20 Micro Disk Box
Holds 20 3½" Disks
or 10 3" Disks
£7.85

All disk box prices include VAT, Post & Packing.

ROCKFORT LABEL 5¼" FLOPPY DISKS

Prices include VAT and carriage

10-SS/DD 48tpi	in MF10 box	**£10.95**
10-DS/DD 48 tpi		**£12.95**
10-DS/DD 96tpi		**£16.95**
25-SS/DD 48tpi	in MF50 box	**£22.95**
25-DS/DD 48tpi		**£26.95**
25-DS/DD 96tpi		**£39.95**
50-SS/DD 48tpi	in MF50 box	**£36.95**
50-DS/DD 48tpi		**£40.95**
50-DS/DD 96tpi		**£59.95**

ROCKFORT LABEL DISKS FEATURE:

- Individual sleeves
- Write protect notch
- Hub rings
- Full set of labels (and write protect tabs)
- Meets all ANSI specifications
- Fully guaranteed

COMPUTERS

BBC MASTER 128K
£455.00 inc VAT
CARRIAGE FREE IN UK

MASTER COMPACT

TV SYSTEM
£449.00
inc VAT & CARRIAGE

THE SECOND GREAT LITTLE PRINTER FROM CENTRONICS



SPECIAL OFFER

Price
£149.95 inc VAT
Tractor feed – £6.00 inc VAT
Add £7.00 for carriage by securicor.

CENTRONICS GLPII
(– IMPROVED VERSION OF GLPI)
EVERYTHING IN THE OLD GLP+
– 100 cps in draft print mode
– 25 cps near letter quality
– 2k input buffer
– Quad density graphics
– 50 million characters print-head life

PRINTER RIBBONS

Prices include VAT and carriage

TYPE	min. 2+
Epson MX100/FX100	**£5.50**
Epson MX80/FX80	**£4.20**
Seikosha GP80	**£4.20**
Seikosha GP100	**£4.70**
Seikosha GP250	**£4.85**
Brother HR15 M/S	**£4.90**
Centronics GLP	**£3.80**
Juki 6100	**£2.45**
IBM 82 (High yield)	**£2.80**
OKI 80/82	**£2.80**

LISTING PAPER

60 grams micro perf 11" x 9½" 1000 **£9.00**
2000 **£15.00**

TO ORDER – PLEASE COMPLETE THE COUPON BELOW AND SEND TO US OR CALL US ON 01-203 0191 TO USE ACCESS/VISA CARDS

PRINTER CABLES

IBM	**£14.95**	BBC	**£8.95**
Apricot	**£14.95**	QL	**£8.95**
Spectrum	**£12.95**		

Other computers and peripherals available – please 'phone or write for a free catalogue.

ROCKFORT PRODUCTS







81 Church Road, Hendon, London NW4 4DP

Please supply the following:

Qty.	Description	Price inc. of Carriage

Name .....
Address .....
..... Postcode .....

TRADE ENQUIRIES INVITED For Sinclair and BBC spares please call

Four-way SCROLLER

By TIM BROWN

ONE of the great programming mysteries of the BBC Micro must be that of sideways scrolling. Yes, I know it's a simple matter of altering registers 12 and 13 of the 6845 CRTC, but it isn't as simple to prevent the jumping that occurs in doing so.

After a little bit of typing and a lot of thinking I came up with this program to scroll a Mode 2 screen in any direction without jumping.

If you are unsure how the 6845 can be used to scroll the screen, it is explained by Alan Plume in the August 1984 edition of *The Micro User*. However you don't need to understand how this program works to find its fast machine code routines useful within your own programs.

Type in the program carefully and save it before you run it, or you might find that it could be lost due to a typing error. Take special care when typing in the variables ending with *lo* or *hi*, as getting one of these wrong can prevent the program from working properly.

When you run the program a simple picture will be drawn on the screen and a beep will be heard. At this point press Z, X, *, or ? to scroll in the appropriate direction. Press space to exit the program.

At the core of the program are four routines, *Right; Left; Up* and *Down*. Calling any of these will scroll the screen in that direction.

The routine *setup* must be called before any scrolling takes place and to use the routines in your own programs you must call *setup* once then *Right*, for example, any time you want to scroll. If you are in Basic use CALL or from machine code JSR.

Now for something flash, or rather to get rid of it. Type the following lines into your program:

```
 75 FOR C=8 TO 15:VDU19,C,0;0;:NEXT
495 EOR#&C8
625 EOR#&C8
1115 EOR#&C8
1245 EOR#&C8
2420 GCOLK,9
2440 GCOLK,10
2460 GCOLK,12
```

You now have a routine that shows two Mode 2 pictures on the screen at once. One picture is drawn in colours 0-7, the other in colours in 8-15.

Lines 495, 625, 1115 and 1245 swap the colours around. Line 75 simply sets the flashing colours all to black. When the sideways routines are called one line of the other picture is revealed.

Be careful when printing or plotting on the screen after scrolling, the effects can be unusual. The program works on all BBC Micros with 32k though on the B+ and Master the shadow mode should not be used, and the Tube should be disconnected.

Well that just about wraps it up (or around) for scrolling. With some clever use of colours as in the amended program a useful advertising display could be created, or a kind of slide show is possible. It is simply a matter of drawing the picture right.

Full listing starts on Page 131

MORLEY ELECTRONICS


NOW NEWCASTLE'S MAIN ATARI DEALER
COMPUTERS, PERIPHERALS, SOFTWARE

The Morley Teletext adapter introduces you to the world of Teletext at a price that wont break the bank. Inside it you will find the latest in second generation Teletext chip technology, which unlike our rivals who are still using chips designed more than eight years ago, will be fully compatible with any future advances in the Teletext system.
With the Morley adapter you will get a unit that automatically tunes itself in to the required station (no more messing around with screwdrivers in the back of the case), a user friendly menu driven program, easy to follow instructions and a 12 month warranty. Add to this the free downloadable telesoftware and we are sure that you will agree that we are offering you one of the best bargains on the market today.

For technical details please ring Morley Electronics on Tyneside (091) 262 7507 after 4.00 pm


FEATURES

- Advanced design uses the latest technology will handle ANY future enhancements to the Teletext system eg: full field: 8 bit data transfer: 2k pages etc.
- Simply plugs into the user port.
- Low power consumption, less than 200ma. Optional power supply available.
- User friendly menu driven software including extended OSCLI and Osword commands for access from BASIC programs.
- No user-RAM required (PAGE remains at default value).
- FREE Telesoftware, no access charges. (at present updated weekly.)
- Save selected pages to disc/tape for later retrieval.
- Full access to all Teletext services and channels eg: CEEFAX, ORACLE, 4-TEL.
- Gives you a real-time clock at your disposal (*TIME).
- Free software upgrades to allow for any enhancements to the teletext service. Eg: extra channels, full field data on cable & satellite systems etc.
- Easy to follow comprehensive user guide.
- No hardware limitations, it can for example receive virtually unlimited numbers of channels.
- Works with Solidisc SWR.



- Utils disc available including printer drivers allows pages to be selected and dumped direct to a printer (no more TV or Radio Times to buy).

ELECTRON TELETEXT ADAPTER
Electron adapter now available, including emulated Mode 7 allowing you to run long Adventure type programs. Please ring for details.



Now available the first true MEGA capacity RAMdisc for the BBC or MASTER computers.
This fully compatible unit, currently available in either 1 or 2 megabyte versions comes complete with operating software on ROM, power supply, battery backup and a comprehensive user guide, add to this our usual 12 months no quibble guarantee and we're sure you'll agree Morley have done it again.

FEATURES

1 Megabyte of RAM connected to the 1 MHz bus.
Used with the supplied ROM software programs and files may be saved and loaded from the RAMdisc in the same manner as from a floppy disc with a large increase in speed, for example, a 20K mode 0 screen takes about 3-4 seconds to load from disc and about 0.2-0.3 seconds to load from the RAMdisc.
The RAMdisc ROM operates as a utility ROM working with the current filing system rather than as a separate filing system. Therefore ensures compatibility with any Acom compatible DFS (not ADFS).
The RAMdisc can be selected by a * command to take the place of any drive number from 0 to 9. If the RAMdisc replaces a floppy drive as 0 for example, all commands addressed to drive 0 will be intercepted by the RAMdisc. The default drive no. is 4.
'Dangerous' * commands such as *COMPACT, *COPY, *BACKUP etc are intercepted and the BBC's RAM from page 2 to &7FFF is saved to RAMdisc workspace, and may be recovered using a * command. This prevents accidental corruption of any programs/data in RAM you may have been using at the time. The save operation delays the * command by just under 0.4 seconds. The BBC's RAM can also be saved by an interrupt-driven routine which can be enabled by a * command.
The 'filing system wedge' ROM supplied supports load/save, byte file access, all relevant OSFSC commands, and contains a formatter, verifier and 'sector' editor for use with the RAMdisc.
Catalogue structure allows up to 2,709 files.

EPROM PROGRAMMER now available programs 8, 16 and 32k EPROMS connects to the user port software available on rom or disc.
Version 1 economy uncased with standard DIL socket.
Version 2 deluxe cased with ZIF socket.

DESFAX 7 – Now you can run your own TELETEXT service!
Incorporates the powerful editing facilities of DESIGN 7, again with Teletext adapter interfacing.
Stores up to 100 of your screen designs on a 40Tk disc or 200 on an 80Tk. Page selection by 3-digit number HOLD, REVEAL, page linking, individual page delays etc.
PLUS – a powerful CAROUSEL facility permits continuous slide-shows. Only one disc access for every 16 screens – reduces wear on drives. Smooth animation, variable speed text printing, built in printer dumps. Sample data disc and 22 page manual included. Beats all other systems for ease of use and versatility.

M/B software DESIGN 7
Easily the best value Mode 7 screen designer on the market today. Design any mode 7 screen, from simple MENU pages to full CEEFAX standard. This program is an invaluable aid. Designs can be saved to disc as automatically numbered files or the program will convert the screen into a Basic Proc.
INTERFACES DIRECTLY WITH ADAPTER allowing CEEFAX-ORACLE pages to be selected and dropped into editor screen for alteration, saving, or conversion to BASIC. Allows channel change from within program.

M/B software MASTER COPY
. . . the selective copier **you** need for the BBC MASTER computer . . .
Dramatically reduces the time taken to copy unprotected discs,
DFS to ADFS, ADFS to DFS, DFS to DFS, ADFS to ADFS
using one or two, single-ro double-sided drives.
An 84K RAM buffer enables many files to be copied in one pass with the minimum of disc swapping, and directories are created automatically as required. Files of any length are handled.
Supplied on disc, MASTERcopy runs form sideways RAM and is invoked with a * command. The program re-installs itself in sideways RAM when copying is done, ready for later use.
The ROM image supplied can be used to blow your own EPROM too, for use in the MASTER's cartridge slots.
Typical time to copy all 31 files DFS to ADFS is under 2 minutes!
£12.95 on disc – £14.95 for ROM version (including postage etc.)

For further details on all products call 091 262 7507 after 4.00pm

To order please fill in and send order form to: **MORLEY ELECTRONICS, Unit 3, Maurice Road Industrial Estate, Wallsend, Tyne and Wear NE28 6BY.**

Adaptor Software
ROM ☐
SWR DISC ☐
40 TRK ☐
80 TRK ☐
Please Tick

Please send me
Qty. ☐ Morley Teletext adaptors @ £99.95 inc. VAT
Qty. ☐ Master Copy ROM @ £13.95 inc. VAT
Qty. ☐ Master Copy Disc @ £11.95 inc. VAT
Qty. ☐ M/B DESIGN7 screen designer @ £7.95 inc. VAT
Qty. ☐ Teletext utilities on Disc @ £5.95 inc. VAT
Qty. ☐ Optional PSU @ £9.95 inc. VAT
Qty. ☐ 1 Mbyte RAM disc @ £199.95 inc. VAT
Qty. ☐ 2 Mbyte RAM disc @ £349.95 inc. VAT
Qty. ☐ Eprom Programmer V.2 @ £18.95 inc. VAT
Qty. ☐ Eprom Programmer V.2 @ £27.95 inc. VAT
Qty. ☐ Desfax @ £23.00 inc. VAT

Total £

BARCLAYCARD VISA Access

NAME _____ PHONE No. _____ CHEQUE No. _____

ADDRESS _____

_____ POSTCODE _____

Please add £3.00 P+P on Adaptors and RAM Discs, £2.00 P+P on PSU's and Programmers, £1.00 P+P on Software *Please allow 28 days for delivery*

Christmas BOX

By
ROLAND
WADDILOVE



IT is Christmas Eve and the presents are under the tree. To while away the time everyone is trying to guess what they are going to receive.

There are seven different types of present and five boxes under the tree. What you have to do is guess what is in each box.

You can have up to 12 guesses and your guess will be marked using black and white pegs:

- A black peg means that one of the five presents in your guess is correct and in the right place.
- A white peg means that one of the presents is correct but in the wrong place.

The pegs are not awarded in any particular order, so you can't tell which peg is for which present.

There are four levels of difficulty to choose from and this quite addictive game is for the whole family.

The controls are simple: Press a number, 1 to 7, to place a present and Delete to erase it.

Christmas Box will stretch your powers of logic to the limit and is just the job for those long winter evenings. It's a real brain teaser! ■



PROCEDURES

board	Set up the screen.
variables	Set the difficulty level.
input	Input your guess.
check	Mark your guess.
initialise	Define the characters.
instructions	Print the instructions.

VARIABLES

guesses	The number of guesses taken.
code(5)	The answer.
guess(5)	Your guess.
level	Difficulty level.
correct	The number of presents correct.

Full listing starts on Page 139



The most adventurous and original way to test your French ever devised.

FRENCH on the RUN!



The adventure game with a big difference.

£9.95 cassette
£11.95 5¼" disc
£13.95 3" disc

You're on your own in Occupied France — facing the toughest test that a British pilot has ever had to experience!

The year is 1943. As an RAF officer stranded in Occupied France you have one aim — to get back to Britain.

The only way to do this is to try to pass as a Frenchman, but if your French isn't good enough you risk capture and interrogation by the police or even the Gestapo.

Even the simplest tasks — from buying food to taking buses — place you at risk. And to add to your problems you've got limited funds: "Should I hitch a lift or take the train?", "Do I sell my belongings or get a job?"

Whatever you decide to do, time is short. And there are always people willing to denounce you . . .

French on the Run is that rare combination: A truly educational program that's also a thoroughly enjoyable game. This text adventure not only tests your grammar and vocabulary, but your knowledge of France and the French way of life.

And as your French improves the language problems get harder and the situations become progressively more dangerous. There are four routes to complete in sequence — you need the password from the last before attempting the next. The standard of French required is about O level, though on the last route it rises to just below A level.

And there's a chance for you to try out the French you'll learn in practice: We are offering a FREE WEEKEND IN PARIS as a prize to the first person to get back to England alive, having broken a code near the end of the final route.

For teachers: *French on the Run uses multi-choice questions with randomised distractors, all carefully chosen to illustrate linguistic points or points concerning things French. The program is meant for individual assessment, but can be used just as effectively for classroom work. A sealed envelope contains details of how the secret passwords are created.*

DATABASE SOFTWARE

TO ORDER TURN TO THE FORM ON PAGE 167

Carry the flag to good effect

By MIKE BIBBY

AS promised, this month we're going to meet a new flag – the Carry flag. It's intimately involved with addition and subtraction which, when you consider that the 6502 sees all its data as numbers, means that Carry is rather vital to machine code programming.

In fact it's so important that the Carry flag is included with the mnemonics for doing sums. Addition is implemented as ADd with Carry (ADC) while subtraction is SuBtract with Carry (SBC). You can't do sums without having Carry in there.

Carry itself is our normal two-valued flag. It can be *set* – when it has the value one – or *clear* – when it has the value zero. As with the zero flag, there are two relative branch instructions based on it:

BCS Branch if Carry Set
BCC Branch if Carry Clear

There are also two instructions that allow us to fix the value of Carry directly:

SEC SEt Carry
CLC CLear Carry

Most of the time we'll be branching as a result of how a particular operation has affected Carry.

Fundamentally, the Carry flag warns us that the sum we're doing is going to give us a misleading result. These misleading results stem from the fact that, as we've seen, the accumulator can only handle numbers in the range 0 to 255 (&FF).

Suppose that the accumulator already has &FF in it. Adding one to it should give us &100 (256) but this is too large for the accumulator, which "wraps round" to zero – exactly 256 out!

Again, if we were to add 2 to &FF, the result in our accumulator would be one. Once more we're 256 out. Think of the sum as:

```
  255+2
=255+1+1
=256+1
=1
```

What happens can be described by the following rule: When you get to a 256 in a sum, discard it!

It's as bad for subtraction. We're used to the fact that 1–2 gives us &FF. One way to think of this is, when the number we're taking away is "too big", we add an extra 256 into our sums to get them to work. The sum above becomes:

```
  1–2
=256+1–2
=256+1–1–1
=256–1
=255
```

The size restriction on the number a byte can handle causes us immense problems. Obviously we need to take its effect into account when we do our sums, otherwise we'd get too many wrong answers. We need something to indicate that we've over-reached the confines of our accumulator. This is the purpose of the Carry flag.

Let's have a look at this in practice: To add, say, 6 to 8 we would need something like:

```
LDA #6
ADD #8
```

The answer ends up in the accumulator.

Notice that we're using immediate addressing: We're not talking about the *contents* of memory locations 6 and 8 (as we would be with absolute addressing), we mean the actual values 6 and 8.

Unfortunately there isn't a straightforward ADD instruction on the 6502. You have to use ADC – ADd with Carry. This does an add, all right, but includes the value of the Carry flag in the sum. The previous instructions would translate into:

```
LDA #6
ADC #8
```

The trouble is this sum can give two answers, depending on whether Carry is set or not. If it is set, it becomes:

```
6+8+1=15
```

If Carry's clear it is:

```
6+8+0=14
```

Obviously it's the second option we want, and to make sure we get it, we use CLC first to ensure that Carry is clear as in:

```
CLC
LDA #6
ADC #8
```

You might be wondering why we bother including Carry in our add instruction at all, since all we've done is

→

```
10 REM PROGRAM I
20 first=&70
30 second=&71
40 result=&72
50 add=&900
60 REM *** Machine Code core ***
70 FOR pass%=0 TO 3 STEP 3
80 P%=add
90 [
100 OPT pass%
110 CLC
120 LDA first
130 ADC second
140 STA result
150 RTS
160 ]
170 NEXT pass%
180 REM *** Basic surround ***
190 REPEAT
200 REPEAT:INPUT '"First Number",number1%:UNTIL number1%>-1 AND number1%<256
210 ?first=number1%
220 REPEAT:INPUT '"Second Number",number2%:UNTIL number2%>-1 AND number2%<256
230 ?second=number2%
240 CALL add
250 PRINT 'number1%;" + ";number2%;" = ";?result''
260 UNTIL 0
```

Program I

From Page 107

to set it to zero so it has no effect. The answer is that we need it to handle sums involving large numbers, as we'll see later in the series.

For the moment, take a look at Program I. It might look rather complex at first, but most of it is a Basic surround for a simple machine code program:

```
CLC
LDA first
ADC second
STA result
RTS
```

The assembly routine adds the value in memory location *second* to the value in *first* and stores the answer in *result* – all three of which are safe, zero page locations. Notice that we've cleared Carry initially.

Once the code's assembled – at *add*, set to &900 – we input the values for *first* and *second* and poke them into memory (lines 200 to 230). We then call our assembled machine code with line 240 and print out the sum, complete with answer, with line 250. Notice how we use *?result* to recover our result from memory location &72.

Following what's going on here should give you no particular problem. Try it out with simple sums such as:

```
2+3
45+23
36+78
```

So long as the answer to the sum doesn't exceed 256 the answer will be correct. However, go past this and you're in trouble, as you'll see from trying:

```
255+2
```

You'll get the answer 1: Since we've exceeded the confines of the byte, we wrap round again.

Although in cases like this we can spot what's going on, in more complex machine code programs we have to anticipate these problems and take avoiding action.

This is what Carry is for: If the result of our ADC instruction takes us over our 255 limit this flag is automatically set to warn us of problems. If, however, all's clear, the Carry flag itself is cleared.

Either way, the Zero flag is changed to reflect whether we're in limits or not.

Armed with this knowledge we can use our BCS and BCC instructions to take remedial action when required.

Program II shows one way of doing this. What I'm doing is to use a zero-page location – called, appropriately, *carry* – to reflect the state of our

```
 10 REM PROGRAM II
 20 first=&70
 30 second=&71
 40 result=&72
 50 carry=&73
 60 add=&900
 70 REM *** Machine Code core ***
 80 FOR pass%=0 TO 3 STEP 3
 90 P%=add
100 [
110 OPT pass%
120 LDA # 0
130 STA carry
140 CLC
150 LDA first
160 ADC second
170 STA result
180 BCC noerror
190 LDA #1
200 STA carry
210 .noerror RTS
220 ]
230 NEXT pass%
240 REM *** Basic surround ***
250 REPEAT
260 REPEAT:INPUT '"First Number",nu
mber1%:UNTIL number1%>-1 AND number1%
<256
270 ?first=number1%
280 REPEAT:INPUT '"Second Number",n
umber2%:UNTIL number2%>-1 AND number2
%<256
290 ?second=number2%
300 CALL add
310 PRINT 'number1%;" + ";number2%;
" = ";?result+256*?carry'
320 UNTIL 0
```

Program II

Carry flag. First of all we set it to zero with:

```
LDA #0
STA carry
```

Having done that we do our sum as before:

```
LDA first
ADC second
STA result
```

It's the next lines that are interesting. We know that ADC affects the Carry flag. If we've not over-spilled our byte, Carry will be clear and no corrective action is required. We cater for this with the next instruction:

```
BCC noerror
```

This simply takes us to our RTS, which is fine – we've done all we need to do. In addition, since we haven't done anything to change it since we made it zero, *carry* holds the same value as the true Carry flag – zero.

On the other hand, if we have gone over 255, our answer – held in *result* – is going to be 256 out. Fortunately, Carry is set to warn us. In this case we do not take the branch at the BCC but continue with the next instructions:

```
LDA #1
STA carry
```

This alters the contents *carry* to reflect the new value of our Carry flag – one. The next instruction then takes us to the final RTS.

When you think about it, our machine code routine gives the same number in *result* as that of Program I. The difference is that this time we also store some additional information in *carry* – whether the Carry flag is set or not.

Our Basic "tail" then takes care of things. Line 310 prints out our sum, calculating our answer as:

```
?result+256*?carry
```

Think about it:

When Carry is clear (so *carry* contains zero), our answer is simply the value in *result*. The formula above boils down to:

```
?result+256*0
```

which gives us what we require.

When Carry is set (so *carry* holds 1), our answer needs 256 adding to it. Again, the formula above takes care of things, becoming

```
?result+256
```

And that's all there is to it. In practice we wouldn't leave our corrective routines to Basic, but write them in machine code. The principle's the same though: By watching Carry, we can take appropriate action.


I'd also better make explicit something that I've taken for granted: Load and store instructions don't affect the Carry flag.

It probably hasn't occurred to you that they might, but now I've mentioned the possibility, have a look at the two routines and see how they would be affected. Then breathe a sigh of relief that you can ignore the problem!

● *We'll look at more elegant solutions to large numbers later in the series. Before that though, in next month's article we'll take a look at subtraction in machine code. If you'd like to play around with ADC in the meantime, you might like to know that ADC# allows you to add "constants" in immediate mode . . .*

...TITION..COMPETITION..COMPE

Over £500 worth of software to be WON



...in this easy to enter competition.

Thunderstruck is Audiogenic's latest release – an arcade adventure with the accent on the adventure! Our hero is SPRECO, the Space Refuse Collector, who has been caught in a freak timestorm and shipwrecked in a strange and eerie castle. To escape he must interact with eight weird characters, and this is where YOU come in.

Your task is to choose famous names (real or fictitious) to play the part of each of these eight characters. For example, you might think that Freddie Mercury would make a good Queen.

Jot down your eight ideas, cut out or photocopy the entry form and send it to the address below to arrive no later than December 31. You could be a winner!

This is what you could win:

1ST PRIZE

A complete set of Audiogenic titles worth over £100: Psycastria, Last of the Free, Bug Eyes II, Genesis Project/International Megasports, Swift spreadsheet, Contraption, Caveman Capers, Frankenstein 2000, Complete BBC Compilation and Thunderstruck.

RUNNERS UP PRIZES

20 copies of The Complete BBC Compilation which contains SEVEN top games on two cassettes and normally sells for £19.95.

King _____

Queen _____

Wizard _____

Craftsman _____

Maiden _____

Dog _____

Guard _____

Revolting hag _____

Name _____

Address _____

_____

_____

_____

Postcode _____ Age _____

Post to: ***Thunderstruck Competition, The Micro User, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 5NY.***



Breaking through the dense cloud cover you were relieved to see a dazzling white snowfield spread below you. Desperately preparing for a crash landing, you were distracted by a glint of sunlight on glass – a building! Could THIS be the lost civilisation?

Your attention however was drawn back to the ground hurtling towards you . . .

From the producers of THE GRAPHIC ADVENTURE CREATOR

AVAILABLE FROM ALL LEADING RETAILERS or direct from: INCENTIVE SOFTWARE LTD., 2 Minerva House, Calleva Park, Aldermaston, Berkshire RG7 4QW. Telephone: (07356) 77288.

BARCLAYCARD VISA — PRIORITY ORDER FORM — ACCESS

Please rush me for my:
Spectrum ☐ BBC B ☐ Commodore 64 ☐ Amstrad CPC ☐

WINTER WONDERLAND	£7.95 ☐
Apache Gold (except BBC)	£7.95 ☐
Graphic Adventure Creator	Tape £22.95 ☐ / Disc £27.95 ☐

I enclose cheque/PO or please accept my credit card No. _____

Name _____

Address _____

_____

POOLSWINNER

THE ULTIMATE POOLS PREDICTION PROGRAM



Boxed, with detailed instruction booklet

- **MASSIVE DATABASE** Poolswinner is a sophisticated Pools prediction aid. It comes complete with the largest database available – 22000 matches over 10 years. The database updates automatically as results come in.
- **PREDICTS** Not just SCOREDRAWS, but AWAYS, HOMES and NO SCORES.
- **SUCCESSFUL** SELEC guarantee that Poolswinner performs significantly better than chance.
- **ADAPTABLE** Probabilities are given on every fixture – choose as many selections as you need for your bet. The precise prediction formula can be set by the user – you can develop and test your own unique method.
- **SIMPLE DATA ENTRY** All team names are in the program. Simply type in the reference numbers from the screen. Or use FIXGEN to produce fixture list automatically (see below).
- **DISC/MICRODRIVE COMPATIBLE** Tapes supplied with conversion instructions.
- **PRINTER SUPPORT** Full hard copy printout of data if you have a printer.

PRICE £15.00 (all inclusive)

NOW AVAILABLE

FIXGEN 86/7 AT LAST: No more struggling for hours to get the fixture list into the computer. FIXGEN has been programmed with all English and Scottish fixtures for 1986/7. Simply type in the date, and the full fixture list is generated in seconds. Fully compatible with Poolswinner. Yearly updates available.

POOLSWINNER with FIXGEN £16.50 (for both)



COURSEWINNER V3

THE PUNTERS COMPUTER PROGRAM

NOT JUST A TIPSTER PROGRAM, Coursewinner V3 can be used by experts and occasional punters alike. You can develop and test your own unique winning system by adjusting the analysis formula, or use the program in simple mode. Coursewinner V3 uses statistical analysis of major factors including past form, speed ratings, course statistics, prize money, weight, going, trainer and jockey form etc, etc. It outputs most likely winners, good long odds bets, forecasts, tricasts etc. The database includes vital course statistics for all British courses. You can update the database – never goes out of date.

PRICE £15.00 (all inclusive) includes Flat AND National Hunt versions.

ALL PROGRAMS AVAILABLE FOR: AMSTRAD CPCs, AMSTRAD PCWs (ADD £3.00), All BBCs, All SPECTRUMS, COMMODORE 64/128, ATARI (48K+), SINCLAIR QL.
Supplied on tape (simple conversion to disc) – except PCW (on 3" disc) and QL (on microdrive)

Send Cheques/POs for return of post service to . . .

VISA phone 24 hrs

selec SOFTWARE

phone 24 hrs

37 COUNCILLOR LANE, CHEADLE, CHESHIRE. ☎ 061-428 7425

(Send for full list of our software)

LOW COST C.A.D.

ATTENTION ALL ELECTRONICS CIRCUIT DESIGNERS !!

IBM PC (and compatibles), BBC MODEL B, B+ and MASTER, AMSTRAD CPC and SPECTRUM 48K

ANALYSER I and II compute the A.C. FREQUENCY RESPONSE of linear (analogue) circuits. GAIN and PHASE, INPUT IMPEDANCE, OUTPUT IMPEDANCE and GROUP DELAY (except Spectrum version) are calculated over any frequency range required. The programs are in use regularly for frequencies between 0.1Hz to 1.2GHz. The effects on performance of MODIFICATIONS to both circuit and component values can be speedily evaluated.
Circuits containing any combination of RESISTORS, CAPACITORS, INDUCTORS, TRANSFORMERS, BIPOLAR AND FIELD EFFECT TRANSISTORS and OPERATIONAL AMPLIFIERS can be simulared – up to 60 nodes and 180 components (IBM version).
Ideal for the analysis of ACTIVE and PASSIVE FILTER CIRCUITS, AUDIO AMPLIFIERS, LOUDSPEAKER CROSS-OVER NETWORKS, WIDE-BAND AMPLIFIERS, TUNED R.F. AMPLIFIERS, AERIAL MATCHING NETWORKS, TV I.F. and CHROMA FILTER CIRCUITS, LINEAR INTEGRATED CIRCUITS etc.
STABILITY CRITERIA AND OSCILLATOR CIRCUITS can be evaluated by "breaking the loop".
Tabular output on Analyser I. Full graphical output, increased circuit size and active component library facilities on Analyser II.
Check out your new designs in minutes rather than days.
ANALYSER can greatly reduce or even eliminate the need to breadboard new designs.


Used by INDUSTRIAL, GOVERNMENT and UNIVERSITY R & D DEPARTMENTS worldwide. IDEAL FOR TRAINING COURSES. VERY EASY TO USE. Prices from **£20 to £195.**

LOW COST COMPUTER DRAUGHTING

ON THE BBC MODEL B, B+ and MASTER

DRAWER I enables quality drawings to be created and modified, quickly, easily and with the minimum of hardware. All of the major program elements are written in machine code giving exceptional speed of operation.

- Rubber Banding for drawing lines.
- Solid or Dotted line types.
- Circles, Arcs and partial or complete Ellipses.
- Vertical or Horizontal Text.
- Pan and Zoom.
- Merging of drawings and library symbols from disc.
- Up to 20,000 lines on a drawing.
- Snap to a user defined grid.
- Absolute or Relative cursor co-ordinates displayed on screen.
- Input from analogue joystick, mouse or trackerball.
- Output to standard dot matrix printer or plotter.
- Price from £45 excl. VAT.



Minimum Hardware Required: BBC Model B. Single or Dual 5.25" Disc Drive – 40 or 80 track. T.V. or monitor. Games joystick, Mouse or Trackerball. Dot matrix Printer (Epson 80 series or Epson compatible – BBC Default Mode).
Full AFTER SALES SERVICE with TELEPHONE QUERY HOT LINE and FREE update service.

For illustrated leaflets and ordering information please write or phone:

NUMBER ONE SYSTEMS LIMITED
Ref: MU. Crown Street, St. Ives, Huntingdon, Cambs PE17 4EB. Tel: 0480 61778.

SANTA'S SLEIGH



By ANDREW WAITE

CHRISTMAS is here once more and Santa is getting ready to deliver all his presents. The sleigh is waiting and all he needs to do is load up the goodies.

Rudolf has been put out to pasture and the sleigh is now gas powered. It's a bit of a fuel guzzler so take it easy and keep an eye on the fuel gauge.

The presents have been stolen and scattered throughout a warehouse, so you guide Santa round on his sleigh and pick them all up.

When you have collected all the presents in one room you can move on to the next through the exit at the bottom of the screen.

This is by no means an easy task since many dangers lurk deep within the warehouse.

Watch out for the large spider descending on its thread and dodge the Christmas crackers bouncing up and down. ■

Controls
Return = thrust
Z = left
X = right

VARIABLES

stage%	Screen.
live%	Number of lives left.
score%	Score.
FUEL%	Amount of fuel left.
walk%	Whether you have landed.
X%,Y%	Santa's coordinates.
HI%()	High scores.
HI$()	High score names.

Full listing starts on Page 135

Opening up the colour floodgates

STEPHEN AUSTIN outlines Flood Fill, a machine code program that offers countless new colour options

EVER felt the need to colour in an irregular shape, but found the task of using the triangle fill routines too daunting? Or have you ever felt the need for more colours?

Well here's the answer to all your prayers – a fast machine code colour flood fill routine that will fill any shape with any of the normal colours, as well as a variety of new ones.

It works with both the B and B+ in the non-shadow mode, but not on the Master – no worry to the fortunate few since the Master's MOS has its own flood fill routines.

The flood routine can be used in all of the graphics modes – that is Modes 0, 1, 2, 4 and 5. It can also be freely used in any of your Basic or machine code programs.

The new colours are obtained by mixing the normal colours in a variety of ways to create different shades and colouring effects.

The two colours to be mixed are stored in the zero page locations &8C and &8D using the indirection operators. For example, if *C1* and *C2* are the two colours to be mixed they are stored in memory as follows:

```
?&8C=C1:?&8D=C2
```

The way in which the colours are mixed is determined by a third byte stored in &8E. If this byte is *pattern*, for example, it is stored with:

```
?&8E=pattern
```

A region is filled using the statement:

```
PLOT K,X,Y
```

where *X* and *Y* are the coordinates of any point within the region to be filled. *K* is a number between 96 and 103 – &60-&67. The PLOT numbers 96 to 103 are not used by the operating system, so they are sent to the VDU extension vector at &226-&227.

The PLOT options are just the same as the other PLOT numbers for drawing lines – 0 to 7 – and for filling triangles – 80 to 87.

The fill routine intercepts this vector so that the normally unused PLOT commands can be channelled to the fill routine.

Therefore the address stored in this vector must be altered to point to the start of the fill routine – &1200. Thus before it is used the vector must be changed as follows:

```
?&226=0:?&227=&12
```

Note the vector need only be changed once – unless Break is pressed – and so for handiness this statement is best placed at the start of any program using the flood routine.

Here's a description of how the two colours are mixed to obtain new shades – the byte which refers to the way in which the colours are mixed is referred to as *pattern:*

If *pattern* = 0 the two colours are mixed by placing horizontal lines of each colour on top of each other – Figure Ia.

If *pattern* = 1 the pixels of the same colour are placed alternately next to each other dithered – Figure Ib.

If *pattern* = 2 the colours are mixed by dithering, but this time the pixels are grouped in pairs of the same colour – Figure Ic.

If *pattern* = 3 the colours are mixed by dithering, this time with groups of four identical pixels – Figure Id.

If 64 is added to *pattern* then in each of the above the first line is all one colour and the second contains the corresponding pattern giving cross-hatching – Figures IIa to IId.

If 128 is added to *pattern* vertical lines of each colour are placed next to each other – Figures IIIa to IIId.

If both 64 and 128 are added only the effect for +64 operates.

The program works on the principle that every pixel in the region to be filled has the same colour. This is the background colour. The borders of the region to be filled are pixels which have non-background colours – or the edge of the screen.

When the routine is called by the appropriate PLOT statement, before control is actually passed to the routine, the OS converts the X and Y coordinates into internal coordinates with the graphics origin and relative plots taken into account.

Internal coordinates are the coordinates that the computer itself uses for graphics. External coordinates are just the normal coordinates – that is 0=<X=<1279 and 0=<Y=<1023 – expressed in terms of pixels. See Figure IV for the internal coordinates.

The OS stores the internal coordinates of the chosen point in locations &320-&323. The fill routine retrieves these coordinates so that it can find the colour of this point using Osword 9. If




Figure Ia: Pattern = 0




Figure Ib: Pattern = 1




Figure Ic: Pattern = 2




Figure Id: Pattern = 3

the colour returned is the same as the background colour these coordinates are stored in an area of workspace hereafter referred to as the coordinate stack.

The stack is of the LIFO type – Last In, First Out. This means that if two numbers were put on this stack the second number would have to be taken off the stack before the first number could be removed.


The algorithm for the fill routine is fairly simple in theory. Firstly the coordinate from the PLOT statement is stored on the coordinate stack and the colour patterns are worked out from the two colours and the pattern type.

The top coordinate is pulled off the coordinate stack. The horizontal line containing this coordinate is then filled with the colour pattern up to the first non-background coloured pixel on both the left side and the right side of this point.

The coordinates of these two points are then stored in *lx* and *rx*. Next the lines above and below the current line are scanned for groups of adjacent background coloured pixels.

The coordinate of the first pixel on the left of each of these groups is then stored on the top of the coordinate stack. Next the program loops back to take another coordinate off the coordinate stack.

This line is then filled and the lines above and below it are scanned and so on. The routine ends when there are no coordinates left on the coordinate stack. This is when the whole region has been completely filled.






Figure IIa: Pattern = 64




Figure IIIa: Pattern = 128




Figure IIb: Pattern = 65




Figure IIIb: Pattern = 129




Figure IIc: Pattern = 66




Figure IIIc: Pattern = 130




Figure IId: Pattern = 67




Figure IIId: Pattern = 131

Type in Program I. This is the assembly language source which generates the machine code fill routine. It is best to type this program in and then save it immediately because any mistakes could prove fatal.

It is not necessary, however, to type in all the comments at the end of each line after the / character. As the model B+ has different look-up tables line 100 sets a variable *table* to ensure the correct table is used on both B or B+.

Once the program has been saved RUN it with PAGE at &1900.

The fill routine is under 1k in length and assembles to &1200 – see below if you want to change this address. Now that the machine code has been generated it is necessary to save it. This is done with the command:

```
*SAVE "FILL" 1200 15ED
```

Whenever the fill routine is to be used the machine code program must be loaded with:

```
*LOAD "FILL"
```

Next the statement:

```
?&226=0:?&227=&12
```

must be inserted at the beginning of your program to ensure the fill routine traps all unrecognised PLOT options.

Finally the two colours and the

From Page 113

pattern type must be stored in memory using:

```
?&8C=col1:?&8D=col2:?&8E=pattern
```

Now the routine itself can be called with:

```
PLOT K,X,Y
```

Program II is a demonstration program that draws a picture of a house and uses the flood fill routine to colour in the picture.

It is necessary to load in the machine code routine *FILL* before running this program. PROCfill is the procedure used to fill the shapes, and it can be used in your own programs.

It has five parameters. The first two are the two colours to be mixed, the third parameter is the pattern type and the last two are the coordinates of a point in the shape to be filled. Note that the VDU vector – &226-&227 – is changed at the start of the program.

The machine code routine is assembled at location &1200 because this is handy for disc users. However this address can be easily changed to any other suitable location by changing the value of the variable *LOC* in Program I – line 90.

Mode	Internal coordinates	
	x	y
0	0-639	0-255
1	0-319	0-255
2	0-159	0-255
4	0-319	0-255
5	0-159	0-255

Figure IV: Internal coordinates

For cassette users the start address could be changed to &A00 only if the shapes to be filled are not very complex because otherwise the coordinate stack would overwrite the flood fill routine.

Other options are to increase the value of PAGE from &E00 on cassette machines to &1200 and then change the value of *LOC* to &E00. Alternatively the value of HIMEM could be lowered by &1000 bytes and the value of *LOC* then changed to that of the resulting value of HIMEM.

The location of the coordinate stack is &900 because this area is only used for file operations on cassette machines or for extended ENVELOPEs – 5 to 16. This address can also be moved by changing the value of the variable *STACKLOC* in line 90 of Program I.

Finally the range of patterns can be extended by adding entries to the data table at the end of Program I – lines 6430 and 6440. Each entry in this table is made up of a two byte sequence.

If another pair of numbers was added to this table the effect could be viewed by filling in a shape with *pattern* set to 4. If more entries than this are added increase the value of *pattern* accordingly.

Try experimenting by adding different numbers to this data table. Some very interesting results can be obtained. ■

Full listing starts on Page 141

REPLAY

The Acclaimed Utility for Tape to Disc Transfer

Vine Micros

"REPLAY is a pretty marvellous device, more than a toy for those who have to document software, very useful if you can only buy a tape version of a program (it doesn't matter what nooks and crannies the code is packed into) and a good opportunity to have fun with the screens of your choice. A liberating piece of software and highly recommended".
'Software Reviews', A&B Computing, Dec. '85

"REPLAY is the current state-of-the-art answer to tape to disc transfer, available for the BBC B (and B+). This consists of a ROM and some hardware which must be attached inside the computer. Once installed it will cope with virtually any program you care to put to the test".
'First Byte', ACORN USER, May, '86.

"Many facilities are advertised to enable BBC micro users to copy or back-up protected programs and transfer them from tape to disc. While some break the protection in the process and thus assist software piracy, others are more responsible, using techniques which retain the protection. Vine Micros, who already leads the field in the latter group with the T.D.ROM, now supplies REPLAY".
'ROM Roundup', MICRO USER, July, '86.

TAPE TO DISC TRANSFER – MID-PLAY 'STOP AND SAVE' - MID-GAME PAUSE FACILITY
MOST DISC TO DISC TRANSFER - DISPLAYS A 'STOPPED' SCREEN READY FOR PRINTING.
Easy to fit with no soldering, uses one sideways ROM socket with three simple connections on to computer.
REPLAY must be matched to the DFS in use: R8271 - Acorn 8271, Pace and Watford S/D: R8272 - U.D.M. DFS: R1770 - Opus 3.45 and Solidisk Issue 1 board: R1770A - Acorn 1770 DFS and ADFS, also Solidisk Issue 2 board: R1770B+ - BBC B+: R1770C - Opus Challenger: R1770W - Watford DDFS: R2791 Opus 3.15: R2793 - Opus 3.35: R8877 - Cumana QFS: (Acorn 'Master' in preparation).
Price **£35.00** inclusive, with full instructions for installation and use.
Further details and reviews available.

ELECTRON & BBC MICRO USER SHOW
See us on Stand 40 at the November Micro User Show

The MATRIX ROM
BBC 'B', B+ and ELECTRON
This ROM will be of interest to Engineers, Scientists and Mathematicians. Using BASIC commands it is an indispensable tool for performing matrix operations and the solving of linear simultaneous equations. The MATRIX ROM was written with the co-operation of the Civil Engineering Dept., University of Southampton.
Price: **£36.00** (plus VAT) includes Manual. Quantity discount offered.
Further details can be provided on request.

"B+ to B" CONVERSION KIT
This addition will enable BBC 'B' tapes to be used on the B+ computer. (requires 1.20 O.S. ROM) Price: £21.95 with O.S. 1.20 ROM.
£15.95 without ROM (both prices include VAT & Post).

The ADDCOMM ROM
BBC 'B', B+ and ELECTRON.
A Toolkit/Graphics utility adding 40 extra BASIC commands. Brilliant programming and value for money. 16-page brochure and reviews sent on request. Price: **£28.00** inclusive.

Ready now
ACORN MASTER PRODUCTS
O.S. Overlay ROM Board
An internal board taking three ROMs which can 'overlay' any of the eight ROMs already built-in.
(Computer must have a socketed 1Mbit ROM.)
Price: **£19.95** (inclusive of VAT and Post.)

WRITE-PROTECT SWITCH
Acorn 'Master'.
A small module which plugs into the computer and offers write-protection to the sideways RAM banks. Price: **£8.95** inclusive of VAT and Post).

VINE MICROS, MARSHBOROUGH, SANDWICH, KENT CT13 0PG. (Tel: 0304 812276)
Or through your local Dealer.

BARCLAYCARD VISA

Your Drive and our Technology make a great team



Now you don't have to buy another disc drive to enjoy all the benefits of the superb Opus Challenger plug-in disc system.

For just £99.95 you can now convert any single disc drive into a powerful 3-in-1 Challenger system with all the advantages of a lightning-fast RAM disc and advanced double density disc interface. No matter what make of drive you own, our special upgrade package will boost its capacity and performance.

RAM DISC SPEED

For the first time our 256K solid state RAM disc is available for use with any disc drive. Up to 20 times faster than a conventional floppy, it allows you to race through work your current drive labours over. You'll create your own unique twin-drive system in a matter of minutes.

DOUBLE DENSITY INTERFACE

The Opus double density disc interface is already a best-seller and it's suitable for use with both 40 and 80 track drives, single or double-sided. It's even compatible with the Master and Master Compact computers. You'll gain an immediate 80% increase in data storage capacity over the standard Acorn DFS and, because our DDOS plugs directly into your micro, there are no complicated interface connections to worry about. You can leave your DFS in place, guaranteeing 100% compatibility.

LIMITED OFFER

This remarkable offer gives disc drive owners the unique opportunity to catch-up with the latest in disc system technology for a fraction of the cost. But hurry, our special offer is available for a limited period only.

☎ **0737 65080**

Of course, if you've yet to choose a disc drive, our complete Challenger system with built-in 5¼" double-sided 40/80 track drive is also available. Choose our 256K RAM version for just £179.95 or 512K RAM option at only £199.95.

Call Opus on 0737 65080 or simply post the coupon below. Our price even includes VAT and FREE guaranteed 72-hour delivery. Generous education and dealer discounts available.

To: Opus Supplies Limited, 55 Ormside Way, Holmethorpe Industrial Estate, Redhill, Surrey RH1 2LW

Please rush me the following: (PRICES INCLUDE VAT AND CARRIAGE)

_____ Challenger Upgrade System(s) at £99.95 each

_____ Complete Challenger Disc System(s) – 256K RAM version at £179.95 each

_____ Complete Challenger Disc System(s) – 512K RAM version at £199.95 each

I enclose a cheque for £_____ or please debit my credit card account with the amount of £_____

My Access ☐ Visa ☐ no. is ☐☐☐☐☐☐☐☐☐☐☐☐☐☐☐☐

NAME _____

ADDRESS _____

_____

TELEPHONE _____ MU

Opus.

Controlling the climate

MIKE COOK adds a hygrometer to the Body Build weather station. But it does have other uses . . .

OUR brand new Editor bounced across the room and said, "What's it to be this month then?" "A computerised hygrometer", I replied. He looked a little puzzled and asked why. "Because," I said, "I am a humid being." "Oh!" he said mysteriously, "so what the previous Editor told me about you is true." And he turned away wondering if he had made the right decision in accepting the job.

For those none the wiser for the anecdote, let me say that a hygrometer is used to measure humidity – the amount of water in the air. It is not very useful to measure the absolute amount of water vapour as this changes with temperature and pressure so we normally deal with relative humidity.

This is a measure of the amount of water vapour in the air relative to how much vapour it can take. As the total amount of water vapour depends on temperature, a sudden drop in temperature can force the relative humidity to 100 per cent and beyond. When this happens moisture is condensed out of the air as dew or fog.

Why should anyone want to monitor the RH? Well those of you who have an interest in weather measurements might like to add this to the Body Build anemometer pressure gauge and wind vane covered in the June 1985 and October 1986 issues of *The Micro User*.

But interest in this device is not restricted to that as it can be used to control and monitor air conditioning systems, humidifiers and greenhouse climate controllers. It can even be used to monitor tumble dryers to detect when the load is dry.

Traditionally electronic humidity sensors have been very expensive but now Mullard has come up with a sensor that is reasonably priced and designed to work over a range of RH between 10 and 90 per cent. While it is not a precision transducer it will perform to an accuracy of 5 per cent under worst case conditions and as these do not prevail most of the time it will be even more accurate.

Mullard is naturally cagey about exactly how the sensor works but basically it is a capacitive sensor. If you remember basic theory you will know that a capacitor is simply a pair of conducting plates separated by some insulating material known as a dielectric. It stores charge and the amount it can store is known as its capacitance, which depends on three things.

The first is the area of the plates – the more area the more charge. Secondly the closer the plates are together the more charge can be stored and finally the type of dielectric also affects the amount of charge. The measure of how a material effects capacitance is known as the material's dielectric constant.

What Mullard has done is to produce a membrane whose dielectric constant changes with the RH. As a warning is given in the data sheets that some solvents such as acetone will attack the membrane, it is a fair guess that it is some sort of plastic. To make the humidity transducer, both sides of the membrane are covered with gold to form a capacitor and the whole unit is mounted in a perforated plastic case. Thus the transducer is easy to handle and to build into a humidity sensor.

So basically the sensor will change capacitance as the RH changes. The capacitance and the change, however, are quite small – it has a value of 112pF with 10 per cent RH rising to 144pF at 90 per cent RH. So our problem is to convert this capacitance into something we can measure with our computer.

We will do this by incorporating the transducer into an oscillator. However, with such a small capacitance the oscillator will be running much too fast for accurate measurements and temperature changes would also affect the accuracy.

To overcome this we have two synchronised oscillators, one with the transducer and the other with variable capacitor trimmer. If we adjust the trimmer to be the same as the standing capacitance of the transducer and then compare the two output pulses, the difference in the two will be proportional to the RH. This is shown in Figure I.

We can simply convert this pulse into a measurable voltage by smoothing it with a resistor and capacitor and then measure it with the computer's analog input port, or more accurately with the Body Build digital voltmeter described in the April 1985 issue of *The Micro User*.

So we need to consider what oscillator to use. An oscillator is a circuit that strives to be in one condition but only achieves it when it reaches a state of "wanting to be in its original condition".

A perfect example of this was given to me by my youngest son, who's particularly fond of dummies. One day while sucking his blue dummy he




Figure I: The block diagram of the hygrometer

spotted his yellow one, which proved such an attraction that he swapped it for the one he was sucking. However, now he could see his blue one and that looked nice too – so he removed the yellow one and replaced it with the blue one. This cycle continued for some time until he was distracted by my laughter.

Figure II shows the basic form of oscillator we will use. It consists of two inverter gates so called because the output is the inverse of the input. If point B is high then point C will be low and point A will also be low. But as time passes the high voltage at point B charges up the capacitor through the resistor until point A goes high.

This will cause point B to go low as they are connected through an inverter and point C will go high. As time passes the capacitor will discharge through the resistor until point A is low, driving point B high.

This cycle repeats and we have an oscillator. The time taken for the oscillator to change states is determined by the capacitor and the resistor.

Figure III shows the full circuit of the humidity monitor. You will see there are two oscillators made from gates on the same integrated circuit. This ensures that any changes in frequency due to temperature variations will occur equally to both oscillators. The




Figure II: The oscillator

THE BEEB BODY BUILDING COURSE

oscillator with the humidity transducer is gated by the other to ensure that the two are synchronised.

The output from the two oscillators is fed into a second integrated circuit where the exclusive OR gate produces an output only when the two oscillator outputs differ. As there are four of these gates in one package we drive them all in parallel.

This uses up all the gates as CMOS should never have unconnected inputs. It also makes a nice low impedence source to drive the next stage. This is simply a smoothing circuit to average the pulse and give a steady voltage that can be measured by the computer's analog input port.

All the parts for the humidity sensor circuit are available as Body Build pack No.37. Note that the sensor alone can be purchased. You will find the order form on Page 118.

The only snag with the humidity transducer is that it has a non-linear response. This means that there is no simple relationship between relative humidity and capacitance. To compensate for this it is traditional to use a linearising circuit but these are difficult to set up and not very accurate.

Instead the linearisation takes place in software and can be tailor-made to your sensor and so will result in quite an accurate measurement.

The data sheet for the sensor gives a curve of relative humidity against capacitance, summarised in Table I. Using this I substituted several accurately measured fixed capacitors for the humidity sensor and noted the readings from the analog input port of the computer.

I could then draw a curve of capacitance against computer reading and finally produce a list of reading and humidity to use in the linearising software.

Alternatively the list may be produced by noting the reading with the humidity sensor fitted and then measuring the humidity by some conventional means, the most common of which is a wet and dry bulb thermometer. A mixture of these two techniques may be used if you prefer.

To make it easy for you to calibrate your system, if you order the kit of parts you will get a calibrating capacitor individually measured with a note of what relative humidity it represents. Then all you have to do is substitute this capacitor for the sensor and adjust the trimmer until the correct humidity is indicated.

Program I is the routine to read the sensor and the DATA statements contain the calibration list we have just been talking about. The first number is the quantity of reading/humidity pairs we have in the other data statements. These pairs are read into two arrays then the value on the analog input port is averaged over five readings. This number is easily changed by line 150.

Having got the reading we must now see what humidity level it corresponds




Figure III: The hygrometer

Capacitance	Relative humidity
112pF	10%
115pF	20%
118pF	30%
121pF	40%
124pF	50%
128pF	60%
132pF	70%
137pF	80%
144pF	90%

Table I

From Page 117

to. The table of readings is then searched until we find a value in excess of our reading, so the reading we have is between the last two array entries looked at.

Line 290 works out the fractional distance our measurement is between the two table entries – for instance it may be half way. Then line 300 takes this fraction and applies it to the two corresponding humidity values.

In other words the actual humidity is half way between the two table entries. This technique is known as interpolating between table entries and gives a much more accurate reading than just relying on the table alone. The more table entries there are the more accurate this becomes.

● *In practice it takes the sensor about five minutes to respond fully to sudden changes in humidity but in most situations this is quite acceptable. So now, in the humid spirit, I can wish you a very merry Christmas.*

```
  10 MODE7
  20 PRINT TAB(0,4)"THE BEEB BODY BU
ILD COURSE"
  30 PRINT"MICRO USER DEC 1986"
  40 PRINT"By Mike Cook"
  50 PRINT"Humidity Sensor"
  60 READ N%
  70 DIM RD%(N%+1),HUM%(N%+1)
  80 FOR A%=1 TO N%
  90 READ RD%(A%),HUM%(A%)
 100 NEXT
 110 RD%(N%+1)=2000
 120 *FX16,1
 130 REPEAT
 140 ACC%=0
 150 T%=5
 160 FOR A%=1 TO T%
 170 ACC%=ACC%+(ADVAL(1) DIV 1023)
 180 TIME=0
 190 REPEAT:UNTIL TIME>10
 200 NEXT
 210 R=ACC%/T%
 220 REM Now search for value
 230 PRINT TAB(0,14);"Relative Humid
ity is ";
 240 S%=0
 250 REPEAT
 260 S%=S%+1
 270 UNTIL RD%(S%)>R
 280 IF S%=1 OR S%>N% THEN PRINT "OU
T OF RANGE":GOTO 320
 290 F=(R-RD%(S%-1))/(RD%(S%)-RD%(S%
-1))
 300 RH=HUM%(S%-1)+((HUM%(S%)-HUM%(S
%-1))*F)
 310 PRINT INT(RH+0.5);" %"
 320 UNTIL FALSE
 330 DATA 9
 340 DATA 585,10,600,20,618,30,636,4
0
 350 DATA 650,50,668,60,680,70,684,8
0
 360 DATA 700,90
```

Program I

Sports Clubs! Leisure Centres! Colleges! Schools! Social Clubs! Youth Clubs!
Sports Halls! Local Groups! Pubs! Golf Clubs! Country Clubs!
For all your future Competitions... at last a full ELECTRONIC SCOREBOARD and RESULTS SERVICE on the BBC micro!!

TOURNAMENT MANAGER by Abico

- Live full-colour scoreboard for every game (just as in TV coverage of Snooker)
- Automatic movement of winners through each round
- Full display of tournament results and status, by round, on demand, with optional printing
- Play games and round in any order
- Up to 128 players, or named pairs, or teams, in up to 7 rounds. Automatic handling of byes
- Instant saving of entire tournament status to disk after every game, if required, or on demand, with ability to restore the 5 most recent saves (avoids impact of power failures etc).
- Easily customised for your Event's title, description, location, date, etc. and names of all entrants
- It even prints smart Certificates automatically at the end of the tournament, for all the top places (Epson codes)
- Child's play to use, but VERY effective and impressive to all your spectators!

Why not drive several screens, using coax splitters etc? A scoreboard in every corner! Already used like this to great acclaim in real snooker tournaments!
Tested on BBC model B with OS 1.20 and DFS 0.90
Complete package supplied on 40-track disk, with Guide. Use it again and again.
Incredible value at only £9.75 incl
Cheque, P.O. to: ABICO (M1), Willow House, Shepreth, Royston, Herts

BEEB BODY BUILDING PACKS ORDER FORM

Body Build Pack 37a: £25
- *Humidity sensor*
- *1 printed circuit board*
- *15 way D-Type connector*
- *2 yards of 3 core cable*
- *2 off 4001B CMOS ICs*
- *1 diode*
- *All resistors and capacitors*
- *Calibrating capacitor*

Body Build Pack 37b: £12
- *Humidity sensor*


Name .....
Address .....
.....
.....
Post code .....

Make cheques payable to Musbury Consultants and send to:-
8 Fairhill, Helmshore, Rossendale, Lancs. BB4 4JX.
Foreign orders add £3 if airmail delivery is required.

All prices include VAT and P&P

AMAZING LIGHTPEN OFFER

- Absolutely insensitive to ambient lighting
- Responds to different colours and screen intensities without adjustment to TV or monitor
- Red LED readout showing that data is available
- Switch for program control (allows pen to approach the screen without erroneous data capture).
- All features are program accessible.



4 Program cassettes with each lightpen
- BEEBPEN colour drawing program
- BRITAIN Geography Quiz
- User routines and introduction programs
- DEFINE Sprite Creator/Editor

Together worth £28.85 – free with lightpen
LIGHTPEN AND 4 CASSETTES ONLY £25.00 inc VAT & P&P
Please send your cheque/P.O./Access No. for £25 to:
Dept. MU
Datapen Microtechnology Limited
Kingsclere Road, Overton, Hants RG25 3JB
Telephone: 0256 770488
More software available: SAE for further details

MEGABYTE MIRACLES



ONLY £109.95
1 MEGABYTE SINGLE DRIVE
5¼" double-sided 80/40 track switchable disc drive. Formatted capacity with DDOS 720K

ONLY £209.95
2 MEGABYTE DUAL DRIVE
5¼" double-sided 80/40 track switchable disc drive. Formatted capacity with DDOS 1.4 Mb

Don't miss this amazing special offer from Opus — a choice of powerful 1 or 2 Megabyte disc drives at simply magic prices.

Choose our 1 Megabyte drive for just £109.95 or 2 Megabyte dual drive offering for only £209.95. Our prices even include VAT and FREE delivery! And, if you need an interface, add just £40 to the cost of either of our special offer drives and we'll supply you with one of the best double-density systems on the market — the Opus DDOS.

OPUS DRIVES

Our 5¼" drives are double-sided, 80/40 track hardware switchable models representing the very latest in disc drive technology and offering superb performance. They feature reliable direct drive mechanisms, low power consumption and fast track access times and they're backed by our no-quibble 2 year guarantee.

THE OPUS DDOS

Our highly acclaimed DDOS is probably the most advanced double-density disc interface available and if you choose one of our Megabyte bargains we'll slash £20 off the normal retail price — it's yours for just £40.

☎ 0737 65080

Our disc interface uses the same disc controller chip as the BBC B+ allowing you to run all leading software titles — just phone for our comprehensive listing.

The Opus DDOS handles tape to disc transfers, Format and Verify utilities are included on ROM and its powerful machine code operating system gives you up to 248 files — the perfect partner for your new Opus disc drive.

Simply post the coupon or call Opus now on **0737 65080** — we'll guarantee delivery within 72 hours. Our Megabyte Miracles offer is available for a limited period only, so call today to avoid disappointment.

Generous education and dealer discounts available.

To: Opus Supplies Limited, 55 Ormside Way, Holmethorpe Industrial Estate, Redhill, Surrey.
Please rush me the following: (PRICES INCLUDE VAT AND CARRIAGE)

_____ 1 Megabyte (unformatted) Sytems(s) at **£109.95** each
_____ 2 Megabyte (unformatted) System(s) at **£209.95** each
_____ Opus Double Density Disc Interface at **£40.00** each
(Only when purchased with drive) BBC

I enclose cheque for £_____ or please debit my credit card account with the amount of £_____

My Access ☐ Visa ☐ no. is: ☐☐☐☐☐☐☐☐☐☐☐☐☐☐☐☐

NAME _____

ADDRESS _____

_____

_____

TELEPHONE _____

Opus.

At last a machine code development system that *really* does outperform ADE

ADE+

Versions and prices

Recommended for Master Compact...
ADE+ MMU and 65C00 series assembler on disc (3.5" ADFS). 32K sideways RAM required.
£42.00 + vat

Recommended for BBC B, B+ ...
ADE+ MMU and 65C00 series assembler on 2 16K EPROMS with DFS 5.25" utilities disc.
£46.00 + vat

Recommended for Master 128, turbo..
ADE+ MMU and 65C00 series assembler on EPROM cartridge with 5.25" ADFS utility disc.
£49.00 + vat

ADE+

Features

- Runs on BBC B, B+, Master, Compact, ADFS, DFS, ANFS, NFS
- Full use of all available RAM
- Intelligent memory management unit (MMU)
- User switches on all main features
- Automatic search for macros on disc
- Assemble absolute or relocatable code
- Source program tokenised or full text
- REPEAT..UNTIL, WHILE..WEND etc. high level language constructs
- Macros nestable to any depth
- Excellent error diagnostics
- Link with libraries of assembled modules
- Full professional specification at home computing price!
- Print spooling system
- Links to symbolic debugger
- Editor and symbolic disassembler provided

ADE+

The Ultimate Assembly Language Development Tool.

ADE+ is a 65C00 series assembler system supporting all the mnemonics of the 65C12 used in the latest BBC microcomputers plus the additional 'Rockwell' instructions. ADE+ is fast, faster in fact than the in-built BASIC assembler and all rival products that we have tested. The assembler produces absolute code that can be *RUN or linker modules that can be merged with the output from other programs using the ADE+ linker. ADE+ is the only assembler available on the BBC to support a linker, normally a feature only found on minis and mainframes. The linker will even link the output from compilers with your assembly language programs. Full library support for both the linker and the assembler. Fast searching for unknown instructions in a random access macro library. ADE+ is built as a modular system with many exciting modules to add later such as a mouse based editor or a Z80 cross assembler! A print spooling system uses sideways RAM as a print buffer to eliminate waiting time: your listing runs off as a background job! Use the print spooler from BASIC or your own programs. ADE+ uses ALL available memory. With a second processor attached the IO processor spare memory is used as a buffer to reduce the amount of disc access. Up to 220K of memory is handled by ADE+'s intelligent memory management module. Use your own favourite editor or the one provided. Assemble from disc or memory. Full error diagnostics. Typeset manual with tutorial and reference guide. Supporting software disc. Available in most media formats to order, three formats as standard. (No requests for paper tape please!) Full utilities including librarians, converter for BBC BASIC etc. 32K of ROM software in the basic system. ADE+ must be *the* bargain of 1986/7!
Available now.

A comparison of three 65C12 assemblers

Feature	ADE+	BBC Basic	MACROM
Number of pseudo-ops	64	4	36
Use of all available RAM	Yes	No	No
Macros	Yes	No	Yes
Strong functions	Yes	Yes	No
True macro libraries	Yes	No	No
Relocatable output	Yes	No	No
Linker with libranes	Yes	No	No
High level constructs	Yes	Yes	No
Use any editor?	Yes	No	No
Number of error reports	39+warnings	3+BASIC errs	20
65C00 extended opcodes	All	65C12 only	65C12 only
Switch off 65C12 opcodes	Yes	No	No
ROM size	32K	16K	16K
Disassembler	Symbolic	No	Simple
Label restrictions	No	Yes	Yes

SYSTEM Software
12 Collegiate Crescent
Sheffield S10 2BA

Tel. (0742) 682321
Access and Barclaycard welcome.
Further information available

Sounding out... and in

Product: The Barry Box
Price: £79.95.
Supplier: BML Electronics, 24 Larch Grove, Bletchley, Milton Keynes, Bucks. MK2 2LL
Tel: 0908 640805.

THE Barry Box is a sound processor that allows you to record and play back any sound on your computer. It connects to the 1MHz bus and is driven from the auxiliary power socket. It comes complete with a microphone and operating software in rom but is not compatible with a second processor.

At this point let me declare an interest. I designed a sound sampler unit as part of the Body Building Course, published in *The Micro User* over the first three months of 1986.

Therefore I know exactly how these units behave, which is probably why I was given the Barry Box to review. Inevitably I found myself making comparisons between this unit and my own design but I hope I managed to be objective.

The construction is adequate if not terribly professional. It is housed in a small plastic box with two volume controls, for input and output level. There is one foot of ribbon cable which terminates in a connector and three miniature jack sockets on the front of the box give access to input signals (microphone and aux) and output. A fourth miniature jack socket is round the back supplying the power.

The Barry Box can be operated in two different modes, direct or program. In direct mode all commands are activated by pressing the appropriate keys.

Typing *BARRY will bring up a display of the various parameters the system is using, which include the buffer length and the sample time. These may be changed by using the cursor keys.

Other keys will directly activate an operation, for example the f1 function key will take the sample of a sound and f2 will output it.

The waveform may be displayed, saved and loaded to tape or disc as well as being transferred to sideways ram. There is also a screen dump for an Epson printer.

If you want to fill the buffer with a pure sound the tuning fork function will produce a pure sine wave. If you have a pure sound in the buffer then another function key will analyse it and report its frequency.

There is also some scope for sound treatment with two simple filter functions. In the manual these are referred to as "frequency smoothing" and "amplitude smoothing" but are actually different forms of low pass filtering.

The sample can also be played backwards and even edited in a limited sense by moving the buffer limits to eliminate the start of a sound.

The function key f4 analyses the samples in the sound buffer using a Fourier Transformation which displays

By MIKE COOK

each frequency component of the waveform. Therefore a pure sine wave should have only one component.

In practice there is some spreading due to the nature of signal and time window used. There was not nearly enough information in the manual to determine what was being done here.



The phrase that "frequency analysis is still somewhat a matter of trial and error" is a measure of the author's confidence in his algorithms. You are encouraged to "go ahead and experiment" to get the best results. This seems a little silly as you will never know if your results are correct or merely an artifact of the sampling parameters or transformation algorithm.

In program mode the operation of the Barry Box may be controlled from within your own Basic program. By means of poking into page zero memory locations and a series of star calls to the Barry Box rom you can perform all of the functions available in direct mode.

Both the Barry Box and my sound sampler used the same basic components, namely the Ferranti 8 bit A/D and D/A converters. This produces quite good quality sound – in fact the Barry Box produces less background noise than my sound sampling unit because it does not include the switching capacitance filters. These produce some high frequency signals that beat down to produce audio whistles at certain settings.

However, the pre- and post-digitisation filters in the Barry Box are barely adequate for the job and the use of ceramic capacitors in active filters is not very good practice. Also the Barry Box is not fully address decoded which means that when it is plugged into the 1MHz bus nothing else can be connected at the same time.

The ultimate limitation of the Barry Box lies not in the hardware itself but in the manual. It simply does not tell you enough about the hardware to do anything new with it.

For example it would have been extremely helpful if the address of the A/D and D/A converters were given along with the two lines of machine code needed to access them.

This would mean that you could use the Barry Box to perform all the real time processing tricks that my sound sampler can perform including echo, multiple echo, frequency speed up and slow down as well as harmonic scale sound outputs. The hardware is capable of this but you are not given any information of how to go about it.

In short what the Barry Box does, it does well. With its software on rom it is simple to operate. It should appeal to the non-technical person who wants to have a taste of sound processing but, like so many products, its manual lets it down.

P 981 ???

P 981 IS A COMMITTEE THAT IS CHANGING IEEE 488

This committee is adding a whole new range of sophisticated protocols forming the basis of:

IEEE 488.2

If you want to add these powerful new extensions to your BBC or Master computers then you need the new IEEE 488.2 interface from Moordene Associates.

This unit consists of an IEEE 488 interface, software in PROM, interface cable and comprehensive handbook giving clear information on the uses and operation of these new protocols.

Some of the new protocols are:

FINDROS . . . Finds which device is requesting service.
RESET . . . Resets the system.
SET RWLS . . . Sets the system up for remote control.

These powerful protocols and others are designed for writing effective instrument control programs quickly and consistently.

Price £320.00 inclusive

To place your order or for more information contact:

Moordene Associates
Axtown Lane, Yelverton, Devon PL20 6BU
Telephone: (0822) 853585
Discounts available to educational establishments.
When ordering state BBC 'B' or Master



IN BROMLEY

BROMLEYS FIRST SPECIALIST COMPUTER STORE

We are official Acorn Dealers with high standards to maintain and take pride in friendly and efficient advice and service.

See our extensive range of printers, monitors, disc drives, software and books.

Data Store

6 Chatterton Road, Bromley, Kent. 460 8991

COMPUTER EXPRESS.



Why Shell out more? Zzzz

PRINTER MADNESS

Epson LX86 - The Best Seller in the World	£195
Star NL10 - The Number Two Seller - Best Spec	£210
Quendata DWP1120 Daisy Wheel - The DWP Leader	£137
Dyneer DWP12 Daisy Wheel - The No. 2 Daisy	£99
Panasonic 1080 100cps & 80col - A Hot Seller	£149
Epson FX105 + - The Old Favourite	£390
Epson FX85 + - IBM Made This One Famous	£299
Epson LQ800 Letter Quality - 24 Pin Printhead	£406
Epson LQ1000 Letter Quality - 24 Pins	£536
Epson FX800 - Brand New!	Call
Epson FX1000 - Brand New!	Call
Epson EX800 300cps & 80 column - Super Fast	£349
Epson EX1000 300cps & 136 Column - Super Fast	£453
Juki 5520 - Colour Option Available	£284
Juki 5510 - A Best Seller	£270
Star SR15 200 cps wide carriage - Good Buy	£414
Roland 880A Plotter - The Leading Plotter	£649
Cherry A3 Digitizer - The Leading Digitizer	£475
HP LaserJet Plus - The Leading Laser	£2744
Seiko-sha MP1300AI - 300cps! (EX800 clone)	£302
Mannersman Tally MT80 + The German Challenge	£166
NEC P5 - Heavy Duty (Office Favourite!)	£780
NEC P6 - Good Buy	£415
NEC P7 - Worth a Look!	£495
Olivetti DM280 - Okay	£314
Olivetti DM290 - Good For A Shortlist	£363
Olivetti DY300 - New Daisy Wheel!	£554
Olivetti DM295 - New	£536
Olivetti DM100 - New and Cheap!	£176
Qume 11/55 55cps - The Classic Daisy Wheel	£1200
Oki Microline 182 - The Number 2 Brand	£215
Okimate 20 Colour Printer - A Good Toy	£191
Oki Microline 192 - Perennial Favourite	£323
Oki Microline 193 - Worth A Look	£425
Oki Microline 293 - Worth A Look	£599
Citizen MSP-15 160cps & 80 column! - Not Bad	£379
Citizen MSP-25 200cps & 132 column - Try It	£391
IBM-Compatible Centronics Parallel Cable (Round)	£11.50
BBC Centronics Parallel Cable (Ribbon)	£7.50
Serial cables Made to Order	£21
Two-Way Printer T-Switch	£50
Fan-Fold White Paper, 11in long, 1000 sheets	£8.99

All prices exclude VAT and delivery and are correct at the time of going to press. Official purchase orders and export enquiries welcome. Full back up and support. Fast delivery service.
Open Mon-Fri 9 am-6 pm. Open Saturday 10 am-4 pm.

0727-72790

VISA

SINGLE AND MULTI-USER MICRO-COMPUTER AND SOFTWARE SALES AND SUPPORT
99 PARK STREET LANE•BRICKET WOOD•HERTFORDSHIRE•AL2 2JA•TEL:ST.ALBANS (0727) 72790
Telex: 8950511 ONE ONE G (Quote ref: 15412001)

For all your Manual requirements contact the specialists ARLON PRINTERS

All enquiries welcome for Quotations or for us to come and see you, contact:-
Richard or David Cockerill on

(09277) 68328
FAX 0442 60740

Any size manuals produced from any form of original ie., laser copy.
(Typesetting service available)

Delivery and Collection Service Countrywide



Arlon Printers
Arlon House, Station Road
Kings Langley, Herts.

Services include: Design, Artwork, Typesetting, Camera and Full Colour Platemaking, General and Full Colour Printing, Collating, Folding, Stitching, Laminating, Wiro-binding and General Print Finishing

OPUS WILL MAKE YOU A BETTER ORGANISER FOR ONLY £60

If your micro system is starting to get out of hand a smart organiser could be the solution to your problems.

At just £59.95 the Organiser desk from Opus Supplies will help to organise your system beautifully. It's purpose built to provide plenty of storage space and because it's produced alongside our range of executive computer desking it offers a level of quality you'll appreciate.

Shelving accommodates your monitor, printer computer, disc drive or cassette recorder and software, and the teak-finished unit is fitted with castors to make it fully mobile. The Organiser's assembled dimensions are: H. 31", W. 40¼" and D. 26".

And our price includes VAT and FREE DELIVERY.

The Organiser desk is suitable for use with all leading home micros including the BBC, Amstrad, Commodore and Sinclair computers.

Getting organised couldn't be easier. Phone us on 0737 65080 or simply post the coupon below.



To: Opus Supplies Ltd,
55 Ormside Way, Holmethorpe Industrial Estate, Redhill, Surrey.

Please rush me the following:
(PRICES INCLUDE VAT AND CARRIAGE)

_____ Organiser Desk(s) at £59.95 each (inc. VAT)

I enclose a cheque for £_____ or please debit my credit card account with the amount of £_____
My Access ☐ Barclaycard ☐ (please tick) no. is:

_____

Name _____

Address _____

_____

_____

Telephone

_____

_____ BBC

Opus.
Opus Supplies Ltd.

Disc filing with a difference

Rory McCloy takes a close look at ACP's Advanced 1770 DFS – and likes what he finds

ALTHOUGH I'm an ardent admirer of the hierarchical filing system on the ADFS, I must admit that it can be confusing for newcomers, especially if they've been used to the more rudimentary Acorn versions of the DFS.

If you've been baffled by the ADFS you've almost certainly thought that it would be nice to have a DFS capable of both single and double density operation, preferably without the bother of a hierarchical directory system, which could format both sides of a double sided disc as a single drive for both single or double density filing, with the choice of a 62 file catalog.

Well ACP has produced the answer to your prayers – the Advanced 1770 DFS.

And for the Master 128, Compact and Model B+128 there's a bonus: It also includes the facility to use your 64k sideways ram as a fast ram drive.

In fact there are three separate versions of the Advanced 1770 DFS for the Electron, B+ and the Master – they are not interchangeable. The Master version was used for this article.

With this DFS ACP have expanded on the usual Acorn disc filing system and, perhaps not surprisingly, have incorporated several features familiar to users of the excellent Watford DFS. There are also some exciting new utilities (summarised in Table I) which make the upgrade well worthwhile, especially for B+ owners who haven't acquired Acorn's Advanced Disc Filing System (ADFS) yet.

Unfortunately, Model B owners with the 8271 disc controller cannot use this DFS unless they have already fitted a 1770 upgrade kit (about £42) but after reading this assessment they may well start saving up to make the change.

The Advanced 1770 DFS commands can be selected by using Z as a prefix to prevent clashes with other roms. *ZDISC will select the new DFS but, of course, Master users have the advantage of turning the Acorn 1770 DFS off by *UNPLUG. Use *INSERT to restore it.

The Acorn DFS has to be unplugged in this way since it is incorporated in the megarom, which has a higher priority than any of the user rom sockets. Master users, however, suffer the disadvantage that one rom socket is wasted by the unplugged Acorn DFS which they cannot remove.

Unlike Acorn's and many other disc filing systems, the Advanced 1770 DFS can operate in either single density (10 sectors per track of disc) or double density modes (16 sectors per track). Double density disc storage increases your storage capacity by 60 per cent.

The single density operation of the Advanced 1770 DFS is fully compatible with the Acorn 1770 DFS provided you choose the small 31 file catalog when you format the disc. Furthermore, Watford DFS users will be delighted to find that the large 62 file catalog system of the ACP DFS is compatible with Watford's.

The double density operation is not compatible with the Acorn ADFS since

***DISC 40 MFM** **80 FM**	Enters DFS and allows all drives to be set to 40/80 track or single/double density.
***DRIVE n 40 MFM** **80 FM**	Changes current drive to n (0-8) and selects 40/80 track or single/double density.
***FILES**	Display the filenames that have been opened for random access.
***FORM40 n S** **80 L** **160**	Formats a disc in drive n with 40/80/160 tracks and small (31 file)/large (62 file) catalog. Formatting with 160 tracks (80 on each side) a double sided disc is treated as one surface.
***MAXFILES n**	Set the maximum number of sequential files that can be open at one time to n (range 0-10). Default number and maximum with Acorn DFS is 5.
***OPT 5 n**	Allows a drive to be set up for double/single density or 40/40 track and set whether DFS automatically senses number of tracks or density of a disc. For values of n (range 0-255) see Table II.
***OPT 6 n**	Changes track sector skew to n (range 0-9) for single density discs. This can be used to minimise disc access time due to head stepping delay.
OPT 7 n	Changes track sector skew to n (range 0-15) for double density discs.
***SRDRIVE n**	Change the ram drive number to n (range 0-8). Default n=8.
***SRFORM S** **L**	Initialises the free sideways ram pages to be used as a ram disc with a small/large catalog.
***SRramS n**	Define which pages of sideways ram can be used as a ram drive (n=4 and/or 5 and/or 6 and/or 7). If no n defined then ram pages free for use displayed.
***WORK filename**	Sets up a default work filename to allow LOAD"" and SAVE"" without specifying a filename. *WORK alone displays current work filename.

Table I: The additional commands featured in the Advanced 1770 DFS

the latter uses the hierarchical catalog (see *The Micro User*, July 1986) whereas the Advanced 1770 DFS uses the standard catalog, with a choice of 31 or 62 files.

For the technically inclined, the ACP DFS uses 20 bit addressing compared with Acorn's 18 bit. In both densities the filenames are limited to the usual seven character length.

Two commands, *DISC and *DRIVE, can select either the single or double density modes by postfixing the command with FM or MFM respectively. *DISC sets all drives to the same density while *DRIVE can set different drive numbers to different densities.

If you set drives 0 and 1 to different densities you can simply use *COPY to transfer files from your existing single density discs to double density discs without resort to the type of utility program required by ADFS users.

*OPT 5 *n* is another command which like *DRIVE allows you to selectively set the drives to single/double density or 40/80 track (double/single stepping), but can also determine whether the DFS will automatically recognise the density and total track number on the disc.

Here I found the manual became rather technical, lapsing into "bit interpretation" to define *n*. I hope Table II clarifies the command.

Although I have only listed the values of *n* for drive 0, you should be able to extend this to other drives if I tell you that *OPT 5 2 would switch all the features off for drive 2 and *OPT 5 243 (&F3) would switch all this option's features on for drive 3.

One of the features of Acorn's ADFS I appreciated was the ability to format both sides of a disc into a single continuous surface so that surfaces on drives 0 and 2 become drive 0 and surfaces 1 and 3 become drive 1.

This is now possible with the Advanced 1770 DFS for both single and double density use – giving 400k and 640k of disc storage respectively – provided you have 80 track drives, by using *FORM160.

Now for the icing on the cake. A series of SR commands (Table I) allows users with an extra 64k ram (integral on the B+ 128 and Master) to format – within seconds – the sideways ram as a silicon disc. This then becomes drive 8, by default, and can be used with all the usual DFS commands.

n	Auto density selection	Auto stepping selection	Drive density	Drive stepping
&00	off	off	single	normal
&10	on	off	single	normal
&20	off	on	single	normal
&30	on	on	single	normal
&40	off	off	double	normal
&50	on	off	double	normal
&60	off	on	double	normal
&70	on	on	double	normal
&80	off	off	single	double
&90	on	off	single	double
&A0	off	on	single	double
&B0	on	on	single	double
&C0	off	off	double	double
&D0	on	off	double	double
&E0	off	on	double	double
&F0	on	on	double	double

Table II: Selections possible with the *OPT 5 n command. The hexadecimal values for n are shown for drive 0. To set up other drives (0-3) alter the first byte of the hexadecimal number (see text)

In order to get some of the DFS commands such as *FREE, *MAP and *COMPACT to work for the ram disc you must first redefine the default drive value of 8 into the range 0-3 using *SRDRIVE. This has the drawback of your not being able to use that particular floppy disc drive number until the ram disc number is redefined.

The Advanced 1770 DFS is intelligent enough to work out which of the 16 ram pages are occupied with rom-image software and so only format the remaining space, which doesn't have to be continuous. Similarly, space in ram can be saved from formatting in case you need it for ram software later.

Thus *SRFORM could format the ram pages which correspond to rom sockets 4 and 7, in this case the ram disc would only be 32k in size.

The ram disc is ideal for use during a computing session without the delays, whirring and clicking of a disc drive, but don't forget to copy any files you want to keep on to disc before you switch off, since all the information will be lost from the ram on power down. This may sound obvious but it is easily done.

The ram disc facility should make B+ owners think about the 64k upgrade to 128k (good value at £32).

Two serious omissions from the ACP DFS are the commands to load and save to ram (*SRLOAD, *SRSAVE) which is surprising since ACP has obviously tailored this DFS to make the most of user ram. I have to insert my Acorn 1770 DFS to load ram software before switching to the Advanced 1770 DFS.

If you have a disc with a suite of programs (less than 64k in total) which is booted by Shift+Break Program I is a short text file that can be *EXECed and will demonstrate the sheer speed of the ram disc.

The listing should be entered as a text file in View without line numbers or using *BUILD and then saved on the floppy disc – but do not call it !BOOT.

It will format the ram disc with 31 file catalog, set the auto-boot option, copy all the files from floppy disc to ram disc, and set the ram disc to be drive 0 – all in a matter of moments. Finally, press Shift+Break to boot the ram disc.

```
1 *SRFORM
2 SY
3 *DRIVE 8
4 *OPT4,3
5 *COPY 0 8 *.*
6 *SRDRIVE 0
```

Program I

Even when I am loading and saving very long text files from View the response of the ram disc appears almost instantaneous, but how fast is it?

To answer this question and find out how the speed of the Advanced 1770

→

From Page 125

DFS compares with the Acorn ADFS I enlisted Jim Notman's help. Jim came round for the afternoon, drank all my coffee, and ran his now famous benchmark programs.

The results of our efforts are listed in Table III. Jim previously published the benchmarks comparing Acorn's 0.90 and 1.2 DFS, 2.20 1770 DFS and 1.30 ADFS in the December 1985 issue of *The Micro User*.

The overall timings show that the Advanced 1770 DFS (version 1.00) in double density (MFM) mode is 13 per cent faster than the Acorn ADFS (version 1.50) and the ACP ram disc filing system is 55 per cent faster than the Acorn 1770 DFS (version 2.20).

Documentation is in the form of an 80 page user guide. Throughout there are clear statements about the compatibilities and incompatibilities with the Acorn filing systems, particularly when exchanging information between large and small format discs, and discs with large and small catalogs.


		Acorn DFS 2.2	Acorn ADFS 1.5	ACP 1.00 MFM	ACP 1.00 RAM DFS
1	OPEN + CLOSE files*1000	8.6	21.5	9.7	21.3
2a	PRINT 1000 numbers	9.9	14.4	6.3	3.6
2b	PRINT 100 strings	42.5	45.9	24.3	13.5
3a	INPUT 1000 numbers	9.5	8.8	6.1	3.2
3b	INPUT 100 strings	24.1	23.5	23.5	11.8
4	BPUT 1000 bytes	4.2	7.1	3.7	1.5
5	BGET 1000 bytes	3.3	3.1	3.5	1.3
6	Move PTR 1000 places	3.1	6.8	3.7	2.0
7a	Write relative file	44.0	47.6	45.1	14.5
7b	Read relative file	24.8	24.2	24.1	12.1
8a	Write relative file backwards	102.8	71.8	79.9	15.3
8b	Read relative file backwards	44.4	28.4	39.8	12.7

Table III: Jim Notman's DFS benchmark times in seconds using a Master

However newcomers to disc filing systems would find the introductory section on disc files too brief. For the experts there is a technical section describing the OS calls for using the filing system in assembler.

Conclusion: An excellent buy for users with a 1770 disc controller which maintains full compatibility with your old single density discs and yet allows you both double density and the possibility of a very fast ram disc.

Product: Advanced 1770 DFS, Version 1.00.
Price: £34.50 inc. VAT
Supplier: Advanced Computer Products Ltd, 6 Ava House, High Street, Chobham, Surrey GU24 8LZ.
Tel: 0276 76545



Breaking out!

CHRIS BOWERMAN's utility will recover programs – and variables

IF a program we are developing isn't quite right and we want to stop it at some point and inspect it we can either press Escape or Break.

Both methods can interrupt a program – and both have completely different effects.

The Escape key will normally stop a program. However, it is often disabled or reprogrammed to provide some other function, and the only solution is to press Break.

Unfortunately the effect of doing this is rather more drastic than Escape and the BBC Micro has an annoying habit of wiping out your program and variables. It's not very useful if you're trying to debug a program.

There is a partial solution. The Break key is function key 10 and:

```
*KEY10 OLD|M
```

will recover your program when Break is pressed. However the variables will still be lost.

This is where BreakVar comes in handy. This short utility will recover both your program and variables.

Enter the listing and save it. At the start of a programming session load and run BreakVar to set up the machine code.

Now whenever the Break key is pressed both your program and variables will be restored.

There are a few points to watch out for:

- Don't run BreakVar twice without pressing Control+Break or switching off as it can become confused and crash the micro.
- PAGE will be set to its default value. If your program is located elsewhere you can get round this problem by altering line 370 to:

```
370 $S%="*KEY10 PAGE="+STR$PAGE+"|M
CA."+STR$break+"|M"
```

- Control+Break will disable BreakVar.
- Type NEW before loading any program to delete the old one.
- BreakVar is stored at &900 so avoid this area of memory or assemble the routine to a different address by altering *org* in line 40 to an unused 281 byte area of memory.

In order to appreciate how the program works you need to understand the basics of variable storage.

They are stored in memory immediately following the program. A pointer is stored with each variable pointing to the address at which the next one with the same initial letter is to be found, thus forming long chains. So all the variables starting with the letter A form a chain, followed by the Bs, the Cs and so on.

The initial pointer to the start of each variable chain is stored at a fixed place in memory. The A chain is at &482/3, B is at &484/5 and so on. The address of any variable chain is given by &400+ASC(a$)*2, where *a$* is the initial letter of a variable.

If no variables exist for a particular initial letter its pointer contains zero.

When you hit Break Basic simply sets all the pointers to zero – leaving (thankfully) all pointers within the chains intact. All we need to do after Break is restore these initial pointers to restore our variables.

The technique used is to set up an interrupt and save the pointers every now and then.

The simplest method is to use one of the BBC Micro's events – number four to be precise – which occurs at the start of frame flyback, 50 times a second.

This particular event has nothing to do with the job in hand and is used only because it conveniently stops program execution at regular intervals so that we can note the value of the variable pointers.

The values of the pointers along with the value of *vartop*, the address of the top of the variable heap stored at &2/3, are stowed away in a safe area of ram, ready to be restored should Break be pressed.

The Break key – function key 10 – is defined to call our routine to copy the saved pointers back to their original locations.

Now you can take a well earned break without losing all your valuable programming. ■

```
  10 REM BreakVar
  20 REM By C.Bowerman
  30 REM (c) The Micro User
  40 org=&900
  50 FOR I%=0 TO 1
  60 P%=org+&83
  70 [OPTI%*2
  80 .start LDA#interrupt MOD 256:ST
A&220 \set vector
  90 LDA#interrupt DIV 256:STA&221
 100 LDA#14:LDX#4:JSR&FFF4:RTS \enab
le EVENT4
 110
 120 .interrupt \routine to save var
iables
 130 CMP#4:BNEout\end if not EVENT4
 140 PHA:TXA:PHA:TYA:PHA:PHP  \save
registers
 150 LDA&12:STA&8C:LDA&13:STA&8D \pr
eserve TOP
 160 JSRpage
 170 LDA&13:CMP&8F:BCCjump1:BNEcont
\end if memory is NEWed
 180 .jump1 LDA&12:CMP#2:BEQend
 190 .cont \....otherwise contine
 200 LDA&2:STAorg:LDA&3:STAorg+1  \s
ave VARTOP
 210 LDY#0
 220 .loop1
 230 LDA&482,Y:STAorg+2,Y  \save var
iable pointers
 240 INY:CPY#127:BNEloop1
 250 .end PLP:PLA:TAY:PLA:TAX:PLA  \
restore registers
 260 .out RTS  \finished
 270
 280 .break  \CALLed when BREAK is h
it
 290 LDAorg:STA&2:LDAorg+1:STA&3 \re
store VARTOP
 300 LDY#0:.loop2 LDAorg+2,Y:STA&482
,Y:INY:CPY#127:BNEloop2\ restore vari
able pointers
 310 LDY#1:LDA#0:STA(&8E),Y:LDA&8C:S
TA&12:LDA&8D:STA&13 \OLD
 320 JMP start \reset
 330 .page LDA#131:JSR&FFF4:STX&8E:S
TY&8F:RTS
 340 ]:NEXT
 350 CALLstart
 360 DIM S%-1
 370 $S%="*KEY10 CA."+STR$break+"|M"
 380 X%=S%:Y%=S% DIV 256:CALL&FFF7
```



Underneath the spreading chestnut tree...

VILLAGE of Lost Souls by Magus is sure to become a classic. A feature well worth a closer look is the way it compiles superb chaining puzzles.

There are several of these, ranging from a simple need to find a pair of pliers for cutting a chain in church, to a very long and involved puzzle indeed.

Here is just one puzzle to give you the flavour of the scenarios Magus dreams up. It contains everything I look for in an adventure game.

Beneath the spreading chestnut tree the village smithy stands. It is a key location in the game, and I made a point of storing quite a lot of things there.

If you climb the tree on one of the branches you will find a locked chest – nut-shaped, of course!

Searching beneath the benches in the church porch showed me that there was a key down in a crack – just out of reach, naturally.

At first I went off on a wild-goose chase. I thought a stone I had seen with the description "attractive" would provide the answer. I felt it had to be a magnet!

I spent a lot of time barking up that wrong tree.

Eventually I realised that the thread attached to the key was the important factor because the key only looked like iron and so was not susceptible to a magnet after all.

It then became a matter of figuring out how to get the thread, rather than the key itself.

I found a glass rod and, later, a wisp of fleece. I took them both to the church porch, rubbed away and hey presto, the key was then mine!

Please don't think that possession of the key is the end of the chain though – it isn't.

Opening the chest(nut) revealed some herb tobacco and it was then that I realised the value of the churchwarden in the rectory.

So the pipe is filled with 'baccy and the chain still has a way to run. But I don't want to spoil things for those of you who have the game – it really is a honey of a problem.

That is what I call a satisfying puzzle. The superbly consistent and thoughtful descriptions are a model for any would-be adventure game writer.

I think Peter Austin would appreciate the following features of Village of Lost Souls – it's up to his awfully high standard of humour, as demonstrated in Dungeon Adventure.

Find a bow, examine bow, answer: It's yew. Find a looking-glass, examine looking-glass, answer: It's you. Find a fleece, examine fleece, answer: It's ewe.

All I can say is that I want three volunteers – yew, you, and ewe. Your job is to locate even worse puns.

To return to serious comment. This sort of chaining puzzle shows what the

PROBLEM CORNER

Adrian Emery is stuck in **Lord of the Rings** – how can he deal with the Green Knight? Readers' help needed here please.

He wants to know how to get out of the willow tree in **Bored of the Rings** – CRY HELP should do it.

Martin Farrington has trouble in **Jet Set Willy** – he reaches the watch tower and the game crashes, and not just on his own BBC Micro. Does anyone know why?

Nick Southgate, 34 Trent Avenue, Upminster RM14 1QZ would be glad to hear from adventure fans, particularly those who have solved **Worm in Paradise** by Level 9.

How does he get the Visor, beat the colour banding machine, take back the scale from the monster and get best use out of the furniture, dog and pizza?

Knowing Pete Austin, I'll bet the pizza just gives heartburn.

Miss T. Mell has problems in **Circus** by Adventure Soft. Where can she get a lamp? Is the clown in the tent of any significance and how does she get into the maintenance wagon?

Jonathan Morris – 860/800 in **Sphinx!** – is stuck in Melbourne House's **Classic Adventure.** How does he cross the pit where the man is waving, how can he cross the reservoir and how can he get out of the game store?

He also has a problem in Superior's **Gideons Gamble.** How can he splice the mainbrace and cool down from the hot sun when he is in the ocean?

HALL OF FAME

Stuart Booth of Aberdeen has sent me a superbly detailed solution to, and map of Level 9's Snowball. You'll see it in due course.

scope of a good adventure should be. There is time to think and lots to consider by way of possible combinations of objects and solutions.

Apart from the useful items that you will find along the way, the village is littered with things that would be there if the situation were a real one.

This cleverly adds to the difficulty of the problems to be solved without resorting to irritating features like mazes.

I'm getting near the end of Village of Lost Souls now, with a score of 800/1200 and the going is beginning to get really tough.

I spend as much time with paper and pencil on an adventure like this as I do on typing instructions.

In fact I seem to spend quite a lot of time just gazing happily at the screen, working out the possible permutations of objects that will allow me to accomplish something safely or successfully.

For me, that is the sign of a top-flight adventure.

I still try to do what many other reviewers don't seem to have time for. I play the game honestly, without a crib-sheet always by my side.

It's true that I do ask for extra help so the editor doesn't have a stroke due to late arrival of copy. But I try to play a game as legitimately as possible because then I can pass on the kind of information that people who might buy the adventure will appreciate.

Very often I am still stuck in there with you!

I'm not a know-it-all whizz kid, just a fan of adventure games. And I won't recommend something I have not tested and played properly.

I'm telling you this for two reasons. First I have seen some reviews that are no more than rehashes of advertisers' blurb.

This is painfully obvious to anyone who has actually played the game supposedly reviewed, as my local software retailer often tells me.

Secondly, I am afraid that some of you will go out and buy inferior games before I have had time to pass judgement – and then be disappointed because the promise and reality don't match.

OK, I'm not Solomon, and I did write at the beginning of my stint on this column that reviews are necessarily a personal judgement.

However, I am appalled at the idea of nice people rushing out to buy a game just because of advertisers' hype combined with ignorant reviewers' recommendations. If you are patient you might save a few pounds and a good deal of heartache as well.

● *See you next month. Until then happy adventuring.*



HELPLINE

Simon Edwards is nearly at the end of ***Sphinx Adventure,*** *but can't find the boat and wonders if there are permanent ways of getting rid of pirates, dwarves and rabbits.*

Rabbits eat carrots, but the other two are incorrigible. So long as the pirate puts his ill-gotten gains in his chest – and you have the keys – you can retrieve them.

Dwarves have to be endured I'm afraid Simon. The boat can be found at the foot of Castle Hill (Vampire's Castle). Simply follow the directions from the Bear's Cave to get there, Nic Outterside tells me.

Nic also furnished the solution to Chris Jones' problem in Sphinx Adventure.

Chris needs a mouse to frighten an elephant. The mouse will be discovered scurrying around the dungeon of the Vampire's Castle (Down from the Ballroom).

Andrew Armstrong has had trouble in ***Acheton*** *– one of the very best games for disc drive owners. How can he find the Gin, and what about the third exit in the Ningy Room?*

Answers are from the masters themselves – David Seal and Jon Thackray, joint authors of Acheton, tell me there's an earthenware pot inscribed London Dry. Guess what's inside?

There are three holes, but one of them is a one-way entrance to the Ningy Room from somewhere else.

Gavin Shek has sent me some tips for Epic's ***Wheel of Fortune.*** *Remember to switch the lamp off whenever coming out of the caves. And if you are jailed, quit.*

The Trolls' Cave is the place to dump treasures – so get the pipe from the vending machine, the basket from the canal south bank, DROP the basket, PLAY pipe and then you have a Troll Scarer!

The music box is a bird scarer, and to get the bucket off the obelisk use the brass key to unlock the hut, take the ladder and up you go.

Attention C. Briancourt, who is stuck in Wheel of Fortune. If Gavin's hints don't help, Epic supplies superb clue sheets.

Write to them c/o 10 Gladstone Street, Kibworth, Beauchamp, Leicester LE8 0HL but be sure to enclose an sae.

An answer for Peter Aumayr stuck in ***Voodoo Castle.*** *Take the sapphire ring from the coffin and wave it to open the stone door. As for the window, I'm pretty sure it's just scenery.*

Adrian Emery has some ***Return to Eden*** *tips. To get across the river you need to give the bird the sweet pea. The bird should lay an egg which, planted in the green sward, grows into a house.*

In the house is a fungus to give to the leviathan. Getting into the parrot's nest means you have to go N, E, W, S from the river bank.

To get down from the island you need to water the bulb from the log on the river – it should turn into a parachute which you can use to jump down safely.

HAPPY XMAS ADVENTUROUS PEOPLE, LOVE ROBICO.

3 Fairland Close, Llantrisant, Mid Glamorgan. CF7 8QH Tel (0443) 227354

'We turn dreams into reality!'

Send SAE for catalogue.

CHRISTMAS CRACKERS

COMPILATIONS

THE ADVENTURER £14.95 (disk) **£12.95** (tape)

A compilation of four of the most original and acclaimed adventures yet released for the BBC Micro. With full instructions, hint sheets and save options. Suitable for a wide range of age-groups and recommended as good family entertainment. These adventures are packed full of mysteries, puzzles, challenges and intrigue and are presented in graphics and text. Explore the sinister village of **Woodbury End** and discover its strange secrets. Travel through three continents guided by the mysterious **Pettigrews Diary**. Mount your expedition to the south seas to encounter the **Mystery of the Java Star.** Travel back in time to the holy land and experience the unique atmosphere of **Galilee.**

FUN ACADEMY £14.95 (disk) **£12.95** (tape)

This educational compendium is suitable for children between the ages of 6-16. The content of these games has been endorsed by schools, parents and reviewers alike, offering the child the best that the computer can offer in playability, colour, sound and graphics, with solid educational content in the best traditions. The 22 routines cover area estimation, times tables, arithmetic, logical thinking, mental arithmetic, proportions, estimations, fractions, alphabet, spelling, letter grouping, word puzzles, code breakers and anagrams. It includes a massive vocabulary of 1500 words.

ADVENTURE

*** OPERATION SAFRAS £7.95** (tape) **£9.95** (disk) **NEW**

Graphic adventure played in modern day Britain. You are Rupert J. Pettigrew, agent extraordinaire. Your mission is to find and rescue your five fellow agents, before it is too late, then to discover the whereabouts of the legendary Safras Sword. This adventure comes with a unique competition. The first 6 people to solve it will feature as characters in our 1987 Adventure blockbuster!

BUDGET RANGE

FAMILY PROGRAMS £4.95 (disk only) **NEW**

Budget compendium of 11 programs covering strategy games, child games, utilities, education, arcade and quizzes, features Crossword, Diamond trial, Shape Maker, Dots and Boxes, Mystery Word, Prog-Aid, Beat the Odds, Simon, Sound Shaper, Tables Chaser and Name the Tune.

LIGHT AND SOUND £6.95 (disk only) **NEW**

A unique and incredible utility collection, all on one disk. Includes:
* Sophisticated artist utility to create sophisticated illustrations
* Screen compacter/un-compacter
* Screen "trapper" to save any screen (eg. from your favourite game)
* Music creator
* Create your own interrupt driven sound. (Runs continuously throughout your program)

BEST OF THE REST

WOODBURY END*: illustrated mystery adventure (age 11+) ..	**£4.95 (tape) £6.95 (disk)**
WHOOPSY: humorous arcade game (all ages)	**£3.95 (tape) £5.95 (disk)**
JAVA STAR: enormous educational adventure (age 8+)	**£3.95 (tape) £5.95 (disk)**
PETTIGREWS DIARY: family adventure (age 11+)	**£3.95 (tape) £5.95 (disk)**
GALILEE: HISTORICAL TEXT ADVENTURE (age 9+)	**£4.95 (tape) £6.95 (disk)**
SCIENCE ONE: Physics education (age 11-16)	**£2.95 (tape) £4.95 (disk)**
FUN TO LEARN: Educational compendium (age 6-12)	**£2.95 (tape) £4.95 (disk)**
MONSTER MATHS: Maths compendium (age 8-14)	**£2.95 (tape) £4.94 (disk)**
FRAC ATTACK: Fractions are fun (age 8-14)	**£2.95 (tape) £4.95 (disk)**
LASER LETTERS: Educational word game (age 6-16)	**£2.95 (tape) £4.95 (disk)**
INFANT PACK: Pre-school games (age 3-6)	**£4.95 (tape) £6.95 (disk)**
JUNIOR PACK: Educational action games (age 6-12)	**£4.95 (tape) £6.95 (disk)**

● **ALL PROGRAMS WILL WORK ON BBC+ and MASTER** (except where marked with *) **AS WELL AS BBC B**
● **SEE US AT ELECTRON/BBC USERS SHOW (UMIST**
● **£1 DISCOUNT ON EVERY £15 SPENT ● 10% DISCOUNT ON OFFICIAL EDUCATION ORDERS**

Either Phone your ACCESS/VISA order to 01-514 4871 or send coupons to SHARDS SOFTWARE, FREEPOST, ILFORD, ESSEX IG1 2BR

Please send me _____

Name _____ Address _____

I enclose a Cheque/PO/VISA/ACCESS for _____ CREDIT CARD No. _____ PLEASE SEND ME YOUR CATALOGUE ____

From Page 103

```
 10 REM 4 Direction Scrolling
 20 REM By Tim M Brown
 30 REM (c) The Micro User
 40 MODE2:VDU23;8202;0;0;0;
 50 PROCassemble
 60 PROCpicture
 70 VDU7
 80 CALL setup
 90 CALL keys
100 *FX15
110 MODE7
120 END
130 DEFPROCassemble
140 lalo=&70:lahi=&71
150 ralo=&72:rahi=&73
160 blo=&74:bhi=&75
170 tlo=&76:thi=&77
180 block=&80
190 :
200 DIM Z%600
210 FOR I%=0 TO 2 STEP2
220 P%=Z%
230 [OPT I%
240 .Right
250 LDA#13:STA &FE00
260 CLC
270 LDA &FE01:ADC#1:STA &FE01
280 LDA#12:STA &FE00
290 LDA &FE01:ADC#0:STA &FE01
300 CMP#16
310 BNE nothigh
320 LDA#6:STA &FE01
330 .nothigh
340 LDA ralo:STA blo
350 LDA rahi:STA bhi
360 SEC
370 LDA ralo:SBC#&80:STA tlo
380 LDA rahi:SBC#2:STA thi
390 LDY#7
400 .Rstore
410 LDA (blo),Y
420 STA block,Y
430 DEY
440 BPL Rstore
450 LDX#31
460 .Rmove1
470 LDY#7
480 .Rmove2
490 LDA (tlo),Y
500 STA (blo),Y
510 DEY
520 BPL Rmove2
530 LDA tlo:STA blo
540 LDA thi:STA bhi
550 SEC
560 LDA tlo:SBC#&80:STA tlo
570 LDA thi:SBC#2:STA thi
580 DEX
590 BNE Rmove1
600 LDY#7
610 .Rrestore
620 LDA block,Y
630 STA (blo),Y
640 DEY
650 BPL Rrestore
660 CLC
670 LDA ralo:ADC#8:STA ralo
680 LDA rahi:ADC#0:STA rahi
690 CMP#&80
700 BNE Rnonewline
710 LDA#&80:STA ralo
720 LDA#&7D:STA rahi
730 .Rnonewline
740 CLC
750 LDA lalo:ADC#8:STA lalo
760 LDA lahi:ADC#0:STA lahi
770 CMP#&32
780 BNE Rexit
790 LDA lalo
800 CMP#&80
810 BNE Rexit
820 LDA#0:STA lalo:LDA#&30:STA lahi
830 .Rexit
840 RTS
850 :
860 .Left
870 LDA#13:STA &FE00
880 SEC
890 LDA &FE01:SBC#1:STA &FE01
900 LDA#12:STA &FE00
910 LDA &FE01:SBC#0:STA &FE01
920 CMP#5
930 BNE notlow
940 LDA#15:STA &FE01
950 .notlow
960 LDA lalo:STA blo
970 LDA lahi:STA bhi
980 CLC
990 LDA lalo:ADC#&80:STA tlo
1000 LDA lahi:ADC#2:STA thi
1010 LDY#7
1020 .Lstore
1030 LDA (blo),Y
1040 STA block,Y
1050 DEY
1060 BPL Lstore
1070 LDX#31
1080 .Lmove1
1090 LDY#7
1100 .Lmove2
1110 LDA (tlo),Y
1120 STA (blo),Y
1130 DEY
1140 BPL Lmove2
1150 LDA tlo:STA blo
1160 LDA thi:STA bhi
1170 CLC
1180 LDA tlo:ADC#&80:STA tlo
1190 LDA thi:ADC#2:STA thi
1200 DEX
1210 BNE Lmove1
1220 LDY#7
1230 .Lrestore
1240 LDA block,Y
1250 STA (blo),Y
1260 DEY
1270 BPL Lrestore
1280 SEC
1290 LDA lalo:SBC#8:STA lalo
1300 LDA lahi:SBC#0:STA lahi
1310 CMP#&2F
1320 BNE Lnonewline
1330 LDA#&78:STA lalo
1340 LDA#&32:STA lahi
1350 .Lnonewline
1360 SEC
1370 LDA ralo:SBC#8:STA ralo
1380 LDA rahi:SBC#0:STA rahi
1390 CMP#&7D
1400 BNE Lexit
```

This is one of hundreds of programs now available FREE for downloading on MicroLink

```
1410 LDA ralo
1420 CMP#&78
1430 BNE Lexit
1440 LDA#&F8:STA ralo:LDA#&7F:STA ra
hi
1450 .Lexit
1460 RTS
1470 :
1480 .Up
1490 LDA#13:STA &FE00
1500 CLC
1510 LDA &FE01:ADC#80:STA &FE01
1520 LDA#12:STA &FE00
1530 LDA &FE01:ADC#0:STA &FE01
```

→

From Page 131

```
1540 CMP#16
1550 BCC Uexit
1560 LDA#13:STA &FE00
1570 SEC
1580 LDA &FE01:SBC#0:STA &FE01
1590 LDA#12:STA &FE00
1600 LDA &FE01:SBC#&A:STA &FE01
1610 .Uexit
1620 RTS
1630 :
1640 .Down
1650 LDA#13:STA &FE00
1660 SEC
1670 LDA &FE01:SBC#80:STA &FE01
1680 LDA#12:STA &FE00
1690 LDA &FE01:SBC#0:STA &FE01
1700 CMP#6
1710 BCS Dexit
1720 LDA#13:STA &FE00
1730 CLC
1740 LDA &FE01:ADC#0:STA &FE01
1750 LDA#12:STA &FE00
1760 LDA &FE01:ADC#&A:STA &FE01
1770 .Dexit
1780 RTS
1790 :
1800 .keys
1810 LDA#19:JSR&FFF4
1820 :
1830 LDX#&BD
1840 JSR keytest
1850 CPY#&FF
1860 BNE ntest
1870 JSR Left
1880 :
1890 .ntest
1900 LDX#&9E
1910 JSR keytest
1920 CPY#&FF
1930 BNE ntest2
1940 JSR Right
1950 :
1960 .ntest2
1970 LDX#&B7
1980 JSR keytest
1990 CPY#&FF
2000 BNE ntest3
2010 JSR Up
2020 :
2030 .ntest3
2040 LDX#&97
2050 JSR keytest
2060 CPY#&FF
2070 BNE ntest4
2080 JSR Down
2090 :
2100 .ntest4
2110 LDX#&9D
2120 JSR keytest
2130 CPY#&FF
2140 BNE ntest5
2150 RTS
2160 :
2170 .ntest5
2180 JMP keys
2190 :
2200 .keytest
2210 LDA#&81:LDY#&FF:JMP &FFF4
2220 :
2230 .setup
2240 LDA#&32:STA lahi
2250 LDA#&78:STA lalo
2260 LDA#&7D:STA rahi
2270 LDA#&80:STA ralo
2280 RTS
2290 ]
2300 NEXT
2310 ENDPROC
2320 DEFPROCpicture
2330 X%=640:XD=-8
2340 VDU29,640;512;
2350 GCOL0,6
2360 REPEAT
2370 MOVEX%,X%:DRAW-X%,X%:DRAW-X%,-X
%:DRAWX%,-X%:DRAWX%,X%
2380 X%=X%+XD:XD=XD*1.1
2390 UNTIL X%<=0
2400 VDU29,0;0;
2410 FORK=0 TO 1
2420 GCOLK,1
2430 PROCcircle(540,512,200)
2440 GCOLK,2
2450 PROCcircle(740,512,200)
2460 GCOLK,4
2470 PROCcircle(640,685,200)
2480 NEXT
2490 ENDPROC
2500 DEFPROCcircle(X%,Y%,R%)
2510 VDU29,X%;Y%;
2520 FORX%=-R% TO 0STEP8
2530 Y%=SQR(R%^2-X%^2)
2540 MOVEX%,Y%:DRAWX%,-Y%
2550 MOVE-X%,Y%:DRAW-X%,-Y%
2560 NEXT
2570 ENDPROC
```

PROBLEM

I ORDERED Monopoly on disc from Leisure Genius through *The Micro User*. When I went to use it all that happened was a lot of very fast head movement and then Disc fault on the screen. I have got a Cumana twin disc drive 400k and an Acorn DFS.

When I rang Leisure Genius they said there is an *FX command that changes the drive from 80 to 40 track as my drive does not have a switch to do this. Will this *FX command work? Or is the disc incompatible with my drive. If there is such a call can you please tell me what it is as I can find no other solution to my problem – apart from sending the disc back. – M.D. Cooper, Sevenoaks.

SOLVED

***There is no *FX command in the Acorn system for changing an 80 track drive to a 40 track. With the Watford system *FX110,0,255 will perform this feat but some software will not play along with it. The only sure fire solution is to use my 40/80 drive switch converter board in the October '85 issue of* The Micro User.**

This listing is included in this month's cassette tape offer. See order form on Page 167.

Christmas with Audiogenic



PSYCASTRIA

The Psycastria are alien beings who, having psycastrated themselves into the bodies of world leaders, have been manipulating world events and plunging humanity into terrible conflict and war, with the ultimate aim of the eventual destruction of mankind. But their secret is out and you have been psycastrated into the body of ace flyer, Commander Ronald Boggleswick (or 'Boggles' for short). You must warp into the different time schedules to undo the evil perpetrated, before finally battling in the present and destroying the Psycastrian mothership that is planning our ultimate destruction. Only you can carry out the daring surprise raid on the Psycastrian installations on land, on sea, on the moon, and finally in deep space.

Superfast smooth-scrolling shoot-'em-up action for the BBC and Electron! Master compatible!

A & B Computing — Game of the Month!

Computer Gamer — Nova Rating!

BBC/Electron cassette **£7.95**

BBC 40 Track disk **£11.95**



THE LAST OF THE FREE

Arcade adventure, with the accent on arcade, starring our hero Clement, the Ordanoid droid!

The Ordanoids have been enslaved and destroyed by the Proleoids, a later model of droid with a fundamental design fault that made them to aggressive. All the Ordanoids have gone except Clement — the Last of the Free!

Clement's mission is to escape from the Proleoids and make it to the teleport to warn humanity about the defective proleoids. The road to freedom is full of dangerous Proleoid enemies and littered with obstacles to avoid and puzzles that must be solved. Apart from his ability to run and jump, Clement has only one advantage, he can pick up and use objects that he finds, but he can only carry one at a time.

The Last of the Free features 55 different and complex screens, 32 different aliens with large animated sprites, music and sound, extending platforms, lifts, doors, lots of puzzles, and much more....

BBC/Electron cassette **£7.95**



BBC POWER PACK

BBC Power Pack gives you seven great BBC titles in one top value twin cassette package....

CONTRAPTION — The potty professor has invented craziest, crankiest machine ever — the Contraption. He must search his house for the golden apples that he needs to feed to the machine. Grapple with the devilishly difficult gameplay and experience some of the best graphics seen on the BBC.

STIX — A freak cosmic storm has trapped a bundle of energy in a warped hypersquare. To keep the energy under control you must restrict its movement to construct a force field inside the square. Colourful, fast arcade action!

SPACE RANGER — A team of astronauts is stranded on the moon. Your job is to pick them up by landing the lunar module on the crater ridden surface and take off through a freak asteroid storm.

CAVEMAN CAPERS — Metalithic multi-screen action concerning the exploits of Ogg the caveman. He's just found a new form of transport — Kickstart the turtle — but is having trouble mastering the art of turtle riding!

ULTRON — Shoot 'em up action against the aliens of Gorfia wave upon wave of them! Try to survive long enough to destroy the nerve centre of the attack — the mothership!

WIZZY'S MANSION — Wizzy the incompetent wizard needs your help to search the rooms of his mansion for the books of spells that he needs in order to destroy the monster that has taken over his attic. But beware because Wizzy's blunderings have made all sorts of objects come to life and get in the way.

WONGO — You are Wongo, the Chinese bomb disposal expert. Your job is to travel along the Great Wall defusing bombs that have been left there by the anti Imperial factions. It's a long wall so they have given you a pogo-stick for transport.

BBC Power Pack **£9.95**



THUNDERSTRUCK

Brain-straining arcade adventure with the accent on adventure and logical puzzle solving. You are SPRECO (the SPace REfuse COllector) who has been transported by a space/time thunderstorm to an eerie castle. All you want to do is get back to Myrtle and the kids, but here you are trapped in these strange medievals surroundings with your Assisdroids. There are various objects littered around the castle that you can carry and use, but because of your bulky space suit you can only manage one at a time. The castle is inhabited by eight characters that you will meet in your search for the way out. If you help them by giving them something they need, they will give you something in return to help you find a way out!

Thunderstruck, for the BBC and Electron, features 100 screens, large-scale graphics, animated backgrounds, aliens, music and sound, and puzzles that constitute a lasting, logical challenge.

BBC/Electron cassette **£7.95**

In your shops NOW!

Also available by mail order
FAST, EFFICENT,
POST FREE

Send for your FREE brochure.

Please send me your BBC/Electron software brochure.

Name:

Address:

Audiogenic Software Ltd.

P.O. BOX 88, READING, BERKSHIRE RG7 4AA TEL: (0734) 303663

CHALICE

SOFTWARE/HARDWARE

MEGA-ROM

67 Powerful commands on this 16K Rom.
A comprehensive BASIC toolkit, friendly and thorough Rom management, utilities for the disk user including format, verify, repair, editor & search routines.

"Overall a good selection of numerous utilities and a recommended buy at around £35" **MICRO USER – JUNE 1986.**

NOW ONLY £29.95

ROM MASTER

New improved version of our powerful Rom management system.

Now with even more commands to control your errant Roms. This Rom will keep others turned off even through CTRL BREAK. Over 20 commands including the ability to encrypt & de-crypt files to keep them secure from prying eyes.

PRICE £14.95

■ VECTOR 1 ▸

TAPE TO DISK UTILITY

FEATURES

+ Once only purchase
+ Can save to any disk
+ Very user friendly, help pages on disk
+ 40/80 Format
+ No awkward ROMs, can be used on any machine
+ Can load to all available RAM &400-&7FFF
= Simply the best tape to disk utility available

Vector 1 versions compatible with Acorn, Opus, UDM, Cumana, BBC+ & Watford (Not 1-42, 1-43 DFS's.)

■ VECTOR 2 ▸

VECTOR 1 & VECTOR 2 now compatible with BBC+ and Master series Please state DFS when ordering

DISK UTILITY

Features

+ 40/80 Format
+ User friendly, menu driven
+ Contains powerful features such as a disk sector editor, Disk Compare, format, verify and track repair
= The most powerful disk utility available

NEW IMPROVED VERSION (1.40)
Send £2.00 with old disk for upgrade.
Prices: £12.00 each for Vector 1 or Vector 2 £23 for both.

SCYTHE TOOLKIT **£21.95**
(Send for full details)

All prices shown include VAT and p&p. Please add £3.00 per disk if you require 3" disks and specify when ordering.

Orders to:
CHALICE SOFTWARE, Dept MU
3 Merlin Way, Covingham,
Swindon SN3 5AN.
Telephone 0793 615026

QUESTION:- What is the difference between a BBC with System Delta and an IBM with dBase II ?

ANSWER:- Over £2000 !

Look more closely and you will find further differences. System Delta has 150 commands which are written as an extension to the 128 BBC BASIC commands. Programs are written using BASIC - a language that most programmers already know, thus reducing the learning curve. System Delta is compatible with all BBC systems and doesn't need the additional purchase of a second processor.

Demonstrations of Graph and Reports programs at the recent Acorn User Show confirmed the speed and power of System Delta and BBC BASIC. Several dBASE programmers quoted at least 1/2 day and 5-6K of program for the graph which was achieved in just TEN minutes and 13 lines of BASIC. This power and flexibility of System Delta is available to you at **ONLY £64.95** so why spend more?

FREE CARD INDEX
Many people buy System Delta purely for the powerful, versatile, Card Index which has received many excellent reviews and been quoted as "exceptionally simple", "ranks with the best databases", "fast and versatile", "a great innovation with its flexibility", "unreservedly recommended" - - - - what's more, it's ABSOLUTELY FREE!

APPLICATIONS **- for use with System Delta ROM**
FLEXIBILITY, EFFICIENCY and SIMPLICITY are the key features :

MAILSHOT - mailmerge and labels	£19.95
VIDEO RENTAL - for efficient shop management	£54.95
SCHOOL ADMINISTRATOR - the most flexible system available	£69.95
HOTELIER - 80 room comprehensive management, bills, mailist	£59.95
NEWSAGENT - Time saving and informative.	£54.95
ORDER PROCESSING/INVOICING - unbeatable on flexibility	£45.95
SALES LEDGER - merge with invoicing or use on its own	£45.95

SYSTEM DELTA REFERENCE GUIDE
Programmers can write their own programs quickly and efficiently with the aid of the 160 page Reference Guide which contains full technical details, example usage and even a fully explained relational tutorial program. **£19.95**

CUSTOMISATION
Any application may be customised or you may have your own system written for you. Contact us if you have an application in mind - it may well be under development at the current time.

PRINTERS ANGEL

NLQ Font Designer
Define your own character fonts for the popular NLQ printers. Fast machine code screen handling routines for fast, simple character definition. Banner mode for designing multiple character definitions. Slant/unslant for easy italics. Create part fonts for merging character sets. Definable figure of eight grid for character design and size consistency. 5 popular type fonts provided. Needs 6264 RAM chip (£6 Extra).



£27.95

PLEASE SEND BY RETURN ☐
PLEASE SEND FURTHER DETAILS ☐
System Delta with FREE Card Index ☐
Reference Guide ☐ Video Rental ☐
School Admin ☐ Mailshot ☐
Order Entry/Invoice ☐ Hotelier ☐
Sales Ledger ☐ Printers Angel ☐

Cheque/Access No.....

Name.....

Address.....

.....

.....

..... Ref. MU12.6b

MINERVA SYSTEMS, 69 SIDWELL STREET, EXETER, DEVON, EX4 6PH. Tel: 0392 37756

From Page 111

```
  10 REM Santa's Sleigh
  20 REM By Andrew Waite
  30 REM (c) The Micro User
  40 MODE7:VDU23,1,0;0;0;0;19,1,2;0;
  50 PROCinst:PROCinit
  60 REPEAT
  70 live%=4:score%=0
  80 stage%=1:tres%=0
  90 ex1%=FALSE:RESTORE 2390
 100 FOR N%=1 TO 8
 110 READ tx%(N%),ty%(N%)
 120 NEXT
 130 REPEAT
 140 MODE 5
 150 VDU 23;8202;0;0;0;
 160 COLOUR 129
 170 FOR N%=0 TO 29
 180 PRINT TAB(0,N%);CHR$224;TAB(19,
N%);CHR$224
 190 NEXT
 200 COLOUR 128:COLOUR 1
 210 PRINT TAB(2,27);"00000"
 220 PRINT TAB(7-LEN STR$(score%),27
);score%
 230 PRINT TAB(15,29);stage%
 240 PRINT TAB(4,29);live%
 250 COLOUR 3
 260 PRINT TAB(2,26);"SCORE"
 270 PRINT TAB(14,26);"FUEL"
 280 PRINT TAB(13,28);"SCREEN"
 290 PRINT TAB(2,28);"LIVES"
 300 RESTORE 2350
 310 FOR N%=1 TO 56
 320 READ X%,Y%,W%,V%
 330 IF V%=224 COLOUR 129:COLOUR 3
 340 IF V%=225 COLOUR 128:COLOUR 3
 350 IF V%=234 COLOUR 128:COLOUR 2
 360 IF V%=235 COLOUR 128:COLOUR 1
 370 PRINT TAB(X%,Y%);STRING$(W%,CHR
$V%);
 380 NEXT
 390 VDU 5
 400 RESTORE 2400
 410 FOR N%=1 TO 8
 420 READ X%,Y%
 430 IF tx%(N%)=0 THEN 460
 440 GCOL 0,1:MOVE X%*64,(32-Y%)*32:
VDU250
 450 GCOL 0,2:MOVE X%*64,(32-Y%)*32:
VDU251
 460 NEXT
 470 B$=CHR$240+CHR$241
 480 S$=CHR$228+CHR$229
 490 S1$=CHR$230+CHR$231
 500 sy%=10:su%=FALSE:by%=3:up%=TRUE
 510 X%=628:Y%=200:FUEL%=400:SPEED%=
0
 520 char%=226:char2%=227:new%=0
 530 out%=TRUE:walk%=FALSE:GCOL 3,1
 540 MOVE X%,Y%:PRINT CHR$226
 550 COLOUR 128:COLOUR 1
 560 IF G$="K" PROCkey ELSE PROCjoy
 570 UNTIL live%=0
 580 FORN%=1 TO 10
 590 FORM%=1 TO 2000:NEXT
 600 PRINT TAB(4+N%,15);MID$("GAME
OVER",N%,1)
 610 NEXT
 620 FORN%=1 TO 10000:NEXT
 630 FOR N%=8 TO 1 STEP -1
 640 IF score%>HI%(N%) HI%(N%)=HI%(N
%-1):HI$(N%)=HI$(N%-1):new%=N%
 650 NEXT
 660 MODE7:PROChi
 670 UNTIL FALSE
 680 :
 690 DEF PROCinit
 700 VDU 23,224,255,16,16,16,255,1,1
,1
 710 VDU 23,225,0,0,0,0,0,0,0,255
 720 VDU23,226,48,112,120,176,58,57,
127,126
 730 VDU23,227,12,14,30,13,92,156,25
4,126
 740 VDU23,228,135,127,57,123,255,52
,84,147
 750 VDU23,229,225,254,156,222,255,4
4,42,201
 760 VDU23,230,1,1,1,1,1,1,1,1
 770 VDU23,231,128,128,128,128,128,1
28,128,128
 780 VDU 23,234,129,66,36,24,24,36,6
6,129
 790 VDU 23,235,0,0,0,0,8,28,62,127
 800 VDU23,240,247,119,255,127,255,1
27,247,119
 810 VDU23,241,238,239,254,255,254,2
55,238,239
 820 VDU23,250,231,231,231,0,0,231,2
31,231
 830 VDU23,251,24,24,24,255,255,24,2
4,24
 840 DIM tx%(8),ty%(8)
 850 DIM HI$(10),HI%(10)
 860 FOR N%=1 TO 10
 870 HI$(N%)="The Micro User"
 880 HI%(N%)=1100-(100*N%)
 890 NEXT
 900 ENDPROC
 910 :
 920 DEF PROCkey
 930 REPEAT
 940 IF INKEY(-98) L%=TRUE ELSE L%=F
ALSE
 950 IF INKEY(-67) R%=TRUE ELSE R%=F
ALSE
 960 IF INKEY(-74) F%=TRUE ELSE F%=F
ALSE
 970 PROCgame
 980 UNTIL out%=FALSE
 990 ENDPROC
1000 :
1010 DEF PROCjoy
1020 REPEAT
1030 joy%=ADVAL(1)
1040 but%=ADVAL(0) AND 3
1050 IF joy%>&D000 L%=TRUE ELSE L%=F
ALSE
1060 IF joy%<&2000 R%=TRUE ELSE R%=F
ALSE
1070 IF but%=1 THEN F%=TRUE ELSE F%=
FALSE
1080 PROCgame
1090 UNTIL out%=FALSE
1100 ENDPROC
1110 :
1120 DEF PROCgame
1130 GCOL 3,1:X1%=X%:Y1%=Y%:char2%=c
har%
1140 IF L%=TRUE X%=X%-12:char%=227 E
LSE IF R%=TRUE X%=X%+12:char%=226
1150 IF F%=TRUE AND FUEL%>0 SPEED%=S
PEED%+2:FUEL%=FUEL%-1:SOUND &10,-15,5
,7
1160 Y%=Y%+SPEED%:IF walk%=FALSE SPE
ED%=SPEED%-1
1170 MOVE X%,Y%:PRINT CHR$(char%):MO
VE X1%,Y1%:PRINT CHR$(char2%)
1180 VDU 4:IF stage%>1 PROCspider:IF
 stage%>2 PROCbouncer
1190 PRINT TAB(14,27);FUEL%;" ":VDU
5
1200 A%=POINT(X%,Y%):B%=POINT(X%+56,
Y%):C%=POINT(X%,Y%-32):D%=POINT(X%+56
,Y%-32)
1210 IF (C%=3 OR D%=3) AND SPEED%>-9
 SPEED%=0:walk%=TRUE ELSE walk%=FALSE
1220 IF walk%=TRUE AND A%=0 AND B%=0
 ENDPROC
1230 IF A%=0 AND B%=0 AND C%=0 AND D
%=0 ENDPROC
1240 IF C%=-1 AND tres%=8 PROCend:ou
t%=FALSE:ENDPROC
1250 atres%=tres%:PROCtreasure:IF (a
tres%+1)=tres% ENDPROC
1260 PROCexplode:out%=FALSE:ENDPROC
1270 :
1280 DEF PROCtreasure
1290 RESTORE 2400
```

→

```
 1300 FOR N%=1 TO 8:READ px%,py%
 1310 IF ((N%<5 AND X%<=tx%(N%)) OR (
N%>4 AND X%+40>=tx%(N%))) AND (ty%(N%
)-8<Y% AND ty%(N%)+36>Y%) PROCscore
 1320 NEXT
 1330 ENDPROC
 1340 :
 1350 DEF PROCscore
 1360 VDU 4
 1370 COLOUR 3
 1380 PRINT TAB(px%,py%);CHR$225;TAB(
px%,py%-1);" "
 1390 COLOUR 1
 1400 score%=score%+100
 1410 tres%=tres%+1
 1420 tx%(N%)=0:ty%(N%)=0
 1430 SOUND 1,-15,100,5
 1440 PRINT TAB(7-LEN STR$(score%),27
);score%
 1450 IF score%>1999 AND ex1%=FALSE l
ive%=live%+1:FOR M%=1 TO 3:SOUND 1,-1
5,200,5:SOUND 1,0,0,5:NEXT:ex1%=TRUE:
PRINT TAB(4,29);live%
 1460 VDU 5
 1470 SPEED%=0
 1480 GCOL0,1
 1490 MOVEX%,Y%
 1500 PRINTCHR$char%
 1510 GCOL3,1
 1520 ENDPROC
 1530 :
 1540 DEF PROCend
 1550 VDU 4
 1560 REPEAT
 1570 IF FUEL%>4 score%=score%+4:FUEL
%=FUEL%-4 ELSE score%=score%+FUEL%:FU
EL%=0
 1580 PRINT TAB(7-LEN STR$(score%),27
);score%
 1590 PRINT TAB(14,27);FUEL%;" "
 1600 SOUND &11,-15,200-FUEL%,1
 1610 UNTIL FUEL%=0
 1620 *FX 15,1
 1630 RESTORE 2390
 1640 FOR N%=1 TO 8
 1650 READ tx%(N%),ty%(N%)
 1660 NEXT
 1670 tres%=0:CLS
 1680 PRINT''" YOU ESCAPE TO FIND"''"
  MORE presents..."
 1690 FOR N%=1 TO 10000:NEXT
 1700 stage%=stage%+1
 1710 VDU 5
 1720 ENDPROC
 1730 :
 1740 DEF PROCspider
 1750 IF su%=TRUE PRINT TAB(9,sy% DIV
 2);"  ":sy%=sy%-1 ELSE PRINT TAB(9,s
y%DIV 2);S1$:sy%=sy%+1
 1760 PRINT TAB(9,sy% DIV 2);S$
 1770 IF sy%>50 su%=TRUE ELSE IF sy%<
12 THEN su%=FALSE
 1780 ENDPROC
 1790 :
 1800 DEF PROCbouncer
 1810 PRINT TAB(4,by%);"  ";TAB(14,25
-by%);"  "
 1820 IF by%<3 up%=FALSE ELSE IF by%>
22 up%=TRUE
```

This is one of hundreds of programs now available FREE for downloading on MicroLink

```
 1830 IF up%=TRUE by%=by%-1 ELSE by%=
by%+1
 1840 PRINT TAB(4,by%);B$;TAB(14,25-b
y%);B$
 1850 ENDPROC
 1860 :
 1870 DEF PROCexplode
 1880 live%=live%-1
 1890 VDU 4:GCOL 0,3
 1900 SOUND &10,-15,6,40
 1910 FOR N%=1 TO 20
 1920 MOVE X%+20,Y%-20
 1930 DRAW X%+RND(100)-RND(50),Y%+RND
(100)
 1940 NEXT
 1950 FORN%=1 TO 10000:NEXT
 1960 ENDPROC
 1970 :
 1980 DEF PROChi
 1990 VDU 19,1,3;0;23,1,0;0;0;0;
 2000 HI$(new%)=STRING$(30,".")
 2010 *FX 15,1
 2020 HI%(new%)=score%
 2030 IF new%<>0 PROCprinthi:PRINT TA
B(7,22);"Please enter your name":INPU
T TAB(5,2+(2*new%))HI$(new%)
 2040 PROCprinthi
 2050 PRINT TAB(3,23)CHR$131;"Hold Sp
ace or Fire for a new game"
 2060 REPEAT FORI%=4 TO 19 STEP2:PRIN
TTAB(1,I%)CHR$(RND(7)+127):FORJ%=1TO1
0:NEXT:NEXT: UNTIL INKEY(0)=32 OR (AD
VAL(0)AND3)=1
 2070 ENDPROC
 2080 :
 2090 DEF PROCprinthi
 2100 CLS:VDU23;8202;0;0;0;
 2110 FORX=1 TO 2:PRINT TAB(10,X)CHR$
141CHR$130;"TODAY'S HI SCORES":NEXT
 2120 FOR N%=1 TO 8
 2130 PRINT'CHR$(128+(N% MOD 7));" ";
N%;STRING$(3-LEN STR$(N%)," ");HI$(N%
);STRING$(30-LEN HI$(N%),".");HI%(N%)
 2140 NEXT
```

```
 2150 IF new%=0 PRINT TAB(9,20)CHR$13
0CHR$136;" Your score was ";score%
 2160 ENDPROC
 2170 :
 2180 DEFPROCinst
 2190 FOR X= 1 TO 2:PRINT TAB(1,X)CHR
$141CHR$131;"Santa's Sleigh......by A
ndrew Waite":NEXT X
 2200 PRINT'CHR$129"Someone has stole
n Santa's presents and"CHR$129"hidden
 them in an old warehouse. It is":PRI
NTCHR$129"guarded by a gruesome spide
r and two":PRINTCHR$129"grisly bounce
rs."
 2210 PRINT'CHR$134"Santa can land on
 the brick floors but":PRINTCHR$134"w
atch out for the spikes and don't":PR
INTCHR$134"crash land too quickly! Sa
nta's sleigh":PRINTCHR$134"has a limi
ted supply of fuel so you'll":
 2220 PRINTCHR$134"have to be very ca
reful."
 2230 PRINT'CHR$129"After collecting
all the presents in a":PRINTCHR$129"r
oom, move on to the next through the"
:PRINTCHR$129"tunnel at the bottom of
 the screen."
 2240 PRINT'CHR$130"   Z=LEFT   X=RIG
HT   RETURN=FIRE":PRINTCHR$130"
  or use a joystick."
 2250 PRINT'CHR$131"Do you want sound
 in the game Y/N? "
 2260 REPEAT:G$=GET$:UNTIL G$="Y" OR
G$="N"
 2270 IF G$="N" THEN *FX 210,1
 2280 IF G$="Y" THEN *FX 210,0
 2290 PRINTCHR$11;SPC(6);CHR$131;CHR$
136"Press Space or Fire"SPC(8)
 2300 REPEAT
 2310 G$=INKEY$(5):IFG$=" " G$="K"
 2320 IF (ADVAL(0)AND3)=1 G$="J"
 2330 UNTIL G$="K" OR G$="J"
 2340 ENDPROC
 2350 DATA 0,0,20,224,0,30,9,224,11,3
0,9,224,1,25,8,224,11,25,8,224,8,26,1
,224,8,27,1,224,8,28,1,224,8,29,1,224
,11,26,1,224,11,27,1,224,11,28,1,224,
11,29,1,224,6,4,8,224,7,8,2,224,7,12,
2,224,7,5,1,224,7,6,1,224,7,7,1,224,1
2,5,1,224
 2360 DATA 12,6,1,224,12,7,1,224,11,8
,2,224,1,5,3,224,1,10,3,224,1,15,3,22
4,1,20,3,224,16,5,3,224,16,10,3,224,1
6,15,3,224,16,20,3,224,6,12,3,224,6,1
8,3,224,11,12,3,224,11,18,3,224,9,1,2
,224,9,2,2,224,9,3,2,224
 2370 DATA 6,17,3,225,11,17,3,225,1,4
,3,225,1,9,3,225,1,14,3,225,1,19,3,22
5,16,4,3,225,16,9,3,225,16,14,3,225,1
6,19,3,225,6,11,3,225,11,11,3,225,1,2
4,8,235,11,24,8,235
 2380 DATA 6,3,3,235,11,3,3,235,8,7,1
,225,11,7,1,225
 2390 DATA 196,896,196,736,196,578,19
6,418,1052,896,1052,736,1052,578,1052
,418
 2400 DATA 2,4,2,9,2,14,2,19,17,4,17,
9,17,14,17,19
```

This listing is included in this month's cassette tape offer. See order form on Page 167.

B AND S COMPUTING (NOTTM) LTD

55 CEDAR AVENUE, LONG EATON, NOTTINGHAM NG10 3JQ.

Tel: 0602 736273

BUSINESS SYSTEMS · VIDEO SYSTEMS · MEDIA

ACORN APPROVED DEALER

Callers welcome to our distribution centre. Please phone for appointment.

ACORN PRODUCTS

BBC Master 128	£399(a)
BBC Master ET (Econet filing system only)	£328(a)

BBC MASTER COMPACT
— PHONE FOR SPECIAL PACKAGED PRICES

Turbo Upgrade	£100(c)
Turbo 512 Upgrade	£329(a)
SC Upgrade	P.O.A.
Master Eprom Cartridge	£13(e)
64K Upgrade kit for B+ 64K	£29(d)
Z80 Second Processor	£324(a)
6502 Second Processor	£164(a)
1770 Disc Interface	£40(e)
ADFS ROM (BBC B+ or BBC B with 1770 Interface)	£25(e)

DOT MATRIX PRINTERS

Kaga KP810 80 col/150 cps + 27 cps NLQ	£219(a)
Mannesmann Tally MT80+ 80 col/100 cps	£161(a)
Mannesmann Tally MT85 80 col/180 cps + 45 cps NLQ	£314(a)
Epson LX86 80 col/120 cps + 16 cps NLQ	£209(a)
Epson FX85 80 col/160 cps + 32 cps NLQ	£329(a)
Epson LQ 800 80 col/200 cps + 67 cps NLQ	£494(a)
Juki 5510 80 col/180cps + 30cps NLQ	£229(a)

** SPECIAL PRINTER OFFERS **

Juki 6100 (Daisy Wheel) 20cps	£229(a)
MP Daisy Junior (Daisy Wheel) 14cps	£149(a)
Canon PW1080A (Dot Matrix) 80col/150cps + 27cps NLQ	£219(a)
Citizen 120D 80 col/120 cps + 25 cps NLQ	£150(a)

MONITORS

Philips BM7502 High Res Mono Green + Sound	£69(a)
Philips BM7522 High Res Mono Amber + Sound	£74(a)
Philips CM8501 Std Res Colour RGB + Sound	£174(a)
Philips CM8533 Med Res Colour RGB + Composite Video + Sound (Green screen switchable)	£239(a)
Philips CF1114 TV/RGB Monitor	£169(a)
Hantarex Med Res Colour RGB/CV + Sound	£159(a)
Microvitec 1431MS Std Res Colour RGB	£179(a)
Microvitec 1451MS Med Res Colour RGB	£224(a)
Microvitec 1441MS High Colour Res RGB	£375(a)
Master Monitor Plinth	£12(c)
Master Monitor Plinth with shelf	£22(b)

* ALL MONITORS ARE SUPPLIED WITH A FREE BBC LEAD *

DISC DRIVES

Opus 5401 single SS 40T 100K	£73(a)
Opus 5802 Single DS 40/80T 400K	£91(a)
Opus 5802SD Single DS 40/80T 400K + PSU (Dual Case)	£109(a)
Opus 5802D Dual DS 40/80T 800K + PSU	£214(a)
Opus Challenger 3: 256K RAM Disc	£165(a)
Opus Challenger 3: 512K RAM Disc (2 x 256K)	£200(a)

DISCS

3M 744 SS/DD 48tpi 5.25" (box of 10)	£11(d)
3M 745 DS/DD 48tpi 5.25" (box of 10)	£13(d)
3M 747 DS/DD 96tpi 5.25" (box of 10)	£17(d)
3M 35SS SS/DD 3.5" (box of 10)	£23(d)
3M 35DS DS/DD 3.5" (box of 10)	£33(d)

Library Cases £1.50(e) or £1.00 if purchased with discs

MODEMS

Miracle WS2000 + BBC Lead	£100(c)
Miracle WS2000 Auto Dial Board	£28(d)
Miracle WS2000 Auto Answer Board	£28(d)
Miracle WS3000 V2123 + BBC Lead	£269(a)
Miracle WS3000 V22 + BBC Lead	£449(a)
Miracle WS3000 V22bis + BBC Lead	£599(a)
Miracle WS4000 V2123 + BBC Lead	£144(a)
Miracle Databeeb Communications ROM	£24(e)
Pace Nightingale + Commstar + BBC Lead	£114(c)
Nightingale Auto Dial/Auto Answer Board	£44(d)
Nightingale Auto Dial/Auto Answer Software	£10(e)
Pace OBBS Bulletin Board Software	£19(e)

*** PLEASE NOTE: BABT APPROVAL ON MODEMS ONLY ***

FANFOLD PAPER AND LABELS

2000 × 1 Part 60gm 11" × 9.5" Std Perf	£11(c)
1000 × 1 Part 85gm 11" × 9.5" Micro Perf	£9(c)
1000 × 1 Part 90gm PERFECT A4 Micro Perf	£13(c)
1000 x 2 Part NCR 60gm 11" x 9.5" STD Perf	£17(b)
1000 Labels 90mm × 36mm	£4(d)
1000 Labels 90mm × 49mm	£6(d)
1000 Labels 102mm × 36mm	£5(d)

PLEASE STATE SINGLE OR TWIN ROW WHEN ORDERING LABELS

AMX MOUSE AND SOFTWARE

AMX Mouse and Super Art	£65(d)
AMX Pagemaker	£37(d)

PLEASE STATE COMPUTER (B/B+/MASTER)

ROM BOARDS

ATPL 'Sidewise'	£36(d)

PRINTER RIBBONS & ACCESSORIES

Epson 8143 Serial XON/XOFF + 0K Buffer	£26(d)
Epson 8148 Serial XON/XOFF + 2K Buffer	£59(d)
Epson LX80/86 Ribbon (compatible)	£2.89(e)
Epson 8302 LX80/86 Tractor Unit	£19(c)
Epson 8338 LX80/86 Single Sheet Feeder	£49(b)
Epson MX80/FX80/FX85 Ribbon (compatible)	£2.24(e)
Citizen 120D Ribbon	£4(e)
Mannesmann Tally MT85 Fabric Ribbon	£4.50(e)
Mannesmann Tally MT85 Carbon Film Ribbon	£5.50(e)
Mannesmann Tally MT85/M86 Font Cartridge	£17(e)
Centronics Parallel Printer Lead (1.5m)	£6(e)

FULL RANGE OF RIBBONS & ACCESSORIES SUPPLIED — CALL FOR DETAILS

LANGUAGES

Micro-Prolog	£49(d)	ISO-Pascal	£42(d)
BCPL	£37(c).	Forth £32(e)	Comal £32(d). LISP £32(e)
Logo	£44(d)		

BUSINESS SOFTWARE

View 2.1	£37(d)	View Sheet	£37(d)
View 3.0	£57(d)	View Store	£37(d)
View Spell	£37(d)	View Plot (Disc)	£21(e)
Hi-View	£37(d)	View Index (Disc)	£10(e)
View Printer Driver Generator	Tape £7(e) Disc £8(e)		
Inter-Sheet	£39(d)	Inter-Chart	£26(d)
Inter-Word	£39(d)	Inter-Base	POA
Wordwise	£30(d)	Wordwise Plus	£37(d)

UTILITIES

Fleet Street Editor (Mirrorsoft)	£31(d)
Fleet Street Editor Fonts and Graphics (Mirrorsoft)	£11.75(e)
Fontwise Plus (Clares Micro Supplies)	£16(e)
Replica III (Clares Micro Supplies)	£10.50(e)

Please state 40 or 80 track when ordering.

BOOKS (No VAT on Books)

Master Reference Manual:	Part 1 £14(d). Part 2 £14(d)		
Advanced Master Reference Manual	£19(d)		
ISO Pascal*	£6.50(e)	Forth	£6.50(e)
View Guide	£4.50(e)	Into View	£4.50(e)
View 3	£9(e)	View Sheet	£9(e)
View Store	£9(e)	Lisp	£6.50(e)
BCPL	£14(d)		

* LARGE RANGE SUPPLIED — PHONE FOR DETAILS *

UK customers: please add 15% VAT to all prices (including carriage) Government and Educational establishments official orders welcomed. When ordering please enclose a cheque or postal order for the appropriate amount.

UK Carriage rates: (a) £8.50 - courier insured delivery. (b) £3.50. (c) £2.50. (d) £1.50. (e) £1.00.
All prices are correct at time of going to press. All offers are subject to availability.
All prices are subject to change without prior notification and are available on request. Current price list is available on request.

SOFTWARE SERVICES

65 SOUTH MOSSLEY HILL ROAD
ALLERTON, LIVERPOOL L19 9BG
051-427 7894

Floppy-Wise PLUS

THE SUPER ROM TO ECLIPSE ALL THE OTHERS
40 COMMANDS ON A 16K CHIP
FULLY TUBE COMPATIBLE

FLOPPYWISE PLUS FOR THE MODEL B

£29.95 + £1 P&P

COMMAND LIST: Ascii, Autosave, Bad, Bmove, Clear, Clm, Clone, Convert, Crom, Derrors, Download, Dsearch, Dspace, Dtape, Dts, Dzap, Edit, Fcompare, Find, Format, Free, Idzap, Mcopy, Menu, Move, Msearch, Mzap, Prepare, Protect, Ramload, Rcopy, Recover, Restore, Roms, Rsearch, Rzap, Tdisk, Tds, Tokens, Verify.

MUST NOT BE USED TO INFRINGE COPYRIGHT LAWS.
"Thoroughly Recommended" Micro User Nov. '85

FLOPPY WISE MASTER – THE ONLY UTILITIES ROM FOR THE ACORN MASTER SERIES

As 'PLUS', but no Prepare, Protect, Dts, Tds, Rcopy or Clone. Added are Mdelete, Mlock, Fs, Files, Rclear, Rmove. ADFS format and Verify replace the DFS routines.

FULLY REWRITTEN TO TAKE ADVANTAGE OF THE NEW MASTER FEATURES – ADFS/SHADOW RAM etc.

LOC-KIT

Professional Disk Protection System

Full Protection of disks and programs. Stop use and/or copying. **40/80T DISK.**

£25.00 + 50p P&P

PROC-KIT

THE Procedures Management System

Up to **255 Files** on any disk with automatic saving and loading of files from disk or program (embedded procedures and GOTO's all catered for). List, Rename or Merge any file.
PLUS: 40 Procedures to start you off – including a special **OVERLAY** Routine for program extension allowing effective lengths up to 400K with single disk drive. **40/80T DISK**

£10.95 + 50p P&P

AD86

Assembler/Disassembler for the Model B/Master (6502/6512)

Disk based assembler and locator in ROM. Fully compatible with Wordwise, View and other Editors. Professional standard – used to compile Flopy-Wise. Fully featured disassembler – Print, Dump, Select ROM etc.

£29.95 + £1 P&P

SECURI-KIT

Make your own Security ROM with or without Password (Clock display on Master – Elapsed time on BBC B)

OR send us your details (name, address, phone no., serial no., Password) and we'll do it for you for £9.95 (+£1 p&p).

KIT £12.95 + £1 P&P
Contains 40/80T Disk & Blank Eprom

ROM/RAM SWITCHER

Don't buy an expensive cartridge until you've used the available sockets in your Master. This switcher gives you 4 extra slots using 27256's.

£9.95 + £1 P&P

PINEAPPLE SOFTWARE

Programs for the BBC models 'B' with disc drive with FREE updating service on all software

DIAGRAM

Still the only drawing program available for the BBC micro which gives you the ability to draw really large diagrams and scroll them smoothly around the screen stopping to edit them at any time if required.

Pineapple's unique method of storing the diagram information on disc means that the size of diagrams is limited only by the free space on disc, and not the amount of computer memory you have available. (A blank 80 track disc will allow up to 39 mode 0 screens of diagram).

The superb print routines supplied with the program enable large areas of the diagram to be printed in a single print run in a number of different sizes and rotated through 90 deg. if required. Full use can also be made of printers which have a wider than normal carriage available.

The program is fully compatible with the Marconi Tracker ball described below.

PLEASE STATE 40 or 80 TRACK DISC & WHETHER STANDARD BBC or MASTER VERSION IS REQUIRED

PRICE £25.00 + VAT

DIAGRAM UTILITIES

A suite of six utility programs which add additional features to the 'Diagram' drawing program. The utilities include the saving and loading of areas of diagram to and from disc. The ability to display the whole of your large diagram on the screen at one time (in either 4★4 or 8★8 screen format). The addition of borders and screen indents to diagrams, and the ability to shift a whole diagram in any direction.

PRICE £10.00 + VAT

MARCONI TRACKER BALL

This high quality device comes with it's own Icon Artmaster drawing program and utilities to enable it to be used in place of keyboard keys, joysticks, or with your own programs.

PRICE £60.00 + VAT p&p £1.75
PRICE INCLUDING 'DIAGRAM' SOFTWARE £79.00 + VAT p&p £1.75

TRACKER BALL for MASTER series

The Pointer ROM is supplied instead of the Icon Artmaster disc and enables the Tracker ball to work directly with the MASTER series computers. (e.g. to use with TIMPAINT etc.). Prices are the same as for the standard tracker ball.

POINTER

The Pointer Rom is available separately for people already owning tracker balls, and comes with instructions for use with the MASTER computer.

PRICE £12.50 + VAT

PCB

This new release from Pineapple is a printed circuit board draughting aid which is aimed at producing complex double sided PCB's very rapidly using a standard BBC micro and any FX compatible dot-matrix printer.

The program is supplied on EPROM and will run with any 32k BBC micro (including Master series). Also supplied is a disc containing a sample PCB layout to demonstrate the programs features.

By using an EPROM for the program code the maximum amount of RAM is available for storing component location and ASCII identification files etc. (Up to 500 components and 500 ASCII component descriptions may be stored for a given layout). These is no limit to the number of tracks for a given PCB, although the maximum size of board is restricted to 8" ★ 5.6".

Using a mode 1 screen, tracks on the top side of the board are shown in red, while those on the underside are blue. Each side of the board may be shown individually or superimposed. A component placement screen allows component outlines to be drawn for silk screen purposes and component numbers entered on this screen may be displayed during track routing to aid identification of roundels.

The print routines allow separate printouts of each side of the PCB in a very accurate expanded definition 1:1 scale, enabling direct contact printing to be used on resist covered copper clad board.

This program has too many superb features to describe adequately here, so please write or 'phone for more information and sample prinouts.

PRICE £85.00 + VAT

CONVERTER LEADS

Converter leads to enable the Trackerball to run mouse software and the mouse to run trackerball software (inc. DIAGRAM). Please state which way round when ordering.

PRICE £8.00 + VAT

BASIC COMPILER

Use our Basic Compiler to produce direct 6502 machine code programs and ROMs for your own Basic programs. Speed increases of up to 25 times are achieved.

PRICE £25.00 + VAT

ALL ORDERS SENT BY RETURN OF POST

39 Brownlea Gardens, Seven Kings, Ilford, Essex 1G3 9NL. ☎ Tel: 01-599 1476

From Page 105

```
  10 REM Christmas Box
  20 REM By R.A.Waddilove
  30 REM (c) Micro User
  40 *TV255,1
  50 MODE 7
  60 PROCinitialise
  70 PROCinstructions
  80 MODE 2
  90 REPEAT
 100 PROCvariables
 110 PROCboard
 120 PROCset_code
 130 REPEAT
 140 PROCinput
 150 PROCcheck
 160 UNTIL correct OR guesses=12
 170 IF correct PROCgot_it ELSE PROC
failed
 180 PROCanother_game
 190 UNTIL INSTR("Nn",key$)
 200 MODE 7
 210 END
 220
 230 DEF PROCinstructions
 240 FOR i=1 TO 2:PRINT TAB(10)CHR$1
41"Christmas Box":NEXT
 250 PRINT''CHR$131"It's Christmas E
ve and the presents"'CHR$131"are unde
r the tree. Can you guess"'CHR$131"wh
at is in them?"
 260 PRINT'CHR$134"There are seven d
ifferent types of"'CHR$134"present nu
mbered 1 to 7 and you"'CHR$134"have t
welve guesses. Press a number"'CHR$13
4"to place a present and delete to"'C
HR$134"erase it."
 270 PRINT'CHR$131"Your guess will b
e marked: a black"'CHR$131"peg means
that one of the presents"'CHR$131"is
correct and in the right place."
 280 PRINT CHR$131"A white peg means
 that one of the"'CHR$131"presents is
 correct but in the"'CHR$131"wrong pl
ace."
 290 PRINT''CHR$129"Press the SPACE
BAR to start...";
 300 REPEAT UNTIL GET
 310 ENDPROC
 320
 330 DEF PROCinitialise
 340 VDU23,224,60,126,255,255,255,25
5,126,60
 350 VDU23,225,124,68,108,40,40,40,4
0,16
 360 VDU23,226,124,124,124,56,56,56,
56,16
 370 VDU23,230,239,239,239,239,0,239
,239,239
 380 VDU23,240,60,60,60,60,60,60,129
,255
 390 VDU23,241,136,138,141,137,138,1
40,248,112
 400 VDU23,242,16,40,16,124,186,16,4
0,108
 410 VDU23,243,56,124,254,198,198,22
2,124,56
 420 VDU23,244,189,90,153,255,195,12
6,66,195
 430 VDU23,245,255,169,217,175,221,1
75,221,255
 440 VDU23,246,248,252,250,255,255,2
55,170,68
 450 DIM code(5),guess(5)
 460 DIM marked_answer(5)
 470 DIM marked_guess(5)
 480 *FX4,1
 490 ENDPROC
 500
 510 DEF PROCvariables
 520 VDU22,1,23,1,0;0;0;0;
 530 guesses=0
 540 PRINT TAB(7,10)"How many types
of present?":COLOUR2:PRINT TAB(13,18)
"Press 4 - 7"
 550 REPEAT
 560 level=GET-48
 570 UNTIL level>3 AND level<8
 580 correct=0
 590 VDU22,2,23,1,0;0;0;0;
 600 ENDPROC
 610
 620 DEF PROCboard
 630 CLS:COLOUR 7:PRINT"   Xmas  Box
";TAB(3,27);
 640 FOR i=1 TO 5:R%=RND(7):COLOUR R
%:COLOUR 128+R%EOR7:VDU 230,9:NEXT
 650 COLOUR7:COLOUR128:PRINT TAB(0,3
0)"Keys:";:FOR i=1 TO level:COLOUR7:V
DU 48+i,8,10:COLOUR i:VDU 239+i,9,11:
NEXT
 660 FOR i=208 TO 976 STEP 64
 670 MOVE 96,i:DRAW 1160,i
 680 NEXT
 690 MOVE 96,96:DRAW 1160,96
 700 MOVE 160,96:DRAW 160,976
 710 MOVE 96,96:DRAW 96,976
 720 MOVE 800,96:DRAW 800,976
 730 MOVE 1160,96:DRAW 1160,976
 740 SOUND1,-15,50,5
 750 ENDPROC
 760
 770 DEF PROCset_code
 780 FOR i=1 TO 5
 790 code(i)=RND(level)
 800 NEXT
 810 ENDPROC
 820
 830 DEF PROCinput
 840 *FX21
 850 guesses=guesses+1
 860 PRINT TAB(3,26-2*guesses);
 870 VDU23,1,1;0;0;0;
 880 i=0
 890 REPEAT
 900 i=i+1
 910 REPEAT
 920 present=GET-48
 930 IF i>1 AND present=79 VDU 8,127
:i=i-1
 940 UNTIL present>0 AND present<=le
vel
```

This is one of hundreds of programs now available FREE for downloading on MicroLink

```
 950 SOUND1,-15,100,1
 960 guess(i)=present
 970 COLOUR present:VDU 239+present,
9
 980 UNTIL i=5
 990 VDU23,1,0;0;0;0;
1000 ENDPROC
1010
1020 DEF PROCcheck
1030 COLOUR 7
1040 FOR i=1 TO 5
1050 IF guess(i)=code(i) PROCblack_p
eg ELSE marked_answer(i)=FALSE:marked
_guess(i)=FALSE
1060 NEXT
1070 IF correct=5 ENDPROC
1080 correct=0
1090 FOR i=1 TO 5
1100 FOR j=1 TO 5
1110 IF guess(j)=code(i) AND NOT mar
ked_answer(i) AND NOT marked_guess(j)
 PROCwhite_peg
1120 NEXT
1130 NEXT
1140 ENDPROC
1150
1160 DEF PROCblack_peg
```

From Page 139

```
1170 VDU 225
1180 correct=correct+1
1190 marked_answer(i)=TRUE
1200 marked_guess(i)=TRUE
1210 ENDPROC
1220
1230 DEF PROCwhite_peg
1240 VDU 226
1250 marked_answer(i)=TRUE
1260 marked_guess(j)=TRUE
1270 ENDPROC
1280
1290 DEF PROCgot_it
1300 COLOUR 8
1310 PRINT TAB(3,0)"Xmas  Box"
1320 SOUND1,-15,100,20
1330 PROCpause(500)
1340 COLOUR 7
1350 PRINT TAB(3,0)"Xmas  Box"
1360 PROCdisplay_answer
1370 ENDPROC
1380
1390 DEF PROCfailed
1400 COLOUR 15
1410 PRINT TAB(3,27)" FAILED  "
1420 PRINT CHR$8;
1430 SOUND1,-15,0,20
1440 PROCpause(500)
1450 PRINT TAB(3,27)SPC9
1460 PROCdisplay_answer
1470 ENDPROC
1480
1490 DEF PROCdisplay_answer
1500 PRINT TAB(3,27);
1510 FOR i=1 TO 5
1520 SOUND1,-15,100,5
1530 COLOUR code(i)
1540 VDU 239+code(i),9
1550 PROCpause(50)
1560 NEXT
1570 COLOUR 15:PRINT CHR$30"  Press
Space     "
1580 *FX21
1590 REPEAT UNTIL GET
1600 ENDPROC
1610
1620 DEF PROCanother_game
1630 VDU22,1,23,1,0;0;0;0;
1640 COLOUR 3
1650 PRINT TAB(12,5)"Do you want to"
TAB(13,7)"play again ?"
1660 COLOUR2:PRINT TAB(12,10)"(Press
Y or N)":*FX21
1670 REPEAT
1680 key$=GET$
1690 UNTIL INSTR("YyNn",key$)
1700 VDU22,2,23,1,1;0;0;0;
1710 ENDPROC
1720
1730 DEF PROCpause(delay)
1740 TIME=0
1750 REPEAT UNTIL TIME>delay
1760 ENDPROC
```

This listing is included in this month's cassette tape offer. See order form on Page 167.

Microdis

FREE CABLE AND PAPER

DISCOUNT!

SPECIAL OFFERS

Daisystep Junior	139.08	159.95
National Panasonic	156.48	179.95
MP165 160cps/40NLQ	182.57	209.95

DOT MATRIX PRINTERS	Ex VAT	Inc VAT & Carriage
Canon PW1080A	217.35	249.95
Canon PW1156	334.74	384.95
Epson LX86 (new model) 120cps/25NLQ	239.09	274.95
Epson LX Tractor Attachment	18.91	21.75
Epson LX Sheet Feeder	48.65	55.95
Epson FX80 (160cps)	347.78	399.95
Epson P40 (Thermal, 80 col)	52.13	59.95
Juki 5510 186 cps/NLQ (colour option)	243.43	279.95
Juki 5510 Colour Upgrade	97.20	111.78
Juki 5520 Colour Printer	304.30	349.95
DAISYWHEEL PRINTERS		
Juki 6100	252.13	289.95
Juki 2200	243.74	269.95
LASER/INK JET PRINTERS		
Epson SQ2000 Inkjet	1529.82	1759.30
OMS Kiss Laser	1995.00	2294.00
Canon LP88A1	2600.00	2990.00

FREE! FREE! FREE!
WITH EVERY PRINTER –
LISTING PAPER + BBC LEAD
(phone for other leads)

LISTING PAPER		
60 GSM (Listing) 9.5"x11" 2000 sheets	15.00	17.25
80 GSM (letter grade) 9.25"x12" 2000 sheets	17.90	20.58
Labels – Box of 8000	39.00	44.86
(2 abreast on 9.5" backing with central perf.)		
MONITORS –		
Philips 7502 (Green)	74.74	85.95
Philips 7522 (Amber)	82.57	94.95
Colour 14" Screen		
Philips TV/Monitor	182.57	209.95
Sanyo CD5123	173.73	199.95

FAST SERVICE

24 HOUR HOTLINE
0783 872430
NOTE: ALL PRICES INCLUDE VAT + CARRIAGE

INCREDIBLE DISC DRIVE PRICES

HIGH QUALITY DISC DRIVES
Cased with leads, etc
FREE DISCS WITH EVERY DRIVE PURCHASED BEFORE CHRISTMAS

5.25"	Ex VAT	Inc VAT & Carriage
Acorn DFS	40.83	46.95
Opus DDOS	40.83	46.95
BBC SX (Uses BBC's Power Supply)		
PSX100 40 track single side (100K)	69.52	79.95
SX400S 80 track double side (400K)	95.61	109.95
Dual Ex PSU		
DX200 Dual 40 track single side	130.39	149.95
DX800S Dual 80 track double side	173.87	199.95
Single With Power Supply		
S100 40 track single side	82.57	94.95
S400S 80 track double side	113.00	129.95
Dual Drives (with Power Supply)		
D200 2x40 track single side	173.87	199.95
D400S 2x80 track single side	199.96	229.95
D800S 2x80 track double side	199.96	229.95

NOTE – All 80 track drives have a 40/80 switch!

CHALLENGER SPECIAL

Challenger 256K	156.48	179.95
Challenger 512K	173.87	199.95
Challenger 256 to 512K upgrade	31.26	35.95


MICROVITEC RGB MONITORS (BBC)		
1431 (472X585 dots)	193.00	221.95
1431 AMP54 (with audio & PAL)	219.09	251.95
1451 (653x582 dots)	234.74	269.95
1451 AMPS4	313.00	359.95

Dept. MU1286, 46 Middle Street, Blackhall, Hartlepool, Cleveland TS27 4EA.
Tel: 0783 872430
Sorry, office only – No callers without appointment
Prices and specifications subject to variation.
Please phone for best prices

BUSINESS SPECIAL
IBM Compatible OPUS PCII SYS.4.
Included as standard:
1Mb On-board RAM – 20Mb Hard Drive
Switchable 8MHz Turbo – High Res
Hercules Graphics Card & Monitor
Serial & Parallel Ports
Choice of Juki Daisywheel or MP165
Dot Matrix Printer.
NewWord Word Processor and Tutor
ONLY £1333 Ex VAT
PCII SYSs 1, 2 & 3 also available –
Phone for details

BBC ROM UTILITY SOFTWARE		
Wordwise	31.26	35.95
Wordwise Plus	40.65	46.75
View 2.1	41.26	47.45
View 3	61.00	70.15
COMPUTERS		
Master 128	426.04	489.95
Compacts	Phone for latest	
OTHER BBC PERIPHERALS		
Teletext Receiver	188.95	217.29
6502 Second Processor	177.50	204.13
Z80A Second Processor	312.95	359.89
ATPL ROM Board	39.09	44.95
MEDIA – ARCHIVE DATA		
(Fully guaranteed)		
High quality diskettes 5.25" boxed in 10's		
40 Track SSSD	9.13	10.50
40 Track DSDD	9.52	10.95
80 Track SSSD	12.83	14.75
80 Track DSDD	11.74	13.50
3" Box of 10	37.35	42.95
3" Disc (each)	3.91	4.50
HEAD CLEANING KITS		
3M Standard	13.87	15.95
Rexel Drive/VDU	19.96	22.95

TAXAN



with BBC cable & paper
£239.00 (£207.83 + VAT)

KAGA KP810

	Ex VAT	Inc VAT
KP910 17" width printer	346.96	399.00
KP810 Paper roll	3.43	3.95
Fontaid (NLQ Designer)	26.00	29.90

Panasonic KX-P1080
with BBC cable & paper
£159.00 (138.26+VAT)

Canon PW1080A
with BBC cable & paper
£239.00 (207.83+VAT)

CITIZEN 120D
with cable & paper
£175.00 (152.17+VAT)

STAR NL10
with BBC cable & paper
£236.90 (206.00+VAT)

JUKI 6100
with BBC cable & paper
£259.00 (225.22+VAT)

MP165
with BBC cable & paper
£199.00 (173.04+VAT)

EPSON LX86
with BBC cable & paper
£236.90 (206.00+VAT)

Epson FX85
with BBC cable & paper
£359.00 (312.17+VAT)

PRINTER ADD ONS

	Ex VAT	Inc VAT
LX Tractor Unit	18.22	20.95
LX Sheet Feeder	47.83	55.00
LX Dust Cover	4.00	4.60
LX View Printer Driver	8.65	9.95
Control/Dump Rom	13.00	14.95
KP Dust Cover	4.00	4.60
DP View Printer Driver	8.65	9.95
KP Control/Dump Rom	13.00	14.95

PRINTER/CABLES

	Ex VAT	Inc VAT
Star NB15	760.00	874.00
Epson LQ800	490.00	563.50
Epson FX100	425.22	489.00
Juki 2200	233.91	269.00
Centronics GLP2	138.26	159.00
1.2m (4 foot) BBC cable	6.00	6.90
2.0m (6 foot) BBC cable	7.78	8.95
Compact cable (printer)	8.65	9.95

DISC DRIVES SPECIAL OFFERS

New UFD CSX400A
400K/640K 40/80T disc drive from Akhter.
£99.00 Inc VAT
Drive & Acorn DFS
£147.00 Inc VAT
(Both above Special Offers finish on 24/12/86)

	ExVAT	InVAT
Cumana CSX100	84.35	97.00
Cumana CSX400	120.00	138.00
Cumana CS400	137.39	158.00
Cumana CD800S	253.04	291.00
Akhter MD400A	94.78	109.00
Akhter MD802E	216.52	249.00
Akhter MD802D	251.30	289.00

DISKETTES (lifetime warranty)

	Ex VAT	Inc VAT
10 96tpi D/S D/D in library case	13.90	15.99
10 Low cost 96tp D/S D/D in library case	7.39	8.50
10 Low cost 96tpi D/S D/D bulk packed	6.52	7.50

EPROMS, 8271
(Hitachi)

	Ex VAT	Inc VAT
1-9 27128 250nS	2.57	2.95
10+ 27128 250nS	2.30	2.65
1-9 2764 25nS	2.26	2.60
10+2764 250nS	2.00	2.30
1-9 27256 250nS	4.57	5.25
10+27256 250nS	4.13	4.75
1-9 TTL/Cmos set	4.77	5.49
1-9 8271 controller	32.17	37.00
10+8271 controller	30.43	35.00

ROMS/UPGRADES

	Ex VAT	Inc VAT
Inter-Word	38.26	44.00
Inter-Sheet	38.26	44.00
Inter-Chart	25.00	28.75
Wordwise Plus	38.26	44.00
View 2.1	36.52	42.00
View 3.0	55.65	64.00
ViewStore	36.52	42.00
ViewSpell	30.39	34.95
ViewPlot (disc)	22.61	26.00
1-9 6264LP 150nS	2.56	2.95
10+ 6264LP 150nS	2.30	2.65
Acorn 1770 DFS	42.61	49.00
Acorn 8271 DFS	41.74	48.00
B Plus 64K to 128K	26.00	29.90

MASTER/COMPACT

	Ex VAT	Inc VAT
Master 128K Micro	395.00	454.25
Master ET 128K Micro	338.00	388.70
512 Co-processor	334.78	385.00
Turbo Upgrade	103.48	119.00
Cartridges	14.95	14.95
Reference Manuals	14.95	14.95
View 3 User Guide	10.00	10.00
View Sheet User Guide	10.00	10.00
Master & B Dust Covers	3.00	3.45

Second user BBC B's bought and sold

MONITORS

	Ex VAT	Ex VAT
Philips CF1114	155.65	179.00
Philips CM8533	233.91	269.00
Philips BM7502	70.43	81.00
Philips BM7522	75.65	87.00
Taxan KX1201G P31	88.70	102.00
Taxan KX1202G P39	94.78	109.00
Taxan KX1203G	97.39	112.00
Taxan Sup. Vision 2	277.39	319.00
Taxan Sup. Vision 3	319.13	367.00

Compact & Master – phone for latest price

Microvitec 1451MS	223.48	257.00

(Prices inc. BBC Cable)

Phone for our best price before placing your order
EDUCATIONAL & GOVERNMENT ORDERS WELCOME
All products have a 12 month no quibble guarantee
Prices subject to variation without prior notification
We are closed all day Wednesday
Carriage 92p (80p + VAT) Securicor £6.90 (£6.00 + VAT)

WeServe

Next day delivery by Securicor


VISA

Micro Dept.
128 West Street,
Portchester,
Hants.
PO16 9XE
Tel: 0705 325354

A compact 256k memory expansion board that is fitted in seconds.

Of straight-forward plug in construction, the Chameleon board is inserted simply into the processor socket of the BBC Model B to give 256k of extra RAM.

Multi-processing software allows programs in each of four 32k banks to occupy up to 8000 hex, whilst being instantly available for use. Sideways software can be loaded into any of eight 16k banks using the ROM software provided.



chameleon

Compatible with most software and hardware add-ons (except ROM boards), it merges easily into its environment.


Complete with manual and ROM: **£126.50** inc VAT.
+ £2.50 postage and packing.

memex

P.O. Box 49
Newbury, Berkshire RG14 7AZ (0635) 34980

A BBC COMPATIBLE TRACKERBALL FOR ONLY £29.95

Full performace optical trackerball with precision bearings, heavy 2.25 inch ball and two independent control buttons.
Plugs directly into the BBC user port and will also run software intended for other similarly connected trackerballs.



The trackerball comes complete with –

SPLASH!

Superb art drawing program for the BBC Micro

This super-fast machine code program is packed with all the features you need to produce arty Mode 2 screen dumps that you can be really proud of. The on-screen menu makes it easy for even a young child to get excellent pictures, yet the combination of commands available allow you to generate amazing results with no effort at all. Some of the "trick" GCOL effects just have to be seen to be believed. Although intended for computer artistry, this program contains enough geometric and "technical" drawing commands to make it a SPLASH! with every type of user.

- Circles, ellipses, triangles, rectangles, etc.
- Brush and line thickness control
- Fast solid and colour pattern filling routines
- "Trick" colour effects available on all commands
- Spray paint, solid or patterned colours
- Full 16 solid colour operation, plus many pattern colours

Postage and packing £2.00
Please send your Cheque/P.O./Access No. for £31.95 to:
Datapen Microtechnology Ltd., Kingsclere Road, Overton, Hants RG25 3JB. Telephone: 0256 770488.

From Page 114

Program 1

```
   10REM
   20REM Colour Fill
   30REM By Stephen Austin
   40REM (c) The Micro User
   50REM
   60X%=&70:Y%=&72:scan_dir=&73:lx=&74:rx=&76:prev_lx=&78:prev_rx=&7A:prev_y=&7C:pointer=&7D:screen=&7E
   70temp1=&80:temp2=&81:temp3=&82:temp4=&83:temp5=&84:tempy=&85:stack=&86:back=&88:mask=&89:pat=&8A:pattern=&8B:col1=&8C:col2=&8D:type=&8E:column=&8F
   80pixels_per_byte=&A8:block_line=&A9:temp_lx_and_rx=&AA:OSWORD=&FFF1:?&226=0:?&227=&12
   90STACKLOC=&900:LOC=&1200:REM Cassette users change LOC to &A00
  100MODE135:IF HIMEM=&7C00 THEN table=&C423 ELSE MODE7:table=&C41A:REM set up table for model B or B+
  110FORPASS=0TO2STEP2
  120P%=LOC
  130[OPTPASS
  140BCCbegin
  150.end
  160RTS
  170.begin
  180CMP#96  \Is the PLOT number
  190BCCend  \between 96 and 104
  200CMP#104 \If not exit from
  210BCSend  \the progras
  220LDX#1       \Store 1 in coordinate
  230STXpointer  \stack pointer
  240DEX
  250STXSTACKLOC+3
  260.loop1        \Store graphics
  270LDA&320,X     \cursor on coord
  280STASTACKLOC,X \stack
  290INX
  300CPX#3
  310BNEloop1
  320STAprev_y
  330LDA#(STACKLOC+4)MOD256
  340STAstack    \Save location of
  350LDA#(STACKLOC+4)DIV256
  360STAstack+1  \coord stack
  370LDA&361
  380STApixels_per_byte
  390SEC
  400LDA#&80   \Save total number of
  410SBC&34E   \columns across screen
  420STAcolumn
  430LDA&314
  440PHA
  450LDA#9     \This OSWORD call
  460LDY#3     \is used to find
  470LDX#&10   \the colour of the
  480JSROSWORD \pixel at this point
  490LDA&360   \The parameter block is
  500AND#7     \at &310 and result is
  510STAtemp3  \returned at &314
  520CLC       \This result is added to
  530ADC&314   \(?&360)AND7 so it can
  540TAY       \be used to index the
  550PLA       \colour tables in the
  560STA&314   \O.S ROM at table
  570LDAtable,Y \Load background colour
  580STAback     \byte and store it
  590LDAcol1     \Load the first fill
  600AND&360     \colour
  610CLC         \Add "temp3" for offset
  620ADCtemp3    \for ROM table
  630TAX
  640LDAtable,X \Store colour byte for
  650STAcol1     \first fill colour
  660LDAcol2     \Load the second fill
  670AND&360     \colour
  680CLC         \Add "temp3" for offset
  690ADCtemp3    \for ROM table
  700TAY
  710LDAtable,Y \Store colour byte for
  720STAcol2     \second fill colour
  730LDAtype     \Shifts BIT 8 of "type"
  740ASLA        \into the carry flag
  750AND#&7F
  760TAX
  770LDA#&FF           \Checks if BIT 8
  780BCCverical_lines \of "type" is set
  790LDA#&00           \and stores the
  800.verical_lines    \appropriate mask
  810STAtemp3          \in "temp3"
  820LDAcol2
  830EORcol1
  840ANDtemp3
  850STAtemp3
  860LDAcol1   \AND first colour byte
  870ANDdata,X \with pattern data
  880STAtemp4
  890INX
  900LDAcol2   \AND second colour byte
  910ANDdata,X \with pattern data
  920ORAtemp4  \OR patterns together
  930BITtype
  940BVScross_hatching
  950STAcol1
  960.cross_hatching
  970EORtemp3
  980STAcol2
  990CMPback   \These tests are to make
 1000BNEstart_main_loop \sure that both
 1010LDAcol1   \of the colours are not
 1020CMPback   \equal to the background
 1030BNEstart_main_loop \colour
 1040RTS       \If that is so, then end
 1050.start_main_loop
 1060LDApointer
 1070BNEpointer_not_zero
 1080RTS       \End - pointer is zero
 1090.pointer_not_zero
 1100SEC
 1110LDAstack  \Decrement stack address
 1120SBC#4     \because coord is to be
 1130STAstack  \taken off coord stack
 1140BCSno_borrow1
 1150DECstack+1
 1160.no_borrow1
 1170DECpointer
 1180LDY#3
 1190.loop2
 1200LDA(stack),Y \Take top coord off
 1210STAX%,Y      \coord stack
 1220DEY
 1230BPLloop2
 1240JSRline   \Fill in current line
 1250LDX#3
 1260.loop3    \Save "lx" and "rx" to
 1270LDAlx,X   \preserve their values
 1280STAtemp_lx_and_rx,X
 1290DEX
 1300BPLloop3
 1310LDAscan_dir  \Load direction of last scan (1=upwards,255=downwards,0=first time)
 1320BNEnot_first_time
 1330JSRscanhi \Scan above current line
 1340JSRscanlo \Scan below current line
 1350JMPfinish_main_loop
 1360.not_first_time
 1370STAtype \Store direction (up/down) of previous scan
```

```
 1380CLC      \Here the value of scan_
dir is added to "prev_y"
 1390ADCprev_y \Note that if 255 is a
dded it is the same as subtracting 1
(carry is not used)
 1400CMPY%
 1410BNErx_smaller_than_prev_rx
 1420CLC           \The carry is clear
ed
 1430LDAprev_lx    \so that "lx" + 1 i
s
 1440SBClx         \subtracted from
 1450LDAprev_lx+1 \"prev_lx" to test
if
 1460SBClx+1       \"lx" + 1 > "prev_l
x"
 1470BCClx_bigger_than_prev_lx
 1480LDAprev_lx    \"lx"<"prev_lx" so
 1490STArx         \the region between
 1500LDAprev_lx+1 \"lx" and "prev_lx"
 1510STArx+1       \is scanned in the
 1520LDA#&FE       \opposite direction
 1530JSRscan       \to the previous sc
an
 1540.lx_bigger_than_prev_lx
 1550JSRrestore_lx_and_rx
 1560CLC           \The carry is clear
ed
 1570LDArx         \so that "prev_rx"
+1
 1580SBCprev_rx    \is subtracted from
 1590LDArx+1       \"rx" to test if
 1600SBCprev_rx+1 \"rx" < "prev_lx" +
1
 1610BCCrx_smaller_than_prev_rx
 1620LDAprev_rx    \"rx">"prev_rx" so
 1630STAlx         \the region between
 1640LDAprev_rx+1 \"rx" and "prev_rx"
 1650STAlx+1       \is scanned in the
 1660LDA#&FE       \opposite direction
 1670JSRscan       \to the previous sc
an
 1680.rx_smaller_than_prev_rx
 1690JSRrestore_lx_and_rx
 1700LDA#0    \Scan line in same dir
 1710JSRscan \as that of previous sca
n
 1720.finish_main_loop
 1730LDX#3         \Restore the values
 1740.loop4        \"lx" and "rx" and
 1750LDAtemp_lx_and_rx,X \store them
 1760STAlx,X       \in "prev_lx" and
 1770STAprev_lx,X \"prev_rx" for use
 1780DEX           \the next time
 1790BPLloop4      \through this loop
 1800LDAY%         \Store Y% in "prev_
y"
 1810STAprev_y     \for use next time
 1820JMPstart_main_loop
 1830.restore_lx_and_rx
 1840LDX#3
 1850.loop5
 1860LDAtemp_lx_and_rx,X
 1870STAlx,X
 1880DEX
 1890BPLloop5
 1900RTS
 1910 \This subroutine scans a line f
or
 1920 \runs of background coloured
 1930 \pixels and stores the first
 1940 \coord of each run on the coord
 1950 \stack
 1960.scan
 1970EORtype    \This tests whether th
e
 1980CMP#1      \line above or below t
he
 1990BNEscanlo \current line is scann
ed
 2000.scanhi    \Initiates scan above
 2010LDYY%
 2020INY          \If Y=0 then at top
of
 2030BEQend_scan \screen - end routin
e
 2040LDA#1      \Direction of scan -up
 2050BNEstart_scan
 2060.end_scan
 2070RTS
 2080.scanlo    \Initiates scan below
 2090LDYY%      \If Y=0 then at bottom
 2100BEQend_scan \of the screen -end
 2110DEY
 2120LDA#255    \Direction of scan -do
wn
 2130.start_scan
 2140STAscan_dir
 2150LDApointer
 2160STApat
 2170LDAY%
 2180STAtempy
 2190STYY%
 2200LDAlx
 2210STAX%
 2220LDAlx+1
 2230STAX%+1
 2240JSRaddress
 2250LDArx                \Calculate th
e
 2260ANDpixels_per_byte \position of
 2270STAtemp1             \pixel in byt
e
 2280LDArx+1  \"rx" is the rightmost
 2290STAtemp3 \limit of the scan
 2300LDArx
 2310STAtemp2
 2320LDApixels_per_byte
 2330.not_in_range \The result of thi
s
 2340LSRtemp3       \shift is the colu
mn
 2350RORtemp2       \number of "rx"
 2360LSRA
 2370BNEnot_in_range
 2380.scan_loop
 2390LDA#&00        \Scan for next the
 2400JSRscan_line  \background pixel
 2410STXX%          \Calculate x-coord
 2420LDA#0          \from "XX" and sto
re
 2430STAX%+1        \it on coord stack
 2440LDApixels_per_byte
 2450.shift_left5
 2460ASLX%
 2470ROLX%+1
 2480LSRA
 2490BNEshift_left5
 2500CLC
 2510TYA
 2520ADCX%
 2530STAX%
 2540BCCno_carry5
 2550INCX%+1
 2560.no_carry5
 2570LDY#3
 2580.loop6  \Store "X%" on coord sta
ck
 2590LDAX%,Y
 2600STA(stack),Y
 2610DEY
 2620BPLloop6
 2630CLC          \Increment the addres
s
 2640LDAstack    \of the coord stack
 2650ADC#4
 2660STAstack
 2670LDAstack+1
 2680ADC#&00
 2690STAstack+1
 2700CMP#(STACKLOC+&200)DIV256
 2710BNEon1
 2720LDAcol1
 2730CMPback
 2740BNEon2
 2750PLA
 2760PLA
 2770.on2
 2780LDApat      \This limits the size
 2790STApointer \of the coordinate
 2800ASLA        \stack
 2810ASLA
 2820STAstack
 2830LDA#&00
 2840ADC#(STACKLOC)DIV256
```

From Page 143

```
2850STAstack+1
2860LDYtempy
2870STYY%
2880RTS
2890.on1
2900INCpointer
2910LDA@%&80      \Scan for the next
2920JSRscan_line \non-background pix
el
2930JMPscan_loop
2940.scan_line
2950STAtemp5
2960LDYtemp4
2970JSRcreate_mask
2980EOR#&FF
2990JSRcreate_border_mask
3000STAtemp3
3010LDY#0         \Shift screen byte
3020CPYtemp4      \until it is in the
3030BEQscan_byte \position which
3040.shift_left1 \corresponds to "X%
"
3050ASLtemp3
3060INY
3070CPYtemp4
3080BNEshift_left1
3090.scan_byte
3100CPXtemp2      \These two tests
3110BCCtest_until_back_col \check if
3120BNEstop_scan \"X%" > "rx"
3130CPYtemp1
3140BCCtest_until_back_col
3150.stop_scan \Exit from scan
3160PLA       \These bytes are pulled
3170PLA       \to remove return addre
ss
3180LDAtempy \of scan_line
3190STAY%
3200RTS
3210.test_until_back_col
3220BITtemp5
3230BMItest_until_non_back_col
3240LDAtemp3 \This sequence scans th
e
3250AND&362  \bytes in the horizonta
l
3260BEQend_scan_line \line until the
3270ASLtemp3 \next pixel is a
3280INY       \background pixel
3290CPYpixels_per_byte
3300BEQscan_byte \Testing here if
3310BCCscan_byte \Y>pixels_per_byte+
1
3320BCSnext_screen_byte
3330.test_until_non_back_col
3340LDAtemp3 \This tests until non-
3350BEQnext_screen_byte \background
3360AND&362              \pixel
3370BNEend_scan_line
3380ASLtemp3
3390INY
3400CPYpixels_per_byte
3410BEQscan_byte \Tests if
3420BCCscan_byte \Y>pixels_per_byte+
1
3430.next_screen_byte
3440LDYblock_line
3450INX
3460CLC       \Increase the screen
3470LDAscreen \address to move onto
3480ADC#8     \next byte to the righ
t
3490STAscreen
3500BCCno_carry2
3510INCscreen+1
3520.no_carry2
3530LDA(screen),Y \Calculate modifie
d
3540EORback       \value of next
3550STAtemp3      \screen byte
3560LDY#0
3570BEQscan_byte  \Loop back
3580.end_scan_line
3590STYtemp4
3600RTS           \Exit from scan
3610 \This subroutine fills the
3620 \current horizontal line left a
nd
3630 \right from the current point
3640 \until the first non-background
3650 \coloured pixel in each directi
on
3660 \The coordinates of both points
3670 \are stored in "lx" and "rx"
3680.line
3690JSRaddress
3700TXA
3710PHA
3720LDAblock_line
3730AND#1
3740TAY
3750LDAcol1,Y \This is the pattern t
o
3760STApat     \be stored on this lin
e
3770LDYtemp4
3780JSRcreate_mask \Create mask for
right side of byte containing "X%"
3790EOR#&FF
3800JSRcreate_border_mask
3810BNEright_border
3820LDA(screen),Y \Preserve left par
t
3830ANDmask       \of byte not to be
3840ORApattern    \filled and fill
3850STA(screen),Y \the rest of byte
3860LDA@%&80
3870STAmask
3880LDYblock_line
3890.fill_right
3900INX
3910CLC
3920LDAscreen \Increase screen addre
ss
3930ADC#8     \to move onto next byt
e
3940STAscreen \to the right
3950BCCno_carry3
3960INCscreen+1
3970.no_carry3
3980CPXcolumn \Right edge of screen
?
3990BEQat_screen_right
4000LDA(screen),Y   \Fill line right
4010EORback         \until there is
a
4020BNEright_border \non-background
4030LDApat          \pixel in the
4040STA(screen),Y   \screen byte
4050JMPfill_right
4060.at_screen_right
4070LDY#&80
4080BEQstore_rx
4090.right_border
4100LDY#&80
4110.shift_left2 \Calculate position
4120BIT&362      \of non-background
4130BNEat_right_border \pixel in
4140ASLA         \screen byte
4150INY
4160CPYpixels_per_byte
4170BNEshift_left2
4180.at_right_border
4190STYtemp5
4200JSRcreate_mask \Create mask for
4210EOR#&FF        \pixels up to
4220ORAmask        \border
4230STAmask
4240EOR#&FF
4250ANDpat         \Calculate patter
n
4260STApattern     \for right border
4270LDYblock_line
4280LDA(screen),Y  \Store pattern in
4290ANDmask        \border byte
4300ORApattern
4310STA(screen),Y
4320LDYtemp5
4330.store_rx \Calculate coord of "r
x"
4340INY       \in internal coords
4350STXrx     \(ie pixels)
4360LDX#rx
4370JSRcoord
4380LDAX%     \Restore address of
```

```
4390STAscreen \"X%" from the beginin
g
4400LDAX%+1   \of subroutine
4410STAscreen+1
4420PLA
4430TAX
4440LDYtemp4
4450JSRcreate_mask \Create mask for
left side of byte containing "X%"
4460JSRcreate_border_mask
4470BNEleft_border
4480LDAmask       \Preserve right pa
rt
4490AND(screen),Y \of byte not to be
4500ORApattern    \filled and fill t
he
4510STA(screen),Y \rest of the byte
4520LDA#&00
4530STAmask
4540LDYblock_line
4550.fill_left
4560DEX
4570SEC
4580LDAscreen \Decrease screen addre
ss
4590SBC#8     \to move onto next byt
e
4600STAscreen \to the left
4610BCSno_borrow2
4620DECscreen+1
4630.no_borrow2
4640CPX#&FF   \At left edge of scree
n?
4650BEQat_screen_left
4660LDA(screen),Y   \Fill line left
4670EORback         \until there is
4680BNEleft_border  \non-background
4690LDApat          \pixel in the
4700STA(screen),Y   \screen byte
4710JMPfill_left
4720.at_screen_left
4730INX
4740LDY#&00
4750BEQstore_lx
4760.left_border
4770LDYpixels_per_byte
4780.shift_right1 \Calculate positio
n
4790BIT&363       \of non-background
4800BNEat_left_border \pixel in
4810LSRA          \screen byte
4820DEY
4830CPY#&00
4840BNEshift_right1
4850.at_left_border
4860INY
4870STYtemp5
4880JSRcreate_mask \Create mask for
4890ORAmask       \pixels up to
4900STAmask       \border
4910EOR#&FF
4920ANDpat        \Calculate patter
n
4930STApattern    \for left border
4940LDYblock_line
4950LDA(screen),Y  \Store pattern in
4960ANDmask       \border byte
4970ORApattern
4980STA(screen),Y
4990LDYtemp5
5000.store_lx \Calculate coord of "l
x"
5010STXlx     \in internal coords
5020LDX#lx
5030JSRcoord
5040SEC
5050LDArx
5060SBC#1
5070STArx
5080BCSno_borrow3
5090DECrx+1
5100.no_borrow3
```

This is one of hundreds of programs now available FREE for downloading on MicroLink

```
5110RTS
5120 \This subroutine creates a mask
5130 \which has the bits correspondi
ng
5140 \to each pixel from the left of
5150 \the byte set according to the
5160 \value of the Y register
5170.create_mask
5180LDA#&00
5190CPY#0
5200BEQout
5210.shift_right2
5220LSRA
5230EOR&362
5240DEY
5250BNEshift_right2
5260.out
5270RTS
5280 \This subrountine creates mask
5290 \and pattern bytes for screen
5300 \bytes which are to be only
5310 \partially filled
5320 \It also loads the screen byte
5330 \masking off the bits which are
5340 \not to be filled
5350.create_border_mask
5360STAtemp3
5370EOR#&FF
5380STAmask
5390LDAtemp3
5400ANDpat
5410STApattern
5420LDYblock_line
5430LDA(screen),Y
5440EORback
5450ANDtemp3
5460RTS
5470 \This subrountine calculates a
5480 \screen address for the coord i
n
5490 \"X%" taking into account the
5500 \current screen graphics mode
5510 \On exit from the subroutine
5520 \"block_line" contains the numb
er
5530 \of the character row which
5540 \contains "Y%", the X register
5550 \contains the colum of "X%" an
d
5560 \"temp4" contains the position
of
5570 \the pixel within that column
5580.address
5590LDA#&FF \The Y-coord is reversed
5600EORY%   \moving the position of
5610PHA     \origin to the top left
5620AND#7
5630STAblock_line
5640PLA
5650LSRA
5660LSRA
5670ORA#1
5680TAY
5690LDA(&E0),Y \Look up the 640
5700STAtemp1   \multiplication table
5710DEY        \in the OS ROM to fin
d
5720LDA(&E0),Y \address of character
5730STAtemp2   \row of coord
5740LDA#&4  \Check if the graphics
5750AND&355 \mode is mode 4 or mode
5
5760BEQnot_mode_4_and_5
5770LSRtemp2 \This is because in mod
es
5780RORtemp1 \4 & 5 there are only 3
20
5790.not_mode_4_and_5 \bytes per lin
e
5800CLC
5810LDAtemp1 \This adds on the addre
ss
5820ADC&350  \of the top left corner
5830STAtemp1 \of the screen
5840LDAtemp2
5850ADC&351
5860CMP#&80 \This checks if address
```

From Page 145

```
5870BCCaddress_less_then_RAM_top
5880SEC     \is bigger then &8000
5890SBC&354 \(is in ROM)
5900.address_less_then_RAM_top
5910STAtemp2
5920LDApixels_per_byte \Position of
5930ANDX%              \pixel within
5940STAtemp4           \screen byte
5950LDApixels_per_byte
5960.shift_right3 \Shift "X%" into t
he
5970LSRX%+1         \range of 0 to 79
5980RORX%          \for modes 0,1,2
5990LSRA           \or range 0 to 39
6000BNEshift_right3 \for modes 4,5
6010LDX% \Column number of "X%"
6020TXA
6030ASLA    \This sequence of bytes
6040ROLX%+1 \multiplies "X%" by 8
6050ASLA    \to get it to correspond
6060ROLX%+1 \address offset for the
6070ASLA    \colouum number within
6080ROLX%+1 \that line
6090STAX%
6100CLC       \This sequence adds
6110LDAX%     \together the value
6120ADCtemp1  \just calculated and
6130STAscreen \the address calculate
d
6140STAX%     \at the begining of th
e
6150LDAX%+1   \subroutine
6160ADCtemp2
6170STAscreen+1
6180STAX%+1
6190RTS
6200 \This subroutine forms a X-coor
d
6210 \using the value contained in t
he
6220 \zero page address specified by
6230 \the X register. The address th
at
6240 \is calculated is stored in tha
t
6250 \zero page location
6260.coord
6270LDA00
6280STA&01,X
6290LDApixels_per_byte
6300.shift_left4
6310ASL&00,X
6320ROL&01,X
6330LSRA
6340BNEshift_left4
6350CLC
6360TYA
6370ADC&00,X
6380STA&00,X
6390BCCno_carry4
6400INC&01,X
6410.no_carry4
6420RTS
6430.data
6440]
6450RESTORE
6460FORN%=0TO7
6470READDAT
6480?P%=DAT:P%=P%+1
6490NEXT
6500REM These bytes are the mask byt
es
6510REM used to create the pattern
6520REM which is stored on the scree
n
6530DATA&FF,&00,&AA,&55
6540DATA&99,&66,&C3,&3C
6550NEXT
```

Program II

```
10REM
20REM DEMO1
30REM By Stephen Austin
40REM (c) The Micro User
50REM
60?&226=0:?&227=&12
70MODE2
80VDU23,1,0;0;0;0;
90GCOL0,2:MOVE0,256:DRAW1279,256
100GCOL0,7
110REM square part of house
120MOVE300,256:PLOT1,600,0:PLOT1,0,
400:PLOT1,-600,0:PLOT1,0,-400
130REM roof
140MOVE300,656:PLOT1,340,174:PLOT1,
340,-174
150MOVE500,760
160PLOT1,0,60:PLOT1,40,0:PLOT1,0,-4
2
170PROCfill(1,0,1,520,800)
180REM door
190MOVE590,256:PLOT1,0,190:PLOT1,10
0,0:PLOT1,0,-190
200MOVE570,256:PLOT1,0,200:PLOT1,14
0,0:PLOT1,0,-200
210?&8C=3:?&8D=3:?&8E=0:PLOT97,-10,
4
220?&8C=4:?&8D=3:?&8E=0:PLOT97,-70,
4
230REM windows
240PROCwindow(364,320)
250PROCwindow(780,320)
260PROCwindow(364,500)
270PROCwindow(780,500)
280PROCwindow(572,500)
290PROCfill(1,1,0,640,460)
300PROCfill(1,1,1,300,256)
310PROCfill(1,3,1,640,820)
320PROCtree(140,256)
330PROCtree(1132,256)
340PROCsun
350PROCfill(4,6,0,640,860)
360REM fill in grass
370GCOL0,2
380FORN%=1TO8
390MOVEN%*160,255:DRAW(N%-4)*240+64
0,0
400NEXT
410FORN%=0TO3
420PROCfill(2,3,0,N%*320+20,250)
430PROCfill(3,6,0,N%*320+180,250)
440NEXT
450REPEATUNTILINKEY(0)<>-1
460END
470DEFPROCwindow(X%,Y%)
480MOVEX%,Y%:PLOT1,140,0:PLOT1,0,10
0:PLOT1,-140,0:PLOT1,0,-100
490MOVEX%,Y%:PLOT0,30,0:PLOT1,0,100
500?&8C=5:?&8D=5:?&8E=0:PLOT97,-10,
-8
510MOVEX%,Y%:PLOT0,110,0:PLOT1,0,10
0
520?&8C=5:?&8D=5:?&8E=0:PLOT97,10,-
8
530?&8C=6:?&8D=7:?&8E=0:PLOT97,-20,
0
540ENDPROC
550DEFPROCtree(X%,Y%)
560GCOL0,2
570MOVEX%,Y%:PLOT1,0,50:PLOT1,-65,0
:PLOT1,75,200:PLOT1,75,-200:PLOT1,-65
,0:PLOT1,0,-50:PLOT1,-20,0
580?&8C=2:?&8D=2:?&8E=0:PLOT97,10,1
50
590ENDPROC
600DEFPROCsun
610GCOL0,3
620MOVE1175,900:FORD%=0TO360STEP30:
DRAWCOS(RAD(D%))*75+1100,SIN(RAD(D%))
*75+900:NEXT
630PROCfill(1,3,0,1100,900)
640ENDPROC
650DEFPROCfill(C1,C2,P,X%,Y%)
660REM C1 and C2 are the two colour
s. p is the pattern type. X% and Y% a
re the coordinates of the point insid
e the region to be filled.
670?&8C=C1:?&8D=C2:?&8E=P:PLOT101,X
%,Y%
680ENDPROC
```

This listing is included in this month's cassette tape offer. See order form on Page 167.

Softlife

LOW COST – HIGH QUALITY – PRODUCTS FOR THE BBC MICRO

EPROM PROGRAMMER: programs 2764, 27128, 2764A and 27128A eproms. Operating software supplied on eprom. ROM formatting facility **£69**

NUMERIC KEYPAD: facilitates rapid entry of numeric data. Fully programmable. Hand-held or free-standing **£60.25**

LOGIC ANALYSER: multiple functions include: test and repair, development of logic circuits, and education. 8 MHz 8 channel **£250**



All products complete with comprehensive documentation and 1 year guarantee. All prices excl. VAT inc. P&P

For further information contact: Gary Daltrey
Softlife Limited 87 Silvertown Way
London E16 4AH Tel: 01 474 0330

C & F ASSOCIATES

Title	RRP	Our Price	Title	RRP	Our Price
Repton 3	9.95	7.75	Dambusters	9.95	5.95
Strykers Run	9.95	7.75	Last of the Free	7.95	6.75
Spy Hunter	9.95	7.75	Southern Belle	7.95	6.50
Raid Over Moscow	9.95	7.75	Trivial Pursuit	14.95	12.95
Thrust	7.95	6.50	Stairway to Hell	12.95	9.95
Mikie	6.95	6.95	Commonwealth Games	7.95	6.50
Psycastria	7.95	6.75	Bruce Lee	9.95	7.50
Airwolf	9.95	7.50	The Quill	16.95	14.95
Commando	9.95	7.50	Jet Set Willy	7.95	6.50
Yie Ar Kung Fu	9.95	7.50	Mini Office 2	14.95	12.45
Exploding Fist	9.95	7.50	10 Computer Hits 2	9.95	7.50
Micro-Power Magic	7.95	6.75	Lord of the Rings	15.95	12.95
Galaforce	9.95	7.50	**BBC DISC SOFTWARE**		
Moon Cresta	7.95	6.50	Repton 3	11.95	10.95
Bug Eyes 2	7.95	6.50	Sing the Bismark	10.99	9.95
Winter Olympics	7.95	6.50	Mini Office 2	16.95	14.95
Steve Davis Snooker	8.95	6.95	Hyper Sports	12.95	10.95
Rick Hanson	9.95	7.95	Enthar 7	15.95	14.95
Project Thesius	9.95	7.95	Strykers Run	11.95	10.95
Myorem	9.95	7.95	Psychastria	11.95	10.95
Beach-Head	9.95	7.50	Trivial Pursuit	19.95	17.50
Worm in Paradise	9.95	7.95	Speech	11.95	10.45
Thunderstruck	7.95	6.75	Exploding Fist	14.95	12.95
Repton	9.95	7.50	Yie Ar Kung Fu	12.95	10.95
Repton 2	9.95	7.50	Citadel	11.95	10.45
Speech	9.95	7.50	Thrust	11.95	10.45
Citadel	9.95	7.50	Scrabble	14.95	12.95
Caveman Capers	7.95	6.50	The Hobbit	17.95	15.95
Strike Force Harriers	9.95	7.50	Lord of the Rings	19.95	16.95
Karate Combat	8.95	6.95	Galaforce	11.95	10.95
Phantom Combat	9.95	7.50	Graphic Adv. Creator	27.95	22.95
Scrabble	12.95	10.95	Moon Cresta	9.95	7.50
Death Star	9.95	7.50	Olympic Decathlon	9.95	7.50
Price of Magik	9.95	7.50	Commando	14.95	12.95

MASTER COMPACT DISCS NOW AVAILABLE
ALL PRICES INCLUDE VAT AND POSTAGE & PACKING
(Overseas Orders add £1.00 per item)
Cheques/PO payable to:
C & F ASSOCIATES
and send to
C & F ASSOCIATES (MU) PO BOX 2, BIDEFORD EX39 3RE
Tel: (023 73) 619
Orders normally despatched within 24 hours of receipt but allow maximum of 7 days

THE AWARD WINNING

GRAPHIC ADVENTURE CREATOR

A CRASH Smash

GOLD MEDAL AWARD

An ANN TAYLOR Piccolade

"Will change the face of the adventure software market."
AMSTRAD ACTION

"THE ANSWER TO YOUR PRAYERS!"
C&VG

"A very clever utility . . . very easy to use."
KEITH CAMPBELL, COMMODORE USER

"Highly recommended."
ACORN USER

"A very impressive and sophisticated adventure generator."
SINCLAIR USER

Now everyone can write professionally illustrated adventure games.
The Graphic Adventure Creator – THE adventure writing utility of the eighties.

*** Unleash the Power of your imagination ***



AVAILABLE AT ALL LEADING RETAILERS or direct from:
INCENTIVE SOFTWARE LTD.,
2 Minerva House,
Calleva Park,
Aldermaston,
Berkshire RG7 4QW.
Telephone: (07356) 77288.

PLEASE RUSH ME (1st Class Postage FREE)

BBC B & BBC B +

THE GRAPHIC ADVENTURE CREATOR Tape £22.95 ☐ Disc £27.95 ☐

Winter Wonderland graphic adventure . . . . . £7.95 ☐

ELECTRON, BBC B & BBC B +

THE ADVENTURE CREATOR (text only) Tape £14.95 ☐

The GAC Adventure Designer Pad . . . . . £7.95 ☐

GAC extra information – free with any order ☐

I enclose Cheque/P.O. for £_____ or please debit my credit card No. _____

Name _____

Address _____

DISCS

AT LOW PRICES
IN PLASTIC LIBRARY CASES

5¼"	10	3½"	10
DSSD	**£7.99**	SS 135tpi	**£15.95**
DSDD	**£9.99**	DS 135tpi	**£19.95**

BULK DISCS AT CRAZY PRICES

5¼"	25	100	250
DS 96tpi	**£14.99**	**£49.99**	**£119.99**
3½"	25	100	250
DS 135tpi	**£39.99**	**£149.99**	**£369.99**

All disks come with envelopes, write protect labels and a lifetime guarantee

Epson LX86	**£229.99**
BBC Master 128K	**£429.95**
BBC Master econet terminal	**£369.95**
Acorn 512 upgrade kit	**£399.95**
Epson LQ800	**£529.95**
Amstrad 8256	**£419.95**
Mitsubishi 1404 monitor	**£229.95**

(all monitors and printers come with cables for BBC)

All prices include VAT and P&P.

Please call for bulk and education prices

Centec Electronic Systems Ltd

47 SPUR ROAD, ORPINGTON, KENT BR6 0QT

Tel: 0689 35353

Access VISA

Carswell Computers

24 Elm Road, Faringdon, Oxon SN7 7EJ
Telephone (0367) 21153

TYPEASY Version 4
- Touch typing course for the BBC B, B+, Master & Electron (version for the compact soon)
- Mistakes displayed with flashing letters
- Teaches correct finger movement
- 139 progressive exercises plus routines for writing more yourself
- Displays errors, speed and performance

disc (40 or 80 track) £15, Econet disc (80 track) £30, cassette £7.50

TYPE INVADERS
- Increases your speed – we guarantee!
- Letters and words rain down faster and faster – type correct letters to stop them
- 10 levels with 4 speeds plus colour and sound
- See review in Acorn User July '86

disc (40 or 80 track) £12.50, Econet (80 track) £25, cassette £7.50

Prices include P&P, please add 15% VAT

MENU-MASTER

The USER FRIENDLY INTERFACE and DISC ORGANISING KIT for the BBC

"an honest-to-goodness bargain" . . .
. . . "will repay its small cost a hundredfold".
(Viewfax - Tubelink)

Keep discs organised with easy to install menus, allowing you to document the entries at 3 levels of detail. Customise for colour, ROM selection etc. Works on model B, B+ 64k, Master with Acorn or Watford DFS (displays up to 61 entries). Compatible with 6502 second processor.

Send £6.95 for disc (state 40 or 80 track) and manual.

Stortsoft

2 Hillfields, Chelmsford Road
Hatfield Heath, BISHOPS STORTFORD
Herts. CM22 7AX. Tel: 0279 730590

COMLEX

Unit 7, Fife St., Nuneaton, Warks. CV11 5PR.
Tel: 0203 371371 Mon-Fri. 9am-5.30pm.

COMPUTERS

BBC Master	£449.00
Amstrad PCW 8512	£594.00
Amstrad PCW 8256	£439.00
Atari 520ST	£699.00
Amstrad PC1512	POA
Opus PC II range	£499-£999
Tandon 256K + 10mB Winchester + Monitor (IBM compatible)	£1595.00
Sperry PC 20 mB Hard Disc (Seagate) MSDOS, Green Monitor, Keyboard	£1,995 + VAT

Victor PC – 32% off R.R.P.

DISC DRIVES

OPUS	
5401	POA
5402	POA
5802 40/80 track	POA
5802SD	POA
5802D	POA
Challenger 256K	£195.00
Challenger 512K	£229.00
DDFS	£45.00

MONITORS

Microvitec 1431	£199.00
Microvitec 1451	£259.00
Microvitec 1441	£389.00
Microvitec 1431AP	£209.00
Microvitec 1451AP	£289.00
Philips 7502 green	£79.00
Philips 7522 amber	£85.00
Philips TV/Monitor	£199.00
Philips CM8501	£199.00
Philips CM8533	£279.00

EPROMS

27128	£2.90
8271	£35.00
8256	£5.60

MODEMS

Pace (with Commstar)	£149.00
WS2000	£129.00

MODEMS cont.

AMX Mouse	£74.95

PRINTERS

Mannesmann Tally MT80	£179.00
Epson LX86	£235.00
Epson GX80	£245.00
Interface for GX80	£50.00
Epson FX85	£359.00
Epson FX105	£479.00
Epson RX100	£259.00
Epson JX80	£499.00
Epson LQ1500	£819.00
Cannon 1080A	£269.00
Cannon A55	£399.00
Okimate 820 Colour	£259.00
Juki 5510	£279.00
Star NL10	POA

Special Offer

Kaga Taxan	£259.00

BROTHER PRINTERS

HR5	£147.00
HR15	£373.00
HR25	£725.00
HR35	£799.00
M1009	£177.00
EP44	£211.00
2024	£895.00


DAISYWHEEL

Juki 6000	£209.00
Juki 6100	£359.00
Juki 6300	£899.00
Epson DX100	£379.00
QuenData	£169.00
Silver Reed 770	£834.00
Cut Sheet Feeder for 550 and 770	£230.00
Listing Paper (2000 sheets)	£15.00

*** PHONE IF PRINTER NOT LISTED ***
Prices subject to variation.
Phone for latest prices.

NOW ALSO AT:
MANCHESTER HOT-LINE Tel: 061-976 3763
CALLERS BY APPOINTMENT ONLY
ALL PRICES INCLUDE VAT. Please add £5.00 Carriage.

Does your BBC have a one track mind?



True multi-tasking will put you out of your misery!


Your BBC now has the true multi-tasking potential of much bigger machines.

CMS Soft have cracked it!

This module, packaged as a ready-to-fit sideways ROM, brings you a robust system that holds its own in the most demanding industrial and laboratory conditions.

And there is no interference with normal BASIC functions; Multi-Basic enhances the power, speed and readability of the best BASIC Interpreter there is.

£39.95 incl. p+p



Real time Programs now possible on the BBC Micro.

- A serious tool – not an 'evaluation package'
- No extra hardware required
- No modifications needed to your BBC Micro
- Faster than procedure driven tasks

So if you want:

- full MULTI-TASKING with up to 8 background tasks running concurrent with the main program
- BBC Basic CONTROL FEATURES powerfully enhanced
- the ability to run REAL TIME PROGRAMS
- control of PHYSICAL INPUT/OUTPUT
- 5 real-time COUNTER/TIMERS
- 8 real-time TASK INTERVAL TIMERS
- a COMPREHENSIVE MANUAL that describes each command in detail, with many practical examples

MULTI-BASIC is what you need



MULTI BASIC


CMS Soft Limited.
Unit 18, Industrial Estate
Chelmsford Road, Great Dunmow
Essex CM6 1XG
Telephone (0223) 324141

CMS SOFT

THE MICRO USER MAIL ORDER OFFERS

Four rip-roaring games for your computer for less than £1 per game!


Three of this high-powered collection are top-rate machine-code versions of arcade classics and the fourth is a thrilling real-time adventure game. There's hours of enjoyment and something to suit everyone in this unique value for money collection.




SNAPMAN – Guide your man through the maze as he munches energy pellets and avoids hostile aliens.

THOUSANDS OF COPIES SOLD!






MAYDAY – A futuristic adventure! As captain of an interstellar cruiser you must guide the sole survivor of a stricken space freighter through the wreckage of his craft. If you fail to recover those vital medical supplies a whole planet is doomed!



PANZER ASSAULT – You are a tank commander engaged in vicious combat against encircling enemy forces.



ALIEN INTRUDERS – With only your laser for protection you must destroy the waves of aliens who threaten to engulf you.

ONLY £3.95 tape
5¼" disc £4.95
3" disc £6.95

TO ORDER TURN TO THE FORM ON PAGE 167

TWILLSTAR COMPUTERS LTD

FREE CATALOGUE and full price list. Call now for your issue.

Computers

MASTER 128

Complete With Internal Software	£454.25
Master Turbo Upgrade	£113.95
Master Econet Module	£46.00
Master ET	£373.75
Master 512 Upgrade	£389.00
Master SC Upgrade	T.B.A.
Eprom Cartridge	£14.95
Reference Manual Part I	£14.95
Reference Manual Part 2	£14.95
6502 Second Processor	£179.00
Z80 Second Processor	£379.00
Acorn Prestel Adaptor	£125.00
Acorn Teletext Receiver	£135.00
Winchester Disk Drive 10 MBYTES	£1250.00
Winchester Disk Drive 30 MBYTES	£1850.00
IEEE Interface	£299.00
Music 500	£178.00

ECONET ACCESSORIES

100m Cable	£89.00
Station Lead Set	£29.00
Econet Starter Kit	£99.00
Econet Bridge	£199.00
Level I Fileserver 40 Track	£99.00
Level 2 Filesaver 80 Track	£235.00
Print Server Eprom	£49.00


BBC Upgrades

64K Upgrade Kit	£39.95
17/70 Upgrade Kit	£49.94
ADFS ROM	£29.95
Disc Upgrade Kit	£89.00
Econet Upgrade Kit	£49.00
Speech Upgrade Kit	£49.00
DNFS ROM	£20.00

Monitors

MONOCHROME MONITORS

Phillips BM 7502 Green Screen	£79.00
Phillips BM 7522 Amber Screen	£95.00
Kaga KX 1202G Hi Res Green	£120.00
Kaga KX 1203G Ultra Hi Res Amber	£120.00



Hantarex H x 12 Dark Gloss Screen high resolution monochrome monitor 12" Composite Video & Audio input **£75.00**

COLOUR MONITORS

Microvitec 1431 Std Res	£201.25
Microvitec 1451 Med Res	£270.25
Microvitec 1441 Hi Res	£391.00
Microvitec 2030 Cs 20 Std Res	£425.50
Microvitec 1431 AP Std Res	£224.25
Microvitec 1451 Ap Med Res	£293.25

OUTSTANDING PERFORMANCE
OUTSTANDING VALUE

Just released by Hantarex 14" Colour Monitor Standard Resolution RGB PAL Audio Input (Inc. VAT) **£175.00**

SPECIAL OFFER

Mitsubushi 1404 Medium Resolution Monitor with 640 X 200 Pixels RGB available with IBM or BBC Leads. **£229.00**

TV MONITORS

Philips 1114 colour TV/monitor with 14" tube offering 10 Preselect channels RF CVBS and RGB inputs **£199.00**

SWIVEL BASE

Tilt and swivel base for 12" or 14" monitor or TV. "Looks very elegant" **£17.25**



PHILIPS
MONITOR TO TV CONVERTER

Converts any make of standard monitor to TV **£69.00**

TCL WORD PROCESSING SPECIAL PACKAGE

PACKAGE 1

Based on Master 128. The TCL All in One Word Processing Package contains a Master 128, View 3.0, Viewsheet, High Res Green Monitor, 800K Dual Drives with PSU, Quendata Daisy Wheel Printer together with a box of Discs, Paper, and all the Cables. **£914.25**

PACKAGE 2

Based on Master Compact 128. The TCL package includes Compact 128, latest version of the View Word processor, single 640K disk drive, monochrome monitor, correspondence quality printer. All connecting cables for above and also 5 disks and some paper. **£635.00**

visit our NEW SHOWROOM
Open 9am-6pm Mon-Sat
OPEN SUNDAYS 10-2



YOUR ONE STOP MEGA-COMPUSTORE FOR

BBC MASTER COMPACT



Twillstar proudly presents MASTER COMPACT for your Home Education and Business needs! Complete with bundled software and an integral 3.5" Disk Drive in the following Systems:-

SYSTEM 1 (inc. VAT) **£458.85**
128K *Single 640K Drive* *UHF Modulator* *Bundled Software*

SYSTEM 2 (inc. VAT) **£539.35**
As System 1. With *12" High Res. Monochrome Monitor*

SYSTEM 3 (inc. VAT) **£688.85**
As System 1. With *14" Medium Res. RGB Monitor*

SPECIFICATIONS: ★ Compatible with Master Series micro subset ★ 128K RAM inc 64K sideways RAM ★ 64K ROM inc 32K MOS, 16K BASIC ★ Up to 4 internal ROM sockets ★ 3.5" 640K formatted disk drive ★ OUTPUTS: Video/RGB/Printer/ Mouse or Joystick ★ Disk drive ★ (optional) Econet ★ Serial ★ 5V power from disk drive module ★ Usual 8 BBC disply modes inc. Mode 7 ★**BUNDLED SOFTWARE:** Pull down menus * Desk top inc. note pad, calculator * VIEW 3.0 * CARD INDEX * Full LOGO * BBC BASIC 4.0 * ADFS + Utils * Welcome suite * Tutorials * (1770 DFS under licence)

2nd DRIVE KIT **£113.00**

MASTER COMPACT OFFER
A free box of 3½" disks worth £30.00 with evey BBC Master Compact System purchased.

Phillips CM 8533 Med Res monitor with dark glass etched screen composite video input RGB and Audio Input. **£289.00**

Taxan Super Vision II



High Resolution colour monitor with several unique features, at an affordable price.
SUPERVISION II
12" RGB High resolution colour monitor. Fully compatable with IBM, Apple, BBC and most other Personal Computers. 635 x 312 line resolution. Positive or negative sync input. Text colour switchable to green, amber, white or blue or inverse white. Super high contrast tube. Optional tilt-swivel base (with clock/calendar available). Special introductory offer. **£299.00**

We are unable to list all the products that we stock—Please call for further details or visit our NEW SHOWROOM

Disc Drives

SOURCE
The Complete Solution

SD 400A **£114.00**
Single 400K 40/80 Track. Double Sided, Double Density.

SD 800C **£219.00**
Dual 800K 40/80 Track. Double Sided, Double Density.


SD 400B **£128.00**
Single 400K 40/80 Track. Double Sided, Double Density & PSU

SD 800E **£245.00**
Dual 800K 40/80 Track. Double Sided, Double Density & PSU

SD 800F **£239.00**
Dual 800K 40/80 Track. Double Sided, Double Density in Dual Plinth

SD 800E **£259.00**
Dual 800K 40/80 Track. Double Sided, Double Density & PSU & Dual Plinth

NEW Mitsubishi Disc Drives
3 YEAR WARRANTY
Source Drives are 100% BBC compatible. Slimline disc drives manufactured to the highest standards. Complete with formatting disc manual and cables.



Printer Accessories

SERIAL INTERFACES

EPSON 8143	£34.00
JUKI	£58.00
CANON	£91.00
KAGA	£85.00
Epson 8148 + 2K buffer	£65.00

LISTING PAPER

11" × 9½ 2000 Sheets	£14.00
1000 Sheets	£7.00
500 Sheets	£3.50
Teleprinter Roll (Telex size)	£4.50
Teleprinter Roll Holder	£14.00
Printer Roll 5" x 2½"	£2.00

PRINTER LABELS

1000 90 × 36mm 1 across	£5.70
2000 90 × 36mm 2 across	£12.00

PRINT FEED SYSTEM

Revolutionary low cost Printer Feed System tidies up all Micro Desks—No more paper on the floor.

80 Col	£35.00
132 Col	£55.00

RIBBONS

Full selection of Ribbons available. Call for latest prices.

PRINTER SHARERS

Printer Sharer (2 to 1)	£39.00
Printer Sharer (6 to 1)	£79.00

EXTERNAL SWITCHES

Spectrum parallel interface	£40.25
QL Serial/parallel interface	£27.60
CBM 64 parallel interface	£19.95


COMPUTER CABLES

Call for full listing of our vast stock.

Printers

KX-P 1080 DOT MATRIX PRINTER


- NEAR-LETTER QUALITY PRINTING IN ALL PITCHES
- OPERATOR ACCESSIBLE PRINT MODE SELECTOR (Std./Pgm.,NLQ, Comp.)
- FRICTION FEED AND ADJUSTABLE TRACTOR ARE STANDARD
- WORD PROCESSING FUNCTIONS (Justification, Centering, L&R alignment)
- PROPORTIONAL SPACE PRINTING
- HIGH RESOLUTION, DOT-ADDRESSABLE GRAPHICS
- UP TO 40 DOWNLOADABLE CHARACTERS
- COMMAND CODE COMPATIBLE WITH POPULAR PRINTER SOFTWARE
- PRINT SPEED, DRAFT: 100 NLQ: 20 COMPRESSED: 86
- 9 PIN PRINT HEAD



The Panasonic PX-P 1080 impact dot matrix printer is ideal for applications that require economical high quality printing. It offers a variety of print modes, all producing crisp clearly formed characters. Wide choice of print sizes includes semi-compressed and compressed (even in near-letter quality printing). Operator accessible print mode selector adds convenience. For a reliable printer at an affordable price, the KX-P 1080 is always a smart choice. **£159.00**


CITIZEN MSPIO

The new MSPIO with 160 CPS Draft and 40 CPS NLQ. With TWO years Warranty **£269.00**



NEW STAR NL-10

Fine Near-Letter-Quality, 100% compatibility and total reliability all in one easy to use printer. For quality, ease of operation and dependability, nothing beats the Star NL-10. You get outstanding print quality at 120 cps in draft mode and 30 cps in near letter quality. Plus, the sleek NL-10 offers full compatibility with most popular computers through plug in interface cartridges. Just insert the appropriate plug in interface cartridge for your IBM-PC, Commodore, Apple IIc or other parallel computer and your Star NL-10 is ready to print. Touch a button on the control panel to set the print pitch (3 choices), to select the typeface and to print in either draft or NLQ mode. You can even set left and right margins, make top of form settings and control forward and reverse feed in the smallest pitch. **£229.00**



EPSON LX86


High performance low on price offering an increased performance at an incredible low price. The LX 86 Dot Matrix Printer represents unprecedented value for money, with a host of built in features, increased draft speed 120 cps and correspondence quality at 16 cps printing this versatile Epson printer carries out every task with effortless style and has the highest standard of reliability. Supports both Epson and IBM character set. (inc VAT) £229.00

ALSO AVAILABLE

Epson FX 86	£365.00
Epson FX 105	£495.00
Seikosha GP 50A (Parallel)	£69.00
Seikosha GP 50S inc. Printer I/F + cables	£69.00
Canon PW 1080A (NLQ)	£249.00
Canon PW 1156A	£379.00
Brother EP 44	£228.00
Shinwa CP 80A	£189.00
MP 165	£240.00

SOURCE *The Complete Solution*

INTRODUCES THE NEW TECO VP1814



Dot matrix printer. VP1814 is fast highly reliable and easy to operate.

- ☆ Standard 80 column
- ☆The high-speed, low energy consumption 9 wire dot head gives printing speed of 189 cps and NLQ speed 36 cps
- ☆Bi-directional, Logic seeking in text mode
- ☆The use of fan-fold, roll or cut-sheet paper is possible with adjustable sproket pin feed and friction feed
- ☆Offers emphasized, double print, super script, sub script
- ☆Justified print mode are also available including left, centre, right and full justification
- ☆9 graphic modes are available
- ☆Both download and inprint buffer can exist simultaneously
- ☆7K input buffer standard can be expanded to 15K
- ☆Printing modes selectable at front panel (NLQ/draft, Pica/Elite, enlarge, emphasize, condense, italic
- ☆11 Language international character font is internalized
- ☆Both IBM and Epson compatable


MAIN UK DISTRIBUTOR
SPECIAL INTRODUCTORY PRICE
(inc. VAT) **£229.00**

HOME, EDUCATION & BUSINESS NEEDS!

DOT MATRIX PRINTERS

Juki 5510 - Gives you 180 CPS & NLQ Standards
£269.00 Inc. VAT

...and thats not all! The Juki 5510 also has full graphics mode, two position 'dip-switch' (providing instant compatibility with both the Epson and the IBM Graphic Printer). Standard 2K memory (expandable to 14K) built-in Parallel Centronics interface and 8-switch international character sets. If you need colour too, the optional Juki 5510 Colour Kit gives you seven colours. **£112.00**



CITIZEN 120D

Dot Matrix Printer. The 120D precision printer brings to the small business, educational and home user good quality and attention to detail. Its compact size, host of standard features and built in quality and reliability that supports Citizen's unique **full TWO-YEAR warranty** make it a must for all computer users. Fast draft output: 120 cps. Built-in NLQ: 25 cps. IBM and Epson compatible. Plug-in interface cartridge. Tractor and friction feed as standard. Optional cut sheet feeder. **£159.00**

BROTHER M1109 NLQ

Printer 100cps Directional Logic Seeking Friction feed and secondary optional tractor feed **£189.00**



KAGA KP810

The 80 column printer with 140 CPS Draft and NLQ with friction and built in tractor feed offering 9 INT character sets. Long life cartridge ribbon and standard centronics interface. Fully compatible with Epson FX80. Designed and made by Canon. The office people. **£239.00**

KP 910

Same specifications as above. 17" wide carriage 156 column. Special limited offer **£379.00**

EPSON LQ800

24 Pin Dot Matrix Printer offers a high 200 CPS draft speed and near letter quality at 67 CPS with high resolution graphics and a variety of fonts **£585.00**

ALL ITEMS LISTED INCLUDE VAT AT 15% 'NO HIDDEN EXTRAS'

DAISYWHEEL PRINTERS

QUENDATA DWP 1120 with optional tractor/sheet feeder and 13" paper width facility. This Daisywheel printer with 20 CPS has 96 character printwheel compatible with the QUME. Standard centronics interface. (optional RS232 C)

Juki 6100	£169.00
Juki 2200	£285.00
Juki 6300	£275.00
	£799.00



PANASONIC KX-P3131

A Fully Formed Serial Impact Daisywheel printer with print speed of 17cps. Diablo compatible print wheels. Print pitches available are: 10, 12, 15 and proportional spacing. Standard friction feed and optional tractor. Paper width 13.5 inches. Standard Centronics optional RS-232C. Built with 6K text buffer expandable to 32K buffer. **£289.00**

CITIZEN MSP-15E

17" Wide carriage . 136 column, operating at 160 cps and at the push of a switch will print near letter quality at 40 cps. Fully Epson and IBM compatible. 8k of standard buffer built in. Standard Centronics are optional RS232 **£379.00**

COLOUR PRINTERS

Canon PJ1080A **£440.00**


TRACTOR ADAPTERS

FX85	£33.00
LX80	£23.00
Juki 6100	£129.00
Juki 6300	£129.00
Quendata DWP 1120	£114.00
Brother HR 15	£95.00
LQ 800	£43.00

SHEET FEEDER


Juki 6100	£173.00
Juki 6300	£173.00
Quendata DWP 1120	£165.00
Brother HR 15	£212.00
LX80	£55.00

Printer Buffer




Now available
Taxan Multipurpose Type Printer Buffer KIF-4308 compatible with any Centronics interface printer **£149.00**

PRINTER STAND



£18.00 Inc. VAT

CONSTRUCTED FROM STEEL SO WILL NOT BEND OR BUCKLE
WORKS WITH BOTH CENTRE AND BACK FEED PRINTERS
POSITIONS PRINTER TO GIVE SUPERB VIEWING ANGLE
REVERSED THE STAND BECOMES IDEAL FOR COMPUTERS AND MONITORS
ADJUSTABLE TO NEARLY ALL PRINTERS
SAVES SPACE AND GIVES PAPER STORAGE
FOAM PADS PREVENT VIBRATION AND SCRATCHING OF DESK TOPS



Accessories

Raven Discs Double Sided, Double Density 96 TPI uses 3M media. Guaranteed for life. Free library Box included £17.00

Lockable Disk Storage Boxes
40*3½ Disk Sorage Box £6.99
70*5¼ Disk Storage Box £9.95
100*5¼ Disk Storage Box £14.00

NIGHTINGALE MODEM
Including Commstar and Comprehensive Manual £130.00
Auto Dial/Auto Answer Board £55.00
Auto Dial Utilities Disc £11.00
OBBS Bulletin Software £23.00

EPROMS
2764 £2.20
27128 £3.95

RAMS
6264 LP 15 £3.95
EPROM Extactor £5.00
EPROM Eraser £32.00
Soft Life EPROM Blower £75.00

GRAPHPAD 2
Draw and Paint in numerous colour and pattern combinations. Copy, invert, mirror and flip any part of your picture. Define your own symbols and colour patterns. With new System 1 ROM Art Software only £69.00

JOYSTICKS
Voltmace 14b Handset £14.95
3b Singlet £12.95
3b Duelset £19.95
14b Interface £14.95
DRAWER Cassette £5.95
DATAPAD Keyboard £39.95

SYSTEM SOFTWARE
THE MUSIC SYSTEM
Disk Pack £29.95
Cassette 1 £14.95
Cassette 2 £14.95

EXPANSION BOARDS
Sidewise, ROM/RAM Expansion for the BBC Micro £42.00
Battery back up kit £18.00
CMOS RAM 8K Bytes £5.00
Sideways Plus ROM board for the new BBC B+ computer £36.00
Range of software specifically designed to enhance and extend the use of sideways RAM an ATPL Sideways. Spool it – allows the sideways RAM to be used as an 8K or 16K printer buffer £11.50
DFS Shift – moves the user RAM workspace required by the DFS into sideways RAM. Allows memory recovery to 0E00 with Acorn 0.9 DFS only £11.50
Sideswipe – allows you to save sideways ROM onto disc and load sideways ROMS from disk into RAM. £11.50
Turboprom – 1-2 uses a fast programming algorithm to greatly reduce programming time of EPROMS (14 mins - 2 mins). Used with Autoprom available on disc or Sideways ROM £17.00
Custom RAM/ROM writer utility to produce a ROM image for Autoprom or Sideways RAM to automatically download and run a Basic programme and/or your utilities on power up. Several utilities supplied with this package. Please specify 40T, 80T disc or cassette. £17.00

BBC BOOKS
BBC B Compendium £5.95
Advanced Disk User Guide £14.95
Advanced Basic Rom User Guide £9.95
The Epson FX Kaga Printer Commands Revealed £5.95
BBC Micro Disk Drives £6.95
Complete Disk Manual £7.95
The BBC Micro Rom Book £9.95
The Super User's BBC Micro Book £9.95
View BBC £10.00
View Store £10.00
Viewsheet Electronic S/Sheet BBC £10.00

Clares Betabase £23.00
Clares Graphdisk £12.30
Clare Replica III Disk £13.50
Clares the Key Disk £12.30
Betabase £21.00
Betabase Utilities £11.00
Beta Accounts £21.00
Profile £11.00
Font Editor £17.00
Fontwise Plus £17.00

BEEBUG
Toolkit Plus £35.00
Wordease ROM £22.00
Wordease Disc £19.00
ICON Master £30.00
Studio Eight £19.00
ROMIT £30.00
Sleuth ROM £28.00
Exmon 2 £28.00
Help 2 £27.00
Spellcheck 3 £32.00
Dumpmaster 2 ROM £27.00
Dumpmaster Disk £13.00
Program Bulder £19.00
Discmaster £19.00
Teletext £13.00
Sprites £13.00
Murom £28.00
Quickcalc £16.00
Hershey Font £19.00
Billboard £21.00
Design £21.00
Paintmaster £15.00

ALTRA
Enigma Disk Imager £42.00
Tube Editor £42.00
Probe I £34.00
Basic Editor 2 £34.00
Basic Editor I £25.00
First Aid II £19.00

GEMINI
Datagem Database £79.00
Gemini DDD Base £29.00
Gemini DDD Calc £29.00
Gemini DDD Plot £29.00
Office Mate £12.00
Office Master £25.00
Fleet Street Editor £39.95

LBO
Life & Business Organiser £19.50

Services


Many components now in stock. Call for details and price.

SERVICES
Fast Repair Service for the BBC Computer
average charge from £23.00
Printer repairs from £20.00
Disk Drive repairs from £15.00

BBC COMPUTER SPARE PARTS AND COMPONENTS
PSU £59.00
Keyswitch £2.00
Complete Keyboard £59.00
Keyboard Connector £5.18
UHF Modulator £5.18
Video ULA £20.00
Serial ULA £16.00
6522 VIA £4.10
6502 2 MHZ CPU £7.50
UPD 7002 £17.25
6845SP CRT CON £7.50
SAA 550 Teletext £10.35
LM 324 £0.50
6522A 2 MHZ VIA £6.33
8271 £52.00
74 LS 123 £0.46
74 LS00 £0.28
74 LS04 £0.28
74 LS10 £0.28
7438 £0.46
74 LS 163 £0.86
74 LS 244 £0.92
74 LS 245 £1.27
74 LS 375 £1.04

TWILLSTAR COMPUTERS LTD

AMX MOUSE & SOFTWARE
AMX Mouse with Super Art ROM £79.00
AMX Mouse with Super Art ROM Master £89.00
AMX Pagemaker BBC/Master £49.95
AMX 3D Zicon £24.95
AMX Database £24.95
AMX XAM £24.95
The Original AMX art Plus Utilities £14.95
AMX Paintpot £14.95
AMX Desk £24.95



PLINTH FOR BBC MICRO
The single Plinth is suitable for BBC & Monitor. The double height provides enough room for single or side by side dual drives. The computer slides in to the lower section
Single BBC Plinth £11.50
Double BBC Plinth £21.00
Printer Plinth £11.50
Single Master Plinth £16.00
Double Master Plinth £26.00
Disk drive Bridge for Master 128 complete with Switch mode PSU for dual drives. Mounted with 40/80 switches in the front. Will take any slimline drive and the computer neatly slides in the lower section £85.00

BBC Software

ACORN SOFT
Acorn View Word Processor £44.00
Acorn View Sheet £44.00
Acorn Logo ROM £55.00
Acorn ISO Pascal £55.00
Acorn BCPL £99.00
GXR ROM £25.00
View 3.0 £69.00
Hi-View £44.00
View Store £44.00
LISP ROM £49.00
BASIC Editor £27.00
Termulator £29.00
Microprolog £65.00
View Spell £34.95
View Plot £25.00
Comal £44.00

COMCONCEPT
Wordwise £30.00
Wordwise Plus £45.00
Intersheet £45.00
Disk Doctor £27.00
Printmaster (Epson) £27.00
Printmaster (Star) £27.00
Caretaker £27.00
Graphics ROM £27.00
Communicator £59.00
Accelerator £55.00
Gremlin Debug ROM £27.00
Interchart £29.00
Speech ROM £30.00
Speech Processor £10.00
Interword £49.00
Interbase £55.00

CLARES
Frontwise Plus £19.00
BROM+ ROM £31.00
BROM+ Disk £27.00
Wordease £27.00

PACE
Commstar £33.00
System ADE ROM £60.00
System SPY ROM £30.00
Edword User Pack £44.00
Edward Teacher Pack £25.00
BBC Ultracalc II £79.00

VINE
Replay ROM £34.00
TD ROM £18.00

MISC.
View Index £14.90
View Printer Driver
Generator Disc £11.00
Cass £9.50
Ram Rod ROM £37.95 Disc £33.95
Advanced Disc Toolkit £32.00
Beeb Text Plus £19.00
Advanced Disc Investigator £27.00
Floppywise Plus £28.00
Advance Ram Manager £14.95
Iso-pascal (c) Master £65.00
Logo (c) Master £65.00
Lisp (c) Master £55.00

GAMES DISK
All the latest games in stock Call for details!!! And ask for our latest catalogue. Listed all games and prices. Or visit our showroom and see for yourself.

MULTI-font NLQ (ROM and 40/80 Disk)
A very powerful facility which will allow the user to display text, information of any kind from sideways RAM. Compatible with most sideways RAM units including ATPL sideways with RAM, Solidisk SWR, BBC B Plus 128K & BBC Master Series. £30.00


How to Order

You can purchase any of the items listed. All you have to do is write your requirements on a sheet of paper, and we will despatch your goods within 24 hours, subject to availability. Please add the following amounts for Postage and Packing.
Items below £10.00 add £1.50
Items below £50.00 add £2.50
Items below £100.00 add £3.50
Items over £100.00 add £8.00
(UK Mainland only)
All prices include VAT at 15%
'No Hidden Extras'
Prices correct at time of going to press but subject to change without notice.
Please make cheques payable to:
TWILLSTAR COMPUTERS LTD.
Access/Visa Card Holders: Welcome. Call now on:-
01-571 5938 or 574 5271


CREDIT FACILITIES
Full credit facilities now available nationwide
* LOW DEPOSITS
* FAST FRIENDLY SERVICE
* UP TO 3 YEARS TO PAY
Call for further details
Typical APR 36.3%



TWILLSTAR COMPUTERS LTD



APEX HOUSE, BLANDFORD ROAD, NORWOOD GREEN, SOUTHALL, MIDDX UB2 4HD
Tel: 01-574 5271 01-571 5938
Telex: 25247 Telex G. attn TIL



Catching and curing the bugs in Basic II

£10 Prize letter

IN response to the letter in the October issue of The Micro User *about Basic II rom bugs, may I elaborate on the bug.*

If Iain Tatch had omitted line 10 from his program (which contained a RESTORE statement) the program with the correct DATA statement would still have worked.

The programs with the corrupt DATA statement (those with PRINT, or nothing, instead of DATA) would have failed with an Out of DATA error, as he would have expected.

They would also have failed as expected if he had changed the RESTORE statement to point to a different line, which did not contain any commas (such as line 10).

What Iain has stumbled upon is a combination of a bug in the RESTORE command, and one of the undocumented features of the READ and DATA commands.

I came across these while researching my Basic Analyser, though omitted the details from the articles for reasons of space (see The Micro User, *Oct/Nov/Dec 1985).*

First, the undocumented features. DATA statements can contain expressions to be EVALuated.

But because the DATA statement is not tokenised (unlike the argument for EVAL), you cannot use an expression such as SIN(x) – it gives an Array error.

DATA statements can also contain comments after each number.

Thus a statement like the following would be perfectly legal in Iain's program:

```
100 DATA 12 (a dozen), A*
A (lets see a dozen dozens)
, 0
```

How does it work? Basic maintains a DATA pointer which points to the character following the last item of DATA that has been READ. Note that when a program starts, it points to the first byte of the program, which is a carriage return.

When a READ is executed, the DATA line is searched for a comma, starting at the DATA pointer. The next item of DATA is READ immediately following this next comma, if found.

This means that when READing a list of numbers you can follow each one with a comment without causing an error.

If the end of the line is reached a search is made, line by line, until another line starting with a DATA token is found.

The DATA pointer is then set to point at this token, which is treated as if it were a comma in the DATA list, as the READ is executed.

Now to explain the bug. In Basic II, and Electron Basic, a RESTORE updates the DATA pointer to point to the first character of that line, whether or not it is a DATA token.

The next time a READ is performed, the RESTOREd line is searched for the next comma (or an initial DATA token).

Anything found after a comma in the line is taken as the DATA to be READ, whether the RESTOREd line was a DATA one or not.

In Basic IV this bug has been corrected. RESTORE adjusts the DATA pointer to point instead at the carriage return preceding the required line.

Thus when the next READ is executed, it finds that the DATA pointer is at the end of a line, and so search is made for the next line starting with a DATA token. – **Mike Stallybrass, Areley Kings, Stourport-on-Severn, Worcs.**

Win a tenner

● *Want to write to Micromail? The address is: Micromail, The Micro User, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 5NY. Writers of the three most interesting letters will each receive a £10 prize.*

No luck loading

SOME games will not load on my BBC Micro. We have had it checked and have used several different tape recorders, but so far we have found nothing wrong.

It is a standard BBC B with OS 1.2, Basic II and issue 7 mother board.

The games which refuse to load all have continuous data streams and include Fortress, Knight Lore, Way of the Exploding Fist, Caveman Capers and Castle Quest.

Do you know what could be wrong? – **Gary Betts, Lancing, Sussex.**

● There are two types of serial ULA fitted to BBC Micros. Unfortunately there are problems loading some software on one of these types.

Your Acorn dealer should be able to fix you another ULA, or the appropriate software house give you a version of the game that works with your present ULA.

Unfair advantage

I WAS very angry to see that The Micro User *has published M. Gower's Karate Combat cheat program. I spent many hours playing the game before I completed it.*

What makes me more angry is the fact that the competition is still open, so anybody with a copy can cheat and have a chance to win the prizes.

I thought The Micro User *would have had more sense and waited until after the closing date of the competition.* – **Matthew Hall, Ripley, Derbys. age 13.**

● Unfortunately, any competi-

More facts on Beebaid

I AM writing regarding the review of our Beebaid product in the October issue of The Micro User *to outline just some of the facilities which the reviewer omitted to mention.*

Firstly, the Load menu is intelligent, automatically determining the type of file you are attempting to load.

This applies particularly to roms, Basic and machine code programs, and teletext screens. Other data files cause the program to ask what to do with the file, such as type it or dump it. When it detects a rom, it prompts for a destination ram socket.

*From the Load menu you can enter *INFO, *DUMP, *TYPE, *EXEC, *DELETE, *LOAD, LOAD, *RUN or CHAIN using a single keystroke. Beebaid users never need to key these commands in full. Files can be locked and unlocked using Control+L and Control+U.*

There is a Copy menu which enables one or more files to be tagged and then copied to another drive by hitting the destination drive address key. This is invaluable when doing selective disc file backups.

Beebaid handles single and multiple sideways rams, both software and hardware controlled, and the Beebaid Run menu works on all models and is fully 6502 second processor compatible.

Incidentally, the Disc Indexing System is supplied free with the Beebaid rom. Full technical details are available from Jaysoft. – **J.W. Bishop, West Wickham, Kent.**

From Page 153

tion is open to cheats. Although you feel that our program helps the cheats, our opinion is that if we had not published it, those few who had access to it would have had an unfair advantage over those who hadn't.

By publishing the program, everyone was brought back to the same level.

Driven to distraction

I HAVE discovered a way of cheating at Acornsoft's game Revs.

I was recently driving around the track backwards when something suddenly occurred to me.

How did the author determine whether the car I was driving had in fact done a whole lap before crossing the finish line and gaining a time?

I then set about testing out the program by going up to each corner, performing 180 degree skids and going back the other way. This is how to cheat.

First of all, when in practice mode drive from your stationary position as fast as you can until you reach the 3rd gear corner, Becketts (refer to map if necessary).

Now slam down the brakes and perform a 180 degree spin – this may take some practice.

Head off in the direction you came from and as soon as you pass the start/finish line perform another 180 degree spin.

You should now be facing in the normal direction and be able to slam the car into 1st gear, gaining as much wheel spin as possible to sprint across the line.

Once you are confident in practice try it in competition mode to get an amazing qualifying time. However, you must watch out for oncoming cars when going back the other way.

I have a recorded time of 0.58.2 seconds. Can any readers do better? – **P. Stout, Stubbington, Fareham, Hamps.**

Graphics dump help

THE Mode 7 screen dump program in the September issue of The Micro User *looks useful, but I cannot get the graphics to dump correctly from my Master. Can you offer any help?* – **Wilf Spurling, Brixham, Devon.**

● On the Master Welcome disc you will find a program called Convert. Run this before you run the Mode 7 dump and you should have no further problems.

Convert makes the Master act more like a Model B, so you may find it useful with other software that has so far failed on your micro.

Witch hunt for variables

HAVING spent the past two days keying in Witch Hunt from the October issue of The Micro User, *imagine my disappointment when I found that the program would not run.*

The problem seems to be in the following line:

```
90 HIMEM = &5400 : FOR A
=&5600 TO &57FF:READ B:?A=B
:NEXT
```

On trying to run the program the computer reports that there is no such variable at line 90.

Please could you advise me whether this is a printing error, or what mistakes I might have made?

Also, is this program compatible with the BBC model B computer, and is there enough memory to run it?

Finally, do I have to be a subscriber before I can buy this program from your mail order offers? I fear that this might be the only option available to me. – **Carolynne Woffington, Woodley, Reading, Berks.**

● There are no mistakes in the listing, and you have typed line 90 correctly. The "no such variable" is caused by the READ B trying to read something that doesn't exist, so check the DATA lines starting at 110.

Check especially that you have not entered letters instead of numbers (I and O especially). If you type:

```
PRINT A-&5600
```

after the error occurs, the response is the number of data items read correctly. Start counting the data from line 110 and you should find your error more easily.

This program will run on all models without memory problems and, like all our tapes and discs, is available to anyone. You will find an order form on Page 167.

Mistaken identity

I NOTED in the September isssue of The Micro User *that the spelling of Carnot was incorrect.*

Carnot was a French physicist who gave his name to the Carnot cycle – to do with heat engines. The person I presume was intended here is Karnaugh – **Chris Butlin, Dunstable, Beds.**

● I always thought it was spelt with a K, but everyone said I was wrong. Maybe now they'll believe me. – Mike Cook

Command corrections

IT has come to my attention that some readers who typed in Listing II from my Printer commands article in the November issue of The Micro User *may have had problems getting it to work correctly.*

The routine was added by

Making the most of Thrust

£10 Prize letter

HERE are some tips on Superior Software's Thrust.

On the first three sheets the reactor is found on the planet's surface and on the fourth sheet it is just below. It is definitely a good idea to destroy the reactor on these sheets.

Certainly on the first three it is very easy to carry out this task and provide new lives with which you can tackle further sheets.

In fact if you destroy all the limpet guns, collect all the fuel tanks and pods and destroy all the reactors on the first three sheets you obtain a score of 21600, five lives and fuel over 2000.

This status is easy to obtain as to destroy a reactor you need only 15-20 shots at it and of course you can give it a good bashing before you have collected the pod.

In playing the game the pod is your biggest manoeuvring handicap, especially in cornering. I think I have found the safest method of steering round a sharp corner with the pod.

Approach the corner slowly and hover. This is achieved by sending out short bursts of downward thrust.

If it is a right hand corner cease hovering when your pod has swung as far left as it can go: vice versa for left hand corners. When you are satisfied with the position of your pod turn your nose into the corner and give a hard thrust.

When you are out of the bend hover in the nearest wide space. Let your pod swing until it is not dragging you around and then continue up the tunnel.

You will find the first corner of this type on the third sheet.

On reverse gravity planets a given amount of thrust will move you further than in normal gravity.

If you are a beginner in Thrust and want to try the sheets further on in the game you can easily get to the fourth and maybe even fifth. All you have to do is shoot the reactor to a critical stage and escape with no pod.

Your mission will have failed, but you will progress on to the next sheet without losing a life.

Finally, when on invisible planets, if possible do not destroy the limpet guns in the tunnels because the base of each limpet gun indicates both the position and angle of the tunnel wall.

Good luck all you Thrusters out there – may the pod be with you. – **Ian Colvin, Stanmore, Middlesex.**

someone else and, unfortunately, will fail on a few systems.

*Firstly, tape users should alter line 10 to read *RUN PRINTER rather than just *PRINTER. Secondly, the routine as it stands will not work at all on machines with Basic I. A new line:*

```
500 DEFPROCos(N) : $&700=
A$(N):X%=0:Y%=7:CALL &FFF7:
ENDPROC
```

is required, and line 70 should be altered to read:

```
70 PROCos(I):PROCos(J)
```

Of course the program is only a short demonstration routine, and neither of these errors will affect the correct functioning of the main program (Listing I). – **Jonathan Temple, Chilwell, Beeston, Nottingham.**

Coming up empty handed

AFTER seeing your last month's poke for Karate Combat by Superior Software, I have found a way to beat your opponent in a competition with the computer without him laying a finger on you.

All you have to do is play in a double player game and when you have finished press Escape and then play against the computer in a competition.

This time your computer opponent will not strike you unless someone controls him on the keyboard or another joystick, so you can hit him until he gets knocked down. – **C.C. Wong, Hampton, Middx.**

Immortal adventuring

ABOUT two weeks ago I got Bruce Lee from US Gold and after a few days I accidentally managed to get never-ending lives. I eventually managed to work out the following solution.

Collect all the lanterns on the top three levels, then go down to the next level through the gap on the middle level, which remains closed until you have collected all the lanterns on the top.

Make your way to the bottom of the screen, collecting all the lanterns on the way, but watch out for the green yamo as he often gets you when you're falling down a gap.

Now go left to the next screen and climb up the waterfall, watching out for the spikes when you get to the top. Don't worry about our friend Mr. Yamo, because the spikes will get him when he gets to the top.

Once on the platform, jump right when the fireball is at the end and you should quickly be back at the bottom.

Next do the same on the left. If you time it right you should be at the bottom at the other end of the waterfall.

Go left, climb up the ladder and walk left off the edge when the fireball is about to cross. You should find yourself in a room with lots of fires in it.

Now the fun and games really start. Go right collecting the lanterns, avoiding being kicked by Mr. Yamo and avoiding the fires.

Then drop off the edge and go left, collecting the rest of the lanterns before going right on to the next screen.

Keep getting yourself killed until it says FALLS 01, then go down, get the lantern and go left to the next screen. As you will notice, this is the screen with the fires but lower down.

Don't go left and get the lanterns – go right and kill yourself on the spike on the right screen.

You will be thrown into the left screen and provided your fall said 01, you will have infinite lives with which to complete the rest of the game. – **Wayne Joyce, Birstall, Leicester.**

Five-year-old favourite

I WOULD like to say how much my five year old son enjoyed Rock Fall, the extra game on August's The Micro User *disc.*

Using the built-in screen editor I have been able to design very simple screens – ideal for

→

Hashes and pound signs

£10 Prize letter

FOLLOWING I.P. Wright's letter in the September issue of The Micro User *concerning the printing of a pound sign, I wrote a short program which may be of interest to him or others with a similar problem.*

A pound sign going to the printer is intercepted and replaced with the code for a hash sign. This is similar to the Wordwise command DP35.

However, whereas Wordwise displays a hash on the screen, my program retains the display of a pound which the printer produces.

The program intercepts the oswrch routine through the vector at &20E and &20F. It then checks that the code in question is a pound. It also checks that the output to the printer is enabled with VDU 2. If both conditions apply a VDU 1,35 is executed and a pound sign is printed. The printer is then switched off, a pound sign displayed on the screen and the printer re-enabled.

The program was written on a disc machine, but will still work with a tape filing system. The code may be easily moved if desired by altering lines 80, 490 and 500. – **Nigel Reed, Langford Budville, Somerset.**


```
  10 REM Printer '£' sign
replacer.
  20 REM(c) The Micro User
  30 REM     by Nigel Reed
  40 osbyte=&FFF4
  50 oswrch=&E0A4
  60 char=&80
  70 FORpass=0 TO 3 STEP 3
  80 P%=&1200
  90 [ OPT pass
 100 \ Store acc and push
registers
 110 STA char
 120 TXA:PHA
 130 TYA:PHA
 140 \ Is character a £?
 150 LDA char
 160 CMP #ASC("£")
 170 BNE end
 180 \ Is printer on ?
 190 LDA #&75
 200 JSR osbyte
 210 TXA
 220 AND #1
 230 BEQ end
 240 \ Print £ on printer
only
 250 LDA #1
 260 JSR oswrch
 270 LDA #ASC("£")
 280 JSR oswrch
 290 \ Print £ on screen
only
 300 LDA #3
 310 JSR oswrch
 320 LDA #ASC("£")
 330 JSR oswrch
 340 LDA #2
 350 JSR oswrch
 360 PLA:TAY
 370 PLA:TAX
 380 LDA char
 390 RTS
 400 \ If printer off and
char not £
 410 .end
 420 PLA:TAY
 430 PLA:TAX
 440 LDA char
 450 JSR oswrch
 460 RTS
 470 ]
 480 NEXT
 490 ?&20E=&00
 500 ?&20F=&12
 510 END
```

MICROMAIL

From Page 155

the young beginner.

I enclose a photograph showing his favourite screen which has his name on it. – **B. Bracegirdle, Stockport, Cheshire.**



Sound of music

THE dreadful music in The Way of the Exploding Fist has been driving me mad.

All the reviews said there was no sound off option, but I've struck on the solution.

When in demo mode press Delete – quickly or else the sound comes back on again. To switch on press Delete again. – **M. Downer, Shipton-under-Wychwood, Oxon.**

Program protection

RECENTLY I have written a program which I want to sell. On some programs such as Way of the Exploding Fist the disc is protected so you can't even catalog it.

Is it easy to do that to any disc? If so, please could you let me know how to do it. – **Christopher Ewels, Ford Heath, Shrewsbury, Shropshire.**

● Protecting discs well requires a lot of programming skills. However, just preventing the catalog from being displayed is quite easy.

On Acorn DFS format discs the first 8 bytes of the title are stored in sector 0 on track 0. If you use a sector editor such as the one by Kevin Edwards in the August 1984 issue of *The Micro User* you can make the title anything you want.

VDU 21 switches the VDU drivers off, so use the editor to change the first byte of the title to 21 (&15), and the drivers will switch off as soon as the title is displayed, thus preventing the catalog being printed.

If you then give your programs strange names, people will have trouble finding them.

You can also change another of the title bytes to 3 if you want to prevent the catalog being output to a printer.

ALL programs printed in this magazine are exact reproduction of listings taken from running programs which have been thoroughly tested.

However, on the rare occasions when mistakes occur corrections are published as a matter of urgency. Should you encounter error messages when you type in a program, they will almost certainly be the result of your own typing mistakes.

Unfortunately we can no longer answer personal programming queries concerning these mistakes. Of course letters about suggested errors will be investigated without delay, but any replies found necessary will only appear in the mail pages.

Confessions of a faint-hearted Micro User

Requiem for a programmer

Dear Trev,

You know that I'm not one to moan, that grin and bare it (is that spelt right?) has always been my motto. Well things are getting on top of me. Well, one thing. Doreen.

It was her fault that I went to the Model B Requiem (written on a Music 500, no flowers just donations – in lire – to Acorn). I wouldn't have heard of it if she hadn't rung up asking me to write a program.

"Can you do me a program that takes all the names of our teachers and picks five at random?" she asked.

"Of course I can, but why?"

"The staff at our school are doing a sponsored parachute jump to raise funds".

"What for?"

"A parachute for the next one. Make sure that the program doesn't pick me and I'll see you at the Requiem".

Now all would have been well except for the fact that Clive had called round earlier in the day and mentioned the Rogues' little "do" to Andrea. As she was suffering from a bout of bellringer's elbow – occasioned by fighting her way to the bar at the Quaasimodo's Revenge (so named because the beer's so bad the customers get the hump) – she decided to come along.

Picture the scene. Me, upstairs at the Ram and Buffer with Doreen on one side and A. on the other. It was like being sat between the Pope and Ian Paisley but with less of the good fellowship. "This is Doreen", I stammered by way of introduction. "She's a teacher and is very good with Masters".

"So I've been told", said A. in a voice that reminded me of the bottles of concentrated nitric acid in my old school lab.

"It's so nice you could come", replied Doreen in a voice that made Margaret Thatcher sound sincere, "I believe you've been having problems with pulling things".

"You mean my bellringer's elbow?"

"Elbow? No. Someone mentioned something about mammals in your bell-tower".

And that's how the repartee went for the rest of the evening. I tried to pay attention to the Requiem but couldn't with dialogues going on like:

"Do you program, Andrea?"

"No. I'm like Bob in that respect".

Not that it wouldn't have been an interesting evening if I'd had the chance to pay attention. During the interval they had one of the Squirrel User writers speaking about Structured Programming. He'd been sent by way of punishment as he was in disgrace for writing an article that people could follow. I didn't understand all of it but some points remain clear.

Apparently you shouldn't start typing right away but think about what you're doing first. (If I thought about it I'd never do it.) Also you get all sorts of nasty bugs from flow charts. And you should write it all down in pseudo-code first – hence the Rogue's new catch-phrase, "Show us your pseudycode, sweety". And it helps if you don't try to do it all at once but break it down into parts that you can manage. "I tell Bob that all the time", A, purred to Doreen.

"I always thought he was perfectly structured", came the alarming reply.

I can't remember too much after that as things became a bit tense. Two pints of the Ram and Buffer's speciality ale, Ewe Name-it, had its usual effect but I didn't dare leave them alone together. And it seemed inappropriate to GOTO anywhere considering the subject being talked about.

However, I seem to recall something about "passing parameters" which didn't help in my state and also there was something about local variables which the landlord objected to as he thought it was a dig at his pub grub. The worst bit was when the speaker held up a program that he said was the most unstructured he'd ever seen. And, of course, it was one of mine. Apparently that was why Clive had called round earlier. I will say no more. I just wish everyone else would do the same.

Yours unstructuredly,

Bob

PS Doreen bought me a present at the Requiem – a badge that says "Structured programmers do it top down". I've bought her a tastefully illustrated copy of "The Joy of Programming".

EPROMS * RAMS * DISKS

We only supply NAMED, QUALITY chips for the BBC
Lowest prices – Fastest delivery
Prices INCLUDE VAT and UK post, normally by return

NEC 2764C once only progr. 2-5 pcs **£1.75**, 6+ pcs **£1.45**
Fujitsu 2764-25 1-2 pcs **£2.50**, 3-9 pcs **£2.25**, 10+ pcs **£2.15**
Fujitsu 27128-25 1-2 pcs **£3.35**, 3-9 pcs **£2.70**, 10+ pcs **£2.50**
Fujitsu 27256-25 1-2 pcs **£4.75**, 3-9 pcs **£4.50**, 10+ pcs **£4.30**
Hitachi 27256-25 1-2 pcs **£5.25**, 3-9 pcs **£5.00**, 10+ pcs **£4.75**
Hitachi 27C256-20/25 1-2 pcs **£6.95**, 2-9 pcs **£6.70**, 10+ pcs **£6.50**
Hitachi 27512-25 1-2 pcs **£14.50**, 3-9 pcs **£13.95**, 10+ pcs **£12.95**
N.B. Hitachi have stopped supplying 21 Volt Vpp EPROMs. Tests show that 21 Volt Vpp Fujitsus are equally as good.

Hitachi 6264LP15 (ATPL, Watford) 1-2 pcs **£2.95**, 3+ pcs **£2.65**
NEC 41254/41464-15 (upgrading Solidisk) **£6.00** each
Hitachi 48416/NEC 41416 (=4416) (upgrading Watford) **£2.50** each
NEC/Sam 41256-15 1-2 pcs **£2.95**, 3-9 pcs **£2.60**, 10+ **£2.50**
Intel 8271 controller **£37.00**

DISKS

DS/DD 96TPI. Hub-ring/Sleeve. Box of 10 **£8.95**

EPROM HARDWARE

SPECIAL OFFER Buy any of the products listed below and deduct 10% from your first order for EPROMs.

VersEprom low cost **EPROM PROGRAMMER**
for BBC B, + and Master with DD and DFS
Supplied in a cream coloured, sloping front case with ZIF socket, **VersEprom** plugs into and takes its power from the user port of the BBC. Software, which includes fast intelligent programming algorithm, is available in ROM.
VersEprom programs 2764, 27128, 27256, 27512/3 EPROMS, including "A" (12.5v Vpp) versions. Commands available are TEST, READ, BLOW, VIEW and COMP.
Prices are:

VersEprom £44.95 Software ROM £5.00

EPROM ERASERS handling up to 3 EPROMS at a time
D1 **£21.45**, D2 (with built-in 15 min timer) **£26.45**

Prices INCLUDE VAT and post, normally BY RETURN

Send UK cheques/PO
LA or Gov't Orders to:

SILICON CITY

Mithian, St. Agnes, Cornwall TR5 0QE
Access/Visa orders, telephone 087 255 2112

CONTRACT BRIDGE
BRIDGE-MENTOR II

VERSION 1.10

NEW COMPACT VERSION

" the best offering we have seen for the bridge player so far" **BRIDGE CLUB REVIEW**
"an ideal teaching aid" **ACORN USER**

"The internationally acclaimed system for the COMPACT/MASTER/BBC/ELECTRON that can really improve your standard of play"

Practise your bidding: Perfect your card-play: Create your own archive of interesting hands

With high resolution colour graphics and sound, BRIDGE-MENTOR II guides you, step-by-step, through expertly analysed hands. A host of features including the spectacular "AUTOPLAY" option. The package now includes the famous "Challenge" hands archive . . . in total-over 60 testing hands to improve your game . . . with unlimited scope for more !!!

Now with comprehensive 24 page on-line user guide



Original Cassette version now only £12.00

BRIDGE-MENTOR II Version 1.10
For all MASTER/BBC/ELECTRON models with 32K+ and DFS/DDFS and MASTER COMPACT with ADFS. Also tape-to-disc for non standard systems.

5.25" Disc (DFS/DDFS)	£17.50
3.5" Disc (ADFS)	£19.50
Tape-to-Disc	£19.50

Please state 40/80 track where relevant

Cheques to:- **MINIC BUSINESS SERVICES, 12 WOBURN CLOSE, BUSHEY, HERTS WD2 3XA.**

INSTAT

* Powerful but easy to use
* Interactive data analysis
* Simple command language

THE MOST POWERFUL STATISTICS PACKAGE YET WRITTEN FOR THE BBC MICRO

INSTAT is a general purpose statistics package with over 70 commands for interactive data analysis. Many commands have optional subcommands for greater flexibility.
INSTAT has been written by statisticians for use in data analysis in any area of application. It is also ideal for teaching statistics.

Facilities include:

* easy data entry and editing
* calculations and data transformations
* interactive multiple regression
* analysis of variance for balanced design
* multiway tables
* comprehensive 'on-line' help
* descriptive statistics
* powerful plotting
* random sample generation
* macros
* probability distributions
* .....and much more.....


INSTAT operates on the **BBC B, B+** and **Master.**
Maximum Data Space: approximately 10,000 to 30,000 numbers, depending on the machine.
The **INSTAT** package consists of a disc, 16K EPROM, Introductory Guide (150pp) and Reference Guide (95pp).
Price: £85 + VAT (includes postage and packing).
Educational and multiple copy discounts.

For further details:
Alison Ansell, Statistical Service Centre,
Department of Applied Statistics, University of Reading, Reading RG6 2AN.
Tel: 0734 875123 Ext. 460 and 0734 861239 (24hr)

COMPUTER REPAIRS (UK)

2 Austins Place, Hemel Hempstead, Herts. HP2 5HN Tel: (0442) 217624

Too many function strips, wondering where to put them?
Then maybe you will be interested in our purpose built function strip holder.



only £5.50

Each holder comes with 10 clear plastic sleeves. Easily fitted to the BBC or BBC - Master series.

To compliment this little add-on, we have commissioned a function strip design programme, compatable with Epson dot matrix printers (works in condensed mode), and can also supply blank function strip cards.

Flip over function strip holder	**£5.50**
Extra sleeves for above	**£0.40**
Blank function strip cards	**£0.25**
	10 for £1.25
Function strip design software	**£4.50**
* **when purchased with holder**	**£1.50**

14 day money back guarantee if not satisfied


Available only from Computer Repairs (UK) Please make cheques or postal orders payable to: Computer Repairs (UK), to the above address.

* State whether disk or cassette.

P.S. We repair all makes of Micro, got something duff, why not give us a ring.

BOX OF TREASURES

A 55 MINUTE AUDIO TAPE – two professionally-produced stories and a play on the theme of 'boxes'. SIX BOOKLETS – lots of useful info., poems, examples, a wealth of ideas to last for many weeks. HELP CARDS – for each program, blank labels for data discs, other items. BOX OF TREASURES – can be used as the core for a lengthy project on the theme of 'boxes' or the individual items may be used independently for all manner of curriculum-related activities. FIVE PROGRAMS ON TWO DISCS: (Epson Dumps Provided). 1. THE BOX OF TREASURES – an exciting adventure. 2. CREATE – a word-processor with a difference – write a story then add animated pictures easily. 3. BLANK – a 'form processor' for designing record sheets, coupons, blank forms etc. 4. BOX DRAW – graphics design made easy – draw a picture, edit it, change the scale. 5. MAKE-A-BOX – a starting point for stories and discussions.



TELE-BOOK

An extremely flexible menu-driven program which allows 'books' of up to 15 pages of text and graphics to be created.

DRAGON WORLD

The package includes an audio tape of the exciting story and original music for dance/drama, a two-part adventure, four supplementary programs including a music synthesizer, an illustrated story book, a comprehensive User's Manual, Concept keyboard overlay, illustrated record sheets and a Book of Ideas containing 100 + suggestions for class activities.

FLOWERS OF CRYSTAL

Two part adventure, introductory dramatised audio story, work sheet, utility, map, superbly illustrated booklet teacher's manual

'LINDEN LEA', ROCK PARK, BARNSTAPLE, DEVON EX32 9AQ. TEL: (0271) 45566

	BBC Disc	BBC Cassette	Spectrum Cassette	RML Disc
Dinosaur Discovery	£16.00	N/A	N/A	N/A
Box Of Treasures	£23.00	N/A	N/A	N/A
Dragon World	£17.65	£16.00	N/A	£17.65
Flowers of Crystal	£17.65	£16.00	N/A	£17.65
Tele-Book	£17.65	£15.00	N/A	N/A
Granny's Garden	£12.00	£10.00	£10.00	£12.00
Spacex	£10.40	£8.65	£8.65	N/A

Prices include P & P. Add 1. VAT on all items. 2. £3.50 for 3" disc. (£7.00 for Tele-Book & Box of Treasures 3" Discs)

UNBEATABLE LOGOSOFT CHRISTMAS OFFER

You probably know by now that there's more to LOGO than just turtle graphics. And there's much more to LOGOSOFT than just LOGO. At the unbeatable all-inclusive price of £35 just see what the LOGOSOFT package contains:

1. A full **LOGO interpreter** on either ROM or DISC. This is the LOGO language in its entirety: list processing, data handling, numbers, variables, procedures, debugging ... and graphics too!
2. The ultimate introductory **LOGO Manual and Textbook:** 232 pages of fully illustrated instructions on how to get started in this new revolutionary programming language.
3. The **LOGOSOFT Toolkit:** Two discs containing an amazing selection of utilities, demonstrations and **applications software** including: ● Interfacing toolkit ● BBC Buggy Driver ● Cheetah Speech Chip Driver ● Epson Printer Screen Dump ● Jessop and Valiant Turtle Drivers ● Zero II Driver ● Joystick interface ● Concept keyboard interface ● Arithmetic Utilities ● Data File Handling ● Fractional Arithmetic ● Graph Plotting ● List Processing ● List Sorting ● Multiple Turtles ● Normal Distribution ● Property Lists ● Rank Correlation Coefficient ● Set Theory ● Statistics ● Transformational Geometry ● Turtle Graphics ● Vector & Matrix Algebra ● Vector Graphics ● Wrapped Turtle Graphics
4. The 40pp colour coded **Toolkit Manual** with full instructions on how to use the Toolkit software.
5. Hotline support via the **LOGOSOFT HOTLINE**, a direct line to the British software team that designed and wrote the fastest and most efficient LOGO for the BBC Micro and Acorn Master.

all for an unbeatable **£35** including VAT including postage

YES PLEASE!

I would like to take advantage of the unbeatable **LOGOSOFT** Christmas offer. Please send me the following package(s):

Quantity ___ **LOGOSOFT** on ROM for the **BBC Micro** (also compatible with the Acorn Master).

Quantity ___ **LOGOSOFT** on DISC for the **Acorn Master** (also compatible with BBC Micro sideways RAM).

Supply ☐ 40-track ☐ 80-track discs. [*please tick*]

I enclose £35 per package (VAT and postage included)

NAME _____

ADDRESS _____

Send this form to: **LOGOSOFT,** 316a Richmond Road, Twickenham, Middlesex, TW1 2PD.

or Telephone 01-891 0989

MICRO USER CLASSIFIEDS

Has upgrading your BBC Micro given you hardware you no longer need? Or have changing interests left you with unwanted software? Then THIS is the place to advertise your surplus items. Our 179,000 readers are always on the lookout for a bargain and this is the first place they'll look!

An added bonus!

Your advert will also be automatically displayed on MicroLink, the electronic mail service operated in association with Telecom Gold. This means it will be seen by thousands of computer enthusiasts who can send an instant response.

Ads will be accepted under the following conditions:

- This service is EXCLUSIVELY for the use of private readers. No trade ads will be allowed.
- To avoid encouraging software piracy, all ads will be carefully vetted before they are accepted.
- Ads can only be accepted on this form (or a photocopy of it).
- There is no maximum to the number of words you include in your ad. If there is insufficient room on the form, continue on a separate sheet of paper.
- The cost is 20p per word, with a minimum of 10 words.
- *We GUARANTEE your ad will appear in the January issue (on sale December 1) providing it is received by November 14.*

● STL 64k2 ROM Board + Discs £45, Watford printer ROM £8, STL DFS2.0 £8. Tel: 04895 2803 (Hampshire).

● Viglen Console Unit £25. Viglen cartridge system and 8 cartridges £15. Tel: Preston 683748.

● How to sell your programs to software houses and magazines. This booklet will help you succeed. Send £2.50 to J. Cassell, 96 Oakdale Close, Ovenden, Halifax, W. Yorks.

● Electron £40. Plus 1 interface £35, Slogger Turbo Board £20. Cumana disc I/F £40. 4*ROM board £10. Tel: 0772 635620 evenings.

● Acorn (Seikosha) AP100A printer, perfect condition with lead and dust cover £60 o.n.o. Buyer collects. Tel: Southport 73210.

● Disc Drive for sale. 40 track drive in excellent condition for BBC micro £50. Phone 021-458 5796.

● Brother XEP44 RS232 printer with simple word processor and calculator functions complete with Epson acoustic coupler, CX21 plus 25 way universal cable. As new, when purchased £400, will accept £150. Tel: 01-577 1738 office hours.

● Seikosha GP-80 dot matrix printer. Immaculate condition £85 + £5 P&P. Atom BBC Basic ROM board £25 + £2 P&P. Andy, 22 Northwood Crescent, Carterton, Oxford.

● Electron with Plus 1, Plus 3, software on cassette, disc and cartridge. Excellent condition, hardly used £300 o.n.o. Tel: Brackley (0280) 702136.

● BBC B with DFS, 400k switchable disc drive, Transferom and Graphics ROM £360. Tel: 0245 414097 evenings.

● BBC B, Acorn DFS, Epson disc drive, View 2.1, TDROM, all boxed as new, much software £280. Microvitec 1431AP, PAL/RGB monitor £140 or both £400. Tel: 0924 840129 evenings.

● APTL Sidewise £25, Wordwise Plus £25, Watford Epson NLQ £15, 6502 Second processor £130, all with manuals. Advanced User Guide £8. Tel: 01-658 3479.

● Opus D/D disc interface, latest upgrade £45. Timewarp clock £15. Tel: Chandlers Ford (04215) 68022.

● Cumana CS100 40T little used and 10 new Discmaster discs. Manual, formatting disc + backup £95. Hurstpierpoint (0273) 832548 evenings.

● BBC B with Acorn DFS and Solidisk 64k sideways RAM. As new £300. Tel: Coventry (0203) 315121 evenings.

● BBC B with Acorn DNFS £235, Opus double sided switchable disc drive with P/S £75. Scandinavian style computer desk £50. All as new. Tel: Ashtead 73228 (pm).

● Epson MX80 perfect condition £130. Pagemaker latest version £25. Dumpout 3 £15. Various software, sell-swap. Tel: Slough 32688 evenings.

● View £25, Driver generator £5. Complete and original. Tel: Harrogate (0423) 504373 evenings after 7pm.

● BBC B, 1.2 OS, Watford DFS, 100k drive, JVC high-res colour monitor, Sidewise, View, Viewspell, Replay, ADE, Disc-Doc, Graphics-Ext, ROMs £200 + original software £700 o.n.o. Tel: 01-570 3170 Mike (evenings).

● BBC B. Acorn DFS, Transferom, Cub colour monitor, Opus 5¼ disc drive, games on disc and tape, tape recorder £350. Tel: (0909) 486889 Worksop.

● Solidisk 256k 2/4Mhz sideways board C/W W.W.Plus ROM and manuals £110. Still boxed. Tel: Oakley 3599.

● Ultradrive Microcassettes storage system loads and saves 7 times quicker than normal cassettes, half price £50 including 8 microcassettes. Tel: 0289 307534.

● 32k RAM board, Watford Electronics £25. Wordwise+ unused, manuals included £25. Tel: 0526 43720.

● 16k Sideways RAMs plug in units, no soldering complete with read/write protect switch and software, simple to fit. Only £12. Cheques to M.J. Barkley, 67 Bishops Ave, Bromley, Kent.

● Kaga hi-res green screen monitor £65. Computer Concept's Communicator ROM, new £35. Tel: 0438 811082/MicroLink MAG10915.

● Watford DFS Upgrade Kit complete with 8271 and associated chips £35. Tel: 0903 755800 (evenings).

● View3 £30, Viewsheet £20, ATPL Sideways ROM board £30, Watford 322k Shadow board £30. Tel: 0626 67646.

● Watford 32k RAM/ROM board £35, Toolkit+ £25. Phone Southampton (0703) 552715.

● Viewsheet £30, Spellcheck £15, Forth-ROM £30, Mini Office II £8, Acorn Speech upgrade £25, 15 original cassettes £15, Mines Terror £5, Romit £14. Tel: 0865 723989.

● 300 unused discs still to go DS/DD 96tpi £6.75 inc P&P per 10. R.P. McCutcheon, 11 Mayflower Drive, Rugeley, Staffs WS15 2SW. Tel: 08894 6772 after 6pm.

● Wordwise Plus. Boxed as new. Checked but otherwise unused and with Wordwise Plus book £30. Tel: 04867 81252 after 7pm.

● Acorn Z80 Second processor only £250 complete with DNFS software and manuals. Contact Grimsby (0472) 49855 during office hours. Delivered free.

● Surplus BBC software for sale. SAE list: Carlin, Vicarage, Ragpath Lane, Stockton, Cleveland TS19 9JN.

● BBC B with sideways ROM board, ZIF socket, LVL DOS, both user guides £200. Opus twin D/S 40/80 drives with PSU £130. Star DP150 printer with cable £70. Tel/Mbx: 01-898 3181.

● BBC B 1.2 OS Basic 2 Watford disc interface, View, Viewsheet, Acorn Speech ROM, Elite, plus other software £285. Tel: 0457 (Mottram) 62376.

● Aries-B12 Romboard C/W adaptor and sideways 16k RAM £40 o.v.n.o. Forth (disc) £10. Gardening Database £3. 65C02 CPU £5. Evenings 0474 65507.

● BBC B OS 1.2 Basic2 Opus DDOS Wordwise complete with manuals. Excellent condition as new £275. Tel: 01-985 1726.

● Electron, Plus-1, Cumana disc drive and interface. View, T2CU, many cassettes (originals). Boxed as new £350 will split. T.J. Newman, 49 Blythe-Meadow Drive, Sprowston, Norwich, Norfolk NR7 8PY.

● BBC B with Acorn DFS dual 40 track drive ATPL ROM board. ROMs inc. View, Viewsheet, Datagem, Micronet, Commstar, Spellcheck2, Prism 1000, Modem, Uchida Daisywheel printer, new Philips RGB/TV monitor, complete system £980. Brian Nuttall (037284) 3017, (0836) 247950.

PLEASE PRINT THIS AD IN THE NEXT MICRO USER

Cheque enclosed for £_____ (minimum £2 for 10 words)

Name _____

Address _____

_____

POST TO: Micro User Classifieds, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 5NY.

Now's the time to link your BBC Micro to the big wide world!



Join the communications revolution and use your BBC Micro (plus the telephone) to roam the world . . . logging on to MicroLink, Telecom Gold, Prestel, Micronet and the ever-growing number of bulletin boards, both in the UK and USA. Help yourself to hundreds of free telesoftware programs – and much, much more!



You'll be able to read all about it in Britain's No. 1 communications magazine ***TeleLink.*** *The latest (Sept/Oct) issue has a free supplement on US databases Plus a guide to all the modems and comms software now available for the BBC Micro range.*

● ***Here's a special offer for readers of The Micro User. For every subscription ordered using the form below, we will give you free registration to*** **MicroLink,** ***worth £5.***

If you would like to take advantage of this offer, don't forget to tick the box!

ORDER FORM

Valid to December 31, 1986

	UK & Eire	Europe	O'seas Airmail	(✓)	£ p
One copy of the Sept/Oct issue of TeleLink	£1.50	£2	£2.50	☐ 5014	
Subscription to the next 12 issues of TeleLink	£15	£23	£38	☐ 5001	
Tick this box if you would like free registration to MicroLink *(Only available if you subscribe to TeleLink)*				☐ 5019	**FREE**
Binder	£3.95	£6.95	£10.95	☐ 5017	

Payment please indicate method (✓)

☐ Access/Mastercharge/Eurocard/Barclaycard/Visa — Expiry date /

Card No. ☐☐☐☐ ☐☐☐☐ ☐☐☐☐ ☐☐☐☐

☐ Cheque/PO/Eurocheque made payable to Database Publications Ltd.

Name _____ Signed _____

Address _____

Post to: TeleLink, Database Publications, 68 Chester Road, Hazel Grove, Stockport SK7 5NY.

Order at any time of the day or night

Telephone Orders:	*Orders by Prestel:*	*MicroLink/Telecom Gold*
061-429 7931	**Key *89, then 614568383**	**72:MAG001**

Don't forget to give your name, address and credit card number

MU12

FOR CONNOISSEURS
OF ACTION, LEISURE OR LEARNING

All programs available for BBC B, B+, Master, Compact & Electron

The ANSWER BACK QUIZ Series — each: £9.95 cassette, £10.95 5.25" disc, £12.95 3.5" disc

ANSWER BACK – JUNIOR *General knowledge for ages 6-11*
Combines a wealth of fascinating information on a multitude of topics with a compelling "Princess & Dragon" game for youngsters.

ANSWER BACK – SENIOR *General knowledge for ages 12 and over*
Space-game fans yearn to learn whilst destroying the aliens! Includes a gigantic general knowledge database of questions and answers.

ANSWER BACK – SPORT *Mega-Sports Game for ages 14-adult*
Includes machine-code football and tennis games together with a mind-bending collection of sports quizzes.

ALL ANSWER BACK PROGRAMS include simple commands for creating and saving an unlimited number of new multiple choice questions files AND are fully compatible with our new range of accessory files "FACTFILE 500".

The FACTFILE 500 Series — each: £4.95 cassette, £5.95 5.25" disc, £8.45 3.5" disc

Each pack contains a massive supplementary database of 500 questions and 2000 multiple choice answers for use with any of the above ANSWER BACK programs. FACTFILE 500 packs are available on an ever increasing range of leisure and educational subjects for youngsters, CSE/O-Level students and adults. FACTFILE 500 subjects include: Arithmetic, Spelling, Sport, Natural History, First Aid, Science, English Words, England, Scotland, and many more. Write or phone for latest subject list and age ranges.

The MODERN LANGUAGE Series — each: £8.95 cassette, £9.95 5.25" disc, £19.95 3.5" disc

Easily the most popular and successful Foreign Language Learning programs of all time, for beginners to O-Level/CSE/GCSE. Complete with extensive vocabulary files which may be extended or modified indefinitely by users.

The French Mistress (Level A or Level B)
The German Master (Level A or Level B)
The Spanish Tutor (Level A or Level B)
The Italian Tutor (Level A or Level B)
The Welsh Tutor (Available November)
*3.5" disc contains both levels A & B

Choose Level A for thousands of nouns;
Choose Level B for verbs, adjectives adverbs, phrases etc

IDENTIFY EUROPE — each: £7.95 cassette, £9.95 5.25" disc, £10.95 3.5" disc

Provides a fascinating and competitive way of discovering and learning the geography of Europe. The program will provide countless hours of amusement and all the family is sure to benefit from it. Includes an incredibly detailed map of Europe. Suitable for all ages, 6-Adult.

When ordering please state your computer type. (BBC disc users please specify 40/80 track) ALL PRICES include VAT, P&P and 24 hour despatch. Send cheque, PO or quote your Access number. Telephone orders welcome.

KOSMOS SOFTWARE

KOSMOS SOFTWARE LIMITED
FREEPOST (no stamp needed), DUNSTABLE, Beds LU5 6BR
Telephone (05255) 3942 or 5406

THE MICRO USER MAIL ORDER OFFERS

Now combined in two fun-filled packages... all the traditional card and board games you've been asking for - again and again!








BBC cassette can also be used on the Electron


B+ ✓
M ✓

BBC Micro cassette
£3.95 each
5¼" disc
£4.95 each
3" disc
£6.95 each


All this in just



WORD PROCESSOR
Compose a letter, set the print-out options using embedded commands or menus, use the mail merge facility to produce personalised circulars – and more!



DATABASE
Build up a versatile card index, use the flexible print out routine, do powerful multi-field sorting, perform all arithmetic functions, link with the word processor – and more!



LABEL PRINTER
Design the layout of a label with the easy-to-use editor, select label size and sheet format, read in database files, print out in any quantity – and more!



...and at a price t

Mini Office II offers the most comprehensive, integrated suite of programs ever written for the BBC Micro – making it the most useful productivity tool yet devised.

A team of leading software authors were brought together to devote a total of 26 man years of programming to the development of Mini Office II. What they have produced is a package that sets new standards in home and business software.

The sample screenshots above illustrate just a few of the very wide range of features, many of which are usually restricted to software costing hundreds of pounds. Most are accessed by using cursor keys to move up and down a list of options and pressing Enter to select.

Is it that easy to use? Several leading reviewers have already sung its praises on this very point.

Yet possibly the best advertisement for Mini Office II is that it comes from the same stable that produced the original Mini Office package back in 1984.

That was so successful it was shortlisted in two major categories of the British Microcomputing Awards – the Oscars of the industry – and sold in excess of 100,000 units!

It was up to Mini Office II to take over where the first Mini Office left off, with 32 extra features, two additional modules, a program to convert existing Mini Office files to Mini Office II format, and a 60 page, very easy to follow manual.

This is the package thousands of BBC Micro owners have been waiting for – and at a price everyone can afford!


Here
Menu
compl
manu
really
packa
you m
What
small
there's

t ONE package!




SPREADSHEET

Prepare budgets or tables, total columns or rows with ease, copy formulae absolutely or relatively, view in either 40 or 80 column modes, recalculate automatically – and more!




GRAPHICS

Enter data directly or load data from the spreadsheet, produce pie charts, display bar charts side by side or stacked, overlay line graphs – and more!



COMMS MODULE

Using a modem you can access services such as MicroLink and book rail or theatre tickets, send electronic mail, telex and telemessages in a flash – and more!



ce that can't be matched!

Here's what some independent reviewers say about Mini Office II:

Menus throughout the program were abundant and well structured, allowing complex choices to be made with hardly a glance at the pocket-sized spiral-bound manual, and offering a wealth of user-defined functions . . . For the money it really is unbeatable. Dedicated word processors, spreadsheets and comms packages may offer some extra facilities, but some are so full of whistles and bells you may find yourself forever in the manual or even not using half of their power. What you get with Mini Office II is a valiant attempt to provide an all-embracing small business package at a down to earth price; it fulfills all its promises, and there's nothing cut-rate about the facilities it provides. – **Viewfax 258 (Prestel)**

The original Mini Office has been recognised as an astonishing bargain for anyone looking for a low-cost introduction to serious software. Now the four programs which made it up have been substantially enhanced and two new programs have been added. The result, Mini Office II, is more than just an introduction to serious software applications. It's good enough to fulfill the entire software needs of many a small business! . . . The range of features in each program is astonishing for a package of this cost . . . The spreadsheet is every bit as good as a program such as MasterCalc which costs more than the entire Mini Office II . . . This delightful little program [Graphics] allows you to produce professional looking charts to illustrate a set of figures. – **Amstrad Action**

The word processor is literally overflowing with excellent features . . . The database is very easy to use yet extremely powerful . . . The spreadsheet program is the next little gem . . . Having used Mini Office II for the past few days I cannot praise it too highly. – **Popular Computing Weekly**

BBC Model B and B+	
Cassette	*£14.95*
5¼" disc	*£16.95*
3" disc	*£19.95*

DATABASE SOFTWARE

Order form on Page 167



4 great offers to su


Now YOU can fly with the legendary Red Arrows – in the most challenging flight simulation ever!

It's the most exciting, full colour flight simulator ever written for the home computer – and it uses every ounce of the micro's power to give the utmost realism to recreating the most spectacular aeronautical displays that have thrilled crowds at air shows for the last 21 years. The program comes with a detailed flight handbook that will soon help you take YOUR place alongside the ace pilots of the Red Arrows!

Save upto £10!

Tape 99p
5¼"disc £1.95
3"disc £2.95

Save up to 60% on these classic books



'Getting started in Sound & Graphics' shows you how to harness the power of your micro to create dazzling displays and superb sound.

In this compilation of their highly praised series of articles in *The Micro User*, Michael Noels, Paul Jones and Nigel Peters explore the BBC Micro's outstanding sound and graphics capabilities.

Assuming only a rudimentary knowledge of Basic, the authors thoroughly explain all the programming methods involved, ranging from the simplest to the most complex.

Based on the highly praised series for beginners in *The Micro User*, 'Getting started in BBC Basic' takes the reader through the fundamentals of writing programs.

Its hands-on approach has been specifically designed to teach the absolute novice not only the formal rules of Basic but also that elusive quality – good programming style.

By working through its many examples, the reader will gain a clear insight into structured programming and will quickly acquire the ability to use structured techniques in creating his own programs.



WERE £5.95 EACH ▶ **NOW ONLY £2.95 EACH** ▶ **OR £4.75 FOR BOTH!**

THE MICRO USER MAIL ORDER OFFERS


to subscribers!

Top of the charts for EIGHT weeks! Now it comes to you at a 50% saving!

Thrust has to be one of the most addictive games ever created for your BBC Micro. Fly over the alien planet, blow up the limpet guns, collect the Klystron pod and, with the pod swinging realistically below your ship, carry it off into space.

Tape £4.00
5¼" disc £4.50

If you already have a subscription which does not expire for several months you can re-order early to benefit from these exceptional offers. (Not available without subscription)



Your BBC Micro needs protecting!




Our luxury dust cover is made of soft pliable water-resistant transparent vingyl, bound with strong cotton and decorated with the *Micro User* logo in black.

Only £3.95

Keep your copies neat and complete

These handsome binders are bound in PVC with the *Micro User* Logo in gold blocking on the spine



Only £4.25

THE MICRO USER MAIL ORDER OFFERS

Here's a feast of games, utilities and educational programs!

MARCH 1985: Astromines, space action. **Castle,** two player catapult battle. **Data Maker,** take the tedium out of entering Data. **Disc Search,** string search utility. **Command,** give your BBC and Epson printer the same character set. **Break Key,** disable Break. ***Plus Flex – a machine code game.***

APRIL: X15, sideways-scrolling spectacular. **Mornington Crescent,** fun on the London underground. **Calculator,** AMX mouse mathematics. **Dithering,** colour mixer. **Chatterbox,** speech chip procedures. ***Plus Rabbit Run – a machine code game.***

MAY: Stellar Rescue, arcade action. **Dominoes,** simulation. **Plot69,** fast Mode 2 plot routine. **Musical Events,** a music interrupt utility. **Pound and Hash,** an Epson printer routine. **Sheila,** let your micro run your slide show.

JUNE: Othello, simulation of the board game. **Activities,** word association. **Catnap,** arcade enjoyment. **Simon Quackers,** superb lightpen game. **Shape recognition,** teach your micro to identify. **Stripper,** a routine for removing line numbers. **Epson,** a type-setting utility. **Lprint,** simplifies string output. **Eval,** using the Basic command from machine code.

JULY: Fly, an arcade spectacular. **Draughts,** a superb version. **Compox,** 3D noughts and crosses. **Double Height,** large characters in Modes 0-6. **Clock,** alarm utility. **Compacter,** compress Mode 2. **Inside Basic,** basic routines in machine code. **RAMpage and RAMsave,** sideways RAM utilities. **Video,** graphics to music.

AUGUST: Harbour Command, protect a Cornish town. **Fruit Machine,** a gambler's favourite. **Mouse Organ,** AMX mouse music utility. **Flash,** alternative flashing colours. **String Formatter,** prevent end of line word splitting. **M/C Games,** random number and key detection routines.

SEPTEMBER: Ball Lightning*, tame the lightning. **Quarters,** game of skill. **6502 Games,** a simple arcade game. **Variable Lister,** track your variables. **Smiley Hunt,** Al's game. **Error handling,** the vital routines.

OCTOBER: Karate, superb martial art action. **Solitaire,** all-time favourite. **Scroller,** text scroll utility. **Case,** an ON PROC command. **Disc Scan,** search for disc files. **Adventure,** avoid the vampire.

NOVEMBER: Whodunnit, solve the murder. **Gloop Gulp,** zany arcade action. **Basic Analyser,** take the drudgery of debugging. **Wordwise F/keys,** get the most from your word processor. **Sideways,** sideways screen clear. **New Modes,** Modes 8, 9 and 10. **Disabler,** prevent star command clashes.

DECEMBER: Wizard's Castle*, recover a diamond from the necromancer's lair. **Squares,** 'join the dots' strategy. **McBase,** powerful database. **Alphabet Train,** early spelling. **Basic Analyser,** the vital cross reference tables. **Wordsquare Creator,** to create your own puzzles. **Dumper,** how your programs affect memory. **Subhunt,** the final listing. ***Plus the listings from Body Building and Adventures.***

JANUARY 1986: Megaroids, exciting space action. **Claustrophobia,** can you get out of the maze in one piece? **Fives,** mind bending noughts and crosses. **Music Editor,** translate musical notation. **Wordsquare Solver,** the program to help you solve them. **Find and replace,** find and replace any item of text in a Basic listing. **Discopy,** copy and/or rename files. **S-sound,** sounds into electronic effects. **Alice,** another baffling problem.

FEBRUARY: Tipaka, can you escape the castle in one piece? **USS Endeavour,** fast and exciting action. **Ploy,** brain teasing strategy game. **Up-and-down-loader,** an aid for loading and saving. **Fast Verify,** verif saved disc files. **Disc Assembler,** assemble multi-part source files to disc. **Shift and Echo,** more electronic effects from the Body Building course. **8271,** using OSWORD to format a disc in a special way. **Elite Cheat,** the easy way to the top.

MARCH: Morris Miner, escape the mine in this levels and ladders spectacular. **Poster Puzzler,** a sliding block simulation. **Quicksort,** a fast machine code sort routine. **Character Sets,** create and display your own fonts. **8271,** four programs to complement the last article in the series. **Sound Sampler,** programs from the Body Building course. **Eleusis,** another mind bending puzzle from Alice.

APRIL: Ghouls of Azzod, can you escape from Azzod manor? **Mousetrap,** a simple but infuriating chase game. **Character Sets,** outputting characters using Epsom compatible bit-imaging. **Special Fonts,** create interesting displays with alternative fonts. **Notepad,** forget scraps of paper with this electronic jotter. **Hexer,** a loader for use in the machine code series. **Hyperspace,** another puzzler from Alice. **While Wend** and **While Wend Demo,** two listings from the mail pages.

MAY: Cavern Quest*, can you collect the diamonds before your oxygen runs out, avoiding the falling boulders as you go? **4-Site,** a 3-dimensional adaptation of noughts and crosses. **Catalog II,** disc operations achieved quickly with a single key press. **Taming the Tube,** turning the 6502 second processor on and off by software. **Character Sets,** creating slim characters for use in Modes 2 and 5. **Alice,** another intriguing puzzle from our adventurer.

JUNE: Pendragon*, can you keep the evil yellow perils away from the sugar cubes, while positioning the four diamonds? **Spacebase,** you must defend Earth from the invading hoarde of aliens. **Rainbow,** this lightpen graphics utility will keep you happy for hours.

JULY: Royal Wedding, celebrate the most exciting royal event of the decade with this superb sliding block puzzle. **Dual Catalog,** This utility provides 56 files on one side of a disc. **Viewgen,** what you see is what you get with this printer driver generator for View. ***PLUS digitised picture of Andrew and Sarah (disc only).***

ONLY
£3.75 tape
£5.75 5¼" disc
£7.75 3" disc

AUGUST: Fruit Worm, can you survive the dangers of the deadly garden? **Upper,** force all your input into upper case. **Inkjet,** a printer test and two screen dumps for the ink jet printer. **Safer,** prevent accidentally overwritten files. **Hash,** a suite of programs illustrating searching techniques. **Geiger,** the software for the Body Building course.

SEPTEMBER: Pear Picker, avoid Plastered Patrick in your attempts to become a professional fuit picker. **Basic Events,** control events from Basic. **Learner,** teach your word processor to remember those key sentences. **View Preview,** a useful program to preview pages of View files. **VDU19,** programs to demonstrate the illusion of animation. ***BONUS PROGRAMS: Rockfall and Any Questions (Mathematics and General studies).***

OCTOBER: Witch Hunt, search for the 42 keys of Transportal. **Coloured Lights,** an educational program to explain the GCOL effects. **Mode 7 Dumps,** screen dumps for Epson compatible or Olivetti Inkjet printers. **Text Compressor,** a clever utility to get long messages into short memory. **Auto Run,** star run Basic programs. **Weather Vane,** the program to complement the Body Building wind direction project. ***BONUS PROGRAMS: Quasimodo's Quest and Any Questions? (Music and Computer Studies).***

NOVEMBER: Maltese Cross, play this superb domino simulation. **Life,** the generation game to produce colourful patterns. **Star Print,** a clever routine to give easy access to print styles. **View Ruler,** a handy program to provide View with a cursor on its ruler line. **Shadows,** an educational program to throw some light on the subject. **Dual Screens,** a routine to store two screens in memory at once. **BOS Editor,** a superb on-screen editor for Basic programs. **Body Building,** three programs for your pressure sensitive devices. ***PLUS three more files for Any Questions (Office practice, DIY, and Tables).***

DECEMBER: Santa's Sleigh, help Santa in his gift warehouse – but watch out for the monster spider. **Christmas Box,** a superb game of logic to test the old grey matter. **Tables,** take the tedium out of multiplication tests with this short but effective routine. **Flood Fill,** a versatile fast fill routine. **Scroller,** a machine code program to provide fast scrolling in any direction. **Speech,** a software utility to get your micro to talk back to you. **Break Recover,** hold on to variables when Break is pressed. **Body Building,** software for the relative humidity measure. ***PLUS Two more files for Any Questions (Arithmetic and Home Economics).***

** Not Master compatible.*

B+ ✓
M ✓

TO ORDER TURN TO THE FORM ON PAGE 167

THE MICRO USER

MAIL ORDER OFFERS

ORDER FORM

Overseas orders:
ALL GOODS NOW SENT AIRMAIL

Valid to December 31, 1986

Please tick items in box below

Annual subscription

		£ p
UK & Eire (Sterling only) £15	2001	
Europe: Surface £25	2365	
Overseas: Surface £25	2366	
Overseas Air £42	2004	

Commence with ..... issue

Renewals

		£ p
UK & Eire (Sterling only) £15	2002	
Europe: Surface £25	2114	
Overseas: Surface £25	2367	
Overseas: Air £42	2113	

Subscription offers*

		£ p
Red Arrows tape 99p	2334	
5¼" 40T £1.99	2335	
5¼" 80T £1.99	2351	
3" disc £2.99	2336	
BBC Basic Book £2.95*	2289	
Sound and Graphics Book £2.95*	2223	
Both £4.75*	2352	
Thrust Tape £4.00	2353	
Thrust 5¼" 40/80 T disc £4.50	2354	

* These offers only available if accompanied by subscription order or renewal

Annual subscription for cassettes and discs

B+ ✓ M ✓

	UK	Europe/ Overseas		£ p
BBC 'B' cassette	£35	£45	2005	
5¼" disc 40T	£50	£60	2006	
5¼" disc 80T	£50	£60	2007	
3" disc	£65	£75	2008	

Commence with ..... (state month)

Renewals

	UK	Europe/ Overseas		£ p
BBC 'B' cassette	£35	£45	2009	
5¼" disc 40T	0	£60	2010	
5¼" disc 80T	£50	£60	2111	
3" disc	£65	£75	2112	

Classic Card and Board Games

B+ ✓ M ✗

		Tape £3.95	5¼" disc 40 track £4.95	5¼" disc 80 track £4.95	3" disc £6.95
No. 1	2460/3				
No. 2	2464/7				

Classic Arcade Games

B+ ✓ M ✗

		Tape £3.95	5¼" disc 40 track £4.95	5¼" disc 80 track £4.95	3" disc £6.95
BBC 'B'	2246/49				

Mini Office II

B+ ✓ M ✗

		£ p
BBC 'B' cassette £14.95*	2368	
5¼" disc 40T £16.95*	2369	
5¼" disc 80T £16.95*	2370	
3" disc £19.95*	2371	

Instant Mini Office II

B+ ✓ M ✓

		£ p
Instant Mini Office £59.95†	2372	
Upgrade Mini Office II to Instant Mini Office £51.95† I enclose full tape/disc pack.	2375	

*Add £2 for Europe Add £5 for Overseas
†Add £3 for Europe. Add £8 for overseas

Dust Covers

		£ p
BBC B & B+ £3.95	2220	
BBC Master £3.95	2222	
BBC Master Compact £3.95	2224	

Christmas Crackers

NEW

B+ ✓ M ✓

		£ p
BBC 'B' cassette £6.95	2355	
5¼" disc 40T £9.95	2356	
5¼" disc 80T £9.95	2357	
3" disc £11.95	2358	

Single copies of monthly cassette/discs

☐ Any 5 tapes for £15

B+ ✓ M ✓

				5¼" disc 40 track £5.75	5¼" disc 80 track £5.75	3" disc £7.75
	1985					
Astro Mines + Flex	Mar	2141/44				
X-15 + Run Rabbit	April	2145/48				
Stella Rescue	May	2149/52				
Othello	June	2153/56				
Mutant Fly	July	2157/60				
Harbour Command	Aug	2161/64				
Ball Lightning*	Sept	2165/68				
Karate	Oct	2169/72				
Whodunnit	Nov	2173/76				
Wizard's Castle*	Dec	2177/80				
	1986					
Megaroids	Jan	2181/84				
Tipaka	Feb	2185/88				
Morris Miner	Mar	2412/15				
Ghouls of Azzod	April	2416/19				
Cavern Quest*	May	2420/23				
Pendragon*	June	2424/27				
Royal Wedding	July	2428/31				
Fruit Worm	Aug	2432/35				
Pear Picker+ Rockfall	Sept	2436/39				
Witch Hunt + Quasimodo's Quest	Oct	2440/43				
Maltese Cross	Nov	2444/7				
Santa's Sleigh	Dec	2448/51				

*Not Master compatible

Micro User back issues

UK £1.75
Europe £2.25
Overseas £3.75

		£ p			£ p
Mar 1985	2033		Jan 1986	2043	
April 1985	2034		Feb 1986	2044	
May 1985	2035		March 1986	2400	
June 1985	2036		Apr 1986	2401	
July 1985	2037		May 1986	2402	
Aug 1985	2038		June 1986	2403	
Sept 1985	2039		July 1986	2404	
Oct 1985	2040		Aug 1986	2405	
Nov 1985	2041		Sept 1986	2406	
Dec 1985	2042		Oct 1986	2407	
			Nov 1986	2408	

Micro User Binders

UK £4.25
Europe £7.25
Overseas £9.25

2221 £ p

French on the Run

NEW

B+ ✓ M ✓

		£ p
BBC 'B' cassette £9.95	2359	
5¼" disc 40T £11.95	2360	
5¼" disc 80T £11.95	2361	
3" disc £13.95	2362	

Fun School

B+ ✓ M ✗

		Tape £3.95	5¼" disc 40 track £4.95	5¼" disc 80 track £4.95	3" disc £6.95
Age 2-5	2338/41				
Age 5-8	2342/45				
Age 8-12	2346/49				

European & Overseas Postage Prices

Please add £2 postage per item unless otherwise stated.

All overseas items now sent Air mail.

>>>

Don't forget to fill in your name and address overleaf.

TOTAL £ p

Payment: please indicate method (✓)

☐ Access/Mastercharge/Eurocard/Barclaycard/Visa

☐☐☐☐ ☐☐☐☐ ☐☐☐☐ ☐☐☐☐

☐ Cheque/PO made payable to Database Publications Ltd.

Expiry Date ☐☐/☐☐

BLOCK CAPITALS PLEASE

Name_____

Address_____

_____

_____

_____ Post Code_____

Tel: _____

Signed_____

Please allow 28 days for delivery

You can also order by phone, Prestel or MicroLink/Telecom Gold

- Any of the goods listed here can be ordered by telephone.
- Micronet subscribers and other users of Prestel can also use the Prestel mailbox.
- MicroLink subscribers and other users of Telecom Gold can also use the MicroLink mailbox.

Orders: 061-429 7931
24 hours
Enquiries: 061-480 0171
9am-5pm.

Prestel
Key Page 89, then send your order to:
614568383
24 hours

MicroLink/Telecom Gold
72:MAG001
24 hours


Don't forget to quote your credit card number AND your full address.

TUCK INTO FLAP

Don't forget to provide: Your address, your cheque/credit card No.
If you've ordered discs have you indicated which format?

The Micro User,
FREEPOST,
Europa House,
68 Chester Road,
Hazel Grove,
Stockport SK7 5NY.

NO POSTAGE NEEDED
(IF POSTED IN U.K.)



BBC/ELECTRON 'IMAGE' V.2

'IMAGE' was the ultimate tape back up system now, it's even better

You can be completely assured that this is the best and most able program of its type available. It can deal with:

* Locked programs
* Programs of any length
* 300† and 1200 BAUD
* Files
* ?'s (Ctrl codes) in Filename
* Multiple back ups
* False or trick block info.
* Changing Filename†
* Continuous data stream†
* Locking and unlocking programs

It is VERY IMPORTANT INDEED purchasers take note that 'IMAGE' is for sale strictly for making BACK-UPS of your own software for your own use, for protecting your own programs, or as an aid to putting software on disk. Any person found using the program for illegal purposes runs the risk of being prosecuted.

To receive your copy of 'image', send a cheque or P.O. for the sum of **An Astounding £5.80 to:**

Peter Donn, Dept. MU, 18 Tyrone Road, Thorpe Bay, Essex SS1 3HF

Please state BBC or Electron version. V.1 owners can obtain V.2 by sending £1.50 + V.1 without case

AA269 †BBC version only

DUAL V.D.U. SPLITTER

This unit plugs into the RGB socket on the computer. Two outlets, allow two V.D.U.s to be connected. Each then displays its INDIVIDUAL foreground picture, with a COMMON background to both. A selector switch allows both V.D.U.s to display the same complete picture. (Ideal for two player games, ie, Battleships, Subhunt, Combat etc).

PLEASE NOTE: Even on colour V.D.U.s, it will only produce black and white pictures.

Two models available are:

M/M, (two monitors) at £24.15.

M/T, (one monitor one TV) at £29.90

Prices include VAT, postage and instructions

A third unit T/T. (two televisions) is under development

Although untested on the new Beeb, the M/T model should be able to drive a Television on its own.

Enquiries and/or cheque to:


TECA Ltd

Swain Road, Tenterden, Kent TN30 6SL. Tel: 05806 4896

Enquiries from the trade or software houses are welcome

RAMFILE

Archmac Software



The SIMPLE, FAST database – the ultimate in User-Friendliness.

Field/Record lengths CONTINUOUSLY VARIABLE within limits. NO setting up needed. Switch on and go.

Holds complete files IN MEMORY for maximum SPEED. Up to 14k – and ALL DATA. NO padding out with spaces.

AMEND records with ease. Simplest ever SEARCH facility. Simple, sure and FAST. Many kinds of PRINT-OUT.

APPEND RECORDS to files directly from textfiles – regardless of field or record lengths!

SPOOL selected records/entire file as TEXTFILE for wordprocessing.

Wordprocessing support included – 5 free Wordwise Plus utilities.

Disc £15.00. State 40 or 80 Track.

Also at £15.00, ROMFILE (RFS) for Cassette and BASIC I users.

Archmac Software, 19 Loskin Drive, Glasgow G22

The AMAZING

★★★ TELEBOX ★★★

Turns any monitor with a composite video input into a QUALITY TV set!!

Now you can add a DUAL PURPOSE to your computer monitor by simply plugging in a TELEBOX – giving you a QUALITY 7 channel off air COLOUR UHF TV SET.

The self contained, mains powered TELEBOX contains all the necessary electronics etc to give a standard PAL video output signal and separate low level audio output to cater for all types of video monitors with a composite video input. For owners of monitors without sound an integral 4 watt audio amplifier will drive any suitable speaker or headphones.

Other features include: SAW filter, Auto AGC, Switched mains output, BRITISH MANUFACTURE, Sold 50% BELOW actual cost, 2 year guarantee.

DON'T MISS this AMAZING OFFER. Many other uses include: HI-FI sound tuners, Front end tuners for TELETEXT, TV sound for partially sighted or hard of hearing, TV tuners for video recorders, Video distribution etc etc.

Available soon for RGB Monitors – send SAE for details.

ONLY £27.50 Plus £2.50 P&P

Send Cheque/PO to:

Dept. MU12, Chiltern Communications Company
8 Chiltern Street, London W1.

Colour picture only with colour tube.

LARGEST COMPUTER CENTRE IN NORTH WEST UK

Home and Business Computers

Main Dealers for:

Acorn, Atari, Ferranti, Epson, Commodore (Amiga), Kaypro, Sanyo, Olivetti, Sperry.

Also joysticks, books, disk drives, calculators, cables, monitors.

Large Showroom. FREE delivery mainland UK for items £100 or over

Personal export specialists.

ALL EXPORT ORDERS TESTED BEFORE DESPATCH

MIGHTY MICRO

NO ORDERS TOO SMALL

268 Wilmslow Road, Fallowfield, Manchester M14 6WL

Telephone: 061-224 8117

Children (of all ages) playing games on BBC model B's?

You need:

SOUND VOLUME CONTROL

and

HEADPHONE SOCKET

Model B only

Easily fitted – no soldering

Price **£6.90** (incl. VAT & p&p)

From:

Cantocks Enterprises Ltd

25 Hillside Avenue, Midsomer Norton, Bath BA3 2LT

«« MORE EXPANSION FOR THE BBC RANGE »»

This month we are introducing two new port selectors, an enhanced Break-Out Box for the 1MHz Bus and a very small battery-backed RAM board. See previous adverts for our normal range.

The USER PORT and PRINTER PORT SELECTORS offer selection of one peripheral from several permanently connected to the port as with our RS423 Selector.

Address decoding, deglitching in the Mk2 1MHz BUS BREAK-OUT BOX gives even greater utility to this popular unit.

BATTERY-BACKED 16K RAM provides non-volatile storage for up to 1000 hours and includes utilities for use in the BBC 'B'.

User Port Selector (3-way)	**£74.95**
Printer Port Selector (2-way)	**£69.95**
Enhanced 1 MHz Bus Breakout Box (Mk 2)	**£29.95**
Battery-Backed 16K Mini-RAM Board	**£37.95**

(P&P - Add £1.50 for B/O Box, RAM Board, £2.50 for other items)

Also ribbon cables, BBC power leads made to your requirements.

Write or phone with full details for quotation.

Information sheets available for all or individual products.

Please make cheques/Postal Orders payable to:

COMPUTECH

The Garth, Hampsfell Road, Grange-over-Sands, Cumbria. LA11 6BG

Tel: 04484 4604

MANSFIELD COMPUTERS AND ELECTRONICS

BBC Master 128	429.00
BBC Master Compact	from 441.00
Amstrad PCW 8256	458.85
Amstrad PCW 8512	573.85
Amstrad PC1512	from 458.85
Spectrum 128+2	149.95
Spectrum 128+2 with joystick + 6 pieces software	159.95
Citizen LSP10 Dot Matrix Printer	199.00
Epson LX80	259.00
Epson LX86	269.00
Full Range of Monitors inc. Thomson 12" Monochrome Monitor (Special Offer)	99.95
Opus Single 40/80 Switchable disk Drive	from 115.95
Opus dual 800K Disk Drive inc. PSU	269.00
Acorn Dual 800K Disk Drive with Plinth	316.00
MCE 'Universal' top quality diskettes 5.25" (box of 10)	9.95

Extensive range of Printer Ribbons and Paper at Special Prices

Joysticks – Interfaces – Business Software – Games Software

All Prices Include VAT

Guaranteed service on all goods, including out of warranty service, by our own service department. We are Acorn, Amstrad, Spectrum and Commodore Specialists

33 Albert Street, Mansfield, Notts NG18 1EA

Telephone (0623) 31202

MCE

ZONE FOUR

ZONE FOUR DISKS 5.25" D/S D/D 96TPI 10's **10.95**
Our own branded disks are of the highest quality and manufactured to the highest specification and with hub rings.

BULK DISKS

	50's	100's	250's	500's
5.25" S/S D/D 96TPI	**30.00**	**55.00**	**130.00**	**250.00**
5.25" D/S D/D 96TPI	**35.00**	**65.00**	**140.00**	**270.00**
	25's	50's	100's	
3.50" S/S 135TPI (½m/byte)	**43.75**	**85.00**	**165.00**	
3.50" D/S 135TPI (1m/byte)	**48.75**	**95.00**	**180.00**	
	10's	50's		
*3.50" S/S D/D 135TPI (½ m/byte)	**19.95**	**92.50**		
*3.50" D/S D/D 135TPI (1 m/byte)	**25.95**	**99.50**		

*with free library case.
3.00" Maxell/Amsoft/Panasonic 10's **34.95** In stock now

JOYSTICKS
MOONRAKER 1 **4.95** QUICKSHOT II **5.95**
LOCKABLE STORAGE BOXES 3.50" & 5.25" IN STOCK
All prices incl. VAT and P&P (Except Lockable Storage boxes)

To order please phone or write to:
ZONE FOUR, 65 Century Road, Walthamstow, London E17. (01-523 2059)
(Mail Order only)

S.P. ELECTRONICS

ALL IN STOCK — BBC SPECIALISTS

BBC MASTER COMPACT	From £458.00
BBC MASTER 128	£499.00
BBC 'B'	£299.00
BBC 'BD'	£350.00
BBC 'BDE'	£375.00
Cumana CD800S (800K) 2 x 80 track DS drive with PSU	£299.00
Cumana CDX800S (800K) 2 x 80 track DS drive without PSU	£244.00
Disc Operating System	£96.00
Disc Drives	from £99.00
G3WHO Rtty Program (Tape)	£7.50
G3WHO Rtty Program (Eprom Version)	£20.00
Circuit board for Rtty decoder Mk3 (inc. instructions)	£10.00
Canon Dot Matrix 160cps NLQ Printer	£299.00
Printer Cable (Centronics)	£12.90
Disc Doctor	£33.00
WORDWISE Word Processor	£33.00
Slow Scan TV Circuit Board & Program (inc. instructions)	£17.50
ADFS	£29.90
1770 DFS Kit	£49.90

We are Acorn approved dealers & repair specialists

Wide selection of software, books, leads, plugs, etc. All prices only
SAE for full list. All available Mail Order while stocks last.

48 Linby Road, Hucknall, Notts. NG15 7TS
Tel: 0602 640377

Educational & institutional orders welcome
(all prices include VAT) *Carriage extra*

Advertisers Index

21st Software 12
Abico 118
Acorn 48, 49
Advanced Memory Systems 3, 13, 23
Advanced Technological Research 88
Amcom 36
Archmac Software 169
Arlon Printers 122
ATPL 96
Audiogenic Software 133
B & S Computing 137
Beebug 15-18
C & F Associates 147
Cantocks Enterprises 169
Care Electronics 92
Carswell Computers 148
Centec 148
Chalice Software 134
Chilterns Communications 169
CJE Micros 64
Clares Micro Supplies 70
CMS Soft 148
Comlex 148
Computech 169
Computer Concepts 50, 51
Computer Express 122
Computer Repairs 157
Contex Computing 98
CP Microsystems 98
Datapen Microtechnology 118, 141
Data Store 122
Design People Software 126
Direct Disk Supplies 42
Disking 100, 101
Flora Electronics 170
Galaset 68
G.P.D.Systems 6
Incentive Software 110, 147
Kosmos Software 160
Leigh Computer Systems 44
Logosoft 158
Mancomp 94
Mansfield Computers 169
Memex 141
Microdis 140
Micro Media 11
Micromen Computers 8
Mighty Micro 169
Minerva Systems 134
Minic Business Services 157
Moordene Associates 122
Morley 104
Musbury Consultants 118
Number One Systems 110
Opus 114, 119, 123
Pace Micro Technology 46
P&H Electronics 86
Paul Fray 170
Peter Donn 169
Pinapple Software 138
Ptarmigan Software 44
Qual-Soft 66
Rock Hall 170
Rockfort 102
Selec Software 110
Silicon City 157
Softlife 147
Software Services 138
Solidisk 24-30
S.P. Electronics 170
Statistical Service Centre 157
Store Stock Systems 34
Stort Soft 148
Superior Software 2, 171, 172
System Software 120
Teca 169
Technomatic 74-82
Twillstar Computers 150-152
Vine Micros 114
Vision Software 46
Volmace 14
Watford Electronics 52-63
We Serve 141
Zone Four 170

S P I D E R 2
REAL-TIME CONTROL FOR THE BBC MICRO

Watch the SPIDER!
- Powerful new BASIC commands for invoking PROCs from the User Port, Serial Port or the Keyboard.
- 8 independent countdown timers.
- Easy to install with no soldering.
- Comprehensive manual supplied.

New SPIDER 2 features
- Special keywords for controlling the Serial Port.
- Professional implementation of Foreground/Background processing.
- Reaction timing and pulse trains accurate to 0.1 milliseconds!

from £65 including VAT

SPIDER 2 is a RAM/ROM combination which uses none of the BBC's memory, so BASIC programs are unaffected. The BBC B+ is fully supported and we supply a complete range of digital, analogue and serial interfaces for use with SPIDER using the 1MHz bus. Ask now for details.



SPIDER – stamps out I/O bugs

NOW AVAILABLE FOR THE MASTER

Paul Fray Ltd
Willowcroft, Histon Road, Cambridge CB4 3JD
Telephone: (0223) 66529

YOUR PERSONAL CENTRONICS PRINTER

UNBEATABLE FROM £99 OPTION TRACTOR
plus vat and £8 p+p



- FAST 50/100cps FAST
- DRAFT MATRIX PRINT
- NEAR LETTER QUALITY
- SUBSCRIPT SUPERCRIPT
- CONDENSE EMPHASISE
- 96 CHAR+48 EURO+16 MATHS
- EPSON/IBM PC GRAPHICS

128 Station Rd
Glenfield
Leicester
LE3 8BR

ROCK HALL
TEL (0533) 313531.

DISKS

PRICES PER BOX OF 10 DISCS
ALL DISCS FULLY GUARANTEED

	40 TRACK		80 TRACK	
5.25" Diskettes	SS/DD	DS/DD	SS.DD	DS/DD
STORAGE MASTER	£11.00	£13.00	£15.00	£17.50
NASHUA (Lib Cased)	£12.00	£15.00	£16.00	£18.50
MAXELL	£14.00	£16.00	£16.00	£21.00
UNBRANDED	£ 7.00	£ 8.00	£ 9.00	£ 9.00
BULK PACK (25 Discs)	£16.00	£19.00		£20.00

3.5"Diskettes, Storage Master, Nashua, Sony (Box of 10)

SS/DD £23.50 DS/DD £32.50

40/80T Switchable Disc Drives

	with PSU	without PSU
Cased Single	£140.00	£130.00
Cased Double	£240.00	£225.00
5.25"Disc Drive maintenance kit		£21.00

MEMORIES (BBC COMPATIBLE)

2764-250ns	£2.25	41256-15	£2.50
27128-250ns	£2.80	41254-15	£5.00
27256-250ns	£5.00	41464-15	£5.00
27C256-250ns	£6.50	41416-15	£2.50
6264LP-15	£2.75	65C02CMOS	
8271 FDC	£37.50	CPU 2Mhz	£9.00
4164-15	£1.00	CPU 4Mhz	£18.00
8271 + TTL & CMOS Chips (Ex DFS ROM)			£42.50

LISTING PAPER

11" x 9.5" Microperforated 60gsm 2000 sheet £11.00 (+ £3 P&P)

FLORA ELECTRONICS

14 LEVER STREET, PICCADILLY,
MANCHESTER M1 1LN
Tel: 061-228 3553

CALLERS WELCOME
Educational & Institutional orders welcome
All prices include VAT & P&P

STRYKERS RUN

The ultimate release for the BBC Micro include a specially enhanced version for the BBC Master making use of its 128K RAM. An extra 40K of detailed graphics are provided together with additional game features and atmospheric music.



Commander Stryker under fire in the city



Battling in the air



An action close-up



Enemy equipment (Enhanced BBC Master version)



A camouflaged Battle fortress (Enhanced BBC Master version)

STRYKER'S RUN for the BBC Micro B, B+, Master and Master Compact.

Compatible with the BBC B, B+, Master and Master Compact computers.

Stryker's Run features probably the best graphics ever seen on the BBC Micro; the action is intense and the animation is superlative.

The battlefield graphics include cities, edifices, wrecked buildings, trees gravestones, bridges, despatch-posts, military bases, helicopters and jet ships, with hills and mountains in the background. The Master-enhanced version also includes statues, watch-towers, a neglected cafe, a deserted cinema, aircraft hangars, aeroplanes, trucks and tanks.

For many years, a war has ensued between the Allied Nations and the Volgans. The battle was reaching a stalemate position, but recently the Allies through good intelligence work and some luck have managed to obtain the plans of the Volgan's next offensive. If the Allied Forces can capitalise on these plans they can end the impasse and the war. You play the role of Commander John Stryker commissioned to take this top-secret information to the Allies' HQ.

Your character in the game can jump, run, duck, fire his laser pistol and throw grenades. He can also board aircraft and fly them, making use of their more powerful weaponry.

Your opponents, the Volgans, have a variety of weapons at their disposal comprising rifles, pistols, grenades, machine-guns, mortars, mines, helicopter gunships, rocket launchers and SAM missiles.

Game Author: Chris Roberts.



PRICE: £9.95 (cassette), £11.95 (BBC Micro 5¼" disc), £14.95 (Master Compact 3½" disc).

PRIZES PRIZES PRIZES PRIZES PRIZES PRIZES PRIZES PRIZES PRIZES PRIZES PRIZES

If you complete the game, you can enter our competition. The prizes include a radio controlled 4-wheel-drive off-road racer (worth £200) complete with control system, trophies and £20 in consolation prizes.

Closing date: 31st March, 1987.



SUPERIOR SOFTWARE Limited

ACORNSOFT

Dept. RS3, Regent House,
Skinner Lane,
Leeds LS7 1AX.
Telephone: 0532 459453.

Access VISA

24 HOUR TELEPHONE ANSWERING SERVICE FOR ORDERS


OUR GUARANTEE


- All mail orders are despatched within 24 hours by first-class post.
- Postage and packing is free.
- Faulty cassettes and discs will be replaced immediately.

For the COMMODORE, AMSTRAD, BBC MICRO, ELECTRON

REPTON 3

THE ULTIMATE CHALLENGE






The Screen Editor.



The Character Editor.



Being pursued by a Monster



The Time Bomb is located



The Poisonous Fungus grows insidiously



Collecting a Golden Crown

Are you ready for the ultimate challenge?

Our original Repton game was immediately acclaimed as a refreshingly new concept: a game requiring dexterity to complete its arcade-style elements, and clear logical thinking to solve its strategic puzzles. Repton involves retrieving treasure from cleverly-constructed traps of falling rocks whilst avoiding the fearsome monsters and haunting spirits. "This is an astounding game reaching new heights in BBC arcade adventures," enthused the Micro User magazine.

Last Christmas saw the release of Repton 2, larger and much more challenging than before. Acorn User's Technical Editor Bruce Smith wrote: "Repton 2 is better than anything I've played on the BBC Micro or Electron. Brilliant!"

Now, completely rewritten and improved for the Commodore, Amstrad, BBC Micro and Electron, we proudly present Repton 3. For the first time, a screen-designer is included: try to devise screens that will perplex your friends, then see if you can solve their newly-designed screens. Another innovation is the character-designer which enables you to design your own monsters, rocks, eggs, spirits, diamonds . . . any or all of the game's characters can be redefined as you wish.

Repton 3 is much larger than its predecessors — it has 24 fascinating screens, and players who are skilful enough to complete them all can enter our prize competition described below. All the favourite Repton characters have been retained, together with several new features: a creeping poisonous fungus which grows at an alarming rate; time bombs and time capsules (for puzzles in the 4th dimension); and golden crowns as well-deserved rewards for your endeavours. **Can YOU complete Repton 3?**

PRIZE COMPETITION

If you complete Repton 3, you can enter our competition. Prizes include over £200 in cash, with T-shirts, mugs, badges and pens for runners-up.

COMMODORE 64/128 • AMSTRAD CPC 464/664/6128
BBC MICROS: B, B+, MASTER, MASTER COMPACT • ELECTRON

Commodore Cassette	**£9.95**	BBC Micro Cassette	**£9.95**
Commodore Disc	**£11.95**	BBC Micro Disc	**£11.95**
Amstrad Cassette	**£9.95**	Master Compact Disc	**£14.95**
Amstrad Disc	**£14.95**	Electron Cassette	**£9.95**

SUPERIOR SOFTWARE Limited

ACORNSOFT

Dept. R6, Regent House, Skinner Lane, Leeds LS7 1AX. Telephone: 0532 459453.

The screen pictures above show the BBC Micro version of Repton 3.

Access VISA


24 HOUR TELEPHONE ANSWERING SERVICE FOR ORDERS

OUR GUARANTEE
- All mail orders are despatched within 24 hours by first-class post.
- Postage and packing is free.
- Faulty cassettes and discs will be replaced immediately.

AD, BBC MICRO, ELECTRON

TON 3

CHALLENGE



The Screen Editor.

The Character Editor.

Bomb
ted

The Poisonous Fungus
grows insidiously

Collecting a
Golden Crown

ady for the ultimate challenge?

ed as a refreshingly new concept: a game requiring dexterity to complete its arcade-style gic puzzles. Repton involves retrieving treasure from cleverly-constructed traps of falling ting spirits. "This is an astounding game reaching new heights in BBC arcade adventures,"

much more challenging than before. Acorn User's Technical Editor Bruce Smith wrote: C Micro or Electron. Brilliant!"

nodore, Amstrad, BBC Micro and Electron, we proudly present Repton 3. For the first time, a will perplex your friends, then see if you can solve their newly-designed screens. Another ou to design your own monsters, rocks, eggs, spirits, diamonds . . . any or all of the game's

24 fascinating screens, and players who are skilful enough to complete them all can avourite Repton characters have been retained, together with several new features: a ng rate; time bombs and time capsules (for puzzles in the 4th dimension); and golden

Can YOU complete Repton 3?

petition.
, badges

COMMODORE 64/128 • AMSTRAD CPC 464/664/6128
BBC MICROS: B, B+, MASTER, MASTER COMPACT • ELECTRON

Commodore Cassette	£9.95	BBC Micro Cassette	£9.95
Commodore Disc	£11.95	BBC Micro Disc	£11.95
Amstrad Cassette	£9.95	Master Compact Disc	£14.95
Amstrad Disc	£14.95	Electron Cassette	£9.95

FT

The screen pictures above show the BBC Micro version of Repton 3.

S7 1AX. Telephone: 0532 459453.

Access VISA

24 HOUR TELEPHONE
ANSWERING SERVICE FOR ORDERS

OUR GUARANTEE
- All mail orders are despatched within 24 hours by first-class post.
- Postage and packing is free.
- Faulty cassettes and discs will be replaced immediately.

THE MICRO USER

December 19

Vol. 4 No. 10

A Database Publication

THE MICR USE

Top-selling guide to the



UTILITIES: Fast Flood F
Fast Scroller, Break Rec

REVIEWS: Advanced 17
Beeb Digitiser, ViewSpel