

nag_zero_cont_func_bd_1 (c05sdc)

1. Purpose

nag_zero_cont_func_bd_1 (c05sdc) locates a zero of a continuous function in a given interval by a combination of the methods of linear interpolation, extrapolation and bisection.

2. Specification

```
#include <nag.h>
#include <nagc05.h>

void nag_zero_cont_func_bd_1(double a, double b, double *x,
                             double (*f)(double x, Nag_User *comm), double xtol,
                             double ftol, Nag_User *comm, NagError *fail)
```

3. Description

The routine attempts to obtain an approximation to a simple zero of the function $f(x)$ given an initial interval $[a, b]$ such that $f(a) \times f(b) \leq 0$. The zero is found by a modified version of procedure ‘zeroin’ given by Bus and Dekker (1975). The approximation x to the zero α is determined so that one or both of the following criteria are satisfied:

- (i) $|x - \alpha| < \mathbf{xtol}$,
- (ii) $|f(x)| < \mathbf{ftol}$.

The routine combines the methods of bisection, linear interpolation and linear extrapolation (see Dahlquist and Bjorck (1974)), to find a sequence of sub-intervals of the initial interval such that the final interval $[x, y]$ contains the zero and is small enough to satisfy the tolerance specified by **xtol**. Note that, since the intervals $[x, y]$ are determined only so that they contain a change of sign of f , it is possible that the final interval may contain a discontinuity or a pole of f (violating the requirement that f be continuous). If the sign change is likely to correspond to a pole of f then the routine gives an error return.

4. Parameters

a

Input: the lower bound of the interval, a .

b

Input: the upper bound of the interval, b .
Constraint: **b** $\neq$ **a**.

x

Output: the approximation to the zero.

f

The function **f**, supplied by the user, must evaluate the function f whose zero is to be determined.

The specification of **f** is:

```
double f(double x, Nag_User *comm)

    x
        Input: the point  $x$  at which the function must be evaluated.

    comm
        Input/Output: pointer to a structure of type Nag_User with the following
        member:

        p - Pointer
            Input/Output: the pointer comm->p should be cast to the required type,
            e.g. struct user *s = (struct user *)comm->p, to obtain the original
            object's address with appropriate type. (See the argument comm below.)
```

xtol

Input: the absolute tolerance to which the zero is required (see Section 3).

Constraint: **xtol** > 0.0.

ftol

Input: a value such that if $|f(x)| < \mathbf{ftol}$, x is accepted as the zero. **ftol** may be specified as 0.0 (see Section 6).

comm

Input/Output: pointer to a structure of type Nag_User with the following member:

p - Pointer

Input/Output: the pointer **p**, of type Pointer, allows the user to communicate information to and from the user-defined function **f()**. An object of the required type should be declared by the user, e.g. a structure, and its address assigned to the pointer **p** by means of a cast to Pointer in the calling program, e.g. `comm.p = (Pointer)&s`. The type pointer will be `void *` with a C compiler that defines `void *` and `char *` otherwise.

fail

The NAG error parameter, see the Essential Introduction to the NAG C Library.

5. Error Indications and Warnings

NE_2_REAL_ARG_EQ

On entry, **a** = $\langle value \rangle$ while **b** = $\langle value \rangle$. These parameters must satisfy **a** $\neq$ **b**.

NE_REAL_ARG_LE

On entry, **xtol** must not be less than or equal to 0.0: **xtol** = $\langle value \rangle$.

NE_FUNC_END_VAL

On entry, **f**($\langle value \rangle$) and **f**($\langle value \rangle$) have the same sign, with **f**($\langle value \rangle$) $\neq$ 0.0.

NE_PROBABLE_POLE

Indicates that the function values in the interval **[a,b]** might contain a pole rather than a zero. Reducing **xtol** may help in distinguishing between a pole and a zero.

NE_XTOL_TOO_SMALL

No further improvement in the solution is possible. **xtol** is too small: **xtol** = $\langle value \rangle$.

6. Further Comments

The time taken by the routine depends primarily on the time spent evaluating **f** (see Section 4).

6.1. Accuracy

This depends on the value of **xtol** and **ftol**. If full machine accuracy is required, they may be set very small, resulting in an error exit with error exit of **NE_XTOL_TOO_SMALL**, although this may involve many more iterations than a lesser accuracy. The user is recommended to set **ftol** = 0.0 and to use **xtol** to control the accuracy, unless there is prior knowledge of the size of $f(x)$ for values of x near the zero.

6.2. References

Bus J C P and Dekker T J (1975) Two Efficient Algorithms with Guaranteed Convergence for Finding a Zero of a Function *ACM Trans. Math. Softw.* **1** 330–345.
Dahlquist G and Bjorck A (1974) *Numerical Methods* Prentice-Hall.

7. See Also

None.

8. Example

The example program below calculates the zero of $e^{-x} - x$ within the interval $[0, 1]$ to approximately 5 decimal places.

8.1. Program Text

```

/* nag_zero_cont_func_bd_1(c05sdc) Example Program
 *
 * Copyright 1998 Numerical Algorithms Group.
 *
 * Mark 5, 1998.
 */

#include <nag.h>
#include <stdio.h>
#include <nag_stdlib.h>
#include <math.h>
#include <nagc05.h>

#ifdef NAG_PROTO
static double f(double x, Nag_User *comm);
#else
static double f();
#endif

main()
{
    double a, b;
    double x, ftol, xtol;
    static NagError fail;
    Nag_User comm;

    Vprintf("c05sdc Example Program Results\n");
    a = 0.0;
    b = 1.0;
    xtol = 1e-05;
    ftol = 0.0;
    c05sdc(a, b, &x, f, xtol, ftol, &comm, &fail);
    if (fail.code == NE_NOERROR)
    {
        Vprintf("Zero = %12.5f\n", x);
        exit(EXIT_SUCCESS);
    }
    else
    {
        Vprintf("%s\n", fail.message);
        if (fail.code == NE_XTOL_TOO_SMALL ||
            fail.code == NE_PROBABLE_POLE)
            Vprintf("Final point = %12.5f\n", x);
        exit(EXIT_FAILURE);
    }
}

#ifdef NAG_PROTO
static double f(double x, Nag_User *comm)
#else
    static double f(x, comm)
    double x;
    Nag_User *comm;
#endif
{
    return exp(-x)-x;
}

```

8.2. Program Data

None.

8.3. Program Results

c05sdc Example Program Results
Zero = 0.56714