

NAG C Library Function Document

nag_zhecon (f07muc)

1 Purpose

nag_zhecon (f07muc) estimates the condition number of a complex Hermitian indefinite matrix A , where A has been factorized by nag_zhetrf (f07mrc).

2 Specification

```
void nag_zhecon (Nag_OrderType order, Nag_UploType uplo, Integer n,
    const Complex a[], Integer pda, const Integer ipiv[], double anorm,
    double *rcond, NagError *fail)
```

3 Description

nag_zhecon (f07muc) estimates the condition number (in the 1-norm) of a complex Hermitian indefinite matrix A :

$$\kappa_1(A) = \|A\|_1 \|A^{-1}\|_1.$$

Since A is Hermitian, $\kappa_1(A) = \kappa_\infty(A) = \|A\|_\infty \|A^{-1}\|_\infty$.

Because $\kappa_1(A)$ is infinite if A is singular, the function actually returns an estimate of the **reciprocal** of $\kappa_1(A)$.

The function should be preceded by a call to nag_zhe_norm (f16ucc) to compute $\|A\|_1$ and a call to nag_zhetrf (f07mrc) to compute the Bunch–Kaufman factorization of A . The function then uses Higham's implementation of Hager's method (see Higham (1988)) to estimate $\|A^{-1}\|_1$.

4 References

Higham N J (1988) FORTRAN codes for estimating the one-norm of a real or complex matrix, with applications to condition estimation *ACM Trans. Math. Software* **14** 381–396

5 Parameters

1: **order** – Nag_OrderType *Input*

On entry: the **order** parameter specifies the two-dimensional storage scheme being used, i.e., row-major ordering or column-major ordering. C language defined storage is specified by **order = Nag_RowMajor**. See Section 2.2.1.4 of the Essential Introduction for a more detailed explanation of the use of this parameter.

Constraint: **order = Nag_RowMajor** or **Nag_ColMajor**.

2: **uplo** – Nag_UploType *Input*

On entry: indicates how A has been factorized as follows:

if **uplo = Nag_Upper**, $A = PUDU^H P^T$, where U is upper triangular;

if **uplo = Nag_Lower**, $A = PLDL^H P^T$, where L is lower triangular.

Constraint: **uplo = Nag_Upper** or **Nag_Lower**.

- 3: **n** – Integer *Input*
On entry: n , the order of the matrix A .
Constraint: $n \geq 0$.
- 4: **a**[dim] – const Complex *Input*
Note: the dimension, dim , of the array **a** must be at least $\max(1, pda \times n)$.
On entry: details of the factorization of A , as returned by nag_zhetrf (f07mrc).
- 5: **pda** – Integer *Input*
On entry: the stride separating row or column elements (depending on the value of **order**) of the matrix in the array **a**.
Constraint: $pda \geq \max(1, n)$.
- 6: **ipiv**[dim] – const Integer *Input*
Note: the dimension, dim , of the array **ipiv** must be at least $\max(1, n)$.
On entry: details of the interchanges and the block structure of D , as returned by nag_zhetrf (f07mrc).
- 7: **anorm** – double *Input*
On entry: the 1-norm of the **original** matrix A , which may be computed by calling nag_zhe_norm (f16ucc). **anorm** must be computed either **before** calling nag_zhetrf (f07mrc) or else from a copy of the original matrix A .
Constraint: $anorm \geq 0.0$.
- 8: **rcond** – double * *Output*
On exit: an estimate of the reciprocal of the condition number of A . **rcond** is set to zero if exact singularity is detected or the estimate underflows. If **rcond** is less than *machine precision*, A is singular to working precision.
- 9: **fail** – NagError * *Output*
The NAG error parameter (see the Essential Introduction).

6 Error Indicators and Warnings

NE_INT

On entry, **n** = $\langle value \rangle$.

Constraint: $n \geq 0$.

On entry, **pda** = $\langle value \rangle$.

Constraint: $pda > 0$.

NE_INT_2

On entry, **pda** = $\langle value \rangle$, **n** = $\langle value \rangle$.

Constraint: $pda \geq \max(1, n)$.

NE_REAL

On entry, **anorm** = $\langle value \rangle$.

Constraint: $anorm \geq 0.0$.

NE_ALLOC_FAIL

Memory allocation failed.

NE_BAD_PARAM

On entry, parameter $\langle value \rangle$ had an illegal value.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please consult NAG for assistance.

7 Accuracy

The computed estimate **rcond** is never less than the true value ρ , and in practice is nearly always less than 10ρ , although examples can be constructed where **rcond** is much larger.

8 Further Comments

A call to nag_zhecon (f07muc) involves solving a number of systems of linear equations of the form $Ax = b$; the number is usually 5 and never more than 11. Each solution involves approximately $8n^2$ real floating-point operations but takes considerably longer than a call to nag_zhetrs (f07mnc) with 1 right-hand side, because extra care is taken to avoid overflow when A is approximately singular.

The real analogue of this function is nag_dsycon (f07mgc).

9 Example

To estimate the condition number in the 1-norm (or infinity-norm) of the matrix A , where

$$A = \begin{pmatrix} -1.36 + 0.00i & 1.58 + 0.90i & 2.21 - 0.21i & 3.91 + 1.50i \\ 1.58 - 0.90i & -8.87 + 0.00i & -1.84 - 0.03i & -1.78 + 1.18i \\ 2.21 + 0.21i & -1.84 + 0.03i & -4.63 + 0.00i & 0.11 + 0.11i \\ 3.91 - 1.50i & -1.78 - 1.18i & 0.11 - 0.11i & -1.84 + 0.00i \end{pmatrix}.$$

Here A is Hermitian indefinite and must first be factorized by nag_zhetrf (f07mrc). The true condition number in the 1-norm is 9.10.

9.1 Program Text

```
/* nag_zhecon (f07muc) Example Program.
 *
 * Copyright 2001 Numerical Algorithms Group.
 *
 * Mark 7, 2001.
 */

#include <stdio.h>
#include <nag.h>
#include <nag_stdlib.h>
#include <naga02.h>
#include <nagf07.h>
#include <nagf16.h>
#include <nagx02.h>

int main(void)
{
    /* Scalars */
    double anorm, rcond;
    Integer i, j, n, pda;
    Integer exit_status=0;
    Nag_UploType uplo_enum;
    NagError fail;
    Nag_OrderType order;
```

```

/* Arrays */
Integer *ipiv=0;
char    uplo[2];
Complex *a=0;

#ifdef NAG_COLUMN_MAJOR
#define A(I,J) a[(J-1)*pda + I - 1]
    order = Nag_ColMajor;
#else
#define A(I,J) a[(I-1)*pda + J - 1]
    order = Nag_RowMajor;
#endif

    INIT_FAIL(fail);
    Vprintf("f07muc Example Program Results\n\n");

    /* Skip heading in data file */
    Vscanf("%*[^\\n] ");
    Vscanf("%ld%*[^\\n] ", &n);
#ifdef NAG_COLUMN_MAJOR
    pda = n;
#else
    pda = n;
#endif

    /* Allocate memory */
    if ( !(ipiv = NAG_ALLOC(n, Integer)) ||
        !(a = NAG_ALLOC(n * n, Complex)) )
    {
        Vprintf("Allocation failure\n");
        exit_status = -1;
        goto END;
    }

    /* Read A from data file */
    Vscanf(" ' %ls '%*[^\\n] ", uplo);
    if (*(unsigned char *)uplo == 'L')
        uplo_enum = Nag_Lower;
    else if (*(unsigned char *)uplo == 'U')
        uplo_enum = Nag_Upper;
    else
    {
        Vprintf("Unrecognised character for Nag_UploType type\n");
        exit_status = -1;
        goto END;
    }

    if (uplo_enum == Nag_Upper)
    {
        for (i = 1; i <= n; ++i)
        {
            for (j = i; j <= n; ++j)
                Vscanf(" ( %lf , %lf )", &A(i,j).re, &A(i,j).im);
            Vscanf("%*[^\\n] ");
        }
    }
    else
    {
        for (i = 1; i <= n; ++i)
        {
            for (j = 1; j <= i; ++j)
                Vscanf(" ( %lf , %lf )", &A(i,j).re, &A(i,j).im);
            Vscanf("%*[^\\n] ");
        }
    }

    /* Compute norm of A */
    f16ucc(order, Nag_OneNorm, uplo_enum, n, a, pda, &anorm, &fail);
    if (fail.code != NE_NOERROR)
    {
        Vprintf("Error from f16ucc.\\n%s\\n", fail.message);
    }

```

```

        exit_status = 1;
        goto END;
    }
/* Factorize A */
f07mrc(order, uplo_enum, n, a, pda, ipiv, &fail);
if (fail.code != NE_NOERROR)
{
    Vprintf("Error from f07mrc.\n%s\n", fail.message);
    exit_status = 1;
    goto END;
}
/* Estimate condition number */
f07muc(order, uplo_enum, n, a, pda, ipiv, anorm, &rcond,
        &fail);
if (fail.code != NE_NOERROR)
{
    Vprintf("Error from f07muc.\n%s\n", fail.message);
    exit_status = 1;
    goto END;
}
if (rcond >= X02AJC)
    Vprintf("Estimate of condition number =%10.2e\n", 1.0/rcond);
else
    Vprintf("A is singular to working precision\n");
END:
    if (ipiv) NAG_FREE(ipiv);
    if (a) NAG_FREE(a);
    return exit_status;
}

```

9.2 Program Data

f07muc Example Program Data

```

4                                     :Value of N
'L'                                 :Value of UPLO
(-1.36, 0.00)
( 1.58,-0.90) (-8.87, 0.00)
( 2.21, 0.21) (-1.84, 0.03) (-4.63, 0.00)
( 3.91,-1.50) (-1.78,-1.18) ( 0.11,-0.11) (-1.84, 0.00) :End of matrix A

```

9.3 Program Results

f07muc Example Program Results

Estimate of condition number = 6.68e+00
