

NAG C Library Function Document

nag_ztrcon (f07tuc)

1 Purpose

nag_ztrcon (f07tuc) estimates the condition number of a complex triangular matrix.

2 Specification

```
void nag_ztrcon (Nag_OrderType order, Nag_NormType norm, Nag_UploType uplo,
                 Nag_DiagType diag, Integer n, const Complex a[], Integer pda, double *rcond,
                 NagError *fail)
```

3 Description

nag_ztrcon (f07tuc) estimates the condition number of a complex triangular matrix A , in either the 1-norm or the infinity-norm:

$$\kappa_1(A) = \|A\|_1 \|A^{-1}\|_1 \quad \text{or} \quad \kappa_\infty(A) = \|A\|_\infty \|A^{-1}\|_\infty.$$

Note that $\kappa_\infty(A) = \kappa_1(A^T)$.

Because the condition number is infinite if A is singular, the function actually returns an estimate of the **reciprocal** of the condition number.

The function computes $\|A\|_1$ or $\|A\|_\infty$ exactly, and uses Higham's implementation of Hager's method (see Higham (1988)) to estimate $\|A^{-1}\|_1$ or $\|A^{-1}\|_\infty$.

4 References

Higham N J (1988) FORTRAN codes for estimating the one-norm of a real or complex matrix, with applications to condition estimation *ACM Trans. Math. Software* **14** 381–396

5 Parameters

- 1: **order** – Nag_OrderType *Input*
On entry: the **order** parameter specifies the two-dimensional storage scheme being used, i.e., row-major ordering or column-major ordering. C language defined storage is specified by **order = Nag_RowMajor**. See Section 2.2.1.4 of the Essential Introduction for a more detailed explanation of the use of this parameter.
Constraint: **order = Nag_RowMajor** or **Nag_ColMajor**.
- 2: **norm** – Nag_NormType *Input*
On entry: indicates whether $\kappa_1(A)$ or $\kappa_\infty(A)$ is estimated as follows:
 - if **norm = Nag_OneNorm**, $\kappa_1(A)$ is estimated;
 - if **norm = Nag_InfNorm**, $\kappa_\infty(A)$ is estimated.*Constraint:* **norm = Nag_OneNorm** or **Nag_InfNorm**.
- 3: **uplo** – Nag_UploType *Input*
On entry: indicates whether A is upper or lower triangular as follows:

if **uplo** = **Nag_Upper**, A is upper triangular;

if **uplo** = **Nag_Lower**, A is lower triangular.

Constraint: **uplo** = **Nag_Upper** or **Nag_Lower**.

4: **diag** – Nag_DiagType *Input*

On entry: indicates whether A is a non-unit or unit triangular matrix as follows:

if **diag** = **Nag_NonUnitDiag**, A is a non-unit triangular matrix;

if **diag** = **Nag_UnitDiag**, A is a unit triangular matrix; the diagonal elements are not referenced and are assumed to be 1.

Constraint: **diag** = **Nag_NonUnitDiag** or **Nag_UnitDiag**.

5: **n** – Integer *Input*

On entry: n , the order of the matrix A .

Constraint: $n \geq 0$.

6: **a**[*dim*] – const Complex *Input*

Note: the dimension, *dim*, of the array **a** must be at least $\max(1, \mathbf{pda} \times \mathbf{n})$.

On entry: the n by n triangular matrix A . If **uplo** = **Nag_Upper**, A is upper triangular and the elements of the array below the diagonal are not referenced; if **uplo** = **Nag_Lower**, A is lower triangular and the elements of the array above the diagonal are not referenced. If **diag** = **Nag_UnitDiag**, the diagonal elements of A are not referenced, but are assumed to be 1.

7: **pda** – Integer *Input*

On entry: the stride separating row or column elements (depending on the value of **order**) of the matrix A in the array **a**.

Constraint: $\mathbf{pda} \geq \max(1, \mathbf{n})$.

8: **rcond** – double * *Output*

On exit: an estimate of the reciprocal of the condition number of A . **rcond** is set to zero if exact singularity is detected or the estimate underflows. If **rcond** is less than *machine precision*, A is singular to working precision.

9: **fail** – NagError * *Output*

The NAG error parameter (see the Essential Introduction).

6 Error Indicators and Warnings

NE_INT

On entry, **n** = *<value>*.

Constraint: $\mathbf{n} \geq 0$.

On entry, **pda** = *<value>*.

Constraint: $\mathbf{pda} > 0$.

NE_INT_2

On entry, **pda** = *<value>*, **n** = *<value>*.

Constraint: $\mathbf{pda} \geq \max(1, \mathbf{n})$.

NE_ALLOC_FAIL

Memory allocation failed.

NE_BAD_PARAM

On entry, parameter $\langle value \rangle$ had an illegal value.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please consult NAG for assistance.

7 Accuracy

The computed estimate **rcond** is never less than the true value ρ , and in practice is nearly always less than 10ρ , although examples can be constructed where **rcond** is much larger.

8 Further Comments

A call to nag_ztrcon (f07tuc) involves solving a number of systems of linear equations of the form $Ax = b$ or $A^H x = b$; the number is usually 5 and never more than 11. Each solution involves approximately $4n^2$ real floating-point operations but takes considerably longer than a call to nag_ztrtrs (f07tsc) with 1 right-hand side, because extra care is taken to avoid overflow when A is approximately singular.

The real analogue of this function is nag_dtrcon (f07tgc).

9 Example

To estimate the condition number in the 1-norm of the matrix A , where

$$A = \begin{pmatrix} 4.78 + 4.56i & 0.00 + 0.00i & 0.00 + 0.00i & 0.00 + 0.00i \\ 2.00 - 0.30i & -4.11 + 1.25i & 0.00 + 0.00i & 0.00 + 0.00i \\ 2.89 - 1.34i & 2.36 - 4.25i & 4.15 + 0.80i & 0.00 + 0.00i \\ -1.89 + 1.15i & 0.04 - 3.69i & -0.02 + 0.46i & 0.33 - 0.26i \end{pmatrix}.$$

The true condition number in the 1-norm is 70.27.

9.1 Program Text

```
/* nag_ztrcon (f07tuc) Example Program.
 *
 * Copyright 2001 Numerical Algorithms Group.
 *
 * Mark 7, 2001.
 */

#include <stdio.h>
#include <nag.h>
#include <nag_stdlib.h>
#include <nagf07.h>
#include <nagx02.h>

int main(void)
{
    /* Scalars */
    double rcond;
    Integer i, j, n, pda;
    Integer exit_status=0;
    Nag_UploType uplo_enum;

    NagError fail;
    Nag_OrderType order;
    /* Arrays */
    char uplo[2];
    Complex *a=0;

#ifdef NAG_COLUMN_MAJOR
#define A(I,J) a[(J-1)*pda + I - 1]
```

```

    order = Nag_ColMajor;
#else
#define A(I,J) a[(I-1)*pda + J - 1]
    order = Nag_RowMajor;
#endif

    INIT_FAIL(fail);
    Vprintf("f07tuc Example Program Results\n");

    /* Skip heading in data file */
    Vscanf("%*[\n] ");
    Vscanf("%ld%*[\n] ", &n);
#ifdef NAG_COLUMN_MAJOR
    pda = n;
#else
    pda = n;
#endif

    /* Allocate memory */
    if ( !(a = NAG_ALLOC(n * n, Complex)) )
    {
        Vprintf("Allocation failure\n");
        exit_status = -1;
        goto END;
    }

    /* Read A from data file */
    Vscanf(" ' %ls '%*[\n] ", uplo);
    if (*(unsigned char *)uplo == 'L')
        uplo_enum = Nag_Lower;
    else if (*(unsigned char *)uplo == 'U')
        uplo_enum = Nag_Upper;
    else
    {
        Vprintf("Unrecognised character for Nag_UploType type\n");
        exit_status = -1;
        goto END;
    }
    if (uplo_enum == Nag_Upper)
    {
        for (i = 1; i <= n; ++i)
        {
            for (j = i; j <= n; ++j)
                Vscanf(" ( %lf , %lf )", &A(i,j).re, &A(i,j).im);
        }
        Vscanf("%*[\n] ");
    }
    else
    {
        for (i = 1; i <= n; ++i)
        {
            for (j = 1; j <= i; ++j)
                Vscanf(" ( %lf , %lf )", &A(i,j).re, &A(i,j).im);
        }
        Vscanf("%*[\n] ");
    }

    /* Estimate condition number */
    f07tuc(order, Nag_OneNorm, uplo_enum, Nag_NonUnitDiag, n,
        a, pda, &rcond, &fail);
    if (fail.code != NE_NOERROR)
    {
        Vprintf("Error from f07tuc.\n%s\n", fail.message);
        exit_status = 1;
        goto END;
    }
    Vprintf("\n");
    if (rcond >= X02AJC)
    {
        Vprintf("Estimate of condition number =%10.2e\n\n",
            1.0/rcond);
    }

```

```

    }
    else
        Vprintf("A is singular to working precision\n");
    END:
    if (a) NAG_FREE(a);

    return exit_status;
}

```

9.2 Program Data

f07tuc Example Program Data

```

4                                     :Value of N
'L'                                 :Value of UPLO
( 4.78, 4.56)
( 2.00,-0.30) (-4.11, 1.25)
( 2.89,-1.34) ( 2.36,-4.25) ( 4.15, 0.80)
(-1.89, 1.15) ( 0.04,-3.69) (-0.02, 0.46) ( 0.33,-0.26) :End of matrix A

```

9.3 Program Results

f07tuc Example Program Results

Estimate of condition number = 3.74e+01
