COMPUTER DESIGN HE MAGAZINE OF DIGITAL ELECTRONICS DECEMBER 1977

PATTERN RECOGNITION: BASIC CONCEPTS AND IMPLEMENTATIONS

MULTIPLE-WORD BUFFERING FOR DISC CONTROLLERS WITH BIPOLAR FIFO MEMORY

MICROPROCESSOR-BASED INTERFACE CONVERTS VIDEO SIGNALS FOR OBJECT TRACKING

At last...a Logic State Analyzer that practically asks you what to analyze and how to display.

A few simple pushbuttons, an interactive display, sophisticated microprocessor-based intelligence . . . now they're all combined in HP's powerful new 1610A Logic State Analyzer. The result is a simplified "menu" approach to instrument setup, ability to choose highly complex trace specifications with a few simple keyboard entries, program-flow displays that are easier than ever to interpret, and an instrument that virtually self tests.

In addition, now you can trace complex branches and nested loops; count the number of states or the time

interval between all words to debug or optimize programming; and drive HP Model 9866A or 9866B printers for hard-copy output of test results and set-up specifications.

The new 1610A, priced at \$9500*, provides fast setup and easy trouble-shooting in nearly any logic system having data rates to 10 MHz. Your local HP field engineer has the complete story. Give him a call today.

* Domestic U.S.A. price only.




The Class of '77

It's the Kennedy 9000 Series Digital Tape Transports—
the culmination of years of experience in defining,
designing and refining a product line. All Kennedy
Tape Transports possess features found in no other
line — features such as front accessible off-line
test panel, linear non-contact (Mag Pot) position
sensor, interchangeable electronics and capacitive
linear-loop sensing on our vacuum column machines.
Performance is equally impressive, with data
transfer rates to 200KHz and tape speeds to 125 ips.
But features and performance are only part of the story.
Kennedy products have always been designed and
built to be the finest in the field.
We call it class. So will you.

KENNEDY CO.

540 W. WOODBURY RD., ALTADENA, CALIF. 91001 (213) 798-0953

CIRCLE 2 ON INQUIRY CARD



KENNEDY- QUALITY- COUNT ON IT



Tally reliability. As good as gold.

Tally reliability is unmatched in the printer industry. The value to you is a 100% duty cycle, 200 line per minute printer that costs far less to own. Less than any other printer around.

You can run the T-2000 as long and as hard as you want without the frustration of downtime and costly repairs. Plus, preventive maintenance is unnecessary. Sliding bearings, pivots and lubrication points are eliminated. There are no electronic timing or hammer flight time adjustments. In short, there's nothing to adjust.

The reason behind this unparalleled reliability is the patented Tally print comb mechanism. It uses a unique flexure technology that's impervious to wear and designed for unlimited life. While other printers like to talk about calculated MTBF, Tally points to field proven MTBF. Most of the Tally printers that have been in the field, including those in operation for over four years, have never required adjustment or repair to the print mechanism. In fact, many have experienced no malfunction at all! No one else can safely make that statement. And Tally backs every T-2000 with a full year print mechanism warranty.

The gold printer above is Tally's commemorative unit marking 10,000 machines delivered. The noteworthy statistic is that 99 per cent plus have never had a mechanism failure.

Find out all the facts on this proven performer and call your nearest Tally sales office, or write or call Tally Corporation, 8301 S. 180th Street, Kent, WA 98031. Phone (206) 251-5524.

TALLY

OEM Sales Offices: Los Angeles (213) 378-0805 • San Antonio (512) 733-8153 • New York (516) 694-8444 Boston (617) 272-8070 • Chicago (312) 325-9788 • Miami (305) 665-5751 Washington, D.C. (703) 471-1145 • Seattle (206) 251-6730 • Business Systems (415) 254-8350

THE MAGAZINE OF DIGITAL ELECTRONICS

COMPUTER DECEMBER 1977 • VOLUME 16 • NUMBER 12 DESIGN

FEATURES

57 PATTERN RECOGNITION: BASIC CONCEPTS AND IMPLEMENTATION by Dennis Feucht

Based on analog-to-digital data acquisition, analysis, and identification, the computerized pattern recognition task involves development and refinement of the software algorithms required to classify complex signals

73 MULTIPLE-WORD BUFFERING FOR DISC CONTROLLERS WITH BIPOLAR FIFO MEMORY

by Krishna Rallapalli

Asynchronous serial-to-parallel and parallel-to-serial data entry and extraction, and large word capacity are combined into a single bipolar LSI device that functions effectively and economically as a local FIFO buffer memory for disc controllers

81 MICROPROCESSOR-BASED INTERFACE CONVERTS VIDEO SIGNALS FOR OBJECT TRACKING

by Kenneth S. Lubinski, Kenneth L. Dickson, and John Cairns, Jr

Random movements of an object over a prescribed area are detected, processed, and recorded using a video monitoring system design. TV camera signals are converted by a video interface into digital X and Y coordinates for data sampling, manipulation, and storage by an 8080-based microcomputer

90 VMOS PERIPHERAL DRIVERS SOLVE HIGH POWER LOAD INTERFACE PROBLEMS

by Lee Shaeffer

Compatible with CMOS, TTL, and ECL, VMOS peripheral drivers offer operating capabilities not common to conventional semiconductor technologies for a wide spectrum of load interface applications

150 COMPUTER GRAPHIC FAMILY OFFERS MULTIFUNCTION CAPABILITY

Printers, plotters, and printer/plotters—operable in either fixed or mobile installations—provide high resolution, electrostatic hardcopy in alphanumeric and/or graphic formats

177 1977 COMPUTER DESIGN INDEX

An annual listing of articles, columns, product features, and special items

DEPARTMENTS

市

- 6 CALENDAR
- 11 COMMUNICATION CHANNEL
- 27 DIGITAL TECHNOLOGY REVIEW
- 48 DIGITAL CONTROL AND AUTOMATION SYSTEMS
- 106 MICRO PROCESSOR/ COMPUTER DATA STACK
- 130 AROUND THE IC LOOP
- 152 PRODUCTS
- 175 LITERATURE
- 181 GUIDE TO PRODUCT INFORMATION
- 184 ADVERTISERS' INDEX

Reader Service Cards pages 185-188



OVER 55,000

Publisher's statement of qualified circulation—67,000

Copyright 1977, Computer Design Publishing Corp.

MICRO or MINI . . . We've Got the Best A/D "Front-End" Module for your computer or system.

Guaranteed 12-bit accuracy and linearity, ultra-stable, 16-256 channels, throughputs to 100 kHz. ... and the price is right!

This is the "first family" of multichannel modular front ends enthusiastically imitated, but never equalled.

Sure, they're all superficially similar. 16 channels of MUX, buffer, sample-hold, 12-bit A/D converter . . . but after that,

Our microprocessor design (MP6812) gives you relative and absolute accuracies better than 0.025%, at a full 30 kHz throughput (faster when shortcycled). And it makes those accuracies meaningful with T.C.'s of 3 to 15 ppm/°C. Tri-state output buffers for ease of interfacing. Ultra-flexible: pinselectable output codes (3), output formats (3), input ranges (4). Cool-running (<1.5 Watts, <8 °C rise), EMI/RFI-shielded metal case, lowprofile, only 3"x 4.6" x 0.375". Tack on one or more MUX expanders for up to 64 channels. Price? Are you ready? The lowest in the field!

Our minicomputer design (MP6912) is even more impressive. 12-bit throughput, 100 kHz (faster if short-cycled), even lower T.C.'s, 3-Sigma noise <0.01% FSR. Even greater flexibility: four output codes, eight input ranges,

expansion to 256 channels. Pinselectable input configurations; singleended pseudo-differential or true differential. And now there's an especially low-priced 75 kHz version that gives you premium performance for less than you'd pay for a pale imitation.

Is it any wonder that Analogic is the leading supplier of A/D and D/A interface hardware to the microcomputer/microprocessor community?

Get All The Facts.



STAFF

Publisher and Editorial Director Robert Brotherston

Associate Publisher Anthony Saltalamacchia

John A. Camuso

Managing Editor Sydney F. Shapiro

Technical Editor George V. Kotelly

Associate Editor Peggy Killmon

Assistant Editor Joanne O'Donnell

Editorial Assistant Renée C. Gregorio

Editorial Advisory Board
Brian W. Pollard
Ralph J. Preiss
Rex Rice

Contributing Editors
Richard Ahrons
A. S. Buchman
H. S. Miller
Harold H. Seward

Production Manager Judy Lober

Advertising Production Linda M. Wright

Art Director James Flora

Technical Illustrator Charles Manchester

Circulation Manager Alma Brotherston

Marketing Manager Geoffrey Knight, Jr.

Assistant Marketing Manager Megan Kern

Research Associate Sidney Davis

Business Manager David C. Ciommo

Vice President-Sales Lindsay H. Caldwell

Editorial & Executive Offices 11 Goldsmith St Littleton, MA 01460 Tel. (617) 486-8944 (617) 646-7872

Editorial manuscripts should be addressed to Editor, Computer Design, 11 Goldsmith St., Littleton, MA 01460. For details on the preparation and submission of manuscripts, request a copy of the "Computer Design Author's Cuido."

Computer Design is published monthly. Copyright 1977 by Computer Design Publishing Corporation. Controlled circulation postage paid at Pontiac, III. No material may be reprinted without permission. Postmaster: CHANGE OF ADDRESS—FORM 3579 to be sent to Computer Design, Circulation Dept., P.O. Box A, Winchester, MA 01890. Subscription rate is \$24.00 in U.S.A., Canada and Mexico, and \$40.00 elsewhere. Microfilm copies of Computer Design are available and may be purchased from University Microfilms, a Xerox Company, 300 N. Zeeb Rd, Ann Arbor, MI 48106.

Tel. (617) 246-0300 / TWX (710) 348-0425 / Telex 94-9307

How FORTHtm software tools have rescued mini and micro project developers reads like a fairy tale.

short time ago, a gloomy Monday found a New York manufacturer desperate. Microprocessor software problems had deep-sixed the delivery date of an artificial-kidney tester.

Four man-months of assembly language programming...and still the device wouldn't work.

Came Tuesday, design specs were rushed to a group of software problem-solvers, FORTH, Inc. Three nights a crack FORTH programmer concentrated on saving the day...flying cross-country to project headquarters on Friday.

By Sunday night, the machine was totally operational!

Five FORTH days, with one man applying microFORTH language and programming techniques, and the tough software task was fully written, debugged and cross-compiled.

For a complicated μP device with: one master panel with thumbwheels, 3-way switch, pushbuttons. Plus dual control panels with more thumbwheels, switches...and lights. Plus two printers; A/D converter; and hydraulic valves. All up in less than a week.

+

elieving in FORTH has solved many a minicomputer project too.


As when the Navy was caught between the devil and the deep blue sea. mini-hardware already configured to develop a missile guidance system required an image processing capability.

The hang-up? High level languages demanded too much memory; but assembler code, too much development time.

Fortunately, project management was wise to FORTH's track record in image processing. *And* the availability of off-the-shelf miniFORTH software that could accommodate just about any-make mini...on order, on hand, or on line.

National secrets can't be spilled, but what can be told is the performance of miniFORTH tools in the hands of *typical* users: software development time, 3-10 times less. Memory requirements reduced up to 50% over assembly code, with full machine speed capability. All simultaneously!

Easy to see why the Navy selected FORTH as the sole source for this software contract.



FORTH is fact...not fable. There *is* a popular myth: it says you can optimize today's advanced mini/micro hardware — with software tools as old as some programmers. But wishing won't make it so; you need rich new programming techniques.

That's FORTH. Combining the operating system with a multilevel language structure, you instruct machines on your own terms.

Whether you're talking new product development or on-going applications. All the way from process control to interactive graphics to data base management systems, FORTH helps you repeat these success stories. Either through our custom programming services. Or take FORTH tools off-the-shelf for in-house use.

For minicomputer projects, miniFORTH is ready to go for all popular minis.

microFORTH runs on disk-based microprocessor development systems, package-priced at \$2500, plus options.

So flexible, so powerful are FORTH capabilities, our case histories strain credulity. We admit it. And we admit, to learn this new shortcut, you'll leave the old-shoe comfort of Basic and Fortran behind.

It's worth it. In cost-effectiveness. In dramatic cuts in development time. In much lower computing-equipment investments. Just what it takes to make heroes in real life.



oral. You don't have to believe in fairy tales, to know that the limitations of Basic, PL/M, and Fortran are often pretty grim.

Calling FORTH in late can save your neck. But calling FORTH *first* can make any software project easier to swallow.

Phone (213) 372-8493, for microFORTH, miniFORTH or programming assistance. Or write: FORTH Inc., 815 Manhattan Avenue, Manhattan Beach, CA 90266. We can help.



CALENDAR

CONFERENCES


- JAN 19-21—U.S./Southeast Asia Telecommunications Conf, Singapore. INFORMA-TION: John Sodolski, Electronic Industries Assoc, Communications Div, Washington, DC 20006. Tel: (202) 457-4934
- JAN 19 and FEB 2—Invitational Computer Conf, South Coast Plaza Hotel, Orange County, Calif; and Pier 66 Hotel & Marina, Ft Lauderdale, Fla. INFORMATION: B. J. Johnson & Associates, 2503 Eastbluff Dr., Suite 203, Newport Beach, CA 92660. Tel: (714) 644-6037
- JAN 24-26—Reliability and Maintainability, Biltmore, Los Angeles, Calif. INFORMA-TION: D. F. Barber, PO Box 1401, Branch PO, Griffiss AFB, NY 13441
- JAN and FEB—Trade Ctr Exhibitions: Mini/Micro Computers; and Computers and Related Equipment, London, England and Tokyo, Japan. INFORMATION: Roy Mitchell or Peter Ryan, U.S. Dept of Commerce, Domestic and Internat'l Business Administration, Washington, DC 20230. Tel: (202) 377-2838 or (202) 377-2849
- FEB 7-10—World Fair for Tech Exchange, Georgia World Congress Ctr, Atlanta, Ga. INFORMATION: Dr Dvorkovitz & Associates, PO Box 1748, Ormond Beach, FL 32074. Tel: (904) 677-7033
- FEB 13-15—WINCON '78 (Winter Conv on Aerospace Electronic Systems), Sheraton Universal Hotel, North Hollywood, Calif. INFORMATION: WINCON '78, 1 Space Pk, Bldg E2/9080, Redondo Beach, CA 90278. Tel: (213) 536-3680
- FEB 15-17—IEEE Internat'I Solid-State Circuits Conf (ISSCC), San Francisco Hilton, San Francisco, Calif. INFORMATION: Lewis Winner, 152 W 42d St, New York, NY 10036. Tel: (212) 279-3125
- FEB 21-23—ACM Computer Science Conf, Detroit Plaza Hotel, Renaissance Ctr, Detroit, Mich. INFORMATION: Seymour J. Wolfson, Wayne State U, Detroit, MI 48202
- FEB 21-23—Datacom '78, Sheraton Park Hotel, Washington, DC. INFORMATION: Ed Bride, The Conference Co, 60 Austin St, Newtonville, MA 02160. Tel: (617) 964-4550
- FEB 28-MAR 2—COMPCON Spring '78, San Francisco, Calif. INFORMATION: COMPCON Spring '78, PO BOX 639, Silver Spring, MD 20901. Tel: (301) 439-7007
- MAR 1-3—Control of Power Systems Conf and Exposition, Lincoln Plaza Hotel, Oklahoma City, Okla. INFORMATION: Dr M. E. Council, OG & E Prof, School of Electrical Engineering and Computing Science, U of Oklahoma, Norman, OK 73019. Tel: (405) 325-4721

- MAR 5-8—TAPPI Internat'I Pulp and Paper Industry Exhibit, Conrad Hilton Hotel, Chicago, III. INFORMATION: Wayne Gross, c/o TAPPI, 1 Dunwoody Pk, Atlanta, GA 30341. Tel: (404) 394-6130
- MAR 14-17—Printemps Informatique, U.S. Trade Ctr, Paris, France. INFORMATION: Helen Burroughs, U.S. Dept of Commerce, Office of Internat'l Mktg, France/Benelux, Rm 6318, Washington, DC 20230. Tel: (202) 377-4941
- MAR 20-22—Industrial Electronics Control Instrumentation (IECI) Conf, Sheraton Hotel, Philadelphia, Pa. INFORMATION: Dr S. J. Vahaviolos, Engineering Research Ctr, Western Electric, PO Box 900, Princeton, NJ 08540
- MAR 21-23—IECI '78 (Industrial Applications of Microprocessors), Sheraton, Philadelphia, Pa. INFORMATION: W. W. Koepsel, Dept of EE, Seaton Hall, Kansas State U, Manhattan, KS 66506
- MAR 22-24—Internat'l Topical Conf on the Physics of SiO₂ and Its Interfaces, IBM Thomas J. Watson Research Ctr, Yorktown Heights, NY. INFORMATION: Dr Sokrates T. Pantelides, Conf Chm, IBM Thomas J. Watson Research Ctr, PO Box 218, Yorktown Heights, NY 10598. Tel: (914) 945-1207 or 945-3000
- MAR 27-31—Automated Business and Banking Equipment Exhibition, U.S. Internat'l Mktg Ctr, Singapore. INFORMATION: George I. Middleton, U.S. Dept of Commerce, DIBA/BIC/OIM, Rm 4126, Washington, DC 20230. Tel: (202) 377-2471
- APR 17-20—Design Engineering Show, Mc-Cormick PI, Chicago, III. INFORMATION: Clapp & Poliak, Inc, 245 Park Ave, New York, NY 10017. Tel: (212) 661-8410
- APR 18-20—The Society for Information Display Internat'l Sym, Hyatt Regency Hotel, San Francisco, Calif. INFORMATION: Lewis Winner, 152 W 42d St, New York, NY 10036. Tel: (212) 279-3125
- APR 24-26—28th Electronic Components Conf, Disneyland Hotel, Anaheim, Calif. INFORMATION: J. A. Bruorton, Mktg Administration Dept, Union Carbide Corp, PO Box 5928, Greenville, SC 29606. Tel: (803) 963-6348
- APR 25-26—26th Annual National Relay Conf, Oklahoma State U, Stillwater, Okla. INFORMATION: School of Electrical Engineering, Engineering Ext 301 EN, Oklahoma State U, Stillwater, OK 74074. Tel: (405) 624-5146
- APR 28-30—PERCOMP '78, Long Beach Conv Ctr, Long Beach, Calif. INFORMA-TION: Royal Exposition Mgmt Corp, 1833 E 17th St, Suite 108, Santa Ana, CA 92701. Tel: (714) 973-0880

- MAY 9-12—Internat'l Magnetics (INTER-MAG) Conf, Palazzo Dei Congressi, Florence, Italy. INFORMATION: E. Della Torre, Dept of Electrical Engineering, McMaster U, Hamilton, Ontario L8S 4L7, Canada
- JUNE 12-15 MIMI '78 (4th Internat'l Sym and Exhibition of Mini and Microcomputers and their Applications), Zurich, Switzerland. INFORMATION: Secretariat MIMI '78, Interconvention, c/o Swissair Postfach, 8058 Zurich, Switzerland
- JUNE 12-16—7th Triennial IFAC World Congress, Helsinki, Finland. INFORMATION: IFAC 78 Secretariat, POB 192, 00101 Helsinki 10, Finland

SHORT COURSES

- JAN 9-13—Microprocessors; JAN 16-20—Structured Programming and Software Engineering; JAN 18-20—Programming Techniques for Computer Graphics; JAN 23-25—Configuration Management of Software Programs; and JAN 23-27—Digital Filters for Control Systems, and Microprocessors and Microcomputers: Theory and Applications, George Washington U, Washington, DC. INFORMATION: Martha Augustin, Continuing Engineering Education, George Washington U, Washington, DC 20052. Tel: (202) 676-6106
- JAN 11-13 and JAN 23-25—Patent Law for Engineers and Scientists, The Rodeway Inn, San Diego, Calif; and The Biscayne College Ctr for Continuing Education, Miami, Fla. INFORMATION: Martha Augustin, Continuing Engineering Education, George Washington U, Washington, DC 20052. Tel: (202) 676-6106
- JAN 16-20 and JAN 23-27—Microprocessor and Microcomputer Short Courses, Los Angeles, Calif; and Houston, Tex. INFORMA-TION: Integrated Computer Systems, Inc, 3304 Pico Blvd, 2nd Floor, Santa Monica, CA 90405. Tel: (213) 559-9265
- JAN 19-20—Program Testing Tutorials, San Francisco, Calif. INFORMATION: Dr E. F. Miller, Jr, Software Research Associates, PO Box 2432, San Francisco, CA 94126. Tel: (415) 921-1155
- FEB 6-10—Data Base Systems: Design, Implementation, Application, and Trends, UCLA, Los Angeles, Calif. INFORMATION: Continuing Education in Engineering and Mathematics, Short Courses, 6266 Boelter Hall, UCLA Extension, Los Angeles, CA 90024. Tel: (213) 825-3344 or 825-1295



IF THE TELETYPE MODEL 40 SYSTEM EVER MALFUNCTIONS, IT'S DESIGNED TO TELL YOU WHAT'S WRONG.

Even though we probably go to more trouble to insure uninterrupted reliability than anyone else, we're still realistic enough to admit that sometime something's going to go wrong.

So instead of burying our heads in the sand and pretending it won't, we've concentrated our efforts on what can be done to make downtime as short and painless as possible.

For starters, we gave the model 40 product line its own diagnostic capability. To tell you quickly what's wrong. Then, to make it easy to fix, we used a modular design concept. The result is an average mean-time-to-repair of only 3/4 hour.

We also made sure that when something does go wrong, you'll never be alone. We've got a nationwide service network standing behind every product with the Teletype name on it. We offer on-call repair service, maintenance contracts, and even an exchange repair service on components and parts.


The way we look at it, building something the best way humanly possible is only half our job. The other half is being ready for the unexpected.


For more information about the Teletype model 40 product line, write: Teletype, 5555 Touhy Ave., Skokie, IL 60076. Or call: 312/982-2000.



Teletype is a trademark and service mark registered in the United States Patent and Trademark Office.

CIRCLE 6 ON INQUIRY CARD











BIPOLAR PROM PROGRESS:

Last year, we invented 8K. This year, we invented 16K. Next year, they'll both be industry standards.

Signetics' acknowledged technological leadership in Bipolar PROMs just took another lengthy stride forward.

Just over a year ago, we announced the world's first fieldprogrammable Bipolar PROM with 8K memory capacity. It was news then, and it's an industry standard now.

Here's even more important news for users of high-density memories-the 16K PROM is a reality. It's the 82S190/191from Signetics.

16K Bipolar PROM More than a Larger Memory. The 16K PROM has a lot more going for it than just raw storage. Like speed, for example—although it has twice the density of its 8K cousin, it's almost as fast, with a maximum address access time of only 80 nsec. Current drain, though, is unchanged—at 175 mA. That's a big advantage for you—half the power per bit, twice the storage capacity.

Like most of its smaller cousins, the 16K PROM is available with two output options: The 82S190 is Open Collector, the 82S191 is Tri-State. That means you can choose the output you need for optimizing word expansion in bused organizations.

> The 82S190/191 is available now in limited sample quantity. Full production due in January 1978.

Both versions are field-programmable, so you can produce custom patterns by using prescribed fusing procedures. On-chip decoding and three chipenable inputs are also provided, permitting easy memory expansion.

> Signetics—Your Supermarket for PROMs. The partial listing of PROM products in the table below will give you a fair idea of why Signetics stands at the forefront of high-speed PROM technology. Each of the types listed is available in economical Power Plastic DIPs or packaged for use in the military temperature range.

Take a closer look at the specifications shown. There's a lot there to find.

The parts themselves can be found on your distributor's shelves. Call him today or use the coupon below to order additional evaluation data.



Signetics Corporation 811 East Arques Avenue

Sunnyvale, California 94086 Telephone 408/739-7700

SIGNETICS PROM SELECTION GUIDE (4K & ABOVE)

Size	Organization	Туре	Output*	Pins	Мах. Тдд (ns)	Max. ICC (mA)	Key Benefits	
4K PROMs	1024 x 4 (4096)	82S136	oc	18	60	140	High speed.	
		82S137	TS	18	60	140		
	512 x 8 (4096)	82S115	TS	24	60	185	High speed. Has built-in latch	
		82S140	OC	24	60	175	Four chip-enable inputs for	
		82S141	TS	24	60	175	easy memory expansion.	
		82S146	OC	20	45	155	Fastest available 4K PROMs.	
		82S147	TS	20	45	155	.3" wide pkg. saves space.	
	2048 x 4	82S184	OC	18	100	120	Low current drain.	
Ms	(8192)	82S185	TS	18	100	120	Low current drain.	
PROMs	1024 x 8 (8192)	82S180	OC	24	70	175	High speed	
8K P		82S181	TS	24	70	175	High speed.	
		82S2708	-	24	70	175	High speed with 2708 pinout	
28	2048 x 8	82S190	OC	24	80	175	16K capacity with drain of	
HOW.	(16,384)	82S191	TS	24	80	175	only 175mA. 80 nsec speed.	

* OC - Open Collector; TS - Tri-State

To: Signetics Inform P.O. Box 9052, I	metics Information Services, 811 E. Arques Ave. D. Box 9052, MS 27, Sunnyvale, CA 94086			
 □ Please send me technical data on the 82S190/82S191 16K PROM. □ I'd like additional data on the(type). □ Send me general product reference material on all PROMs, including those with smaller capacities. □ I have an urgent requirement. Please have a PROM specialist phone me at once: () 				
Name	Title _	West her year		
Company	Division	n		
Address	MS			

signetics

Sperry Univac's new mainframe-on-a-board: What you do with it is your business.

Whether your systems business is scientific, instrument control, or data communications, know this:

Our new V77-200 delivers more computing power than any other computer-on-a-board you can buy. Handling up to 32K/16-bit words of 660ns MOS memory.

Reason enough to call it the world's first mainframe-on-a-board. But there's more.


Because our new 7-200 comes loaded

V77-200 comes loaded with "big machine" features. Like 8 programmable registers with byte, word and double word manipulation. Up to 32-bits of arithmetic precision. A powerful set of 187 instructions. Hardware multiply/divide. Direct memory access. Programed I/O. Multi-device automatic program loaders. A real-time clock. And a teletype/CRT controller. All standard. And all on a single 10.8" x 17" board.

There's even Virtual Console Logic that eliminates the need for a programmer's console by allowing you to control the V77-200 from a teletype or CRT keyboard.

You get "big machine" performance, too. Example: a microinstruction cycle time of 165ns that allows multiplication functions to be handled in just 4.9 microseconds—divide in just 8.

Plus your choice of OEM-tailored options. Like a variety of connector planes and general purpose interface boards for custom I/O designs. Three different 660ns memory boards (in 8K, 16K, and 32K-word modules). An operator's console. Power-fail detect and data save. Memory parity. Hardware for up to 64 priority vectored interrupts. An integral or modular power supply. And a system chassis. All the "unbundled" pieces you need for quick and easy system integrations.



The new V77-200 also saves you time and money by allowing you to use Sperry Univac's well-established floppy or disk-based VORTEX real-time operating system. In effect, allowing you to concentrate on the development of your application software.

And giving you access to Sperry Univac's extensive library of software subsystems, language processors, and system

utilities.

Best of all, the world's first mainframe-on-a-board has a base price of just \$1200. Plus a discount plan designed to give even modest-volume OEM buyers a big break. And you can take delivery in a matter of days—not months.

No matter how you configure it, the new V77-200 is the most economical Sperry Univac yet. Delivering the kind of price/performance value that just makes good sense. No matter what business your systems are in.

For more information on the world's first main-frame-on-a-board, please contact: Sperry Univac Mini-Computer Operations, 2722 Michelson Drive, P.O. Box C-19504, Irvine, California 92713,



by John E. Buckley
Telecommunications Management Corp
Cornwells Heights, Pa.

Certification 1977

Mandatory use of interface connecting arrangements for customer-owned communications equipment connected to the switched telephone network of the communications common carriers has been one of the more prolonged issues in the field of telecommunications. In many intrastate communications network applications, these "protective" devices were also required for access to leased lines

provided by telephone companies.

-

* * * * * * * *

These connecting arrangements burst upon the telecommunications world following the 1968 Carterfone Decision by the Federal Communications Commission (FCC). In that decision the FCC allowed the connection of nontelephone company equipment to telephone facilities. Referred to as "foreign attachments," such connections had been universally prohibited in all existing federal and state tariffs in effect at that time. Naturally, mandatory use of these devices was strongly opposed by private manufacturers of telecommunications equipment as unnecessary and restrictive, while traditional communications common carriers defended their existence on the grounds of protecting the telephone network from the hazards of the customer-owned equipment.

Since then, unending varieties of telecommunications applications and devices which require connecting devices have been developed and applied to the telephone network. Conflicts between the telephone companies and their opponents on this issue have been debated and tested in technical, regulatory, judicial, and legislative arenas. However, conclusions have always been indecisive, and at best have provided small shifts in their relative positions. Fundamental differences have remained unresolved: the telecommunications industry wanted the connecting arrangements to be eliminated while the majority of the

telephone companies insisted that they remain.

After nine years, the issue finally is about to be resolved. On October 5, 1977, the U.S. Supreme Court announced that it will let stand a Fourth Circuit Court of Appeals ruling which validates FCC Part 68 Rules and decided not to hear a pending case filed on this issue. Those FCC Rules permit direct connection of telecommunications systems and equipment to switched and leased line facilities of the telephone network if the telecommunications systems and equipment have been certified by the FCC. All judicial avenues have been utilized and concluded; even the U.S. Congress has been involved in this issue by the attempt to pass the Consumer Communications Act of 1976 (see "Communication Channel," Computer Design, Sept 1976, pp 14, 19). These past events appear to be finished; FCC certification and


registration of telecommunications systems and equipment are now law.

The U.S. Supreme Court's decision, rather than ending this issue, has merely set in motion the events necessary to conclude it. Many of the finer points pertaining to this Supreme Court decision have yet to be resolved by the FCC; the definition and time of those subsequent resolutions are still uncertain. The Supreme Court decision was scheduled to be final on October 24, 1977, but could actually be delayed if telephone companies or states file further petitions for reconsideration of the Court's action in refusing to hear the case.* By mid-October, U.S. Congressman Lionel Van Deerlin (D-Calif), Chairman of the U.S. House Subcommittee on Communications, requested in writing that FCC Chairman Richard Wiley rule on the primary line concept petitioned to the FCC. The concept, related to small key telephone systems and residential telephones, proposed that in the event of certification, the telephone company could insist that at least one telephone set provided by the telephone company be required, at tariff rates, at each location that was equipped with customer-owned telephone instruments or a key telephone system. The FCC must respond to this notification, which could add as much as six months to the effective date of the Supreme Court decision. Delays in the finalization of this decision are, therefore, expected.


A more significant aspect that must be resolved is the matter of "grandfathering telephone systems." Telephone companies pleaded that an unreasonable burden was being imposed to require all telecommunications equipment to meet FCC certification standards in order to connect directly to the telephone network. Since most existing equipment provided by the telephone companies was not expected to meet these standards, it was proposed by the FCC that telecommunications systems and equipment that the telephone companies installed prior to June 1976 would be considered "grandfathered" and initially exempt from certification. They could remain uncertified and in direct connection with the telephone network until some future date. Since the Supreme Court decision to confirm the validity of this FCC Ruling has taken so long, a new cutoff date will be negotiated by the telephone companies and ruled by the FCC.

All similar regulatory aspects must be reconsidered and redefined by the FCC before a definitive conclusion can

^{*}Due to necessary deadlines, it is possible to provide only information and related developments concerning this ruling which were available up until press time.



R SINCE OUR GREAT



When we introduced the Fairchild 64K F464, we said it had the stuff to be the industry standard someday. We even started out with a second source. Apparently, a lot of memory people took us seriously. Response has been so positive, we've already increased our production capacity.

Plugging the gap between MOS and magnetic memories, the F464 is the first semiconductor Bulk Storage Devise (BSD).

The F464 is the densest semiconductor memory ever made. A compact die size of less than 40,000 mil² — not much larger than today's 16K RAMs. All packaged neatly in a standard 0.3-inch 16-pin DIP. POIN FAIRCHILD

HIGH PERFORMANCE, LOW OVERHEAD.

EGHED TECHNOLOGY

There has never been a device like the F464. It's a 65,536 x 1-bit dynamic serial memory organized as 16 randomly accessible shift registers of 4096 bits each. The four address bits are decoded on-chip to select which one of these 16 shift registers is to be accessed. Control inputs include Write Enable and Chip Select. It requires

standard power supplies of +12 V and $\pm 5 \text{ V}$.

All inputs (except the clocks) are directly TTL compatible. The two high-frequency and two low-frequency clock inputs are low capacitance 12 V signals which can be easily generated with simple logic.

The logic required to generate this 4-phase clock costs less than one memory chip and is generated only once per system.

Part Number	Maximum Frequency (MHz)	Maximum Active Power Dissipation (mW)	
F464-4	2	238	
F464-3	4	298	
F464-2	5	336	

Speed and power dissipation for F464 family.

So you don't pay for memory overhead every time you expand. This lower overhead cost means lower system costs to you.

Maximum data rates range from 2 MHz (F464-4) to 5 MHz

(F464-2). The minimum frequency for the SPS structure is 1 MHz. Since all 16 registers shift simultaneously, the average random access time (called latency) is only 410 μs at 5 MHz — a truly significant performance improvement over other bulk memory technologies! And, at the same time, the power dissipation remains low: typically 3.5 μ W/bit at 5 MHz, and 0.6 μ W/bit during standby at 1 MHz. Three part types are available to cover a wide range of maximum speed requirements.


These performance benefits make the F464 a natural for hybrid head-per-tracks or fixed-head discs, extended cache, and many other high-density memory applications.

Other outstanding F464 characteristics include solid state ruggedness, speedy data rates and the most semiconductor memory per square centimeter in the industry.

Not bad for a small chip!


LOW COST, HIGH VERSATILITY.

The new F464 is three to four times less expensive per bit than RAMs. It is also cost-competitive with all fixed-head discs.



F464 applications range from typical computers to atypical portable memories and digital delays.

And once you order, you can rest assured that you'll get prompt delivery. Fairchild has a 250,000-square-foot plant in San Jose, California that's totally dedicated to VLSI technology and production.



FOLLOW THE LEADER.

Fairchild pioneered CCD technology. We introduced the world's first commercially available charge-coupled device in 1973. Today, we offer the world's broadest line of CCD products. It stands to reason we'd be the ones to make CCD memories a reality.


For more information on the F464 (or our other CCD products), contact your Fairchild sales office or representative today. Or write directly to our MOS/CCD Division at Fairchild Camera and Instrument Corporation, P.O. Box 880, Mountain View, California 94042. TWX: 910-373-1227.



be attained. Technical realities must also be considered before present users disconnect existing connecting arrangements. While preliminary certification specifications and procedures have been issued by the FCC, finalization and approval of this certification standard must still be accomplished. Registered telecommunications devices do not actually exist; even traditional connecting arrangements are not presently considered as certified and registered by the FCC. Although many manufacturers are tentatively claiming that their equipment or systems meet certification, in actuality it means only that their product is considered certifiable under the present preliminary, nonapproved specifications. Admittedly, such products have a higher probability of certification than other products that have never attempted adherence to the preliminary standards.

A second technical factor is that most customer-owned systems and equipment were designed to interface to a connecting arrangement, not directly to telephone lines. These interfaces are dramatically different. It is false to assume that removing a connecting arrangement is the sole event necessary to accomplish direct connection. It appears that present telephone line characteristics will be considerably modified with the advent of certification. Present certification standards impose an interface characteristic modification on both the telephone line appearance and the terminal equipment. Devices installed by the telephone companies directly to the telephone line once it is modified will also require modification to be registered.

The transition from connecting arrangements to fully certified telecommunications systems and equipment is a complex procedure which the FCC must coordinate and control in phased sequences. Unfortunately, it appears



inevitable that each subsequent phase would tend to impact equipment or devices purchased to meet the requirements of some previous phase. Idealistically, the telecommunications industry and user communities would like to stop all new installations and, without economic concern, be able to immediately convert all existing installations and make certified equipment available from all manufacturing sources.

Three areas of concern are shared by telecommunications users. The first is the availability of present connecting arrangements to permit the continued installation of customer-owned telecommunications systems and equipment. These manufacturers are motivated to curtail and discontinue further manufacturing because the arrangements do not meet preliminary certification standards, facing them with inevitable obsolesence. Telephone companies want to stop the purchase of these obsolete devices and wish to deplete their present inventories as soon as possible. Without a clearly defined alternative, a shortage of such devices can be expected for new installations as well as for maintenance replacement.

Secondly, certified trunks and equipment terminations are not yet finalized and hence are unavailable. Non-availability of a connecting arrangement may be temporarily overcome by permitting direct connection of customer-owned equipment to existing trunks. Present circuits in customer-owned equipment must then be extensively modified, if possible, or replaced. The latter incurs the same short-term obsolesence as present connecting arrangements. Manufacturers are not willing to invest in the development and manufacture of direct connection interfaces to present trunk characteristics when certified trunks will replace them shortly. In the same context, users would not purchase interim equipment interface circuits even if they were available.

The third concern is that telephone companies will automatically disconnect existing connecting arrangements once the court's decision is finalized. The validity of this depends on how each state regulatory agency addresses this decision, since state tariffs have jurisdiction over the installation, service, and rental aspects of connecting arrangements. The probability that all telephone companies will immediately remove all present connecting arrangements is very low. Over 500,000 connecting arrangements are installed by telephone companies in the U.S. At an average monthly rental of \$6 each, this represents approximately \$3M dollars in revenue that will continue as long as the connecting arrangements remain installed. External influences, however, could force a change. For example, a matter pending with the Massachusetts Public Utility Commission could require Massachusetts telephone eompanies to terminate all charges for existing connecting arrangements. In California, the pending request would refund all past revenue realized from connecting arrangements. Without the revenue, the telephone companies might be prompted to disconnect these arrangements on the grounds that they are maintenance and cost liabilities.

A euphoria has been provided by the Supreme Court's resolving this issue. However, the transitional problems may be discouraging. Discontinued connecting arrangements coupled with the lack of finalized certification standards would result in the nonavailability of registered devices and trunks, and might serve to accomplish the telephone companies' previous objective of curtailing competition in spite of the court decision. The next few months are critical for implementing this decision. The FCC, given the opportunity it has been seeking, is responsible for an orderly transition. Hopefully they will bring that opportunity to reality in an equitable manner without unnecessary delays.

Color and smarts don't cost a lot anymore.

Ramtek's new MICROGRAPHIC™ terminal gives you color, intelligence, graphics, and alphanumerics at a price you can afford.



Here's great resolution and a bright, flicker-free display on a matrix of 512 elements by 256 lines in a terminal that's easy to program to your requirements.

No longer do you have to put up with poor resolution in economypriced terminals. Ramtek gives you a combination of true graphics—such as vectors, conics, plots and bar charts and high-speed alphanumerics with a high-resolution industrial-quality monitor. You can choose two sets of 8 colors for both graphics and alphanumerics. Dual and split screen capability too, with all the price/performance benefits of raster scan technology. And the independent alphanumeric refresh offers you singlecharacter addressability within a visible matrix of 25 rows of 80 characters that are bright, crisp, sharp, and well defined. The refresh memory also allows selective erase, modification, and update

The MICROGRAPHIC terminal is controlled by a powerful Z-80 microprocessor with up to 28K bytes of PROM and 16K bytes of RAM. Ramtek's control software gives you TTY compatibility and high-level graphic functions commanded by ASCII text strings. Choose from an extensive list of options such as additional serial I/O ports, alphanumeric overlays, programmable fonts, and packaged software.

Best of all, you'll find Ramtek gives you an affordable price, depending upon your individual requirements. Find out more by contacting us. We're Ramtek, 585 N. Mary Avenue, Sunnyvale CA 94086. In a hurry? Pick up the phone and call us. We'll tell you why you can afford color, and smarts.

ramtek Our Experience Shows

REGIONAL OFFICES: Sunnyvale, Catifornia (408) /32-3572 - Dallas, Texas (214) 422-2200 - Huntsville, Alabama (205) 837-7000 - Cleyveland, Ohio (216) 464-4053 - Stamford, Connecticut (203) 348-8804 - Washington, D.C. (703) 960-3550 Europe (0611) 595980

CIRCLE 11 ON INQUIRY CARD

DAY MOVING AU

Intel delivers the 8085, designers just

8155 8355 Sink your to You Standard Memory

Sink your teeth into Intel's new 8085. You'll find it's the only micro-

computer that combines the performance, economic advantages and total support it takes to be recognized as

the new industry standard. So it's no surprise that there are already four announced

sources for the 8085. In fact, the deeper you go, the better the 8085 gets.

The 8085, even more than the 8080 it succeeds, is a total design solution, not just a component. It delivers higher performance, for capabilities far beyond the 8080's. It has a higher level of integration, so you can design your products with fewer components, making them more competitive and more profitable. And to help you get those products to market quicker we've given the 8085 the industry's broadest base of system and development support.

Yet the 8085 is fully compatible with the 8080. So your investment

in existing designs is protected, and implementing new designs is simplified by the wealth of 8080

software and peripherals at your disposal.

It all adds up to a design solution you won't be able to resist. That's true for a broad range of applications. The 8085 can be designed in as an economical stand-alone three-chip system using the 8085 CPU, the 8155 256-byte RAM with I/O and timer, and the 8755 2K-byte EPROM with I/O or its interchangeable 8355 ROM with I/O.

You can expand this basic system for larger applications using additional RAM, ROM, EPROM and Intel's complete family of first and second generation peripheral controllers, including our four new programmable peripheral controller chips—the 8271* Floppy Disc Controller, 8273* Synchronous Data Link Controller, 8275 CRT Controller and 8279 Keyboard/Display Interface. All these components including 8755 EPROM operate from a single +5V supply.

^{*}Available 4th Quarter 1977

the new microcomputer can't resist.

A multiplexed data/address bus permits integration of many auxiliary system functions—such as clock generation, system control and multiple interrupts—onto the 8085 chip while maintaining 8080 compatibility and the same 40-pin package. And forward-thinking engineers will realize that it is also a link to Intel's

future generation microcomputer products.

No microcomputer can match the 8085 as a total design solution because no microcomputer can come close to the 8085's support base. Support for the 8085 includes the Intellec® microcomputer development system with resident PL/M, the high level programming language that can cut months off your software development time. Intellec is the only development system with ICE-85,™ providing in-system emulation for faster system development and debugging. Then there's application assistance, training classes and seminars worldwide. And a comprehensive development software library at your disposal.

The quickest way to get a taste of the 8085's power and versatility is with the SDK-85 System Design Kit. It's available now for only \$250. You can order SDK-85 and all MCS-85™ components directly from your nearest Intel distributor: Almac/Stroum, Components Specialties, Cramer, Hamilton/Avnet, Harvey Electronics, Industrial Components, Pioneer, Sheridan, L.A. Varah, Wyle Liberty/Elmar or Zentronics.

Or, for more information on the 8085 and SDK-85, use the reader service card or write: Intel Corporation, 3065 Bowers

Avenue, Santa Clara, California 95051. Telephone: (408) 987-8080.

intel delivers.

MCS-85™ Microcomputer System Components Family

8085 CPU with system bus control, system clock generator, serial I/O and 4-level interrupt control. 8155/8156 RAM, I/O & Timer. 256-byte static RAM, 22 I/O lines, 14-bit programmable interval timer/event counter.

8355 ROM & I/O. 2048-byte masked ROM, 16 I/O lines. Interchangeable with 8755. 8755 Erasable PROM & I/O. 2048-byte UV erasable and electrically reprogrammable EPROM. Interchangeable with 8355.

Compatible MCS-80™/MCS-85™ Peripheral Components

General Purpose
8251 Programmable Communications Interface
8253 Programmable Interval Timer
8255 Programmable Peripheral Interface
8257 Programmable DMA Controller
8259 Programmable Interrupt Controller
8205 High Speed 1 out of 8 Binary Decoder
8212 8-bit Input/Output Port (Latch/Buffer)
8216/8226 4-bit Parallel Bidirectional Bus Driver
Dedicated Function
8271 Programmable Floppy Disk Controller
8273 SDLC Protocol Controller
8275 Programmable CRT Controller
8279 Programmable Keyboard/Display Interface

Performance Matched Standard Memory

Static RAM
2114 1024x4-bit, 450 nsec, 18 pin
2142 1024x4-bit, 450 nsec, 20 pin
8101A-4 256x4-bit, 450 nsec, separate I/O
8102A-4 1024x1-bit, 450 nsec, separate I/O
8111A-4 256x4-bit, 450 nsec, common I/O
ROM/EPROM
2716 2048x8-bit Erasable PROM, 450 nsec
2708 1024x8-bit Erasable PROM, 450 nsec
2316E 2048x8-bit Masked ROM, 450 nsec
8308 1024x8-bit Masked ROM, 450 nsec



AMP introduced the DIP switch to solid-state electronics. Now we've gone still further. AMP's new low-profile DIP switches are as low as you can get. You can use them to program ICs right-on-the-board without remote wiring. And sandwich boards in less space, to cut packaging costs.

With our new, low-profile DIP switches, cleaning boards is easier than ever. Simply place our protective covers or pieces of tape on the switches and you can clean complete boards without damage.

We're the people who developed and perfected DIP switches

—a whole family of them—including our innovative, pluggable Hexadecimal Rotary Switch. Our experience is broader and deeper than anyone's. At AMP we'll have the right answers for your applications.

Bright new lights.

Unique LED DIP switches are available in SPST "on" or "off" as well as momentary-contact types. They permit rapid, visual circuit test, fault indication and programing verification. Plus, for the first time, they permit DIP packaging of LEDS.

Rockers are detented to avoid accidental actuation.

Switch leads and LED leads are terminated independently for circuit connection versatility.

There's nothing quite like new AMP LED DIP

switches. For more details on them, or the new AMP low-profile DIP switches, call (717) 564-0100. Or write AMP Incorporated, Harrisburg, PA 17105.

AMP is a trademark of AMP Incorporated.

AMP

AMP has a better way.

AMP EUROPE

4

*

-

46

Austria — AMP Austria. Branch of AMP Deutschland GmbH. Markgraf-Ruediger Str. 6-8, 1150 Vienna. Phone: 924191/92

Belgium — AMP Belgium. Branch of AMP-Holland B.V., Rue de Brabant 62-66, Brussels. Phone: 322.17.55.17

Finland — AMP Finland OY Postilokero 3, 00401 Helsinki 40 Phone: 90/584122

France—AMP de France. 29 Chaussée Jules-César. Boite Postale No. 39. 95301 Pontoise France. Phone: 030 82 20, 030 92 30

Germany — AMP Deutschland GmbH. Ampérestrasse 7-11, 607 Langen, B. FFM., West Germany. Phone: (06103) 7091

Great Britain — AMP of Great Britain Limited, Terminal House, Stanmore, Middlesex, England. Phone: 01-954-2356

Holland — AMP Holland B.V., Papid 5223 AW 's-Hertogenbosch, Holland. Phone: (073) 125221

Trally — AMP Italia S.p.A., Via Fratelli Cervi 15, 10093 Collegno (Torino), Italy. Phone: 785-656
Spain — AMP Española, S.A., Apartado 5294. Pedro IV, 491, 495, Barcelona 5, Spain. Phone: 307-75-50

Sweden — AMP Scandinavia AB, Datavägen 5, 17500 Jakobsberg, Sweden, Mailing Address: Fack S-175 20 JARFALLA 1, Sweden. Phone: 0758/10400

Switzerland — AMP AG, Haldenstrasse 11, 6006 Luzern, Switzerland, Phone: (414) 235421, 235422, 235423

AMP NORTH AMERICA

Canada — AMP OF CANADA LTD., 20 Esna Park Drive, Markham, Ontario, Ph. 416-499-1251

Mexico — AMP de Mexico, S.A., Apartado Postal 179, Naucalpan de Juarez, Edo, de Mexico, Phone: Mexico City 576-41-55

Puerto Rico - AMP OF CANADA LTD. 677 Calé de Diego, Rio Piedras, Puerto Rico 00924, Phone: (809) 766-2346

United States — AMP Incorporated, Harrisburg, Pa. 17105, Phone: 717-564-0100

AMP SOUTH AMERICA

Argentina — AMP S.A. Argentina 4 de Febrero, 76 Villa Zagla — SAN MARTIN, Buenos Aires, Argentina, Phone: 752-4612

Brazil — AMP do Brasil Ltda., AV Comendador Martinelli 185, Lapa, Sao Paulo, Phone: 262-4353

AMP PACIFIC

Australia — Australian AMP Pty. Limited, 155 Briens Road, Northmead, N.S.W. 2152 Australia, Mailing Address: P.O. Box 194, Baulkham Hills, N.S.W. 2153 Aus. Ph. 630-7377

Japan — AMP (Japan), Ltd., No. 15-14, 7-Chome, Roppongi Minato-Ku, Tokyo, Japan, Ph: 404-7171

Products and services for many specialized industries are provided by the AMPLIVERSAL Division. In the United States, this division is known as AMP Special Industries.

For Amp products and services in other countries, write: AMP International Division, Harrisburg, PA 17105, USA.



COMMUNICATION CHANNEL

Management Capabilities Aid In Monitoring Communications Costs

Selection of communications management hardware has been enhanced with three additions to the family of expandable communications management systems. Datapoint Corp, 9725 Datapoint Dr, San Antonio, TX 78284 has aimed the compatible devices at particular problems of distribution of incoming calls, long distance cost control, and outgoing calls control.

Call processing is performed by reliable, stored program microcomputer-controlled switching or metering subsystems. One of the company's host computer systems performs functions of data base management, optimization of routing decisions, and management and facilities utilization

Infoswitch™ Automatic Call Distributor (ACD) is a telephone switching and management system for uniform distribution of incoming calls among agents and agent groups, affording control and measuring of incoming call traffic and generation of detailed management statistics and reports. The turnkey system, requiring no user programming, includes a host computer, agent telephone instruments with group supervisors, and intelligent switching subsystem for automatic distribution of calls.

Also incorporated are one or more video display supervisor consoles, multiple port asynchronous communications interface, and large disc storage facility. High speed local printers may also be configured with the system. System sizes range from four to 110 telephone trunks, with from four to 72 agent positions.

The multiple Infoswitch Telephone Communications Management System (SHARE) allows multilocation corporations to economically distribute intelligent long distance telephone switching (LDCS), and local and tie-line metering facilities in the field, while maintaining centralized control over the corporate telecommunication network and data base. Main component of the various configurations is a computer with keyboard, video display screen, and large internal user memory capacity. Host computer is equipped with one or two high density cartridge disc drives.

The switching subsystem handles all processing of long distance calls;

an intelligent metering subsystem can also be used to monitor long distance, local, directory assistance, and tieline calls originating within a company. Standard and extended configurations are available.

To account for all outbound telephone calls, the Infoswitch Station Message Detail Recorder (SMDR) extends the long distance telephone control system to a full telephone management system. The intelligent switching system for long distance call control; metering subsystem for local, directory assistance, and tie-line calls; and host computer constitute the system. Printers and mag tape drives may be used with the system.

It can be configured from 16 to 2048 station lines in increments of 16 lines. Rotary dial is standard; tone dial is optional. A variety of interfaces and modems are available for external communications.

Circle 400 on Inquiry Card

2-Way Service To Access Information Via Telephone and TV

Immediate access to a store of information will be possible via an adapted domestic TV set and a telephone line with the Viewdata system. A numeric handheld keypad is used to select information displayed on the screen. As a means of stimulating telephone traffic, especially residential, the United Kingdom Post Office has been developing the teleprocessing service since 1970 to provide immediate and convenient information retrieval and interactive facilities for the general public and business community at a small fee.

Viewdata is transmitted via the telecommunications network, while Teletext is a broadcast signal. However, both services feature a common memory, character generator, and display unit of a combined decoder.

Basic elements of the Viewdata system are the terminal (TV set), transmission system, computer, and data base with progressive indexing system (treeing structure). Currently consisting of 6000 pages, the data base is expected to be expanded to 60,000 for market trials, to be held on a central computer configuration. It was decided to incorporate the line interface unit, comprised of the A-D converter, terminal identifier, and auto-dialer (for automatic dialing of the Viewdata center from the terminal) in the TV set at the time of manufacture.

Key parties involved in the project are the UK Post Office, the TV set industry (as well as its semiconductor suppliers), and the information industry, which currently involves 80 information providers offering 300 topics with more to follow. The combined Teletext/Viewdata receiver should be through trial production by mid-1978, to coincide with the beginning of a market trial of 700 households and 300 business representatives. Following this, geographically restricted public service is expected by late 1979, with further expansion commensurate with demand.

Refinements to the system are being developed. These include closed user groups requiring a confidential pass number known to an authorized user, conversational mode designed for the deaf community, and hard copy especially useful for businesses. Further details of the system are con-

tained in the paper entitled "'Telecommuting' by Viewdata," by Roy Bright, Intelcom 77 Exposition Proceedings, Vol 2, 1977, pp 595-599. Circle 401 on Inquiry Card

Advanced Satellite Joins Expanding Global Communications Systems

The first of the Intelsat IV-A communications satellites designed to orbit over the Indian Ocean has been launched as part of the expanding global satellite communications system, to replace older models over heavy traffic areas of the 98-member countries of the International Telecommunications Satellite Organization. Over the Indian Ocean, the satellite will have beam diversity and the ability to switch two narrow beam channels to wide beam channels to cover the countries it serves.

The principle of beam diversity has allowed Hughes Aircraft Co, PO Box 90515, Los Angeles, CA 90009 to increase the satellite's capacity to relay more than 6000 simultaneous telephone calls plus two TV programs, compared with 4000 circuits and two TV channels for the earlier Intelsat IV

series. To transmit the same band of frequencies twice with beam diversity, the satellite directs a communications beam with a certain frequency to one area of the world and the same frequency to another area. There is no interference because the beams are directed thousands of miles apart.

After launch, the satellite undergoes a period of testing; ground stations communicating with the satellite make equipment changes to conform with allotted frequencies. By June of 1978 these tasks will be complete and the unit will be in position off the east coast of Africa and southwest of India, delivering service to more than 40 nations.


Forms of Electronic Communications Should Depend Upon Users

Users of such emerging, interrelated forms of electronic communications as electronic funds transfer, electronic mail, and computer communications "should have the final choice" in how they are provided, according to Edward Goldstein, director of product management, American Telephone and Telegraph, 195 Broadway, New York, NY 10007. Addressing the House Communications Subcommittee discussing national telecommunications policy, he cautioned against taking any steps that would slow or stop this dynamic field. Believing that common carriers would best meet user communications needs, Goldstein added that any revisions to the Communications Act must retain flexibility to accommodate these emerging applications, which are characterized by lower cost and more convenient methods of communications.

Telecom Service Promises Substantial Savings For Smaller Businesses

Telemax II Telephone Management and Control System will save up to 30% of annual phone charges for smaller business offices with monthly long distance telephone charges above \$3000. TDX Systems, Inc, 7670 Old Springhouse Rd, McLean, VA 22101 guarantees a minimum savings of 10%, above the cost of its service.

The network links the user by data circuit to a microcomputer located at an office of Southern Pacific Communications Corp, which in turn is linked by data circuit to one of the company's host computers in Virginia.



Ann Arbor makes over 1000 standard RO and KSR display terminal models. Alphanumerics. Graphics. Or both.

We also thrive on tough CRT display applications. Unique character sets. Unusual graphics. Difficult interfacing. Custom keyboards. Special packaging. You name it.

Standard or custom, every terminal produced is based on a field-proven Ann Arbor engineering concept. DESIGN III desktop terminals to complement any office decor. Compact, rugged Series 200 modular terminals that defy industrial environments. Or barebones board sets for OEMs who prefer to roll their own.


Many companies sell CRT terminals. But Ann Arbor sells creative solutions to CRT display problems, as well.

Probably at lower cost than anyone else in the business.

Contact us at 6107 Jackson Road, Ann Arbor, MI 48103. Tel: 313-769-0926 or TWX: 810-223-6033. Or see our catalog in EEM, Volume One.



... creating new ways to communicate



Internationally acclaimed Miproc-16 with a compute-rate of up to 4 million instructions per second is the fastest 16-bit microcomputer card family available.

Now supplied with an OEM chassis package, Miproc-16 is even more quickly brought into action. This cost-effective application system, named Miproc-16 AS, has room for one, two or even three Miproc-16 CPU's. Smartly styled and equipped with add-in 13-slot card bay modules, fans and power supply, this new OEM chassis package eases the way into high speed microcomputing.

Instruction Power

Up to 170 instructions including multiply/ divide and bit manipulation give Miproc-16 formidable processing capability.

16-bit Power

16-bit program words make programming easy. 16-bit data words maintain high precision in arithmetic operations.

Addressing Power

16-bit dual memory architecture gives 65k words of directly addressable program memory and 65k words of data memory with 8 powerful address modes.

Interrupt Power

Multilevel, priority vectored interrupt system handles context changes in less than 2 microseconds.

I/O Power

256 directly addressable I/O channels with data I/O rates of up to 1.7 megabytes/sec. under program control, and up to 20 megabytes/sec. for DMA.

High Speed Processing Power

The unique dual memory architecture combines with high speed Schottky TTL technology to execute most instructions in a single machine cycle.

Software Power

Easy to use cross-assemblers for mainframe or minicomputer make programming faster, and PL-MIPROC, a super-efficient high level assembly language.

Hardware Power

Comprehensive range of processor, memory and interface cards backed up by sophisticated hardware development aids.

Ruggedized Power

Miproc can be configured to meet any known military specification.



Phil Burnley, Plessey Microsystems, 1641 Kaiser Avenue, Irvine, California 92714, USA.

Tel: (714) 540 9931

David Garrison, Plessey Microsystems, Suite 408, 11141 Georgia Avenue, Wheaton, Maryland 20902, USA

Tel: (301) 949 1664

654 PP044

Long distance telephone calls for the user's office are routed through his own wars lines, as well as over Southern Pacific's network.

Automatic callback or camp-on queuing, and least cost routing of calls are provided. Additional savings are obtained with a detailed call report that enables individual cost allocation, departmental billing, and reduced call abuse.

Circle 402 on Inquiry Card

Agreement Assures Continued Support of Data Terminals

An agreement-in-principle has been announced under which TRW Communications and Services, Customer Service Div, Fairfield, NJ 07006 will service customers of Wiltek's data communication terminal systems in existing locations and will expand the service to over 20 additional locations presently covered by TRW personnel. TRW will also acquire the spare parts inventory and specialized equipment for the installed base of the over 2000 model I and II terminals. Wiltek, Inc, Norwalk, CT will continue to provide computerized message service and actively market data communications terminal systems and data storage units.

Optical Fibers in Telephone Cable Work Successfully

Optical fibers made by Corning Glass Works, Corning, NY 14830 have been used in an existing telephone network in Italy, carrying messages experimentally more than 5.5 miles (about 9 km) without amplifying the signal. Less than 0.5" (1.3 cm) wide, the cable is manufactured by Industrie Pirelli, Italy, and was laid in Turin between two telephone exchanges of SIP (Italian state telephone organization). The experiment has been carried out by CSELT, Italian telecommunications laboratory and research study center, since September.

The high speed digital transmission system that provides the equivalent of 2000 telephone lines moved data over a single Corguide optical fiber less than 0.004" (0.0102 cm) thick at a rate of 140M bits (140M signal pulses)/s. Signals went the full 9 km

without needing amplification or regeneration. Full capacity of the cable with eight fibers will be 8000 2-directional, simultaneous telephone conversations.

The lacquer-coated fibers used are identical to the 1053, except with greater bandwidth and less attenuation; they average more than 400 MHz at 1 km and less than 4 dB/km, respectively. No change in attenuation occurs over a -60 to 80°C operating temperature.

Switching System Unites Separate Telex and Data Services

Formerly separate telecommunication services such as Telex, Gentex, Datex, store-and-forward message service, and high speed data switching are integrated with the digital data switch (DDS) from Collins Commercial Telecommunications Group of Rockwell International, Dallas, TX 75207. Implemented during initial system installation or added later as an optional service, the switch can be configured for application as an international gateway, national transit, or local subscriber exchange, or any combination of these.

Major exchange building blocks of the CCITT-compatible device consist of a single network control group providing programmed control and reporting functions, and one or more call service groups performing call processing and circuit switching operations. The time division multiplex switch matrix is fully nonblocking in operation and is transparent to data. Basic implementation of the matrix provides capacity for 480 low speed or 24 high speed terminations.

A built-in administrative data system provides visibility of the operating status of the network, exchange, and dynamic traffic patterns that occur. Both network and exchange configurations adapt to dynamically changing traffic conditions.


Expanded subscriber features of the switch include automatic international routing of calls, abbreviated selection codes for national address, automatic retry and camp-on to minimize lost operator time, and call duration recording in minutes and tens of seconds. Also included are conference calling with individual recording of call durations, multiline hunting groups to form private branch exchanges of up to 30 stations, and available direct call and dedicated point-to-point circuits.

Call your nearest ISC sales representative.

If your state is not listed call 800/241-9888. ALABAMA: Huntsville W. A. Brown Inst. Inc. 205/539-4411 ARIZONA: Phoenix Thorson Co. 602/956-5300 CALIFORNIA: Goleta Thorson Co. 805/964-8751 CALIFORNIA: Los Angeles CALIFORNIA: Mountain View Thorson Co. 415/964-9300 CALIFORNIA: San Diego Thorson Co. 714/298-8385 CALIFORNIA: Tustin Thorson Co. 714/544-5121 COLORADO: Denver Thorson Co. 303/759-0809 FLORIDA: Ft. Lauderdale W. A. Brown Inst. Inc. 305/776-4800 FLORIDA: Melbourne W. A. Brown Inst. Inc. 305/723-0766 FLORIDA: Orlando W. A. Brown Inst. Inc. 305/425-5505 FLORIDA: Valparaiso W. A. Brown Inst. Inc. 904/678-7932 **GEORGIA: Atlanta** W. A. Brown Inst. Inc. 404/939-1674 LOUISIANA: Gretna W. A. Brown Inst. Inc. 504/366-5766 MARYLAND: Bethesda Bartlett Assoc. 301/656-3061 MASSACHUSETTS: Framingham Bartlett Assoc. 617/879-7530 MICHIGAN: Madison Hts. WKM Associates 313/588-2300 **NEW MEXICO: Albuquerque** Thorson Co. 505/265-565 NEW YORK: White Plains Bartlett Assoc. 914/949-6476 NORTH CAROLINA: Durham W. A. Brown Inst. Inc. 919/682-2383 OHIO: Cleveland OHIO: Cleveland
WKM Associates 216/267-0445
OKLAHOMA: Norman
Data Marketing Assoc. 405/364-8320
PENNSYLVANIA: Pittsburgh
WKM Associates 412/892-2953
PENNSYLVANIA: Wayne
Bartlett Assoc. 215 16/89, 7326 Bartlett Assoc. 215/688-7325 SOUTH CAROLINA: Columbia W. A. Brown Inst. Inc. 803/798-3297 TENNESSEE: Knoxville McCoin Elec. Equip. 615/584-8411 TEXAS: Austin Data Marketing Assoc. 512/451-5174 TEXAS: Dallas Data Marketing Assoc. 214/661-0300 TEXAS: Houston Data Marketing Assoc. 713/780-2511 TEXAS: San Antonio Data Marketing Assoc. 512/828-0937 WASHINGTON: Bellevue Thorson Co. 206/455-9180 AUSTRALIA: Mt. Waverly, Victoria Anderson Digital Elec. 03-543-2077 CANADA: Montreal CANADA: Montreal
Cantec Rep. 514/620-3121
CANADA: Ottawa
Cantec Rep. 613/225-0363
CANADA: Toronto Cantec Rep. 416/624-9696 EUROPE: England Techex, Ltd. 0202-293-115 EUROPE: France **EUROPE: Switzerland** Intertest, AG 031-224481 JAPAN: Tokyo Munzing International 586-2701



Intelligent Systems Corp.



Two very sophisticated desk top computers with two very unsophisticated price tags.

+

*

*

We're Intelligent Systems Corporation and we've developed two brand-new stand-alone desk top systems. Both are capable of handling an incredibly diverse range of business, control, research and financial applications—in color. Both have a better price/performance ratio than any other compact computer system on the market.

Take a look at the Intecolor 8031. A compact 13-inch 8-color CRT, it comes complete with graphics hardware and software, a built-in mini disk drive for extra storage, plus "File Handling BASIC" which lets you create, delete, and retrieve program segments from storage, by name.

Now take a look at the Intecolor 8051. Perfect if your needs call for a largescreen format. It comes with the same standard features as the 8031, but it has a big 19-inch diagonal screen and external mini disk drive.

We also have a variety of options available for both units, including a convenient bi-directional desk top printer and a new 2708/2716 PROM programmer.

Contact the ISC representative nearest you for a working demonstration of these two highly sophisticated, versatile and dependable desk top systems. Prices are based on a one unit, cash-with-order basis. Guaranteed 30-day delivery or your money back.



Intelligent Systems Corp. .

5965 Peachtree Corners East Norcross, Georgia 30071 Telephone 404-449-5961 TWX: 810-766-1581



Motorola's introducing

1977 MPU family introductions MC68A21P MC68B50P MC68B488P MC3870P MC68B50L MC68B488L MC3870CP MC68A21L MC6852P MCM6830AP MC3870L MC68B21P MCM6830ACL MC6852CP MC68B21L MC3870CL MC6852BJCS MC6800P MC6840P MCM68A30AP MC6852CJCS MCM68A30AL MC6800CP MC6840CP MC6800BQCS MC6840L MC68A52P MCM68B30AP MC6800CQCS MC6840CL MC68A52L MCM68B30AL MC6854P MC68A00P MC6840BTCS MCM68308P MC6854CP MC68A00L MC6840CTCS MCM68308L MC6854L MC68B00P MC68A40P MCM68308CL M06854CL MC68/A40/L MCM68A308P MC68B00L MO6854BTCS MC6802P MC68B40P MCM68A308L MC6854CICS MC68B40L MC6802CP MCM68316AP MC68A54F MC6843P MC6802L MCM68316AL MC68A54L MC6802CL MC68431 MCM68316EP MC6844P MC68B54F MC6802BQCS MCM68316EL MC68B54L MC6802CQCS MG68441 MCM68316EBJCS MC6860P MCM68316ECJCS MCM6810P MC6845P MC6860BJCS MCM6810CP VICM68A316EL MC6845 MC6860CUCS MCM6810BJCS MC6846P MCM68708L MC6862P MC6846CP MCM6810CJCS MCM68708BJCS MC6862BJCS MC6846L MCM68708CJCS MCM68A10P MC6862CJOS MC6846C MCM68A10L MCM68A708L MC6846BQCS MC6875P MCM68B10P MCM68332P MC6846CQCS MC6875L MCM68B10L MCM68322L MC6821P MC6850P MC68488P MCM68A332P MC68488CP MC6850CP MC6821CP MCM68A322L MC6850BUCS MC68488L MC6821L 2nd Quarter, 1978 MC6801 MC68488CL MC6821CL MC6850CJCS 3rd Quarter, 1978 MC6821BQCS MC68A50P MC68A488P MC6809 MC6821CQCS MC68A50L MC68A488L Frequency Range MC68XX = 1.0 MHz MC68AXX = 1.5 MHz Suffix A, Suffix E Introducing Now MC68XXC = -40°C to +85°C MC68XX MC68XXBXCS and MC68XXCXC MC68XXL = Ceramic = Screened to MIL-STD-883 Class B and C

a Hi-Rel M6800 Family

We're committed to introduce over 100 compatible microcomputer system components in 1977. This makes 94.

Yes, in addition to the recently introduced MC3870 single-chip microcomputer, we're adding well over 100 fully-compatible M6800 microcomputer system components this year.

Counted among them are the 26 types that constitute the bulk of the new Hi-Rel M6800 Family processed to MIL-Standard-883. As the simplified flow chart indicates, there is only one significant difference between Class B and Class C screening methods. For some of you that's a very big difference, so Motorola provides both. If you don't want burn-in there's no need to pay for it, but if you need it, you can get it.

Hi-Rel M6800 introductions through November and early December encompass the MC6802 two-chip system, the MC6800 microprocessor, and most of the M6800 Family functions. That includes RAM, EPROM, ROM, Asynchronous Communications Interface Adapter, Peripheral Interface Adapter, Synchronous Serial Data Adapter, Programmable Timer, and Advanced Data Link Controller. Introduction of the Hi-Rel MC68488 General-Purpose Interface Adapter is just around the corner in the first quarter of 1978. See the table at left for a complete guide to this year's Hi-Rel M6800 Family activity.

Motorola MIL-STD-883 Screening Methods				
Screen	Class B	Class C	Comments	
Internal Visual	100% 2010 B	100% 2010 B		
Stabilization Bake	100% 1008 C	100% 1008 C	24 Hours	
Temperature Cycling	100% 1010 C	100% 1010 C	10 Cycles	
Constant Acceleration	100% 2001 E	100% 2001 E	Y ₁ Only	
Seal	100% 1014	100% 1014	Fine and Gross	
Burn-In	100% 1015		160 Hours at 125°C	
Final Electrical Test	100% 3 Temps.	100% 3 Temps.	Per Motorola Device Specification*	
External Visual	100% 2009	100% 2009		
Quality Conformance Inspection†	Sample	Sample	Per Motorola Device Specification*	
*Can be Slash Spec. †Quality Conformance Ins Data Available Upon Red	spection Consists of Lot Sample quest.	Electrical Tests with Generic 0	Groups B, C, and D.	

Here's a quick guide to decoding the device number suffixes.

MC6800 B Q C S- Electrical

	M = Slash Sheet
u o	S = Motorola
#	Lead Finish,
<u>ii</u>	A = Hot Solder
dentification	B = Acid Tin Plate
ie G	C = Gold Plate
Ť	Case Outline
Suffix I	Screening Level Class (See Class B and C Above.)
	Motorola Device Type


	Case Designation	Leads	Size (in.)
e	C	14	0.25 x 0.75
utline	E	16	0.3 x 0.75
On	V	18	0.4 x 1.1
Case C	W	22	0.4 x 1.1
	J	24	0.5 x 1.25
0	T	28	0.6 x 1.4
	Q	40	0.6 x 2.0

Let us demonstrate how Motorola can serve your unique systems requirements. Use the coupon today for fast, personalized response.

To: MOTOROLA SEMICONDUCTOR PRODUCTS, INC. DIRECT ACTION Motorola Microproducts, 3501 Ed Bluestein Blvd., Austin, Texas 78721					
I have an immediate requirement. Please call me. Phone					
My application is:	My application is:				
NAME	TITLE				
FIRM	DEPT				
ADDRESS		1			
CITY/STATE/ZIP		non la			



MOTOROLA Semiconductors
The mind to imagine... the skill to do.



Gould introduces a new range of switching power

Gould's new SMG series lets designers switch to smaller, lighter, more efficient switching power supplies without buying more specs than are needed.

Eighteen new SMG models give the Gould line both wider wattage and a lower price range while maintaining the reliability demonstrated by more than 40,000 Gould units now in use.

The SMG series offers outputs

from 8 to 2,250 watts in a wide selection of voltage/current combinations. Units rated above 500 watts are fan cooled and are front panel selectable for 110 or 220 VAC.

All SMG units have short circuit and over-voltage protection. Temperature stability and voltage regulation are outstanding. Holdup protection is as high as 63 milliseconds. There's even an LED "on" indicator on the front panel of every unit.

For complete information contact Gould Inc., Electronic Components Division, 4601 N. Arden Drive, El Monte, CA 91731 or phone (213) 442-7755. TWX 910 587 4934.

Gould.

The power in switching power supplies.



DIGITAL TECHNOLOGY REVIEW

32-Bit Computer System Contains 2M Bytes of Main Memory, 4G Bytes of Virtual Memory Address Space

Based on a 32-bit wordlength-for the first time in this computer manufacturer's history-the VAX-11/780 system announced by Digital Equipment Corp, Maynard, MA 01754 combines mainframe capacity and performance with minicomputer price and flexibility. It is claimed to be the industry's fastest computer system

priced below \$200,000.

The VAX (for virtual address extension) system includes up to 4.3G bytes of virtual address space and up to 2M bytes of main memory, yet is compatible with the company's 16bit PDP-11 computer family. It has an effective memory access time of 290 ns and is capable of an aggregate throughput rate of 13.3M bytes/s. A single virtual memory operating system (VAX/VMS) allows programs much larger than the physical memory to be run in a manner that is transparent to the programmer. The system is particularly relevant to scientific, data processing, and interactive time-critical applications. It can support as many as 64 users simultaneously.

Main memory consists of 4k metaloxide semiconductor (Mos), error checking and correction (ECC), random-access memory (RAM) chips, with a minimum system configuration of 128k bytes and a maximum of 2M. A request buffer in the memory controller increases system throughput and eliminates most needs

for interleaving.

The rear to the factors at the

The instruction set consists of 243 instructions, nine addressing modes, and five data types. It includes integral floating point, packed decimal arithmetic, character string manipulation, and context switching instructions. Up to 15 operations combine in a single instruction. This instruction set has the same mnemonics as the PDP-11. In addition, a system compatibility mode provides the PDP-11 instruction set except for privileged and floating point instructions. An optional accelerator performs a double-precision floating point 64-bit addition in 1.4 µs.

Four hierarchical protection modes, each with read-write access control, support paging memory management. The system contains sixteen 32-bit general registers and 32 interrupt

priority levels-16 each for hardware and software. It has two standard clocks-programmable real-time and time-of-year with battery backup for automatic system restart.

A synchronous backplane interface (SBI) serves as main control and data transfer path. Connection of high speed PDP-11 peripherals including high performance mass storage devices with parity checking is enabled by use of up to four massbus buffered interfacing adapters; a single UNIBUS interfacing adapter allows connection of conventional PDP-11 peripherals. This compatibility permits the VAX-11/780 to be used also as host development system for RSX-11M and -11S operating systems running on PDP-11s. Throughput rate for MASSBUS to the SBI is 2M bytes/s; via unibus it is 1.5M.

A diagnostic console subsystem includes an LSI-11 microcomputer with 16k bytes of read-write memory and 8k bytes of read-only memory (ROM), as well as a single floppy disc and an LA36 teleprinter. Use of this console is claimed to permit simplified bootstrapping; improved distribution of software updates; and fast, online, local or remote diagnosis. It provides automatic consistency and error checking to detect abnormal instruction uses or illegal machine conditions. Integral fault detection and maintenance features detect errors on memory or discs, record recent bus activity, detect hung machine conditions, and allow restart recovery.

Among the automatic monitoring activities are parity checking for data integrity on the synchronous backplane interface, bus adapters, memory cache, address translation buffer, and error checking and correction on memory. In addition, operating system consistency checks, redundant recording of critical information, uniform exception handling, online error logging, online diagnostics, and unattended automatic restart are performed.

Programs as large as 32M bytes are enabled by a full demand paging operation. Multiple functions are maintained through the VAX/VMS operating system. Program development capabilities include two editors, language processors, symbolic debugger,

librarian, and utilities.

Memory management facilities are user-controllable. Pages of a program or an entire program can be locked in memory for time-critical applications. There are 32 levels of software process priority for fast scheduling.

Both Digital control language (DCL) and master control routine (MCR) language are used. As with other PDP-11s, these languages implement VAX-11 FORTRAN IV PLUS. VAX-11 MACRO, PDP-11 COBOL, and PDP-11 BASIC-PLUS-2. FORTRAN and MACRO generate 32-bit native code. FORTRAN can concurrently execute a subset of the PDP-11 instruction set in its "compatibility" mode. A file and record management facility provided by the operating system permits users to create, access, and maintain data files and records with full protection. Such facilities include sequential and relative file organization, sequential and random access. Networking capabilities are supported for task-totask, access and file transfer, and downline loading.

Batch capabilities include job control, multistream, spooled input and



Multiprogram capability of Digital Equipment Corp's VAX-11/780 32-bit computer system enables access by up to 64 interactive users simultaneously. Intended for data processing, large laboratory, and research center applications, the system contains virtual memory addressing capability more than 4G bytes

output, operator control, conditional command branching, and accounting. Nonprivileged tasks can be run with little or no modification as a result of an applications migration executive.

Three standard configurations, available to both end-users and oems, are offered. Deliveries are scheduled to begin in early 1978, with volume pro-

duction in mid-year.

A minimum system configuration consists of the VAX-11/780 CPU with 128k bytes of main memory, LA36 DECwriter II teleprinter, two RK06 14M-byte disc drives, and a multiplexer with eight EIA terminal connections and vax/vms operating system-priced at \$128,000. The next configuration contains 256k bytes of main memory, an RM03 67M-byte disc drive, a TE16 800/1600-bit/in (315/630-bit/cm) magnetic drive, plus 8-line multiplexer and operating system—at \$153,000. Top configuration has 512k bytes of main memory, an RP06 176M-byte disc drive, a TE16 tape drive, plus multiplexer and operating system-at \$185,-

All systems have provisions for additional memory and peripherals. It is expected that the majority of systems, including chosen additional memory and peripherals, will sell in the \$200,000 to \$300,000 area.

Circle 140 on Inquiry Card

Portable Magnetic Tape Recording System has Bandwidths to 2 MHz

SE7000M tape recording systems are claimed by EMI Technology, Inc, 55 Kenosia Ave, Danbury, CT 06810 to bring the performance of fixed installation systems to field applications in a convenient portable form. The units have direct record/reproduce bandwidths to 2 MHz, FM recording bandwidths to 500 kHz, 7-track (0.5"tape) or 14-track (1.0" tape) channel capacities, and record at 30k bits/in with a 2.5M-bit/s serial transfer rate. Costs are claimed to be from 20 to 60% less than those for units with approximately comparable performance.

FM bandwidths include IRIG intermediate (dc to 40 kHz) and wideband groups I (dc to 8 kHz) and II (dc to 500 kHz). Eight carrier frequencies range from 1.68 to 216 kHz (INT), 3.38 to 432 kHz (GP I), and



SE7000M recording systems from EMI Technology provide fixed installation performance in portable unit. Equalizers and filters enable tape speed switch to be used like oscilloscope; calibration controls are minimized for simple operation

14.0625 to 900 kHz (GP II). A \pm zero offset doubles effective dynamic range when recording unipolar data, and a squelch circuit holds the reproduce output at zero until the transport reaches synchronized speed.

FM mode input sensitivity is 0.5 to 10 V peak for 40% carrier deviation, linearity is $\pm 0.5\%$, and harmonic distortion is less than 1.3% for all tape speeds. Input impedance is 20 k Ω (INT/GP I) and 75 Ω or 1 k Ω (GP I/GP II), output impedance is less than 10 or 75 Ω , and the output signal is \pm 1.5 V into not less than 1 k Ω or 75 Ω .

Tape transport is a balanced tension system combining easy threading with operational performance. It provides eight switch-selectable speeds—0.93, 1.0875, 3.75, 7.5, 30, 60, and 120 in/s (2.37 to 304 cm/s)—and the capstan can be phase-locked to an external oscillator for nonstandard speeds.

Signal conditioning electronics include, in addition to input channel conditioners that operate at all tape speeds without adjustment, built-in equalizers and filters for all tape speeds in the reproduce circuits; this permits the operator to use tape speed switch like an oscilloscope time-base control, without the need for substituting plug-in conditioning modules.

Controls have been reduced to the minimum and are mostly of the set and forget type. Included are push-button fast forward and reverse, run forward and reverse, record, stop, power, ready, tape/tack, INT/WBI, WBI/WBII, flutter comp, local/remote,

and a rotary tape speed select switch. A built-in FM calibrator with digital meter permits calibration of the complete FM channel without jumpers.

For high density digital recording (HDDR), a compact rack of electronics is available for recording serial or parallel data from TTL or balanced line sources, in either NRZ-L or delay modulation (DM-M) codes. A phase-locked oscillator, adjustable over a 2.5:1 range, permits use of any external clock frequency. With this arrangement an optional 14-channel stuffer can be used for continuous recording of parallel data at an increased record data rate to allow insertion of a block marker for subsequent deskewing.

Circle 141 on Inquiry Card

Graphics Controller Uses Compatible RAMs For Variable Resolution

The MTX-512 graphics controller, designed by Matrox Electronic Systems, PO Box 56, Ahuntsic Sta, Montreal, Quebec H3L 3NS, Canada, exploits the compatibility of 16-pin 4k, 8k, and 16k dynamic RAMS to provide selectable resolutions of 256 x 256, 256 x 512, 512 x 512, and 256 x 1024 on a single controller card. Cards are designed to interface mini- or microcomputer to a TV-type monitor and produce a graphics raster that extends close to the physical limit of the scan monitor.

Variable resolution is achieved through the use of circuit design techniques which permit higher density RAMS to replace lower density RAMS. Thus, the 256 x 256 version uses 16 4k dynamic RAMS, the 256 x 512 display uses 8k devices, and the 512 x 512 and 256 x 1024 units utilize 16k versions. Standard TV interlacing, produced when lines of one field or scan fill in spaces between lines of the previous field, can effectively double vertical resolution. Vertical interlace is used to produce the 512 x 512 display; the 256 x 1024 display uses a proprietary horizontal interface technique, which permits horizontal resolution to be doubled while using standard speed memories and logic.

The unit's x-y addressing scheme uses two directly addressable registers to select a given dot, allowing two computer memory locations to address up to 262k bits of refresh memory. The X register occupies the 10 LSBS of a 16-bit data word for a max-



In a world of claims and counterclaims, one thing is clear. EMM SEMI is still in the lead. Of course, we not only had a healthy head start, but we field a whole family of 4K static RAMs.


We delivered the industry's first 4K static RAM in 1975, a full year and a half before anyone else. We are now delivering 7 basic static RAM types with many versions

of each, and producing them at a greater monthly rate than our nearest competitors combined. By now we have more 4K static RAMs operating in a wider range of customer equipment than anyone else in the semiconductor memory business - from 10 Megabyte IBM add-on memory systems to hobbyist microprocessor kits.

Whatever your application, from mass storage to telecommunications, from medical electronics to toys and games, chances are there's an EMM SEMI static RAM just right for you. Please call or write today for full details - and ask about our byte oriented RAMs, too.

Memory at work EMM SEMI, Inc.

a subsidiary of Electronic Memories & Magnetics Corporation • 3883 N. 28th Avenue, Phoenix, Arizona 85107 • (602) 263-0202



imum resolution of 1024 points. The LSB of X is ignored for 512-point resolution and two LSBs of X are ignored for 256-point resolution. This allows software written for 1024-bit resolution to work for lower resolution units. This principle also applies to the Y register.

By stacking identical multiple boards, color/gray scale systems can be obtained. Each card's sync generator acts as master or slave; a master card can control up to 24 slaves. When a system consists of a master and a number of slaves, video outputs of each card are synchronous, allowing users to combine outputs to form a customized color/gray scale system with up to 24 bits/picture element.

Cards are available for the PDP-11 Unibus and the LSI-11 bus which operate using the 16-bit PDP-11 instruction set. It is possible to interface either card to other computers through a standard 16-bit parallel I/o port. Any card can be user-programmed to produce 256 x 256, 256 x 512, 512 x 512, or 256 x 1024 point matrix. American or European TV standard operation is also field programmable.

Circle 142 on Inquiry Card

Fortran Processor Subsystem Performs 1.5M Operations/s

An Attached Fortran Processor (AFP) that can execute FORTRAN programs at rates of up to 1.5M operations/s—as much as ten times faster than the B 6807—has been developed by Burroughs Corp, Detroit, MI 48232 to provide the high speed processing necessary for engineering and scientific problems. With the AFP attached to any B 6800, 6700, 7800, or 7700 computer, users gain the performance necessary for mathematical operation while retaining the system's business-oriented capability.

The AFP serves as a mathematical program-oriented subsystem to a computer which acts as the system manager. Operating under the master control program, the system manager provides an automatic control environment for the AFP and, at the same time, performs business-related data processing tasks. The AFP is programmed exclusively in FORTRAN.

Advantages of using a dedicated subsystem for high performance engineering and scientific processing lie in the structures of the problems to be solved. Architecture of the AFP is designed for processing large individual programs in which sets of data are operated on repetitively.

Such programs execute most efficiently when they have complete access to processor logic, main memory, and secondary storage devices.

Three major elements make up the total system: system manager, Fortran processor, and file memory. A large standard data processing system, the system manager provides an automatic control environment for the AFP, and is responsible for compiling application programs, scheduling jobs, providing data 1/0, controlling peripherals, monitoring errors, and performing online system diagnostics.

The system manager exchanges supervisory information with the AFP via two I/O channels linking the AFP

The P400 makes excuses obsolete.

A new product comes on line and the circuit boards start piling up. This is when the excuses begin:

"I can't get near the


computer."

4

"I need more programmers."
"I just got schematics last
week."



It's a difficult time for a test engineer because the success of an important product can hang in the balance.




But Teradyne's P400 Automatic Programming System has changed all that. Used with L100 series test systems, the P400 creates the entire test program



automatically. It gives you all input patterns, provides all diagnostic data, and resolves all races. It cuts programming time from weeks to days. And it does it all without tying up the computer on your production tester or increasing your programming staff.


Suddenly, new programs can be ready on time, even in the face of the tightest schedules. And even for the most complex boards. Just as important, the P400 spares you all the boring work it usually takes to deliver new programs. You get typically better than 95% fault coverage simply by using the telephone to access a large computer containing the P400 software.



The P400 Automatic Programming System.

Now there's no reason for being late.

And we think that's the way you want it.





Most graphics terminals are too dumb for words.

Even expensive models get tongue-tied when it comes to alphanumerics. But now there's a bright new graphics terminal that has a lot to say for itself.


Alpha-graphics: the perfect combination.

It's the Hewlett-Packard 2648A alpha-graphics terminal. For just \$5500,* it will dazzle you with a



virtuoso display. You'll see zoom and pan, area shading, pattern definition, rubber band line, scientific plotting and graphics text composition. Having independent memories for graphics and alphanumerics, you can do auto-plots with or without words and figures on the screen.

And when you need a smart alphanumeric terminal for on or off-line work, stay right where you are.



How smart is smart?

Ever seen a graphics terminal scroll 200 lines of interactive dialogue? And store up to 220K bytes of data (words and pictures) on twin cartridges? And cut out repetitive routines by storing up to 80 characters on each of eight "soft keys"?

The HP 2648A can also edit with the best of them. Communicate with a computer at rates up to 9600

baud. And accept a plug-in forms drawing mode to generate just about any form your company uses.



Strong as well as intelligent.

Like all our terminals, the HP 2648A has a clean, tough, modular design. Open it up like a suitcase, and you'll see the neat row of plug-in PC boards.

That makes it easy to add options or take care of maintenance. Not that downtime is a problem. Our terminals have such a good track record that we've lowered our maintenance price three times in the past two years. When you do need service, more than 1000 Systems and Customer Engineers worldwide are ready to take care of you. So why settle for any dumb graphics terminal when ours can figure in your picture? See for yourself by calling the Hewlett-Packard office listed in the White Pages. Or send us the coupon and give our 2648A alpha-graphics terminal a screen test.



Yes, give me the good words (and pictures) on the HP 2648A terminal.

☐ I'd like a demonstration. ☐ Send me information.

Name Title
Company
Address

City/State/Zip

Phone

Mail to: Ed Hayes, Marketing Manager, Hewlett-Packard Data Terminals Division, 19400 Homestead Road, Dept. 1214, Cupertino CA 95014.

CIRCLE 21 ON INQUIRY CARD

*U.S. domestic price



42801HPT5

processing take place concurrently, maximizing throughput and requiring a minimum of overhead.

To support use in distributed processing systems and provide general capability to communicate with remote systems and support remote 1/0, the processor provides a communications option. Implemented with a special 1/0 processor, which occupies one 10P slot in the CPU, the option supports one or two bisynchronous lines at speeds of 1200, 2400, 4800, or 9600 baud. Protocols include 2780/3780 emulation, 3270 emulation, remote 2246P workstations, and HASP.

ANSI-74 COBOL, RPG-II, and BASIC languages, plus an assembly language, containing most instructions of the IBM 360/370, are supported by the system. Programs can be written incorporating all four languages, and programs based on each can be run simultaneously on the system at different workstations.

An interactive text editor, symbolic debug facility, three utilities for data entry/file maintenance, and utilities for sort/merge/copy are provided. Other features include automatic program sharing, automatic data compaction, print spooling, memory error correction, and an ID/Password security system.

Circle 146 on Inquiry Card

Dispersed Processor Offers Concurrent Data Entry/Communication

The diskette-based 1500 dispersed processor offers intelligent data entry and local data processing capability, as well as concurrent communication with remote location. The system may operate standalone or in conjunction with a host computer.

In the system, Datapoint Corp, 9725 Datapoint Dr, San Antonio, TX 78284, incorporated an advanced processor, typewriter-style keyboard, two diskette drives, high speed video display, and integral communications capability. The display presents 24 lines x 80-char on a nonglare green-on-black screen; an inverse video feature can be programmed to highlight fields such as error messages or program status indicators.

The processor contains 32k bytes of RAM and an additional 4k of system ROM. Processor and support circuitry as well as system memory are all on a single board. System memory provides complete support for communications 1/0, display and keyboard logic, an optional serial printer, and diskette 1/0.

Software for intelligent data entry, local data processing and storage, and communications is provided. DATAFORM^R OF DATABUS^R programming languages and the diskette operating system allow the system to verify data entered before they leave the system. The operating system dynamically manages the internal flow of data, maintains system reliability and security, and provides for maximum usage of system and associated devices.

With the addition of an appropriate communications modem, the integral communications interface facility supports communications with other systems. Using either an IBM 3780 emulator or datapoll communications software, the processor can transmit data at speeds to 4800 baud in synchronous mode. Under the datapoll package the system acts as a slave processor, automatically transferring text files to and from a central processor.

Under the multitasking operating system, the system can run two programs at once. A primary application (data entry or processing) can proceed at the same time as a secondary program (communications or print spooling).


Circle 147 on Inquiry Card

Smart Data Logger Uses Microprocessor To Add Features

System 9300, a smart data logger, handles thermocouples and voltage side-by-side, autoranges, produces engineering units, averages, and provides up to four different alarm levels per channel. The unit, announced by Monitor Labs, Inc, 4202 Sorrento Valley Blvd, San Diego, CA 92121, is built around the F8 microprocessor, which enables it to implement in software many functions previously handled by hardware.

The unit features simple setup and daily operation through a Rom-stored application program. Operator entered data are stored in RAM, and an EAROM program save option provides backup during power outages. The operator programs the unit via a 20-key pad, responding to English language questions displayed on a 20-digit alphanumeric display.

Thermocouple linearization and compensation are handled by the application program, which accepts operator-entered slope and intercept corrections for each channel. Alarm and limit levels are also implemented in software. Each channel has four individually programmable limits. The



Handling temperature and voltage side by side, 9300 series data logger from Monitor Labs uses ROM-stored program to provide easy setup and daily operation

operator specifies which devices will output under alarm conditions, including reporting by exception.

The unit precisely measures analog inputs from 1 μ V to 12 V, either with autoranging or by selecting the 30-mV, 300-mV, 3-V, or 12-V range for each channel. Resistor networks are available for measuring current or higher voltages.

A universal reference for thermocouples is located on each isothermal connector. Each channel is digitally compensated, allowing adjacent channels to mix thermocouple types and voltages, while maintaining 0.1-degree resolution and high accuracy.

Data on any or all 40 channels can be averaged through digital accumulation and division. Sample period is selectable from the keyboard, allowing up to 999 samples/average. Invalid data are automatically excluded from the average, which is computed for the remainder of the current period following a power outage.

(Continued on p 42)

There may be a µP board out there we can't test.



But we haven't found it yet.

Chances are we won't.
Dozens of different µP boards have run through our new 3040A Logictester™ in the first six months, with 100% success.

You never know what our rapidly changing technology will produce tomorrow though, and you need assurance your tester can handle it. The 3040A delivers that confidence, and more.

Like testing at full data and clock rates. Four bi-directional buses handled at one time. And

four processors test your board's µP instructions, RAMs, ROMs, PIAs . . . all at multi-MHz rates!

All this and programs finished in days, not months.

To us, the most important consideration is that boards passing our tester will work in your product... every single IC and component. That's confidence, and it keeps both of us in business.

If confidence is important to you, look into the Fluke logic testers priced between \$13,000 and \$60,000. Features like dynamic LSI diagnostics and Autotrack,™ the guided clip system that reduces your operator's probing time and error, and saves money.

We've got more logic test systems operating in the world than anyone. For data out today, CALL COLLECT (415) 965-0350. Or, circle the number below for general data.

For a complete technical

package, drop a line on your company letterhead to Don Harter, Fluke Trendar Corporation, 630 Clyde Avenue, Mountain View, California 94043.

In Europe, write Fluke (Nederland) B.V., P.O. Box 5053, Tilburg, The Netherlands. Or, telephone: (013) 673973. Telex: 52237.



Standard equipment includes a 4½-digit digitizer, battery-protected clock, 16-column alphanumeric printer, 20-digit alphanumeric display, dual scan modes, and monitor mode. The system expands to 1040 inputs with good channel-to-channel isolation through low thermal switches. High normal mode rejection ratio is supplemented with an optional multipole active filter.

An optional monitoring feature called Mag-Check immediately verifies that each data record is properly written on magnetic tape. This feature uses a built-in buffer controller which reads what is written and compares the record to data initially placed in the write buffer. If an error is detected, data are erased and the record is rewritten.

Enhanced Process Control System Allows Central

Control with Color CRTs

Circle 148 on Inquiry Card

Contending that CRT consoles will supplant conventional analog displays in industrial-instrumentation installations, Honeywell Inc, Process Control Div, 1100 Virginia Dr, Fort Washington, PA 19034 announced enhancements to its TDC 2000 process control system. These additions to the system allow centralized control with color video displays, and can be applied to simple process units or to complex plant installations.

System enhancements include historical and real-time trend recording, alarm annunciation and display, logging, CRT and keyboard interface to intelligent multiplexers, and digital start/stop operations. System security is guaranteed with Uninterrupted Automatic Control which automatically detects malfunction of from one to eight controllers, alerts the operator, switches in a reserve controller, and resumes control of the process.

The distributed control concept provides centralized operations with three levels of capability: basic, supervisory, and total. All three provide automatic transfer of control to reserve controller devices and redundant process-interface units, and permit remote placement of control and interface equipment.

A basic configuration supplements fundamental control interfaces with a logger/printer. Three video stations replace single-function panel mounted devices for alarming, recording, indicating, and timekeeping. On the supervisory level, the center consists of one supervisory station and two or three basic stations. Used when enhanced display and computational functions are required, it performs alarm-scan functions as well as data handling and control. The total approach is used when complex programmable computing capability is needed.

Circle 149 on Inquiry Card

Vision System May Allow Computers to Handle Inspection Tasks

If computers can be given "eyes," they will be able to process visual data, and can then be used to handle inspection tasks as well as jobs involving the transfer and assembly of parts. Scientists at the General Motors Research Laboratories, General Motors Technical Center, Warren, MI 48090, after several years of investigation, have formulated two approaches which were reported at the Fifth International Joint Conference on Artificial Intelligence in Cambridge, Mass recently.

Described by Drs Michael L. Baird and Walton A. Perkins, each of the two approaches uses a television camera. Images picked up by the camera are digitized and relayed to a computer. From this point, however, the methods differ.

Dr Baird's system uses a program to sharpen the image so that the computer can rapidly and reliably find non-overlapping parts even on visually confusing surfaces which tend to camouflage the parts' outlines. Using digitized data (a mosiac of minute squares in shades of gray), the computer works through a sequence of image enhancement operations to silhouette the part and emphasize its outline. From this well-defined outline, position and orientation of the part can be calculated.

The computer vision system presented by Dr Perkins can recognize and determine the position of several objects, even if they overlap and are partially obscured. To achieve this, the computer is shown the parts it is to recognize. It analyzes each part, computes geometric properties of its boundaries and internal holes, forms a model, and stores these data. Characteristics of objects which the camera views are then matched to the stored data, allowing the system to recognize those parts that are similar even when partially obscured. When a part is found, its position and orientation is determined.

Claimed to be the first industrial computer vision system of its kind, SIGHT-I, installed at GM's Delco Electronics Div in Kokomo, Ind, locates and calculates the position of transistor chips during their processing. The computer-camera system also verifies a chip's structural integrity and rejects those that are defective.

According to the scientists, the next step is to couple the computer vision system with a manipulator, so that it can "do something" with the recognized part. This manipulation problem is currently under study at the Research Laboratories.

Circle 150 on Inquiry Card

Document System Adds Word Processing To DECsystem 10

An automated document management system (ADMS) has been developed by Adapt, Inc, 450 Sansome St, San Francisco, CA 94111 specifically for the DECsystem 10 and 20. With ADMS, users of these systems will be able to manage an unlimited number of large and small documents interactively, thereby adding the dimension of word processing to their data processing capabilities.

The package, a user-oriented text processing language that allows flexibility in processing of documents, justification/hyphenation, automatic page makeup, page size flexibility, footnoting, universal commands, and automatic numbering as well as photocomposition, typewriter terminal, or microfilm output. Information can be accessed directly from a data base and converted into camera ready pages. The system is suited for interfacing with most data processing systems presently in use, and will not greatly reduce the total processing power of the system.

Circle 151 on Inquiry Card



Our family gives you a flat answer.

Our new flat cable connector family has both standard and stackable sockets, PCB connectors and headers, all designed for lowest total applied cost.

In socket connectors our BA Series gives you a low profile package with the option of either open or closed cover design for both end-cable and throughcable applications.

Our BD Series stackable socket line concept permits stacking two connectors on a wire-wrappable post.

For direct solder applications our BC Series handles PCB connector needs.

Featured with the product family is a simple universal termination system designed for minimum tooling cost.


For your header applications our low profile BB Series line is available for both vertical and right-angle mounting in solder or wire-wrappable designs.


Contact GTE Sylvania, Connector Products Operation, Box 29, Titusville, PA 16354. Phone: 814-589-7071.

Remember, good connections run in our family.



HIGH RELIABILITY






DIPSOCKETS for the price you're paying for junk!

Robinson Nugent "side-wipe" DIP sockets make 100% greater contact than any edge-bearing socket on the market.

This 100% greater contact with the wide, flat surface of your IC leads is your guarantee of unmatched reliability. This RN "side-wipe" contact provides constant low contact resistance. No edge-bearing contact can possibly deliver this long term dependability. This designed-in reliability of RN DIP sockets is your assurance of trouble-free IC interconnects—yet they cost no more than ordinary sockets.

Put an end to troublesome junk sockets! Write today for catalog and informative book "What to Look for in IC Interconnects." It's free from RN—the people who make more kinds of high reliability IC sockets than anyone.





They're even packaged for high reliability.

"Protecto-pak" packaging delivers consistently perfect RN sockets to your production line—for automated or manual assembly.



High reliability IC sockets . . . we've got 'em all!

Computer System Uses Editing Terminals to Speed Braille Production

A computer configuration containing two 4070 central processors will be used in the production of braille literature. Supplied by GEC Computers Ltd, Elstree Way, Borehamwood, Hertfordshire WD6 1RX, England, the equipment will be used in the Royal Institute for the Blind's printing center to produce a range of braille books for educational, vocational, and recreational purposes.

The configuration will include two cpus, each with 192k bytes of core memory; four 4.8M/4.8M-byte fixed/removable cartridge disc units; two 300-line/min printers; two 9-track 800-bit/in magnetic tape units; four digital I/O devices; two control thermal printers; paper tape unit; four magnetic tape cassette decks for

braille coded tapes; and two cassette decks for maintenance and diagnostic programs. Input and text editing terminals are Lynwood displays. Braille editing terminals and manual cassette encoders were specially developed by Sigma Electronic Systems.

Operators at 16 text entry visual display terminals key in text from English originals. The computer system directly accepts these inputs and translates data into braille output coded onto magnetic tape cassettes. These cassettes control embossing machines that automatically punch the braille characters onto zinc plates for use on a printing press.

Visual display terminals allow operators to edit text on entry. Separate refresh graphics display terminals are used to edit the braille characters prior to committing the output to embossed paper or zinc.

Circle 152 on Inquiry Card

Interactive screen formatting allows rapid implementation by new users.

Screen form designers format their screen on the CRT face as desired. Data entry fields and user prompts or cues are marked with a special keyboard character. The entire screen face is sent to the transaction controller which responds with a series of interactive fill-in-the-blanks forms, which solicit information for input data validation when the system is put into service.

Online testing allows forms to be completely tested before they are used. An online utility transaction called modify allows specific changes to be made without affecting the rest of the screen, and without changing the COBOL program. These features shorten development cycles and speed system maintenance.

ITRAC runs as a series of related tasks under the operating system; users can also run other online or batch tasks, including the multiterminal monitor. Communications services transparent to the user are provided through ITAM with the system's line control module. System requirements are a model 7/32 or 8/32 processor with at least 192k memory, 10M-byte disc, communications, and a model 1200 terminal.

Circle 154 on Inquiry Card

Report Writing System Eases Access to Public Data Bases

A simplified means of obtaining information from demographic, economic, or corporate data bases, the Qwick Query report writing system is available on General Electric's MARK III^R remote computing service. The system has access to several public and proprietory data bases maintained by CACI, Inc, Washington, DC, which were previously accessible only after programming report requirements, and is suitable for use in accessing corporate records.

To retrieve information and format reports from office terminals, users define categories of information in a data dictionary according to their own specifications. Complex calculations or comparisons can be reported by answering queries made by the system.

Dictionaries are available for Site II, a demographic data base of population and housing information categorized by ZIP code, county, state, and metropolitan statistical area, and for County Business Patterns, which lists vital statistics of commercial organizations by county. Both are derived from Bureau of Census data.

Circle 153 on Inquiry Card

Transaction Controller Allows Interactive Screen Formatting

A transaction-oriented software monitor developed by Interdata, Inc, a unit of Perkin-Elmer Data Systems, 2 Crescent Pl, Oceanport, NJ 07757 enables online transaction processing systems to be developed, imple-

mented, and maintained. The Interdata Transaction Controller (ITRAC) runs on the company's 32-bit systems, and features compatibility with COBOL language, interactive screen formatting, and online screen-form testing capability.

Compatibility with COBOL enables application programmers to focus on the application, providing high productivity and avoiding training costs.

Business Software Adds Capability to Color Control Systems

Software packages for use with computerized color control systems provide additional production control capabilities and operating cost reductions. With the Cogit system, the computer system from Applied Color Systems, Inc, PO Box 5800, Princeton, NJ 08540 will generate production batch tickets, formula explosions, and a current product cost analysis as well as give detailed information on quantities and costs of raw materials onhand and onorder, work-in-process, and finished goods.

Interactive operation between operator and video terminal provides detailed descriptions of various possible responses to program questions. The software monitors all phases of color matching operations including modification of production formulas complete with manufacturing instructions, explosion of formulas to production quantities, and generation of complete batch tickets.

Announcing a small breakthrough.

TI's compact Model 763 send/receive terminal with built-in bubble memory.

The new Silent 700* Model 763 Memory Send/Receive Terminal is a data entry breakthrough in a small package. It's the table-top terminal with powerful ASR capabilities...all built-in.

Magnetic bubble memory.

Built-in bubble memory means you can enter and edit data off-line, then transmit it when you want to.

The bubble memory is expandable, in the terminal, to 80K bytes. And it's non-volatile, so it retains data even when the power is off.

With the 763 you have the standard ASR functions such as playback on/off, record on/off, rewind playback and record, and playback forward and reverse. And the builtin, easy-to-use text editor brings new power to data handling.

Silent 700 Performance.

Virtually silent 30 characters-persecond printing, a hard copy you can keep, and excellent value is what the 763 offers with its *Silent* 700 heritage.

It's microprocessor based, which means fewer components for more reliability, less weight and size.

There's a keyboard that's as familiar to use as a standard typewriter, and there's TTY current loop or EIA interface standard.



The 763 send/receive terminal...a breakthrough in a small package.

Backed by TI.

When you buy from TI, you are backed by our worldwide network of factory-trained service personnel. And by the resources of Texas Instruments...the company that makes technology affordable.

To find out how the 763
can benefit your business,
fill out and mail the coupon,
or call your nearest TI sales
office, or Terminals and Peripherals

Marketing at (713) 491-5115, extension 2124.

TEXAS INSTRUMENTS

Yes! I am interested in the 763 Memory Te ☐ Please have your representative call me ☐ Please send me more information.	
Name	
Title	
Company :	
Phone	
Address	
CityState	Zip
Mail to: Texas Instruments Incorporated M/S 784, Houston, Texas 77001	, P.O. Box 1444,

*Trademark of Texas Instruments

Copyright©1977, Texas Instruments Incorporated

TEXAS INSTRUMENTS.

DIGITAL CONTROL AND AUTOMATION SYSTEMS

Cargo Vessel Load Stresses Simulated by Multipoint Computer Systems

When Spanish cargomasters loaded gold and silver ingots aboard their tiny vessels for the long trip from the Americas to Europe, they distributed the weight as best they could by instinct and by rules based on experience. Yet many of those cargo ships are still being sought by treasure hunters hoping to salvage their bullion. Instinct and experience did not always suffice against hurricanes and unexpected shifts of unbalanced cargoes.

Even in more modern days, on much bigger vessels, manual calculations—and experience—were the chief tools when deciding where to store certain cargo and what cargo to place in specific ship locations. On the whole, those methods were successful. Ships managed to move from port to port safely—if not always comfortably.

Today, however, the situation is drastically different. Merchant ships are designed and built for specific types of cargo. Each class of vessel—containership, RO-RO (roll on-roll off or trailer carrying) ship, drilling vessel, oil tanker, bulk carrier, O/B/O (oil/bulk/ore) carrier, LASH (lighter aboard ship) vessel, ore carrier, and "ordinary" cargo ship—has unique lading requirements.




Fig 1 Typical LOADMAX-200[™] system. "Live" mimic diagram configuration at top of front panel is for a trailership (designated RO/RO for roll on/roll off). More than 100 cargo locations are specified and considered in calculating shear force and bending moment limits. Tonnage information for cargo to be stored at each specified location is entered through keyboard. Microprocessor constantly updates overall data

Such special problems that must be considered in lading involve hull stresses, stability, and trim. Stability is particularly important with the relatively new LNG (liquified natural gas) carriers because of the cargo's low specific gravity.




Fig 2 System data flow diagram. Ship locations and data on cargo to be stored at those locations are entered by cargo officer through keyboard on front panel. These data interact with data on characteristics of the ship (stored in ROM) to determine effects proposed loadings would have on ship's balance. Shear force and bending moment effects as well as summary of total weight at each location are displayed on front panel



Still another factor involved with all these ships, although not concerning safety, is the time required to unload, reload, and return to sea. This consideration can have a strong effect on economics and profit structures.

Digital Loading Computer System

One method of accurately determining proper loading and stability for a vessel is LOADMAXTM (a commercial designation for load monitoring and control system). Basically a digital computer system with unique display panels (mimic diagrams) for each vessel (or class of vessel when applicable), LOADMAX-100 computes shear force, bending moment, draft, and displacement (or deadweight). A more sophisticated model, the -200, performs stability calculations in addition. The system operator or ship's cargo officer instantly knows the effect of any suggested amount of cargo on a ship before that cargo is loaded aboard.

Each system, designed and built by Raytheon Co, Maritime Systems Dept, W Main Rd, Portsmouth, RI 02871, is about as simple to use as a desk calculator yet retains the value of the cargo mate's experience and knowledge (Fig 1). The "live" mimic diagram for the vessel being loaded depicts each storage and ballast area on that vessel. Knowing the weight and dimensions of each cargo unit to be loaded, the cargo officer can address

any one of the many individual locations and "load" the cargo through a small keyboard.

Data on longitudinal and vertical centers of gravity, hydrostatic characteristics, and stress limits for the vessel and for each addressable location are maintained in non-volatile memory. This memory cannot be affected by operator error, line voltage fluctuations, electromagnetic or radio frequency interference, or other factors. Shear force and bending moment effects are calculated and compared to stress limits, then displayed on the front panel.

As the operator introduces tonnage data through the keyboard, that information appears on the display directly above the keyboard. When a tonnage entry is made for any storage location, the data are again displayed on the mimic diagram at the specified location. Cumulative effects of all loadings are shown on several displays at the lower center of the front panel. Excessive shear force or bending moment values and any load that causes stress limits to be exceeded are shown both numerically and graphically. Fig 2 indicates the data flow throughout the system.

In effect, a cargo officer has a continuous presentation of loading distribution, drafts, and resultant stresses throughout the vessel. This presentation is always current since the system also computes and displays distribution




Fig 3 Front panel variations. Lower left configuration is for ore carrier; upper center panel is for LASH (lighter aboard ship) and contains impact printer for hard copy record of data; lower right configuration for containership includes small calculator in bottom right corner and blank white space alongside printer for grease pencil notations. Other formats might include clipboard for notes on cargo to be loaded. Still other mimic diagram configurations are used for drilling vessels, oil tankers. oil/bulk/ore carriers, and liquified natural gas carriers

Sly buy.

A CRT that costs more but actually costs less.

At \$907,* our Perkin-Elmer Model 1100 CRT Terminal has been the price-performance leader in the CRT business for almost a year. Recently, some CRT makers cut their prices to a few dollars below ours.

Don't be fooled. The Model 1100 still costs less. Here's why.

Program debugging takes less time.

You'll save the few extra dollars you spend for our CRT the first time a programmer uses it for debugging a program.

The secret? A feature called Transparent Mode, which displays everything coming down the line-including control characters—and helps solve the most complicated host computer and communication link problems in seconds.

Operators make fewer errors.

You'll save money day after day with the Model 1100. Thanks to a 9 x 12 character matrix, the Model 1100 has crisp, clear, strikingly sharp characters. So operators see their work better and make fewer mistakes.

The Model 1100 also has a hooded display to eliminate reflection and end eyestrain. The display is right at eye level, too, which means no bending, no neck problems, and less fatigue.

All our standard goodies.

A big 12-inch screen, 128-character ASCII set, upper and lower case, Typamatic repeat on all keys, and a 24-line display are standard. The same goes for our exclusive No Hassle toll-free 800 number. One call gets you service. Where you need it. When you need it. Worldwide.

The Perkin-Elmer Model 1100. Feature for feature, it still costs less.

PERKIN ELMER | TERMINALS DATA SYSTEMS | DIVISION

Randolph Park West, Route 10 & Emery Avenue, Randolph, N.J. 07801 (201) 366-5550, TWX: 710-987-7913

(617) 890-1305 Boston, MA (312) 437-3547 Chicago, IL (214) 234-8880 Dallas, TX (714) 544-9093 Los Angeles, CA (201) 229-4040 Oceanport, NJ (408) 249-5540 San Francisco, CA

CIRCLE 28 ON INQUIRY CARD



DIGITAL CONTROL AND **AUTOMATION SYSTEMS**

and weight of fuel and other consumables on the ship. A recall function on the keyboard permits the operator to obtain a display on the keyboard window of the total tonnage entered for any tank or cargo area.

The graphic display provides a "curve" of computed values on a scale of 0 to $\pm 199.9\%$, in either shear force (SF) or bending moment (BM) as chosen by a pushbutton at the bottom of the panel. An "excess" alarm light for each point alerts the operator to stress values of ±100% or greater. The numeric display shows the values of shear force and bending moment simultaneously for any readout point selected by the operator by pressing one of the pushbuttons above the display.

Two sets of shear force and bending moment maximum values are stored in the permanent memory. One is for normal "still water" conditions, while the other allows temporary higher hull stress limits to be maintained during loading and discharge through use of a "port condition" mode. In addition, a "light ship" switch allows all tonnage entries to be cleared instantaneously, setting up the system for all new input.

The keyboard address code enables distinction among cargo, ballast, and consumable tonnages so that the system can provide separate totals for each. Data also can be input from punched cards, magnetic tape, discs, or




Fig 4 Interior view of system cabinet with cover raised. Printed circuit boards in subchassis at left rear of cabinet contain 8080A microprocessor for system, up to 16k of p/ROM in 8k units, 2k RAM, and separate 8080A microprocessor for printer control. Remainder of cabinet contains front panel/printer interface electronics and emergency power source capable of supplying memory power for up to four hours after main power fails or is disconnected

other devices. The system will reject illegal entries such as an attempt to make tonnage in a location a negative value by removing more than exists at that point.

We're showing Commonwealth

Chicago's Commonwealth Edison uses Ramtek color graphic displays for rapid display and status reporting of pipelines, valves, pumps, and other generating station data. A clear, color-coded display is updated every 5.0 seconds, giving nearinstantaneous visual scan-log-alarm functions, bar graphs, one-line piping diagrams, flow status, etc.

Before the Ramtek systems were installed, status reporting was by hardwired mimic boards, black and white alphanumeric CRTs and typers.

The Ramtek system not only costs less, it also allows more information to be presented to the operator in a form that is quickly and easily under-

stood. This results in better operator efficiency, and faster alarm reaction time. In Commonwealth Edison's 16,000 Megawatt system, thirty Ramtek color graphics displays will be utilized.





Fig 5 Block diagram of overall system. Processor interfaces to all switches, displays, and printer assembly via motherboard bus. Up to 16k bytes of p/ROM can be supplied (in 1k increments, 8k per board) as data base for permanent ship statistics and program. RAM maintains displays based on both p/ROM-stored data and information input through the keyboard. Processor CPU is 8080A microprocessor; separate similar microprocessor maintains line buffering, matrix character conversion, timing, and control of dot matrix printer

(Continued on p 54)



Commonwealth Edison monitors on-off, full-empty, flow status, and other parameters on a Ramtek FS-2400. Color is assigned for steam, water, no-flow, and oil flow to differentiate visually between materials and status. On the RM-9000, resolutions from 240 lines x 320 elements to 512 lines x 640 elements are available.

Commonwealth Edison is but one of a growing number of customers who are finding that Ramtèk's raster scan modular graphics and imagery systems are giving them the expandability, flexibility, and increased productivity they need. Besides the basic alphanumeric and imaging capability, Ramtek offers a wide variety of other functions including graphics—vectors, conics, plots, bar charts—pseudocolor, and grey-scale translation.

Ask about our new Ramtek RM-9000 family that is totally controlled by a standard 8080 microprocessor that really makes it easy to develop and download your own control software.

To find out more about how Ramtek can show off for you, call or write: Ramtek Corporation, 585 North Mary Avenue, Sunnyvale, California 94086 (408) 735-8400.



CIRCLE 29 ON INQUIRY CARD

Various mimic diagram panel configurations are attainable (Fig 3) to match the storage areas of practically any vessel. A maximum of 64 4-digit light-emitting diode (LED) individual tonnage displays and 16 digital summary displays can be included. Panel legends can be provided in any of several languages, and engineering measurement units can be either metric or British.

If desired, a Practical Automation, Inc miniature alphanumeric impact data printer can be included for a hardcopy record of desired data. It provides 20 columns in ASCII format on 2.25" (5.7-cm) paper. This printer routinely prints out a record of each entry made through the keyboard. On demand, it will print out a full tabulation of final entries by tonnage categories as well as a summary of final calculations and values of the percent of shear force/bending moment at each readout point. It will also print out a complete "sailing report."

System control is maintained by an 8080A microprocessor located on one of several printed circuit boards housed on a subchassis in the left rear of the system case (Fig 4). This microprocessor performs calculations and updates displays within 2 s for a complicated ship. It works out the balance of the ship, the relation of ship and load, the moment for the ship to get its trim in the water, and the total load weight to obtain mean draft. It also computes shear force/bending moments at each readout point along the ship between adjacent sections of the hull. Up to 16 shear force/bending moment points can be accommodated depending upon requirements of the application.

To perform these calculations, the microprocessor (Fig 5) selects data on each location from up to 16k bytes of electrically-programmable read-only memory (p/ROM) and combines them with information received from a 2k-byte random access memory (RAM). The p/ROM data base contains both program and permanent conditions of the ship that must be considered in all calculations. The PC board subchassis houses p/ROM boards (up to 8k/board in 1k increments) as well as the RAM board and a separate 8080A microprocessor board for the printer.

System accuracy is within 0.4% for draft and stability between light ballast and full load. Power requirements are 90 to 135/185 to 255 V, 47 to 63 Hz 1ϕ , 750 W max. Operating temperature range is 0 to 55° C if no printer is included (0 to 50° C with printer); nonoperating range is -40 to 70° C. Both ranges are at up to 95% relative humidity, non-condensing. Claims for the system include that the cost can usually be returned in a single voyage because of the increased earning capability. Circle 160 on Inquiry Card

DC&AS BRIEF

Multiterminal Systems Offer Variations of Supervisory Control

Redac 800, a microprocessor-based, supervisory industrial control system especially designed for transit, pipeline, and conveyor applications, is made up of combinations of Redac 800 master and Redac 80 remote communications terminals. Basic system and components are manufactured by Westinghouse Electric Corp, Industry Systems Div, 200 Beta Dr, Pittsburgh, PA 15238. Possible configurations include one master and several remote terminals; one master tied to several other masters, each of which is tied to several remotes; a 16- or 32-bit central computer tied to several masters, each in turn tied to several remotes; or a central computer tied directly to several remotes. Other components can be added to enable direct digital control.

A master terminal, using an internal microprocessor as controller, can handle up to 96 remote terminals on one to four party lines as well as a port to the central computer. A data logger can be included if desired. Either 25- or 32-bit word lengths can be


handled for remote addressing, data transfer, control, and checking. A single printed circuit board contains all logic, decoding memory, 16 status inputs, 16 analog inputs, and a 300-baud FSK modem.

Remote terminals are based on large-scale integrated circuit technology and are capable of withstanding harsh environments. A standard unit can operate at an ambient temperature of 50°C; a -20 to 70°C optional range is also available.

Before a remote terminal performs a control function, it checks with the master in BCH coding to be certain a received message is correct. Functions can be controlled with either latched or pulsed capability. Because a single-word interrogation system is used, the remote's 300-baud modem becomes equivalent to a 1500-baud system; however, for expanded operation, the terminal can be supplied with a 1200-baud FSK modem (capable of 9600 baud) or an RS-422 channel providing 76.8k-baud direct line switching.

The Z80° Program Development System.

A low-cost high performance programmer's work station.



The Z80-PDS is a portable, light-weight and modular computer system based upon the powerful Z80-CPU. It offers an ideal solution for developing and debugging Z80 programs. The PDS is available with options that allow easy expansion for additional I/O or memory. And the price for the basic Z80-PDS is only \$2850*. That includes:

- ☐ 16K bytes of RAM memory plus 3K bytes of Monitor PROM.
- ☐ Floppy disc drive with 300K bytes of on-line data storage.
- ☐ Serial I/O with R-232 or current

loop interface at rates from 110 BAUD to 19.2K BAUD—allows interconnection to any type terminal.

- PROM Resident I/O drivers, debug package and bootstrap loader.
- ☐ Powerful disk resident software including operating system, assembler, editor, file utilities and complete documentation and support.

☐ Optional items available:
• Printer I/O Port • Zilog Video
Monitor and Keyboard • PROM
Programmer • Up to 64K bytes of
Memory • Additional Serial or
Parallel I/O Ports.

Full disc compatibility with Zilog's larger Development Systems makes the Z80-PDS an excellent low-cost work station for adding program development power to microcomputer design teams.

For more information on Zilog's new Z80-PDS and complete product specifications, call or write us today.

*Excluding CRT.

10460 Bubb Road, Cupertino, California 95014 (408) 446-4666/TWX 910-338-7621

EASTERN REGION: (617) 667-2179 MIDWESTERN REGION: (312) 885-8080 SO. WESTERN REGION: (714) 549-2891 NO. WESTERN REGION: (408) 446-4666 EUROPE (ENGLAND): (0628) 36131/2/3







We can't afford to run out of ideas.

Make America smarter. Give to the college of your choice.

A shortage becomes a crisis only when there is a shortage of trained minds to solve it. And for today's manifold shortages, that means college-trained minds.

Colleges are facing an altogether different kind of shortage. They're having to drop courses, fire professors, close laboratories, limit libraries. Without your help, we'll have the ultimate crisis on our hands: a shortage of ideas.



Basic digital principles for classifying and distinguishing complex analog signals using computational algorithms are presented for system designers. These algorithms are particularly conducive to modification and optimization by computer software

Pattern Recognition: Basic Concepts and Implementations

Dennis Feucht

Tektronix, Incorporated Beaverton, Oregon

Clearly distinct but interrelated phases—data acquisition, pattern analysis, and pattern classification—evolve in a typical pattern recognition task. During acquisition, analog data (such as speech, environmental variables, or process changes) are gathered from physical sources (such as transducers, sensors, or detectors) and converted into a digitized format for computer processing. Then, the data are examined for recognizable structures or features that can be formulated for further systematic investigation. Typically, data analysis includes feature extraction, feature selection, and cluster determination. Finally, the analyzed information is best-fitted by computer algorithms to a known class of patterns for identification.

This discussion first defines the problems in pattern recognition, and then surveys the current approaches to decision-making and classification. Two techniques in particular—clustering and learning—are examined in detail.

Pattern Recognition Tasks

Three phases exist in the pattern recognition task: (1) acquisition of analog data and conversion to digitized data, (2) extraction of features (characteristics) from collected data, and (3) classification of data by these features. For example, physical variables, such as sound or light intensity, are converted by means of transducers (such as microphones, or photocells) into

electronic signals. Further processing converts these physical data into a digital form capable of being further processed by a computer (first phase).

For a complex waveform (such as sound waves), it is necessary to determine what features are most useful for classifying the waveform (second phase). If the pattern recognition (PR) system designer knows the classes, a set of features is selected (often empirically), and transducer signals are processed to extract the desired features. Consider the classification of speech signals. One approach is to select frequency ranges over the audio spectrum (100 to 3500 Hz for speech recognition), and then to measure how much of a given sample of a speech signal falls within each frequency band. These measurements are the features extracted from the speech signals. The system could extract these features with electronic hardware, or it could extract them by converting the speech signals first to digital signals and then to the appropriate features. For small computer systems, the latter approach is less attractive since it usually requires large amounts of memory to store digitized speech.

After the features are determined, a PR system must have some method to identify them as belonging to a particular class of patterns (third phase). The designer must develop a classifier, usually in the form of a set of decision functions. Decision functions may be determined by trying them on a set of patterns for which the classifications are already known, and then modifying them until a satisfactory classification results. This set of known patterns is called the training set. Another

set of known patterns which includes a typical selection of expected patterns may be used to verify performance; this is the test set. For a general pattern recognition problem, therefore, basic elements are a set of features, a set of classes, a training set of patterns, and a test set of patterns.

Pattern Vectors and Feature Space

Each feature can be considered a variable in n-dimensional space, where each feature is assigned to a dimension. If there are fewer than three features, this space, known as feature-space or pattern-space, can be illustrated graphically.

Each pattern appears as a point in pattern-space. When a pattern is described by more than one feature, the pattern is a multidimensional or vector quantity. If the features of n-dimensional pattern-space are designated as x_i , i = 1, ..., n, a pattern x is

$$\mathbf{x} = \begin{bmatrix} x_1 \\ x_2 \\ \vdots \\ x_n \\ 1 \end{bmatrix}$$

Here, the augmented "1" is included for compatibility with further developments involving decision functions. Pattern-space may be described by a vector of m pattern vectors (or matrix), X, where

$$\mathbf{X} = \begin{bmatrix} \mathbf{x}_1' \\ \mathbf{x}_2' \\ \vdots \\ \mathbf{x}_{m'} \end{bmatrix} = \begin{bmatrix} \mathbf{x}_{11} & \mathbf{x}_{12} & \dots & \mathbf{x}_{1n} \\ \mathbf{x}_{21} & \mathbf{x}_{22} & \dots & \mathbf{x}_{2n} \end{bmatrix}$$

and the prime (') after a vector indicates that it is transposed.

Pattern Recognition of Speech

The speech signal, which is a function of time, must be transformed so that it is a function of both time and frequency. At any interval in time, an analysis of the frequency components of the speech signal may be carried out using the Fourier transform for the analysis. The transform actually used is a modified version that can work on discrete data, such as a digitized speech signal. This modified form may be either the discrete Fourier transform (DFT) or the computationally more efficient fast Fourier transform (FFT). These transform a time-related signal, f(t), into a frequency-related function, g(f). To do this, however, the transform must use f(t) over all time. Since this is not possible, a time interval long enough to achieve a good approximation is adequate. Therefore, f(t) may be divided into regular intervals of time, and an FFT analysis done on f(t) within each interval. For speech, this interval is typically 10 ms long. Once the transforms are carried out, a 3-dimensional plot of the signal amplitudes as a function of frequency and time can be made (called a spectrogram).

If a frequency-amplitude cross-section for any time interval is plotted, amplitude peaks usually occur at several frequencies, known as formant frequencies. With their corresponding amplitudes, formant frequencies can be used as features of speech patterns. The first three formants are adequate for speech recognition.

Elemental speech sounds are known as phonemes. A phoneme is characterized by its formant frequencies and peak amplitudes, and also (more subtly) by the changes in these features as phonemes are produced in succession. A cross-section of pattern-space in the f_1 - f_2 plane (where f_1 and f_2 are the first two formant frequencies) may reveal two successive phonemes, p_1 and p_2 , which will appear as two different points in pattern-space. The transitional sound from one phoneme to another may take one of many trajectories in pattern-space to get from p_1 to p_2 . On a spectrogram (with only the peak amplitudes shown), the transitions appear as shown in Fig 1.

Decision and Classification Techniques

Once features have been extracted from the physical pattern, the pattern vectors can be placed in pattern-space as points. For different classes of patterns, clusters of points would be expected, where each cluster represents a distinct class. The classifier serves to determine to which class a particular pattern belongs.

Decision Functions

One approach to designing a classifier is to find a function which separates two classes, or several functions which separate three or more classes. These functions are called decision functions. In this discussion, only linear decision functions are considered; however, extrapolation of these concepts to nonlinear functions is fairly straightforward. In two dimensions, these functions are lines, and may be written in the form

$$x_1 - mx_2 - b = 0$$
 or $w_1x_1 + w_2x_2 + w_3 = 0$

where m = slope of line, $b = x_1$ intercept, $w_1 = 1$, $w_2 = -m$, and $w_3 = -b$.

In the n-dimensional case, the decision functions are hyperplanes of the form

$$w_1 x_1 + w_2 x_2 + \ldots + w_n x_n + w_{n+1} = 0$$

Thus, this equation may be written in vector form as: $\mathbf{w} \cdot \mathbf{x} = 0$ where

$$\mathbf{w} = \begin{bmatrix} \mathbf{w}_1 \\ \mathbf{w}_2 \\ \vdots \\ \vdots \\ \mathbf{w}_{n+1} \end{bmatrix} \text{ and } \mathbf{x} = \begin{bmatrix} \mathbf{x}_1 \\ \mathbf{x}_2 \\ \vdots \\ \vdots \\ \mathbf{x}_n \\ 1 \end{bmatrix}$$

To illustrate the operation of a decision function in two dimensions, consider the case of two patterns.

$$\mathbf{x}_1 = \begin{bmatrix} 1 \\ 4 \end{bmatrix}$$
 and $\mathbf{x}_2 = \begin{bmatrix} 4 \\ 2 \end{bmatrix}$

with the decision function $d(\mathbf{x}) = 0$ separating them (Fig 2), where

$$d(\mathbf{x}) = x_1 - \frac{1}{2}x_2 - 2 = 0$$

or, in vector form




Fig 1 Trajectories of transitional sound. Transition intervals between elemental speech sounds, such as p_1 and p_2 characterized by the lowest resonant frequencies (formants) f_1 to f_3 , contain significant information for classifying an utterance

$$d(\mathbf{x}) = \mathbf{w} \cdot \mathbf{x} = \begin{bmatrix} 1, -1/2, -2 \end{bmatrix} \begin{bmatrix} \mathbf{x}_1 \\ \mathbf{x}_2 \\ 1 \end{bmatrix} = 0$$

If x_1 is substituted into $d(x) = w \cdot x$, then

$$d(\mathbf{x}_1) = [1, -\frac{1}{2}, -2] \begin{bmatrix} 1 \\ 4 \\ 1 \end{bmatrix} = 1 -2 -2 = -3$$

and for $d(\mathbf{x}_2)$

and the same and the same and the same

4

K T P R T W T T T

$$d(\mathbf{x}_2) = [1, -\frac{1}{2}, -2] \begin{bmatrix} 4\\2\\1 \end{bmatrix} = 4 - 1 - 2 = +1$$

Note that $d(\mathbf{x}_1) < 0$ and $d(\mathbf{x}_2) > 0$. For any point above $d(\mathbf{x}) = 0$, $d(\mathbf{x})$ is positive, and negative for points below. Thus for the 2-class case, the polarity of the evaluated $d(\mathbf{x})$ determines to which class a given pattern belongs.




Fig 2 Decision function in 2-dimensions. Decision function $\mathbf{d}(\mathbf{x})=0$ separates two patterns in 2-dimensional feature-space. For \mathbf{x}_1 , $\mathbf{d}(\mathbf{x}_1)$ will be positive; for \mathbf{x}_2 , $\mathbf{d}(\mathbf{x}_2)$ will be negative, thereby providing a means of discriminating between two classes of patterns linearly separable in feature-space

Multicategory Classifiers


With the 2-class problem the classifier needs only one decision-function. For multicategory classification, more than one decision function is required. Therefore, multicategory classifiers are needed to make a class identification of a pattern from the results of two or more decision functions.


A type I multicategory classifier considers a given class, say ω_i , as one class and all other classes, collectively, as a second class. Then a decision function is found which will separate these two classes. For n classes, n decision functions will result. For a given pattern belonging to class ω_i , only $d_i(\mathbf{x}) > 0$ and $d_j(\mathbf{x}) < 0$, for all $j \neq i$ [Fig 3(a)].

A type II classifier [Fig 3(b)] consists of pairwise separation which requires decision functions that separate two classes at a time. Separation of classes ω_i and ω_j requires a decision function $d_{ij}(\mathbf{x}) = 0$. Classification results if, for all classes, $d_{ij} > 0$; then, the pattern belongs to class ω_i .

The third type of multicategory classifier is a special case of the second type, modified so that any point in pattern-space is assigned to a given class. In the previous classifiers, any point within the triangle formed by the three lines would not be classified as belonging to any of the three classes shown. To eliminate this indeterminate region, the general decision function $d_{ij}(\mathbf{x}) = 0$ is made to be $d_i(\mathbf{x}) - d_j(\mathbf{x}) = 0$ where d_i and d_j are the decision functions of a type I classifier. For this scheme, the criterion for pattern assignment to class ω_i is that $d_i > d_j$ for all $j \neq i$. Notice that no indeterminate region exists for the type III classifier [Fig 3(c)].

A type I classifier has the largest amount of indeterminate space, being the center triangle and the three wedges radiating out from it. If classes can be separated with a type I classifier, the region of identification is more constrained, and therefore better identified, than with types II and III. In addition, if one class is of special interest it can be discriminated more easily. The type II classifier indeterminate space consists only of the center triangle. When classes of patterns are easiest to separate by class-to-class comparison, the type II classifier will probably be the easiest to design.








Fig 3 Multicategory classifier. A type I classifier (a) separates multiple classes of patterns by separating a given pattern from all others so that only that class will yield a positive decision function. If $x \in \omega_1,$ $d_1(x) > 0,$ $d_2(x) < 0,$ $d_3(x) < 0.$ A type II classifier (b) separates multiple classes in pairs. If $x \in \omega_1,$ $d_1(x) > 0$ for all $j \neq i.$ A type III classifier (c) is a combination of types I and II, leaving no indeterminate regions. If $x \in \omega_1,$ $d_1 > d_3$ for all $j \neq i$




Fig 4 Hyperplane properties. A hyperplane in pattern-space is illustrated in plane x_1 - x_2 with line $\mathbf{w} \cdot \mathbf{x} = 0$. Unit vector \mathbf{w}_0 direction specifies orientation of the line, and is useful for determining distance between given point in space and line

Weight Vectors and Hyperplane Properties

In describing basic types of classifiers, it is assumed that the decision function coefficients $w_1, w_2, \ldots, w_{n+1}$ are already known. The primary goal in designing a pattern classifier is to find some method to determine these cofficients. Since the general form of a decision function is $\mathbf{w} \cdot \mathbf{x} = 0$, the goal is to find \mathbf{w} , the weight vector. The expression $\mathbf{w} \cdot \mathbf{x} = 0$ then describes a hyperplane in pattern-space. Before investigating methods for deriving \mathbf{w} , some properties of hyperplanes should be discussed.

Given the equation of a hyperplane, $\mathbf{w} \cdot \mathbf{x} = 0$, which can be expressed as

$$\mathbf{w}_0 \bullet_{\mathbf{X}} + \mathbf{w}_{n+1} = 0$$

where

$$\mathbf{w}_0 = \begin{bmatrix} \mathbf{w}_1 \\ \mathbf{w}_2 \\ \vdots \\ \mathbf{w}_n \end{bmatrix}$$

If the dot product of two vectors is zero, they are perpendicular in direction, or $\mathbf{w} \cdot \mathbf{x} = 0 \Longrightarrow \mathbf{w} \perp \mathbf{x}$. If \mathbf{x}

and \mathbf{p} are points contained on $\mathbf{w} \cdot \mathbf{x} = 0$, $\mathbf{x} - \mathbf{p}$ is contained by the hyperplane. Consequently, if \mathbf{w} is perpendicular (or normal) to the hyperplane, $\mathbf{w} \cdot (\mathbf{x} - \mathbf{p}) = 0$ or $\mathbf{w} \cdot \mathbf{x} = \mathbf{w} \cdot \mathbf{p}$. Writing out the dot products, and canceling \mathbf{w}_{n+1} from both sides results in $\mathbf{w}_0 \cdot \mathbf{x} = \mathbf{w}_0 \cdot \mathbf{p}$ or $\mathbf{w}_0 \cdot (\mathbf{x} - \mathbf{p}) = 0$. This result indicates that the vector \mathbf{w}_0 is normal to the hyperplane $\mathbf{w} \cdot \mathbf{x} = 0$ since $\mathbf{x} - \mathbf{p}$ lies on the hyperplane.

A vector with a magnitude of unity in the direction of \mathbf{w}_0 is

$$\mathbf{w}_0 = \frac{\mathbf{w}_0}{|\,|\,\mathbf{w}_0\,|\,|}$$

where the \wedge symbol indicates a unit vector and $||\mathbf{w}_0||$ is the magnitude (norm or length) of \mathbf{w}_0 .

$$||\mathbf{w}_0|| = \sqrt{|\mathbf{w}_1|^2 + |\mathbf{w}_2|^2 + \dots + |\mathbf{w}_n|^2}$$

In two dimensions, these equations can be graphically presented as shown in Fig. 4. Note that the distance from the origin to the line is the length of \mathbb{N} , or $\mathbf{w}_0 \cdot \mathbf{p}$. This is true for any point on the line since, for arbitrary point $\mathbf{x}, \mathbf{w}_0 \cdot \mathbf{x} = \mathbf{w}_0 \cdot \mathbf{p}$.

The distance to the line described by $\mathbf{w} \cdot \mathbf{x} = 0$ is

$$D(line) = |\mathbf{w}_0 \cdot \mathbf{x}| = \left| \frac{-\mathbf{w}_{n+1}}{|\mathbf{w}_0|} \right| = \left| \frac{\mathbf{w}_{n+1}}{|\mathbf{w}_0|} \right|$$

For any point in general in hyperspace, y, the distance from $\mathbf{w}^{\bullet}\mathbf{x} = 0$ to y is the length of $\mathbf{Y} - \mathbf{N}$. Also, $||\mathbf{Y}|| = |\hat{\mathbf{w}}_0^{\bullet}\mathbf{y}|$ (see Fig 4). Then,

$$||\mathbf{Y} - \mathbf{N}|| = |\mathbf{w}_0 \cdot \mathbf{y} - \mathbf{w}_0 \cdot \mathbf{x}|$$

This equation for the distance of a point to a line can be presented in a more useful form by rewriting $\mathbf{\hat{w}}_0 \cdot \mathbf{x}$ as

$$\mathbf{w}_{0} \cdot \mathbf{x} = \frac{\mathbf{w}_{0} \cdot \mathbf{x}}{||\mathbf{w}_{0}||} = \frac{\mathbf{w} \cdot \mathbf{x}}{||\mathbf{w}_{0}||} - \frac{\mathbf{w}_{n+1}}{||\mathbf{w}_{0}||}$$

Since $\mathbf{w} \cdot \mathbf{x} = 0$,

$$\mathbf{w}_0 \bullet_{\mathbf{X}} = - \frac{\mathbf{w}_{n+1}}{| | \mathbf{w}_0 | |}$$

and

$$D (\text{point to line}) = \left| \frac{\mathbf{w_0} \cdot \mathbf{y} + \mathbf{w_{n+1}}}{||\mathbf{w_0}||} \right| = \left| \frac{\mathbf{w_0} \cdot \mathbf{y} + \mathbf{w_{n+1}}}{||\mathbf{w_0}||} \right|$$

Summarizing, vector $\mathbf{\hat{w}}_0$ is normal to the hyperplane $\mathbf{w} \cdot \mathbf{x} = 0$ and describes its orientation. The constant term in the equation for line, \mathbf{w}_{n+1} , is related to the distance of the line from the origin. When $\mathbf{w}_{n+1} = 0$, the line passes through the origin.

Minimum-Distance Classifiers

If two clusters of points in pattern-space are well separated, a decision function in the form of a hyperplane can be used to separate pattern-space into two regions that correspond to two classes. A technique can be developed for determining a decision function which will linearly separate the two clusters of points. First, points representing the typical values of each cluster must be determined. These points are known as prototypes or cluster-centers, since they are usually located at an average (or mean) distance from the points of the cluster they represent. The value of the prototype point may be found by averaging the points in a cluster of N points.

$$\mathbf{z} = \frac{1}{N} \sum_{i=1}^{N} \mathbf{x}_{i}$$

Next, some measure is needed of the similarity of a given pattern with the prototype. One similarity measure is the Euclidean distance of the point from each prototype point. Whichever prototype point is closest is considered to be the most similar and is assigned to the same class. This approach is known as minimum-distance classification. The distance of a given pattern, \mathbf{x} , from a cluster-center, \mathbf{z} , is the length of $\mathbf{x} - \mathbf{z}$ or $\mathbf{D} = ||\mathbf{x} - \mathbf{z}||$. For two dimensions, this is

$$D^{2} = (x_{1} - z_{1})^{2} + (x_{2} - z_{2})^{2}$$

$$= x_{1}^{2} - 2x_{1}z_{1} + z_{1}^{2} + x_{2}^{2} - 2x_{2}z_{2} + z_{2}^{2}$$

For multiple classes, the general form of the decision functions can be derived by considering that, for the ith class

$$D_1^2 = || (\mathbf{x} - \mathbf{z}_1) ||^2 = (\mathbf{x} - \mathbf{z}_1) \cdot (\mathbf{x} - \mathbf{z}_1)$$

= $\mathbf{x} \cdot \mathbf{x} - 2\mathbf{x} \cdot \mathbf{z}_1 + \mathbf{z}_1 \cdot \mathbf{z}_1$

Since $\mathbf{x} \cdot \mathbf{x}$ is the same for all classes, it can be eliminated. Multiplying by (-1/2), the general decision function is

$$d_{i}(\mathbf{x}) = \mathbf{x} \cdot \mathbf{z}_{i} - (\frac{1}{2})\mathbf{z}_{i} \cdot \mathbf{z}_{i}$$

Because D_i^2 was multiplied by a negative number to obtain d_i (x), the largest decision function identifies the minimum distance and hence the class of x. Since the general form of a decision function is $d(x) = w \cdot x = 0$, the components of w can now be determined. They are

$$w_i = z_i \text{ for } i = 1, ..., n$$

 $w_{n+1} = -(\frac{i}{2})z_i \cdot z_i$

The third type of classifier uses decision functions for each class derived from the prototype for that class. In this case, the decision boundary in two dimensions for two classes is a line which is the perpendicular bisector of the line joining the two cluster-centers. It fits the intuitive notion of the minimum-distance classifier concept by running midway between cluster-centers.

As an example, consider a 2-dimensional patternspace containing the training set for the three classes shown below. Prototypes are found by taking the average of the individual vector components (with **x** and **z** not shown as augmented).

$$\omega_{1} = \left\{ \begin{bmatrix} 1 \\ 4 \end{bmatrix}, \begin{bmatrix} 2 \\ 6 \end{bmatrix}, \begin{bmatrix} 3 \\ 4 \end{bmatrix}, \begin{bmatrix} 2 \\ 6 \end{bmatrix}, \begin{bmatrix} 2 \\ 5 \end{bmatrix} \right\} \mathbf{z}_{1} = \begin{bmatrix} 2 \\ 5 \end{bmatrix} \\
\omega_{2} = \left\{ \begin{bmatrix} 2 \\ 2 \end{bmatrix}, \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \begin{bmatrix} 0 \\ 1 \end{bmatrix}, \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \begin{bmatrix} 1 \\ 1 \end{bmatrix} \right\} \mathbf{z}_{2} = \begin{bmatrix} 1 \\ 1 \end{bmatrix} \\
\omega_{3} = \left\{ \begin{bmatrix} 4 \\ 4 \end{bmatrix}, \begin{bmatrix} 4 \\ 3 \end{bmatrix}, \begin{bmatrix} 5 \\ 2 \end{bmatrix}, \begin{bmatrix} 3 \\ 4 \end{bmatrix}, \begin{bmatrix} 4 \\ 3 \end{bmatrix} \right\} \mathbf{z}_{3} = \begin{bmatrix} 4 \\ 3 \end{bmatrix}$$

Then, for a type III classifier,

$$\begin{aligned} &d_{1}(\mathbf{x}) = \mathbf{w}_{1} \bullet \mathbf{x} = [2, 5, -14.5] \bullet \mathbf{x}, \\ &\text{where } \mathbf{w}_{13} = -(\frac{1}{2}) \ (\mathbf{z}_{11}^{2} + \mathbf{z}_{12}^{2}) = -(\frac{1}{2}) \ (4 + 25) = -14.5 \\ &d_{2}(\mathbf{x}) = \mathbf{w}_{2} \bullet \mathbf{x} = [1, 1, -1.0] \bullet \mathbf{x}, \\ &\text{where } \mathbf{w}_{23} = -(\frac{1}{2}) \ (1 + 1) = -1.0 \\ &d_{3}(\mathbf{x}) = \mathbf{w}_{3} \bullet \mathbf{x} = [4, 3, -12.5] \bullet \mathbf{x}, \\ &\text{where } \mathbf{w}_{33} = -(\frac{1}{2}) \ (16 + 9) = -12.5 \end{aligned}$$

To test this classifier, a point chosen near z, such as

should result in $d_1 > d_2$, d_3 . Substituting,

$$\begin{array}{l} d_1 \left[\begin{bmatrix} 1\\4\\1 \end{bmatrix} \right] \; = \; [2,\,5,\,-14.5] \left[\begin{array}{c} 1\\4\\1 \end{array} \right] = \; 2 + 20 \, - \, 14.5 = \, 7.5 \\ d_2 \left[\begin{bmatrix} 1\\4\\1 \end{bmatrix} \right] \; = \; [1,\,1,\,-1.0] \left[\begin{array}{c} 1\\4\\1 \end{array} \right] = \; 1 + 4 \, - \, 1 = \, 4.0 \\ d_3 \left[\begin{bmatrix} 1\\4\\1 \end{bmatrix} \right] \; = \; [4,\,3,\,-12.5] \left[\begin{array}{c} 1\\4\\1 \end{array} \right] = \; 4 + 12 \, - \, 12.5 = \, 3.5 \end{array}$$

Thus.

$$\mathbf{x} = \begin{bmatrix} 1 \\ 4 \end{bmatrix}$$

is closest to z_1 and farthest from z_3 ; therefore,

$$\begin{bmatrix} 1 \\ 4 \end{bmatrix} \epsilon \omega_1.$$

A geometric interpretation of the minimum-distance classifier is obtained by examining the terms of $d(\mathbf{x}) = \mathbf{x} \cdot \mathbf{z} - (\frac{1}{2}) \mathbf{z} \cdot \mathbf{z}$. The distance $|\mathbf{x} \cdot \mathbf{z}|$ is found graphically by projecting \mathbf{x} onto \mathbf{z} . The length-squared of the segment along \mathbf{z} to point 1 is $|\mathbf{x} \cdot \mathbf{z}|$. The second term has a length-squared of the segment along \mathbf{z} to point 2, which is midway between \mathbf{z} and the origin. The decision function is positive if point 1 is closer to \mathbf{z} than to the origin. When decision functions are compared, the result is relative to the other cluster-center rather than to the origin.

Clustering Techniques

Techniques known as clustering algorithms can be used to classify patterns in an unsupervised manner. Among these are several algorithms that can be programmed and run on a small computer.

Threshold Algorithm

The threshold algorithm is conceptually simple. First, a cluster-center, \mathbf{z}_1 is established. An easy method of doing this is to use the first pattern vector, \mathbf{x}_1 . Then, the next pattern is taken (arbitrarily) and its distance to \mathbf{z}_1 (and any other cluster-centers, as they appear) is computed. If this distance is less than a specified threshold value, T, it is assigned to that cluster. If not, the algorithm creates a new cluster-center using that pattern as the cluster-center. Fig 5 is a flowchart of this algorithm.

Several characteristics of the threshold algorithm deserve special attention. First, since the choices of \mathbf{x}_1 for the initial cluster-center greatly affect the classification, the algorithm is improved if approximate values for the cluster-centers are chosen as initial values. Second, the value of the distance threshold, T, affects the resolution of the clustering. If T is too large, several distinct clusters may be lumped together as a single

cluster. Conversely, if T is too small, a cluster may be broken into several artificial clusters. To determine a value for T, consider what effect its value has on the number of clusters. A typical function is plotted in Fig 6(a).

Notice that between T_1 and T_2 , N_c is relatively independent of T. This may be explained by considering the clusters in pattern-space [Fig 6(b)]. If clusters a and b are separated as shown, good classification will occur for $T_1 < T < T_2$, and T is usable in this range. If clusters a and b overlap, no interval of $N_c(T)$ will be flat, and a and b will not be linearly separable. In this case, statistical techniques for optimal classification are needed. Of course, if T is too large, the curve will be flat for $N_c = 1$, but this is a trivial condition.

Maximin-Distance Algorithm

To improve on the simple threshold algorithm, the maximum-minimum-distance or maximin-distance algorithm uses Euclidean distance measures in a similar fashion. It is shown as a flowchart in Fig 7.


An initial \mathbf{z}_1 is an arbitrarily chosen pattern, \mathbf{x} , and the point farthest from \mathbf{x} is set equal to \mathbf{z}_2 . A minimum-distance classifier, such as the one already discussed, is used to classify the remainder of the pattern points. Then, from each class, the pattern farthest from its assigned cluster-center is chosen, and the distance to its cluster-center is compared with the average distance between cluster-centers. If it is greater than this average distance, it is made a cluster-center. This is done for all classes, and if any new cluster-centers appear, the procedure is repeated until no changes in the number of cluster-centers occur.

Although the maximin-distance algorithm is an improvement over the threshold algorithm, its final classification of patterns is still dependent upon initial conditions. For a chosen \mathbf{z}_1 , the farthest point from it may be a bad data point, as noise in the data will often lead to lone points far from any others. However, the algorithm chooses a threshold value automatically by using the average distance between cluster-centers.

To find the farthest point from z_1 , the distance to every other point must be computed. This may be time-consuming for a large data base. Also, choosing the farthest point may cause a distinct cluster to be combined with the nearest cluster since the average distance between cluster-centers will be large at first. Finally, this algorithm will not converge to a final solution for some distributions of patterns. If a point is located midway between two cluster-centers whose clusters contain an equal number of points distributed similarly around their respective cluster centers, the algorithm will not converge.

K-Means Algorithm

Examination of the pattern distribution may allow approximate choices of cluster-centers. The K-Means algorithm begins with such choices (even if they are arbitrarily chosen data points in pattern-space). Using a minimum-distance classifier as a similarity measure, the algorithm assigns the remaining points to one of the K cluster-centers, then computes a new cluster-center for each class by averaging the points for each cluster.



大 安 安 女 大

4 5

4

Fig 5 Threshold algorithm. This simple algorithm uses given distance threshold, T, as basis for determining class membership of pattern




Fig 6 Number of clusters as function of threshold value. (a) When value of T is between T_1 and T_2 , number of clusters, N_c , is independent of T. In this interval, T corresponds to length which sets threshold boundary in feature-space between clusters (b)





Fig 7 Maximin-distance algorithm. Similar to the threshold algorithm in approach, threshold value is not fixed but is calculated from mean value of cluster-centers



Classification is repeated, assigning all points to the new clusters. When the assignments do not change from the previous iteration, the algorithm has converged. This algorithm is affected by K, the number of clustercenters to start with, as well as their values.

General Cluster-Seeking Algorithm

The problem of designing a completely general clustering algorithm has not been solved. However, there is a general technique for the development of specific algorithms (see Fig 8). At times it may be desirable to

lump two or more clusters into a single cluster. This requires some set of rules (death rules) to determine when this should be done. Similarly, the creation of new cluster-centers requires a set of rules, as in the threshold and maximin algorithms (birth rules).

Learning Techniques

Cluster-seeking algorithms that have been developed are unsupervised algorithms, since the classes of a given set of patterns are determined by the algorithm. It is possible, however, for an algorithm to be trained to recognize the proper class for a given pattern using a reward-punishment concept. Once the algorithm has been trained to properly classify patterns of a known class membership (the training set of patterns), it can be used on unknown ones.

Perceptron Algorithm

For a training set of N patterns which belongs to one of two known classes, ω_1 and ω_2 , the weight vector w for N decision functions must be determined. For patterns

 \mathbf{x}_{1i} belonging to ω_1 , decision functions are of the form $\mathbf{x}_{1i} \cdot \mathbf{w} > 0$ and for patterns \mathbf{x}_{2i} belonging to ω_2 , $\mathbf{x}_{2i} \cdot \mathbf{w} < 0$ or $-\mathbf{x}_{2i} \cdot \mathbf{w} > 0$. The set of patterns $\{\mathbf{x}_{1i}, -\mathbf{x}_{2i}, i = 1, \ldots, N\}$ can be written in matrix form where \mathbf{X} is the matrix of training sample patterns. Then, the learning algorithm's goal is to find a weight vector, \mathbf{w} , which satisfies $\mathbf{X}\mathbf{w} > 0$. This perceptron algorithm is shown in Fig 9.

When the algorithm chooses a pattern and calculates its decision function, if $d(\mathbf{x}) > 0$, the weight vector is satisfactory at least for that pattern and is not changed—the next pattern is tried. When $d(\mathbf{x}) < 0$, the weight vector must be adjusted so that the decision function will come out positive. The pattern vectors of class ω_2 have been multiplied by -1 so that all decision functions must come out positive to be correct. This is done by replacing \mathbf{w} with $\mathbf{w} + \mathbf{c} \cdot \mathbf{x}$, where \mathbf{c} is a positive correction increment. Therefore, on the kth iteration, the new value of \mathbf{w} is

$$\mathbf{w}(\mathbf{k}+1) = \begin{cases} \mathbf{w}(\mathbf{k}) & \text{if } \mathbf{w}(\mathbf{k}) \cdot \mathbf{x} > 0 \\ \mathbf{w}(\mathbf{k}) + c\mathbf{x} & \text{if } \mathbf{w}(\mathbf{k}) \cdot \mathbf{x} \le 0 \end{cases}$$




Fig 9 Perceptron algorithm. This 2-class learning algorithm modifies weight vector of decision function d(x) in search of a w which allows for correct classification of all known patterns. Only linearly separable clusters can be classified

On the next iteration, w will be closer to the correct value, even if $d(x) \le 0$, since d(x) is now

$$d(\mathbf{x}) = \mathbf{w}(\mathbf{k} + 1) \cdot \mathbf{x} = (\mathbf{w}(\mathbf{k}) + c\mathbf{x}) \cdot \mathbf{x} = \mathbf{w}(\mathbf{k}) \cdot \mathbf{x} + c\mathbf{x} \cdot \mathbf{x}$$

This new d(x) is greater than the previous d(x), which is equal to the first term, $w(k) \cdot x$. Now d(x) is greater than the previous d(x) by the amount $cx \cdot x$. This second term must be positive since c > 0 and $x \cdot x$ must be positive. Therefore, it appears that the algorithm will converge.

To better understand how this algorithm works, consider the training set in 2-dimensional feature-space.

$$\omega_1 = \{\mathbf{x}_1, \mathbf{x}_2\} \text{ where } \mathbf{x}_1 = \begin{bmatrix} 3 \\ 1 \end{bmatrix} \mathbf{x}_2 = \begin{bmatrix} 1 \\ 2 \end{bmatrix}$$

$$\omega_2 = \{-\mathbf{x}_3, -\mathbf{x}_4\} \text{ where } \mathbf{x}_3 = \begin{bmatrix} -2 \\ -4 \end{bmatrix} \mathbf{x}_4 = \begin{bmatrix} -4 \\ -3 \end{bmatrix}$$

Letting c = 1 and w(0) = 0, the algorithm proceeds as follows:

$$d(\mathbf{x}_1) = \mathbf{w} \cdot \mathbf{x}_1 = [0, 0, 0] \cdot \begin{bmatrix} 3 \\ 1 \\ 1 \end{bmatrix} = 0$$

a service the teath of the teath of the service to the service to

Since d(x1) is not greater than 0, w must be modified.

$$\mathbf{w}(1) = \mathbf{w}(0) + 1 \cdot \mathbf{x}_1 = \begin{bmatrix} 0 \\ 0 \\ 0 \end{bmatrix} + \begin{bmatrix} 3 \\ 1 \\ 1 \end{bmatrix} = \begin{bmatrix} 3 \\ 1 \\ 1 \end{bmatrix}$$

Nevt

$$\mathbf{d}(\mathbf{x}_2) = \mathbf{w} \bullet \mathbf{x}_2 = \begin{bmatrix} 3, 1, 1 \end{bmatrix} \begin{bmatrix} 1 \\ 2 \\ 1 \end{bmatrix} = 6$$

Since

$$d(\mathbf{x_2}) > 0, \mathbf{w}(2) = \mathbf{w}(1) = \begin{bmatrix} 3\\1\\1 \end{bmatrix}$$

The procedure continues as shown in Fig 10. All d(x) are correct when the procedure terminates with

$$\mathbf{w} = \begin{bmatrix} 2 \\ -1 \\ 6 \end{bmatrix}$$

Why does the perceptron algorithm work? Instead of developing a proof of its convergence (for linearly separable classes), an intuitive approach is used. First, it is already known from the hyperplane properties previously developed that w is perpendicular to the de-

ITERATION	CLASS	w	×	q(x)	MODIFY W
1	1	(0,0,0)	(3,1,1)	0	YES
2	1	(3,1,1)	(1,2,1)	6	NO
3	2	(3,1,1)	(-2,-4,1)	-9	YES
4	2	(1, -3,2)	(-4, -3,1)	7	NO
5	1	(1, -3,2)	(3,1,1)	2	NO
6	1	(1,-3,2)	(1,2,1)	-3	YES
7	2	(2, -1,3)	(-2, -4,1)	3	NO
8	2	(2, -1,3)	(-4,-3,1)	-2	YES
9	M Horning and whole	(-2, -4,4)	(3,1,1)	-6	YES
10	1	(1,-3,5)	(1,2,1)	0	YES
11	2	(2, -1,6)	(-2, -4,1)	6.	NO
12	2	(2, -1,6)	(-4,-3,1)	1	NO
13	1	(2, -1,6)	(3,1,1)	11	NO
14	1	(2, -1,6)	(1,2,1)	6	NO

Fig 10 Example of perceptron algorithm in tabular form. Each of two patterns of classes one and two are used to determine d(x) with w. If d(x) < 0, w is modified by adding x to it

cision surface described by the decision function $d(\mathbf{x}) = \mathbf{w} \cdot \mathbf{x} = 0$. For a particular pattern \mathbf{x}_1 , $\mathbf{w} \cdot \mathbf{x}_1 > 0$ if \mathbf{w} and \mathbf{x}_1 lie in the same general direction so that the angle between them, θ , is less than 90 degrees. Another expression of the dot product of two vectors, \mathbf{a} and \mathbf{b} is

$$\mathbf{a} \cdot \mathbf{b} = ||\mathbf{a}|| \cdot ||\mathbf{b}|| \cdot \cos \theta$$

Since magnitudes of vectors are always non-negative, the dot product is such that the following cases can occur.

Sign of Dot Product	Angle Between Vectors
Positive	<90 degrees
Zero	=90 degrees
Negative	>90 degrees

For the perceptron algorithm, a w must be found which points in the same general direction as the pattern vectors. Then, adding a vector \mathbf{x} to \mathbf{w} causes \mathbf{w} to point more in the direction of \mathbf{x} . This is why $\mathbf{w} \cdot \mathbf{x}$ always improves after \mathbf{w} is modified. In adding the patterns \mathbf{x}_i to \mathbf{w} , the effect on \mathbf{w} is to cause it to tend toward the mean of \mathbf{x}_i since the mean is

$$\mathbf{m} = \frac{1}{N} \sum_{i=1}^{N} \mathbf{x}_{i}$$

As the algorithm proceeds, the value of w approaches m. This is similar to the minimum-distance classifiers already discussed. However, the method of arriving at the result illustrates a primitive form of learning since w iterates toward the correct value, and is corrected when wrong.

Absolute Increment Correction

In the perceptron example, c is arbitrarily chosen to be 1, a fixed increment. However, the algorithm would converge faster if c were made just large enough to have the correct classification occur after weight adjustment (using the same pattern, of course). This value can be found by choosing c so that $\mathbf{w}(\mathbf{k}+1) \cdot \mathbf{x} > 0$ or $[\mathbf{w}(\mathbf{k}) + c\mathbf{x}] \cdot \mathbf{x} > 0$. Then $\mathbf{w}(\mathbf{k}) \cdot \mathbf{x} + c \cdot \mathbf{x} \cdot \mathbf{x} > 0$, and $\mathbf{c} > -\mathbf{w}(\mathbf{k}) \cdot \mathbf{x} / \mathbf{x} \cdot \mathbf{x}$. Since $\mathbf{x} \cdot \mathbf{x} > 0$ and $\mathbf{w}(\mathbf{k}) \cdot \mathbf{x} < 0$ (having been wrongly classified), then $-\mathbf{w}(\mathbf{k}) \cdot \mathbf{x} < 0$ and $\mathbf{c} > 0$. Therefore, the equation for c could also be written

$$c = \frac{\mathbf{w}(\mathbf{k}) \cdot \mathbf{x}}{\mathbf{x} \cdot \mathbf{x}} = \frac{\mathbf{w}(\mathbf{k}) \cdot \mathbf{x}}{||\mathbf{x}||^2}$$

This value of c is used in the absolute-correction perceptron algorithm.

Multicategory Perceptron Algorithm

For three or more classes, three types of classifiers have been discussed. The perceptron algorithm could employ the first type of classifier (one-of-N) by using N decision functions for N classes, where each decision function discriminates between the given class ω_i and all other classes considered together as ω_j . The N weight vectors could converge toward a solution of each decision function as it was exposed to the class it identified versus the patterns of the other classes. Similarly, for

a type II classifier (pairwise) the number of decision functions needed is N taken two at a time or

$$\frac{N(N-1)}{2}$$

In this case, the perceptron algorithm trains individual decision functions by presenting patterns of two classes and adjusting the weight vector accordingly. For the third type of classification, the largest decision function determines the class; or, if $\mathbf{x} \in \omega_i$, $d_i(\mathbf{x}) > d_j(\mathbf{x})$ for all $j \neq i$.

Using the type III classifier, a more general form of the perceptron algorithm can be developed. On the kth iteration, if pattern $\mathbf{x} \in \omega_i$, the N decision functions are tested with \mathbf{x} . If $d_i(\mathbf{x}) > d_j(\mathbf{x})$ for all $j \neq i$, the weight vectors are not adjusted, or $\mathbf{w}(k+1) = \mathbf{w}(k)$. However, if for some m, $d_i(\mathbf{x}) \leq d_m(\mathbf{x})$, the weight vector of $d_i(\mathbf{x})$ is increased. The weight vector of $d_m(\mathbf{x})$ is decreased, and the other weight vectors are unaffected.

Summary

Classification of complex information by computer algorithms requires the selection of decision functions which will allow separation of patterns of signals into classes. These classes may be predetermined and represented by linear classifiers based on chosen decision functions or specified by the recognizer itself, as with clustering techniques. In addition to clustering, a different approach to unsupervised classification is to use learning algorithms such as the perceptron. All of the approaches to pattern recognition presented here require well-separated clusters of classes in feature-space since the decision functions are linear and no statistical properties of the patterns, which are necessary for overlapping clusters, have been considered. The ease with which these algorithms may be modified and optimized as computer software makes them particularly attractive when compared with fixed hardware designs.

Bibliography

- Y. T. Chien, "Interactive Pattern Recognition: Techniques and Systems," Computer, May 1976, pp 11-25
- L. S. Coles, Tech Note 41, Artificial Intelligence Center, Stanford Research Institute, Stanford, Calif, 19—
- R. W. Schafer, L. F. Rabiner, "Digital Representations of Speech Signals," Proceedings of the IEEE, Apr 1975, pp—
- J. T. Tou, R. C. Gonzales, Pattern Recognition Principles, Addison-Wesley, 1974



Dennis Feucht received a BSEE degree in computer science from Oregon State University. As an instrument design engineer at Tektronix he is presently involved in oscilloscope design; his previous design experience includes pulse and function generators and microcomputer systems.



NEW:

memory for PDP-8/A PDP-11/70, 11/04 & 11/34



Mini-Memory. From Dataram.

Either way, you get more memory, more throughput, more performance. Everything but more cost.

If you're looking for a way to get more from your minicomputer without putting too much more into it, our family of ADD-ON/ADD-IN mini-memories adds up to the right answer for you.

Including our new, expanded family of ADD-ON/ADD-IN systems that's ready to go to work for your minicomputer: or call us at 609-799-0071.

Data General	DEC®	Varian
Nova® 830	LSI/11	620/f
Nova 1200	PDP®-8/A	620/i
Nova 1210	PDP-8/E	620/L
Nova 1210	PDP-8/F	620/L-100
Nova 1230	PDP-8/M	622/i
Nova 2/4	PDP-11/04	V-71
Nova 2/10	PDP-11/05	V-72
Nova 3/4	PDP-11/10	V-73
Nova 3/4	PDP-11/15	V-74
NOVA 3/12	PDP-11/20	V-75
Interdata	PDP-11/34	
Model 50	PDP-11/35	Data 100
Model 55	PDP-11/40	CDP 135
Model 70	PDP-11/45	
Model 74	PDP-11/50	DCC
6/16	PDP-11/55	116
7/16	PDP-11/70	116E

7/32

8/32

Whether you're adding it on or in, Dataram will meet your mini-memory requirements with new, reliable 16K single-board design that delivers the performance you want, and saves you money while doing it. Find out more—return this coupon at once,

I'd like more ar	nswers about mini-memories for my minicomputer.
☐ Please send ☐ Please have	information. a salesman contact me.
Name	
	Divina
Title	Phone
Title	




PRINCETON-HIGHTSTOWN ROAD CRANBURY, NEW JERSEY 08512 TEL:609-799-0071 TWX:510-685-2542

DEC and PDP are registered trademarks of Digital Equipment Corporation. Nova is a registered trademark of Data General Corporation.

Canada: Tracan Electronics Corporation, Ontario/Quebec/British Columbia • Belgium/Luxembourg/Netherlands: Synelec Information Systems, (02) 647-67-12 • France: YREL, 950-224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Teleinstrument AB, 08-380370 • Spain: Aupoca, (01) 457-53-12 • Switzerland: Intertest AG, 031-224481 • United 2224 • Italy: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Telcom, s.r.l. 422-8646 • Sweden/Finland/Norway: Telcom, s.r.l. 422-8646 • Sweden/Fi

CMOS MICROS? CALL HARRIS.

THE CMOS MICROCOMPUTER



Doing high powered thinking about low power CMOS?

Call Harris. Or, call Intersil. Either way you get the source. And a second source. What's more, you get the best in CMOS products produced by two companies whose continuing commitment to CMOS means an expanding family of low power CMOS components and capabilities.

Start with the 6100, 12 bit microprocessor.

The best CMOS micro solution. The fastest. The most memory efficient. The easiest to program. The simplest to use.

Finish with a complete family!


1-1-1-1-1-1-1			
ТҮРЕ	DESCRIPTION	HARRIS	INTERSIL
6100	CMOS 12 bit microprocessor	X	X
6101	CMOS Programmable Interface Element	X	Х
6102	CMOS Memory Extension/ DMA/Interval Timer/Controller	1978	х
6103	CMOS Parallel Input-Output Port	1978	X
6312	CMOS 1024 x 12 ROM	х	X
6402	CMOS UART	X	X
6405	CMOS Bit Rate Generator	x	1978
6431	CMOS Hex Latch Buffer	x	1978
90 0 30	Contract of the part of the pa		

x - product available nov

SOURCE US. SECOND SOURCE THEM.



CMOS MICROS? CALL INTERSIL.



ТҮРЕ	DESCRIPTION	HARRIS	INTERSIL
6432	CMOS Hex Bidirectional Buffer	X	1978
6433	CMOS Quad Bus Separator	Х.	1978
6440	CMOS Latched Decoder Buffer	X	1978
6495	CMOS Hex Three State Buffer	x	1978
6504	CMOS 4K x 1 RAM	x	2Q 1978
6508	CMOS 1K x 1 RAM	x	x
6512	CMOS 64 x 12 RAM	x	X
6514	CMOS 1K x 4 RAM	X	2Q 1978
6561	CMOS 256 x 4 RAM	х	X
6603	CMOS 1K x 4 UV EPROM	1978	X

Source us. Second source them.

Either way you get the best CMOS micro solution. Call Intersil. (408) 996-5000 or (800) 538-7930. Ext. 5379, 5071, 5164. TWX: 910-338-0171. 10710 N. Tantau Avenue, Cupertino, CA. 95014.

Call Harris, (800) 528-6050.

Ext. 455. P.O. Box 883, Melbourne, FL. 32910.





aste little shift registers du can bu

TRW's new TDC-1006J 256-bit serial shift register is unmatched for speed and power.

When you need a fast, compact shift register, there's nothing around to match the TRW TDC-1006J 256-bit serial shift register. Advanced bipolar construction gives you speeds of 30 MHz. Power consumption is under 500 mW. It's TTL compatible, with complementary outputs. And the 16 pin C DIP configuration lends itself nicely to inexpensive, high density packaging.

Also available is the TDC-1005J Dual 64-bit serial shift register with a speed/power product comparable only to the TDC-1006J. It consumes only 350 mW.

Cost: 256-bit \$55 in 100's—dual 64-bit \$40 in 100's. Contact your nearest TRW Electronic Components field sales office or call us at (213) 535-1831, or send the coupon.

ALL TRW LSI PRODUCTS ARE NOW IN STOCK AND DISTRIBUTED EXCLUSIVELY BY HAMILTON/AVNET

TRW LSI Products An Electronic Components E P.O. Box 1125 Redondo Beach, Californi	
Please send data she	eets on your shift registers.
NAME	
COMPANY	
ACCOUNTY OF THE PARTY	MAIL CODE
DIV/DERT	MAIL CODE
COMPANY DIV/DERT ADDRESS CITY	MAIL CODE

TRW LSI PRODUCTS

For Digital Signal Processing

Multiple-word data buffering in device controllers is important whenever high speed discs are interfaced with computers that handle several DMA devices. Utilizing current technology, bipolar LSI FIFO devices represent significant functional and economical advances for processing fast bit rates and complex computer interfacing

Multiple-Word Buffering for Disc Controllers With Bipolar FIFO Memory

Krishna Rallapalli*

Bipolar Memory/LSI Division
Fairchild Camera and Instrument Corporation
Mountain View, California

When a disc is interfaced with a computer, a multiple-word buffer memory usually is needed in the disc controller since data bits arrive continuously in a serial stream from the disc. Data bits are first assembled into words in a serial-to-parallel converter and then are loaded into the buffer. Next, a request is made to the computer for direct memory access. However, no computer can respond instantaneously to a direct memory access request and simultaneously grant access to the memory. The delay from the time of request to the access grant is known as direct memory access latency and usually lasts a few microseconds.

4

Since the disc is a synchronous device, data bits continue to arrive while the disc controller is waiting for a grant to memory. If the controller does not have enough local buffering capacity, a data overrun condition will result, necessitating re-reading the whole sector from the disc. A similar situation exists while performing a write operation. Parallel data are obtained from memory using the direct memory access (DMA) facility, and a parallel-to-serial converter generates the serial bit stream to be written on the disc. Without sufficient local buffering, DMA latency will cause an overrun condition because another word will not be available as soon as the previous word is written.

In the past, disc drives had modest bit rates, and computer systems did not contain many DMA devices.

Also, two to four words of local buffering were deemed satisfactory by designers. Buffers and associated serial-to-parallel and parallel-to-serial converters were implemented using medium-scale integration (MSI) devices. However, for today's increasing disc speeds and complex computer systems containing many DMA devices, 16 or more words of local buffering are required in the disc controllers. Such large buffers containing MSI devices are no longer attractive economically, especially since bipolar large-scale integration (LSI) is now more cost-effective.

A first-in first-out (FIFO) buffer memory is an LSI device that automatically stores words in the order they are entered at the input and makes them available at the output in exactly the same order. Moreover, data entry and data extraction from the FIFO buffer can be asynchronous. Because these two properties are precisely what a buffer memory in a disc controller needs, FIFO devices are ideal candidates for this application.

Two industry-compatible bipolar FIFO memory devices to be discussed are a 16-word by 4-bit low power Schottky device (9403), and a 64-word by 4-bit isoplanar integrated injection logic (I³L)TM device (9423). Except for storage capacity, both devices are identical

^{*}Mr Rallapalli is currently employed by National Semiconductor Corp, Santa Clara, Calif.


in architecture, pin configuration, and packaging. Also, data can be entered in serial or parallel format and can be extracted in either serial or parallel mode for both devices. Of greatest importance, serial-to-parallel and parallel-to-serial conversions and buffer memory functions are combined into a single LSI device.

FIFO Buffer Operation

As shown in Fig 1, the FIFO buffer contains a 4-bit input register with serial and parallel data inputs, and control inputs and outputs for handshaking and input expansion. The fall-through stack is N-2, 4-bit words deep with self-contained control logic, where N equals 16 for the 9403, and N equals 64 for the 9423. Thus, the stack is 14 or 62 words deep, respectively. The fallthrough stack physically consists of rows of flip-flops (four per row). If data are loaded into the first row of flip-flops and the second row contains no data, the stack control logic transfers data from the first row to the second. If the third row is empty, data will fall from the second row into the third, and so on. Also, the device has a 4-bit output register with serial and parallel data outputs, and control inputs and outputs for handshaking and output expansion.

Parallel data are entered into the input register using data inputs Do through D3, and the parallel load (PL) input as the clock pulse. A high level on the PL input operates the direct set and clear inputs of the input register flip-flops. The quiescent state of the PL input is low. Serial data are entered using Ds as data input and the serial input clock (CPSI) as clock input. Data entry occurs on the high-to-low transition of CPSI; the quiescent state of the clock is low. For CPSI to effect shifting, the serial input enable (IES) input must be low. The decision to assign individual pins for the CPSI, PL, and Ds inputs was deliberate, since the chances of entering data in both serial and parallel formats at the same time are rare. Hence, the use of one parallel data input pin for serial data entry is possible. However, in disc controllers, parallel data come from the computer data bus and serial data come from the disc read electronics. If the same pin were used for both types of data, an external multiplexer would be required to feed into the FIFO buffer. Assigning individual pins eliminates this requirement.

Whenever the input register receives four data bits (by serial or parallel entry), the status flag, input register full (IRF), output goes low. If the transfer-to-stack (TTS) input is activated with a low pulse, data



from the input register are transferred into the first stack location, provided this location is empty. As soon as data are transferred, control logic attempts to initialize the input register so that it can accept another word. However, initialization is postponed until the PL input is low. The device is designed so that IRF can be connected to the TTS input. With such a connection, when a data word is received by the input register, the word automatically enters the stack and falls through toward the output, pausing on the way as needed for an "empty" location. Initialization of the input register causes the IRF output to go high. A high on IRF shows that data may be loaded into the input register.

Normally, output register empty $(\overline{\text{ORE}})$ is low, indicating that the output register does not contain valid data. As soon as a data word arrives in the output register, $\overline{\text{ORE}}$ goes high to indicate the presence of valid data. If the output enable $(\overline{\text{EO}})$ input is low, the 3-state buffers at the output are enabled, and data are available on the Q_0 through Q_3 outputs. If the $\overline{\text{EO}}$ input is high, the 3-state buffers are disabled and, hence, the outputs will be in a high impedance state

大十日子十四日十四年 日本日十日十七日十日

Data can be extracted from the output register either serially or in parallel. The Q_s output is used for serial data output, and $\overline{\text{CPSO}}$ for the associated clock input. The Q_s output is also driven by a 3-state buffer; however, its enabling is controlled internally. The output register is shifted on the high-to-low transition of the normally low $\overline{\text{CPSO}}$ input. As soon as the last data bit is shifted out, $\overline{\text{ORE}}$ goes low, designating an empty output register.

The quiescent state of the Tos input is low. A high-to-low transition on this input allows new data to be loaded from the stack into the output register. If data are waiting in the last stack location, they appear in the output register after the high-to-low transition of the Tos. If the last stack location is empty at the transition, any data that arrive into the last stack location automatically fall into the output register. The ORE output can be connected to the Tos input so that as soon as the last data bit is shifted out, other data are automatically demanded from the stack.

For the ToP input, the quiescent state is high. A low-to-high transition on this input allows data to be loaded into the output register. Moreover, a low level on the ToP input causes the $\overline{\text{ORE}}$ output to go low. ToP and $\overline{\text{EO}}$ inputs can be connected together so that data are made available at the Q_0 through Q_3 outputs when $\overline{\text{EO}}$ is low. When $\overline{\text{EO}}$ goes high to disable the Q_0 through Q_3 outputs, data are automatically demanded from the stack. Note that $\overline{\text{TOS}}$ does not affect $\overline{\text{ORE}}$.

In summary, TOS is used for automatically demanding data in the serial mode of operation and TOP is used for demanding data in the parallel mode. Also note that serial and parallel data outputs are assigned to independent pins. It would have been possible to share one of the parallel data output pins for serial data. However, in a disc controller, parallel data from the FIFO buffer are connected to the computer data bus, and serial data output from the FIFO buffer is connected to the write electronics of the disc. If a common output pin were used, a demultiplexer would be

needed to separate the serial data. Assigning separate pins eliminates this requirement. The output enable serial (OES) signal is used for serial expansion.

The FIFO buffer is cleared by a low on the master reset (\overline{MR}) input. This level causes the flag outputs \overline{IRF} and \overline{ORE} to indicate an empty condition; ie, \overline{IRF} is high and \overline{ORE} is low. The \overline{MR} input does not clear data flip-flops in the stack or output register; it only initializes the control section. Thus, the Q_0 through Q_3 outputs are not affected by the \overline{MR} input.

Expansion Capability

FIFO buffer organization has been designed so that LSI devices can be arrayed. Expanding vertically results in increased word storage; horizontally results in longer word lengths (in multiples of four bits). To illustrate the expansion connections, a FIFO buffer array consisting of eight devices is shown in Fig 2. If m 9403 devices are used in a row with n such rows in the array, 15n + 1 words of storage with 4m bits in each word are obtained. If 9423 devices are used instead of 9403, the results are 63n + 1 words with 4m bits in each word.

The D_s inputs of the first four devices are connected together, and serial data from the disc are entered on this line. The CPSI inputs are also connected together, and this line is used for shifting data. The IES input of device 1 is grounded, while the IES inputs of devices 2, 3, and 4 are connected to the IRF outputs of devices 1, 2, and 3, respectively. The TTS inputs of all four devices in the first row are connected together and to the IRF output of device 4.

After initialization by a low on the MR input, the IRF outputs of all devices in Fig 2 go high. Under these conditions, only device 1 responds to CPSI because its IES input is low; the next four clock pulses shift four bits of data into the input register of device 1; its IRF output then goes low. Control logic in device 1 inhibits CPSI from affecting this device any further.

The IES input of device 2 is now low, and the clock shifts data into the input register of device 2. On the eighth clock pulse, the IRF output of device 2 goes low and prevents further shifting into device 2. This process continues with devices 3 and 4. Therefore, on the sixteenth clock pulse, the IRF output of device 4 goes low and activates the TTS inputs of all four devices in the first row. The stack control logic in each device responds by transferring data into the stacks from the respective input registers; the input registers then are initialized. Thus, the IRF outputs of all four devices become high once again. An automatic priority scheme assures that if the IRF output of device 4 is high, the input registers of all four devices have been initialized.

In Fig 3 the timing diagram illustrates the serial entry of 16 data bits. Any attempt to clock data when the IRF output of device 4 in Fig 2 is low can be designated as a data overrun condition.

Parallel entry into the array in Fig 2 is made with a high level pulse on the PL inputs. In disc controllers, parallel loading is used during write operations to the disc. The same conditions prevail (ie, IRF outputs of all four devices are low) in the input section




Fig 2 16-bit FIFO memory array consisting of eight devices (two rows of four devices each). FIFO devices can be expanded both horizontally and vertically without external logic. Data are entered into or extracted from array in either serial or parallel format




Fig 3 Timing diagram depicting 16-bit serial data entry into FIFO memory array. Clocking occurs on high to low transition of $\overline{\text{CPSI}}$ input. $\overline{\text{IRF}}$ output of each device goes low to indicate that its input register is full. $\overline{\text{IRF}}$ of device 4 activates $\overline{\text{TTS}}$ of all four devices to initiate fall-through. Automatic priority scheme is designed into devices so that high level on $\overline{\text{IRF}}$ of device 4 guarantees that input registers of all four devices are empty. $\overline{\text{ITS}}$ is propagation delay from $\overline{\text{CPSI}}$ to $\overline{\text{IRF}}$ (typ 18 ns), $\overline{\text{IRF}}$ is propagation delay from $\overline{\text{CPSI}}$ to $\overline{\text{IRF}}$ (typ 31 ns)

that exist after the sixteenth clock pulse in the serial entry mode. Because all TTS inputs of the first row of devices are activated, data are loaded into the stacks. Note that initialization of the input registers does not take place until the PL inputs are low. During a write operation, a DMA request can be generated whenever the IRF output of device 4 is high. Data loaded into the stacks arrive into the output registers of the first four devices. When the MR input was activated to initialize the array, the ORE outputs of the first row of devices are low, and the IRF outputs of the second row are high. As soon as data arrive into the output registers of the first row, the ORE outputs go high. An automatic priority scheme exists in the output section also. Thus, a high on the ORE output of device 4 guarantees that valid data are present in all four output registers of the first row.

大人人 中心 中心 中心 中心 中心

4

The ORE output of device 4 is connected to the PL inputs of devices 5 through 8, as well as to the TOS inputs of the first row. Note that if serial extraction is not needed, the TOS inputs can be grounded. The EO inputs of the first row are also grounded; hence, data appear on the first row outputs. The high level on the ORE output of device 4 activates the PL inputs of the second row. Thus, input registers of the second row are loaded from output registers of the first row. The IRF outputs of the second row go low; the IRF output of device 8 is connected to the TOP inputs of the first row and to the TTS inputs of the second row. A low level on the TOP inputs of the first row causes their ORE outputs to go low. This makes the PL inputs of the second row low. Moreover, the low on the IRF output of device 8 activates the TTS inputs of the second row. Thus, data from the input registers of the second row go into their stacks. The stack controls in the second row initialize their input registers, and the IRF outputs go high. The automatic priority scheme mentioned earlier also is present at the inputs of devices 5 through 8. The high level from the IRF output of device 8 restores the TOP inputs of the first row to the quiescent high state.

If the stacks in the second row are full, activating the TTS input does not initiate a data transfer from the input registers. The IRF output of device 8 remains low until data are transferred into the stacks of the devices in the second row. Thus, as long as devices 5 through 8 are holding 16 words for 9403s (64 words for 9423s), the IRF output of device 8 remains low. This level also holds the TOP inputs of the first row low. As long as the TOP inputs are low, data cannot be loaded into the output registers by the stack control. Under these conditions, the first row of devices temporarily loses the ability to use its output registers for new data storage. As a result, the array of 9403s in Fig 2 has a storage capacity of 31 words instead of 32. For 9423 devices, the same array results in 127 words instead of 128.

Data loaded into the stacks eventually arrive at the output registers of devices 5 through 8, and the ORE outputs go high. Note that the automatic priority scheme is still in effect at the outputs, and a high level at the ORE output of device 8 guarantees availability of data. During a read operation from the disc, the ORE output of device 8 can be used to make a DMA request.

Available through 3-state buffers are the Q_s outputs of devices 5 through 8. These outputs are connected together to extract serial data for writing onto the disc. The CPSO inputs are connected together and driven by the write clock. When no valid data are present in the output register, the Q_s outputs are in the high impedance state.




Fig 4 Timing diagram depicting 16-bit serial data extraction from FIFO memory array. After shifting out four bits of data, $\overline{\text{ORE}}$ output goes low, indicating that its output register is empty. $\overline{\text{ORE}}$ output of device 8 activates $\overline{\text{TOS}}$ signal of second row of devices to demand new data word from stack. Automatic priority scheme guarantees that when $\overline{\text{ORE}}$ output of device 8 is high, data have arrived into output register of all four devices. T_1 is propagation delay from $\overline{\text{CPSO}}$ to $\overline{\text{ORE}}$ (typ 32 ns), T_2 is propagation delay from $\overline{\text{TOS}}$ to $\overline{\text{ORE}}$ (typ 26 ns)

The $\overline{\text{OES}}$ input of device 5 is grounded, while devices 6, 7, and 8 receive their $\overline{\text{OES}}$ inputs from the $\overline{\text{ORE}}$ output of the preceding device. As soon as data arrive into the output registers, the $\overline{\text{ORE}}$ outputs go high. The Q_s output of device 5 is enabled and contains information identical to that on the Q_0 output. The Q_s outputs of devices 6, 7, and 8 are disabled because their $\overline{\text{OES}}$ inputs are high. The $\overline{\text{CPSO}}$ clock shifts out the data bits in the same order as they are entered at the array input. After the fourth clock pulse, the $\overline{\text{ORE}}$ output of device 5 goes low and its Q_s output is disabled into the high impedance state.

The $\overline{\text{ORE}}$ output of device 5 inputs a low on the $\overline{\text{OES}}$ of device 6 to enable its Q_s output. Device 6 now begins shifting out its data, and the Q_s output is disabled when the device is emptied. Then, the $\overline{\text{ORE}}$ output of device 6 goes low and device 7 is enabled. The process continues until the last data bit has been shifted out and the $\overline{\text{ORE}}$ output of device 8 goes low. This activates the $\overline{\text{TOS}}$ inputs of the second row, and more data may be loaded into the output registers.

Illustrated in Fig 4 is the timing diagram for 16-bit data extraction. During a write operation, any attempt to shift data when the ORE output of device 8 is low will result in a data overrun condition. Data can be extracted from the array in parallel by making the TOP inputs of the second row devices low.

Automatic Priority Scheme

Most conventional FIFO buffer designs provide flag outputs analogous to the IRF and ORE outputs. However, when such devices are operated in arrays, unit-to-unit delay variations require external gating to avoid transient false indications. This technique is commonly referred to as composite status generation. The FIFO array described has been designed to avoid this situation. An automatic priority scheme is built in to assure that a slow device automatically dominates the array regardless of its location.

In Fig 2, devices 1 and 5 are called row masters, and devices 2, 3, and 4 are slaves to row master device 1. Similarly, devices 6, 7, and 8 are slaves to their row master, device 5. Row mastership is established by sensing the IES input during the period when MR is low. As described previously, a low MR input results in a high level at the IRF output. Thus, when MR is low, only the row masters have a low on their IES inputs (they are grounded). The IES inputs of slaves are high. This condition is sensed and stored by device logic to establish and retain row mastership.

All devices in any given row transfer data from their input registers into the stacks simultaneously. However, no slave can initialize its input register until its IES input goes high. Thus, initialization starts with the row master and eventually ends with the last slave in that row.

A similar situation occurs at the output registers of a row; data are loaded simultaneously from the stacks into the output registers of all devices in a row. Only the ORE output of the row master is allowed to go high. The ORE output of a slave cannot go high unless its OES input is high. Therefore, the row master is the first to indicate data arrival on its ORE output, and the last slave of that row is the last device to indicate data arrival. Although the automatic priority scheme allows arrays to be built with no external logic, this scheme is essentially based on a ripple effect, and maximum speed of the array operation is affected by the rippling. Design of the FIFO array is such that master-slave hierarchy can be easily replaced by traditional composite status logic to improve the array's operating speed; however, this would require some external logic.

Conclusions

FIFO buffers can be implemented using MSI elements such as counters and register files. However, such realizations require several integrated circuits even for modest word capacities of four or eight words. To use such a FIFO implementation as a local data buffer in a disc controller, serial-to-parallel and parallel-to-serial converter logic must be added. FIFO buffers first appeared as MOS/LSI devices several years ago, but were not accepted immediately for disc controller designs because of their speed limitations and cerial-to-parallel and parallel-to-serial conversion logic overhead.

A low power Schottky FIFO device (9403) is now available which surmounts many of the above disadvantages and offers 16 words of storage. Development of I³L technology made 64 words of FIFO storage economically feasible in the 9423. As this technology matures, larger FIFO buffers will become economical, and buffering a whole sector rather than a few words in a disc controller will be viable.

Bibliography

- R. Derickson and K. Rallapalli, "Universal First-In First-Out Memory Device," U.S. Patent 3,972,034, July 27, 1976
- K. Rallapalli, "Anatomy of a FIFO," Progress, Fairchild Camera and Instrument Corp, Mountain View, Calif, May/June 1977, pp 10-12
- K. Rallapalli, "FIFO Memory," Progress, Fairchild Camera and Instrument Corp, Mountain View, Calif, July 1975, pp 18-22 Macrologic/Bipolar Microprocessor Data Book, Fairchild Camera and Instrument Corp, Mountain View, Calif, 1976




Krishna Rallapalli is currently employed by the Computer Products group at National Semiconductor, participating in future systems development. Prior to this, he was involved in processor and peripheral controller designs, and performed managerial functions in application engineering pertaining to bipolar LSI products. He holds an MSEE from the University of Saskatchewan, Canada.

First...



Grayhill brought you the different DIP Switch.



Different actuations

4

Raised and recessed rockers for back panels Toggles for front panel usage Side actuated "Piano-DIP" for access from racked boards

Different circuitries

SPST in 9 sizes, from 2 to 10 rockers; the DIP-C®, SPDT switching and the Double-DIP®, DPDT circuitry in 1, 2, 3 and 4 rocker versions.

Toggle DIP[®] available with SPDT circuitry, 2, 3 or 4 stations; DPDT with 1 or 2 stations.


Piano DIP[®] (side actuated) from 4 to 10 stations, SPST circuitry under each rocker.


Different performance standards

Two exclusive features improve Grayhill DIP Switch reliability. Molded-in terminals protect against contact contamination. Reliable spring loaded sliding ball contact system provides DIP Switches life-rated at 50,000 operations, with positive wiping action and immunity to normal shock and vibration.

Different delivery standards, too

Most Grayhill DIP Switches are available off the shelf in production quantities from Grayhill or its nationwide distributor network.





For detailed information on Grayhill DIP Switches, consult EEM or write for Bulletin#276 to Grayhill, Inc., 561 Hillgrove Ave., La Grange, Illinois 60525, phone: (312) 354-1040.

Our first SBC 80 compatible systems for 1977!

4K to 64K RAM Up to 8K EPROM on one board

Now you can have RAM and EPROM on the same board and buy as much or as little memory as you need. And because our memories use 16 pin memory element sockets you can change your memory when you change your mind.

Speaking of changing your mind, when you want to change address locations of either RAM or EPROM, it's done with two, on-board switches—providing 16 possible start locations for each memory.

Compare these features with our much improved read, write and refresh cycle times and you'll choose MSC first.

16K RAM Version

Up to $16K \times 8$ of RAM and up to $8K \times 8$ of EPROM on the same board.

RAM expandable in 4K × 8 increments and EPROM expandable in 1K × 8 or 2K × 8 increments.

On-board DIP switches to select any of 16 address start locations for RAM and 16 address start locations for EPROM.

Cycle times: Read, 350 nsec. Write, 500 nsec. Refresh, 500 nsec.

Totally SBC 80 and Intellec MDS hardware and software compatible.

Limited one year warranty on parts and labor.

Delivery 30 days ARO.



MSC 4502

64K RAM Version

Up to $64K \times 8$ of RAM and up to $8K \times 8$ of EPROM on the same board.

RAM expandable in 16K × 8 increments and EPROM expandable in 1K × 8 or 2K × 8 increments.

On-board DIP switches to select any of 16 address start locations for RAM and 16 address start locations for EPROM.

Cycle times: Read, 350 nsec. Write, 500 nsec. Refresh, 500 nsec.

Totally SBC 80 and Intellec MDS hardware and software compatible.

Limited one year warranty on parts and labor.

Delivery 30 days ARO.



MSC 4602

Beginning firsts

Beginning with compatible memories, Monolithic Systems will continue to introduce SBC 80 systems with features which are firsts.

First to take advantage of the latest technology. And first in reliability, value and delivery.

You can be among the first, when you call us for SBC 80 compatible systems.

SBC 80 compatible systems... from the first.



14 Inverness Drive East Englewood, CO 80110 303/770-7400

Intellec is a registered trademark of Intel Corporation.

© 1977, Monolithic Systems Corp.

Integrated into a video monitoring approach that provides data processing and cost benefits for a diverse application, a digital interface accepts TV scanning signals and produces equivalent X and Y tracking coordinates—under microcomputer direction—that accurately define object movements

@ ×

4

かいかられた日本のからなると

Microprocessor-Based Interface Converts Video Signals for Object Tracking

Kenneth S. Lubinski, Kenneth L. Dickson, and John Cairns, Jr.

Virginia Polytechnic Institute and State University Blacksburg, Virginia

Recent advances in electronic technology have benefitted many indirectly related fields of research. In the process of investigating certain effects of environmental contaminants, a video monitoring system was developed to record and analyze the movements of individual objects (fish). A television camera tracks the object in a square observation tank, and the video signals produced by the camera are converted into 8-bit X- and Y-position coordinates by a video-microprocessor interface. A voltage comparator in the interface acts as an image detector, responding to negative voltage peaks in the video signal produced when the vidicon tube in the camera detects a dark image against a lighter background. An 8080-based microcomputer samples these coordinates from the interface, averages all coordinates along the object's length into mean X and Y coordinates, determines whether the object has moved far enough to warrant recording a new position, and, if so, stores the mean coordinates and the running time using a teleprinter and punch. The system is relatively simple and less expensive than more sophisticated video-digitizing equipment, has greater resolution capabilities than photocell-array systems, and does not require "pingers," miniature transmitters that are attached or implanted during ultrasonic studies. In addition, raw data produced by the system, a timeseries of X-Y coordinates, can be analyzed immediately or subsequently. This monitoring approach can easily be applied to situations where the analysis of the movements of objects in a 2-dimensional field is required.

System Description

The monitoring system includes the observation area, overhead television camera, video-microprocessor interface, 8080-based microcomputer, Teletype™ terminal (TTY), and a video monitor (Fig 1). The observation area is normally sealed off from external disturbances by a plywood housing, and internal indirect lighting evenly illuminates the area from above. Suspended directly above the center of the observation area, which measures 50 cm on each side, the television camera is oriented such that the video lines produced by it run parallel to the left and right sides of the tank (water flows slowly from the deep to the shallow end). Although each video field, or scan, is made up of 262.5 lines, only 200 of these travel across the observation area. Video signals are delivered to both the video-microprocessor interface and the video monitor; the monitor permits visual observation of the





Fig 1 Monitoring system. Video signal from television camera enters both video-microprocessor interface and video monitor. Interface generates digital X and Y coordinates of points along length of object, and microcomputer controls sampling of coordinates, data manipulations, and storage using teleprinter and tape punch. Raw data are a time series of mean X and Y coordinates (time in seconds followed by a 3-digit octal Y coordinate and a 3-digit octal X coordinate



Video signal. Camera produces variable voltage signal (1 V peak-to-peak) containing low amplitude vertical and horizontal sync pulses. High voltage peaks between these pulses represent light reflecting off boundaries (screens and baffle) of observation area, while low voltage peaks represent points along length of object. Video signal is fed into two voltage comparators whose reference voltages are adjusted to detect sync (VC1) and object pulses (VC2)

object's movements while its coordinates are being sampled and stored. Under normal conditions, water depth in the tank averages around 8 cm, reducing problems from parallax during up or down object movements.

Interface Operation

An explanation of video-microprocessor interface operation requires a brief description of the video signal produced by the camera. The video signal is a variable voltage signal (Fig 2) having a 1-V peak-to-peak range. Short (5-µs), low-amplitude horizontal sync pulses occur between each video line, and long (400-µs), low-amplitude vertical sync pulses occur at a 60-Hz rate between each video scan. Between these sync pulses, high voltage peaks correspond to bright images picked up by the vidicon tube in the camera and low peaks to dark images. For instance, high voltage peaks occur in the video signal when the vidicon tube detects bright light reflecting off the screens and baffle that make up the downstream and upstream boundaries, respectively, of the observation area. Each video line

that passes over the dark image of the object, on the other hand, contains a low voltage peak that corresponds to a point along its length.

In the interface, the video signal is input to two voltage comparators (Fig 3). A single integrated circuit (IC) (SN72720) houses both comparators, designated VC1 and VC2. These comparators and the other electronic devices in the interface are powered by the power supply for the microcomputer. The reference voltage (+) to VCl is adjusted to approximately 1.2 V using a potentiometer. This allows VC1 to detect the vertical and horizontal sync pulses described earlier. The reference voltage to VC2 is adjusted to approximately 1.5 V, which allows that comparator to detect negative voltage peaks that correspond to points along the length of the object. Outputs of the voltage comparators are transistor-transistor logic (TTL) compatible and are used to trigger the other digital devices in the interface.

Two digital counters (actually two pairs of 4-bit binary counters, SN7493A) run constantly in the interface and are the sources of the 8-bit numbers that serve as tracking coordinates. The first counter is reset to zero during each video scan when the video lines




Fig 3 Interface schematic. Generalized schematic shows all digital devices and signals used to convert video signal into X and Y coordinates. Coordinates originate in two pairs of binary counters, one triggered by VC1 and other by a 5-MHz crystal-controlled oscillator that divides each video line into 176 sections. Monostable multivibrators, MM1 to MM5, are used to limit periods during which object can be detected to those when video signal is traveling across interior of observation area, and also to reset counters

finish crossing the inside of the observation area. When the video lines again start crossing the observation area, they are triggered by VCl and produce Y-coordinates. The second counter is reset to zero each time a single video line leaves the observation area. When the following line reenters the observation area, this counter is triggered by a 5-MHz crystal-controlled oscillator. The oscillator divides the segment of each video line that falls within the observation area into 176 divisions, thus creating X-coordinates.

-

4

かってもないのようとなるとのという

Each data bit of the counters is connected to a latch (four separate latches are available on each SN7475 chip). Output of VC2, the comparator adjusted for detection, is gated into the enable (G) of all of the latches. Each time a video line crosses a point on the object that is dark enough to trigger VC2, the output from VC2 enables the latches. As a result, the binary numbers present in the counters at that point in time are transferred and held in the latch outputs. Output of VC2, however, must be gated into the latches to prevent them from being enabled by vertical and horizontal sync pulses. For this purpose, monostable multivibrators (MM1 to MM5) produce two separate gating signals; two monostable

multivibrators are available on SN74123 chips, and one each on SN74121 chips. Relationships between these signals and the video signal are illustrated in Fig 4.

Each gating signal must be at a high logic level for VC2 to enable the latches. The first gating signal is produced by adjusting MM1 to detect vertical sync pulses. MM1 is retriggerable and produces a positive pulse only if it does not detect a horizontal sync pulse within a 200-us time interval. Output of MM1 is fed through MM2 to MM3. These multivibrators create, respectively, the rising and falling edges of the vertical gating signal. This signal, therefore, allows detection only during the central portion of each video scan that passes over the observation area. Similarly, MM4 and MM5, triggered by VC1, produce the rising and falling edges, respectively, which make up the horizontal gating signal. This signal, however, allows detection only during the central segment of each video line. By using external capacitors and potentiometers to adjust the monostable multivibrators in the interface, the size of the detection area may be adjusted to almost any rectangular shape within the field of view of the camera lens. Outputs (Q)




Fig 4 Timing relationships between video and gating signals. Vertical and horizontal gating signals and output from VC2, the detection comparator, are input to a 3-input NAND gate. When all three signals are at a high logic level, data latches are enabled, resulting in transfer of binary numbers present in counters to latch outputs

from MM3 and MM5, which represent the complement of the gating signals, are used to reset the vertical and horizontal counters as explained previously.


Latch outputs are directed into 3-state gates; four gates are available on each SN74125 chip. Two separate device-select pulses for the vertical and horizontal coordinates are produced by a device address decoder in the microcomputer. These pulses are used to enable the 3-state gates to output either the Y- or the X-coordinate in the latches onto the data bus and into the accumulator register of the microcomputer.

Software Control

The microcomputer controls the sampling of coordinates during tracking and thereafter manipulates and stores the collected data. A software flowchart describing the operation of the microcomputer is shown in Fig 5.

After all counters and storage locations are initialized, the microcomputer waits for a 4-s flag that is produced internally by a crystal-controlled oscillator. At each 4-s interval, a running time counter is incremented through the use of a floating-point program resident in programmable read-only memory (p/ROM). Initially experiments were performed with faster sampling rates, but results proved that sampling once every 4 s was more than sufficient to accurately track objects at the speeds they exhibited. Even at this seemingly slow sampling rate, a constantly moving object could produce 9000 data points in a 10-h experiment, and this volume of data would approach the storage capacity of available paper tape equipment. Typically, between 4000 and 7000 data points were produced.

After the running time counter is incremented, the pair of coordinates present in the interface latches are input into the accumulator of the microcomputer via the data bus. These coordinates are then moved into the first two memory locations of a data storage buffer. A second pair of coordinates are then input from the interface, but are not stored in the data buffer unless the Y-coordinate of the pair is different from the Y-coordinate of the previous pair. If this



-

-SW

*

q ×

-

Fig 5 Flowchart of control decisions and sampling steps. At every 4-s flag, different X and Y coordinates are input into a data buffer until it is full. Mean X and Y coordinates are then calculated and printed along with running time of experiment, if object has moved a distance greater than one-half its length along either axis

step were omitted and the sampling happened to begin during a period of video lines that did not cross the object, the data buffer would fill up over and over again with the same pair of coordinates, representing the last point on the fish that was dark enough to trigger VC2. Coordinates are continually fed into the data buffer in this manner until it is full.

Size of the data buffer can easily be changed according to the size of the object being monitored. Other factors that must be taken into account in determining the size of the data buffer are how many coordinates are necessary to estimate accurately the object's mean location and how much time can be spent sampling coordinates from the interface. Objects that measure approximately 5 cm in total length have been monitored but usually only 60 to 70% of the length is dark enough to be detected by VC2. If an object this size orients directly perpendicular to the video lines, 10 to 12 lines may cross points that are dark enough to trigger VC2. An object oriented parallel to the video lines, however, may only be crossed by two to three lines. Typically, the data buffer size is set to hold 10 to 12 pairs of coordinates. This size buffer requires a maximum of only three to four video scans, or 51 to 68 ms, to become full even if the object's orientation is parallel to the video lines, while at the same time providing enough data points from which to derive accurate mean coordinates.

When the data buffer is full of coordinates that represent points along the length of the object, a subroutine is called to average both X- and Y-coordinates. Mean coordinates are stored, and a comparison is made between the current mean coordinates and the previous mean coordinates. If the object travels a distance greater than 50% of its total length along either the X- or Y-axis, the new mean coordinates are output to the teleprinter along with the running time of the experiment. Although this technique somewhat reduces the system's working resolution, it prevents unnecessary data from being accumulated during long periods of time when objects remain stationary. The new coordinates are then substituted for the old coordinates in memory. Fig 6 illustrates a sample of typical data output.

The present monitoring program occupies about 1k of random-access memory (RAM). The floating-point program resident on p/ROM occupies 1.25k and requires an additional 0.25k of RAM as a scratchpad. Currently, a more sophisticated software program is being developed for the video monitor system which will allow 15-min intervals of coordinate data to be analyzed for several parameters in real time. This program may require an additional 3k of RAM, and will require faster data storage capabilities than are now available with punched paper tapes. The parameters currently being analyzed by running the stored coordinate data through a larger computer include percent of time spent in motion, total distance traveled, percent of time spent turning, mean straight path length, and

Position	Time — VVV ₍₈₎ *	HHH ₍₈₎ **	DATA DESCRIPTION
а	4.000 — 262	233	/EXPERIMENTAL RUN NING TIMES ARE RE- CORDED IN DECIMAL COORDINATES IN OC TAL
b	8.000 — 211	237	
С	12.00 — 124	244	/MOVEMENT CONTINU OUS FROM POSITION & THROUGH e
d	16.00 — 037	242	
е	20.00 — 030	233	/OBJECT REMAINED STA TIONARY AT POSITION e FOR 140 S
f	160.0 — 071	217	
g	164.0 — 150	156	/CONTINUOUS MOVE MENT RESUMED
h	168.0 — 217	071	
1	172.0 — 300	051	

^{*} Vertical or Y (\uparrow) coordinate: 310s to 0s ** Horizontal or X (\rightarrow) coordinate: 0s to 260s

Fig 6 Typical output. Object movements result in listed output. Note that only mean coordinates are recorded if object has moved a prescribed distance from its previous position

total time spent in each of four quadrants of observa-

System Advantages, Limitations, and Possible Applications

The video-microprocessor interface provides several advantages over both methods previously used to monitor object movements and other general monitoring systems. The practicality and convenience offered by these advantages may well stimulate other applications of computer-controlled processes via video-monitoring.

This system's most obvious and important advantages over previously used methods are that movements can be recorded faster, for longer periods of time, with greater accuracy, and automatically without a full-time observer. These advantages are particularly beneficial because, traditionally, studies of animal behavior have been laborious, time-limited, and highly subjective. An additional advantage from a monitoring standpoint is that raw data produced by the system are immediately stored and can be analyzed later for any parameter that may attract sudden interest.

The major advantage of the video-monitoring system over other similar monitoring systems lies in its power of resolution. Photocell-array systems are limited in resolution by the number of photocells used; some other video-monitoring systems (see Ref) are similarly limited. At the same time, increasing the number of photocells in an array also increases the chances of device failure, which may be critical during long-term monitoring. In addition, photocell equipment is restricted to one use, while the video camera is portable and could easily be reassigned to other monitoring uses.

A final advantage of the video-monitoring system is that it represents an initial developmental stage and, with some minor modifications, could perform additional tasks. For instance, by positioning a mirror next to the observation area at a proper angle to provide the camera with a side view of the object, a 3dimensional position could be monitored. Alternatively, by storing additional coordinates (eg, maximum and minimum Y-coordinates sampled at each time interval and their corresponding X-coordinates), rotational orientation of the object to the water flow could be analyzed. These modifications would require some programming changes, however, and it should be noted that certain tradeoffs are necessary between how many points can be stored and how many analyses can be made on those points in real time.

**

*

T X

中北 的 并 所 所 都 於 即 於 都 以 如 多 之 分 於 於

The video-monitoring system is not without limitations. Its primary limitation is that the object being monitored must necessarily be darker than any other point in the observation area (although the system can likewise monitor bright points by reversing the inputs to the voltage comparators and by readjusting the reference voltages). Technically, voltage comparators are minimally sensitive to a difference of approximately 4 to 5 mV between their inputs; this represents the magnitude of how much darker (or lighter) the monitored object must be than background levels. Turbidity and variable background levels of light, therefore, create detection problems. For this reason, the system does not compare well with ultrasonic tracking systems, even though it does not require transmitters. Light limitations of the system for all practical purposes restrict its use to controlled-lighting environments. Time limitations of the system are caused by data storage and recording devices rather than by scanning time of the camera or response time of the interface. It should be noted, however, that in other applications where sampling time is critical, the 60-Hz video-scan rate may be limiting.

A list of possible video-monitoring applications to industrial control, measurement, and inspection processes was prepared by Sparks (see Ref). These include several processes that deal with the monitoring of moving objects such as particle counting, automatic speedometer calibration, pattern recognition, and operation of safety devices (kill-switches). Other possible applications might include liquid-level sensing and monitoring of flow rates or assembly line velocities. In any case, the video-microprocessor interface described should be adaptable to applications in many areas of research and industrial monitoring in addition to that of animal behavior, and the practical con-

veniences of video-monitoring in general should hasten the actual development of these applications.

Summary

The electronic structure and operation of a video-micro-processor enable an interface to convert standard video signals into 8-bit X and Y coordinates of sufficiently dark (or light) objects within the field of view of the camera. Advantages and limitations of the complete video-monitoring system in which the interface operates must be considered by designers when deciding on the applicability of the system to their needs. The main advantages of the system over other monitoring systems are in its speed and resolution capabilities, whereas its major limitation lies in its dependence on controlled lighting conditions.

Acknowledgements

The authors wish to thank Gary F. Westlake for his original ideas concerning the development and design of the interface and the Manufacturing Chemists Association for providing the funds for its development.

Reference

J. E. Sparks, "Television that nobody watches," Machine Design, Feb 10, 1972, pp 3-7




Kenneth S. Lubinski is a research assistant and doctoral candidate in the Biological Monitoring Laboratory of the Center for Environmental Studies at Virginia Polytechnic Institute and State University. He holds BS and MS degrees in zoology from Western Illinois University.



Kenneth L. Dickson is assistant director of the Center for Environmental Studies and an associate professor of zoology at Virginia Polytechnic Institute and State University. His research activities involve evaluation of environmental stresses on aquatic communities.



John Cairns, Jr is university distinguished professor and director of the Center for Environmental Studies at Virginia Polytechnic Institute and State University. His research activities involve evaluation of the effects of environmental stresses on aquatic communities.





XEBEC HAS AN OUT.

You package the world's most popular minicomputer. And that's your problem. There simply aren't enough PDP® 8's and 11's to go around.

Consider DEC's® LSI-11 with a full line of peripherals from XEBEC.

- Single and double-density floppies
- Cartridge disks
- 40 −300 MB storage modules
- Industry-standard mag tapes

All economical...reliable...and ready to ship. Not only for the LSI-11, but for the entire family of DEC minicomputers.

XEBEC. Think of us as the interface between their popularity and your future.



Xebec Systems, Incorporated 2985 Kifer Road, Santa Clara, Ca. 95051 Phone: 408: 988-2550/TWX: 910-338-0130

CIRCLE 37 ON INQUIRY CARD

® Registered Trademark Digital Equipment Corporation

APPLICATION NOTE

VMOS Peripheral Drivers Solve High Power Load Interface Problems

Lee Shaeffer

Siliconix incorporated Santa Clara, California

Design of VMOS-type peripheral drivers results in high output current, easy paralleling, transient immunity, negligible input drive, and no supply voltage to overcome disadvantages of traditional devices for logic interfacing to high power loads

Traditional peripheral drivers suffer from several problems when called upon to deliver high power to loads—output current is limited, paralleling to increase current capability is difficult, and damage by transients is possible when driving reactive loads where high current and high voltage are present simultaneously. Furthermore, most peripheral drivers require substantial supply and input drive currents, which make their compatibility with metal-oxide semiconductor or complementary metal-oxide semiconductor logic marginal.

A different metal-oxide semiconductor field-effect transistor (MOSFET) technology, the VMOS (Vertical MOS) process produces a peripheral driver that has a high output current capability, is easily paralleled, is relatively immune to transients, and requires negligible input drive power. Power required from the supply may also be neglected—no supply is needed. An additional advantage of




Fig 1 Cross-section of VMOS channel. High current chip is made by laying many channels side-by-side. S55V01/S55V02 series peripheral drivers, which conduct 2 A, have total gate length of 1.1" (2.8 cm) on chip which is 43 x 71 mils. Because current is automatically shared between channels, no special layout is needed



"After a head-to-head MTBF comparison, Digi-Data was Unitote-Regitel's choice"

George Groth — Unitote-Regitel V.P., Engineering

When you make point-of-sales systems for retail stores, your customers won't tolerate excessive downtime. And, since our reputation as a P.O.S. system pioneer is in the balance, we make doubly sure our System 430 has a synchronous tape drive that will last.

Unitote, a Digi-Data user since 1963, faced a decision to consider switching to another tape drive used by Regitel, a company acquired in 1972. However, when actual field service records for both tape drives were compared head-to-head, Digi-Data was selected. Continuing field records now show that the actual 41-month MTBF of the Digi-Data drive achieves a 33% edge, while the Formatter's 60-month MTBF was 2½ times better than the other tape drive.

This MTBF advantage, plus prices under competitive drives made Digi-Data the clear-cut choice for all three Unitote-

Regitel systems. Five different Digi-Data drives are used . . . each at a remote (in-store) or main (multi-store) central processor where reliability is paramount.

Through enhanced tape-handling features and ultimate design simplicity, Digi-Data drives are daily insurance against downtime for Unitote-Regitel P.O.S. systems customers. And that's what our business is all about.



DIGI-DATA CORPORATION

8580 Dorsey Run Road, Jessup, MD 20794 (301) 498-0200

® ... First in Value!

CIRCLE 38 ON INQUIRY CARD

Hard copy made easy.

With the help of a high-speed microprocessor, Hewlett-Packard combines exceptional performance and convenience in a new low-cost printer and printing terminal.

The HP 2631A printer and HP 2635A printing terminal with alphanumeric keyboard are the first members of a new Hewlett-Packard family of hard copy terminals.

Each machine was designed to give you a number of high-performance features. And both can support a variety of interfaces, including RS232 and CCITT.V24, to fit into systems made by HP and other manufacturers.


Bi-directional printing increases throughput. Both printers zip along at 180 cps in both directions, depending on your line layout. The microprocessor chooses the quickest path, and increases the speed even more by suppressing leading and trailing blanks.

High-speed slew for columnar data. When the microprocessor senses more than ten blanks in a row, it slews the print head at 45 inches per second to the next print position.

Three ways to print. The Character Compress/Expand Modes let you print more data on a page and emphasize points with headlines and titles. You can get as many as 132 characters on an 8-inch line, or 227 on a 14-inch line.

High-quality print, with six copy resolution. A 7 x 9 dot matrix (versus the usual 7 x 7) gives you clear, crisp printouts, right down to the sixth copy and meets the 128-character USASCII standard. And the extra two dot rows allow true underlining and descenders without character blurring.

Programmably interchangeable character sets. The HP 2631 can be made to print alternate character sets without reconfiguring the printer.



Long lasting, quick change print head saves service calls. The 9 wire print head is conservatively rated at a 100 million character life-span. It's also self-aligning. When you finally replace the head, you can do it yourself in a couple of minutes.

Long-life cartridge ribbon for a clean change. With a life span of at least 10 million characters, this innovative drop-in cartridge takes the mess and trouble out of ribbon changes.



Self-test for quick status checks. One key tells you if the printer is ready to go. If it isn't, the self-test feature helps you isolate the problem, reducing the time and cost for repairs.


Run everything under program control. All the features described and more can be programmably controlled. The software can take you in and out of the various modes. Or you can make a change yourself using one of the front panel switches or keys.

In a network or as part of a standalone system, HP now makes it simple to get the hard copy you need. If you'd like to see our printer or printing terminal in action, call the Hewlett-Packard sales office listed in the White Pages and ask for a computer systems representative. Or send us the coupon.

Yes, I'm interested in your new
Printer Printing Terminal.
Have your representative contact me.
Send me more information.
Send me OEM information.

Name
Title
Company
Address
City/State/Zip
Phone
Mail to: Bill Murphy, Marketing Manager, P.O. Box 15, Dept. 1208, 11311 Chinden Blvd., Boise, Idaho 83707

46701HPB2



devices produced in this way is a very fast switching time—4 ns to switch 1 A, when driven properly. When applied to peripheral interface systems, these features increase capability and reliability, and decrease power requirements and parts count.

VMOS Technology

While vmos performance is similar to that of a standard n-channel MOS (n-Mos) transistor, VMOS processing is similar to that of a double-diffused epitaxial (epi) planar transistor. Key advantage of vmos over standard n-Mos is that the vertical structure is capable of a much higher current density; appreciable current flows perpendicular to the chip plane rather than parallel, and may be conducted through a chip of moderate size. For example, a 43 x 71-mil vmos chip can conduct 2 A, while 10 A will pass through an experimental chip which is approximately 160 mils on a side.

A vmos channel (Fig 1) is started by growing an n-epi layer on an n+ substrate. A p-well, which later becomes the body, is then diffused into the epi, followed by an n+ source diffusion. A V-groove is preferentially (anisotropically) etched through the entire structure, with gate oxide and field oxide grown, and aluminum metal is deposited to form the source connection and gate. The groove effectively produces two channels and doubles the current density. Finally, the entire chip is passivated to prevent contaminants from entering the sensitive gate region.

The n+ substrate, which is also the drain, is the output connection, while the body and source are tied to ground, and the gate becomes the control and input terminal. In operation, the drain (output) to body (ground) diode junction is reverse biased and no current flows. When the gate is positive with respect to ground, however, n-type carriersinduced in the p-type body by the electric field surrounding the gatecreate the so-called "channel" through which current passes. Electrons can now flow from the n+ substrate, through the induced n-type channel in the body, and out the n+ source. Since this electron current passes entirely through n-type material, VMOS is strictly a majority carrier device.

Bipolar transistor operation is fundamentally different because electrons flow through the base region as minority carriers. Also, collector current is controlled by a low voltage (<1 V) and relatively high current input, rather than by a low current and relatively high voltage (approximately 10 V) input as it is for vmos. The difference between the operation of vmos and bipolar transistors is striking, considering the similarities in processing. Processing for a power transistor is essentially the same until the V-grooves are etched.

Comparing VMOS with a standard n-MOS transistor shows major processing differences, although electrical operation is nearly the same. Vertical structure gives VMOS the following advantages.

- (1) Defined by diffusion depths rather than by less controllable mask spacings, VMOs channel length is shorter, one to two microns versus five or more microns for standard processing. Since the current density of a MOSFET is proportional to w/l (channel width divided by channel length), its current density is three to six times greater. Therefore, for a given channel width—which is the primary determinant of chip size—the technology can deliver three to six times the drain current that standard MOS can deliver.
- (2) Shorter channel length also reduces chip capacitances by a comparable amount. For example, a 2-A VMOS geometry has an input capacitance of about 45 pF, while a standard device with equal current capabilities, if it could be fabricated, would have an input capacitance of 250 to 300 pF. The lower capacitance produces switching times which are approximately five times faster (4 ns versus 20 to 25 ns, with a 50-Ω pulse generator input).
- (3) The vMos epi-layer increases breakdown voltage, because it absorbs the depletion region from the reverse-biased body-drain diode junction. This layer is thin and is part of the drain, so it does not adversely affect performance other than by adding a slight series resistance. To achieve a high breakdown voltage in a standard MOSFET, the body—and therefore the substrate—must be lightly doped. Unfortunately, this makes the threshold voltage difficult to control, and renders the devices

susceptible to parasitic leakage paths created both by contaminants and by electric fields surrounding the drain metalization. Furthermore, gate oxide must be thick enough to withstand the entire gate-drain voltage (versus about one-third V_{DG} in VMOS), so that a high voltage standard MOSFET would conduct less current for a given input voltage.

Peripheral Driver Capabilities

S55V01/S55V02 series drivers conduct 2 A of continuous current, 3 A peak (at 35, 60, or 90 V breakdown) -considerably greater than the 300 mA specified for standard drivers. such as the 55450/75450 series. This extra current is needed when driving heavy duty relays, solenoids, and stepper motors. Extra power dissipation encountered at these higher current levels is not a problem, since the S55V01 series is packaged in a TO-3 header with a maximum power dissipation of 25 W, and the S55V02 series is capable of dissipating 6.25 W in a TO-39 package.

If greater current is needed, drivers may simply be paralleled, since they have resistive output characteristics -two devices in parallel will automatically share current. Furthermore, the temperature coefficient of their saturation (ON) voltage (VOL) is positive; thus, if one device draws more current initially, it dissipates more power and heats up. This, in turn, causes Vol to increase, forcing the other paralleled drivers to conduct a greater share of the current. Power-wasting buffers or ballast resistors are not needed for eliminating the current hogging prevalent in bipolar output stages. The only compensation needed for paralleling VMOS devices is the inclusion of a noncritical resistor (300 Ω to 1 k Ω , 0.25 W) or ferrite bead in each input lead to prevent high frequency oscillations. The current mismatch between paralleled devices is usually less than 20%.

The same phenomenon responsible for automatic current sharing also increases the reliability of a single device, because hot spots cannot develop during switching transitions. If current tries to flow more heavily through a particular portion, the chip heats up only slightly before the excess current is forced to other areas on the chip. Bipolars behave


Andr.

THE PDP-11 AND NOVA COMPATIBLE SUBSYSTEM YOU NEED IS BEING DELIVERED TODAY BY WANGCO

Societé de la constant de la constan

Magnetic Tape Subsystems, vacuum column and tension-arm designs, with speeds from 12.5 to 75 ips are offered in one to four drive configurations, formatted in PE, NRZI or dual density. Autoload cartridges or open reel tape from 7 to 10½ inches are available.

A new totally cost effective cartridge disk subsystem for NOVA users gives 20 Mbytes per drive capacity at 200 tpi... up to 80 Mbytes in a compact, four drive system. RDOS compatible, this new product joins Wangco's full line of high performance disk subsystems for PDP-11 and NOVA.



provide all necessary logic for reading and writing PE or NRZI formats on both 7-track and 9-track tapes. The space and cost saving microprogrammed embedded formatter is contained on a single multi-layer PWB within the transport.

Magnetic Tape Formatters, embedded or stand-alone models,

to PDP-11 and NOVA computers are available in one to four drive configurations for low cost data storage in IBM compatible format.

Wangco single-source systems feature high
Wangco delivers the broadest line of PDP-11 and

Wangco delivers the broadest line of PDP-11 and NOVA compatible tape and disk subsystems in the industry, including drives, controllers, formatters and diagnostic software, all designed together to work together more reliably and more economically. Whether OEM or end user, Wangco meets your requirements through an extensive network of direct sales, distributors and service/support centers. Contact Wangco for full information. Wangco, a

Division of Perkin-Elmer Data Systems, 5404 Jandy Place, Los Angeles, California 90066. (213) 390-8081. In Europe: P.O. Box 7754, Building 70, 1st floor, Schiphol-OOST, Netherlands. Phone: (020) 458269. TWX: 844-18822 WANGCO NL.

Flexible Disk Drive Systems for interface

WANGCO PERKIN ELMER DATA SYSTEMS

CIRCLE 40 ON INQUIRY CARD

Wangco single-source systems feature high-performance PDP-11 and NOVA compatible controllers designed to work at maximum efficiency and lowest cost with Wangco disk and tape transports. Compact controller design requires minimum space in the

host computer.

in just the opposite way; a hot spot conducts even more current, which further aggravates the problem and decreases reliability due to resulting high temperatures, metal migration, and secondary breakdown. This should be considered when switching inductive loads, such as relays, solenoids, or magnetically actuated printer hammers, since peak voltages are often present simultaneously with peak currents.

Another major advantage of the technology is its low power requirements: drive current is 10 nA typical, 500 nA maximum. For an input drive of 10 V, this represents a maximum power dissipation of 5 µW. If a CMOS gate has an output current capability of 1 mA, and switching time is not important, the gate can simultaneously drive two thousand VMOS peripheral drivers (a fanout of 2 x 103. Conversely, bipolar peripheral drivers designed to mate with cmos logic, such as the 1631, require 50 to 200 µA typical, a current factor of at least five thousand more. vmos, therefore, is suitable when many peripheral drivers are to be driven from a single logic element, or when the logic itself is low

A second power consideration concerns the current that the peripheral driver draws from the logic supply. In a typical bipolar driver, logic consumes roughly 5 mA, which is 25 mW at 5 V or 75 mW at 15 V. Direct power supply requirements of a VMOs driver are zero, because it requires no logic supply; it obtains its required power from the logic element driving it. This saves more than 0.25 W when ten loads are driven.

Complete lack of a power supply connection represents an additional advantage when the load is located away from the logic. By physically incorporating the vmos driver into the load as a buffer, the load presents a high impedence to whatever logic element it may be connected. Only two high impedance connections—the control input and ground—need to be made between the logic and buffered load.

vmos peripheral drivers can switch very quickly—1 A in 4 ns when driven by a $50-\Omega$ pulse generator. This high speed is a definite advantage when driving PIN diodes or laser diodes. Of course, this speed is not possible unless the device is




Fig 2 CMOS logic interface. All that is required to interface S55V01 to digital CMOS is simple connection (a). Switching times are on order of 50 ns and depend somewhat on logic supply voltage (b). Switching speed is doubled by connecting four CMOS gates in parallel to quadruple available peak input drive current (c) and (d)


driven fairly hard. Still, when driven by standard CMOS logic, it can switch within 25 to 30 ns, including the delay introduced by the gate itself.

Several inherent factors must be evaluated when designing with VMOS. First, VMOS peripheral drivers do not have sharply defined switching transitions; that is, there is no definite voltage for which a peripheral driver is fully on or fully off, since it actually has a linear transfer characteristic. Output current capability of the drivers is about 700 mA with a 5-V input (V_{IH}); the guaranteed minimum is 300 mA. Increasing V_{IH} to 10 V raises the output current (I_{OL}) to 2 A typical, 1 A minimum. In the off state, the output current (I_{OH})

is a maximum of 1 mA with an input drive (V_{IL}) of 0.8 V; taking the input closer to ground reduces this current considerably $(I_{OH}=0.5~\mu\text{A})$ max for $V_{IL}=0$.

In most applications, the lack of sharp switching transitions is not a problem since on/off levels are fully compatible with outputs of CMOS logic. TTL can also directly drive VMOS, but some pullup or level shifting is helpful, or even necessary, when switching high currents. This may even be an advantage since limiting the drive voltage reduces the maximum surge current into the load.

A second design consideration is that the on voltage drop $(V_{\rm OL})$ in-



creases with increasing temperature because of its positive temperature coefficient—it nearly doubles when the temperature increases from 0°C to 150°. This phenomenon increases the power dissipation in the peripheral driver which, in turn, further increases the temperature. While this is not a factor at low power levels, a good rule of thumb at high power levels is to increase the calculated power dissipation by 50% when figuring heat-sink requirements.

Applications

* * * *

がかないというと

Low input current requirement of the peripheral drivers is desirable when interfacing with standard

CMOS logic. Fig 2(a) is the simplest possible configuration—the driver is connected directly to the output of the VMOS, with no extra components needed. Fig 2(b) shows the switching response of the circuit for different values of logic supply voltage. Since the inherent delay of the driver is 2 ns, the CMOS gate is responsible for most of the delay in the circuit. The driver loads the CD 4011 NAND gate with 1000 M Ω in parallel with 65 pF, its input and Miller capacitance, which should be considered when driving multiple peripheral drivers from a single CMOS gate in an application where speed is important. To decrease switching time, the drive current to the driver is increased by paralleling several cmos gates [Figs 2(c) and 2(d)]. Of course, operation from the highest possible logic supply voltage (for example, 15 V) also ensures fast switching times.

Interfacing to TTL is not as straightforward since the output voltage swing of TTL is less than it is for CMOS. When driven by the minimum guaranteed V_{OH} of 2.4 V, the input drive to the VMOS is inadequate, and the peripheral drivers will switch currents of only 50 mA or less, which is far below their 3-A peak capability. A pullup resistor to V_{CC} should be used to increase the current capability to a guaranteed minimum of 300 mA, which is the output current realizable with a 5-V drive to the input [Fig 3(a)].

A better solution is to use opencollector TTL with its output pulled up to 15 V [Fig 3(b)]. Driven by the increased voltage, the driver will switch 1 or 2 A comfortably. If faster switching times (<30 ns) are needed, the best approach is the totem-pole drive shown in Fig 3(c). To achieve a fast turn-on time without an unduly small pullup resistor, which dissipates considerable power when the switch is in the off state, an emitter follower drives high peak currents into the capacitive VMOS input. A bipolar transistor may also be used to amplify the TTL voltage levels if open collector TTL is not available [Fig 3(d)]. Note that this circuit can be driven by any low level signal, including ECL, if a comparator such as the AM686 is used in place of the SN7400 quad NAND gate. Switching times of this circuit are less than 40 ns in both directions.

Interfacing to ECL is slightly more complicated due to its negative logic levels. The S55V01/S55V02 series can be used to buffer an ECL-compatible peripheral driver, such as the SN75441, which is good to 30 V and 150 mA. The S55V12, which is identical to the S55V01 except that its breakdown/saturation voltage is higher, increases these capabilities to 90 V and 2 A, respectively. The 75441 has an open collector output, so it interfaces to VMOS with either a pullup resistor or totem-pole driver (Fig 4).

Two vmos peripheral drivers are needed to make a line driver, since capacitive loads such as cables or long data buses require a bidirec-






Fig 4 ECL interface methods. S55V12 can increase voltage and current capabilities of 75441 ECL-compatible peripheral driver; (a) uses only pullup resistor on output of 75441 to interface to S55V12. Increased performance is achieved using totem-pole output in (b). ECL can be interfaced to S55V12 without use of 75441 with MC10110 circuit (dual 3-input, 3-output OR gate) shown in (c)





tional current drive. Fortunately, because of the simplicity of these peripheral drivers, it is relatively easy to source as well as to sink current into the load. However, the VMOS that is sourcing current must have its "ground" terminal connected to the output bus, and its input driven by a peak voltage whose value is greater than the positive supply for maximum efficiency. Bootstrapping (using a charged capacitor to generate a voltage higher than the positive supply) is therefore necessary since the output will only rise to within 4 or 5 V of the rail if the input is driven directly from the positive supply. The value of the bootstrap capacitor is small (about 0.05 µF at 500 kHz) because of the low input drive current requirements of vmos. Using several high speed bipolar transistors in an invertertotem pole arrangement produces turn-on and turn-off times of 20 and 30 ns, respectively, into a load of 50 Ω in parallel with 1000 pF.

Summary

VMos has several advantages when used to fabricate peripheral drivers. It requires negligible drive current and no power supply connection; thus, it is suited for CMOS logic and low power systems. In high power applications, it is rugged, reliable, easily paralleled, and extremely fast. Although fully CMOS-compatible, VMOS peripheral drivers will also interface directly to TTL, and to ECL with level shifting. Present VMOS peripheral drivers are capable of up to 3-A currents, 90-V breakdowns, and 25-W dissipation; even greater capabilities should be available in the near future.

Bibliography


L. Shaeffer, "vMos—A Breakthrough in Power Mosfer Technology," Application Note AN76-3, Siliconix inc, Santa Clara, Calif, May 1976

M. Vander Kooi and L. Ragle, "Mos Moves Into Higher Power Applications," Electronics, June 24, 1976, pp 98-103

L. Shaeffer, "Use FETs to Switch High Currents," *Electronic Design*, April 26, 1976, pp 66-72

D. Hoffman, "A vmos Line Driver Achieves High Speeds," Siliconix Inc, Santa Clara, Calif, July 1977

iCOM's Intelligent Floppy."



Controller/Formatter built-in. Packaging problems designed out.

When designing a floppy disk into a compact microcomputer-based system, engineers have been plagued with the problem of where to mount the controller/formatter cards and associated cables.

Our new FD5200 Intelligent Floppy™ solves this packaging dilemma by mounting all circuitry, including the single chip LSI controller/formatter, as an integral part of the disk drive chassis. A neat idea!

The 8 bit bi-directional bus makes it simple to integrate the iCOM® FD5200 into any system. Accrued benefits include: reduced hardware costs, smaller size, shorter assembly time, easier software development, improved reliability and lower maintenance. A mighty impressive list!

Compatibility to IBM 3740 Format... and Others

The special LSI controller/formatter chip provides the complex logic needed to write data on the diskette in IBM 3740 format — or other user selected formats as well. Another big plus is a phase-locked-loop for data and clock bit separation, and address word detection, which maximizes data reliability.

Pertec Makes the Driving Easy...

Since a floppy disk drive system is only as good as the mechanics, we use our field proven Pertec drive with three stepper-track head positioning for better accuracy and the unique head retract system for longer media life.

Why iCOM®?

iCOM® part of Pertec Computer Corporation, is one of the world's largest manufacturers of Microperipherals® Thousands of our floppy disk systems are operating reliably in the field. And many major computer manufacturers have incorporated iCOM® floppies into their systems. Which means we deliver — and will be around to give you service whenever and wherever you may need it.

Speaking of Delivery...and Price

Our new FD5200 Intelligent Floppy™ is available now at a unit price of just \$795. Naturally, OEM discounts are available.


So phone us today. Or send for our

com

MICROPERIPHERALS

Products of Pertec Computer Corporation

Microsystems Division 6741 Variel Ave., Canoga Park, CA 91303 U.S.A. Tel: (213) 348-1391 TWX: 910-494-2788



GA counts in microcomputing.

There's not a machine that can touch GA's 220. Not from DEC, Data General, or anywhere else.

- 1. The only μ C with COBOL, FORTRAN and in-depth software support.
- 2. The only μ C with a full file management system.
- 3. The only μC to offer OEMs a wide choice of operating systems: like FSOS, DBOS, RTX, RTOS.
- **4. The broadest** μ**C instruction repertoire:** speeds program development, conserves memory, accelerates execution.
- 5. The only μ C that can handle big disks: I/O rate is 2.0 mB/second.

- 6. The fastest μ C: LDR/STR (indexed) 2.6 μ s.
- 7. The only μC with parity built-in: hardware test, verification, fault isolation, plus write protect.
- 8. The only μ C with a back-up power supply built-in: protects semiconductor memory from power failures.
- 9. The only μC with board-level operator controls, switches and displays: in a microconsole.
- 10. The only μ C with over 100 field-proven I/O controllers.

GENERAL AUTOMATION

A big break for OEMs: family compatibility, throughout General Automation's extensive micro/mini line, gives GA-16/220 instant access to multiple batch and real-time operating systems, and to software off-the-shelf.


 □ Rush me full details on GA-16/220 μC capabilities. □ Contact me for immediate requirements.
Name
PhoneExt
Clip coupon to company letterhead and send to General Automation, 1055 South East Street, Anaheim, CA 92803. Or call (714) 778-4800.

READ THESE TEN CHAPTERS. AVOID CHAPTER 11.

• Data General How To Handle
The Ten Biggest Risks
OEMs Take. ☐ I want to see how a computer vendor can help me. Send me your book today. ☐ I'm too busy to read another book. Have your salesman come and show me the way. Name Title Company Department Phone Address. City_ Zip_ Data General, Westboro, MA 01581, (617) 366-8911. Data General (Canada) Ltd., Ontario.
Data General Europe, 59-65 rue de Courcelles, Paris, France. Data General Australia, Melbourne (03) 82-1361 **Data**General © Data General Corp., 1977 We make computers that make sense

102

Compare the new Sanders Graphic 7 with other interactive terminals.



You'll draw a graphic conclusion.

Sanders' new Graphic 7 is plug-toplug compatible with practically any host. And our price is easy to take.

The new Graphic 7 is an intelligent terminal with all necessary hardware and software as standard -not cost-you-extra-features.

But the Graphic 7 doesn't just save you money when you buy it. It also saves you money after you buy it.

Simply wheel your Graphic 7 through the door and plug it in. No installation problems.

Your programmer won't have to spend much time with your Graphic 7. lt comes pre-programmed. Tire-tread design. Avionics defense

And your operators will be able to handle your Graphic 7 after a 10-minute briefing, because it works with a one-button initialize.

Application programs? Our Fortran-based graphic support package can reside in any host that supports Fortran.


And with the intelligence at the terminal, there's minimum impact on the host. You can do more work faster.

Sanders experience? Our graphic terminal systems are used in computerized production projects. systems. Flight training. Land-use management. Air traffic control. And dozens of other areas.

Compatible, fully equipped, very low priced. What other graphic conclusion can you draw than the new Sanders Graphic 7? Send for specs and specific applications. Sanders Associates, Graphic Systems Marketing, South Nashua, NH 03061. 603-885-5280.

SANDERS

LET'S PUT OUR HEADS TOGETHER.




The Facit 4540 Serial Matrix Printer has already made a name for itself with its standard 250 characters a second – all crisp, fullbodied and perfect throughout the 500 million character service life of the printhead. Versatility comes from the rare 9×9 dot matrix, and the Facit 4540 offers a genuine 100% duty cycle and entire elimination of adjustment and lubrication.

The whole secret is in the unique printhead and its microprocessor controlled impact printing mechanism.

Integration of mechanics and electronics has made Facit peripheral data products world famous.

Facit 4540 extends this tradition. So let's put our heads together. To make your systems more efficient, more competitive and more in demand.



Facit 4540 Serial Matrix Printer with the unique printhead.



FACIT-ADDO INC., 66 FIELD POINT RD, GREENWICH, CONN. 06830. (203) 622-9150. TELEX 96-5998.

TEGRATED COMPUTER SYSTEMS, INC. FLF-STUDY MICROCOMPUTER TRAIN

COURSE SELF-STUDY MICROCOMPUTER SOFTWARE HARDWARE

WHAT THIS TRAINING COURSE IS NOT

- NOT A KIT! This New Microcomputer Training System is FULLY ASSEMBLED AND TESTED. (Sparing you days of frustrated debugging.)
- NOT just another typical microcomputer (whose skimpy manual forces you to learn by trial and error). This is a unique SELF-STUDY COURSE based on a 650-PAGE WORKBOOK/TEXT.
- NOT a cheap or unpopular microprocessor (which will come to have the familiar "software lock" on you). This course is based on the 8080A MICROPROCESSOR
- NOT a useless "come-on" system requiring expensive peripherals such as a TTY or CRT. With its BUILT-IN KEYBOARD and DISPLAY, the Training System is easily portable and ready to use in your office or home.

Using the Training System, you will be taught both programming and hardware through clear explanations and scores of exercises on your own microcomputer. You will first learn each 8080 instruction through simple exercises which illustrate its effective use. These exercises then progress to more and more advanced techniques. Other exercises specifically teach how to debug your programs quickly and effectively. Furthermore, throughout the course, hardware design projects are coordinated with programming problems.

8

ph.

14

-

TA

94

典

4

10


Y

*



COMPUTER INCLUDES

- The 8080 Microprocessor
- . 0.5K CMOS RAM (with capability for battery back-up) • 1K MONITOR PROM
- 3 parallel 8-bit I/O ports Two serial ports • DMA channel • On-board 8-digit display and 25-Key Key board



Furthermore, the computer is easily expandable (see Course 536 below).

- Introduction to the training system
 Hardware fundamentals
 Software fundamentals • The 8080 instructions — one by one • Using the keyboard/display to load and check programs • I/O programming — parallel/serial • Using a programmable I/O device • Interrupt handling (vectored/priority)
- Organizing data in program (PROM) and data (RAM) memory Sub-
- routine structures Advanced math routines (trig, logs, floating point, etc.) Advanced I/O block data and DMA use Annotated work sheets for designing and implementing your own application

\$545.00 TOTAL PRICE


Includes: 8080A training microcomputer, educational monitor, coordinated 650-PAGE WORKBOOK/TEXT with exercises, software, flowcharts, block diagrams and schematics. A separate power supply (+5V-1.5A, +12V-0.8A) is available for \$95.00

S36 SELF-STUDY

This new Hands-On Interfacing Course includes a FULLY ASSEMBLED INTERFACING SYSTEM ready to connect with the training computer of Course 525, together with a 450-PAGE WORKBOOK/TEXT with dozens of exercises to teach you both the hardware and software to interface to

In addition to analog and digital I/O, other features include: Cassette interface for easy program storage and retrieval on any audio cassette recorder, RAM expansion space for larger programs, and TTY/RS-232 interfaces. Also included is a cassette with dozens of advanced programs including mathematics, games (ping-pong of course) and a real-time executive.

MICROCOMPUTER INTERFACING SYSTEM



KEY TOPICS

- Introduction to the interfacing hardware INTEL 8255 I/O ports
- INTEL 8253 Interval Timer Real-time Clock Cascaded Timers
 Waveform Generators Numerical Integration Pulse Width Modulation
- D/A Conversion Music Generation Motor Speed Control (open and closed loop) A/D conversion Digital Voltmeter Digital Thermometer
 Calibration Linearization Proportional Temperature Control Real-
- time Interrupt-driven Executive Advanced Interfacing Techniques

\$495 total price

Includes: Interfacing System, cable to training computer, coordinated 450-PAGE WORKBOOK/TEXT with exercises, programs, flowcharts, block diagrams and schematics, and cassette with programs.

BOOKS & CASSETTES

SELF-STUDY AUDIO CASSETTE COURSES

Now you can benefit from our comprehensive, vendor-independent courses without leaving your desk. These microprocessor courses which have been attended by over 6000 engineers and managers world-wide are NOW RECORDED LIVE ON AUDIO CASSETTES

EACH SELF-STUDY AUDIO CASSETTE COURSE INCLUDES BOTH:

- 300-500 page course book
- 5-9 hours of instruction on easy-to-use audio tape cassettes keyed to the course book.

One Course: \$185 Additional Courses: \$175

COURSES AVAILABLE:

- 101: A MANAGER-LEVEL OVERVIEW OF MICROPROCESSORS AND MICROCOMPUTERS (249 pages)
- 102: MICROPROCESSORS/MICROCOMPUTERS: A Comprehensive Technical Introduction and Survey (420 pages)
- 111: MICROPROCESSOR PROJECT MANAGEMENT: Design, Manufacturing, QA and Field Service (220 pages)
- 156: SOFTWARE DEVELOPMENT. TOOLS AND TECHNIQUES FOR MICROCOMPUTERS (320 pages)
- 187: BIT-SLICE MICROPROCESSORS, PLA'S AND MICROPROGRAM-MING (310 pages)
- 220: MICROPROCESSORS IN MANUFACTURING AND INDUSTRIAL CONTROL (325 pages)
- *202: MILITARY/AEROSPACE MICROPROCESSOR SYSTEMS: A Comprehensive Technical Introduction with Applications (420 pages)
- *205: MICROPROCESSORS AND LSI IN TELECOMMUNICATIONS APPLICATIONS (400 pages)

*Books only

COURSE BOOKS: (with optional periodic updates)

All course books are available without audio cassettes if desired. Each book contains 300-500 pages of up-to-date course notes fully illustrated with system diagrams, flow charts, circuit diagrams, code, etc. . . . vital information to save you WEEKS of research.

One Course Book: \$99.50 Any additional Course Book: \$89.50 PERIODIC UPDATES: One year subscription: \$80.00 per course

TO ORDER Please Write:



Integrated Computer Systems, Inc. Self-Study Training Dept. 4445 Overland Ave., P.O. Box 2368 Culver City, Calif. 90230 USA

Telephone: (213) 559-9265 TWX: 910-340-6350

These Products Also Available in Europe. Contact: Integrated Computer Systems Publishing Co., Inc. Boulevard Louis Schmidt 84, Bte 6 B-1040 Brussels, Belgium Telephone: (02) 735 6003 Telex: 62473

Microcomputer Interfacing: Sample-and-Hold Devices

David G. Larsen Peter R. Rony

Christopher Titus Jonathan A. Titus

Virginia Polytechnic Institute & State University

Tychon, Inc

Sample-and-hold devices or sample-and-hold amplifiers are analog circuit elements equivalent to the digital latch. They are used to sample an analog signal and then hold it steady at a particular point so that a voltage of interest may be measured or used elsewhere in a system. Operation of an ideal sample-and-hold device (Fig 1) shows that the sample-and-hold output follows, or tracks, the input during the sample period and then holds the latest analog voltage when it switches to the hold mode. Input and output voltage lines in the Figure are offset slightly for clarity.

Concepts Relating to S/H Devices

Acquisition Time

Time required (generally a few microseconds) to go from the hold state to tracking state, in which output remains within a 0.01% range of input. This is also called settling time when the S/H device is already in sample mode. (Fig 4)

Offset

Difference between the device's input and output voltages when input is ground. It is generally in millivolts. Offset may be adjusted to zero using external components, but will usually change with time and temperature. (Fig 4)

Slew Rate

Maximum rate of change for output, expressed as V/s. It is a limitation imposed by the charging rate of capacitors and actual slew rates of operational amplifiers present in the S/H circuit. (Fig 4)

Aperture Time

Time period required by the device (usually a few nanoseconds) to go from sample mode into hold mode once the hold command has been received. (Fig 5)

Droop Rate, Decay Rate Rate of discharge of the S/H capacitor, expressed in mV/s, which is a function of switch leakage current and current required by other circuit elements connected to the capacitor. (Fig 6)

Gain Error, Linearity Variation of the observed output from the expected output over the S/H device's entire output voltage range. It is usually expressed as a percentage, say 0.01%. (Fig 6)

These sample-and-hold (s/H) devices are extensively used in conjunction with digital-to-analog (D-A) and analog-to digital (A-D) converters. For example, they may be used to:

- 1. Hold an analog signal steady so that an A-D conversion may be performed
- 2. Simultaneously sample many analog inputs for later measurement (requiring one s/H device per analog input)
- 3. Deglitch a D-A converter's (DAC) output to eliminate output voltage spikes or settling transients
- 4. Distribute one DAC's output to several points, where analog voltages must be constantly maintained

The second and fourth uses are becoming less important than they were two or three years ago. It is probably less expensive now to dedicate an A-D converter (ADC) to each input to be measured and to have one DAC per output, depending upon the specific application.

The most common use of s/H devices is to sample and hold an analog signal at a particular point while an ADC measures it. An s/н device is particularly useful in situations in which a DAC and comparator are used in conjunction with microcomputer software to create an ADC.1 When an s/H device is used prior to inputing the unknown signal to the comparator (or an ADC module if one is used), the digitization may give an accurate representation of the unknown voltage. For example, Fig 2 represents a block diagram of a typical s/H computer interface that permits the peak voltage from an instrument to be measured. It is assumed that the instrument provides a positive clock pulse, called PEAK, when the peak maximum is reached. The SAMPLE pulse from the computer allows the s/H module to sample the unknown signal from the instrument. When the peak is reached, the PEAK signal clocks a logic 0 into the output of the flip-flop, forcing the s/H device into the hold mode. Fig 3 shows the timing diagram that would be generated by the interface circuit in Fig 2. Again, the s/H output and instrument output have been offset for clarity. Now, either a slow ramp ADC or fast successive approximation ADC can be used to provide the correct value for the peak voltage since the s/H device will maintain the voltage until it can be digitized.

s/H devices are not, however, ideal. Some terms that aid in understanding their restrictions and uses are contained in the Listing and are illustrated in Figs 4, 5, and 6.2 As can be observed, there are important limitations to their capabilities. Those devices that have short acquisition times use small capacitors and thus will have a large voltage droop rate. Use of larger capacitors means longer acquisition times but less voltage droop. When high acquisition speeds and long hold times are required in an application, two s/H modules may be used. The first quickly acquires the analog signal at the point of interest, and the second acquires and holds the output from the first device. The second s/H device takes longer to acquire the voltage presented by the first device, but since a large capacitor is used, its droop rate will be much lower. Ref 3 provides further details.

A number of s/H devices are commercially available, eliminating the need to construct your own. The following

INTRODUCING THE BENDIX PORTABLE MODULE TESTER



1

14

W.

WA

M

4

Now automatic, on-thespot module testing is on the way.

Here's a new way to test anything from a printed circuit board to a complex logic system. And you can do it on the job.

Our new portable unit

weighs just 30 pounds and has no moving parts. Yet it does everything that stationary digital cabinet-type units can. It eliminates downtime while modules are tested away from the job site. Does away with trial-and-error testing and unwarranted returns, too.

You can take it on board planes or ships, to hospitals, to labs, to computers or communications equipment, and to sophisticated quality-

control operations in mass production plants.

Highly trained operators are not needed. Programming procedures are so easy to pick up. And an interactive display system makes operation easier still. Test systems are stored on solid-state cards, providing reusable data memory.


The Basic Bendix unit is capable of testing cards to 64 pins and has the capacity to expand to 256. Additional options are available including:

- · Fault Isolation Testing
- Digital Voltmeter/Frequency Counter
- Teletype Interface and Advanced Software Aids. For more information, contact: Bendix Corporation, Test Systems Division, Teterboro, N.J.

07608. Or call (201) 288-2000, extension 1789.

Bendix

CIRCLE 45 ON INQUIRY CARD






Fig 1 Inputs and output for ideal S/H device. Both sample and hold modes of operation are shown




Fig 2 Block diagram of typical S/H microcomputer interface circuit. Instrument supplies PEAK input pulse to flip-flop; SAMPLE pulse from computer presets flip-flop to logic 1




Fig 3 Typical timing diagram for interface circuit in Fig 2




Fig 4 Representation of acquisition time, offset, and slew rate³ (Courtesy of Analog Devices, Inc. All rights reserved)




Fig 5 Representation of aperture and settling times² (Courtesy of Analog Devices, Inc. All rights reserved)




Fig 6 Representation of linearity, droop rate, and feedthrough² (Courtesy of Analog Devices, Inc. All rights reserved)

list of modules, although not complete, is representative of those available.

Analog Devices, Inc SHA-5 SHA-1A	c, Norwood, Mass General-purpose General-purpose	\$ 47
		\$150
Burr-Brown, Tucsor		
SHC80KP		\$ 34
SHM60	High speed	\$104
Datel, Inc, Canton,	Mass	
	Low cost IC	\$ 8
SHM-CM	General-purpose, ±12 V	\$ 89
Hybrid Systems Con		
SH703	Low cost	\$ 22
Intersil, Inc, Cupert		
IH5110	Low cost IC	\$ 9
National Semicondu	ictor Corp, Santa Clara, Calif	
LF398	Low cost IC	\$ 5

Teledyne Philbrick, Dedham, Mass Model 4853 High speed

\$125

Prices of the above s/H devices are subject to change without notice; however, keep in mind that the general price trend is down, as is true for most semiconductor devices.

References

- J. A. Titus, Microcomputer Analog-Digital Conversion Devices, E & L Instruments, Inc, Derby, Conn, 1977
- D. H. Sheingold, Analog-Digital Conversion Handbook, Analog Devices, Inc, Norwood, Mass, 1972
- LF-398 Data Sheet, National Semiconductor Corp, Santa Clara, Calif, 1976

This article is based, with permission, on a column appearing in American Laboratory magazine.



THEOEMO

These products will make you rich

De

*

Every OEM wants a minicomputer that fits his specs. We've got 'em...a complete line of high powered minis with lots of bells and whistles. We're also making waves with the

best hardware in the business, backed by super software, excellent documentation, and extensive field support. And naturally, darn good pricing.


> If you need anything from our single board 5/16, 16-bit minicomputers, with the microcomputer price of \$868...to our high-powered 32-bit 8/32 Megaminis (onehalf the speed of the IBM 370/158 for about one-seventh the cost)...plus a full line of field proven peripherals, interfaces and software...you can count on Interdata.

We're the one vendor that works for you. with delivery dates you can live with, pricing that makes you rich, and support services that make you a hero. Hard to believe?

Just call me, Steve Sutker, OEM Marketing Manager, at (201) 229-4040.

A UNIT OF PERKIN-ELMER DATA SYSTEMS

Oceanport, New Jersey 07757, U.S.A.



Real-time problems? Systems has timely solutions.

Systems Engineering Laboratories has dedicated its 16 year corporate life to solving challenging real-time problems. The experience gained in solving these problems is what led us to pioneer the development of true 32-bit computer systems.

-

4

1

1

*

Y

8

Look into the operating systems, the languages, the data base system, the real-time device handlers and terminal systems, and you will see that we build for the real-time environment. That's our business.

Choose from a well-bred family of computing systems: The SEL 32/35, the SEL 32/55, or the SEL 32/75. Unlike other so-called "32-bit minis" that are only bridge-the-gap systems developed from essentially 16-bit architecture, all SEL 32 systems are true 32-bit machines. This results in richer instruction sets, more precision in data representation and larger, directly-addressable memory. All are available with throughput rates in excess of 26 million bytes/second.

Systems computers fit the term "minicomputer" in price alone. If your application is performance-sensitive, we'll save you money. If you're budget-sensitive, we'll give you more performance for your dollar.

The SEL 32/35 can be configured from 64K bytes to 512K bytes of 900 nsec memory. Resembling its more powerful brothers, the SEL 32/35 is a complete package, including control processor with floating-point arithmetic, memory, chassis, power supplies and cabinet.

The SEL 32/55 is offered in a variety

of both single and multiple CPU configurations, with from 32K bytes to 1 million bytes of 600 nsec memory.

The SEL 32/75, with up to 16 million bytes of main memory, has a concept so new, we had to coin a special term to describe one of its main features: Regional Processing Units. Working independently, these RPU's contain sufficient control and buffer storage areas to process an I/O region and transfer the resultant data directly to main memory. Computer system throughput is further enhanced by High-Speed Floating-Point Hardware and Writeable Control Storage.

Just circle our number on the Reader Service Card, or call us today. We'll send you the powerful story of the SEL 32 family.

SYSTEMS ENGINEERING LABORATORIES

SEND ME MO	ORE INFORMATION
I HAVE PRES	SENT NEED FOR SYSTEM
NAME	
COMPANY	
PHONE	
ADDRESS	
CITY	
STATE	ZIP

Added Quad Serial Port Module and Optically Isolated Digital Input Module Enhance Microcomputer Series

Two modules for the SuperPac 180 microcomputer series are the 1821 optically isolated digital input module and 1860 quad serial port module with total communications capability. Process Computer Systems, Inc, 750 N Maple Rd, Saline, MI 48176 developed the multiport input module to function in a 180 system under control of the company's 1806 or 1810 microcomputer system; the quad serial port module interfaces modems, computer peripherals, and other computers to the SuperPac series.

Digital Input Module

Interfacing of machines, instruments,

sensors, controllers, and other 180 microcomputer series devices is facilitated by the 1821 which provides complete isolation of the microcomputer from the process. A major feature is the module's ability to protect the microcomputer from electrical interference, ground loops, and common mode noise normally found in industrial environments.

Three configurations are available: the baseline module which accommodates 32, 24-Vdc digital input signals, and options A and B which are configured to accept 32, 115-Vac and 5-to 50-Vdc input signals, respectively. Optical isolation and bounce filters, as

well as individual reference return lines, are provided for each of the 32 inputs (organized as four 8-bit parallel ports).

1


10

The module is useful in either industrial or laboratory environments which develop ac or dc compatible signals for measurement and control purposes. Multiple devices may be used in the same chassis with other series modules to extend system input capability. All modules are automatically connected, upon insertion, through the Flexibus II backplane circuit board and connectors.

Circle 170 on Inquiry Card

Quad Serial Port Module

On the single PC board of the 1860 module are four independent, asynchronous, full-duplex, tri-function serial ports (RS-232-C, 20-mA current loop, and party line), each with optically isolated UARTS. Baud rates from 110 to 9600 are switch selectable on a per port basis.



Input interface of 1821 optically isolated module consists of 32 digital input bits organized as four 8-bit parallel ports. Inputs are optically isolated and multiplexed, and may be bit or byte organized by user program under appropriate software control. Bounce filters of 5 ms are provided for dc inputs; hold up circuitry is provided for ac inputs

112



...with Burroughs new microprocessor-controlled thin display systems!

Burroughs announces a major advance in its popular line of SELF-SCAN® gas plasma displays: *microprocessor-control and memory!* This means big savings plus the greatest operating and packaging flexibility *ever* in the flat panel display of alphanumeric information.

Your engineers will "light-up", too, as they discover operating advantages unmatched by any display. The new SELF-SCAN II displays are bright, crisp, easy-to-read. And, with Burroughs' unique new simplified control circuitry, the display panel — complete with electronics — is less than 2" thin for easy installation in compact designs.

The display's built-in microprocessor memory and control eliminate the need for you to design, develop and build circuitry to effect display operation. Just feed in appropriate 8-bit signals for the characters and control commands and you're in operation. Large system manufacturers save 95% of the engineering and development time formerly required and small system producers can now use displays since "design-in" cost is no longer a significant factor.


Adapting the Burroughs displays to your needs is as easy as a change in software. Their operation can be tailored for any product and changed for others with different display requirements.

The display subsystem operates off an 8-bit bi-directional buss or a TTL buss. Data can be entered at rates up to 1 MHz. and, with the addition of a keyboard and communication interface, it becomes a low-cost, compact data terminal!

The system's edit and control routine allows insertion, deletion and blinking of letters or lines, increasing or decreasing brightness, right-to-left data entry, etc.

Light up your customers and your engineers. And lighten your costs with Burroughs SELF-SCAN II microprocessor-controlled displays. For a copy of our SELF-SCAN Subsystems Brochure, write Burroughs Corporation, Electronic Components Division, P.O. Box 1226, Plainfield, New Jersey 07061 or call (201) 757-5000. Overseas, contact Burroughs ECD International, Buckingham House, The Broadway, Stanmore, Middlesex, England.

Burroughs



Quad serial module 1860 features RS-232-C, 20-mA current loop, and party line compatible interface circuitry for each serial port, selection of which is accomplished by connecting external device to specific pins provided on each user serial port connector. Port 0 is major modem compatible and ports 1, 2, and 3 are minor modem compatible. Up to 32 satellite microcomputer systems (remoted up to 1000 ft, 305 m from host) may be interfaced to host system via module

Each port allows independent software programmable options including parity bit generation and checking, odd, even, or no parity. Interrupt or polled operation may be selected by user software commands to the interrupt controller. Port interrupts, processed by the interrupt controller, operate in one of four modes: fully nested, rotating priority, maskable, and polled.

Interface circuitry providing RS-232-C serial communications is provided on each of four ports; circuitry for 20-mA current loop compatibility is identical for all ports. A high level digital output per serial port is provided for controlling a TTY paper tape reader. Party line operation may also be selected for each serial port, for distributed systems interfacing. Circle 171 on Inquiry Card

Programmable µComputer Analog I/O System Cuts Development Time

Electrically and mechanically plugcompatible with Motorola Micromodule and EXORciser microcomputer systems, the MP7400 is a low cost 8-bit analog I/O system containing both input and output on a single board. Burr-Brown, International Airport Industrial Pk, Tucson, AZ 85734 has accommodated up to 64 single-ended or 32 differential input channels, and

two output channels on each board, functioning as analog data acquisition and analog output systems, respectively.

The input portion includes an analog multiplexer, high gain instrumentation amplifier, 8-bit ADC, plus



Our new mini/micro computer printers... "the easy ones."

Features:

*

- Three popular ASCII input configurations
- Forty characters per line
- Internal data storage
- Double-width character selection
- Power line filter
- Optional tally-roll and/or fast paper feed

EASY TO INTERFACE

The new DP-1000 Series Printer family fits right into most minimicro computer and modem applications – thanks to three popular ASCII formats available in four different basic models.

Standard Baud rates from 110 to 2400 Baud, and internal storage of up to 104 characters (more optionally) with "hand-shake" control signals, let you pick from a variety of off-the-shelf configurations to fit your specific application.

EASY TO USE

A time-proven, dot matrix impact printing element can print 64 alpha-numeric and special symbols in 40 characters/line at 50 CPS on single or multiple-copy paper rolls. Options such as Tally Roll take-up and Fast Paper Feed, make the printers easy to fit point-of-sale and related fields.

Combining form and function, the modern package blends with virtually any surroundings, while


its flip-top design allows convenient access for paper replacement and servicing.

EASY ON BUDGETS

Best of all, single-unit prices for the DP-1000 Series start at under \$700, with substantial Dealer and OEM quantity discounts.

Want to see a demonstration in your office, or more details? That's easy too. Just contact Ken Mathews at Anadex; 9825 DeSoto Avenue; Chatsworth, CA 91311; Telephone (213) 998-8010; TWX 910-494-2761.





Components in block diagram comprise Burr-Brown's MP7400 analog I/O system for Motorola Micromodule and EXORciser. It serves to digitize low or high level analog signals. Single-board system is treated as memory input or output by CPU

timing, decoding, and control logic. The amplifier handles input levels as low as 10 mV FS allowing direct connection to low level inputs such as thermocouples.

Two 8-bit DACS with input latches and control logic comprise the output portion. A dc-dc converter is available for operation from the computer's 5-Vdc power supply.

Simplifying software implementation, the system interfaces to the microcomputer as memory. Any memory instruction can be used to access or write data. Memory mapped operation allows it to be used with or without halting the CPU, or in interrupt mode.

Input voltage range is ± 10 mV to ± 5 V, input overvoltage protection is ± 15 V, and input throughput accuracy is better than $\pm 0.4\%$ FSR on the ± 5 -V range. Output voltage range is strap selectable with five ranges to ± 10 V at 5 mA. Output throughput accuracy is better than $\pm 0.4\%$.

Circle 172 on Inquiry Card

Software is Efficient Memory and Real-Time Management System

A fast multitasking, multiuser, realtime operating system for 8080 and Z80 microcomputers, FAMOS[™] is an efficient management system which maintains dynamic, noncontiguous disc files; dynamic memory and program allocation; and extensive application of disc buffering in system functions and in the compiler. It supports more than 25 interactive terminals, in-house and remotely.

Multisessioning capability allows one terminal to perform as many tasks concurrently as memory will allow. MVT Microcomputer Systems, Inc, 21822 Sherman Way, Canoga Park, CA 91303 has also extended dynamic resource management to programs, file space, and buffers. System operates with 8k MVT-BASICTM compiler. Circle 173 on Inquiry Card

Input/Output Card Programs EPROMs for All Microcomputers

Working with microcomputers having 5-V I/O ports, the EP-2A EPROM

programmer needs 1½ 1/o ports and 256 bytes of microcomputer memory. Power requirements for the 2.2 x 4.3" (5.6 x 10.9-cm) card from Optimal Technology, Inc, Blue Wood 127, Earlysville, VA 22936 are 5, -5, 12, and 28 V with a maximum current of 150 mA for any voltage.

Software on paper tape is available for the Fairchild F8 kit #1 and Motorola MC6800 D1 evaluation card. A software listing is also available for the D2 evaluation card. A program p/ROM routine and verify routine comprise the software.

Circuit provisions include a 25-V regulator, 20-mA programming current limiter, and address counter. Jumpers added at the board connector permit programming of the Intel 2716 EPROM with no software changes. Circle 174 on Inquiry Card

Dual Floppy Disc Option Is Available for 12-Bit µComputer System

A dual floppy disc module interfaces the PCM-12 microcomputer system to Data Systems Design's model 210 floppy disc memory system. Fully plug-compatible with that model, the 12440 module from Pacific Cyber/Metrix, Inc, 3120 Crow Canyon Rd, San Ramon, CA 94583 allows users of the company's PCM-12 (see Computer Design, May 1976, p 210) to execute all PDP-8 floppy disc diagnostics, and makes it compatible with mass storage operating systems designed for the PDP-8 minicomputers. Circle 175 on Inquiry Card

Microprocessor Lab Facilitates Development of µProgrammed System

Microprogrammed systems, regardless of their architecture, can be prototyped and programmed with the microprocessor-based System 29, which includes a CRT console and dual-drive floppy disc configured and programmed for this purpose. The development system is a complete prototyping setup that can be used to develop hardware and firmware designs, and then check out the prototype design.

Introduced by Advanced Micro Devices, Inc, 901 Thompson Pl, Sunnyvale, CA 94086, the basic system consists of a mainframe with two separate systems in one package. A support processor includes an Am-

Our Level 6 Minicomputers: modular hardware, modular software, all under one umbrella.



The flexibility of having software that's as modular as your hardware. The security of having it all from a single vendor—with worldwide maintenance and support.

Honeywell has your requirements covered.

Modular Hardware. Level 6's fully open-ended architecture lets you select processors, memories, communications, and peripherals to meet just about any system requirements.

Packaging includes table-top, rack-mounted, and office versions. Options include the ability to address up to 2 million bytes of memory, a memory management unit, a powerful scientific instruction processor, and a wide choice of peripheral devices.

Modular Software. Our new GCOS 6 operating system features an array of software modules that you can assemble to match your individual needs. It's a multifunctional system that supports functions such as forms data entry and remote batch with local processing. Plus time-shared program development, terminal concentration, transaction processing, data base management, and file transmission modules that allow connection to Honeywell and other host processors, all in a real-time, distributed systems environment.


And GCOS 6 lets you run your own applications,

utilize Level 6 functions like transaction processing, and communicate simultaneously with a host processor – all on a single Level 6 system.

And Support. Level 6 is backed by Honeywell's worldwide support: systems analysts, instructors and a field maintenance force of over 3,500 in the United States alone.

n Systems, 87), Waltham, MA 02154
ormation on Level 6.
Put me on your mailing list
I've read enough, let's talk.

Honeywell



Digital announces a PDP-8 with an enormous memory,

Something big has just happened to the world's most famous small computer. In fact, something enormous.

*

T

1

42

04

Digital has just put 128K of memory into the PDP-8.

This act is brought to you by a powerful new memory management option called KT8-A. And by two new MOS memory modules that fit large amounts of memory into small amounts of space. Simply by adding these 16K or 32K modules in whatever combination you choose, you now expand your PDP-8/A into something bigger. What's even better, you can mix MOS and core. And that means you can protect your program in non-volatile core while you expand your data base in MOS.

And thanks to the KT8-A all this memory is under new management. Not only does the KT8-A let you address up to 128K words of memory, but it also offers you memory relocation and memory protection, while asking little in operating system overhead so you get faster system performance.

What's the cost of these enormous advancements? That's the next attraction.

The new PDP-8A MOS memory models are available at prices that are as crowd-pleasing as their performance. For a 16K 8A205 you'll pay as little as \$3900 (quan. 1). 8A425 with 64K

is as low as \$11,000. And the top of the line 8A625 with 128K is yours for as little as \$18,050.

They're the new bigmemory Eights from Digital. Step right up.

Large memories aren't our

only new trick.

New hardware and software improvements are also in

the PDP-8 spotlight.

The VK8-A is a new low cost PDP-8A option that provides high quality video output plus keyboard and printer interfaces. Video character generation uses a super-sharp 9x9 dot matrix for high resolution on single or multiple CRT monitors up to one thousand feet away.

Also new for PDP-8 users is MACREL/LINKER—a sophisticated assembler with MACRO facilities that lets you implement, expand and update your system faster while reducing software development time.

And last but not least there's DECNET 8—a series of software protocols that let you form your own PDP-8 network.
The PDP-8. Bigger.
Smaller. And better than ever.


A short while ago, we made big news with DECstation 78. A low-end system that set new highs for ease of use and simplicity.

Now we're expanding the PDP-8 family up, as well as down, and that means new opportunities for OEMs and end-users alike. Look into what's happening with PDP-8s. Call your nearest Digital sales office today.

Or send the coupon to PDP-8 Marketing Communications, Digital Equipment Corporation, 129 Parker Street, PK3-1/M34, Maynard, Massachusetts 01754. European headquarters: 12, av. des Morgines, 1213 Petit-Lancy/Geneva. In Canada: Digital Equipment of Canada, Ltd.


digital

PDP-8 Marketing Communications Digital Equipment Corporation, 129 Parker Street, PK3-1/M34, Maynard, MA 01754 Please send additional information about the PDP-8 family.						
Name	Title					
Company						
Address						
City	State	Zip				
	OEM					
Application						
		CD127				



DATAPRODUCTS' NEW ERA T-80 THERMAL PRINTER:

80 CPS FOR THE PRICE OF 30.



44

A.

Dataproducts' New Era T-80 thermal printer is nearly three times faster than other thermal printers.

Yet it costs about the same.

What's more, the T-80 offers you Dataproducts dependability,

assured by a smartly conservative design, a unique solid-state print head, and a minimum of moving parts.

Noise, too, has been minimized. The quiet T-80 hums at 80 cps, so it can be seen but barely heard.

And head changing is a snap.

Any operator can put in one of our incredibly small, self-cooling heads in a snappy 10 seconds.

Our New Era T-80 thermal printer, with its parallel or optional RS-232-C interface, is ready to tie into your CRT, your terminal, or your processor.

The T-80: fast, inexpensive, quiet,


and reliable.

Altogether, an unbeatable combination.



THE PRINTER COMPANY

NORTH AMERICAN SALES HQ: 6219 De Soto Avenue, Woodland Hills, CA 91365, (213) 887-8451; Telex 69-8492. EUROPEAN SALES HQ: Darmstaedter Landstrasse 199, Frankfurt, W. Germany, Phone 681034; Telex 841-416344.



Support processor of System 29 is configured and programmed to support a microprogrammed system. Advanced Micro Devices has incorporated facilities of an interactive editing system for building microcode definition and source files, a microprogram assembler for assembling microcodes, and prototype checkout workstation for debugging hardware designs

9080A CPU card; 32k-byte memory card, expandable to 64k; four RS-232 serial ports; a parallel port; and power supply. The microprogrammed system has one writable control store card of 2k x 64 bits; an instrumentation card; computer control unit

application card; five slots for user cards; and a power supply of 5 V, 25 A (50 A optional).

Available facilities are an interactive editing system, resident microprogram assembler, and prototype checkout workstation. Universal pro-

totyping cards allow prototyping within or outside of the system's structure. Software includes various microprogram aids, disc operating systems, and programs.


Circle 176 on Inquiry Card

LSI-11 Controls Minidisc Drives Through Interface Board

The MDC-11 multifunction controller allows up to three Shugart SA-400 minidisc drives [5¼" (13.3-cm) format] to be controlled by an LSI-11 computer system. Being produced by Andromeda Systems, 14701 Arminta St #J, Panorama City, CA 91402, the interface board provides a DMA dynamic memory refresh controller, minidisc controller, and sockets for up to 4096 16-bit words of EPROM. The single dual-width card containing these functions plugs into the LSI-11

Q-bus, using standard voltages (5 and 12 V).

Minidisc controller controls the drives via programmed command and



Physical configuration of dualdrive minidisc controller from Andromeda Systems shows SA-400 drives connected to MDC-11 board via controller cable. Minifloppy diskette is shown in front. Three useful functions of LSI-11 compatible interface are divided into minidisc controller, DMA dynamic memory refresh controller, and 4k x 16 EPROM area

Now-Remote Printing and Plotting:\$8180!

You could pay more for a printer alone. But now you can have remote print stations with plotting capability . . . for no extra cost. A new opportunity that should interest you . . . more than remotely.

The Printronix 300 lpm impact matrix line printer is the one that offers you several advantages. Like print quality on six-part forms other printers can't match. Or a 160 character capacity that gives you a standard 96 character set plus another 64 characters, such as OCR-A, large block characters, Farsi and many others. And the capability to plot bar codes, charts, graphs, and anything else that can be displayed on a CRT . . . at the price of a printer alone.

Our new Model P-300DC printer/plotter has an integral microprocessor data communication interface for direct communication with your host computer over switched or private telephone lines, emulating any one of the following line protocols: IBM BISYNC (2780) (3780) (3270); Burroughs; Honeywell (VIP-7700); or UNIVAC (DCT-1000). Remote printing. Remote plotting. Anywhere. Anytime. For \$8180.

If you order one today, we'll ship it tomorrow.

*\$8180 is the domestic U.S. price, which includes installation and 90 days of on-site service. No "extra" costs. Just extra performance.

Printronix, Inc., 17421 Derian, Irvine, California 92714. Call us at (714) 549-8272.





PRINTRONIX...

More than a remote possibility!

CIRCLE 52 ON INQUIRY CARD

data transfer. It automatically performs track seek and verify, 16-bit CRCC generation and checking, and drive motor timeout shutoff. In addition to data R/w capability, the board also formats the minidiskettes.

The DMA dynamic memory refresh controller, available separately, allows the user to disable the CPU microcode controlled refresh function. The EPROM section, accommodating up to 4k words of 2708-type or 8k words of 2716-type chips, permits critical software and data to reside in nonvolatile memory. It generates its own -5 V in an onboard inverter.

The EPROM may be addressed at any 4k or 8k increment. Also, standard LSI-11 bootstrap addresses may be mapped into the EPROM chips no matter where they are addressed. Several variations of the controller are offered.


Circle 177 on Inquiry Card

Advanced Diagnostic Techniques Form Basis of Microprocessor Analyzer

Designed primarily for field maintenance use as well as production and depot use, the MicroSystem Analyzer (µSA) combines two advanced diagnostic techniques—signature analysis and in-circuit emulation—to locate faults in microprocessor-based products. In-circuit emulation, implemented by connecting an umbilical cord from the analyzer to the unit's microprocessor socket, exercises the DUT in a precise, repeatable way. As



Portable MicroSystem Analyzer contains all facilities required to monitor and control fault isolation process in a 6800 or 8080 microprocessor-based system under test. Signature analysis and in-circuit emulation combine to provide capabilities that are more powerful than those of either approach used alone



the signal generating portion of the design, it is effective for diagnosing system faults at the module or function level. Functional testing can also be done on an inoperable unit.

Troubleshooting at the component level is achieved with the signature analysis option that provides signature probe, additional function keys, and signature analysis board. Locating faults by probing test nodes, this method causes a defined stimulus to be applied to the system under test and then observes the signatures.

Universal design of the tool, developed by Millennium Systems, Inc, 19020 Pruneridge Ave, Cupertino, CA

95014, permits it to be used with 8080 and 6800 microprocessors. Additional devices will be supported in the future, with the substitution of a CPU card.

Access to the system under test is via the keyboard and 20-character alphanumeric display. Both are under software control, allowing modification through program changes.

Expansion is possible with space for additional modules. Options include real-time trace of 128 transactions of 32 bits relative to a designated event, and communications module for connection to an RS-232 modem.

Circle 178 on Inquiry Card

Multiple Microprocessor Development System Adds 8085 Support

With complete 8085 software and hardware emulation, software development support, and hardware debug capability, the 8085 option for the 8000 series microprocessor labs from Tektronix, Inc, PO Box 500, Beaverton, OR 97077 extends coverage of this multiple-approach development aid to another microprocessor. Like the other 8080, 6800, Z80, and 9900

support packages (see Computer Design, April 1977, p 120), the 8085 option runs as a component of the total system approach to easing microprocessor-based designs.

Integration sequence has three stages involving emulation of program execution; debugging using the prototype's 1/0 and clock; and verification of normal operations by the prototype with the prototype control probe substituted for the emulated microprocessor. A real-time trace and debug capability is optional.

Circle 179 on Inquiry Card



Microcomputer Offers Multiple Function Capabilities on One Card

A one-card microcomputer for the F8TM based systems, the OCM/1 operates as a standalone board for low volume production, real-time emulation of pilot production, and field testing, or as a low cost development system using a teletypewriter or keyboard display. The board, introduced by the Instruments and Controls Div of Fairchild Camera and Instrument Corp, 1725 Technology Dr, San Jose, CA 95110, consists of a processor, memory, 1/0, and interrupt. Standard configuration incorporates two interrupts and two timers.

The processor includes 3850 CPU, 3853 static memory interface, clock generation, and reset circuitry. Contained onboard are 1k bytes of RAM for permanent storage; sockets will hold 2k bytes of EROM and 2k bytes of fusible-link p/ROM. The program storage unit (PSU) contains the FAIRBUG resident monitor for debugging.

I/o consists of the 3850 CPU and 3851 PSU, each with two 8-bit I/o ports. Two sockets allow two more PIO devices for four additional I/o ports. A circuit allows additional I/o capability of communicating with a teletypewriter, RS-232 device, or 20-mA current loop. An alternate PSU is available separately for low cost I/o. Circle 180 on Inquiry Card

Micromonitor Provides In-Circuit Hardware/ Software Debugging

COSMAC Micromonitor CDP 18S030 pemits in-circuit debugging of any CDP1802 microprocessor system hardware and software in real time, Avail-



able from RCA Solid State Div, Rte 202, Somerville, NJ 08876, the tool is housed in an attache case containing built-in keyboard, display, and status indicator lights, as well as software debugging routines. A self-test card simulates a user system to verify and assure the monitor's operation.

Controlled by a built-in microprocessor, the unit uses the 1802 CPU, power supply, clock, and memory of the test system to run a user program. Operation is either from the keyboard or from an external terminal if a hardcopy record is desired. Three modes are available for running programs.

Circle 181 on Inquiry Card

Microcomputer for OEMs Features Simple Analysis and Troubleshooting

The M68-MBC microcomputer system for OEMS consists of a hexadecimal keyboard, 6-digit hexadecimal display, monitor program, general-purpose board, and 4-slot motherboard. Mounting frame with brackets for front, back, side, or 19" (48-cm) rack panel mounting accepts three peripheral boards. Main computer board accepts up to 768 words of RAM, 2.5k p/ROM with optional p/ROM adapter, and TTY/CRT/cassette interface. Electronic Product Associates, Inc, 1157 Vega St, San Diego, CA 92110 provides onboard monitor program.

Expandable, Assembled µComputer Features Upward Compatibility


Circle 182 on Inquiry Card

Typical configuration of the Xycon III microcomputer from Computer Systems Unlimited, 25903 Peterman Ave, Hayward, CA 94545 consists of a 1.3-μs 8085 process card with master/slave capabilities, built-in RS-232/TTY port, real-time clock, and eight level interrupts. Other components include a 32k RAM, 63-key u/1c keyboard with numeric keypad, and 24 x 80 crt. The expandable system is compatible with a variety of peripherals. System software is also available.

Circle 183 on Inquiry Card

System for Peripherals and uProcessors Operates With Test Packages

Testing of microprocessors, microprocessor support chips, Roms, and RAMS takes a different approach with the MX-17 microprocessor family test system introduced by Adar Associates,



Inc, 11B North Ave, Burlington, MA 01803. A "conditioned natural environment" is used so that the logic sequence, through which the DUT is exercised, is written in the language of the microprocessor itself.

The user retains full programmable control over all test variables, including logic levels, bias voltages, all timing edge placement, and formatting of data, addresses, and clocks. System operating modes include basic go/no-go testing and sorting into bins.

Turnkey test packages for 8080A, 6800, Z80, and 8085 microprocessors as well as peripheral devices enable testing by simply loading the package into the system. Elements include a program cassette with complete logic sequence and test conditions, device programming unit which configures the system to test the device, a device board wired to the pinout of the DUT, and documentation package.

Circle 184 on Inquiry Card

Expansion Card Adds High Speed I/O to Computer Series

Series/80 board level computers based on the 8080 microprocessor have been expanded with the addition of the BLC 508 I/O expansion card, which connects to the system bus through the 86-pin card edge, and has a 100-pin edge connector for parallel I/O. The 8-bit parallel ports—four input

nov even better

Though it looks the same on the outside, today's Mini-Raycorder incorporates many improvements which make it even more reliable, easier to use and better performing than the original design. The Model 6409 Mini-Raycorder, which scored such a resounding success as the world's first tape recorder for ANSI proposed standard Mini-Data Cassettes, is now impossible to beat.

Check these new features for yourself:


Ball-bearing motor for improved reliability
New servo design for better tape handling
Full bi-directional operation available
Optional connector configurations available for easy interfacing
Improved cassette insertion and removal



CIRCLE 56 ON INQUIRY CARD



**



and four output with variable width strobe for peripherals—have data transfer rates as high as 1.3M bytes/ port. National Semiconductor Corp, 2900 Semiconductor Dr, Santa Clara, CA 95051 has designed all data, address, and control signals to be TTL-compatible. Operating on 5 Vdc, board accepts eight external interrupt requests which are buffered and passed onto the system bus.

Display Terminal Communicates With EXORciser System

Hardware and software development power of the M68SDT EXORciser are increased by the EXORterm 100, announced by Motorola Semiconductor Products, Inc, Microsystems Div, PO Box 20912, Phoenix, AZ 85036 as the first of a series of display terminals for the EXORciser development system. Communications between the two devices takes place via a detachable keyboard and RS-232-C serial communications link at manually selectable rates from 110 to 9600 bits/s. Keyboard contains 12 special encoded function keys plus standard teletypewriter terminal keys.

A video display using a 12" (30-cm) diagonal CRT presents user input and EXORciser response on 24 lines of up to 80 characters each. Terminal activities are coordinated by a self-contained micro-executive module operating in conjunction with control and application modules.

Circle 185 on Inquiry Card

Hardware, Firmware, and Software Features Enhance Microcomputer

The versatile modular microcomputer model 2000 is designed for OEMS, with maximum access to registers, in-

terrupts, and system diagnostics. Astral Computer Co, 991 Commercial St, Palo Alto, CA 94303 has based the computer on the 6800 microprocessor. It is available as a standalone single-board computer or in one of two enclosures complete with power supplies and 12-position motherboard.

Separate 10 x 4.5" (25.4 x 11.4-cm) cards contain the processor, memory (8k ram, 8k eprom, or both), I/O, and floppy disc interface. System is supported with extended 8k basic, assembler, text editor, and disc operating system software. Firmware consists of a powerful monitor that occupies the two available p/roms. Two separate interchangeable front panels are also available.

Circle 186 on Inquiry Card

Here's why you should rent your electronic test equipment from us...

You'll get action—When we tell you you'll get your equipment when you need it, it'll be there. Calibrated and ready to go.

You can count on our people—They're specialists, trained to help you find the most effective solution to application problems.

-water

You'll have a much larger selection— We have the largest electronic test equipment inventory in the nation. Over 17,000 pieces.

You'll find us nearby—We have Electro Rent inventory/service centers and representatives near every major city in the nation.

So call toll-free 800-423-2337 now!


(In California: 800-232-2173)

Or write our Marketing Manager at: 4131 Vanowen Place, Burbank, CA 91505 for a FREE CATALOG. Contact our Equipment Sales Division if you are interested in buying quality used equipment.



G.S.A. Contract #GS-04S-21907

CIRCLE 57 ON INQUIRY CARD



AROUND THE IC LOOP

Charge-Transfer Devices Part 2: CCD Memories

Eric R. Garen

Integrated Computer Systems, Inc Culver City, California

The first in this series of three columns dealt with the principle of operation of the three basic charge-transfer technologies—charge-coupled, bucket-brigade, and charge-injection devices. This second column describes some early charge-coupled device memories and systems and emphasizes the characteristics of two new chips with 64k-bit capacity from Fairchild Semiconductor and Texas Instruments.

Charge-coupled device (CCD) digital memories of course have been available for several years. Although early introductions included the Fairchild 9k-bit CCD 450 and 16k CCD 460 as well as the Intel 16k 2416,* these chips have seen relatively limited use. Because of their basically serial organization, they are obvious alternatives to disc and drum memory. However, these early CCD devices are generally economical only for requirements of less than 1M byte; in such small sizes, the high fixed cost of the mechanical drive system makes disc more expensive. Above 1M byte, even fixed-head discs are more economical.

The primary advantage of these first ccds was access time rather than cost. ccd access times of 250 to 1000 μ s were far more attractive than the 8 to 10 ms of disc or drum for applications such as "memory swapping" in timeshare systems. In addition, there was improved reliability and error rates. ccd memories equipped with even single-bit error correction encoding and decoding circuitry exhibit rates of 1 error per 10¹³ operations, and recent Fairchild data show the same rate with no error correction.

Within the last year significant advances have been made in ccp technology. Both Fairchild and Texas Instruments have been sampling 64k ccp memories for several months, and both expect to be in full-scale production by the publication date of this column. These 64k chips are so much more economical than the earlier 9k and 16k versions that the earlier chips are now virtually obsoleted for disc and drum replacement applications.

Fairchild's CCD 464 and Texas Instruments' TMS-3064 64k chips have the same structure from the user's point of view. Essentially, they are organized internally as 16 addressable 4k-bit shift registers. Each chip has

one data input line and one data output line (Fig 1) which can be selectively multiplexed to any of the 16 internal shift registers. The multiplexer is controlled by four address lines. Each of the 16 registers normally recirculates its data except during a write operation. In a write operation, data from the input line are written into the selected register while the other 15 registers are recirculated.

Both chips are rated at a maximum transfer rate of 5 MHz. Thus the maximum latency time (the time to read out any desired bit) is about 800 μ s (4095 shifts at 5 MHz) and the average access time is 400 μ s. The 16 x 4k organization was chosen to achieve a latency 16 times less than the latency of a straightforward 1 x 64k organization.

While each of the internal registers appears to the user as a single 1 x 4k shift register, in actuality it is organized in a serial-parallel-serial format (Fig 2). For example, each of the registers in the TMS-3064 inputs data into a "horizontal" 32-bit input register clocked at the 5-MHz rate. After 32 clocks, this register is full and the 32 bits are shifted in parallel into 32 "vertical" shift registers (each 126 bits long). These vertical registers are shifted downward at one thirty-second the rate of the 5-MHz horizontal clock. At the final stage, another horizontal register shifts the bits out in series at 5 MHz.

This serial-parallel-serial structure has several advantages. First and foremost, it requires far less power than a single 1 x 4k register since the vast majority of the bits are shifted through the vertical registers at slow speed. Because power consumption is proportional to frequency, this organization is vastly superior to a 1 x 4k register in which all bits would shift at high speed. The second major advantage of this structure is that each bit is transferred only 160 times (128 vertical and 32 horizontal transfers). Thus the

^oH. R. Crouch, J. B. Cornett, Jr, and R. S. Eward, "CCDs in Memory Systems Move Into Sight," *Computer Design*, Sept 1976, pp 75-80

The CRT terminal for the systems designer

You can change it to fit your system—instead of vice versa.

New microtechnology, new systems, new applications. It's all changing quickly. Our challenge: design a CRT terminal flexible enough to keep up with your ideas—one to help you make the most of your latest system, not compromise it.

The 480/25 is the result.

Need an intelligent CRT terminal?

100 M

10

T

WY

O.K. The 480/25 is an addressable/pollable intelligent CRT terminal that can accommodate a variety of protocols. It offers local editing, protected field formats, block transmission, and more.

It can save time; no time-fill characters needed, even at 9600 bits per second.

It offers cursor positioning by—and reporting to—the host computer.
And, of course, it can store forms locally and automatically check formats.

Need a cluster controller or a microcomputer?

Fine. One 480/25 can control a series of terminals and also communicate with a host computer. Or, you can add a disc, a printer, and expanded memory to a 480/25—and you've created a true microcomputer with integrated CRT and keyboard.

Etc., etc., etc.

The fact is, combine your software and the right peripherals and you can have 480/25 doing all kinds of handsprings for you. So instead of clamping a lid on your system, it can spring loose some great ideas.


Get the details.

It's easy, just ask.
Call (213) 966-3511. Or write.
CONRAC, 600 N. Rimsdale Avenue,
Covina, CA 91722



Check your OLS requirements today

Check what you look for in an off-line switcher	and check what our new OLS Model 10 gives you.	Check what you look for in an off-line switcher	and check what our new OLS Model 10 gives you.
☐ Brown-out protection	50 ms hold-up of output voltages at full load and Vin nominal.	☐ Synchronized outputs	All outputs are synchronously clocked to a 20 kHz switching frequency.
☐ High efficiency	70% typical, 65% min. at full load and Vin nominal.	☐ Short-circuit protection	Foldback (adjustable).
☐ High reliability	Conservative design with safe areas considered.	☐ Overvoltage protection	V _{out} + 10% to 20%.
□ Compact size	5-1/2" x 5-1/2" x 11"	□ UL, CSA, VDE approvable	When incorporated into your equipment.
□ Input line filtering	EMI line filter standard. Meets VDE and other domestic and international requirements.	☐ Adjustable outputs	5 V nominal, 4.8 to 5.3; +/-12 V nominal. 11.5 to 12.5(+/-15 V also available
□ Low noise	5 V output, 75 mV peak-to-peak max. +/-12 V outputs, 125 mV peak-to-peak max.	☐ Easy maintenance	95% modular circuit cards and subassemblies.
☐ Wide range temperature	0° to 60° operating temperature.	Write for the	OLS data shee
	OWERCUBI 4 CALVARY STREET, WA		



MICROPROCESSOR

New Features:

- ✓ 16 special centered symbols (in addition to the standard character set)
- Circle generation capability
- ✓ Enhanced vector length
- ✓ Will work with offline tape cassette

Call Rod Schaffner at (512) 837-2820

Tried and Proven Features:

- ✓ Totally interruptable without loss of origin
- ✓ Hardware character vector generation
- Error detection/retransmission
- ✓ 196 or 1024 character buffer
- ✓ Operates at 110,300 and 1200 baud
- ✓ Use with IBM 5100 calculator, Wang 2200 series and others listed in the brochure

houston instrument



DIVISION OF BAUSCH & LOMB

ONE HOUSTON SQUARE (at 8500 Cameron Road) AUSTIN, TEXAS 78753 TWX 910-874-2022 cable HOINCO

(512) 837-2820 TELECOPIER ER EUROPEAN OFFICE Rochesterlaan 6 8240 Gistel Belgium Phone 059/277445 Telex Bausch 19399

®A registered trademark of Houston Instrument

40 A M OF

1 4

438

1


48

0

KY

Another first

440 Kbytes on-line without a flip.



from number 1

Introducing Shugart's SA450 double-sided minifloppy.

Why flip? Nobody delivers this much on-line data storage from a single minifloppy disk drive with total compatibility. Nobody but Shugart offers a complete family of minifloppy disk products. Now a single minidisketter can carry operating system software, application programs or about 220 pages of text. All avaliable on-line. Reach 440 Kbytes (unformatted) with random access speed. Without flipping media. Two heads are better than one. The proprietary Shugart head design allows you to read and write both sides of the minidiskette. So you can write and read larger data files without the delays and risks that come from additional diskette handling. We promised. We delivered. The SA450 delivers true upward expansion based upon the industry standard 35 track format. This proven Format With a Future allows you to use single or double-sided minidiskettes without sacrificing the margin that you've come to expect with the minifloppy. Proven technology—single or double density. The Shugart SA450 minifloppy disk drive has the same compact size and low weight as the original minifloppy—the Shugart SA400. And it's electrically, mechanically, and media compatible. Double density (MFM/M²FM) is standard, but you can also operate single density on one side

or two. There's more. The unique direct-drive spiral cam actuator. Low heat dissipation, write protect, activity light, die cast base plate, and DC drive motor, too. But you get the idea. Nobody makes more minifloppy disk drives than Shugart. Over 25,000 have been installed since we introduced the little guy in September 1976. Nobody can claim more experience. So if you want 440 Kbytes of on-line storage, big


drive data integrity, with proven reliability—and you're into word processing, intelligent terminals, small business systems or home computing—you'll love the SA450. Why flip? You can have the real double-sided minifloppy from the people who started the minifloppy revolution. Shugart.






415 Oakmead Parkway, Sunnyvale, California 94086 Telephone: (408) 733-0100 West Coast Sales/Service: Telephone: (408) 252-6860 East Coast Sales/Service: Telephone: (617) 890-0808 Europe Sales/Service: 3, Place Gustave Eiffel, Silic 311 94588 Rungis, France Telephone (1) 686-00-85

**minidiskette trademark of Shugart Associate:





transfer efficiency (percentage of charge actually transferred from cell to cell) is far less critical than it would be for a 1 x 4k register.

Several key differences exist between the Fairchild and Texas Instruments chips. First, the Texas Instruments chip requires only the two high frequency (5-MHz) clock phases. From these the high capacitance driving, low frequency clocks are generated onboard the CCD chip. Texas Instruments regards this as an advantage over the Fairchild chip which requires four

external clocks, including two high and two low frequency clocks. Fairchild contends that inexpensive external clock drivers will suffice, and the cost is marginal.

Although Texas Instruments initially sampled some very large chips (60,000 mil²), the size of their current version is 192 x 210 mils (40,000 mil²), which is only slightly larger than the Fairchild 39,000-mil² size. The difference in size is partially attributable to Texas Instruments' onchip clocks, but even more to a unique seventeenth loop on the chip. This loop is not

Introducing Lear Siegler's Theory of Relativity.




What goes in must come out.

Lear Siegler, the manufacturer of world famous Video Display Terminals, now gives you hardcopy. The proven dependability in the Dumb Terminal[™] and his Smarter Brothers is built into the newest family member - the Ballistic™ Printer.

Its reliability lies in the simplicity of its patented Ballistic™ head, which has no moving cores attached to the wires. Instead, it uses small "swatters" that propel the matrix wires. And it's designed in such a way as to eliminate tube clogging with inks, dust, and paper fibers. Even wire tip wear is substantially reduced.

The Ballistic Printer prints bi-directionally, at 180 cps, using a lead screw drive direct, simple, positive, and very accurate. Gone are clutches, gears, belts, return springs and dashpots, along with the possibility of their malfunction or failure. Instead, a servo motor is used to move the head, providing



Patented Ballistic™ head.

substantially longer printer life.

Add to this such features as fully buffered input. Optional interfaces: serial, RS232, Parallel, and Current Loop. And you can see why we believe our Ballistic Printer is one of the most versatile printers you can buy.

stic™ head. And, of course, the Ballistic Printer plays well with Lear Siegler's entire line of Video Display Terminals.

So if you require a matrix printer with reliability, you should take a close look at ours.

You see, at Lear Siegler, we believe you should get out of your computer what you put into it. Relatively speaking, that is.

Ballistic Printer. Because what goes in, must come out.



Lear Siegler, Inc./E.I.D., Data Products, 714 Brookhurst Street, Anaheim, CA 92803; (800) 854-3805. In California (714) 774-1010.

CIRCLE 106 ON INQUIRY CARD





Fig 3 Pictorial representation of IN-65 CCD memory system data organization and operating speed. This system can be thought of as a pair of super fast head-per-track drums with 36,864 tracks, each made up of 128 storage cells for 9-bit bytes (Courtesy Intel Memory Systems)



4

Fig 4 Fairchild 1M-byte CCD memory board. This single board contains 162 CCD memory devices of 64k each for a total capacity of 1 million 9-bit bytes. It uses a 3-layer PC board with a center layer ground plane (Courtesy Fairchild Semiconductor)

used for data; instead it provides temperature compensation for improved performance over the full 0 to 70°C still-air range. Fairchild claims that they did not use the extra loop because their tradeoff analysis showed that the extra silicon does not sufficiently improve margins over temperature to be worthwhile.

This extra loop does solve a problem, however. Ordinarily, empty charge wells in the data loops tend to fill with charge as a result of leakage current, and leakage current increases rapidly with temperature. If a fixed "1/2" voltage were to be used for comparison when sensing the data wells for 0 or 1, a bias would develop toward 1 at high temperature. To compensate for this in their initial device, Texas Instruments shifts 1/2 charges into the seventeenth loop. As these 1/2 charges are shifted through this auxiliary loop, they will be augmented by any leakage current and reduced by any charge transfer inefficiency, at exactly the same rate as the data charges in the other 16 loops. Thus, they will serve as a perfect reference value for the comparison circuit to determine if each of the 16 data bits is a 1 or 0. Temperature effects thereby will be greatly reduced.

Fairchild designed the CCD 464 chip to be longer and narrower so that it fits into a 0.3" (0.76-cm) 16-pin package compared to Texas Instruments' 0.4" (1.0-cm) 16-pin case. The 0.3" (0.76-cm) package facilitates

the use of automatic insertion equipment, which may be a marketing advantage when chip volumes become large. Fairchild also points out that Motorola will second source their chip as part of the companies' technology exchange agreement. David Ford, Motorola's strategic marketing manager for ccp memories, says he expects the MCM-0464 to be sampled by the time this column is published.

An example of a memory system which utilizes such devices is the Intel IN-65. This CCD memory is organized as a system of eight PC boards, each containing 128k x 9 bits of storage. A board is logically arranged as 512 sets of nine parallel loops, so that each loop set stores data bytes in parallel with parity. Since a loop set is 256 locations long, it can be thought of as a 256-position, 9-bit wide shift register. There are 512 such 9-bit wide registers on a single board; thus a system of eight boards has a total capacity of 1,048,576 9-bit bytes. In effect, this system is comparable to a super fast head-per-track drum with 36,864 tracks, each consisting of 128 storage cells for 9-bit bytes (Fig 3). Because of its short loop length (256 positions), the maximum access time to any location is less than 300 µs, making this unit extremely attractive for memory swapping applications.

Considerably more density is accomplished on a developmental Fairchild memory system which packs 1



NOBODY, but nobody offers a fast **Head per Track Disc** at this LOW PRICE!

-except alpha data

THE MASS MEMORY TECHNOLOGISTS

MODEL -

- *Storage to 64 million bits!
- *8 millisecond access time!
- *Retractable head! No disc contact!
- *Shock mounted and sealed!
- *Controllers available for computer plug compatibility.
- *Small package!!

Get the whole picture-

call Ted Lincoln 213/882-6500

20750 Marilla Street, Chatsworth, CA 91311 TWX (910) 494-4914

million 9-bit bytes on a single 15 x 16" (38 x 41 cm) board-eight times that of the IN-65. This board contains a total of 162 Fairchild CCD 464 64k chips for a total operating capacity of 9,437,184 bits (1,048,576

9-bit bytes). Data density is 41.9k bits/in2.

On this board, data receivers, input latches, multiplexers, and output drivers are located adjacent to the contact pins in the section labeled as data 1/0 on Fig 4. Receivers, at the center of the contact pin edge, are provided for address, chip select, write enable, and clocks. By locating logic very close to the contact pins, in both receiving and driving circuits, lead lengths are kept short enough to eliminate the need for terminating networks.

Array address drivers, chip select, and write enable drivers are located in a center strip between the two halves of the CCD array. CCD predrive logic is located just above that strip with ccp high power clock drivers located on either side such that they are at the farthest points from the contact pins. Clock drive circuits drive the CCD memory array and are terminated near the

data 1/0 logic.

64k ccp memories are aimed not only at the rotating memory market, but even more directly at mainframe RAM. Currently, mainframe and minicomputer memory represent nearly one-third of the total semiconductor market; so CCD practitioners are not thinking small. They believe that a practical approach to reducing large computer memory cost could be to use a combination of a small, high speed mos or bipolar cache memory, a larger medium speed mos buffer, and a very large CCD main memory. To attack this market, CCD designers follow a rough rule of thumb—the one-third rule-which says that if the per-bit cost of CCD is roughly one-third that of RAM, CCD will win. So far, they are optimistic. The 64k ccp chips are about the same size as Intel's and Texas Instruments' 16k RAMS (although larger than Mostek's 27,000-mil² 16k RAM). Since the 64k CCD and 16k RAM rely on similar design rules and processing, the CCD designers expect similar yields and similar prices.

Of course, if the 16k RAM is initially used in higher volume, it could move down the experience curve somewhat more rapidly, thus dropping in price faster than CCD. The technologies are so similar, however, that it would be hard for any large difference to develop. CCD designers, therefore, expect to keep pace and hope to maintain a competitive chip price with the 16k RAM.

Price estimates have the 64k ccp pegged as

Year	64k CCD Chip Price (dollars)	Chip Price/Bit (millicents)
1977	65	100
1978	20	30
1979	10	15
1980	7	10

At these prices, CCD should be very competitive not only with RAM, but also with bubble memories (the subject of an upcoming column). Price projections for bubbles are not unlike those given for ccps, and the principle differences will be non-volatility of bubbles, denser packing of bubbles in the long run (CCD is better now), and higher speed of CCD (10X). Based on these projections, a system price of \$1400 for the Fairchild 1M-byte ccp board (Fig 4) will be feasible in 1980.

Just as exciting as these prospects for CCD memories, charge-transfer devices are now taking the fields of signal processing and image sensing by storm. They will be the subject of next month's column.

Another first for 155

THE INDUSTRY'S FIRST "SMART" FIXED MEDIA DRIVE

Announcing another in a long line of industry first's from ISS—the EFF 735—the first disk drive of its kind ever to employ an on-board microprocessor.

ent

Ta got

49

大百年 安田大百年四年 大年四年 日本

The advantages of microprocessor power in a disk drive are impressive. Complete internal drive diagnostics. Simplified circuitry because most analog circuits are eliminated. No field adjustments—ever. And a lot more, including microprocessor controlled routines that ease the

The EFF 735 gives you 353.8 megabytes on a single spindle using a fixed and sealed disk. There's one spindle per drive and each drive has its own internal power supply and air filtration system. Average access time is 23 milliseconds.

load on the controller and the mainframe.

With our fixed head option, you get another 1.26 megabytes and zero access time.

Besides the microprocessor, the EFF 735

Microprocessor makes it a "smart" drive.



gives you a sweeping lineup of operating and maintenance features. A single phase motor. Dual port capability. A completely electronic tachometer. Total modularity of subassemblies. And truly outstanding serviceability, with no field adjustments and no requirement for special tools—one of the big reasons why your total cost of ownership is exceptionally low with the EFF.

EFF stands for Expandable File Family. The 735 is the first member of this new ISS family, later versions of which will have even greater capacities and capabilities. And all versions will be field upgradable so you can increase performance as your needs increase.

ISS is an operating unit of Sperry Univace bringing technological leadership for the generations ahead. For more details on the new EFF 735, write or call OEM Marketing, ISS, 10435 N. Tantau Avenue, Cupertino, California 95014, telephone (408) 257-6220.

Fixed disk pack holds 353.8 megabytes.

EFF 735. The first "smart" disk drive.

SPERRY LINIVAC

Sperry Univac is a Division of Sperry Rand Corporation

Combination RAM-I/O Chip Consolidates Functions for Smaller Microprocessor Systems

Low end microprocessor-based systems which have relatively small memory requirements but which nevertheless require a number of peripheral interfaces are suggested as ideal for application of a combined RAM and I/O chip. The n-channel LSI device is said to do the job of five or more standard memory and peripheral interface units.

INS8154 was designed by National Semiconductor Corp, 2900 Semiconductor Dr, Santa Clara, CA 95051 to interface with the SC/MP II and other of the company's microprocessors. The memory portion of this dual function device contains 1024 bits of static RAM organized 128 x 8; the I/O portion consists of two peripheral ports of eight bits each. Each I/O pin may be defined as an input or an output to provide maximum flexibility and each port may be read from or written into in a parallel (8-bit byte) mode.

To improve efficiency and simplify programming in control-based applications, a single bit of 1/0 in either port may be set, cleared, or read with a single microprocessor instruction. This is claimed to be virtually unique among 1/0 devices.

In addition to basic 1/0, one of the ports may be programmed to operate in several types of strobed mode with handshake. Strobed mode together with optional interrupt operation permit both high speed parallel data transfers and interface to a wide variety of peripherals with no external logic.

The data bus buffer (see Figure), a Tri-State (R) bidirectional, 8-bit buffer, interfaces the RAM-I/O chip to a microcomputer data bus. Data, control, and status information are transmitted to and received from the chip via the data bus buffers. Execution of a store instruction by the microprocessor may be used to transmit data and control information from the CPU to the chip. Execution of a load instruction may be used to transmit data and status information from the chip to the CPU.

A low on CSO plus a high on CS1 chip select input pins enables communication between the chip and the microprocessor. State of the M/IO input pin determines whether communication between the CPU and chip will involve the RAM or the I/O portion. A high on M/IO selects the RAM while a low selects the I/O.

NRDS is an active-low read strobe. A low on this pin enables data or status information to be read from the chip. NWDS is an active-low

write strobe. A low on this pin enables data or control information to be written into the chip.

The address input bus determines where communication will take place in the chip. When the RAM is selected, the address bus determines which of the 128 bytes of RAM will be read from or written into. When I/O is selected, the address determines which I/O or control register will be enabled for communication with the CPU. These pins are normally connected to the seven low address lines of the microprocessor.

Since the RAM is fully static, no refresh or clocks are required. Data out of the RAM are the same polarity as data in, and readout is nondestructive. The RAM is a standard 6-transistor cell similar in design to the 2102A.


Each of the two ports consists of an 8-bit output data latch with buffer and an 8-bit input data latch. Full flexibility is provided with the ability to define any bit of the two ports either as an input or as an output. Bit set, clear, and read of all I/O pins are also provided. Moreover, port A may be operated in strobed input or strobed output modes.

Associated with each port is an output definition register (ODR), an 8-bit latch that defines which of the I/O pins in the respective port are to be used as outputs. Both ODRs are write only registers. If a read operation is performed with the address set to that of an ODR, the data bus will remain in the high impedance state.

The interrupt request (INTR) output is an active high signal used to interrupt the microprocessor when a strobed mode data transaction has occurred. This signal is active only when port A is in the strobed mode. INTR will be set to a low when a master reset is applied (NRST set low).

NRST is the master reset input for the chip. A low on this pin clears all registers in the I/O portion of the chip (ODRA, ODRB, and the port output data latches) and places the data bus in the high impedance state independent of any other control strobes. After a master reset, both I/O ports will be in the basic I/O mode and configured as inputs. The master reset does not change any data previously stored in the RAM and does not allow data to be written into or read from the RAM while NRST is low.

The RAM-I/O is packaged in a 40-pin DIP. It operates with a single 5-V power supply and is fully TTL compatible.



Our floppy disk system delivers twelve things DEC's can't.



Just load/address 173000 and go with your PDP-11. An all new hardware bootstrap for the PDP-11. No one can offer you a simpler, more reliable way to attach a floppy disk system to your PDP-11.

VP

Save \$300 and a Q-bus slot on your LSI-11. With this new interface card with built-in bootstrap, you can save the cost of DEC's REV 11 card and the Q-Bus slot it takes up. The L-11 bootstrap includes dynamic memory refresh, clocking circuits, and bus termination.



The confidence & reliability that only Shugart drives can give. Data Systems uses only

field proven Shugart drives, the industry standard for reliability and performance. Your choice of one, two or three of these rugged drives in your DSD-210.



Plus

- 4. Complete modularity
- 5. Write protect switches
- 6. Diskette formatting capability
- 7. Up to three drives per controller
- 8. Interchangeable 50/60 Hz operation
- 9. Front panel activity LED lights
 - Front panel system status indicators
 - 11. Self-testing microcode
 - 12. Quick delivery



3130 Coronado Drive Santa Clara, California 95051 (408) 249-9353

®registered trademark of Digital Equipment Corporation

ASTRO Devices Second-Sourced

Pin-for-pin compatible with the UC1671 (from Western Digital) and the INS1671 (from National), the second-source COM1671 asynchronous/synchronous transmitter-receiver (ASTRO) is now in production by Standard Microsystems Corp, 35 Marcus Blvd, Hauppauge, NY 11786. The n-channel, software responsive device can handle complex communication formats in a variety of system applications.

It performs the functions of interlacing a serial data communication channel to a parallel digital system, is capable of full-duplex communications (receiving and transmitting) with synchronous and asynchronous systems, and operates on a multiplexed bus with other bus oriented devices. Programming is provided by a processor or controller via the bus, with all parallel data transfers accomplished over the bus lines.


Baud rates from dc to 1M/s are handled. Integral handshaking terms insure easy interfacing with modems or other peripheral devices such as display terminals. A programmable diagnostic mode allows the selection of an internal looping feature to connect the device internally for processor testing.

Circle 350 on Inquiry Card

Hybrid Peak Detectors Provide ±0.01% Accuracy

First of its type to be offered in a hybrid circuit package and the only one available for operation over the full military temperature range are only two of the claims being made by Burr-Brown, PO Box 11400, Tucson, AZ 85734 for its 4085 hybrid peak detector. In addition, the ic is said to be the lowest priced unit currently on the market. Its applications include monitoring of power lines and analytical instrument output as well as testing of components.

The device detects positive-going input signal peaks over the -10 to 10 V range with ± 15 -V supplies and holds each peak value until reset or until a higher peak is detected. Optionally, it can be put in hold



* INTERNALLY CONNECTED TO CASE ON 4085BM AND 4085SM

Functional diagram and pin configuration for Burr-Brown 4085 sample/hold amplifier. Versions of completely self-contained hybrid circuit are available for operation over both industrial and full military ranges. Modes of operation are initiated by open or closed conditions of switches S1 and S2

mode to ignore higher peaks. Dynamic accuracy is better than 0.01% (12 bit) to 500 Hz and output droop is ± 0.06 mV/ms max at 25°C.

In operation, the specialized sample/hold amplifier tracks an input signal until a maximum amplitude is reached. That maximum value is held at the analog output, and the digital status output indicates that a peak has been detected. Then the device can be commanded to hold that value, ignoring additional peaks, or to reset to a user-specified reference voltage.

In peak detect mode (S1 closed, S2 open as shown on diagram), the analog output tracks the analog input until a peak value is reached. When the input voltage falls below the magnitude of the peak voltage, CR1 becomes reverse biased, and the feedback loop between A1 and A2 is broken. At this point, the status output transistor turns on and the magnitude of the peak voltage is held on the analog output.

In hold mode (S1 open, S2 open), the current charging path from the output of A1 to the capacitor is opened. The output voltage is equal to the voltage stored in the capacitor even though the input voltage may become larger than the peak voltage.

In reset mode (S1 open, S2 closed), the voltage on the capacitor will charge to whatever voltage is applied to the reset voltage input. If both S1 and S2 are closed at the same time, the output of A1 will be connected to the reset voltage input through a low impedance. This represents an illegal mode of operation, but will cause no damage to the unit.

Three versions are available: the ceramic 4085KG has a specification range of 0 to 70°C while BM and SM are hermetically sealed metal packages with specification ranges of -25 to 85°C and -55 to 125°C respectively.

Acquisition time is 200 μ s max, input offset is 2 mV typ (adjustable to zero), input offset drift is 50 μ V/°C typ, and input bias current is 15 pA max.

Typical prices quoted for these hybrid peak detectors in 1 to 24 quantities are \$49, \$64, and \$81, respectively, for the 4085KG, BM, and SM. 100 to 249 prices, respectively, are \$36, \$42, and \$59.

Circle 351 on Inquiry Card

If you're this kind of systems OEM,

You're building complex turnkey projects.

You need more than "iron".

2000

東京 1 大京 中央

You know that your best buy is not a mixed bag of bottom-priced components, but a proved system, with all essential support, from a supplier who becomes your working partner.

we're your kind of computer systems source.

We're different. Instead of selling you black boxes, we supply complete computer systems. We've been doing this for seven years.

We have a state-of-the-art line of standard processors, memories, I/O devices, terminals and other peripherals. Plus proved system operating software that speeds

your application programming. Advanced network and transaction software. And we'll quote special hardware and software where needed.

You'll like our systems engineering help, because we understand system problems. And we don't love you and leave you, but supply full support — field service, documentation, personnel training, even sales support.

What you get from MODCOMP is a fully checkedout system, factory burned-in, ready to bring on-line

quickly and efficiently.

Get the full MODCOMP OEM story, by asking for the brochure, "Power Tools For Building OEM Systems". Modular Computer Systems Inc., 1650 W. McNab Road, Fort Lauderdale, Fla. 33309. (305) 974-1380.

MODCOMP

The systems store.

European Headquarters:

Export House, Woking, Surrey, England


Surrey, England Phone: (04862) 71471

CIRCLE 65 ON INQUIRY CARD



Single DIP Combines Features of Three ICs

Features previously available only on three separate devices are now combined on a single octal register—the Am25LS2520. This device consists of eight positive edge-triggered D-type flip-flops in a single, 22-pin, 0.4" (1 cm) center-to-center DIP and



Am25LS2520 octal register. Capabilities of three separate ICs are obtained from a single 22-pin package

offers features of the 20-pin Am25LS273 (common clear), the Am25LS374 (common 3-state enable), and the Am25LS377 (common clock enable) octal registers. Typical clock-to-output delay is 21 ns.

When the clear input is low, internal flip-flops are reset to logic 0 (low), independent of all other inputs. When the clear input is high, the register operates normally.

When the 3-state output enable (OE) control input is low, the Y outputs are enabled and appear as normal TTL outputs. When OE is high, the Y outputs are in the high impedance (3-state) condition. This does not affect the internal state of the flip-flop Q output.

The clock enable (E) input is used to selectively load data into the register. When the E input is high, the register will_retain its current data. When the E is low, new data are entered into the register on the low-to-high transition of the clock input.

Availability of these three features in one package enables designers to reduce both the device type proliferation and package count in new system designs. In many cases this 22-pin device will replace two 20-pin functions.


A.W.

The register is produced by Advanced Micro Devices Inc, 901 Thompson Place, Sunnyvale, CA 94086 in molded and ceramic hermetic packages for use over commercial and military operating ranges. It is processed fully to the requirements of MIL-STD-883.

Circle 352 on Inquiry Card

IC Functions as Floppy Formatter/Controller

The dual density FD1781, an Mos/LSI floppy disc controller/formatter that accommodates the interface systems of most drive manufacturers, has been introduced by Western Digital Corp, PO Box 2180, Newport Beach, CA 92663. Special features of the n-channel silicon gate device include automatic track seek with verification; selectable track-to-track stepping, head settling, and engage



Announcing the quality **oem** fixed and removable Cartridge Module Drive with SMD interface.



Ask

The new Model 9448. The highestperformance, highest-capacity Cartridge Module Drive available today.

Here is the first OEM Cartridge Module Drive with a 9.67 MHz transfer rate and 30 ms access time. This speed makes our CMD compatible with industry standard controllers. And the highest-performance CMD available today.

What's more, it's the first CMD that's interface-compatible with MMD and SMD disk storage. This means you can operate from a single controller three types of storage with capacities ranging from 12 to 300 Megabytes. And get a new, highly flexible growth path.

You also get the options you need. Control Data's new CMD is available in 32, 64, and 96
Megabyte capacities. Each model contains 16
Megabytes of easy front-loading cartridge memory. The remainder is fixed memory. Data can easily be copied from fixed disk to removable cartridge for greater security at lower cost.

All three models offer hard or soft sectoring, same packaging, common spares and many other benefits. Find out more about CDC's CMD breakthrough. Mail the coupon.

Call (405) 946-5421 or return coupon to Terry J. Hardie, Control Data Corporation, 4000 N.W. 39th Street, Oklahoma City, OK 73112.

Ask our **Oem** people

Tell me more about your OEM Cartridge Module Drive.

Name_____Title____

ompany_____Phone____


Address City State Zip

GD CONTROL DATA CORPORATION

PRODUCT

Computer Graphic Family

Multifunction




All units employ a proprietary nonimpact writing process called matrix electrostatic writing technique (MEWTTM). Dual array writing head configurations, with either 100 or 200 stationary nibs/linear inch (39 or 79/cm), permit overlapping of dots for improved contrast and precise image formation. Image areas can be clear white, completely black, or anything in between.

Design Features

A specially coated paper used with this printing technique temporarily stores electrostatic charges selectively imposed by the writing head nibs. These patterns become visible after the paper is exposed to a liquid toner. Black particles suspended in the toner adhere to the paper only where an electrostatic charge exists. Copies are ready for immediate use when they leave the print unit.

In this raster scan writing method, one horizontal line—a single row of dots—is written, after which the paper is incremented slightly and another row (or scan) is written. By programming each scan, any design can be output, including shaded graphics and any size alphanumerics.

Internal circuitry converts ASCII-coded characters to preprogrammed plot patterns. Each character is formed by either a 7 x 9 or 16 x 16 dot matrix. An option, called simultaneous print/plot or SPP, permits print characters to be overlaid with plot data.



Most system control and write timing functions are carried out by an Intel 8080 microprocessor. Data and internal state information are transferred to other electronic and electromechanical subassemblies via an 8-bit bidirectional, 3-state data bus. Memory and peripheral device addresses are transmitted over a separate 16-bit address bus. Six timing and control outputs are available, and four control inputs, four power inputs, and two clock inputs are accepted by the microprocessor.

Two 256 x 4-bit random-access memories (RAMs) comprise a print buffer which can store one line of print data. Two other similar RAMs store one scan of plot data for a plot buffer. Presettable counters address the buffers to input or output a character or byte.

Either read-only memories (ROMs) or programmable ROMs (p/ROMs) store character dot patterns. ROMs are 2048 x 8 bits in size and each can contain 128 7 x 9 characters or 64 16 x 16 characters. p/ROMs are 1024 x 8 bits and are used for special character sets. Normally one ROM is used for standard 7 x 9 units and two are used for 16 x 16 units.

All printed circuit boards, including one for the power supply, plug into a common backplane, providing electronic modularity. The switching-regulator type power supply provides 5, -5, 12, -12, and 400 Vdc to the electronic and electromechanical subassemblies.

Operational adjustments are minimized by a self-aligning feature. The backplate electrode self-aligns to the writing head, the toner wiper bars self-align to the toner channel, and the 2-part cutting assembly self-aligns. In addition, a differential drive eliminates paper tracking problems to prevent the paper from skewing and tearing.

Print data are sent to the printer/plotter one ASCII-coded byte at a time. When one complete print line is received or a print line is properly terminated, the printer/plotter converts the codes into plot patterns and performs a number of plot scans to generate a character line. For 7 x 9 characters, nine scans are used for normal character generation and three additional scans generate the descenders where relevant; units with 16 x 16 character sets generate a total of 20 scans per print line.

Design of the series is based on operation with 11" (28-cm) wide roll paper which can be cut in varying lengths either remotely by computer program or manually from a front panel control. However, 11 x 8.5" (28 x 21.6 cm) fanfold paper can be used in applications where required.

Standard available controllers interface with Data General, Digital Equipment, Hewlett-Packard, IBM, Interdata, and Control Data computers. Optional controllers permit hardcopy production from Tektronix and Hewlett-Packard display terminals and other digital video sources.

times; double buffering of data; 8-bit bidirectional bus for data, control, and status; and flexible formatting, including full compatibility with IBM 3740 data entry systems. The device also provides data, data strobe and address mark input/output for reading and writing data, and can accommodate MFM, M²FM, group coding, as well as other double-density encoding methods.

Circle 353 on Inquiry Card

wit.

ar:

10

F 4

Multiplying DACs Meet MIL-STD-883 Class B

MDA 100 and 120 high reliability, 4-quadrant multiplying hybrid digital-to-analog converters, available from ILC Data Device Corp, Airport International Plaza, Bohemia, NY 11716, feature exclusive pull-up resistors for guaranteed logic compatibility. Each device also incorporates a welded-lid package design and meets MIL-STD-883 Class B requirements, allowing use in rugged military and industrial applications.

MDA 100 is a true 10-bit multiplying DAC with a full 10-bit linearity. The 16-pin device is a pin-for-pin replacement for the Analog Devices AD-7520 and the Hybrid Systems

HS-331. MDA 120 is a true 12-bit multiplying DAC with a full 12-bit linearity. The 18-pin device is a pinfor-pin replacement for the Analog Devices AD-7521.

Circle 354 on Inquiry Card

FPLAs Offer Alternative To Random Logic Designs

Two high performance Schottky TTL field programmable logic arrays (FPLAS) are claimed by their manufacturer to be practical LSI alternatives for random logic designs. This is said to result from coupling innovative control options with increased cost effectiveness. SN54S/ 74S330 and SN54S/74S331 feature a built-in capability for multidimensional expansion of their basic 12input x 50-product term x 6-output organization. A special circuit is included that can decode true product terms to automatically enable the FPLA outputs.

Expandability is possible to virtually any size array without external logic or control. The control option can be activated by fusing a single titanium-tungsten link or by implementing a dedicated enable

input as an alternative for conventional expansion or logic control. Outputs are constantly enabled when system power is applied so that the devices can be programmed to stand

Among the advantages of these FPLAS from Texas Instruments Inc, PO Box 5012, Dallas, TX 75222 is that time consuming reduction of complicated Boolean functions can be eliminated or reduced significantly by "writing" compound/multiple gating functions directly. Virtually any combination of AND, NAND, OR, or NOR logic functions can be programmed to replace random logic gates.

Typical delay time of 35 ns specifically enables use of these devices as one of the major building blocks in the company's S481 Schottky bitslice chip set, a micro/macroprogrammable 4-bit slice processor element which can perform micro-operations at rates up to 15 MHz. Design flexibilities of the bit-slice permit emulation of virtually any hardware or algorithm to provide full protection of software investment.

Packaging is in high density 20-pin DIPS for either commercial (0 to 70°C) or extended temperature (-55 to 125°C) requirements.

Circle 355 on Inquiry Card

MDB SYSTEMS presents... The INTERDATA Connection

GP Logic Modules · Peripheral Controllers · Communications Interfaces · Special Purpose Modules · Accessory Hardware

New: PASLA and Universal Clock Modules.

MDB Systems products always equal and usually exceed the host manufacturer's specifications and performance for a similar interface. MDB interfaces are software and diagnostic transparent to the host computer. MDB products are competitively priced; delivery is usually within 14 days ARO or sooner.

Here are some MDB Systems connections to Interdata computers:

☐ General Purpose Interfaces
Universal Logic Module
provides handshake plus 92
wire wrap positions;
handles two independent
device controllers.
G.P. Interface board; full wire

wrap with 197 socket positions.

- ☐ Universal Clock Module (includes line frequency clock).
- Line Frequency Clock Module.

 □ Communications Modules
 PASLA, programmable crystal
 controlled baud rate.
 Communications connectors mounted on rear

nectors mounted on rear edge of board (male and female, can be both terminal or data set). All addressing and speeds DIP switch selectable.

Current Loop Interface for TTY device; multiple baud rate selection, one of sixteen, from 50 to 19.2K baud.

☐ Device Controllers for most major manufacturer's

Printers

Card equipment

Paper tape equipment

All Controllers are software transparent using Interdata diagnostics.

Check first with MDB Systems for your Interdata computer interface requirements.

MDB also supplies interface modules for DEC PDP-11* and Data General NOVA* computers and for DEC's LSI-11 microprocessor.

MDB SYSTEMS, INC.

1995 N. Batavia St., Orange, California 92665 714/998-6900 TWX: 910-593-1339 *TMs Digital Equipment Corp. & Data General Corp.

22-Pin 4k RAMs Provide Higher Access Speeds

Improved speed-power performance plus increased noise immunity without changes in system design are promised system manufacturers that use the 2107C family of 22-pin 4k RAMS. Offered in both ceramic and plastic, C-1, C-2, and C versions, respectively, provide maximum access speeds of 150, 200, and 250 ns; read and write cycles of 380, 400, and 430 ns; and read-modify-write of 450, 500, and 550 ns. These speeds are guaranteed over a 0 to 70°C range. Typical power dissipation is 420 mW in active operation.

All power supplies (12, 5, and -5 V) have $\pm 10\%$ tolerances, which Intel Corp, 3065 Bowers Ave, Santa Clara, CA 95051 says is twice the industry standard. In addition, maximum supply currents are lower; maximum average I_{DD} from the 12-V supply ranges from 35 mA for the C-1 to 30 mA for the C.


Based on the same fabrication technology and storage cell design as the 2104A family of 16-pin 4k RAMS, the 2107C family is expected to be used in new system designs where higher access speeds are desired. In addition, the family can directly replace 2107B, 2107A, and other standard 22-pin devices. Demonstrations have shown it to be compatible and interchangeable at board socket level.

Circle 356 on Inquiry Card

p-Channel MOS Circuits Drive Large LCDs

According to the manufacturer, the LS7100 and LS7110 are the first Mos devices capable of driving 8" (20 cm) LCDS that are offered off-the-shelf in large quantities. The 16-pin, p-channel circuits from LSI Computer Systems, Inc, 1235 Walt Whitman Rd, Melville, NY 11746 are input-compatible with cMOS and TTL systems to drive liquid crystal displays requiring segment drive voltages of from 5 to 60 V. Both operate over the -40 to 85°C range.

LS7100 is a BCD to 7-segment latch/decoder/driver that operates at 5 to 80 V. It requires a minimal amount of circuitry to interface with a 120-Vac line and drive a liquid crystal or gas discharge display. Its reper-



Block diagram of LS7110 multiplexer/demultiplexer/driver. In addition to driving LCDs of up to 8" (20 cm), this device can serve in many communications applications

toire includes the digits from 0 to 9, as well as -, L, U, P, A, and H.

LS7110 is a combination binary-addressable, latched 8-channel multiplexer, demultiplexer, and driver operating at 5 to 80 V. In addition to driving LCDS, it can be used for

switching analog or digital signals, as a switching matrix, in communications, and for gathering and dispatching information. It can perform at high voltage levels and readily interfaces with 28- or 50-V signals. Circle 357 on Inquiry Card

DAC Prices Reduced

Price reductions up to 29% for a line of high speed multiplying digital-toanalog converters have been announced by Signetics, PO Box 9052, 811 E Arques Ave, Sunnyvale, CA 94086. The NE5007/5008 converter ICS offer direct interface to TTL, ECL, HTL, CMOS, and p-MOS families, and incorporate advanced circuit design that achieves 85-ns settling time as well as high swing, adjustable threshold logic inputs to provide full noise immunity. Units are pin- and functionally-compatible with mono-DAC-08 converters originally introduced by Precision Monolithics. Circle 358 on Inquiry Card

Semicustom MOS Chips Offer Up to 550 Gates

A family of Mastermos chips announced by International Microcircuits, Inc, 3004 Lawrence Expressway, Santa Clara, CA 95051 consists of 10 semicustom chips ranging in size from the equivalent of 50 2-input gates to 550 2-input gates in 50-gate intervals. They operate at 7 MHz at 15 V, twice the speed of the original Mastermos family. Each chip includes additional buffers for interfacing with LS-TTL or TTL. Computer-designed symmetrical logic cells are said to increase layout efficiency of interconnections of functions; eg,

only four weeks are required to produce the first 75 prototypes. Circle 359 on Inquiry Card

Bipolar Multipliers Feature Reduced Power Dissipation

Power reductions in MPY-8, -12, and -16 bipolar multipliers, resulting from substitution of military temperature range chips for commercial range devices, now eliminates all forced air cooling for operation over the 0 to 70°C commercial range. According to the manufacturer, TRW Electronic Components Div, PO Box 1125, Redondo Beach, CA 90278, this is achieved by a 20 to 30% reduction in supply current. However, the devices are fully compatible with previous MPY series multipliers.

Output delay times have been improved for all of the multipliers. The 8-bit, 130-ns MPY-8 has reduced average power from 1.75 W to an average of 1.2 W. One-half of the 1.2-W total power is consumed by the onchip registers. The multiplier itself consumes only 0.6 W. Efficiencies have been increased for the 12-bit, 150-ns -12. Average power has been cut from 3.5 to 3.0 W. The 16-bit, 160-ns -16 has dropped from a 5-W average power dissipation to an average of 4 W.

Circle 360 on Inquiry Card

Offers

11

1

本のずる大

*

-

Capability

Specifications

Printers 3150 and 3250, featuring 100- and 200-dot/in (39.4 and 78.7/ cm) resolution, respectively, have the following respective specifications: 1056 and 2112 writing nibs: 1000- and 500-line/min print speed, 7 x 9 and 16 x 16 character dot matrix; 12.5-char/in (5/cm), ASCII 96 gothic character set for both; 132 columns/line, 6.6 lines/in (2.6/cm) for both; and 57 and 64 lines/fanfold page. The 3100 and 3200 plotters, respectively, also have 1056 and 2112 writing nibs, plus 2- and 1-in/s (5- and 2.8-cm/s) plot speed; and 10.24- and 10.56-in (26.77- and 26.82-cm) plot widths. Printer/plotters 3100A and 3200A combine all specifications of the printer and plotter of the respective resolutions.

General specifications include 110/115/200/300-Vac ±10%, 48- to 400-Hz, 500-W max power requirements; and 32 to 105°F (0 to 40°C), 10 to 95% relative humidity (noncondensing) operating environment. Paper and toner can be stored for a maximum of one year at 40 to 80°F (4 to 27°C) and 40 to 70°F (4 to 21°C), respectively.

Standard desktop models measure 17.5 x 19 x 22.5" (44.5 x 48.3 x 57.2 cm), or 46 x 19 x 22.5" (117 x 48.3 x 57.2 cm) with base; rackmount models measure 17.5 x 19 x 22.5" (44.5 x 48.3 x 57.2 cm). These three configurations weigh 105, 160, and 105 lb (47.6, 72.6, 47.6 kg), respectively.

Price and Delivery

Single unit prices are \$8550 for the 3100 plotter and 3150 plotter, \$9250 for the 3100A printer/plotter, \$10, 500 for the 3200 plotter and 3250 printer, and \$11,400 for the 3200A printer/plotter. Mounting base/supplies cabinet costs \$495. OEM discounts are available on all. Deliveries are 60 days Aro. Versatec, a Xerox Co, 2805 Bowers Ave, Santa Clara, CA 95051. Tel: (408) 988-2800.

For additional information circle 199 on inquiry card.



Look at a Memory & LSI Test System in this Light!

The Micro Control M-10AT does it all... and more for a lot less!

Use it for

Memory System Burn-in Testing • Memory Device Testing • Memory Device Burn-in • Memory Board Testing • LSI Testing • Memory Systems Testing (hardware and software) • Production Testing (manufacturing) • Engineering Evaluation • Incoming Inspection
 • Failure Analysis • More

Have this standard

- Fully automatic operation (computer controlled) with up to 32K of Memory
- \bullet Programmable Multiphase Timing (one range, 0 to 65 $\mu \rm sec$ in 1 nsec steps)
- Sixteen or 24-bit Address Generators with optional scrambler.
 Sixteen to 72-bit Data Generators with Arithmetic Logic Unit and
- optional Buffer Memory.

 Large Control Memory for Microprogrammed Pattern Generation

(256 Word x 96 Bits). • More With this software (no charge)

- Terminal Operating System, interactive, interpretive operator control
- Higher Level Language, interpretive, sequential control programs.

Schmoo Plot

- Error Mapping, real time error logging
- and Special Software at a nominal charge

Your Test Engineer can write complex Supervisory Programs with minimum training and experience.

Plus this

- Real time error logging of chip or cell
- Real time clock for test data recording
- Universal Device and Board Test Adaptors and interfacing with Handlers, Wafer Probers, Environmental Chambers

Plus this

• Special Engineering • Training • Same-day Maintenance • Five Year Parts Warranty • Software Updates • Design changes to meet special application needs.

All for

\$45.9K BASIC SYSTEM PRICE! Compare the M-10AT in this light!

There are over 50 systems now installed.

MICRO CONTROL COMPANY


MAIN OFFICE • 7956 Main Street N.E. • Minneapolis, MN 55432 • (612) 786-8750 WEST COAST OFFICE • 377 Avenida Manzanos • San Jose, CA 95123 • (408) 226-1171

CRT and Line Printer Combine Visual Plotting and Rapid Hard Copy



Full graphic requirements from simple charts to complex engineering drawings and 3-dimensional views are met by the 2282 graphics CRT and the 2231W-3 matrix line printer. The CRT adds plotting and fully automatic alphanumeric lettering capability to the System 2200 CPU. A matrix of 800 X- and 512 Y-addressable locations are provided in a 7 x 6" (17.8 x 15.2-cm) area on the 12" (30-cm) diagonal screen. Plotting vectors are generated by turning a series of dots on or off. All CPU plotting output is displayed for possible operator modification. In addition, a 112-char ASCII set is stored in memory and can be plotted in 15 different sizes for different applications. The printer uses a 7 x 8 dot matrix for the same character set, printing at 120 char/s and 40 to 250 lines/min, depending on line length. Hardcopy of the CRT display is generated by printing strips of 800 x 8 dots under program control until the display is reproduced. Normal line feed spacing is reduced during image reproduction to provide vertical image continuity. An expanded character can be provided for highlighting. Wang Laboratories, Inc, 1 Industrial Ave, Lowell, MA 01851. Circle 200 on Inquiry Card

Microprocessor-Controlled Calibrators Provide Multipurpose Capabilities



Models 5100A and 5101A, combining the capabilities of several instruments, accept data through simple front panel keyboards or with optional system interfaces for calibration of VOMs as well as 31/2-, 41/2-, and most 51/2-digit DMMs. Control is maintained by a microprocessor. Outputs include dc voltage to 1100 V with 50-ppm accuracy; ac voltage to 1100 V with a bandwidth of 50 Hz to 50 kHz; ac and dc current outputs from 10 µA to 2 A; and resistance of eight decade values from 1 Ω to 10 $M\Omega.$ An option provides wideband ac from 10 Hz to 10 MHz with function ranging from -57.5 to 23 dBm. In addition, a tape cassette built into the 5101A provides a permanent storage of frequently used procedures. After a cassette containing output parameters is read into memory, the operator presses the advance key to select the sequence. Each cassette can store up to 58 procedural steps and can be programmed as easily as operating the basic instrument itself. John Fluke Mfg Co, Inc, PO Box 43210, Mountlake Terrace, WA 98043.

Circle 201 on Inquiry Card

Intelligent Keyboard Offers Broad Programming Options for Terminal Designers

Combining 103 Hall-effect logic scan key modules with a single-chip microcomputer results in a full-function key-



board for intelligent and distributed processing terminal applications. The microcomputer integrates 8-bit CPU, ROM, RAM, I/O lines, and a time/event counter on a single chip. A 40-pin EPROM, pin-compatible with the ROM, is available for prototyping. Features of the 19.38 x 16.34 x 1.44" (49.23 x 16.1 x 3.66-cm) model 103SD24-1 keyboard include 4mode, 8-bit ASCII code assignment; choice of serial or parallel data outputs; 14 relegendable keytops for programming keys; 8-deep FIFO character storage; N-key rollover; and timed/auto repeat for selected keys. Each key module provides one isolated input and one isolated output. The output signal is valid when the input interrogation signal is true and the key is depressed. Enabled output will reflect the normal performance of a level sinking output. When the input is at high level, the output is inhibited by forcing the output transistor into off state. Micro Switch Div of Honeywell, 11 W Spring St, Freeport, IL 61032.

Circle 202 on Inquiry Card

Have it your way.

Bit by bit our Standard Modular Memory lets you make every word count.

The Standard.

10

ph

-

1

0

12

4

768K x 16 in one 51/4 x 19 inch chassis.

Need more?

You can address up to eight of our MSC 2601 Standard Modular Memory units for up to 6144K x 16.

Want it your way?

Our field-proven MSC 2601 uses dynamic 16K RAM elements. You can organize each card 16K x 1 to 64K x 9. Multiple cards give you almost any word and bit size you want.

Any way you like it.

Up to 14,155,776 bits in one MSC 2601.



MSC - 2601

When you like it.

Access time up to 350 nsec. Cycle time as fast as 450 nsec.

Together in the rack.

RETMA rackmountable or freestanding. Self-contained with power supplies and forced air cooling. Battery backup available, too, for nonvolatile storage.

And for another way.

If you want 4K RAM our static or dynamic versions will let you have your way with up to 192K words.

Our way.

We use fewer components and low power for high reliability. Multiple source, full specification components tested, assembled and then systems tested under worst case operating conditions.

The MSC 2601, Standard Modular Memory... We set the standard.



14 Inverness Drive East Englewood, CO 80110 303/770-7400 © 1977 Monolithic Systems Corp.

Intel delivers PDP-11 memory for people who can't afford to wait.

When you're in a hurry for more semiconductor memory for your PDP-11, call Intel. We deliver memory for the full PDP-11 line. And because we're the largest manufacturer of semiconductor memory in the world, delivery is when you want it.

Why wait? Since you've chosen the leader to supply your minicomputer, it makes sense to go to the leader for memory, too. That's us.

Intel memory systems save you more than time. Our in-1670 add-on memory for the PDP-11/70 is one example. It gives you four times the capacity in the same frame compared to the DEC MJ11-A core memory. And built in Error Correction Code (ECC) and Error Logging improve up-time and reduce maintenance time by automatically correcting and recording single-bit failures and detecting and recording double-bit errors.

For PDP-11 add-in memory go with our in-4711 plug in boards. You'll get memory that's even faster than DEC's. 16K words per hex-wide board. With or without parity. To further expand PDP-11 memory and reduce UNIBUS™ loading choose our in-4011 add-on. With memory management you can expand to 128K words in 16K increments. And since the in-4011 requires only one UNIBUS load, you get added system flexibility.

Get more memory for your LSI-11 and PDP-11/03 in less space with our in-1611 add-in memory. You get up to 32K words, in 8K increments, on a single, two-wide, board. That's up to eight times the memory you get with a DEC board.

When you can't afford to wait call us at 800-538-8476. In California and Canada, call 408-734-8102, x575. We'll save you time, and much more.

intel delivers.

Intel Memory Systems 1302 N. Mathilda Avenue		CD-1
Sunnyvale, California 94086		
I can't wait! Must have delivery in 5	Days 🗆 30 Days 🗆 Days	
☐ Please call me at/	Ext	
☐ Please send me information on a following: ☐ LSI-11, PDP-11/03 ☐ PDP-11/04 ☐ PDP-11/05 ☐ PDP-11/34 ☐ PDP-11/35 Name/Title	☐ PDP-11/40 ☐ PDP-11/45 ☐ PDP-11/55 ☐ PDP-11/70	
	Mail Station	
AddressCity/State/Zip		

intel MEMORY SYSTEMS

U.S. AND CANADA SALES OFFICES

-

4

1

1

1

-

The

k

-

1

ALABAMA Col-Ins-Co Huntsville (205) 881-9512 Glen White Assoc. Huntsville (205) 883-9394

ARIZONA Intel Corp. Phoenix (602) 242-7205 BFA Corp. Scottsdale

Scottsdale (602) 994-5400
CALIFORNIA Intel Corp. Santa Ana (714) 835-9642 Intel Corp. Sunnyvale (408) 738-3870
Earle Assoc. San Diego (714) 278-5441 MAC-I Berkeley (415) 843-7625 MAC-I Cupertino (408) 257-9880

Cupertino (408) 257-9880 MAC-I Fountain Valley (714) 839-3341 MAC-I Woodland Hills (213) 347-1374

COLORADO Intel Corp. Denver (303) 373-4920 BFA Corp. Denver (303) 837-1247

CONNECTICUT Intel Corp. Danbury (203) 792-8366

FLORIDA Intel Corp. Ft. Lauderdale (305) 971-7200 Intel Corp. Orlando (305) 628-2393 Col-Ins-Co. Orlando (305) 423-7615

GEORGIA Col-Ins-Co Stone Mountair (404) 299-2138

ILLINOIS Intel Corp. Oak Brook (312) 325-9510 Data Electronics Chicago (312) 283-0300

INDIANA
Data Electronics
Indianapolis
(317) 784-6360

IOWA Technical Reps. Inc Cedar Rapids (319) 396-5662

KANSAS Technical Reps., Inc. Olathe (913) 782-1177

LOUISIANA Col-Ins-Co Baton Rouge (504) 292-1755

MARYLAND Intel Corp. Timonium (301) 252-7742 Glen White Assoc. Timonium (301) 252-7742

Mesa, Inc. Rockville (301) 881-8430

MASSACHUSETTS Intel Corp. Chelmsford (617) 256-4131 Computer Marketing, Inc. Waltham (617) 890-1776

MICHIGAN Intel Corp. Southfield (313) 353-0920 Lowry and Assoc., Inc. Brighton (313) 227-7067

MINNESOTA Intel Corp. Bloomington (612) 835-6722 Data Electronics Minneapolis (612) 786-9666

MISSOURI Technical Reps., Inc. Hazelwood (314) 731-5200 NEW JERSEY Intel Corp. Edison (201) 985-9100

NEW MEXICO BFA Corp. Albuquerque (505) 292-1212 BFA Corp. Las Cruces (505) 523-0543

NEW YORK Intel Corp. Hauppauge (516) 231-3300 Intel Corp. Rochester (716) 328-7340 Intel Corp. Poughkeepsie (914) 473-2303 Measurement Tech., Inc Great Neck (516) 482-3500 T-Squared, Inc. Pittsford (716) 381-2551 T-Squared, Inc. Syracuse (315) 463-8592

NORTH CAROLINA Col-Ins-Co Winston Salem (919) 748-0297 Glen White Assoc. Raleigh (919) 787-7016

OHIO Intel Corp. Dayton (513) 890-5350 Intel Corp. Euclid (216) 289-0101 Lowry and Assoc., Inc. Cleveland (216) 464-8113 Lowry and Assoc., Inc.

Dayton (513) 435-4795 OREGON ES/Chase Co. Portland (503) 620-9616

PENNSYLVANIA Intel Corp. Ft. Washington (215) 542-9444 Lowry and Assoc., Inc. Pittsburgh (412) 922-5110 O.E.D. Electronics, Inc. Hatboro (215) 674-9600

TENNESSEE
Glen White Assoc.
Germantown
(901) 754-0483
Glen White Assoc.
Johnson City
(615) 928-0184

TEXAS Intel Corp. Dallas (214) 241-9521 Mycrosystems Mktg., Inc. Austin (512) 472-2492 Mycrosystems Mktg., Inc. Dallas (214) 238-7157 Mycrosystems Mktg., Inc. Houston (713) 783-2900

UTAH BFA Corp. Salt Lake City (801) 466-6522

VIRGINIA Glen White Assoc Lynchburg (804) 384-6920

WASHINGTON ES/Chase Co. Seattle (206) 762-4824

CANADA

Intel Semiconductor Corp. of Canada Ottawa (613) 232-8576 Multilek, Inc. Ottawa (613) 825-4553

EUROPEAN MARKETING HEADQUARTERS BELGIUM


Intel International Brussels Tel: (02) 660 30 10 Telex: 24814

ORIENT MARKETING HEADQUARTERS JAPAN

Tokyo Tel: (03) 426-9261 Telex: 781-28426

PRODUCTS

DOT MATRIX IMPACT PRINTERS



Model 520 2-stage receipt and journal printer, model 540 ticket or slip printer, and model 510 roll printer, comprise the series 500 family of 40-col dot matrix impact printers. Dc motor-driven mechanism prints at 2.5 lines/s; unit weight is 2.5 kg, and size as small as 175 x 146.5 x 112.5 mm. Warranty includes continuous duty headlife of 100M char and MCBF (mean cycles before failure) of 5M lines/mechanism. **C. Itoh Electronics, Inc,** 280 Park Ave, New York, NY 10017.

Circle 203 on Inquiry Card

ULTRA-MINIATURE FAN

Designed for applications where limited space is available, model V60CL features a multi-vane impeller, driven by a high efficiency ac motor. With an output of 10 ft³/min (4720 cm³/s) in free air, high performance fan has an impeller diam of 2.3 x 1.26" (5.8 x 3.2 cm) and weighs 1.7 oz (47.6 g). Compactly designed with aerodynamic characteristics, fan provides optimum pressure/flow. **Micronel**, Box 271, 8 Kane Industrial Pk, Hudson, MA 01749. Circle 204 on Inquiry Card

UNIBUSTM SWITCHES




The OSR11-A busrouter allows physical and electrical switching of the Unibus[™] for DEC PDP-11 series computers. Each switching plane allows a Unibus cable to be plugged in as the common and then selectively connected to one of two other cables via normally closed or normally open relay contacts. Using up to eight switching planes, various configurations perform multiple bus switching, and insertion and deletion of peripherals in the middle of the Unibus. **Datafusion Corp**, 21031 Ventura Blvd, Woodland Hills, CA 91364. Circle 205 on Inquiry Card

SUBMINIATURE CONNECTORS

MELO-D series devices are non-environmental, rectangular connectors, with snap-in front removable contacts, which are intermountable and intermateable with existing D-type connectors. Crimp, solder cup, and wrap-post contacts are provided. Five configurations range from 9 to 50 contacts. Positive locking is provided with stainless steel threadlocks or a quick coupling system. Positronic Industries, Inc, 208 W Center St, Rogersville, MO 65742.

WECO-COMPATIBLE MODEM




GDC 212A transmits and receives binary, serial data over switched telephone network in asynchronous operation at 300 bits/s and synchronous or asynchronous at 1200 bits/s. With special buffer, modem is compatible with WECO 212A and 100 series. Std features of standalone unit include local and remote loopbacks, end-to-end test, and selftest. General Data-Comm Industries, Inc, 131 Danbury Rd, Wilton, CT 06897.

ASYNCHRONOUS SERIAL LINE ADAPTER


Circle 207 on Inquiry Card

The MDL-11W serial line adapter combines all operational features of the DEC DL-11A, B, C, and D modules on a single board. Functions include switch selectable mode of operation, address, interrupt vector, and transmitter/receiver clock sources. Std features are a 20-mA active current loop interface, EIA RS-232-C interface drivers/receivers for local or remote terminal operation, full- or half-duplex operation, and 16 baud rates from 50 to 19.2k. Module is compatible with DEC operating systems and diagnostic software. MDB Systems, 1995 N Batavia, Orange, CA 92665.




Circle 208 on Inquiry Card

uP-BASED MINI-FLOPPY DRIVE



Digidisk™ system for emulating paper and mag tapes allows the operator to prepare and edit messages and data off-line, and then transmit them through the optional built-in acoustic coupler. Unit operates with any data communication printer or CRT terminal through std RS-232 interface. Responding to remote control code from a computer, microprocessor-based drive uses flexible minidisc with a capacity of >100k char. Control program resides on the disc. Digicom Data Products, Inc, 1440 Koll Cir, Ste 108, San Jose, CA 95112. Circle 209 on Inquiry Card

HIGH SPEED PRINTER



Model 1654, a 1200-line/min chain printer, has been added to the 1600 family of remote batch terminals and distributed processing systems. Major applications for unit are in high volume production environments. Features include 132 or 136 print positions/line, a selector for 6 or 8 lines/in, and EBCDIC print chains having 0.095 and 0.079" (0.24- and 0.20-cm) fonts in various paired combinations of 48-, 64-, and 96-char sets. Harris Corp, Data Communications Div, 11262 Indian Trail, PO Box 44076, Dallas, TX 75234. Circle 210 on Inquiry Card

CRT TERMINALS




COPS 15, 20, and 30 series terminals are available with upward and downward software and functional capability. Std features are 1920-char screen capacity, 7 x 9 dot matrix, 128 ASCII char set, 12" (30-cm) diag CRT screen, and variety of keyboards to suit particular application. Communication interface has full- or half-duplex/buffered transmission; EIA RS-232-C and 20-mA current loop; switch-selectable baud rates; and odd, even, mark, or space parity. Computer Peripheral Corp, 1225 Connecticut Ave, Bridgeport, CT 06607. Circle 211 on Inquiry Card

Replace your PDP-8 with a microprocessor

without changing a line of software.

For less than half the cost of DEC®-built machines, our 12000 series microprocessor modules (and fully packaged PCM-12 microcomputer) can modernize your PDP®-8 oriented products... and increase reliability to boot!

Designed around the 6100 microprocessor, our modules execute the same binary instruction set as the PDP-8 minicomputer family, and save space through use of modern MSI and LSI technology.



Low-cost PCM microcomputer modules offer full TTL bus compatibility, a variety of static and non-volatile memory modules expandable to 32K words, and a wide selection of I/O interfaces. Ask for complete product information.

®registered trademark of Digital Equipment Corp.



Pacific Cyber/Metrix, Inc. 3120 Crow Canyon Road San Ramon, CA 94583 Phone (415) 837-5400.

Techtran truly the best



New Compact Portable Model 815

Designed for lower speed terminals

- 145,000 characters per tape
- Full local and remote control
- Selectable speeds—10 and 30 c/s
- Character edit
- Optional battery powered
- Custom made carrying case available
- Only 6 lbs.

All Techtran Recorders have

- RS-232 Terminal and Modem/ CPU Interfaces
- ASCII coding (Baudot Optional)
- Character edit
- Low cost magnetic tape cassettes
- 145,000 characters per tape
- Full local and remote control

Only \$950.

... much lower in OEM quantities

for PRINTERS

4

Popular Model 8400

- 1000 c/s Data Search
- Powerful text editor
- Timesharing compatible
- Fast 110-2400 speeds
- File protect

for DATALOGGERS

Fast Model 8410

- Large 145,000 character storage per tape
- Remote, unattended data retrieval
- Operates under logger command
- Fast 110-2400 speeds

for CRT's

Powerful Model 8421

- Dual decks for merging and copying
- Powerful text editor
- 1000 c/s Data Search
- Format Mode
- Program control
- Fast 110-2400 speeds



for TEST STANDS

Versatile Model 8420

- Fast 110-2400 speeds
- Transparency Mode
- Dual decks for merging and copying





Choose the one that's best for you.



PRINT TERMINAL MONITOR



A fully programmable, microprocessorbased hardware monitor, Micromeasure will compute, accumulate, and print response time information for up to four CRT terminals simultaneously, including total number of transactions, time of day, date, high and low responses, average response, and total time of all transactions. Summaries are printed either automatically or on command over preselected time frames of up to 24 h. All instructions and machine functions are controlled through a hexadecimal keypad located on the front panel. Computer Resources, Inc, 4650 W 160th St, Cleveland, OH 44135.

Circle 212 on Inquiry Card



DIRECT-DIAL DATA STATION


The 40+TK1 stores messages in an MOS solid-state buffer rather than on paper tape or magnetic tapes, and is designed to replace low speed, leasedline, and tape-operated terminals. Data transmission speed can range from 1200 to 2400 bits/s over dial-up lines. All data communications functions are fully automatic. Data station includes an ICC 40+ data display system, keyboard, and control modules, as well as communications control module and buffer, and 110-char/s printer. Racal-Milgo, Inc, 8600 NW 41st St, Miami, FL 33166. Circle 213 on Inquiry Card

LOW INSERTION FORCE IC SOCKET



Intended for high pin-count packages, the LIF-Lock socket is a low-insertion force connector designed to minimize package and lead damage. Contacts grip package leads on both flat faces with a force of approximately 200 g To accommodate misaligned leads, each contact position has a generous funnel entry. Sockets are available in 24-, 28-, and 40-position sizes, fit std 0.100 x 0.600" (0.254 x 1.524-cm) PC board hole patterns, and are rated at 3 A with <25-m Ω contact resistance. AMP Inc, Harrisburg, PA 17105. Circle 214 on Inquiry Card

WIREWRAP DIP SOCKETS



Permitting wirewrapping on same side of board as the IC, wirewrap pins on AS/U DIP socket are bent around and are on its upper side, where each IC lead can be seen and quickly wirewrapped, saving time in breadboarding of prototype circuits. Available in 14-, 16-, 20-, 24-, 28-, and 40-pin sizes, socket permits board-to-board space savings of from 25% to 30% in depth when multiple boards are used. Robinson-Nugent, Inc, 800 E Eighth St, New Albany, IN 47150.

Circle 215 on Inquiry Card

DATA COMMUNICATIONS TERMINAL

and

40

in

100

CAN'T



MIGET (miniature interface general-purpose economy terminal) provides keyboard entry and simultaneous 32-char display output compatible with all microcomputer and microprocessor systems using RS-232-C interface and ASCII code. The 8 x 10 x 3" (20 x 25 x 7.6-cm) terminal weighs 4 lb (1.8 kg). Features include eight selectable baud rates from 110 to 9600, complete TTY compatibility, and optional self-contained memory system and acoustic coupler. Micon Industries, 252 Oak St, Oakland, CA 94607.

COMMUNICATIONS NETWORK SYSTEM

Smart/Network connects geographically dispersed asynchronous data terminals to host computers while maintaining error-free transmission and compatibility with all common computers and terminal types. Data-driven statistical multiplexing techniques automatically route a terminal at any speed to any user-specified host computer, transmitting data over lines not normally usable. Digital Communications Associates, Inc, 135 Technology Pk, Norcross, GA 30092. Circle 217 on Inquiry Card

FIBER OPTIC READOUT ASSEMBLY

Designed and packaged to resist shock, vibration, moisture, and other environmental hazards, nonencoded model 905-H display fiber optic readout assembly meets MIL-STD-883, Level B. It features an internal decoder, and LEDs that transmit through fiber optic tubes to produce a 0.43" (1.09-cm) high char display on the 0.500 x 0.62" (1.27 x 1.57-cm) display screen. Screen is a 7-segment display with 0 to 9 numeric capability as well as plus, minus, decimal point, and limited alphabetical char. **Master Specialties Co**, 1640 Monrovia Ave, Costa Mesa, CA 92627.



Circle 218 on Inquiry Card

IEEE-488 TAPE RECORDING SYSTEM

Data transfer directly from the GPIB (IEEE-488) to 0.5" (1.27-cm) mag tape without interfacing is possible with the model 1015A-S tape recording system. Once on tape, data may be transferred into any computer for analysis, or read back through the bus to any GPIB-compatible minicomputer or calculator. Features include dual 2048 buffers to insure no loss of data during interrecord gaps, and transfer rates of up to 7.5 kHz. Both 7- and 9-track models are available. **Dylon Corp**, 7854 Ronson Rd, San Diego, CA 92103.

Circle 219 on Inquiry Card

CRIMP CONTACT CONNECTORS

Miniature D-shaped rear-release Amphenol[®] 17 series rack and panel connectors feature insulation-support crimp contacts that secure both wire conductor and insulation in place, lessening chance of strain in actual application. The pin and socket contacts accept any conductor size from 22 to 26 AWG and are designed with backend tabs to crimp insulation up to a 0.050" (0.127 cm) max OD. Std contact configurations are 9, 15, 25, 37, and 50. Amphenol North America Div, Bunker Ramo Corp, 900 Commerce Dr, Oak Brook, IL 60521.

Circle 220 on Inquiry Card




TELERAY DIVISION RESEARCH INC

Call collect: 612-941-3300. Ask for Superay!

FULL DUPLEX, 1225-BIT/S MODEM

The VA3415 modem series, an improved version of the VA3400, transmits and receives at speeds up to 1225 bits/s, permitting it to operate with multiplexers that overspeed. Crystal controlled unit works with the company's multiline dialer, allowing a single automatic calling unit to handle up to seven lines. Two modems can be connected at



each end of a 4-wire leased line to provide two 1200-bit/s data streams without separate multiplexers. Modem connects to any dial-up telephone line with registered DAA. Vadic Corp, 222 Caspian Dr, Sunnyvale, CA 94086. Circle 221 on Inquiry Card


OSCILLOSCOPE ADAPTER SWITCH

Converting any conventional, single-channel oscilloscope into a multichannel logic analyzer for troubleshooting digital logic circuits, MS-1 adapter allows switch-selectable display of two, four, or eight channels of data and operates in either chop or alternate sweep modes. Up to eight data lines may be sampled simultaneously while displaying digital logic levels and timing relationships on a conventional scope.

Mid-South Instrument Services, Inc, PO Box 1252, Gretna, LA 70053.

Circle 222 on Inquiry Card

PORTABLE PROGRAMMABLE TEST SET



Model 6125C is a flexible, lightweight package that offers programmability on all front panel functions, and serves as voltage calibrator, sweep/delay-time or frequency calibrator, risetime calibrator, and error indicator. As an oscilloscope calibrator, the user can program ranges, divisions of vertical amplitude, marker frequency and number of markers, deviation, rep rate of the fast square wave, and either of two modes of remote operation. Ballantine Laboratories, Inc, PO Box 97, Boonton, NJ 07005.


Circle 223 on Inquiry Card

PHONEME SYNTHESIZER KIT

Votrax^R VSK, designed to be used with a microprocessor, combines unlimited vocabulary, operational simplicity, and low data requirements. Programmed to speak based on phonetic coding principles, unit can produce all combinations of words and phrases. Phonetic coding permits production of speech at low data rates, offering continuous speech at 20 char/s and easy interfacing to any microprocessor system with an 8-bit parallel output. Fully assembled, the single circuit board uses std 5- and ±12-V power supplies. Vocal Interface Div, Federal Screw Works, 500 Stephenson Hwy, Troy, MI 48084. Circle 224 on Inquiry Card

CONTROL SYSTEM MODULES

Paricode II modules connect directly to a voice-grade communication circuit and provide for transmission of alarms, analog and digital data, control signals,



and status information via coded audio tone signals. Single and multiple-channel equipment includes scanner modules for transmission of multiple signals on one tone channel, and frequency multiplexing modules which provide for 20 or more tone channels on one circuit. MiniData modules each transmit up to four data quantities and eight status or alarm signals on each channel. Harris Corp, Controls Div, PO Box 430, Melbourne, FL 32901.

FLEXIBLE DISC WORD PROCESSOR

Circle 225 on Inquiry Card

m.k


119



A single, flexible disc word processing system uses either the IBM Selectric typewriter or a high speed daisy wheel printer to provide recording, editing, and printing of text. User-oriented keys select char, word, line, or continuous printing as well as a 3-digit indicator for line selection. Std features of Data-Master II include rapid search, or search and list; automatic letterwriting; merging of paragraphs and automatic right margin adjust; and ASCII communications. Tycom Corp, 26 Just Rd, Fairfield, NJ 07006.

Circle 226 on Inquiry Card

MULTIPLEXER



TDM-2, a 2-channel time division multiplexer, enables simultaneous transmission of two channels of asynchronous data over a single synchronous data communication line. It can be used in private line terminal-to-terminal or computer-to-terminal applications and in point-to-point or multipoint networks, allowing each channel to operate independently in full-duplex, half-duplex, or simplex mode. The number of channels for split stream synchronous modems is doubled with the device. An EIA cable and two EIA receptacles are included. Syntech Corp, 11810 Parklawn Dr, Rockville, MD 20852. Circle 227 on Inquiry Card


COMMUNICATION INTERFACE MODULES

Used to repeat data, convert data from one format to another, indicate line conditions, and display faults, DR-1 is a circuit repeater converter, DR-2 a 12-circuit current loop to RS-232-C converter, and DR-3 a 12-circuit RS-232-C to current loop converter. OSA-4C provides 4-circuit current loop line monitor display and OSA-232-C serves as a 4-circuit RS-232-C line monitor and display. All modules are implemented on 4.5 x 6.5" (11.4 x 16.5-cm) PC cards. Dataprobe Inc, 254 Green St, South Hackensack, NJ 07606.


SUBSUBMINIATURE SWITCH

B2 series basic snap-action switch, rated at 7 A, 28 Vdc or 115 Vac, features five different terminal styles, and conforms to and is qualified under M8805/4 (MS24547). Measuring 0.500 x 0.200" (1.275 x 0.508 cm), the unit provides movement differentials up to 0.005" (0.013 cm), operating force of 5 oz (140 g) max, and silver or gold contacts for low level or dry circuit requirements. The unit complements the B3 series, allowing users a choice of mechanisms. Otto Controls Div, Otto Engineering, Inc, 36 Main St, Carpentersville, IL 60110.

Circle 229 on Inquiry Card



SWITCHING POWER SUPPLIES



For use in enclosed unit applications in data processing and telecommunication areas, the SMG series consists of 12 5-V models at current levels from 1.6 to 450 A, three 12-V models, and three 24-V models. All units operate from a 115-Vac input. Output power ranges from 8 to 2250 W. Models with outputs of 500 W and above incorporate 115/230-Vac switchable inputs and built-in fan cooling. Power density for larger units exceeds 2 W/in3 (0.12/cm3). Efficiencies exceed 70%. Gould, Inc, Electronic Components Div, 4601 N Arden Dr, El Monte, CA 91731. Circle 230 on Inquiry Card

DATA CARTRIDGE RECORDER



A write-only drive, the 300W utilizes the DC-300A type cartridge and can store over 350,000 characters in a single track configuration. Tapes can be written in 128- or 256-char blocks with a 16-bit CRC character as required by the ANSI tape cartridge standard, and read with ANSI-compatible cartridge readers. Input buffers accept incremental 8-bit parallel or asynchronous serial data via RS-232 or current loop. Columbia Data Products, Inc, 6655 Amberton Dr, Baltimore, MD 21227. Circle 231 on Inquiry Card

IMPACT MATRIX LINE PRINTER/PLOTTERS


Incorporation of a microprocessor data communication interface enables remote printer/plotters to communicate with a computer base station over switched or private telephone lines. Interface functions by emulating Burroughs, Honeywell (VIP-7700), IBM

BiSync (2780, 3780, or 3270), or Univac (DCT 1000) line protocols. Printing mechanism can plot graphics, charts, curves, bar codes, labels, and char of any size. Model 300DC operates at 300 lines/min, and 150DC at 150 lines/min. Printronix, Inc, 17421 Derian Ave, Irvine, CA 92714.

Circle 232 on Inquiry Card

14-BIT DAC

ZDA14QM, a modular 14-bit D-A converter, offers stability of 0.0003%; it is usable in two current or three voltage modes for either unipolar or bipolar operation. Gain, unipolar, and bipolar offsets are externally adjustable. Preselected and screened analog switches and 1-ppm/°C thin film resistors are used in design to insure accurate performance. Epoxy encapsulated case measures 2 x 4 x 0.4" (5 x 10 x 1 cm). Zeltex, Inc, 940 Detroit Ave, Concord, CA 94518.



Circle 233 on Inquiry Card





DC-DC CONVERTERS

*

Dat

4

Dual and triple outputs totaling up to 12 W at levels suitable for microprocessors, memories, data converters, and op amps are delivered by a family of 55 to 65% efficient dc-dc converters. The MC series of oncard local power sources offers a π input filter to reduce input reflected ripple to <1% of input voltage, I/O isolation of 300 Vdc min, and output ripple and noise of 2 mV rms (30 mV pk-pk typ). MTBF of each model exceeds 100 kh. Semiconductor Circuits, Inc, 306 River St, Haverhill, MA 01830.

WIREWRAP PANELS

Circle 234 on Inquiry Card

Model 2-1077MPB Micro-Designer series is a 6.875 x 10.775" (17.5 x 27.4 cm) microprocessor panel featuring min of two ground planes and four power buses for mounting 120 ICs (14- or 16-pin) and discrete components. Panel has documentation package and accessories for use in engineering design and production programs. Component pin eliminates need for carriers. Panel contains plated-through holes on a 0.100×0.100 " (0.254 x 0.254-cm) grid, available with three I/O formats. Hybricon Corp, 410 Great Rd, Littleton, MA 01460.

PROGRAMMABLE DIGITAL SIGNAL PROCESSOR

Circle 235 on Inquiry Card

Range of signal processing software found on the SPS-81 is utilized at a fraction of the hardware costs by the SPS-61 high speed programmable digital signal processor. It permits asynchronous I/O tasks to proceed concurrently with processing to achieve digital processing of continuous data streams with or without host computer involvement. User programming for realtime or batch operations can be at the FORTRAN, Macro-assembler, or Microcode assembler level. Signal Processing Systems, Inc, 223 Crescent St, Waltham, MA 02154.

TOGGLE SWITCHES

MINIATURE

Circle 236 on Inquiry Card

Toggle actuators, with color-coded plastic caps, are offered in 571 and 573 series switches. Options include five round toggles: short (0.220" or 0.559 cm), std (0.410" or 1.04 cm), and long (0.550, 0.640, and 0.840" or 1.4, 1.63. and 2.13 cm) as well as two lengths of flatted toggles (0.450 and 0.840" or 1.14 and 2.13 cm). With or without epoxy seals, 571 series offers six terminal options, while 573 series are designed for PC board mounting. Dialight, a North American Philips Co, 203 Harrison Pl, Brooklyn, NY 11237. Circle 237 on Inquiry Card

ALPHANUMERIC KEYBOARDS




Series EA boasts a bounce of <3 ms, resistance of <50 Ω , and key travel of 0.125" (0.318 cm). Keyboards include full alphanumeric assemblies for data entry applications and provide 60 keys and a space bar with as few as 24 output lines on a flexible tail to decode all contact closures. Custom legends and a range of coding matrices are available. Chomerics, Inc, 77 Dragon Ct, Woburn, MA 01801. Circle 238 on Inquiry Card

INTERCONNECT TEST SYSTEMS

Series 8210 automatic wire circuit analysis systems check electrical circuit paths of PC boards, wired backplanes, harnesses, wired racks or assemblies, and cables. System 8211 provides single real-time function with local single test station control; 8212 provides single or dual real-time functions with local or remote control of a single test station; and 8213 accommodates up to four test stations (local or remote) with real-time access to central control. A digital comparator performs resistance and voltage comparisons under program control over many decades. DIT-MCO International Corp, 5612 Brighton Terr, Kansas City, MO 64130. Circle 239 on Inquiry Card

KEYBOARD ENCODERS

A BCD or hexadecimal encoder can be added to the company's low profile keyboard with an optional "Adder-Board." Std unit is a 16-line to 4-bit parallel data encoder providing either BCD output when used with a 10-, 12-, or 16-station keyboard; or hexadecimal output when used with a 16-station keyboard. Optional key bounce elimination circuitry provides a delayed strobe pulse. Inputs are intended to be supplied Vcc (5 Vdc) through keyboard switches. Outputs interface with TTL or DTL. Stacoswitch, Inc, 1139 Baker St, Costa Mesa, CA 92626.



Circle 240 on Inquiry Card

With 87 different switching supplies to choose from, no wonder people are switching Power Mate.







But at Power-Mate we know it's not enough to offer you 87 different switching models in 10 different case sizes. From 2 volts to 28. In currents all the way up to 200

amps.
And we know it's not enough to build them to the highest quality standards in the industry.
Standards you've come to expect from Power-Mate.

When you need a switcher fast, your entire business could depend on ours.
So Power-Mate stocks all models

for immediate delivery on every switching model we make from both our East and West Coast plants.

The same goes for our open frame, modular and miniature models, as well as our laboratory supplies.


Whether starting from scratch, updating your system, or in need of emergency service, it's good to keep Power-Mate's name and number in mind. Because knowing where to get the switchers you want isn't much good, unless you can get them when you want them.



514 S. River St./Hackensack, New Jersey 07601/(201) 343-6294/TWX (710) 990-5023 17942 Skypark Circle/Irvine, California 92714/(714) 957-1606/TWX (910) 595-1766

The world's largest supplier of quality power supplies.

ASCII PARTY LINE SYSTEM



A mainframe which houses up to 10 programmable plug-in Smart PC cards permits automatic data acquisition and control systems to be connected without building hardware interfaces or writing software drivers. Transparent to user programs, the cards communicate with calculators, computers, and microprocessors via pre-formatted ASCII char, using decimal notations and std formats expected by the programs. ASCII party line system appears to the user's system as either a high speed teletypewriter (7000 ASCII char/s) or IEEE-488 bus instrument. Computer Data Systems, Inc, 186-58 Homestead, Morrison, CO 80465. Circle 241 on Inquiry Card


8-BIT TELEPRINTER

TC480, available in receive only (RO), keyboard send/receive (KSR), and automatic send/receive (ASR) versions, can be upgraded with optional I/O units and memory to an interactive terminal for both on- and offline data collection, time sharing, limited batch communications, text editing, and word processing. Minicomputer interface allows TC480 to operate as a console terminal. It can be equipped with RS-232, telegraphic (polar or neutral current), passive telegraphic, and 20 mA current loop options. Communication code is ASCII in 10- or 11-unit char structure, and transmission mode is asynchronous. Olivetti Corp of America, Telecommunication Products, 500 Park Ave, New York, NY 10022.



Circle 242 on Inquiry Card

POWER LINE CONDITIONER



Protecting sensitive electronic equipment against electrical interference, the line 2 conditioner filters and regulates electrical power. It eliminates installation of dedicated power lines needed by minicomputers, microcomputers, and other equipment. Line also protects against brownouts by automatically correcting voltages of 90 to 120 Vac to 120 Vac ±7%, or within ANSI limits. Plugged into a 120-V outlet, unit has two std 3-prong receptacles for powering equipment. Models are rated at 1 and 2 kVA. Topaz Electronics, 3855 Ruffin Rd, San Diego, CA 92123. Circle 243 on Inquiry Card

A stepper drive system for only \$12.60!

A quality stepper motor and IC driver that cuts design costs, simplifies circuitry, minimizes space

We've just put the cost of an incremental drive stepping system within reach! And we've simplified your job in doing so. The \$12.60 includes our K82701-P2 12V dc stepper motor and our SAA1027 IC driver in 100 piece quantities, basically all you need for a complete system, if you supply dc voltage and stepping pulse. The motor has a 7½° step angle, 200 steps/sec pull-in rate and 6.0 oz-in working torque. If these specs don't suit your proposed application, we have 7 other motors to choose from with pull-in rates and working torque values to satisfy most drive applications. 15° step angles are also available, as are 5V do models. Any one of the 7 can be driven by the IC driver without the need for discrete power stages. Use of the driver, in fact, cuts the cost and complexity of your circuitry to the bone. It's small in size, low in cost and assures maximum stepping accuracy in conjunction with our stepper motors. Find out more about NAPCC stepper systems.

Write for information today!

NORTH AMERICAN PHILIPS CONTROLS CORP.

Cheshire, Conn. 06410 • (203) 272-0301



terminals never die, never fade away. They are made of the finest materials, by people who care

about quality and durability. CAMBION offers 96 basic styles, more than 400 types — the widest selection of off-the-shelf solder terminals you can get anywhere. Terminals come in swage, press and thread mount types. Single, double or triple turrets, pin types without turrets, feed-thru, double-ended, hollow, flared and forked types. Close tolerances, precision threads, durable finishes, the best quality base materials—all are standard from CAMBION. Try us. You will return. For a free catalog, write or call CAMBION. Cambridge Thermionic Corporation, 445 Concord Avenue, Cambridge, MA 02138. Phone:

(617) 491-5400. In California, 2733 Pacific Coast Highway, Torrance, CA 90505. Phone: (213) 326-7822.

1:1[0

Guaranteed to be the right connection.

DATA COMMUNICATIONS DIAGNOSTIC UNIT

24

0


4



Interactive Hawk 4000 Datatrap monitors, transmits, and receives data between a modem and terminal on a 9" (23-cm), 512-char screen. Its internal microprocessor allows quick diagnosis of data communication problems; it permits trapping and storage of 2000 char for later recall and study. System operates with BISYNC, SDLC, HDLC, and ADCCP std protocols and handles fullduplex asynchronous data rates from 75 to 19,200 bits/s and synchronous line rates up to 75,000 bits/s. International Data Sciences, Inc, 100 Nashua St. Providence, RI 02904. Circle 244 on Inquiry Card

16-CHANNEL DIGITAL LATCH

The 16-channel DL 502 digital latch enhances the user's ability to make asynchronous measurements by latching pulses as narrow as 5 ns and amplitudes as small as 500 mV centered on a threshold set by the user. Device plugs into any TM 500 mainframe/power module and interfaces to the company's LA 501W logic analyzer with both housed in the mainframe. The company's P6451 low capacitance data acquisition probes connect to the latch, which can then interface to either the 7D01 or LA 501W analyzers. **Tektronix**, **Inc**, PO Box 500, Beaverton, OR 97077.



Circle 245 on Inquiry Card


uC-CONTROLLED 10-MHz MEMORY TESTER



M-5 is a dedicated benchtop tester designed for production testing of memory devices, memory boards, and memory systems, and for functional burn-in testing. An 8080A microcomputer functions as test supervisor, controlling the pattern processor, programmable power supplies, control panel emulation, error mapping software, and user communications. Basic system contains two 8-bit address generators; data pattern generation is expandable from 16- to 40-bit data word widths in 8-bit increments. Micro Control Co, 7956 Main St NE, Minneapolis, MN 55432. Circle 246 on Inquiry Card

Microprocessor Controlled Impact Printer for just \$345* Now that's what we call Practical! Laugh all the way to the bank, OEM's. With both matrix impact print head and built-in microprocessor controller, our DMTP-6uP is a budget printer in price only. In practice, it's one of the greats. You can print 80-96 columns of both data and text at a fast 110 cps. Turn out up to four copies at once on regular 8½ inch roll paper, even on fan-fold forms and labels. Not only are All that for \$345*? It's phenomenal... all needle drivers and diagnostic routines included with the microprocessor, but you can and it's also very Practical. choose the interface function you want — parallel ASCII, RS-232C/I-Loop, or switch-selectable baud rates from 110 to 1200. You even get the PRACTICAL AUTOMATION, INC. economy of easily-replaceable ink rollers and Trap Falls Road, Shelton, CT. 06484 a self-reversing 10-million character life ribbon. Tel: (203) 929-5381 * \$345 in 100 qts.; single units \$472 CIRCLE 87 ON INQUIRY CARD

HIGH RESOLUTION LINEAR ENCODER



With up to 50,800 pulses/in, (2000 pulses/mm), model 8716 consists of a glass scale with vacuum-deposited chrome lines, an optical reading head that takes up <2 in³ (32 cm³), and a separate electronics package. Salient features include non-contacting, friction-free operation; output data rates up to 500 kHz; quadrature square waves or direction-sensed pulse outputs; complete DTL, TTL, HTL, or CMOS compatability; and optional zero index pulse. Teledyne Gurley, 514 Fulton St, Troy, NY 12181.


Circle 247 on Inquiry Card

HIGH POWER HANDLING SOLID-STATE DEVICES

Handling high electrical currents in a compact efficient form, units have a heat pipe bonded directly to the silicon wafer. This cooling technique permits production of devices which are capable of handling hundreds of watts of power, yet are 75% smaller and 85% lighter than existing devices. The transcalent semiconductors have integral heat pipes that are bonded directly to the silicon wafers. Circular fins mounted on the external part of the heat pipe radiate the heat into the surrounding environment. RCA Corp, Solid-State Div, Rte 202, Somerville, NJ 08876. Circle 248 on Inquiry Card

DATA COMMUNICATIONS LINE MONITOR

Epiview accepts full-duplex data in either synchronous or asynchronous modes at speeds up to 100k bits/s, and displays them on a CRT in ASCII, EBCDIC, or hexadecimal code. In std





configuration, data are displayed on an integral 5" (12.7-cm) CRT, with selected segments accentuated by character blinking and/or reverse imaging. Data stream can be viewed in real time, or can be recorded to allow later data analysis. **Epicom, Inc,** 592 N Douglas Ave, Altamonte Springs, FL 32701. Circle 249 on Inquiry Card

MOBILE UPS SYSTEMS



PEP is designed to provide clean uninterruptible electric power to sensitive electronic equipment, and to protect this equipment from circuit fluctuations caused by voltage changes, overloaded lines, frequency shifts, or power failure. Std models output 100, 250, or 500 VA, and are complete with stainless steel cart. The system operates from internal batteries or from any std ac line, or from both. Marine Electric RPD, Inc, 178 National Rd, Edison, NJ 08817. Circle 250 on Inquiry Card





MULTICHANNEL MULTIPLEXERS

In plug-in configurations for use with either single-ended or differential analog input signals, the GMM-4 provides three performance features that complement the high resolution and accuracy of the company's 15-bit GMAD-4 A-D conversion system. Input-to-output linearity is within 0.01%; input impedance of 1 GO assures min degradation of accuracy with high impedance signal sources; and input current offset of <20 pA permitting high impedance signal sources to be directly connected to the ADC without reducing their accuracy. Preston Scientific, Inc, 805 E Cerritos Ave, Anaheim, CA 92805. Circle 251 on Inquiry Card

MAG TAPE CONTROLLER BOARDS

1

Mag tape controllers for all Data General Nova/Eclipse and compatible computers are software transparent to the computer's operating systems. Designed with std low power Schottky, single-board controllers are imbedded in mainframe or expansion chassis. TFC 701 offers NRZI recording for all std tape drives over a speed range of 12.5 through 125 in (31.8 to 318 cm)/s; TFC 702 offers both NRZI and/or phase encoded recording techniques over the same range. **Aviv Corp**, 300 Sweetwater Ave, Bedford, MA 01730. Circle 252 on Inquiry Card

2-SPEED SYNCHRO-TO-DIGITAL CONVERTER

Module set consists of two independent type II tracking S-D converters and a digital combiner to offer single speed and multispeed commonality, and immunity from analog crossover instability. Full 19-bit resolution reduces quantization and hysteresis error to <2.5 s of arc. Model LSI/36 2-speed modular S-D converters are based on an LSI Trig Logic™ processor and have 100-h burn-in. Specs include 10-r/s tracking on fine speed input. North Atlantic Industries, Inc, 200 Terminal Dr, Plainview, NY 11803. Circle 253 on Inquiry Card

SNAP-IN LED INDICATOR

Constructed of a finned black nylon body which can be simply snapped into a 0.156" (0.396-cm) hole in the panel, the 5L4 mounts on 0.25" (0.63 cm) center-to-center. With a T-1 size red diffused LED, unit outputs 0.5 mcd min at 20 mA. Operating voltages up to 28 V are permitted with the addition of a resistor on the anode lead. Electrical specs without resistor are typ forward voltage of 1.8 V at 20 mA and max continuous forward current of 70 mA. The Sloan Co, 7704 San Fernando Rd, Sun Valley, CA 91352.

Circle 254 on Inquiry Card


MODULAR BATTERY RECHARGER

Addition of a modular charger and substitution of NiCd cells for nonrechargeable dry cells, now permits a recharge capability. Recharger measures 1.75 x 1.75 x 1.75 x 1.75" (4.45 x 4.45 x 4.45 cm), plugs directly into wall socket, and has snap terminals that mate with terminals of std battery holders. All that is required for recharging batteries is unsnapping the battery pack from the product and snapping it onto the charger. **Dynamic Instrument Corp**, 933 L I Motor Pkwy, Hauppauge, NY 11787. Circle 255 on Inquiry Card

MULTICHANNEL DATA ACQUISITION SYSTEM

Model DA, a multichannel system with switching functions, is designed to accommodate from four to ten information channels. Auxiliary output signal drives remote indicators, recorders, controls, or computers for test stand monitoring or process control. Each channel has a single PC board that plugs into solidly mounted connectors, supplying transducer excitation and continuous output of 0 to 1 V. Tyco Instrument Div, 4 Hartwell PI, Lexington, MA 02173.

Circle 256 on Inquiry Card



ICC. The leader in light pens since 1966. Now offering improved performance. Lower prices too. What are you waiting for? Write for full details or call, today.



INFORMATION CONTROL CORPORATION

9610 Bellanca Ave., Los Angeles, Ca. 90045 (213) 641-8520

REMOTE CONTROL **MUX TERMINAL**



The 5000/6000 line of microprocessordriven remote terminal units (RTUs) for hostile environment and process/industrial applications are easily interfaced with most minicomputers. They are linked to central computers via in-plant wiring, voice-grade phone circuits, mi-crowave, or uhf/vhf radio. UART-compatible word formats and std RS-232-C serial interface permit RTU-CPU communications via std serial asynchronous interface port at rates to 1200 baud. Units can have up to 16k bytes of p/ROM-RAM. LFE Control System Industries, 2920 San Ysidro Way, Santa Clara, CA 95051. Circle 257 on Inquiry Card

STORAGE MODULE CONTROLLER

Model 4091 embedded storage module disc controller provides an interface for up to two CDC storage module series (or equivalent) disc drives, with capability of mixing or matching drives. Max storage capacity is 600M bytes. Unit contains a microprocessor for monitor and control of events, execution of commands, alternate-track selection, and on-the-fly CRC generation. Designed around Data General's 4231 controller, the device runs Data General software or company software drivers that can be system generated under RDOS. Datum, Inc, 1363 S State College Blvd, Anaheim, CA 92806. Circle 258 on Inquiry Card

FLEXIBLE PROBE

Unpluggable piercing flexiprobe, designed to flex on irregular surfaces, automatically realigns itself after contact with a test point, and penetrates any substance or residue on solder joints to give an accurate test reading of circuit boards. It can be inserted into front or rear loading receptacles and is interchangeable with all of the company's matching barrel diam unpluggable probes. Ostby and Barton, 487 Jefferson Blvd, Warwick, RI 02886. Circle 259 on Inquiry Card

TIME DIVISION MULTIPLEXER


Designed primarily for multiplexing/demultiplexing two simultaneous teleprinter messages with rates of 50 baud each in a full-duplex communication of 75 baud over a single line, unit possesses four switch operational modes: MUX, A ONLY, B ONLY, and LOOP. For single line mode, 50-baud carrying line is connected directly to long distance line, with the remaining subscriber line connected to an additional teleprinter, via AUX socket. Koor Systems Ltd. Sgoola Industrial Zone, PO Box 76, Petach Tykva, Israel.

Circle 260 on Inquiry Card


PE/NRZ MAG TAPE CONTROLLER

A plug-in single-board dual density controller, the TC-140 features total software compatibility with existing Interdata operating systems. With all interface and formatting electronics for both PE and NRZ, unit operates via selector channel or multiplexer bus. Up to four drives can be handled in any combination of 7-track NRZ, 9track NRZ, 9-track PE, or 9-track PE/ NRZ, at any two speeds in the range of 12.5 to 125 in (30.5 to 317.5 cm)/s. Western Peripherals, Inc, 1100 Claudina Pl, Anaheim, CA 92805. Circle 261 on Inquiry Card





DUAL-CHANNEL SILICA CORE FIBER OPTIC CABLE



Designed for 2-way communication, PFX-S220R cable resists physically hostile environments. Two inner cables, color-coded for identification, are reinforced with Kevlar 49 aramid fiber in a protective jacket of Hytrel polyester elastomer. Typ properties are 40-dB/km at 775 nm attentuation (50-dB/km at 820 nm), 0.4 (calculated) numerical aperture, 0.27 (-10 dB) exit numerical aperture, and core diameter of 200 μm. Silica core is well-centered within a tough hard cladding to which a connector may be directly crimped. Cables are resistant to radiation, vibration, microbends, impact, water immersion, and temp cycling from -80 to 150°C. Run lengths up to 1 km are possible. E. I. du Pont de Nemours & Co, Plastic Products and Resins Dept, Wilmington, DE 19898.

Circle 262 on Inquiry Card

-

20

44

10-1

1

CRT DISPLAY TERMINALS



A Teletype[™]-compatible display terminal with roll or page mode of operation utilizing the ASCII code set, model 200 features 80 x 24-char display, 9 x 9 dot matrix, character mode transmission, RS-232-C and 20/60-mA current loop interface, and 16 switch-selectable data rates up to 19,200 bits/s. The

unit's detached solid-state keyboard comes in five different configurations. Model 400 is a multifunctional terminal using the ASCII code set. Advanced functionality results from the internal Z80 microprocessor and firmware design. Capabilities include complete formatting and editing with block mode transmission, as well as character mode for normal log-in procedures or straight character operation. Infoton, 2nd Ave, Burlington, MA 01803.

Circle 263 on Inquiry Card

DATA CONVERTER

1

BAC-2780 receives EBCDIC data via IBM binary synchronous protocol, performs required error-checking functions, translates data to ASCII, and outputs them in serial asynchronous format to a user-attached receiving device. IBM bisync protocol with CRC-16 error checking allows error-free operation, yet the user can attach a peripheral device equipped with asynchronous ASCII RS-232-C interface. In operation, the unit receives data via a modem connection at modem-specified data rates up to 9600 Hz. The converter and its attached peripheral output device emulate an IBM 2780 receive-only terminal. Additional features include data transparency protocol and full BSC handshaking. KMW Systems Corp, 11807 Royalton Rd, North Royalton, OH 44133.



TAPELESS NUMERICAL CONTROL



CalCuTrol 52, a 5-digit, 2-axis control, combines a pocket calculator's simplistic operation with a microcomputer's programming sophistication and contains keys, displays, logic, and power supplies needed to drive two stepping motors in an open-loop configuration. Unit accepts random mixture of absolute and incremental data. Control features include insert/delete, high and low speed program examine, nine subroutines, ten canned programs, 475 sequences, and condensed step/repeat format. Automation Unlimited, Inc, 120 New Boston Pk, Woburn, MA 01801. Circle 265 on Inquiry Card

DUAL, ALPHANUMERIC LED DISPLAY

Hercules model 1785 LED display consists of two 0.54" (1.37-cm) high, red 14-segment char combined in a single package, which can display alphanumeric char plus some symbols. Composed of GaAsP emitting material, solid-state displays have typ 600 μ cd/segment luminous intensity at 20 mA/1.6 V_F. The 18 horizontal double DIP pins on 0.100" (0.254-cm) spacing are set up for multiplex drive. End stackable units have common cathode with right-hand decimal point. Industrial Electronic Engineers, Inc, 7740 Lemona Ave, Van Nuys, CA 91405.

Circle 266 on Inquiry Card

CRYSTAL CLOCK OSCILLATORS

HY-4560 low power CMOS oscillator operates from 5- to 15-Vdc power supply, draws only 20 mW, and can be furnished at any frequency from 600 Hz to 5 MHz. Requiring a 5-Vdc power supply, HY-4550 250 kHz to 50 MHz oscillator is TTL compatible. Both units measure 0.815 x 0.515" (2.07 x 1.31 cm) with a seated height of 0.200" (0.508 cm) and possess frequency stability of \pm 0.01% over specified operating conditions. **Hytek Microsystems Inc**, 16780 Lark Ave, Los Gatos, CA 95030. Circle 267 on Inquiry Card

QUAD BACKPLANE OPTION TO FLOPPY DISC SYSTEM

MF-11 floppy disc/LSI-11 system doubles backplane capacity through its optional H9270 quad backplane. Functionally identical to the PDP-11/V03, and using only 10.5" (26.7 cm) of rack space, it houses the Shugart dual floppy system, front panel console, DEC H9270 quad backplane, and power supply. System accommodates additional interface cards for various LSI-11 peripherals. Charles River Data Systems, Inc, 235 Bear Hill Rd, Waltham, MA 02154.

Circle 268 on Inquiry Card

INTELLIGENT REMOTE CONTROLLER

An S-100-based computer control system that communicates over std 110-Vac power lines, the IntrolTM system is intended to control appliances and equipment, or read status information at remote locations without the need for direct wiring. The AC ControllerTM board is S-100-compatible, controlling up to 64 remote units; AC RemoteTM unit has two independently controllable ac sockets that can turn two 500-W appliances on or off. Computer can also poll the remote to check on/off status. **Mountain Hardware, Inc,** PO Box 1133, Ben Lomond, CA 95005.

Circle 269 on Inquiry Card

NEW!



A mighty big catalog about some mighty small switches.

This 44 page catalog consolidates the complete line of C&K small switches into a single, fact-filled, easy-to-read volume. It includes everything you need to know about toggles, rocker and lever handles, printed circuit mountings, snap-acting pushbuttons, 6 AMP alternate action and momentary pushbuttons, subminiature and microminiature pushbuttons, illuminated rockers, miniature power, slide, and thumbwheel switches—plus how-to-order information and a complete list of worldwide C&K distributors. Ask for your free copy and we'll show you a million and one ways to turn on the juice.

C&K Components, Inc. 103 Morse Street, Watertown, MA 02172 TEL: (617) 926-0800 TWX: 710 327-0460 TELEX: 92 2546 Free Engineering Samples on Request.



René Robert Cavelier de La Salle led an expedition across the Atlantic in 1684 to colonize New Orleans. Unfortunately his campaign failed. He missed New Orleans and landed in Texas. His faulty sense of direction was not over-

looked by his followers who eventually killed him.

The right campaign in the wrong place can kill you.

Many a great campaign has died because it didn't get to the right place or the right people. When you advertise with BPA-audited (Business Publication Audit of Circulation, Inc.) magazines you know exactly whom you're reaching. BPA publications regularly update circulation figures, so your message gets to the people who can make your campaign a success.



We count, so your ads will.

This BPA-audited magazine donated the space for this ad, with creative and production costs contributed by BPA agency and advertiser members.

MAGNETIC TAPE TEST SYSTEM

1

27

用曲

W


11

-

di di

中華日本中

MBG-1 magnetic media BERT permits selective measurements of bit error on magnetic tape systems in the frequency band from 1 bit/s to 50M bits/s. The unit fully stresses systems by providing a broad range of pattern




generation and detection capability to cause the magnetic tape media as well as associated electronics to exhibit failure modes. In record mode, the instrument allows for combinations of switchprogrammable words up to 2048 bits long to be

interleaved with pseudorandom sequences ranging in length from 63 bits to approx 1M bits. In play back mode, error rate measurements can be made on either switch-programmable data field or pseudorandom data field as well as the composite. **Tau-Tron**, 11 Esquire Rd, Billerica, MA 01862. Circle 270 on Inquiry Card

LOGIC ANALYZER DISPLAY FORMATTER

Designed to expand capabilities of 50D and 50D16 logic analyzers, model 50D011 permits display of digital data on any std XY display or XY oscilloscope in timing domain, data domain, or map mode format. Data can also be viewed as either positive or negative true. In timing domain format all 16 lines and 510 bits of digital data, stored in the logic analyzer's memory are shown horizontally across the display. Cursor, trigger marker, and cursor readout operate as in the basic analyzer. In data domain format, sixteen 16-bit words, with their respective addresses and hex/octal conversions, are displayed in binary form according to the position of the cursor. Map mode generates an XY plot of data stored in memory, arranging them in a 4 x 4 (50D) or 8 x 8 (50D16) configuration. BP Instruments, Inc, 10601 S De Anza Blvd, Cupertino, CA 95014. Circle 271 on Inquiry Card

REAL-TIME CLOCK FOR TI 960/990



Clock models 960-030 and 990-030 are designed to operate as CRU interface cards, to provide hardware time and data support for 960 and 990 computer systems. Provision for battery backup allows time and date information to be maintained during power loss, eliminating need for operator initialization of time and data software counters. Operating systems on both computers can be modified to read time and data information directly from the clock module, providing long term accuracy not available with software counters. The 60-Hz line frequency supplies an accurate timebase under normal operation, while a crystal-controlled oscillator is used during power failure. Digital Interface Systems, Inc, PO Box 1446, Benton Harbor, MI 49022. Circle 272 on Inquiry Card

NEW!

...the MSC-300



The MSC-300...now available in the same simple, trouble-free design as the other clutches in our MSC Series.

Size for size the PSI Magnetic Spring Clutch (MSC) offers considerably more torque than conventional electric clutches.

features:

- A complete package ready for immediate installation
- Low cost
- Availability of standard D.C. voltages
- Self-lubricating powdered metal parts
- Wide range of applications

also:

- Bore sizes up to 1"
- 3¼" maximum O.D.
- Torque ratings to 250 lb. in. (static)



OEM using Dot Matrix, see this... **FULLY FORME**

CHARACTERS



Uses a unique EPSON designed



The world's largest manufacturer of minidigital printers now offers the desktop size model 10 Line Printer for OEM.

Compare these value features

- ☐ Clear readable fully formed characters.
- ☐ Prints minimum 150 lines per minute using 64 character set, 80 column format.
- ☐ Available also as OEM mechanism only.

EPSON products are made by Shinshu Seiki Co., Ltd., Japan.


Write or call for complete information

EPSON AMERICA, INC.

23844 Hawthorne Blvd., Torrance, CA 90505 Telephone (213) 378-2220 · TWX 910 344-7390

PRODUCTS

LIMITED DISTANCE MODEM



LDM404B, designed for full-duplex synchronous communication at 4800 bits/s, operates over 4-wire voice grade metallic lines (conditioned or unconditioned) and T carrier and most other carrier systems, and is suitable for use in metropolitan areas for mid-range applications where short haul units are not satisfactory but distances do not warrant the cost and complexity of long haul modems. Transmitter uses quaternary amplitude modulation followed by frequency translation to a narrow band centered in the voice channel. Receiver performance is optimized by delay equalizing with digital filtering techniques and using custom designed hybrid active phase processing networks. Gandalf Data Inc, 1019 S Noel, Wheeling, IL 60090.

Circle 273 on Inquiry Card

HIGH DENSITY STATUS/ALARM DISPLAYS

From eight to 64 alarm points are monitored in a unit only 1.75" (4.45 cm) high which can be rack, panel, or desk mounted. This high density packaging is suitable for applications requiring visual alarm annunciation. Control logic monitors status of alarm points. A pair of indicator lamps assigned to each point display status: green represents normal and red alarm. In event of alarm, the appropriate indicator lamp will show a flashing red display; simultaneously, a pulsating audible alarm will sound. Alarm inputs may be either NC or NO contacts or 24 Vdc, 48 Vdc, or ground voltage. Unit can be powered by 115 Vac, 24 Vdc, or 48 Vdc. All std ISA sequences are available. Puleo Electronics, Inc, 415 Merchant St, San Francisco, CA 94111. Circle 274 on Inquiry Card

MULTIPLE-OUTPUT SWITCHING SUPPLY



A natural convection-cooled unit that provides up to three independent dc outputs from 2 to 28 V, the 9F is available with a variety of current ratings (eg, 9F250TC-006 provides 5 V at 40 A, 12 V at 2.1 A, and 5 V at 5 A). Operation at 40 kHz not only eliminates heavy and large low frequency magnetic elements, but also insures silent

operation. Efficiency of approx 80% minimizes heat dissipation and provides economical operation. The unit accepts either 115- or 230-Vac line input with a tolerance from -20% to 10%. This tolerance combined with a 30-ms storage time makes the supply virtually brownout proof. Builtin overvoltage and overload protection are provided along with input fusing and soft-start circuitry. Powertec, Inc, 9168 De Soto Ave, Chatsworth, CA 91311.

Circle 275 on Inquiry Card

PROCESSORS WITH UP TO 128k WORDS OF MEMORY

PDP-8A/205, 425, and 625 processors incorporate a KT8-A memory management option in all configurations having from 32k to 128k words of core, MOS, or mixed core and MOS memory. The MS8-C MOS memory modules, available in both 16k- and 32k-word configurations, use 4k RAMS for high density. KT8-A and MS8-C modules permit current PDP-8/As to be upgraded to 128k-word capacity. The memory management option is software-compatible with programs written for -8s and permits access to the entire 128k words of memory by program and DMA devices. It also allows extended virtual field addressing, memory protection, and reduced operating system overhead. Digital Equipment Corp, Maynard, MA 01754.

Circle 276 on Inquiry Card


17

124

時

DOCUMENT READER/SORTERS

The 92660 and 92680 can read and sort encoded checks, credit card charges, customer billings, and food coupons at speeds over 35,000 documents/h. The smaller 92660 reader/sorter separates magnetically encoded documents according




to predetermined sets of characteristics and groups similar documents into individual pockets. Primarily for use in check processing applications, it features a MICR system that captures data from documents conforming to ABA spec 147R3 or ANSI X3.3, processing documents

at rates up to 830 6" (15-cm) documents/min. 92680 contains 14 document pockets and optional OCR and OMR reading capabilities which can capture magnetic as well as optical characters and marks from intermixed documents in a single pass. **Control Data Corp,** Box O, Minneapolis, MN 55440.

Circle 277 on Inquiry Card

INSTRUMENTATION CONTROLLER FOR ATE SYSTEMS



A-1000 Autoprogrammer is specifically designed for the company's SPG-800 programmable generator, but can also interface with other ASCII format equipment. For incoming or production inspection, calibration, or quality-control applications, the controller drives an SPG-800 linked to the UUT. Test unit is then connected to a programmable DVM and a printer, both of which may be controlled by the device. In operation, the autoprogrammer sends the generator specifying commands for parameters such as waveform, frequency, and amplitude; the generator in turn produces the signal needed for the UUT. Data from the tested device are read out on the DVM and hardcopied on the printer. The unit can be programmed to insert time delays from 1 to 10 s in multiples of 25 ms. Interstate Electronics Corp, 707 E Vermont Ave, Anaheim, CA 92803. Circle 278 on Inquiry Card

Stepmotors



Warner Electric, the leading manufacturer of Variable Reluctance step motors, is unique in its capability to respond to the need for a single prototype design or the highest volume production requirement at competitive prices.

Applications include: printers • floppy disc drives • sorting machines • postage systems • photographic equipment • solar panels • paper tape drives • instruments & controls.


Warner VR motors feature high stepping rates, with accuracy within ½°, fast response and high torque-to-inertia ratio.

Standard design models are listed below.

MODEL	STEP ANGLE	STEPS/ REV.	HOLDING TORQUE
SM-024	15°	24	35 to 140 oz. in.
SM-036	10°	36	30
SM-048	7.5°	48	170
SM-060	6°	60	750
SM-072	5°	72	60
SM-080	4.5°	80	750



STOP THEF!



Electronic Info-guard™ stops computer thieves

Computer-information thieves are among the most sophisticated of all white-collar criminals. Data transmission, processing, and storage are all open to the potential threat. Whether you are using small, medium, or large-scale computers or shared-resource networks.

Motorola's Info-guard system protects data against unauthorized access.

All Info-guard systems provide hardware, not software, protection for your computer information using the National Bureau of Standard's algorithm . . . an encryption code adopted by the U.S. Government to make it virtually impossible for information thieves to electronically crack your system.

OEM compatible, or simply added on to interface with operating computer systems.

Info-guard's designed-in protection is based on decades of experience in building secure communications for national defense.

If you're interested in making your computer data electronically safe, you need copies of the free booklets, "Computer Threats" and "The Infoguard Security Kit." Then we can talk about hardware prices and delivery. Call James Booth, 602/949-4111 or write to him at Motorola Government Electronics Division, Dept. F-4, P.O. Box 2606, Scottsdale, AZ 85252.



PRODUCTS

MINIATURIZED 6250-BIT/IN TAPE SUBSYSTEM



Offering minicomputer users four times the tape capacity in one-fourth the space, model 6250, a 6250-bit/in (2460/cm) magnetic tape subsystem, is available in std 19" (48-cm) EIA rackmount configurations. Transport is designed to fit PE and GCR data formats. A lower performance 6240 model, differing in only three plug-in modules and head assembly, operates with NRZI and PE data formats. Available in 45-, 75-,

100-, and 125-in/s (114, 190, 254, and 317 cm/s) configurations, units transfer data at rates up to 781k bytes/s, and have a rewind speed of 500 in/s (12.7 m/s). Subsystem includes a microprogram-controlled formatter/controller which can accommodate up to eight tape transports and can intermix any combination of up to four speeds and three tape densities. **Telex Computer Products, Inc,** 6422 E 41st St, Tulsa, OK 74135.

Circle 279 on Inquiry Card


FIXED-HEAD DISC SUBSYSTEMS

High performance head/track disc subsystems using Winchester-type technology provide high speed, extended controller features, and configuration flexibility necessary for applications requiring high speed data access or data acquisition rates. The subsystems transfer data at 910k bytes/s and have an avg access time of 10.12 ms. Drives are available in 2M-byte (model 6064) and 1M-byte (6063) capacities. Both are 8.75" (22.22-cm) high rackmounted units. Max subsystem capacity is four drives per subsystem in any combination of the two sizes. For use with Nova or Eclipse computers, the units are supported by multiprogramming advanced operating system (AOS) and real-time disc operating systems (RDOS). **Data General Corp,** Rte 9, Westboro, MA 01581.

Circle 280 on Inquiry Card

PDP-11 TO IEEE-488 BUS INTERFACE

Designed for use with DEC PDP-11 computers, the GPIB11-1 interface to the IEEE Std 488-1975 bus is configured as a single quad-height board which plugs directly into a small



peripheral controller slot, allowing the PDP-11 to talk, listen, or control up to 14 instruments on the bus. Hardware decoding of bus command messages ensures high speed operations. Software is provided as utility and driver programs that are available as macro source files which may be assembled as

FORTRAN, BASIC, or macro-callable subroutines. Interface includes a 2-m cable with a std bus connector on one end. **National Instruments**, PO Box 9922, 8330 Burnet Rd, Austin, TX 78758.

Circle 281 on Inquiry Card

LITERATURE

Supervisory Control Equipment

100

中国是中国的一个公司工作的一个人的一个人的一个人的一个人的一个人

Block diagrams and descriptions are given in brochures describing series 8000, a master station designed for small to moderate size supervisory control and data acquisition systems, Harris Corp, Controls Div, Melbourne, Fla. Circle 300 on Inquiry Card

Accustic Telephone Coupler

Data sheet describes the model 503A acoustic coupler, designed to interface with any std LA36 terminal for conversational timesharing of a remote computer system. Omnitec Data, Phoenix, Ariz. Circle 301 on Inquiry Card

Digitizing Systems

Folder defines the process of and application for sonic digitizing, and details specific applications for data converters, interfaces, and related devices. Science Accessories Corp, Southport, Conn. Circle 302 on Inquiry Card

Rack Mounted Modems

Data sheet describes and illustrates the 113BR2 FCC-registered LSI modem that transmits and receives binary serial data at rates up to 300 bits/s. General Data-Comm Industries Inc, Wilton, Conn. Circle 303 on Inquiry Card

Connecting Systems

Connectors, relay sockets, metal plating and anodizing, systems installation hardware, and fluid systems are presented in condensed catalog containing features and photographs. Viking Industries, Inc, Chatsworth, Calif. Circle 304 on Inquiry Card

Programmable Controllers

Foldout bulletin, including diagrams and condensed specs, outlines the Automate^R 31M and 31ML microprocessor-based controllers that incorporate functional programming language. Reliance Electric, Cleveland, Ohio.

Circle 305 on Inquiry Card

Screened Image Displays

Application note provides an overview of SP-400 screened-on-glass, planar gas discharge displays by encompassing a description of family characteristics, applications, and specs. Beckman Instruments, Inc, Information Displays Operations, Fullerton, Calif.

Circle 306 on Inquiry Card

CCITT V.35 Interface

Wallet card and stick-on labels contain a chart that gives pin assignment, common mnemonic name, direction of signal flow, RS-232 or V.35 spec, and function of each signal in terminal-modem interface. International Data Sciences, Inc, Providence, RI.

Circle 307 on Inquiry Card

Switches

Catalog, comprised of photos, line drawings, and specs, describes slide, snap action, rotary, pushbutton, toggle, leaf, rocker, and paddle switches. Chicago Switch, Inc, Chicago, Ill.

Circle 308 on Inquiry Card

CMOS Microprocessor Components

Features, descriptions, functional diagrams, and instruction summary are given in 20-pg brochure on the 1800 family of LSI components. Hughes Aircraft Co, MOS Products, Newport Beach, Calif. Circle 309 on Inquiry Card

Digital Datalogging

Benefits of digital datalogger are demonstrated in booklet that covers data reliability, noise rejection, low cost alarm annunciation and process control, and operation with online computer systems. Acurex Autodata Inc, Mountain View, Calif. Circle 310 on Inquiry Card

Timeshared Microcomputer System

Brochure lists features, utilities, and systems available for S-100 bus-compatible Alpha Micro multiuser, multitasking software development system, MicroAge, Tempe, Ariz.

Circle 311 on Inquiry Card

Card Edge Connectors

Series "AC" gold dot connectors are featured in brochure that includes a cutaway diagram, statistics, and technical information on contact type and tail length, number of positions, dimensions, and options. GTE Sylvania Inc, Titusville, Pa. Circle 312 on Inquiry Card

Data Communications

Handbook, "Telecommunications from the Terminal User's Viewpoint," covers technical aspects and applications of modems, automatic dialers, and associated equipment with diagrams and graphs. Vadic Corp, Sunnyvale, Calif.
Circle 313 on Inquiry Card

Alphanumeric Impact Printer

Standalone model AIP-40 printer with a 50-char/s rate is discussed in booklet containing block and timing diagrams, and electrical and mechanical specs. Datel Systems, Inc, Canton, Mass.

Circle 314 on Inquiry Card

Microminiature Connectors

Miniature rectangular, circular, center jackscrew, and strip connectors, available in densities up to 1600 contacts/in², are depicted through dimensional diagrams, electrical specs, and std wire terminations in 64-pg catalog. ITT Cannon Electric, Santa Ana, Calif.

Circle 315 on Inquiry Card

Thyristor Gating

Application report describes use of triacs, scrs, and thyristors in microprocessor-based control systems, noting factors involved in coupling, isolation, transient noise problems, and circuit malfunction protection. Texas Instruments Inc, Dallas, Tex.

Circle 316 on Inquiry Card

Variable Resistors

Series 550 of 2-W, 0.75" (1.9-cm) diam cermet resistors are depicted through dimensional drawings in catalog that also includes electrical and mechanical characteristics. CTS Corp, Chicago, Ill. Circle 317 on Inquiry Card

DIP Headers

Catalog on DIP header series 600, 625, and 8625, and pin line header series 0600 and 0625 gives dimensioning, material details, and available platings. Aries Electronics, Inc, Frenchtown, NJ.

Circle 318 on Inquiry Card

Component Burn-In

Graphs, charts, tables, photographs, applications, typ burn-in load circuits, and glossary of terms characterize handbook on component burn-in technology. Wakefield Engineering, Inc, Systems Div, Wakefield, Mass.

Circle 319 on Inquiry Card

Power Cords

Catalog presents technical and application details, physical and electrical specs, and illustrations on type SJT shielded and unshielded electronic cords for data handling equipment. Belden Corp, Electronic Div, Geneva, Ill.

Circle 320 on Inquiry Card



LITERATURE

Low Profile DIP Relay

Features, applications, and dimensional diagrams comprise brochure illustrating the sensitive dpdt electromechanical relay that fits std 16-pin IC sockets. Gould, Inc, Control and Systems Div, Plantsville,

Circle 321 on Inquiry Card

Teleprinters

Illustrated with photogaphs, brochure lists features and specs for the EDT 1232 line of 120-char/s teleprinters. Western Union Data Services Co, Mahwah, NJ. Circle 322 on Inquiry Card

Indicator Lights and Lampholders

Short-form catalog covers features, dimensional drawings, and electrical and mechanical specs of std lenses, incandescent and neon indicators, cartridge hardware, and lampholders. Chicago Miniature Lamp Works, General Instrument Corp, Chicago, Ill. Circle 323 on Inquiry Card

Monopanel Keyboards

Brochure lists detailed product specs, dimensional drawings, schematic diagrams, and output code charts for 12- and 16-key keyboards with alphanumeric or telephone format nomenclature. Centralab Electronics Div, Globe-Union Inc, Milwaukee, Wis. Circle 324 on Inquiry Card

Magnetic Media Measurements

Brochure contains techniques utilized in making digital measurements and includes a description of typical stress patterns as well as the making of measurements on selected portions of these patterns. Tau-Tron, Inc, North Billerica, Mass. Circle 325 on Inquiry Card

Scanning Systems

Line of computer-assisted, high speed and precision digital flatbed scanning systems is encompassed in brochure that points out descriptions and operating specs for each model. Optronics International, Chelmsford, Mass. Circle 326 on Inquiry Card

10-Col Thermal Printhead

Bulletin on DM-1050, a printhead that allows nonimpact printing at speeds to 8 lines/s, specifies descriptions, features, performance characteristics, application data, thermal paper manufacturer listing, and dimensional drawings. Gulton Industries, Inc, Hybrid Microcircuit Dept, Metuchen, NJ.

Circle 327 on Inquiry Card

1977 Computer Design Index

An annual listing of articles, columns, product features, and special items

120

	COMPONENTS		
C	ircuit Protectors		
0	verload-Protector/Fault-Indicator Circuit, NASAMay,	р	130
P	ower Converters		
Se	Application Contest—A Microprocessor-Con- trolled Three-Phase Power Inverter, P. van der Gracht and K. MauchMay,	p	120
P	ower Sources and Regulators		
	witching Power Supplies: Design Considera- tions, E. R. HnatekFeb,	p	89
Si	witching Power Supplies: Specification Criteria, J. H. Burens		
	COMPUTERS		
C	communications Processors		
C	ommunications Processor Fulfills Multiplicity of Duties Under Program ControlSept,	р	168
P	rogrammable Multiline Communications		
P	rocessor Provides Front-End Flexibility, K. T. CoitMay,	p	99
C	computer Auxiliary Units		
	n Asynchronous Arbiter Resolves Resource Allocation Conflicts on a Random Priority asis, K. Søe Højberg	р	120
C	computer Diagnostic Equipment		
p	/ROM Card Simplifies Computer Diagnosis, S. WaserJan,	p	98
G	General		
C	Computer Simulation on a Pocket Calculator, R. Zussman	D	105
C	omputer Queuing Analysis on a Handheld		
D	Calculator, R. ZussmanNov,		
Т	DishonApr,	þ	00
	processor Systems, J. PathakJuly,	p	95
	nformation Systems igital Controller for Microfiche Display Selection, G. E. KingOct,	p	110
	licroprocessors/Microcomputers		
	Analysis of Multiple-Microprocessor System Architecture, A. J. WeissbergerJune,	p	151
	n Integral Real-Time Executive for Microcomputers, K. Burgett and E. F. O'NeilJuly, Task-Scheduling Executive Program for Mi-	p	77
H	last collecting Excounte Flogram for mi-		

crocomputer Systems, D. A. TownzenJune, p 194

cessor Efficiency, J. Cosley and S. VasaJan, p 81


Block Transfer with DMA Augments Micropro-

Comparisons and Trends in Microprocessor Architecture, E. E. KlingmanSept,	p	83
Complete Microcomputer Control System Develops and Debugs Programs Online in High Level Language		
Dual System Develops Software for Two Independent Microcomputers at Same TimeAug,		
Fifth Prize—Microprocessor/Microcomputer Application Contest—Electronic Diet Control-		
ler, K. M. MoranAug, First Prize—Microprocessor/Microcomputer Ap-	p	116
Plication Contest—Microprocessor Restroom Robot, C. A. WiatrowskiApr, Formal Methods Expedite Microprocessor-	p	98
Based System Design, B. J. CareyFeb, Fourth Prize—Microprocessor/Microcomputer	p	97
Application Contest—A Microprocessor Controller For an Epitaxial Reactor, D. Herberg, N. Ratnakumar, and P. E. LobbanJuly,		100
Hardware Multiplication Techniques for Micro- processor Systems, B. Parasuraman		
Microcomputer Interfacing: Data AcquisitionSept,	p	124
Microcomputer Interfacing: Interfacing a 10-Bit DACJune,	p	203
Microcomputer Interfacing: Interfacing Analog- to-Digital ConvertersAug,	p	124
Microcomputer Interfacing: Internal Registers Within the 8080 ChipJan,	p	123
Microcomputer Interfacing: Preparing Your ProgramsNov, Microcomputer Interfacing: Register Pair In-	p	124
structions	p	122
DevicesDec,	p	106
Microcomputer Interfacing: Subroutines and Stacks Oct,	p	132
Microcomputer Interfacing: The 8080 Logical Instructions	p	136
Microcomputer Interfacing: The MOV and MVI 8080 InstructionsFeb,	p	120
Microcomputer Interfacing: Using Digital-to- Analog ConvertersJuly,	p	116
Microcomputer Interfacing: What is a Logical Instruction?	p	116
Data Communications Network, D. J. MuellerOct,	p	81
Microprocessor System Validation and Failure Isolation with Portable Tester, J. W. NeeseSept,	p	105
Peripheral Interfacing with Microprocessors, A. J. WeissbergerFeb, Portable System Enables Online Debugging of	p	108
Microprocessor-Based EquipmentJune, Second Prize—Microprocessor/Microcomputer	p	228
Application Contest—A Microprocessor-Con- trolled Three-Phase Power Inverter, P. van		400
der Gracht and K. MauchMay, Third Prize—Microprocessor/Microcomputer	p	120
Application Contest—A Microcomputer-Con- trolled Seeder, V. WrobelJune,	p	184

Minicomputers and Small Computers	Data Communications Networks
Approach to Unified Bus Architecture Side- steps Inherent Drawbacks, J. W. ConwayJan, p 71	Microcomputers Decentralize Processing in Data Communications Network, D. J. MuellerOct, p 81
Design Decisions Achieve Price/Performance	Data Transmission Equipment
Balance in Mid-Range Minicomputers, J. C. MudgeAug, p 87	Two-Step Procedure Improves CRC Mechanism,
Microcode Increases Minicomputer Processing Capability, S. BuchwaldOct, p 91	P. J. FortuneNov, p 120 General
Multiprocessors	Certification 1977Dec, p 11
Time Slicing Offers an Alternative to Multi-	Computer-Aided Network DesignApr, p 18
processor Systems, J. PathakJuly, p 95	Computerized Voice Network ControlAug, p 12
Programmable Calculators	Data Communications ConsultantsOct, p 10
Computer Simulation on a Pocket Calculator,	Data Network ResponseJan, p 14
R. ZussmanMay, p 105	Office AutomationNov, p 14
Computer Queuing Analysis on a Handheld	Possible 1977 WATSMar, p 12
Calculator, R. ZussmanNov, p 85	Ramifications of the Revised WATS TariffJuly, p 11
Signal Processors	Shared User NetworksJune, p 11
Multichannel High Speed Correlator, NASAFeb, p 114	System Environmental FactorsSept, p 18
Pattern Recognition: Basic Concepts and Imple-	Terminal Storage Systems
mentation, D. Feucht	WATS Past and PresentFeb, p 14 Other Data Communications Equipment
Time-Sharing Computers and Systems;	Continuous-Phase Frequency-Shift-Keyed GeneratorFeb. p 118
Distributed Systems	Manchester Transition Tracking LoopOct, p 124
A Distributed Computer System for Laboratory Automation, G. A. KornJune, p 177	Taking 200p
	DIGITAL CIRCUITS
CONFERENCES	Digital Integrated Circuits (See Semiconductor Storage under Memory/
COMPCON 77 Spring: IEEE Computer Society International ConferenceFeb, p 58	Storage, and Microprocessors/Microcomputers under Computers)
COMPCON 77 FALL: IEEE Computer Society	Logic Circuits
International ConferenceAug, p 82	Mixed Logic Leads to Maximum Clarity with
ELECTRO 77	Minimum Hardware, F. Prosser and D. WinkelMay, p 111 LSI Circuits
strumentation Conference	Charge-Transfer Devices—Part 1: The Tech-
IFIP 77: International Federation for Information Processing CongressJune, p 144; July, p 64	nologiesNov, p 146
ISSCC 77: IEEE International Solid-State Circuits ConferenceJan, p 60	Charge-Transfer Devices—Part 2: CCD Memories
MIDCON 77Oct, p 74	Have the LSI Parts You Buy Been Thoroughly
NCC 77: National Computer Conference	Tested?Oct, p 152
May, p 68; June, p 85	Multiple-Word Buffering for Disc Controllers
WESCON 77: Western Electronic Show and	with Bipolar FIFO Memory, K. RallapalliDec, p 73
ConventionAug, p 62	Semicustom Integrated Circuits—The Do-It- Yourself LSI ChipsSept, p 148
And the second s	Peripheral Drivers
DATA COMMUNICATIONS	VMOS Peripheral Drivers Solve High Power Load Interface Problems, L. ShaefferDec, p 90
Communications Multiplexers	
Multiplexer System Reduces Cost of Terminal Interfacing, A. Lesea and N. UrkumyanAug, p 109	DIGITAL MATHEMATICS
Communications Systems	Arithmetic
Communications Processor Fulfills Multiplicity of Duties Under Program ControlSept, p 168	An Algorithm for Nonrestoring Division, S. Sanyal
Programmable Multiline Communications Processor Provides Front-End Flexibility, K. T.	Hardware Multiplication Techniques for Micro- processor Systems, B. ParasuramanApr, p 75
CoitMay, p 99	Digital Logic and Switching Theory
Data Communications Interfaces	Mixed Logic Leads to Maximum Clarity with
Design Constraints For a UART-Based Minicomputer Communications Interface, A. HirschJune, p 167	Minimum Hardware, F. Prosser and D. WinkelMay, p 111

Information Theory		
An Asynchronous Arbiter Resolves Resource Allocation Conflicts on a Random Priority Basis, K. Søe Højberg		120
Computer Queuing Analysis on a Handheld Calculator, R. ZussmanNov,		
Computer Simulation on a Pocket Calculator, R. Zussman	p	105
Data Compaction in Computer Systems, Y. Dishon	p	85
Two-Step Procedure Improves CRC Mechanism, P. J. Fortune	p	120
INPUT/OUTPUT AND RELATED EQUIPME	N.	Т
Data Collection		
Designing a Microprocessor-Based Terminal for Factory Data Collection, W. S. HolderbyMar,	р	81
Display Equipment (See also Graphic Equipment)		
Design of Intelligent CRT Terminals Stresses		
User Considerations		
	P	100
Graphic Equipment An Interactive Software Program for a Stand-		
alone Graphic System, R. I. RossSept, Computer Display Monitor Combines Benefits	p	114
of Both Storage and Refresh GraphicsMay,	p	158
Digital Image Processor Links TV Signal Sources to Computer, R. DahlbergOct, Flat Panel Displays Offer Graphics Alternatives,	p	115
J. W. AichrothOct,	p	101
Low Cost Analog I/O Systems Fully Compatible with Single-Board MicrocomputersFeb,	p	148
Optical Data Acquisition System Combines Video and Digital TechnologiesOct,	р	166
Single Architecture Terminal Combines Graphic and Alphanumeric CapabilitiesApr,	p	150
Interface Equipment		
Computer/Computer Interface, NASAMar, Design Constraints for a UART-Based Minicomputer Communications Interface, A.	p	118
HirschJune,	p	167
Peripheral Interfacing With Microprocessors, A. J. WeissbergerFeb,	p	108
Printers/Plotters		
Computer Graphic Family Offers Multifunction Capability	n	150
Printer/Plotter is Price-Compatible with Micro-processor SystemsJuly,		
Voice Response Equipment		
Design Guidelines for a Computer Voice Response System, P. ThordarsonNov,	p	73
INSTRUMENTATION AND CONTROL		
Analog-Digital and Digital-Analog Conversion Equipment		
Highly Stable Analog-to-Digital Converter, NASA Jan,	р	106
Low Cost A-to-D Conversion During Microcomputer Idle Time, H. A. RaphaelMar,	р	112

**



Raster scan high resolution refresh graphics

at a price you can't ignore

Now you can have a system to meet your unique computer-graphics applications

System-sophistication made practical for the $\ensuremath{\mathsf{OEM}}$ and end-user

- Full refresh, flicker-free, raster scan display

 up to 1280 x 1024 pixels in 16-levels of grayscale
 display 1024 simultaneous colors from color look-up table
 up to 16 bits of intensity or overlay data per pixel
- Interfaces for most minicomputers
- Gamma-corrected and composite video output
- High-speed, variable image processing

 pixel update as fast as 45 nsec per pixel
 random and sequential update
 dynamic memory allocation
 writeable control store
- User can program the alphanumeric generator and define the cursor
- Nondestructive functions to highlight image displayed -vector and alphanumeric overlays on image -zoom with continuous 4-directional scrolling
- Command I/O and DMA to host computer
- Peripheral options

A versatile graphics-system to meet your widely diverse needs that you'll want to know more about. Just write Lexidata Corporation, 215 Middlesex Turnpike, Burlington, MA 01803 or faster yet, call us at 617 273-2700, and ask for Martin Duhms.



215 Middlesex Turnpike, Burlington, MA 01803 617 273-2700 • TWX 710-332-1381

Code Converters	Control Gas DistributionFeb, p 46
A 1½ Level On-Chip-Decoding Bubble Memory Chip Design, NASAFeb, p 116	Weather Study System Incorporates High Ca- pacity Semiconductor MemoriesOct, p 66
Binary/BCD-to-ASCII Data Converter, NASANov, p 110 Microprocessor-Based Interface Converts Video	Process and Instrument/Computer Interfaces
Signals for Object Tracking, K. Lubinski, K. Dickson, and J. Cairns, JrDec, p 81	Low Cost Analog I/O Systems Fully Compatible
	with Single-Board MicrocomputersFeb, p 148
Data Acquisition Systems	
Microprogramming for Real-Time Data Acqui- sition, NASA	MEMORY/STORAGE
Optical Data Acquisition System Combines Video and Digital TechnologiesOct, p 166	Flexible Disc Storage
Digital Equipment Testers	Diskette Drive Provides 4-sided, Double-Den- sity CapabilityNov, p 168
Common Misconceptions in Digital Test Gen-	Synchronous Adapter Reduces Complexity of
eration, J. J. ThomasJan, p 89	Floppy Disc Controller, M. E. Eidson and L. A. ParkerApr, p 102
Electrical Scanning Reduces Back-Panel Test- ing Time, M. KarrMar, p 104	Magnetic Disc and Drum Storage
Microprocessor System Validation and Failure Isolation with Portable Tester, J. W. NeeseSept, p 105	Multiple-Word Buffering for Disc Controllers
Pattern Sensitivity Techniques for Testing CCD	with Bipolar FIFO Memory, K. RallapalliDec, p 73 Servo Control Technique Enhances Perfor-
Memories, I. D. VancovNov, p 106 Portable System Enables Online Debugging of	mance of Disc Storage Units, T. W. WrightMar, p 99
Microprocessor-Based EquipmentJune, p 228	Magnetic Domain Memories
Understanding Logic Analyzers, R. L. DownJune, p 188	A 1½ Level On-Chip-Decoding Bubble Memory Chip Design, NASAFeb, p 116
Digital Filters RAM Digital Filter, NASAMay, p 134	Variable-Gap Bias Structure for Magnetic Bub-
Monitoring and Control Equipment	ble Memory Package, NASAJan, p 104
Aircraft Landing/Take-Off Noise Levels Identi-	Magnetic Tape Storage Magnetic Tape Formatter Design Reduces
fied and Monitored by Computer SystemsSept, p 76 Automated Updating Gives Security Trading	Hardware/Software Requirements, A. S. McPhillipsNov, p 99
Firm Constant View of InventoryAug, p 52	Read-Only Storage
Automatic, Interactive Graphic Systems Main- tain Pipeline Network MapsApr, p 58	p/ROM Card Simplifies Computer Diagnosis,
Brooklyn Firefighting Units Respond to Computer-Aided Dispatching SystemNov, p 48	S. WaserJan, p 98 Solving Mass-Produced ROM Programming
Cargo Vessel Load Stresses Simulated by Multi- point Computer SystemsDec, p 48	Problems with Base Registers, J. A. CarrollAug, p 99
Chromatography System Provides Continuous	Semiconductor Storage An Update on MOS ROMs, D. HuffmanSept, p 95
Analysis of Gas SupplyJune, p 67 Complete Microcomputer Control System De-	Battery Backup for Minicomputer Semiconduc-
velops and Debugs Programs Online in High Level LanguageMar, p 146	tor Memories, J. WashburnApr, p 108 Pattern Sensitivity Techniques for Testing CCD
Computer-Directed Warehouse System Relieves	Memories, I. D. VancovNov, p 106 The Case for Using Partially Good Memory De-
Personnel by Locating Parts and Maintaining PaperworkOct, p 54	vices, R. H. F. LloydApr, p 93
Computerized Ripple Control Eliminates Excessive Drain On Electric Utility SupplyMar, p 55	Timing Peculiarities of Multiplexed RAMs, J. R. BrownJuly, p 85
Computers Oversee All Activities of Tower RestaurantMay, p 50	
Data Acquisition System Automatically Moni-	NON-EQUIPMENT
tors Steel Rolling MillJune, p 62	Magnetic Media
Efficiency of Electric Power Generation and Distribution Improved by Energy Management SystemJuly, p 48	Designer's Guide for Selecting Magnetic Mini- Media, A. B. ManildiSept, p 120a
Fourth Prize—Microprocessor/Microcomputer	Purchasing
Application Contest—A Microprocessor Controller For an Epitaxial Reactor, D. Herberg,	Competent Purchase Specifications Help Assure Successful Product, D. M. HamblenMay, p 128
N. Ratnakumar, and P. E. LobbanJuly, p 108 Instrument Industry Recognizes Digital Elec-	Software
tronics—Almost, S. F. ShapiroJan, p 50 Microcomputer-Controlled Laser Burns Labels	An Interactive Software Program for a Stand-
on ContainersOct, p 66	alone Graphic System, R. I. RossSept, p 114 A Task-Scheduling Executive Program for Mi-
Program and Extensive Data Base Alert Physicians to Possible Adverse Drug ReactionsJune, p 72	crocomputer Systems, D. A. TownzenJune, p 194
Program Flexibility of Microprocessor-Con- trolled Elevators Enables Easy System Modifi-	Standards Decumentation Standards Clarify Decign F
cationsSept, p 54	Documentation Standards Clarify Design, J. F. WakerlyFeb, p 75

GUIDE TO PRODUCT INFORMATION

NOTE: The number associated with each item in this guide indicates the page on which the item appears—not the reader service number. Please do not circle the page number on the reader service card.

MATERIALS PAGE	PAGE	PAGE
OPTICAL MATERIALS AND FORMS	POWER SOURCES, REGULATORS,	Communication Interface Modules
Fiber Optic Cable	AND PROTECTORS	Dataprobe161
E. I. du Pont de Nemours/Plastic Products and Resins169	Power Supplies ACDC Electronics160	Communications Module Process Computer Systems112
	Power/Mate163	Asynchronous Serial Line Adapter
HARDWARE	Switching Power Supplies	MDB Systems155
BUSES	Gould/Electronic Components26, 162 Powercube132	Control System Modules
Busing PC Board	Powertec	Harris/Controls160
Bussco Engineering166	Mobile UPS Systems	A-D Converter Module Analogic
CONNECTORS AND INTERCONNECTION	Marine Electric RPD166	D-A Converter Module
SYSTEMS	DC-DC Converters Semiconductor Circuits163	Zeltex162
Connectors Amphenol North American/Bunker	Power Line Conditioner	S-D Converter North Atlantic Industries167
Ramo49, 159	Topaz Electronics164	Keyboard Encoder Board
Flat Cable Connectors	Modular Battery Recharger	Stacoswitch163
GTE Sylvania/Connector Products 43	Dynamic Instrument167	Voice Response Board
Subminiature Connectors	SEMICONDUCTOR COMPONENTS	Vocal Interface/Federal Screw Works160
Positronic Industries155	Solid-State Power Devices RCA Solid State166	Real-Time Clock
FANS AND BLOWERS		Digital Interface Systems171
Ultra-Miniature Fan Micronel155	SENSORS; TRANSDUCERS Audio Indicators	DIGITAL AND INTERFACE
HEAT SINKS	Citizen America 14	INTEGRATED CIRCUITS
Heat Sink	SWITCHES	Semicustom MOS Chips
Vemaline Products/Ostby and Barton168	Switches	International Microcircuits148
INDICATORS; READOUTS;	C&K Components170	FPLAs Texas Instruments/Components147
DIGITAL DISPLAYS; LAMPS	Micro Switch/HoneywellCover III	Bipolar Multipliers
LED Indicator	DIP Switches AMP 18, 19	TRW Electronic Components148
Sloan	Grayhill 79	4k RAMs
Fiber Optic Readout Assembly Master Specialties159	Subsubminiature Switch	EMM SEMI/Electronic Memories & Magnetics
Dual, Alphanumeric LED Display	Otto Controls/Otto Engineering161	Intel148
Industrial Electronic Engineers170	Miniature Toggle Switches Dialight/North American Philips163	RAM-I/O Chip
Status/Alarm Displays	Unibus Switches	National Semiconductor140
Puleo Electronics172	Datafusion155	16k p/ROM Signetics8, 9
PANELS AND BOARDS	Oscilloscope Adapter Switch	CCD Memory IC
Wirewrap Panels Hybricon163	Mid-South Instrument Services160	Fairchild Semiconductor Products12, 13
		Shift Registers
PARTS	CIRCUITS	Advanced Micro Devices
Sprockets La Vezzi Machine Works162	CIRCUIT CARDS AND MODULES	Flexible Disc Controller/Formatter
SOCKETS	Logic Modules	Western Digital146
Sockets	MDB Systems147	Microprocessors
AMP158	Semiconductor Memory Boards	Intel
Robinson-Nugent44, 45, 158	Intel Memory Systems154, 155 Monolithic Systems80, 153	Motorola Semiconductor Products24, 25
WIRE AND CABLE	EPROM Programmer	D-A Converters
Wire and Cable	Optimal Technology116	ILC Data Device147
Belden/Electronic158	Flexible Disc Interface	Signetics148 Display Drivers
WIRING PINS AND TERMINALS Solder Terminals	Pacific Cyber/Metrix116 Analog I/O Boards	LSI Computer Systems148
Cambridge Thermionic164	Burr-Brown114	HYBRID CIRCUITS
	I/O Expansion Card	Hybrid Peak Detectors
COMPONENTS AND ASSEMBLIES	National Semiconductor126	Burr-Brown144
MOTORS; ROTATIVE COMPONENTS	Tape Controller Boards Aviv167	LINEAR INTEGRATED CIRCUITS
Stepper Motor/Driver	Western Peripherals168, 176	Transmitter-Receiver IC
North American Philips Controls164	Controller/Interface Board	Standard Microsystems144
Brakes and Clutches	Andromeda Systems122	OSCILLATORS
Warner Electric Brake & Clutch169, 171, 173	Bus Interface Board National Instruments174	Crystal Clock Oscillators Hytek Microsystems

PAGE	PAGE	PAGE
MEMORY/STORAGE EQUIPMENT	COMPUTER PERIPHERALS	Line Printer/CRT Plotter
LEXIBLE DISC UNITS	Microcomputer Peripherals	Wang Laboratories152
Flexible Disc Drives	Standard Engineering166	Electrostatic Printer/Plotter Versatec/Xerox
Digicom Data Products156	Xebec Systems88, 89	PRINTING EQUIPMENT
iCom	DATA TERMINALS (See also Graphic Equipment)	
Shugart Associates134, 135	Data Terminals	Printers Diablo SystemsCover IV
Flexible Disc Systems Charles River Data Systems170	Teletype 7	Facit-Addo104
Data Systems Design143	Texas Instruments/Digital Systems 47	Hewlett-Packard92, 93
Flexible Disc Interface	Teleprinters	Lear Siegler137 Printronix123
Pacific Cyber/Metrix116	Hewlett-Packard92, 93 Olivetti America/Telecommunication	Tally 2
Flexible Disc Controller/Formatter	Products164	Line Printer
Western Digital146	CRT Display Terminals	Epson America172
MAGNETIC CORE MEMORIES	Ann Arbor Terminals 20	Thermal Printer Dataproducts120, 121
Core Memory Systems Ampex Memory Products125	Computer Peripheral156 Conrac131	Impact Printer
Dataram	Infoton169	Practical Automation165
MAGNETIC DISC AND DRUM UNITS	Motorola Semiconductor Products/	Chain Printer
See also Flexible Disc Units)	Microsystems128 Perkin-Elmer Data Systems/Data	Harris/Data Communications156
Disc Drives	Terminals51	Dot Matrix Printers
Control Data149	Teleray/Research159	C. Itoh Electronics155
ISS/Sperry Univac141	Data Communications Terminal	Digital Printer Anadex115
Disc Systems Alpha Data140	Micon Industries159	Alladex
Wangco/Perkin-Elmer Data Systems 95	Remote Control MUX Terminal LFE Control System Industries168	COMPUTERS AND
Disc Subsystems		COMPUTER SYSTEMS
Data General174	DISPLAY EQUIPMENT (See also Data Terminals and Graphic	AUTOMATIC TEST SYSTEMS
Storage Module Controller	Equipment)	Automatic Circuit Board Tester
Datum168	Gas Plasma Displays	Teradyne
MAGNETIC TAPE UNITS	Burroughs/Electronic Components113	Automatic Microprocessor Board Tester
Tape Transports	GRAPHIC EQUIPMENT	Fluke Trendar/John Fluke Mfg40, 41
Kennedy 1	Graphic Display Terminals	CONTROL PROCESSORS
Tape Drives Digi-Data91	Hewlett-Packard	Intelligent Remote Controller
Cartridge Tape Drive	Data Systems103	Mountain Hardware170
Qantex/North Atlantic Industries161	Color Graphic Display Terminal	MICROCOMPUTERS AND MICROPROCESSORS
Tape Controller Boards	Ramtek 15	Microcomputers
Aviv167 Western Peripherals168, 176	Graphic Display Systems	Astral Computer128 Computer Systems Unlimited126
Tape Systems	Lexidata179 Ramtek52, 53	Data General102
Wangco/Perkin-Elmer Data Systems 95	Light Pens	Digital Equipment118, 119
Miniaturized Tape Subsystem	Information Control167	Electronic Product Associates126 Fairchild Camera and Instrument/
Telex Computer Products174	INTERFACE EQUIPMENT:	Instruments and Controls126
Tape Recording System Dylon159	CONTROLLERS	General Automation100, 101
Cassette Recorders	Bus Interface Board	General Robotics168 Intelligent Systems22, 23
Raymond Engineering127	National Instruments174 Controller/Interface Board	Pacific Cyber/Metrix156
Techtran Industries157	Andromeda Systems122	Plessey Microsystems 21
Cartridge Recorder	Flexible Disc Interface	Microcomputer Software
Columbia Data Products162	Pacific Cyber/Metrix116	MVT Microcomputer Systems116
Magnetic Tape Test System Tau-Tron171	Storage Module Controller	Microprocessors
	Datum168	Intersil70, 71
ROM/RAM PROGRAMMERS AND SIMULATORS	Tape Controller Boards Aviv167	Motorola Semiconductor Products24, 25
Optimal Technology116	Western Peripherals168, 176	Microprocessor Development Systems
SEMICONDUCTOR MEMORIES	Instrument Controller	Advanced Micro Devices116 Tektronix124
Semiconductor Memory Systems	Interstate Electronics173	Zilog 55
Intel Memory Systems154, 155	Unibus Switches	Automatic Microprocessor Board Tester
Monolithic Systems80, 153	Datafusion155	Fluke Trendar/John Fluke Mfg40, 41
CCD Memory IC	KEYBOARD EQUIPMENT	Microprocessor Analyzer Millennium Systems124
Fairchild Semiconductor Products12, 13	Intelligent Keyboard Micro Switch/Honeywell152	Micromonitor
Shift Registers Advanced Micro Devices146	Alphanumeric Keyboards	RCA Solid State126
TRW LSI Products 72	Chomerics163	MINICOMPUTERS; SMALL- AND
16k p/ROM	Keyboard Encoder Board	MEDIUM-SCALE COMPUTERS
Signetics	Stacoswitch163	Computer Systems
4k RAMS EMM SEMI/Electronic Memories &	OTHER INPUT/OUTPUT EQUIPMENT	Modular Computer Systems145
Magnetics	Document Reader/Sorters Control Data173	OEM Medium-Scale Computer Digital Equipment34, 35, 36, 37
Intel148	Terminal Monitor	Minicomputers
RAM-I/O Chip National Semiconductor142	Computer Resources158	Data General102
Hational Commondator	PLOTTING EQUIPMENT	Digital Equipment173 Honeywell Information Systems117
INPUT/OUTPUT AND	Digital Plotter	Interdata/Perkin-Elmer Data
RELATED EQUIPMENT	Houston Instrument/Bausch &	Systems109
AUDIO RESPONSE EQUIPMENT	Lomb133	Sperry Univac 10
Voice Response Board	PRINTER/PLOTTERS	SIGNAL PROCESSORS
Vocal Interface/Federal Screw	Line Printer/Plotters	Programmable Signal Processor

SALES OFFICES

PAGE	PAGE
TIMESHARING/DISTRIBUTED PROCESSING COMPUTERS AND SYSTEMS	Intelligent Remote Controller
Distributed Processing System Systems Engineering Laboratories110, 111	Mountain Hardware170 Remote Control MUX Terminal
WORD PROCESSORS	LFE Control System Industries168 Tapeless Numerical Control Automation Unlimited
Flexible Disc Word Processor Tycom161	Status/Alarm Displays Puleo Electronics
DATA COMMUNICATIONS EQUIPMENT	S-D AND D-S CONVERTERS
COMMUNICATIONS INTERFACES Communication Interface Modules Dataprobe	S-D Converter North Atlantic Industries167
Asynchronous Serial Line Adapter MDB Systems	TEST AND MEASUREMENT EQUIPMENT; INSTRUMENTATION
COMMUNICATIONS MONITORS	COUNTERS; TIMERS Real-Time Clock
Data Communications Line Monitor Epicom166	Digital Interface Systems171
Data Communications Diagnostic Unit International Data Sciences165	Portable Tester
COMMUNICATIONS MULTIPLEXERS	Bendix107 Automatic Circuit Board Tester
Multiplexer Syntech161	Teradyne
Time Division Multiplexer Koor Systems168	Automatic Microprocessor Board Tester Fluke Trendar/John Fluke Mfg40, 41
Multichannel Multiplexers Preston Scientific	Logic State Analyzer Hewlett-PackardCover II
COMMUNICATIONS TERMINALS	Logic Analyzer Display Formatter BP Instruments171
Data Communications Terminal	Logic Probe
Micon Industries	Kurz-Kasch
Racal/Milgo158	Ostby and Barton168
DATA TRANSMISSION EQUIPMENT Communications Module	Memory Tester Micro Control151, 165
Process Computer Systems112	Magnetic Tape Test System Tau-Tron171
Communications Network System Digital Communications Associates159	Microprocessor Analyzer
Data Converter KMW Systems169	Millennium Systems124 Microprocessor Family Test System
MODEMS; DATA SETS	Adar Associates126
Data Modems	Micromonitor RCA Solid State126
Gandalf Data	OSCILLOSCOPES
Vadic160	Oscilloscope Adapter Switch Mid-South Instrument Services160
DATA ACQUISITION AND	OTHER TEST AND MEASUREMENT EQUIPMENT
CONTROL EQUIPMENT	16-Channel Digital Latch Tektronix165
A-D AND D-A CONVERTERS	Calibrators
A-D Converter Module Analogic	John Fluke Mfg152 Portable Programmable Test Set
D-A Converters	Ballantine Laboratories160
ILC Data Device147 Signetics148	Interconnect Test Systems DIT-MCO International163
Zeltex162	SIGNAL AND CODE CONVERTERS
ANGLE AND POSITION ENCODERS Linear Encoder	Data Converter KMW Systems169
Teledyne Gurley166	KWW Systems
DATA ACQUISITION SYSTEMS	OTHER PRODUCTS; SERVICES
Data Acquisition System Tyco/Instrument167	EDUCATION
DATA TRANSFER AND INTERFACE EQUIPMENT	Seminars Integrated Computer Systems105
Analog I/O Boards Burr-Brown114	EQUIPMENT BUYING, SELLING, AND LEASING
I/O Expansion Card	Test Equipment Rentals ElectroRent/Telecor129
National Semiconductor126	OTHER NONDIGITAL PRODUCTS
Process Computer Systems112	Security System Motorola Government Electronics174
Data Transfer System Computer Data Systems164	PRODUCTION AND ASSEMBLY EQUIPMENT
Bus Interface Board National Instruments174	DIP Insertion Tool OK Machine & Tool146
Instrument Controller Interstate Electronics	SOFTWARE
MONITORING AND CONTROL EQUIPMENT	Software 5
Control System Modules	Microcomputer Software
Harris/Controls160	MVT Microcomputer Systems116

NEW ENGLAND. **NEW YORK STATE**

> Lindsay H. Caldwell 129 Cedar Hill Road East Dennis, MA 02641 phone: (617) 385-2533

MIDDLE AND SOUTH ATLANTIC STATES

Hajar Assoc., Inc. Emile H. Hajar Paul Hajar Silvio Mandino 521 5th Avenue New York, NY 10017 phone: (212) 682-5844

MIDWESTERN STATES

Hajar Assoc., Inc. Emile H. Hajar Paul Hajar Silvio Mandino 664 North Michigan Avenue **Suite 1010** Chicago, IL 60611 phone: (312) 337-8008

SOUTHWESTERN STATES

Lindsay H. Caldwell 129 Cedar Hill Road East Dennis, MA 02641 phone: (617) 385-2533

WEST COAST STATES

Buckley Boris Assoc. Terry Buckley-Tom Boris 912 South Barrington Avenue Suite 202 Los Angeles, CA 90049 phone: (213) 826-4621

ADVERTISERS' INDEX

ACDC Electronics Alpha Data, Inc. AMP, Inc. Ampex Memory Products Amphenol North American Div.,	140 19 125
Bunker-Ramo Corp. Anadex Corp. Analogic Corp. Ann Arbor Terminals	115
Belden Corp. Bendix Corp., Test Systems Div.	
Burroughs Corp., Electronic Computer Div. Bussco Engineering, Inc.	113
C & K Components	164
Control Data Corp.	131
Data General Corp. Dataproducts I Dataram Corp. Data Systems Design, Inc. Diablo Systems, Inc., a Xerox Co.	20, 121 69 143
Digi-Data Corp. Digital Equipment Corp. 34, 35, 36, 37, 1	91
EMM SEMI, Inc., a sub. of Electronic Memories & Magnetics Corp ElectroRent, a Telecor Co. Epson America, Inc.	129
Facit-Addo, Inc. Fairchild Semiconductor Corp., Operations Div. Fluke Trendar, a sub. of John Fluke Mfg. Co., Inc. Forth, Inc.	12, 13
General Automation, Inc., Standard Products Div. General Robotics Corp. Gould, Inc., Electronic Components Div. Grayhill, Inc. GTE Sylvania, Connector Products Operation	168 26 79
Hewlett-Packard Co	117
iCOM Microperipherals, Microsystems Div. Information Control Corp. Integrated Computer Systems Intel Corp. Intel Memory Systems Intelligent Systems Corp. Interdata, Inc., a unit of Perkin-Elmer Data Systems Intersil Corp. ISS/Sperry Univac	167 105 116, 17 154, 155 22, 23

19 4 7 1

Kennedy Co	162
	1/0
	162
Lear Siegler, Inc.	
Lexidata Corp.	1/7
MDB Systems, Inc.	147
Micro Control Co.	
Micro Switch.	
a div. of HoneywellCover	111
Modular Computer Systems, Inc.	145
Monolithic Systems Corp. 80,	153
Motorola, Inc.	
Government Electronics Div.	174
Semiconductor Products Div	
North American Philips Controls Corp.	164
[12] [12] [12] [13] [14] [15] [15] [15] [15] [15] [15] [15] [15	
OK Machine & Tool Corp.	146
Pacific Cyber/Metrix	154
Perkin-Elmer Data Systems,	100
Terminals Div.	EI
	21
Powercube Corp.	
Power/Mate Corp.	
Practical Automation, Inc.	
Printronix, Inc.	
Frintronix, Inc.	123
Qantex,	
Div. of North Atlantic Industries	161
Ramtek Corp	53
Raymond Engineering, Inc.	127
Possarch Inc	
(See Teleray)	159
Robinson Nugent, Inc44,	
C A :-!	
Sanders Associates,	100
Military Data Systems Div.	
Shugart Associates, Inc	135
Signetics Corp.,	
Bipolar Memory Div.	5, 9
Sperry Univac	10
Standard Engineering Corp.	100
Systems Engineering Laboratories, Inc	111
Tally Corp.	2
	157
Teleray,	
Div. of Research, Inc.	159
Teletype Corp.	7
Teradyne, Inc.	31
TEXAS INSTRUMENTS INCORPORATED,	0.1
Digital Systems Div.	47
TRW LSI Products	72
Vemaline Products,	
a div. of Ostby and Barton	168
Wanges Inc	
Wangco, Inc.,	95
a unit of Perkin-Elmer Data Systems Warner Electric Brake & Clutch Co	
Western Peripherals, Inc.	1/0
Xebec Corp. 88	, 89
7:1	
Zilog, Inc.	55