
INSIDE TRACK with CENTELLAX's JULIO PERDOMO p32



WIRELESS DEVICES AID MEDICAL COMMUNICATIONS p38



MODULAR INSTRUMENTS TACKLE FULL-SIZED MEASUREMENTS p88




MicroWaves&RF

JULY 2012 TRUSTED ENGINEERING RESOURCE FOR 50 YEARS www.MWRF.com

INDUSTRIAL/MEDICAL APPLICATIONS ISSUE

Microwave VNAs Recruit Receiver for Noise-Figure Testing to 125 GHz




Digi-Key CORPORATION
NEW PRODUCTS ADDED DAILY
DIGIKEY.COM/NEW

A PENTON PUBLICATION Periodicals Postage Paid • USPS 100 Approved Poly

NOW AVAILABLE FOR PURCHASE ONLINE

macomtech.com

POWER PALLETS & TRANSISTOR



INTEGRATED CIRCUITS



ACTIVE COMPONENTS




QUOTE


SAMPLES

PURCHASE


SWITCH LIMITERS, SWITCHES, DIODES



PASSIVE COMPONENTS



MULTI-CHIP MODULES



You can shop our broad portfolio of products at
www.macomtech.com

MACOM Technology Solutions
THE FIRST NAME IN MICROWAVE®

The Ins And Outs of MITEQ


Surface Mount

- Mixers
- Amplifiers
- PLL Oscillators



Coaxial

- Standard
- Blind Mate
- 90 Degree




Standard and Custom Waveguide

- Mixers
- Amplifiers
- Converters



Optical

- Broadband RF Fiber Optic
- Amplifiers with FO outputs



Drop in/open Substrate

- Mixers
- Amplifiers



PC Mount

- Flat Pack Logs
- Hybrid Couplers



ISO 9001 Registered · ANAB Accredited · AS9100 Registered

For additional information or technical support,
please contact our Sales Department at (631) 439-9220 or e-mail components@miteq.com

Let MITEQ help you process your signals!

MITEQ


100 Davids Drive, Hauppauge, NY 11788 USA
631-436-7400 FAX: 631-436-7430
www.miteq.com

BLUETOOTH® RF MODULES
www.panasonic.com/Bluetooth

Panasonic offers a new Bluetooth RF Module product line that makes connectivity between mobile devices easily implemented, creating a seamless data chain from sensors to the Web.

New Series featuring:

Bluetooth® Classic
Bluetooth Dual Mode
Bluetooth ANT™
Bluetooth Low Energy



New! PAN1720 Series Bluetooth Low Energy

A Complete Bluetooth 4.0 Low Energy Solution

The **New PAN1720 Series** is a cost-effective, low-power, true system-on-chip (SoC) for Bluetooth Low Energy applications. The module includes an eight channel, twelve bit analog-to-digital converter, 19 GPIOs plus battery and temperature sensors.

Bluetooth® SMART



For more on Panasonic RF Modules go to
www.panasonic.com/RFmodules

POWERED BY Panasonic Electronic Components

Providing cutting edge technology to give your product the **performance**, **reliability** and **quality** that today's consumers demand.

- Capacitors
- Resistors
- Inductors and Filters
- Circuit Protection
- Electromechanical
- RF Modules
- Semiconductors

Make Your Product Powered by Panasonic

Visit us online at **www.panasonic.com/industrial/electronic-components**
email **industrial@us.panasonic.com**
or call **1-800-344-2112**

engineering a better world




Panasonic
ideas for life

DON'T LET THE SAME OLD SUPPLIER SOLUTION RAIN ON YOUR DEVELOPMENT PARADE.

WE'VE GOT YOU COVERED!

narda | Defense Technology Solutions

High dynamic range front-end assembly



L3

With today's emphasis on superior performance in a smaller, lighter, more cost-effective package, why settle for yesterday's chip and wire solutions?

Narda Defense Technology Solutions has pioneered the development of high-performance, densely packaged integrated microwave assemblies and subsystems in footprints previously unachievable. By leveraging commonly available multi-layer board materials with unique interconnection techniques, and incorporating DSP and sophisticated monitor and control functions, our solutions are currently redefining "State of the Art." For more information, please visit our website at **www.nardamicrowave.com/defense**, or call us at **(631) 231-1700**.

- Module and Subsystem Solutions to 40 GHz
- Frequency Converters, LNAs, BUCs & SSPAs
- EW, Radar, Radio and SATCOM Applications
- Pin Diode Switch Products


narda | Defense Technology Solutions


AWR
A National Instruments Company™
Achieve hyper speed simulations on complex multi-tone circuits.
Stop waiting and waiting and waiting for your complex multi-tone designs to simulate. AWR users don't wait. They simulate at turbo speeds thanks to multi-rate harmonic balance (MRHB) technology. With simulation times that are typically 10x faster, designs with 2, 3, 4 or even more tones converge quickly— and nail the performance, too! Fewer mouse clicks and novel MRHB technology mean shorter process times, right-the-first-time designs, and less stress for you. Don't you deserve that? Grab a test copy at awrcorp.com/MWO.
Stop waiting and start designing™
MICROWAVE OFFICE™

JULY | 2012
Volume 51, Issue 7

MicroWaves&RF


CONTENTS




20



38



20


50




59


64


88


91

COVER STORY



84 VNAs Measure Noise From 70 kHz To 125 GHz

Two new options arm an established line of microwave vector network analyzers for making accurate noise figure measurements, along with the capability to make those measurements up to 125 GHz.

NEWS & COLUMNS

9 Web Table Of Contents
13 Editorial
19 Feedback
20 News
26 People
28 Company News
32 Inside Track with Centellax's Julio Perdomo
34 R&D Roundup
36 Microwaves In Europe
82 Application Notes
93 New Products
95 Advertiser's Index



Penton
Design Engineering & Sourcing Group

INDUSTRY TRENDS AND ANALYSIS

38 | Medical Applications Seek Wireless Solutions
The healthcare industry is hoping to adopt wireless technology for patient monitoring on a large scale.

42 | RF ESSENTIALS
Transceivers Trim Power In WPANs
These highly integrated circuits and modules are designed to provide short-range wireless networking functions.

46 | INDUSTRY INSIGHT
Assemblies Combine Multiple Components
Integrated microwave assemblies allow for the combining of multiple component functions in a single compact package.

DESIGN FEATURES

51 | Mixer Translates Multiple Standards
This broadband frequency-upconversion mixer is suitable for multiple-standard wireless applications from 1.0 to 10.6 GHz.

59 | Create UWB Filters With Coaxial Cables
With the aid of a commercial EM simulator, sliced coaxial cables can be used to design a high-performance bandpass filter.

64 | Transmitter/Receiver Manages MIMO
This low-cost two-way transmitter and receiver design achieves high-data-rate transmissions at 8 GHz.

70 | Tiny Spiral Spans 1.4 To 10.0 GHz
This miniature arm-width-tapered ATARSA features tapered antenna arms, enabling significant size reduction.

76 | Compact Monopole Sleeve Antenna Reaches 11.8 GHz
A sleeve and ladder-shaped ground-plane structures help to widen the impedance bandwidth of a planar monopole antenna.

PRODUCT TECHNOLOGY


88 | PRODUCT TRENDS
Making Microwave Measurements Modular
An increasing number of measurement functions are now available in modular form, allowing for smaller system sizes.

91 | TO-8 YIGs Tune 3 To 13 GHz
These compact microwave oscillators can tune across customer-specified bands with generous output power.


92 | Envelope Tracking Makes Phones Smarter
Using envelope-tracking techniques, the efficiency of the power amplifiers found in cellular telephones can be improved.

Rosenberger® SMA+™ Cables


THE PLUS MEANS 36GHz PERFORMANCE AT A FRACTION OF THE COST.



Mated with SMA



Mated with 3.5mm



Mated with 2.92mm

Features and Benefits

- High-performance, high-frequency test cables built for day-to-day applications
- Available in Rosenberger RTK-Flex 405 (flexible) cable or RTK-FS-085 (conformable) cable. Or, special order in 085 semi-rigid cable built to your specifications
- Excellent performance over a broad frequency range (see charts above)
- Standard SMA interface — intermatable with SMA, 3.5mm and 2.92mm (K*) connectors
- Gold-plated center contacts, passivated stainless steel coupling nuts and a proprietary dielectric
- Unique over-molded strain relief is exceptionally rugged and durable
- Temperature range: -55°C to +125°C
- Minimum return loss: -18dB when mated with SMA, 3.5mm or 2.92mm (K*) connectors

* K Connector® is a registered trademark of Anritsu Corporation



SMA+ Female Connector

Rosenberger®

RFMW

RoHS 202/95/EC

©2011, Rosenberger NA

	Part # RoHS Compliant	OAL in FT.	IL (dB)	Ret Ls (dB)
SMA+m-SMA+m RTK-Flex 405	L71-404-305	1.0	1.4	25
	L71-404-457	1.5	1.9	25
	L71-404-610	2.0	2.4	25
	L71-404-915	3.0	3.5	25
	L71-404-1220	4.0	4.5	25
	L71-404-1830	6.0	5.6	25

To purchase cables please contact:
RFMW, LTD. 90 Great Oaks Blvd.
Ste. 107, San Jose, CA 95119
Ph: 877-367-7369 (North America)
Ph: 408-414-1450 (all other areas)
Fax: 408-414-1461 • sales@rfmw.com • www.rfmw.com
Offices located thoughout North America, UK and Israel.
Se habla Espanol: 954-476-8630


WIDEBAND
TRANSFORMERS & COUPLERS

Transformers			
Model Number	**Frequency (MHz)**	**Impedance Ratio**	**Schematic**
TM4-0	0.2 - 350	4:1	
TM1-0	0.3 - 1000	1:1	
TM1-1	0.4 - 500	1:1	
TM1.5-2	0.5 - 550	1.5:1	
TM2-1	1 - 600	2:1	
TM1-6	5 - 3000	1:1	
TM2-GT	5 - 1500	2:1	
TM4-GT	5 - 1000	4:1	
TM8-GT	5 - 1000	8:1	
TM4-1	10 - 1000	1:4	
TM4-4	10 - 2500	1:4	
TM1-2	20 - 1200	1:1	
TM1-9	100 - 5000	1:1	
TM1-8	800 - 4000	1:1	

Couplers			
Model Number	**Frequency (MHz)**	**Coupling**	**Coupling Flatness**
GC6-2	1 - 700	6 dB ±0.5 dB (Nom.)	±1.0 dB
GC6-1	10 - 500	6 dB ±0.5 dB (Nom.)	±1.0 dB

Features

- > Low Cost
- > Wide Bandwidth
- > Good Amplitude / Phase Unbalance
- > Rugged Welded Construction
- > RoHS Compliant
- > Patented REL-PRO® Technology



RoHS COMPLIANT

SYNERGY®
MICROWAVE CORPORATION


Phone: (973) 881-8800 | Fax: (973) 881-8361
E-mail: sales@synergymwave.com
Web: WWW.SYNERGYMWAVE.COM
Mail: 201 McLean Boulevard, Paterson, NJ 07504


RF Amplifiers and Sub-Assemblies for Every Application

Delivery from Stock to 2 Weeks ARO from the catalog or built to your specifications!


- Competitive Pricing & Fast Delivery
- Military Reliability & Qualification
- Various Options: Temperature Compensation, Input Limiter Protection, Detectors/TTL & More
- Unconditionally Stable (100% tested)

ISO 9001:2000 and AS9100B CERTIFIED











OCTAVE BAND LOW NOISE AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1-dB	3rd Order ICP	VSWR
CA01-2110	0.5-1.0	28	1.0 MAX, 0.7 TYP	+10 MIN	+20 dBm	2.0:1
CA12-2110	1.0-2.0	30	1.0 MAX, 0.7 TYP	+10 MIN	+20 dBm	2.0:1
CA24-2111	2.0-4.0	29	1.1 MAX, 0.95 TYP	+10 MIN	+20 dBm	2.0:1
CA48-2111	4.0-8.0	29	1.3 MAX, 1.0 TYP	+10 MIN	+20 dBm	2.0:1
CA812-3111	8.0-12.0	27	1.6 MAX, 1.4 TYP	+10 MIN	+20 dBm	2.0:1
CA1218-4111	12.0-18.0	25	1.9 MAX, 1.7 TYP	+10 MIN	+20 dBm	2.0:1
CA1826-2110	18.0-26.5	32	3.0 MAX, 2.5 TYP	+10 MIN	+20 dBm	2.0:1

NARROW BAND LOW NOISE AND MEDIUM POWER AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1-dB	3rd Order ICP	VSWR
CA01-2111	0.4 - 0.5	28	0.6 MAX, 0.4 TYP	+10 MIN	+20 dBm	2.0:1
CA01-2113	0.8 - 1.0	28	0.6 MAX, 0.4 TYP	+10 MIN	+20 dBm	2.0:1
CA12-3117	1.2 - 1.6	25	0.6 MAX, 0.4 TYP	+10 MIN	+20 dBm	2.0:1
CA23-3111	2.2 - 2.4	30	0.6 MAX, 0.45 TYP	+10 MIN	+20 dBm	2.0:1
CA23-3116	2.7 - 2.9	29	0.7 MAX, 0.5 TYP	+10 MIN	+20 dBm	2.0:1
CA34-2110	3.7 - 4.2	28	1.0 MAX, 0.5 TYP	+10 MIN	+20 dBm	2.0:1
CA56-3110	5.4 - 5.9	40	1.0 MAX, 0.5 TYP	+10 MIN	+20 dBm	2.0:1
CA78-4110	7.25 - 7.75	32	1.2 MAX, 1.0 TYP	+10 MIN	+20 dBm	2.0:1
CA910-3110	9.0 - 10.6	25	1.4 MAX, 1.2 TYP	+10 MIN	+20 dBm	2.0:1
CA1315-3110	13.75 - 15.4	25	1.6 MAX, 1.4 TYP	+10 MIN	+20 dBm	2.0:1
CA12-3114	1.35 - 1.85	30	4.0 MAX, 3.0 TYP	+33 MIN	+41 dBm	2.0:1
CA34-6116	3.1 - 3.5	40	4.5 MAX, 3.5 TYP	+35 MIN	+43 dBm	2.0:1
CA56-5114	5.9 - 6.4	30	5.0 MAX, 4.0 TYP	+30 MIN	+40 dBm	2.0:1
CA812-6115	8.0 - 12.0	30	4.5 MAX, 3.5 TYP	+30 MIN	+40 dBm	2.0:1
CA812-6116	8.0 - 12.0	30	5.0 MAX, 4.0 TYP	+33 MIN	+41 dBm	2.0:1
CA1213-7110	12.2 - 13.25	28	6.0 MAX, 5.5 TYP	+33 MIN	+42 dBm	2.0:1
CA1415-7110	14.0 - 15.0	30	5.0 MAX, 4.0 TYP	+30 MIN	+40 dBm	2.0:1
CA1722-4110	17.0 - 22.0	25	3.5 MAX, 2.8 TYP	+21 MIN	+31 dBm	2.0:1

ULTRA-BROADBAND & MULTI-OCTAVE BAND AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1-dB	3rd Order ICP	VSWR
CA0102-3111	0.1-2.0	28	1.6 Max, 1.2 TYP	+10 MIN	+20 dBm	2.0:1
CA0106-3111	0.1-6.0	28	1.9 Max, 1.5 TYP	+10 MIN	+20 dBm	2.0:1
CA0108-3110	0.1-8.0	26	2.2 Max, 1.8 TYP	+10 MIN	+20 dBm	2.0:1
CA0108-4112	0.1-8.0	32	3.0 MAX, 1.8 TYP	+22 MIN	+32 dBm	2.0:1
CA02-3112	0.5-2.0	36	4.5 MAX, 2.5 TYP	+30 MIN	+40 dBm	2.0:1
CA26-3110	2.0-6.0	26	2.0 MAX, 1.5 TYP	+10 MIN	+20 dBm	2.0:1
CA26-4114	2.0-6.0	22	5.0 MAX, 3.5 TYP	+30 MIN	+40 dBm	2.0:1
CA618-4112	6.0-18.0	25	5.0 MAX, 3.5 TYP	+23 MIN	+33 dBm	2.0:1
CA618-6114	6.0-18.0	35	5.0 MAX, 3.5 TYP	+30 MIN	+40 dBm	2.0:1
CA218-4116	2.0-18.0	30	3.5 MAX, 2.8 TYP	+10 MIN	+20 dBm	2.0:1
CA218-4110	2.0-18.0	30	5.0 MAX, 3.5 TYP	+20 MIN	+30 dBm	2.0:1
CA218-4112	2.0-18.0	29	5.0 MAX, 3.5 TYP	+24 MIN	+34 dBm	2.0:1

LIMITING AMPLIFIERS

Model No.	Freq (GHz)	Input Dynamic Range	Output Power Range Psat	Power Flatness dB	VSWR
CLA24-4001	2.0 - 4.0	-28 to +10 dBm	+7 to +11 dBm	+/- 1.5 MAX	2.0:1
CLA26-8001	2.0 - 6.0	-50 to +20 dBm	+14 to +18 dBm	+/- 1.5 MAX	2.0:1
CLA712-5001	7.0 - 12.4	-21 to +10 dBm	+14 to +19 dBm	+/- 1.5 MAX	2.0:1
CLA618-1201	6.0 - 18.0	-50 to +20 dBm	+14 to +19 dBm	+/- 1.5 MAX	2.0:1

AMPLIFIERS WITH INTEGRATED GAIN ATTENUATION

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1-dB	Gain Attenuation Range	VSWR
CA001-2511A	0.025-0.150	21	5.0 MAX, 3.5 TYP	+12 MIN	30 dB MIN	2.0:1
CA05-3110A	0.5-5.5	23	2.5 MAX, 1.5 TYP	+18 MIN	20 dB MIN	2.0:1
CA56-3110A	5.85-6.425	28	2.5 MAX, 1.5 TYP	+16 MIN	22 dB MIN	1.8:1
CA612-4110A	6.0-12.0	24	2.5 MAX, 1.5 TYP	+12 MIN	15 dB MIN	1.9:1
CA1315-4110A	13.75-15.4	25	2.2 MAX, 1.6 TYP	+16 MIN	20 dB MIN	1.8:1
CA1518-4110A	15.0-18.0	30	3.0 MAX, 2.0 TYP	+18 MIN	20 dB MIN	1.85:1

LOW FREQUENCY AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure dB	Power-out @ P1-dB	3rd Order ICP	VSWR
CA001-2110	0.01-0.10	18	4.0 MAX, 2.2 TYP	+10 MIN	+20 dBm	2.0:1
CA001-2211	0.04-0.15	24	3.5 MAX, 2.2 TYP	+13 MIN	+23 dBm	2.0:1
CA001-2215	0.04-0.15	23	4.0 MAX, 2.2 TYP	+23 MIN	+33 dBm	2.0:1
CA001-3113	0.01-1.0	28	4.0 MAX, 2.8 TYP	+17 MIN	+27 dBm	2.0:1
CA002-3114	0.01-2.0	27	4.0 MAX, 2.8 TYP	+20 MIN	+30 dBm	2.0:1
CA003-3116	0.01-3.0	18	4.0 MAX, 2.8 TYP	+25 MIN	+35 dBm	2.0:1
CA004-3112	0.01-4.0	32	4.0 MAX, 2.8 TYP	+15 MIN	+25 dBm	2.0:1

CIAO Wireless can easily modify any of its standard models to meet your "exact" requirements at the Catalog Pricing.

Visit our web site at www.ciaowireless.com for our complete product offering.


Ciao Wireless, Inc. 4000 Via Pescador, Camarillo, CA 93012

Tel (805) 389-3224 Fax (805) 389-3629 sales@ciaowireless.com

MicroWaves&RF ON THE WEB

MWRF.com

Techniques for Making Measurements of Noise-Like Signals with a SPECTRUM ANALYZER



MANY OF TODAY'S COMMUNICATION FORMATS, such as W-CDMA, cdma2000®, and WLAN, produce signals that are noise-like in nature. Accurately measuring these types of signals requires tools and setups that are different than traditionally used for continuous-wave (CW) signals. In this web-exclusive article, Agilent Technologies' Bob Nelson examines the best approach for doing so.

To read the article in its entirety, *visit www.mwrf.com.*


REVISIT IMS2012

The 2012 installment of the RF/microwave industry's flagship event, the *International Microwave Symposium*, has come and gone. Luckily for you, it needn't live on just in memory. Visit *www.mwrf.com* to check out our show coverage, as well as www.engineering tv.com to view exclusive videos from the show floor.

IMS2012 MONTRÉAL

engineering tv

NEWS UPDATES Sent To Your Desktop


LATEST ARTICLES | TOP 20 ARTICLES | ONLINE NEWS

Free Software Still A Bargain

No question, software can be expensive—but that is never an excuse not to pay for it. After all, someone (often a team) put a great deal of effort into writing that code. But when free software comes along, the "thrifty" among us usually take notice. ...

Free SPICE Software Tackles Linear Circuits

Analog Devices and National Instruments have announced the availability of an "Analog Devices" version of National's Multisim™ SPICE-based software for evaluating components by means of analyzing linear circuits. The software works with 550 models ma ...

Don't believe everything you read, unless it's in the latest issue of *Microwaves & RF UPDATE.* The industry's longest-running weekly e-mail newsletter, it combines insightful commentary with the latest product and industry business news. It is sent directly to your computer desktop each week, and often contains the little things that engineers love, such as links to free white papers and even design software. If you're not already reading it, subscriptions are free, and available from the *Microwaves & RF* website at www.mwrf.com.



MWRF.com has archives of print and online articles dating back to October 2002. Visit MWRF.com today and click the "Back Issues" link. And while you're taking a look around the site, click on "Product Directory" to gain access to our complete directory of products and suppliers.

SHARE YOUR THOUGHTS with QUICK POLLS

Quick polls allow you to regularly share your opinion on a wide range of topics.

LATEST POLL RESULT:

Will traditional radio architectures eventually be replaced by software-defined radios (SDRs) and cognitive radios?


73% YES
14% NO
14% DON'T KNOW

NEW POLL QUESTION:

Can the microwave/wireless industry contribute technology useful to the medical/healthcare industries?

YES NO
DOESN'T MATTER

Why Coilcraft wirewound chip inductors are your #1 choice



Higher Q Compared to non-wirewounds, our chip inductors usually have Qs that are 50 to 150% higher.


Lower DCR Put up to 3 times more current through our chip inductors thanks to their low DC resistance.

Higher SRF The solenoid winding of our inductors gives them a much higher SRF than multilayer parts.

Tighter tolerance Precision manufacturing lets us consistently make parts with ±2% inductance tolerance. Many popular values also come in ±1%.

Better support With our engineer-friendly web site, interactive design tools and generous free samples, Coilcraft is just plain easier to do business with.

Visit **www.coilcraft.com** for information on all our high performance wirewound inductors.




coilcraftdirect.com
No min order. Next day delivery.

Coilcraft®

WWW.COILCRAFT.COM

PIN DIODE SWITCHES



FEATURES:

- Multioctave bands 0.2 to 18 GHz
- Reflective or Absorptive
- Current or TTL control
- Low insertion loss
- High isolation

Frequency Range (GHz)	Model Number	Insertion Loss (dB, Max.)	Isolation (dB, Min.)	VSWR (Max.)	Rise/Fall Time (ns, Typ.)	On/Off Time (ns, Typ.)	On/Off Time (ns, Max.)	DC Power Positive/Negative (mA, Max.)
SPST								
0.2 – 2	SW1-002020RN1NF	1.7	70	1.6:1	10/10	20	35	35/70
2 – 8	SW1-020080RN1NF	2	80	1.7:1	10/10	20	35	35/70
4 – 12	SW1-040120RN1NF	2.2	80	1.7:1	10/10	20	35	35/70
2 – 18	SW1-020180RN1NF	3	80	2:1	10/10	20	35	35/70
1 – 18	SW1-010180RN1NF	3	70	2:1	10/10	20	35	35/70
SP2T								
0.2 – 2	SW2-002020RN1NF	1.5	70	1.6:1	10/10	20	35	60/60
2 – 8	SW2-020080RN1NF	1.8	80	1.7:1	10/10	20	35	60/60
4 – 12	SW2-040120RN1NF	2.2	80	1.7:1	10/10	20	35	60/60
2 – 18	SW2-020180RN1NF	2.8	80	2:1	10/10	20	35	60/60
1 – 18	SW2-010180RN1NF	3	70	2:1	10/10	20	35	60/60
SP3T								
0.2 – 2	SW3-002020RN1NF	1.6	70	1.6:1	20/20	150	180	85/85
2 – 8	SW3-020080RN1NF	1.9	80	1.7:1	20/20	150	180	85/85
4 – 12	SW3-040120RN1NF	2.4	90	1.7:1	20/20	150	180	85/85
2 – 18	SW3-020180RN1NF	3	80	2:1	20/20	150	180	85/85
1 – 18	SW3-010180RN1NF	3.1	70	2:1	20/20	150	180	85/85

Note: The above models are all reflective switches. Absorptive models are also available, please contact MITEQ.

ISO 9001 Registered · ANAB Accredited · AS9100 Registered · RoHS compliant · 3 YEAR WARRANTY

For additional information or technical support, please contact our Sales Department at (631) 439-9220 or e-mail components@miteq.com


MITEQ®

100 Davids Drive, Hauppauge, NY 11788
(631) 436-7400 FAX: (631) 436-7430
www.miteq.com

Now!

MULTIPLY UP TO 20 GHz

x4 x12 x3 x4 x3 x3 x2 x2 x3



Frequency Multipliers from $5.95 qty. 10-49

For your leading-edge synthesizers, local oscillators, and Satellite up/down converters, Mini-Circuits offers a large selection of ***broadband doublers, triplers, quadruplers, and x12 frequency multipliers.***

Now generate output frequencies from 100 kHz to 20 GHz with excellent suppression of fundamental frequency and undesired harmonics, as well as spurious. All featuring low conversion loss and designed into a wide array of, off-the-shelf, rugged coaxial, and surface mount packages to meet your requirements.

Visit our website to choose and view comprehensive performance curves, data sheets, pcb layouts, and environmental specifications. And you can even order direct from our web store and have a unit in your hands as early as tomorrow! ***Mini-Circuits...we're redefining what VALUE is all about!***

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

YoniM2® ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

U.S. Patents 7739260, 7761442

IF/RF MICROWAVE COMPONENTS



From the Editor

Grappling With Old-Cell-Phone Guilt

A FEW DAYS ago, my six-year-old daughter was rifling through our junk drawer. She was delighted to discover a number of old cell phones, which she promptly used to "call" her ex-boyfriend—supposedly a boy named Jake. (I guess when you're six, it's okay for an ex to come before an actual boyfriend.) While it was fun watching her play, it reminded me—guiltily—that my family still had not recycled our old cell phones. From a personal to a global level, it seems that the process of recycling cellular phones—and electronics in general—could stand a lot of improvement.

To me, one should be able to get rid of an old cell phone much the way one disposes of an old mattress: Buy a new one and the retailer offers to take the old one away. Instead, it often falls to the individual consumers to hunt down someone at their local recycling centers, who will hopefully advise them on where they can bring their old cell phones. Alternatively, one could look for a solution online or find someone who is collecting used cell phones for a cause (although this raises security concerns if any of your information is still on the phone).

Even if I find a way to recycle these old phones, it's likely that only a few parts will be plucked out while the rest is simply discarded. e-Cycle (www.e-Cycle.com) notes that only a small percentage of e-waste is sent to recyclers (as little as 11% to 14% in the US). The remainder is often dumped or burned. The US Environmental Protection Agency estimates that 70% to 80% of supposedly reputable electronics-recycling companies in the US are directly or indirectly (through downstream vendors) shipping e-waste into "toxic wastelands" in developing countries.

e-Cycle recommends that organizations and businesses work with a recycler that is e-Stewards-certified (simply visit http://e-stewards.org/find-a-recycler/). e-Stewards is a globally recognized electronics-recycling certification. Among other lofty goals, it prohibits the landfilling and incineration of e-waste.

In addition to the proper disposal of electronic waste, many manufacturers are trying to design products that are "greener." This month, for example, AT&T is launching a fourth-generation (4G) Long-Term Evolution (LTE) smartphone with "sustainable" features. The Samsung Galaxy Exhilarate boasts a rear casing made from 80% recycled (post-consumer waste) material and a low-load, energy-efficient charger. It also is the first 4G LTE smartphone to receive platinum certification from UL Environment, the environment-minded business unit of Underwriters Laboratories (UL).

"Green" requirements can complicate the challenge of juggling size, performance, power, and cost tradeoffs. The Restriction of Hazardous Substances (RoHS) directive, which was passed in 2003, will probably end up being the first of many such "green" mandates. Despite the resulting design pressures, the upshot will be products that are more easily dismantled, recycled, and even reused. After I recycle our old cell phones, I may even go about recycling some other stuff in that junk drawer. Judging by the amount of rubber bands, I could make a decent-sized rubber-band ball for the kids. MWRF

Nancy K. Friedrich

Editor-In-Chief

DETECTORS FOR VERY LOW SIGNALS

Direct Measurement of Microwave Signals at -80 dBm or lower over 1 to 40 GHz



MODEL	FREQ RANGE (GHz)	MIN VOLTAGE SENSITIVITY K (mV/µW)	TYP TSS (dBm)
DTA1-1860A	1-18	10	-60
DTA1-1870A		100	-70
DTA1-1880A		1000	-80
DTA182660A	18-26	10	-60
DTA182670A		100	-70
DTA182680A		1000	-80
DTA264060A	26-40	10	-60
DTA264070A		100	-70
DTA264080A		1000	-80
DTA184060A	18-40	10	-60
DTA184070A		100	-70
DTA184080A		1000	-80

- *> Octave Band or Wide Band*
- *> Options for TSS to -60 dBm, -70 dBm, -80 dBm*
- *> Very High Sensitivity*
- *> Stable and Quiet Low 1/f Noise Operation*
- *> Extremely Fast Pulse Response (1 nsec rise time typical)*
- *> Matched Input for Low VSWR*
- *> Flat Frequency Response*
- *> Hermetically sealed package*
- *> Removable connectors*


Narrow Band models are also available


Other Products: Amplifiers, Comb Generators, Limiters, Switches, Impulse Generators, Integrated Subsystems

Please call for Detailed Brochures

Herotek

155 Baytech Dr. San Jose, CA. 95134
PH: 408-941-8399 . FAX: 408-941-8388
E-Mail: info@herotek.com
Web Site: http.//www.herotek.com
Visa/MasterCard Accepted





POWER SPLITTERS/ COMBINERS

NOW! from **2 kHz to 18 GHz** as low as **79¢**

The Industry's Largest Selection includes THOUSANDS of models, from 2 kHz to 18 GHz, at up to 300 watts power, and in coaxial, flat-pack, and surface-mount housings for 50 and 75 Ω systems.

From 2-way through 48-way designs, with 0°, 90°, or 180° phase configurations, Mini-Circuits power splitters/combiners offer outstanding performance for insertion loss, isolation, and VSWR. Decades of experience with multiple technologies make it all possible, from core & wire, microstrip, and stripline, to semiconductors and LTCC ceramics.

Get easy-to-find, detailed data and performance curves, S-parameters, outline drawings, PCB layouts, and everything else you need to make a decision quickly, at minicircuits.com. Just enter your requirements, and our patented search engine, Yoni2, searches *actual test data* to find the models that meet your needs.

All Mini-Circuits catalog models are in stock, continuously replenished, and backed by our 1-year guarantee. We even list *current stock quantities and real-time availability*, as well as pricing, to help our customers plan ahead and make quick decisions. So why wait? Take a look at minicircuits.com today!

RoHS Compliant
Product availability is listed on our website.

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100


P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

Yoni2® U.S. Patents 7739260, 7761442 ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

448 rev J


TECDIA



THIN FILM CERAMIC TECHNOLOGY

Science, Engineering, Tradition spawn today's solutions and tomorrow's innovation for Micro & Light waves.

Single Layer Capacitors & Resistors



Dense, fine grain ceramics

GBBL designs for Hi-K

ALTAS®

Multiple pattern options

Unbeatable quality and reliability

IRC™

WWW.TECDIA.COM

MicroWaves&RF

EDITORIAL

EDITOR IN CHIEF: **NANCY K. FRIEDRICH** (212) 204-4373 nancy.friedrich@penton.com

TECHNICAL CONTRIBUTOR: **JACK BROWNE** (212) 204-4377 jack.browne@penton.com

MANAGING EDITOR: **JEREMY COHEN** (212) 204-4243 jeremy.cohen@penton.com

ART DEPARTMENT

GROUP DESIGN DIRECTOR: **ANTHONY VITOLO** tony.vitolo@penton.com

CREATIVE DIRECTOR: **DIMITRIOS BASTAS** dimitrios.bastas@penton.com

SENIOR ARTIST: **JAMES MILLER** james.miller@penton.com

INTERN: **COREY BAUMANN**

PRODUCTION

GROUP PRODUCTION DIRECTOR: **JUSTIN MARCINIAK** justin.marciniak@penton.com

AD PRODUCTION COORDINATOR: **KARA WALBY** kara.walby@penton.com

CLASSIFIED PRODUCTION COORDINATOR: **LINDA SARGENT** linda.sargent@penton.com

AUDIENCE MARKETING

AUDIENCE MARKETING MANAGER: **BRENDA ROODE** brenda.roode@penton.com

ONLINE MARKETING SPECIALIST: **RYAN MALEC** ryan.malec@penton.com

Free Subscription • Status of Subscription • Address Change • Missing Back Issues (866)-505-7173 microwaves&rf@halldata.com

SALES & MARKETING

BRAND DIRECTOR, e/DESIGN: **TRACY SMITH** (913) 967-1324 Tracy.Smith@penton.com

Northwest/Northern CA/ Western Canada
REGIONAL SALES REPRESENTATIVE: **JAMIE ALLEN** (415) 608-1959 Jamie.Allen@penton.com

South
REGIONAL SALES REPRESENTATIVE: **BILL YARBOROUGH** (713) 636-3809 Bill.Yarborough@penton.com

BRAND CHAMPION: **DAVID MADONIA** (212) 204-4331 Dave.Madonia@penton.com

EUROPEAN SALES: **MARK DURHAM** 44 (0) 7958 564137 mark.durham@penton.com

Taiwan, R.O.C.
CHARLES C.Y. LIU (866)2727 7799

Japan
HIRO MORITA 81-3-3261-4591

Korea
JO YOUNG SANG (011)82-2-739-7840

LIST RENTAL: **MARIE BRIGANTI** (877) 796-6947 marie.briganti@meritdirect.com

CUSTOMER SERVICE-SUBSCRIPTIONS: **MARIE BRIGANTI** (877) 796-6947 marie.briganti@meritdirect.com

ONLINE

ONLINE DEVELOPMENT DIRECTOR: **STEPHANIE CAMPANA** stephanie.campana@penton.com

DIRECTOR OF DIGITAL CONTENT: **PETRA ANDRE** petra.andre@penton.com

WEB PRODUCTION COORDINATOR: **JACKIE CROSS** jackie.cross@penton.com

DESIGN ENGINEERING & SOURCING GROUP

VICE PRESIDENT & MARKET LEADER: **BILL BAUMANN**

GROUP DIRECTOR OF OPERATIONS: **CHRISTINA CAVANO**

GROUP DIRECTOR OF MARKETING: **JANE COOPER**

RESEARCH MANAGER: **JULIE RITCHIE**

MARKETING & EVENTS SPECIALIST: **ADRIAN PIAZZA**

MARKETING COMMUNICATIONS SPECIALIST: **CYNTHIA RODRIGUEZ**

Penton
Design Engineering & Sourcing Group

Electronic Design • Machine Design • Microwaves & RF • Source ESB • Energy Efficiency & Technology Power Electronics • Global Purchasing • Defense Electronics • Medical Design • Mobile DevDesign Electronic Design China • Motion System Design • Engineering TV • Electronic Design Europe Hydraulics & Pneumatics • Auto Electronics


PENTON MEDIA, INC.

CHIEF EXECUTIVE OFFICER: **DAVID KIESELSTEIN** david.kieselstein@penton.com

CHIEF FINANCIAL OFFICER/EXECUTIVE VP: **NICOLA ALLAIS** nicola.allais@penton.com

SENIOR VP, DESIGN ENGINEERING GROUP: **BOB MaCARTHUR** bob.macarthur@penton.com

249 West 17th Street, New York, NY 10011



You work in all kinds of conditions, so should your spectrum analyzer.

Worst-case scenario: You've got minutes to troubleshoot RF interference that has shut down communications on the ground, at dusk, in the desert.

Best-case scenario: You've got the only spectrum analyzer with benchtop performance in a lightweight MIL-PRF 28800F Class 2 compliant handheld—with secure erase to keep classified data classified.

That's thinking ahead. That's Agilent.

Scan the QR code or visit http://goo.gl/Rfbde to see a HSA N9344C demo guide video

Handheld Spectrum Analyzers (HSA)			
Key Specs	**N9344C**	**N9343C**	**N9342C**
Frequency	1 MHz–20 GHz	1 MHz–13.6 GHz	100 kHz–7 GHz
DANL	-155 dBm/Hz	-155 dBm/Hz	-164 dBm/Hz
Sweep time	< 0.9 s	< 0.7 s	< 0.4 s
Weight with battery	3.6 kg (7.9 lbs)	3.6 kg (7.9 lbs)	3.6 kg (7.9 lbs)

Agilent and our Distributor Network
Right Instrument.
Right Expertise.
Delivered Right Now.

metrictest
866-436-0887
www.metrictest.com/agilent

View online HSA video demos
Download demonstration guides
www.metrictest.com/agilent/specan.jsp

© 2012 Agilent Technologies, Inc. *(U.S. Army photo by Spc. Patrick Tharpe) (Released)*

Agilent Technologies

Fairview Microwave Inc.


ADAPTERS



SM5250 $55.62 SMA SWEPT 27GHZ | SM4979 $37.08 SMA 27 GHZ | SM4923 $93.00 SMA FLANGE 27 GHZ | SM3224 $216.30 2.92 BULKHEAD 40 GHZ | SM3321 $135.96 3.5-3.5 34 GHZ | SM3935 $421.27 1.85-1.85 65 GHZ | SM8867 $155.00 SMP-2.4 40 GHZ | SM2927 $132.87 1.85-1.85 65 GHZ


SM3358 $216.30 7mm-3.5 18 GHZ | SM3397 $49.50 7/16 90° 6 GHZ | SM4531 $165.00 N 90° 18 GHZ | SM3547 $37.08 TNC-BNC 8 GHZ | SM5514 $139.05 ZMA-SMA 18 GHZ | SMW75ACN $295.00 WR75-N 10-15 GHZ | 28AC206 $345.00 WR28-2.92 26-40 GHZ | SM4835 $165.00 SSMA-2.92 40 GHZ

ATTENUATORS




SA18N5WA $59.28 N 5 W 18 GHZ | SA18N25WA $228.80 N 25 W 18 GHZ | SA18N507 $338.00 N 50 W 18GHZ | SA3015 $13.35 SMA 2 W 3 GHZ | SA18S50W $332.80 SMA 50 W 18 GHZ | SA3N511 $160.00 N 50 W 3 GHZ | SA4020 $728.00 2.92 10 W 40 GHZ | SA5074 $270.40 2.4 1 W 50 GHZ

COUPLERS, POWER DIVIDERS



MC0626 $1,034.80 2.92 COUPLER 6-26 GHZ | MC0618 $338.00 SMA COUPLER 6-18GHZ | MC4061 $750.00 N-SMA COUPLER 1-12 GHZ | SMC4037 $52.00 N COUPLER 700-2700 MHZ | MP0218-4 $265.20 SMA 4-WAY 2-18 GHZ | MP1540-2 $1,034.80 2.92 2-WAY 15-40 GHZ | MP8769 $468.00 N 2-WAY 2-8 GHZ | MP8758-4 $82.16 N 4-WAY 800-2500 MHZ


TERMINATIONS



ST27N301 $416.00 N 700-2700 MHZ LOW PIM | ST3N501 $130.00 N 50 W 3 GHZ | ST3D-50 $206.96 7/16 50 W 3 GHZ | ST1831 $18.72 SMA PUSH ON 1 W 18GHZ | ST2671 $48.88 SMA 2 W 27 GHZ | ST6T-5W $50.96 TNC 5 W 6 GHZ | ST4021 $499.20 2.92 5 W 40 GHZ | ST5038 $286.00 2.4 1 W 50 GHZ

INTRODUCING NEW PRODUCTS: GAIN HORNS AND LOW PIM SERIES







FAST DELIVERY!

CHECK OUT OUR INVENTORY LEVELS, PRICING, DATA SHEETS, & PLACE ORDERS **ONLINE** AT

WWW.FAIRVIEWMICROWAVE.COM 1-800-715-4396

1130 JUNCTION DR. STE 100 ALLEN, TX 75013 1-800-715-4396 FAX: 972-649-6689 EMAIL:SALES@FAIRVIEWMICROWAVE.COM

FEELING OUT FILTER OPTIONS

I was reading your article "Searching through Software for a Filter" (March 2012). You've covered lots of useful software I didn't even know about that captures both synthesis and realization of different filters. However, there are also pure synthesizers out there that are equally important, especially for coupled filters (pretty much all narrowband bandpass/bandstop filters). There's the CMS tool from Guided Wave Technology (www.guided-wavetech.com) and a similar tool from CoupleFil (www.couplefil.com), both about $1000 for a license. I've also just started developing a synthesizer for iPhone/iPad called Couplings Designer, which is a $30 download from the Apple iPhone AppStore (www.applied.com/iphone) or free for the lite version.

These synthesizers are not capable of realizing a filter in terms of physical dimensions, but the couplings can be easily found from tools like Momentum from Agilent Technologies and HFSS from Ansoft (www.ansys.com), Microwave Wizard from Mician (www.mician.com) is another great tool you didn't write about that can be used to fully design filters and uses mode-matching, which is incredible fast compared to method-of-moments (MoM) or finite-element-method (FEM) approaches (but quite expensive).

I hope these tips can be useful in future articles on filter design. Many think it's some kind of black art. But as you pointed out, there are lots of tools available—many even for free—to the engineer that can be helpful to understand and demystify filter design.

GÖRAN GRANSTRÖM

SOFTWARE SUPPLEMENTS

I was enjoying my May issue and the article "Matching Software to Design Needs." I noticed you hadn't mentioned the program BAMP that was an early S-Parameter CAD tool in the '70s, that ran on HP Basic controllers/desktop calculators from Hewlett-Packard Co. (www.hp.com). Also, there is a GPL-license freeware simulation tool called QUCs (Quite Universal Circuit Simulator; http://qucs.sourceforge.net). It doesn't have all the tools and bells and whistles that are available in the commercial programs, but it's not bad!

BILL CLAUSEN
PROWAVE LLC

Microwaves & RF welcomes mail from its readers. The magazine reserves the right to edit letters appearing in "Feedback." Address letters to:


Jack Browne
Technical Contributor
jack.browne@penton.com

Nancy Friedrich
Editor-In-Chief
nancy.friedrich@penton.com



Is An Oscillator Upgrade On The Horizon?

CELL PHONES, WIFI-ENABLED TABLETS, and other electronic devices all incorporate oscillators, which are traditionally silicon-based structures that generate signals by means of an electron-charge mechanism. Recently, however, a team of researchers from the University of California, Los Angeles (UCLA)—Zhongming Zeng, Pedram Khalili Amiri, Ilya N. Krivorotov, Hui Zhao, Giovanni Finocchio, Jian-Ping Wang, Jordan A. Katine, Yiming Huai, Juergen Langer, Kosmas Galatsis, Kang L. Wang, and HongWen Jiang—have developed a new type of oscillator that utilizes the spin of an electron. This development could potentially pave the way for cheaper, more energy-efficient mobile communication devices that deliver much better signal quality.



Pictured is a schematic representation of an STNO showing free and pinned magnetic layers (left), along with a cross-section showing top and bottom metallic electrodes (right).

The new oscillators grew out of research at the UCLA Henry Samueli School of Engineering and Applied Science, which had been sponsored by the Defense Advanced Research Projects Agency (DARPA). The researchers' focus was originally on spin-transfer torque magnetoresistive random access memory (STT-RAM), which has demonstrated several advantages over other types of computer memory. But in the process, they realized that STT-RAM's layered nanoscale structures could also be developed for microwave oscillators, and utilized in communications applications.

These structures, known as spin-transfer nano-oscillators (STNOs), are composed of two distinct magnetic layers: One has a fixed magnetic polar direction, while the other can be made to gyrate in response to an electric current **(see figure)**. This allows the structure to pro-

duce very precise and stable microwave oscillations. The SNTO was tested to show output power of close to 1 μW, with a record narrow signal linewidth of 25 MHz.

In addition, the new nanoscale system is about 10,000 times smaller than current silicon-based oscillators. The nano-oscillators can easily be incorporated into existing integrated circuits (ICs), as they are compatible with current IC fabrication techniques. Best of all, the oscillators can be used in both analog and digital communications, which means smartphones can take full advantage of them.

To learn more about these new oscillators, the researchers' findings can be reviewed in their article "High-Power Coherent Microwave Emission from Magnetic Tunnel Junction Nano-oscillators with Perpendicular Anisotropy." This report has been published online in the journal *ACSNano* (http://pubs.acs.org).

Extra Defense For Mobile Devices

CONDUCTING BUSINESS over commercial cell phone networks has become an increasing risky proposition, particularly when your job necessitates the sharing of sensitive information. To address this threat, General Dynamics C4 Systems (www.generaldynamics.com) is integrating its defense-grade cyber and information security technologies into Samsung's (www.samsung.com) line of smartphones and tablets.

Known as the Samsung Approved for Enterprise (SAFE) line, these devices are being targeted to customers ranging from government and law enforcement agencies to financial and utility personnel—essentially, any entity whose employees need to browse the public Internet as well as access secure networks. The secure technologies being integrating into the Samsung products are similar to those utilized for the US Department of Defense, Department of Homeland Security, federal agencies, and coalition partners to secure classified information.

In total, 20 different SAFE devices are being made available across all major US carriers, addressing different price points and form factors. In addition, all will be upgraded with Samsung's new Secure Android platform. Expected to be made available by mid-2013, the devices will be sold directly by General Dynamics, as well as through government contract vehicles [including the General Services Administration (GSA; www.gsa.gov)].

Defense Heavyweight Makes Microwaves Play



ATTEMPTING TO ESTABLISH a strong foothold in the RF/microwave industry, Chelmsford, MA-based Mercury Computer Systems (www.mc.com) has signed an agreement to acquire Micronetics (www.micronetics.com). A provider of intelligence, surveillance, and reconnaissance (ISR) and electronic-warfare (EW) subsystems for defense prime contractors, Mercury will acquire Micronetics via merger for $14.80 per share. This represents a fully diluted equity value of approximately $71.7 million and an enterprise value of approximately $75.4 million (including $3.7 million of net debt).

Based in Hudson, NH, Micronetics designs and manufactures RF/microwave subsystems and components used in defense and commercial applications. These include EW, radar, electronic countermeasures (ECM), satellite communications (satcom), and commercial wireless products. Approximately 78% of the company's revenues are defense-related.

For its fiscal year ended March 31, Micronetics reported revenues of $46 million with net income of $3.4 million. The firm has more than 200 US-based employees with additional manufacturing sites in West Caldwell, NJ; Ewing, NJ; and Manteca, CA.

The acquisition is subject to customary closing conditions and the approval of Micronetics' shareholders. The boards of directors of both companies have unanimously approved the transaction. At present, the deal is expected to close within the first quarter of Mercury's 2013 fiscal year.

MarketQuote



By 2017, the annual volumes of smart payment and banking cards shipped are forecast to reach 3.5 billion—a dramatic increase from the 1.1 billion shipped in 2011.

Source: IMS Research (www.imsresearch.com)


IMS 2012 Posts Strong Attendance Figures

Leading up to this year's International Microwave Symposium (IMS), some had questioned whether holding the traditionally US-based show in Montreal, Canada would hurt its attendance. As it turned out, however, the show received very good attendance. According to event organizers, IMS 2012—held June 17 to 22 at Montreal's Palais des Congrès—was visited by more than 7600 RF/microwave designers, researchers, developers, academics, executives, and exhibitor staff. The symposium also boasted strong international involvement, featuring representation from some 57 countries.

Leading the pack in attendees was the US (46%). Host country Canada occupied the runner-up spot with 17%. Of particular note was China, which posted a 200% increase in attendees over the previous year. More attendees also came from multiple European countries including Germany, France, the United Kingdom, and The Netherlands.

In total, IMS 2012 welcomed 569 exhibitors from 21 countries. Impressively, a record 1225 paper submissions were received from 49 different countries Of the 4118 symposium registrants, 2653 registered for the technical program with 1465 registering for the exhibits alone.

Next year, IMS will be making a return to the United States. The event is scheduled for June 2 to 7, 2013 at the Washington State Convention Center in Seattle, WA. For more information, visit www.ims2013.org.



STANDARDS WATCH

Wi-Fi Users Get Ready To Roam

WITH WI-FI CAPABILITY built into devices ranging from smartphones to laptops, many consumers rely on hotspots for mobile connectivity. Unfortunately, a good Wi-Fi user experience has usually been a fixed one, where the user remains in one place so as not to lose his or her connection and/or provider. Now, the Passpoint certification program is looking to foster multi-provider Wi-Fi roaming. As a result, Wi-Fi networks will soon offer a cellular-like connectivity experience.

Based on the Wi-Fi Alliance Hotspot 2.0 specification, Passpoint promises to provide a consistent, streamlined, Wi-Fi-hotspot connection process. Just as im-

TINY TOUGHEST MIXERS UNDER THE SUN



Rugged, tiny ceramic SIM mixers *from* $4.95 *ea. qty. 1000* offer unprecedented wide band, high frequency performance while maintaining low conversion loss, high isolation, and high IP3.


0.2"x 0.18"

Over 21 models IN STOCK are available to operate from an LO level of your choice, +7, +10, +13, and +17 dBm. So regardless of the specific frequency band of your applications, narrow or wide band, there is a tiny SIM *RoHS* compliant mixer to select from 100 kHz to 20 GHz. Built to operate in tough environments, including high ESD levels, the SIM mixers are competitively priced for military, industrial, and commercial applications. Visit our website to view comprehensive performance data, performance curves, data sheets, pcb layouts, and environmental specifications. And, you can even order direct from our web store and have it in your hands as early as tomorrow!

Mini-Circuits...we're redefining what VALUE is all about!

U.S. Patent #7,027,795 *RoHS compliant*

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

YoniZ® U.S. Patents 7739260, 7761442 ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see **minicircuits.com**


IF/RF MICROWAVE COMPONENTS

428 rev H

portantly, it supports the use of one set of account credentials for multiple hotspots. Service providers will benefit from Passpoint's underlying technology, which allows them to ease data offload while enabling roaming agreements. Passpoint network equipment will provide users with the assurance of enterprise-grade Wi-Fi Protected Access (WPA2) security for hotspots.

These efforts are just getting underway with the Wi-Fi Alliance's Wi-Fi CERTIFIED Passpoint test-bed program. That program will use comprehensive testing to ensure that wireless-local-area-networking (WLAN) products from multiple manufacturers work together. All Passpoint-certified devices implement a single solution for many operator networks. Among the initial participants in this program are Marvell (www.marvell.com) and Qualcomm Atheros (www.qca.qualcomm.com). The list of Wi-Fi CERTIFIED Passpoint products and more is available at www.wi-fi.org/passpoint.





STEM Teachers Go To Summer School

BUILDING YOUTH INTEREST in science, technology, engineering, and math (STEM) has garnered much attention in recent years. Lockheed Martin (www.lockheedmartin.com), however, has long recognized the importance of this directive. This summer, the company is hosting 20 middle- and high-school teachers in support of the Industry Initiatives for Science and Math Education (IISME; www.iisme.com). In all, the company has sponsored 354 such fellowships since 1985.

The IISME's primary initiative, the Summer Fellowship Program, places qualified teachers into local companies and research labs for an eight-week learning experience. During this period, each teacher—paired with industry mentors—augments his or her science and math skills by solving real-world problems. The challenges posed to Lockheed Martin's fellows and the teachers pertain to space systems under development by the company including satellite communications and missiles. The expectation is that participants will transfer their newfound knowledge and enthusiasm to their students upon returning to the classroom in the fall.

26 years ago, National Instruments redefined instrumentation with LabVIEW.



This summer, we're doing it again.

Visit **RFredefined.com** for a sneak peek at the next big thing in instrumentation.

©2012 National Instruments. All rights reserved. LabVIEW, National Instruments, NI, and ni.com are trademarks of National Instruments. Other product and company names listed are trademarks or trade names of their respective companies. 06426

NATIONAL INSTRUMENTS™

PEOPLE

ANADIGICS—TIM LAVERICK has joined the company as Vice President, Infrastructure Products. Most recently, he served as Vice President of Engineering and Product Development at Jacket Micro Devices. Laverick has held previous positions at Anadigics both as General Manager of the company's fiber-optic product segment and Vice President of Design Technology. In addition, ROBERT BAYRUNS has been appointed Vice President and Chief Technology Officer.


LAVERICK


BAYRUNS

LEMKO CORP.—ROBERT CONDON has been named President of Lemko Europe. Condon, the Founder of Atlantic Telecom, also served as President and Chief Operating Officer of Comcast BroadNet.

MICREL—THOMAS S. WONG, Vice President of the company's High Bandwidth Division, has announced his retirement. Wong joined Micrel in 1998, following the company's acquisition of Synergy Semiconductor Corp. RAMI KANAMA, Vice President of Clock and Timing Products, will take over responsibility for the High Bandwidth Division.

WEST WIRELESS HEALTH INSTITUTE—RODGER CURRIE has been appointed Senior Vice President of Government Affairs—a newly created appointment. Previously, Currie served as Senior Vice President for DEKA Research & Development.


CURRIE

INMARSAT GOVERNMENT—DAVID HELFGOTT has been named President and Chief Executive Officer. Helfgott joined Inmarsat in 2011 as both President of Inmarsat, Inc. and Senior Vice President of Business Development and Strategy for parent company Inmarsat plc.

LOCKHEED MARTIN—The board of directors has appointed President and Chief Operating Officer CHRISTOPHER E. KUBASIK to the newly established position of Vice Chairman. Kubasik will succeed ROBERT J. STEVENS as Chief Executive Officer on Jan. 1, 2013.

GLOBAL SEMICONDUCTOR ALLIANCE (GSA)—The industry group has named DR. ABHIJIT GUPTA Analog/Mixed-Signal/Radio Frequency (AMS/RF) Working Group Chairman. Gupta is the Director of Foundry Technology for SanDisk.

ETISALAT GROUP—KHALIFA AL SHAMSI has been named Chief Digital Services Officer. Al Shamsi most recently served as the company's Senior Vice President of Technology Strategy.


AL SHAMSI

INDIUM CORP.—ROBERT PLOESSL, Ph.D., has been named Product Manager for indium, gallium, germanium, and tin compounds. Ploessl, who joined Indium Corp. in 2010, is based out of the company's global headquarters located in Clinton, NY.


PLOESSL

ANALOG DEVICES (ADI)—Has appointed SOMSHUBHRO (SOM) PAL CHOUDHURY as Managing Director for Operations in India. Pal Choudhury joins ADI from NETGEAR, where he served as Product Line Director.

New Corporate Structure Shields IP

In addition to delivering products to customers more quickly, Qualcomm, Inc. (www.qualcomm.com) wishes to insulate its patent portfolio from any claims resulting from actions and activities by portions of the company other than the Qualcomm Technology Licensing Division (QTL). As a result, a new corporate structure will feature the parent company, Qualcomm, Inc., which includes QTL and corporate functions as well as most of Qualcomm's patent portfolio. A new, wholly owned subsidiary, Qualcomm Technologies, Inc. (QTI), will—along with its subsidiaries—operate substantially all of Qualcomm's research and development activities. It also will be in charge of the product and services businesses including the semiconductor business, QCT.

The new corporate structure essentially formalizes the way that the company has been operating its primary businesses. Yet Qualcomm does expect QTI and its subsidiaries' product and service businesses to increase their volume of work with open-source software in the future. The restructuring will help to ensure that the activities of QTI and its subsidiaries will not result in the licensing of any patents belonging to Qualcomm, Inc.—including its third- and fourth-generation (3G and 4G) patents.

The new structure will help ensure the activities of QTI and its subsidiaries will not result in the licensing of any patents belonging to Qualcomm, Inc.

Under the new structure, QTI and its subsidiaries will own patents that were specifically developed to provide their open-source software contributions. Substantially all of the remainder of the company's patent portfolio will continue to be owned by Qualcomm, Inc. QTI and its subsidiaries will have no rights to grant licenses or other rights to patents held by Qualcomm, Inc. There will be no changes to the IP that is currently owned by Qualcomm Innovation Center, Inc., which works closely with the open-source community to accelerate the advancement of the wireless industry. Qualcomm anticipates that the new corporate structure will become effective during the first fiscal quarter of 2013.


A/D CONVERTERS

Offers Lowest Power Consumption for Best SNR!



Analog, Digital & Mixed-Signal
ICs, Modules, Subsystems & Instrumentation





Hittite's Analog-to-Digital Converter (ADC) products provide ultra low power dissipation per channel, ease of use and cost efficiency while maintaining high SNR / SFDR performance. When coupled with our RF & microwave IC solutions these ADCs will optimize your system performance.

Analog-to-Digital Converters

	Part Number	Resolution	Maximum Sample Rate	# of Channels	Power Dissipation	SNR (dBFS)	SFDR (dBc)	EasySuite™ Evaluation Kit P/N
	HMCAD1520	14 / 12-Bit	640 MSPS	1, 2, 4	490 mW	70	60 / 75 [1]	EKIT01-HMCAD1520
	HMCAD1511	8-Bit	1 GSPS	1, 2, 4	710 mW	49.8	49 / 64 [1]	EKIT01-HMCAD1511
	HMCAD1510	8-Bit	500 MSPS	1, 2, 4	295 mW	49.8	49 / 65 [1]	EKIT01-HMCAD1510
NEW!	HMCAD1104	10-Bit	65 MSPS	8	30 mW / Channel	61.6	81	EKIT01-HMCAD1104
	HMCAD1102	13 / 12-Bit	80 MSPS	8	59 mW / Channel	70.1	77	EKIT01-HMCAD1102
	HMCAD1101	13 / 12-Bit	65 MSPS	8	51 mW / Channel	72.2	82	EKIT01-HMCAD1101
	HMCAD1100	13 / 12-Bit	50 MSPS	8	41 mW / Channel	72.2	82	EKIT01-HMCAD1100
	HMCAD1050-40 / 80	13 / 12-Bit	40 / 80 MSPS	2	55 / 102 mW	72.7 / 72	81 / 77	EKIT01-HMCAD1050
	HMCAD1051-40 / 80	13 / 12-Bit	40 / 80 MSPS	1	33 / 60 mW	72.7 / 72	81 / 77	EKIT01-HMCAD1051
	HMCAD1040-40 / 80	10-Bit	40 / 80 MSPS	2	43 / 78 mW	61.6	81 / 75	EKIT01-HMCAD1040
	HMCAD1041-40 / 80	10-Bit	40 / 80 MSPS	1	25 / 46 mW	61.6	81 / 75	EKIT01-HMCAD1041

[1] *Excluding Interleaving Spurs.*

Ultra High Speed Analog-to-Digital Converter

	Part Number	Input Frequency (GHz)	Sample Rate	Resolution	ENOB	SFDR (dBFS)	EasySuite™ Evaluation Kit P/N
NEW!	HMCAD5831LP9BE	20	26 GSPS	3-Bit	2.9	26	EKIT01-HMCAD5831

Hittite MICROWAVE CORPORATION

Contact Us: adc@hittite.com

2 Elizabeth Drive • Chelmsford, MA 01824
978-250-3343 tel • 978-250-3373 fax • timing@hittite.com

Visit Us: www.hittite.com
Receive the latest product releases - click on "My Subscription"

CONTRACTS

Lockheed Martin—Has been awarded a $68-million contract by the US Air Force in support of the first and second GPS III satellites. Lockheed Martin will provide mission readiness, launch, early orbit checkout, and on-orbit operations engineering support. In addition, the company has been awarded a Phase I Airborne Launch Assist Space Access (ALASA) program study contract by the Defense Advanced Research Projects Agency (DARPA). The contract is valued at approximately $6.2 million.

General Dynamics—Has been awarded a contract to support the US Department of Homeland Security's (DHS's) Tactical Communications Equipment and Services (TacCom) program. General Dynamics was one of five companies selected for each of six defined technical categories. The multiple-award, indefinite delivery, indefinite quantity contract has a potential value of $3 billion to all 30 awardees over five years, if all options are exercised.

Raytheon Co.—Has received a contract from the US Navy for the delivery of 47 additional Navy Multiband Terminal (NMT) systems. The order is valued at $79 million. In addition, the company has received a $19-million contract to modify the NMT, linking it with the US Air Force's Enhanced Polar Satellite (EPS).

RELM Wireless Corp.—Has received orders totaling approximately $2 million from the US Department of Agriculture Forest Service (USFS) and the National Interagency Fire Center (NIFC). The orders are for RELM's D-Series digital P-25 portable and mobile radios, in addition to accessories.

GENERAL DYNAMICS Tapped For DHS TacCom Contract

RAYTHEON Receives Dual NMT Orders

Nordic Semiconductor—The company's wireless technology is being used by Qingdao Haier Intelligent Electronics Co. in its QWERTY-keypad-equipped RF/infrared (IR) remote control. The remote is designed for use by consumer-electronics (CE) manufacturers of emerging "connected" products, such as smart TVs.

Ceragon Networks—Has signed a contract to supply high-capacity microwave solutions and turnkey services to the Navajo Tribal Utility Authority (NTUA). The combined orders are worth approximately $4 million.

COM DEV—Has been awarded a $12-million follow-on contract by Boeing Satellite Systems. COM DEV will supply filters, switches, and ferrite components for use in NASA's Tracking and Data Relay Satellite (TDRS) program.

Giga-tronics—Has completed negotiations with an undisclosed aircraft supplier to continue delivery of its high-performance filters. The new contract totals more than $4.9 million if all options are exercised.

Frequency Electronics—The company's FEI-Elcom Tech subsidiary has received an order for its broadband 18-GHz synthesizers from an undisclosed client. The total value of the contract is expected to exceed $4 million and is to be completed in less than 12 months.

FRESH STARTS

Qualcomm—Is establishing an integrated-circuit (IC) design and engineering R&D center in Singapore. The new facility will focus on chip-set design and development including analog and power, mixed-signal, and digital design.

Underwriters Laboratories (UL)—Has been accredited as a Bluetooth 4.0 testing laboratory by the United Kingdom Accreditation Service (UKAS). UL is now able to test and certify products equipped with the latest Bluetooth standard in the UK.

National Instruments (NI)—Is collaborating with the Technical University of Dresden (Dresden, Germany) on new technologies for fifth-generation (5G) wireless systems. NI's LabVIEW system design software is being utilized in the effort.

xG —Has been granted six new patents related to its cognitive-radio (CR) work. The technologies covered by the new patents include spectrum sharing, media-access control (MAC), mobile voice-over-Internet-protocol (VoIP) signaling, and interference detection/mitigation.

IF Engineering (IFE)—Has signed a distribution agreement with East Coast Microwave Distributors (ECM). Per the arrangement, ECM will stock and distribute IFE's line of power dividers, couplers, transformers, and switches.

LadyBug Technologies—Has named Bangalore-based VigVen Tech Mark Pvt. as its authorized distributor in India. VigVen will carry LadyBug's entire range of Universal-Serial-Bus (USB) power sensors.

Federal Communications Commission (FCC)—Has proposed expanding eligibility in the 4.9-GHz band to include utilities and other critical-infrastructure industries (CII) on a primary basis. This band would provide utilities with access to 50 MHz of spectrum, supporting high-capacity and short-range communications for a variety of applications.

RFMW—Has announced a distribution agreement with Aeroflex/Metelics covering Europe, the Middle East and Africa (EMEA), and the Americas. Per the agreement, RFMW will distribute Aeroflex/Metelics' full product portfolio. In addition, RFMW has announced immediate delivery of selected cable assemblies from Florida RF Labs.

Modelithics—Has signed a comprehensive representative and reseller agreement with Medeos SRL. Medeos will sell all Modelithics products and services throughout Italy.

Indium Corp.—Has acquired a new manufacturing facility in Rome, NY. The plant is currently being outfitted to expand production capacities of various compounds including indium-, gallium-, germanium-, and tin-based materials.


Mindspring Technologies—Is forming a joint development lab with China Mobile Communications Corp. The collaboration will support China Mobile's recent deployment of Time-Division Synchronous Code Division Multiple Access (TD-SCDMA) femtocells.

Silicon Labs—Has signed a definitive agreement to acquire Ember Corp. Based out of Boston, MA, Ember is a provider of silicon, software, and development tools for 2.4-GHz wireless-mesh-networking solutions.

99¢

only

ea.(qty. 20)



FLAT GAIN WIDEBAND amplifiers

flatness from ±0.7dB across 0.1-6 GHz IP3 up to 38 dBm

Our new GVA-62+ and GVA-63+ amplifiers are spot-on for high performance base stations, portable wireless, LTE and cellular, CATV/DBS systems, MMDS, and wireless LANs. They make excellent gain blocks for almost any 50Ω circuit. DC power as low as 5V/69 mA delivers a typical output power of 18 dBm, unconditional stability, and built-in ESD protection, all with no external matching components required!

Just go to minicircuits.com for technical specifications, performance data, export info, pricing, ***real-time availability***, and everything else you need to make your selection today—for delivery as soon as tomorrow!

Model	Freq. Range (MHz)	Gain (dB)	P_{OUT} (dBm)	Price $ ea. (Qty. 20)
GVA-62+	10-6000	15	18	0.99
GVA-63+	10-6000	20	18	0.99

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661


YoniFind® U.S. Patents 7739260, 7761442 ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

505 rev A



Mini-Circuits...
we're redefining what VALUE is all about!



MIXER MAGIC?

It's no illusion—

Mini-Circuits makes more mixers, that meet more needs, than all other manufacturers combined!



500 Hz to 20 GHz

from $1.69 ea. Qty. 1000

More models, more applications. For instrumentation, hi-rel military projects, tough industrial equipment, high-traffic cellular systems, and tightly budgeted commercial products, Mini-Circuits has over 500 mixer models, with tens of thousands in stock for immediate shipment, and ten of thousands more ready for production in a snap!

Outstanding performance. Our hermetic LTCC/semiconductor mixers are so robust, they're guaranteed for 3 years! You'll also find IP3s up to 37 dBm, 1-dB compression as high as 23 dBm, excellent unit-to-unit matching, extremely wide bandwidths, LO power levels from 3 to 27 dBm, and case profiles as low as 0.06"!

Forty+ years of manufacturing experience—in multiple technologies—help us meet the demands of each of our customers, from cutting-edge performance to low price, small size, and sheer durability.

Quick and easy selection. Enter a few specifications, and our patented Yoni2 search engine will find all the models that meet or exceed your needs. And custom models are just a phone call or email away, with quick turnarounds and surprisingly low prices.

It's no secret—industry leaders have known for years: go to minicircuits.com today to find the mixers you need, and get them in your hands as soon as tomorrow!

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

Yoni2® *The Design Engineers Search Engine finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

U.S. Patents 7739260, 7761442

IF/RF MICROWAVE COMPONENTS

501RevOrg

Inside Track with Julio Perdomo,

CEO, CENTELLAX

Interview by NANCY FRIEDRICH



NF: Although this is an evolving market, many firms have made their living by offering the same types of products for decades. Recently, however, Centellax made a bold change by selling its test and measurement business to Agilent Technologies. What inspired this move?

JP: Centellax's initial mission was to develop high-speed components for optical communications. Our test business grew from the need to test our own products and the opportunity for others to benefit from our test development. Both businesses have grown substantially. And both demanded dedicated focus from management as well as investment to capitalize on opportunities. Considering the choices of where to focus as a company and the challenges ahead, we decided to continue with our original mission and divest our test business.

NF: As part of Centellax, did you feel that the test and measurement business was limited in its growth potential?

JP: No. We are very proud of the products that we developed. And the acquisition by Agilent is a validation of the innovation and value that we created. There is great potential for these products in the growing markets that they serve. I am sure that Agilent, with its extensive sales channel and worldwide coverage, will take full advantage of that business potential.

NF: The test and measurement product line was one of the firm's "babies;" I'm sure it was hard to let it go. What gave you the confidence to sell the business to Agilent in particular? Did the company have a relationship with Agilent prior to the transaction that might have encouraged your choice?

JP: Agilent is the number-one test company in the world. Under its leadership, I feel confident that the team and the technology that we developed will thrive. Although many of us are familiar with the excellence of Agilent as a company and as a technology leader, there was no specific prior relationship other than as a customer.

NF: What is the firm's core concentration since selling the test business?

JP: Our focus is to design and manufacture components for optical communications used in telecommunications, data communications, and data-center applications. We also offer a product line for RF

and microwave applications.

NF: With more of a streamlined operation, what do you feel that Centellax can better accomplish?

JP: We are focusing on being more responsive to changing market needs and better supporting our customers. We are expanding our current portfolio to better serve our customers with the technologies and products that they want.

NF: Do you have any advice for other microwave companies looking to make bold moves to reorganize their firms?

JP: I believe the key to success is focusing on core competencies and product roadmaps to better serve your customer base.

NF: Centellax was established in 2001. The last 11 years have been quite a bumpy ride. How has the company weathered the storms?

JP: We have adapted our core technology of integrated circuit (IC)/packaging design to address the changing demand for high-speed, high-performance products. Our test-business success was also based on this core technology.

NF: Do you expect the role of optical technology in future communications rollouts [fourth generation (4G) and beyond] to shrink or remain stable? Why?

JP: Due to the bottleneck in high-speed data transmission, there is a growing demand for greater capacity in optical-communication systems operating at 40 Gb/s, 100 Gb/s, and soon-to-come 400 Gb/s. Centellax has experienced major growth in 40G in the last three years. We see the same trend in 100G for 2013 and beyond. This supports the market-research studies that indicate the large growth of these markets through the next five years.

NF: What are the major technical challenges that your customers are trying to overcome to succeed in those rollouts?

JP: Our customers need to reduce system cost and maintain excellent performance with unquestionable quality and reliability. It is our job to provide them with products that offer lower power dissipation and packaging cost with the performance they need to meet their goals.

NF: Do you see those challenges becoming more complex? Or do you predict that you will be dealing with new issues in the future?

JP: We expect to see higher-level modulation schemes to achieve higher spectrum efficiency. This trend is similar to what we observed in the RF communications markets. The challenges make things more complex because some requirements contradict each other, like higher dynamic range, lower power dissipation, higher linearity, and lower noise. To meet these requirements, new techniques will have to be used at the IC level. That will make the design more complex.



NF: Right now, you are supporting 40G, 100G, and 400G optical communications with your products. Where do you see optical communications going beyond 400G? Will Centellax be prepared to support such an evolution?

JP: The drivers for the evolution of the optical-communications transmission rate are the need for lower cost and higher efficiency in data transfer. To some extent, cost is addressed with lower power dissipation and more integration. The higher-transmission efficiency requirements are addressed by higher degrees of complex modulation. We are engaged in developing the technology and products to address these requirements by integrating more functionality into the products, reducing form factors, and lowering power dissipation. MWRF

60-GHz HELICAL ARRAY Relies On LTCC

SEVERAL GIGAHERTZ of bandwidth are now available in the 60-GHz band for short-range communications applications. For antennas, this trend has reinforced the move from discrete designs to integrated on-chip or in-package solutions. For designs that are closer to bringing low-cost, highly integrated 60-GHz solutions to fruition, multilayer, low-temperature co-fired ceramic (LTCC) technology has been used successfully. At the National University of Singapore, for example, a 60-GHz wideband, circularly polarized helical antenna array of 4x4 elements has been designed and fabricated using LTCC technology. This antenna is the work of Changrong Liu, Yong-Xin Guo, Xiaoyue Bao, and Shao-Qiu Xiao.

LTCC has been heralded for its light weight, compactness, and high performance. In this design, the flexible via-hole distribution is leveraged to realize a helical antenna array with good circular polarization performance. For probe-station measurements, grounded coplanar waveguide (GCPW) to stripline is used. The fabricated antenna array, which measures 12 x 10 x 2 mm, shows a measured impedance bandwidth of 52.5 to 65.5 GHz for $|S_{11}|$ below –10 dB. See "60-GHz LTCC Integrated Circularly Polarized Helical Antenna Array," *IEEE Transactions On Antennas And Propagation*, March 2012, p. 1329.

WAVEGUIDE-BASED MIXER Excels In Terahertz Range

TO ROUGHLY 1.25 THz, the most sensitive and high-resolution heterodyne spectrometers are based on superconductor-isolate-superconductor (SIS) tunnel junction mixers. Beyond 1.25 THz, however, superconducting hot-electron-bolometer (HEB) mixers are considered a better option. Most HEB mixers operating above 2 THz couple the mixer element to a planar antenna on a dielectric substrate lens. Yet waveguide feeds boast better coupling efficiency to free space while naturally reducing the direct detection response of HEBs. It also is generally easier to implement compact, high-pixel-count, focal-plane arrays using waveguide technology. At NASA's Jet Propulsion Laboratory, a combination of conventional metal machining and metallic micro-plating techniques has been used to construct a low-noise superconducting mixer operating near 2.7 THz.

The JPL team—Faouzi M. Boussaha, Jonathan H. Kawamura, Jeffery A. Stern, Anders Skalare, and Victor White—adopted an approach that combined ultraviolet (UV) lithography with micro-plating techniques to make the waveguide embedding circuit. The resulting low-noise, waveguide-based heterodyne mixer uses a superconducting NbN hot-electron bolometer (HEB) operating near 2.7 THz. The NbN nano-bridge is integrated with a gold-bowtie planar antenna on a silicon substrate that is merely ~2 to 3 μm thick.


The mixer chip is placed in a channel across the input waveguide. These chips are produced using high-purity, silicon-on-insulator (SOI) substrate. The mixer chips are suspended at a distance corresponding to the substrate thickness plus an air-cavity depth from the waveguide backshort. With this configuration, the effective dielectric constant of the silicon substrate is reduced from 11.9 to ~2.8. See "A Low Noise 2.7 THz Waveguide-Based Superconducting Mixer," *IEEE Transactions On Terahertz Science And Technology*, May 2012, p. 284.

QUADRATURE LO Spans 5 To 10 GHz

TO MORE efficiently use spatial and temporal spectrum from 50 MHz to 10 GHz, many are eying cognitive radio (CR). On a system-on-a-chip (SoC), however, a heterodyne approach requires multiple local oscillators (LOs) to handle the potentially independent operations of the CR RF transceiver. Such an implementation can be very tricky, as the design of LO for CR applications demands silicon-area compactness and low power consumption. Recently, a low-quadrature LO was designed and implemented by the University of California's Ning-Yi Wang, Mau-Chung Frank Chang, and Jianhua Lu (who is also with Peregrine Semiconductor Corp.). Their LO can create 13.3-to-20.0-GHz signals from a differentially tuned, inductive-capacitive voltage-controlled oscillator (LC-VCO). It converts those signals to the 5-to-10-GHz band with continuous frequency coverage.

In this design, a frequency-extension solution takes advantage of the natural characteristics of a four-stage, differential, injection-locked ring oscillator (ILRO) to obtain the desired quadrature outputs with a precise 50% duty cycle. Impressively, both the output 50% duty cycle and quadrature matching can be maintained even with the input signal's duty cycle deviating from 50%. The team implemented the integrated, quadrature-phased LO in 65-nm general-purpose CMOS integrated-circuit (IC) technology. It occupies less than 0.11 mm^2 and consumes a maximum of 22 mA current from a 1-V supply. The LO exhibits worst-case phase noise of –104 dBc/Hz at 1 MHz offset across the entire 5-to-10-GHz band. See "A Compact and Low Power 5-10 GHz Quadrature Local Oscillator for Cognitive Radio Applications," *IEEE Journal Of Solid-State Circuits*, May 2012, p. 1131.

High Linearity LNAs



NF as low as 0.5 dB • IP3 up to 43 dBm • DC current 20 mA and up

from $1.49 ea. (qty. 20)

Pick your parameters, and meet your needs at Mini-Circuits! With over 20 low noise/high linearity amplifier models to choose from, you'll likely find the output power, gain, DC current, and broad bandwidths required to upgrade almost any 3-to-5V circuit—from cellular, ISM, and PMR to wireless LANs, military communications, instrumentation, satellite links, and P2P—and all at prices that preserve your bottom line!

Our catalog models are in stock and ready to ship, so why wait? Go to minicircuits.com for all the details, from data sheets, performance curves, and S-parameters to material declarations, technical notes, and small-quantity reels—as few as 20 pieces, with full leaders and trailers. Place an order today, and see what these tiny, high-performance amplifiers can do for your application, as soon as tomorrow!

RoHS compliant

Model	Freq. (MHz)	Gain (dB)	NF (dB)	IP3 (dBm)	P_{out} (dBm)	Current (mA)	Price $ (qty. 20)
PMA2-162LN+	700-1600	22.7	0.5	30	20	55	2.87
PMA-5452+	50-6000	14.0	0.7	34	18	40	1.49
PSA4-5043+	50-4000	18.4	0.75	34	19	33 (3V) 58 (5V)	2.50
PMA-5455+	50-6000	14.0	0.8	33	19	40	1.49
PMA-5451+	50-6000	13.7	0.8	31	17	30	1.49
PMA2-252LN+	1500-2500	15-19	0.8	30	18	25-55 (3V) 37-80 (4V)	2.87
PMA-545G3+	700-1000	31.3	0.9	33	22	158	4.95
PMA-5454+	50-6000	13.5	0.9	28	15	20	1.49

Model	Freq. (MHz)	Gain (dB)	NF (dB)	IP3 (dBm)	P_{out} (dBm)	Current (mA)	Price $ (qty. 20)
PGA-103+	50-4000	11.0	0.9	43	22	60 (3V) 97 (5V)	1.99
PMA-5453+	50-6000	14.3	0.7	37	20	60	1.49
PSA-5453+	50-4000	14.7	1.0	37	19	60	1.49
PMA-5456+	50-6000	14.4	0.8	36	22	60	1.49
PMA-545+	50-6000	14.2	0.8	36	20	80	1.49
PSA-545+	50-4000	14.9	1.0	36	20	80	1.49
PMA-545G1+	400-2200	31.3	1.0	34	22	158	4.95
PMA-545G2+	1100-1600	30.4	1.0	34	22	158	4.95
PSA-5455+	50-4000	14.4	1.0	32	19	40	1.49



PSA PMA PGA

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®

ISO 9001 ISO 14001 AS9100


P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

U.S. Patents 7739260, 7761442

The Design Engineers Search Engine *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

506 rev C



Microwaves in Europe

SALLY WARD-FOXTON, *Associate Editor*
Electronic Design Europe

Wireless SoCs Use Cortex-M0 Core To Slash Power Consumption

FOR MORE THAN A DECADE, designers of wireless products have been struggling to deliver ever-increasing performance while consuming less power. Among the latest products promising to satisfy these opposing demands are two wireless system-on-a-chip (SoC) devices from Nordic Semiconductor (www.nordicsemi.com). Conveniently, the first two low-power wireless SoCs in the nRF51 series share the same architecture and multi-protocol radio. While the nRF51822 has a Bluetooth-low-energy/proprietary 2.4-GHz stack, the nRF51422 has an ANT/ANT+ stack (see p. 42 for more on ANT).

This third generation of Nordic's wireless integrated circuits (ICs) features a new, power-efficient architecture **(see photo)**. Compared to the company's previous product generation, Nordic claims that both devices enable power reductions to 50% as well as RF link budget improvements of as much as 9.5 dB. These improvements are derived from the use of a new multi-protocol radio alongside a 32-b ARM Cortex-M0 core.



The third generation of Nordic Semiconductor's wireless ICs promises to deliver increased performance while consuming less power.

"This project was codenamed Princess," says Thomas Embla Bonnerud, Nordic's Director of Product Management. "We had very ambitious goals. We wanted to do Bluetooth low-energy and ANT single-chip SoCs that had the ease-of-use of two-chip solutions."

Perhaps most impressive of the nRF51's qualities is its extremely low power consumption. Nordic made small enhancements to the radio's current budget. But the biggest improvement came from a new power-management scheme. "Power modes 0, 1, 2, 3...We threw that away," Bonnerud explains. "These devices are not constrained by power modes. Simply power-on in software [the blocks] you want and everything else remains asleep."

Alongside the new power-management scheme is a programmable peripheral interface (PPI), which minimizes the central processing unit's (CPU's) active time to save power. Peripherals can therefore operate autonomously and talk to each other without waking the CPU. This approach also reduces real-time requirements on the CPU.

Introducing the ARM Cortex-M0 core to this IC generation improved processing speed by a factor of 10. Startup time has been reduced by a factor of 100 to 2.5 µs, which helps to save power. The company also managed to reduce the devices' supply voltage from 1.9 to 1.75 V in order to "squeeze the last juice out of a coin cell or AA," explains Bonnerud.

The devices' multi-protocol radio also was entirely redesigned. It now incorporates Easy-DMA (which stands for "direct memory access"). Essentially, it can access data directly from the memory, convert it to packets, and transmit it. An increased output-power range now stretches from –20 to +4 dBm. The radio's sensitivity depends on its operational mode: For example, it is –92.5 dBm in Bluetooth low-energy mode. The 9.5-dB improvement in link budget is derived from a combination of these two specifications.

In terms of software, the nRF51 clearly separates its application and Nordic-provided stack code. Comparing this IC to older solutions, which had a single framework, the application and stack are now compiled separately. Dependencies between them have been removed. As a result, bugs in the application code will not affect the stack or vice versa.

According to Suke Jawanda, Chief Marketing Officer for the Bluetooth SIG (www.bluetooth.org), reducing power consumption by 50% could extend the battery life of some consumer devices up to eight years. The battery life would therefore exceed the lifetime of the device—an important milestone. From the SIG's point of view, Jawanda adds, a chip that can do proprietary 2.4-GHz protocols and Bluetooth low-energy would definitely help ease companies' transition to Bluetooth low energy.

Rod Morris, Vice President of ANT Wireless, emphasizes that the launch of the nRF51422—the world's first ANT SoC—is a significant milestone. The IC's 60-kb/s burst rate makes it three times faster than previous generations. ANT requires less than 32 kB of code space and 2 kB of random-access memory (RAM), leaving more than 224 kB of Flash and 14 kB of RAM for the application code. Morris points out that the single-chip solution also will contribute to making ANT-compliant devices smaller. The 32-b M0 core has been implemented in around 12,000 silicon gates. In other words, it fits into the same physical space that was formerly occupied by 8-b devices.

HIGH POWER

5 - 500 WATTS PRODUCTS

POWER DIVIDERS

RoHS

Model #	Frequency (MHz)	Insertion Loss (dB) [Typ./Max.] ◊	Amplitude Unbalance (dB) [Typ./Max.]	Phase Unbalance (Deg.) [Typ./Max.]	Isolation (dB) [Typ./Min.]	VSWR (Typ)	Input Power (Watts) [Max.] ▫	Package
2-WAY								
CSBK260S	20 - 600	0.28 / 0.4	0.05 / 0.4	0.8 / 3	25 / 20	1.15:1	50	377
DSK-729S	800 - 2200	0.5 / 0.8	0.05 / 0.4	1 / 2	25 / 20	1.3:1	10	215
DSK-H3N	800 - 2400	0.5 / 0.8	0.25 / 0.5	1 / 4	23 / 18	1.5:1	30	220
P2D100800	1000 - 8000	0.6 / 1.1	0.05 / 0.2	1 / 2	28 / 22	1.2:1	5	329
DSK100800	1000 - 8000	0.6 / 1.1	0.05 / 0.2	1 / 2	28 / 22	1.2:1	20	330
DHK-H1N	1700 - 2200	0.3 / 0.4	0.1 / 0.3	1 / 3	20 / 18	1.3:1	100	220
P2D180900L	1800 - 9000	0.4 / 0.8	0.05 / 0.2	1 / 2	27 / 23	1.2:1	5	331
DSK180900	1800 - 9000	0.4 / 0.8	0.05 / 0.2	1 / 2	27 / 23	1.2:1	20	330
3-WAY								
S3D1723	1700 - 2300	0.2 / 0.35	0.3 / 0.6	2 / 3	22 / 16	1.3:1	5	316

◊ In excess of theoretical split loss of 3.0 dB
▫ With matched operating conditions

HYBRIDS

RoHS

Model #	Frequency (MHz)	Insertion Loss (dB) [Typ./Max.] ◊	Amplitude Unbalance (dB) [Typ./Max.]	Phase Unbalance (Deg.) [Typ./Max.]	Isolation (dB) [Typ./Min.]	VSWR (Typ)	Input Power (Watts) [Max.]	Package
90°								
DQS-30-90	30 - 90	0.3 / 0.6	0.8 / 1.2	1 / 3	23 / 18	1.35:1	25	102SLF
DQS-3-11-10	30 - 110	0.5 / 0.8	0.6 / 0.9	1 / 3	30 / 20	1.30:1	10	102SLF
DQS-30-450	30 - 450	1.2 / 1.7	1 / 1.5	4 / 6	23 / 18	1.40:1	5	102SLF
CSDK3100S	30 - 1000	0.8 / 1.2	0.05 / 0.2	0.2 / 3	25 / 18	1.15:1	50	378
DQS-118-174	118 - 174	0.3 / 0.6	0.4 / 1	1 / 3	23 / 18	1.35:1	25	102SLF
DQK80300	800 - 3000	0.2 / 0.4	0.5 / 0.8	2 / 5	20 / 18	1.30:1	40	113LF
MSQ80300	800 - 3000	0.2 / 0.4	0.5 / 0.8	2 / 5	20 / 18	1.30:1	40	325
DQK100800	1000 - 8000	0.8 / 1.6	1 / 1.6	1 / 4	22 / 20	1.20:1	40	326
MSQ100800	1000 - 8000	0.8 / 1.6	1 / 1.6	1 / 4	22 / 20	1.20:1	40	346
MSQ-8012	800 - 1200	0.2 / 0.3	0.2 / 0.4	2 / 3	22 / 18	1.20:1	50	226
180° (4-PORTS)								
DJS-345	30 - 450	0.75 / 1.2	0.3 / 0.8	2.5 / 4	23 / 18	1.25:1	5	301LF-1

◊ In excess of theoretical coupling loss of 3.0 dB

COUPLERS

RoHS

Model #	Frequency (MHz)	Coupling (dB) [Nom]	Coupling Flatness (dB)	Mainline Loss (dB) [Typ./Max.]	Directivity (dB) [Typ./Min.]	Input Power (Watts) [Max.] ▫	Package
KDS-30-30	30 - 512	27.5 ±0.8	±0.75	0.2 / 0.28	23 / 15	50	255 *
KFK-10-1200	10 - 1200	40 ±0.75	±1.0	0.4 / 0.5	22 / 15	150	376
KBS-10-225	225 - 400	10.5 ±1.0	±0.5	0.6 / 0.7	25 / 18	50	255 *
KDS-20-225	225 - 400	20 ±1.0	±0.5	0.2 / 0.4	25 / 18	50	255 *
KBK-10-225N	225 - 400	10.5 ±1.0	±0.5	0.6 / 0.7	25 / 18	50	110N *
KDK-20-225N	225 - 400	20 ±1.0	±0.5	0.2 / 0.4	25 / 18	50	110N *
KEK-704H	850 - 960	30 ±0.75	±0.25	0.08 / 0.2	38 / 30	500	207
SCS100800-10	1000 - 8000	10.5 ±1.5	±2.0	1.2 / 1.8	8 / 5	25	361
KBK100800-10	1000 - 8000	10.5 ±1.5	±2.0	1.2 / 1.8	8 / 5	25	322
SCS100800-16	1000 - 7800	16.8 ±1.5	±2.8	0.7 / 1	14 / 5	25	321
KDK100800-16	1000 - 7800	16.8 ±1.5	±2.8	0.7 / 1	14 / 5	25	322
SCS100800-20	1000 - 7800	20.5 ±2.0	±2.0	0.45 / 0.75	12 / 5	25	321
KDK100800-20	1000 - 7800	20.5 ±2.0	±2.0	0.45 / 0.75	14 / 5	25	322

* Add suffix - LF to the part number for RoHS compliant version.
▫ With matched operating conditions

Unless noted, products are RoHS compliant.

SYNERGY® MICROWAVE CORPORATION

Phone: (973) 881-8800 | Fax: (973) 881-8361
E-mail: sales@synergymwave.com
Web: WWW.SYNERGYMWAVE.COM
Mail: 201 McLean Boulevard, Paterson, NJ 07504

JACK BROWNE | Technical Contributor



Medical Applications Seek Wireless Solutions

THE HEALTHCARE INDUSTRY IS HOPING TO ADOPT WIRELESS TECHNOLOGY ON A LARGE SCALE, ALLOWING DOCTORS AND NURSES TO MORE EFFECTIVELY MONITOR THEIR PATIENTS' VITAL SIGNALS EVEN FROM REMOTE LOCATIONS.

MEDICAL AND INDUSTRIAL WIRELESS APPLICATIONS often involve machine-to-machine or machine-to-human communications. Typically using unlicensed frequencies in the industrial-scientific-medical (ISM) bands, these applications are considerably different from what most wireless users consider communications. Yet, these frequencies and the devices that support them are among the fastest growing applications for wireless technology—including for emerging applications in healthcare; in home and factory automation; in smart meters and wireless sensor networks; and in the wireless hospital of the future.

Most industrial and medical wireless applications are short range in nature, such as within a factory or a hospital, and many require low-power operation. *(See p. 44 for more on low-power wireless solutions.)* Other important considerations for these applications include the potential of a wireless system to interfere with other electronic systems, or itself to be subject to interference; how the choice of operating frequency translates into desired propagation characteristics; how long the system must be able to operate on a given power supply, such as a battery; the security of the transmission; and the amount of data or other content that must be transmitted and received.

The healthcare industry received a recent boost with the United States' Federal Communications Commission (FCC; www.fcc.gov) ruling to allocate additional spectrum for medical wireless applications, known as medical body area networks


(MBANs). The use of this spectrum (from 2360 to 2400 MHz) for medical applications was supported by two large companies in the electronic healthcare industry: General Electric Healthcare (www.gehealthcare.com) and Phillips Electronics NV (www.phillips.com).

However, it was opposed by an even larger aerospace company, Boeing (www.boeing.com). Since this bandwidth was already occupied by aerospace applications—notably for flight testing—Boeing had initially blocked the use of this bandwidth for medical purposes. The positive ruling for the health-care industry comes after both sides submitted a joint proposal to the FCC on how the bandwidth could be effectively shared. The FCC's rule aligns with its National Broadband Plan, which set the goal of advancing several specific "national purposes" including healthcare.

This ruling provides more available spectrum for the development of MBAN devices, typically health-sign monitors worn by a patient that detect and transmit information about a patient's vital signals to a central monitoring station. The first 30 MHz of the newly available 40-MHz bandwidth is intended for indoor use (such as in hospitals) and will be regulated. The last 10 MHz can be used in any environment, including in the home.

Prior to the availability of this bandwidth, the FCC had established several frequency bands for use by the wireless medical telemetry service (WMTS) for medical telemetry over radio, such as ECG waveforms. These bands include 608 to 614 MHz, 1395 to 1400 MHz, and 1427 to 1432 MHz. WMTS electronic devices are licensed by rule under FCC Part 95 guidelines—that is, individual licenses are not required for each product; they must only comply with the established regulations for frequency occupancy, transmitted power, spurious levels, and other parameters.

As emerging WBAN devices may still have interference problems under certain circumstances with flight-data recorders and other transmitters in their band, WMTS devices have had some history of problems with higher-power digital-television (DTV) transmitters operating within their bands, notably in the lower-frequency channels. Effective WMTS designs require adequate filtering to remove adjacent-channel interference from nearby DTV transmitters. For hospitals considering the use of such devices for wireless medical telemetry applications, organizations such as American Society for Health Care Engineering (ASHE; www.ashe.org) can offer assistance. They perform risk assessments on potential interference to and from other electronic emitters.



1. The ADF7022 transceiver IC is designed for low-power building automation applications from 868 to 869 MHz. It is supplied in a 5 x 5 mm package. [Photo courtesy of Analog Devices (www.analog.com)]

Both GE Healthcare and Phillips are major suppliers of wireless healthcare products, such as the ApexPro® CH hospital telemetry system from GE for use in the WMTS frequency bands. It is designed to provide continuous patient surveillance, operating in both the 608-to-614-MHz and 1395-to-1400-MHz bands for flexibility and scalability. Patient information is available through a variety of viewing devices, allowing hospital staff convenient monitoring of patient vital signs. Phillips offers medical telemetry solutions for both the US and Europe, such as its 2.4-GHz IntelliVue Telemetry System (not for use in the US).

A somewhat smaller medical electronics supplier specializing in wireless electrocardiogram (ECG) monitors, Great Lakes Neurotechnologies (www.glneurotech.com), has developed a lightweight monitor for reading heart, brain, and muscle electrical activity. The firm's BioRadio™ product provides 12 channels: eight for external sensors; three embedded channels for accelerometry, pulse oximetry, and pressure-based airflow; and an embedded DC auxiliary channel. The physiological monitor operates from 2400 to 2484 MHz and provides a line-of-sight (LOS) range of about 100 ft. It measures 5.25 x 2.50 x 1.10 in. and weighs 7.4 oz. with batteries. The operating voltage range can be configured from +750 μV to +2 VDC, while sampling rates can be configured from 128 to 960 Samples/s per channel. It is designed to operate continuously for 10 hrs. on batteries.


These wireless telemetry products require reliable but low-cost wireless technology, usually in the form of low-power integrated circuits (ICs). A number of IC manufacturers have responded to the needs of medical and industrial wireless electronic product developers with highly integrated transceivers capable of low-power operation in the WMTS, ISM, and other frequency bands.

Analog Devices (www.analog.com) offers a wide range of transceiver ICs for ISM-band applications through 2.4 GHz including its model ADF7021 narrowband transceiver IC for WMTS applications. It operates over frequency ranges of 80 to 650 MHz and 862 to 950 MHz supporting data rates to 32.8 kb/s by means of various modulation schemes, including two-state frequency-shift-keying (2FSK) and minimum-shift-keying (MSK) modulation. The chip can operate on voltages from +2.3 to +3.6 VDC, with only 0.1 μA leakage current in power-down mode.

This is a highly integrated device that requires only a handful of external components to fashion a complete WMTS transceiver. It features an on-chip voltage-controlled oscillator (VCO) and fractional-N frequency synthesizer, automatic frequency control (AFC) loop, and an on-chip temperature sensor with 7-b analog-to-digital converter (ADC) for readback of the sensor, as well as monitoring of battery voltage. The transceiver IC can set transmit levels from –16 to +13 dBm in 63 steps and provides receiver sensitivity of –130 dBm at 100 b/s with 2FSK and –122 dBm at 1 kb/s with 2FSK. It meets FCC Parts 15, 90, and 95 requirements

for use in the US, ARIB STD-T67 requirements for use in Japan, and ETSI EN 300 220 requirements for use in Europe. It can be used across operating temperatures from –40 to +85°C.

The company also offers a device specifically for home and building automation, its ADF7022 transceiver **(Fig. 1)**. Designed to operate at 868 to 869 MHz, it supports one-way and two-way communications at extremely low power levels. It runs on voltages of +1.8 to +3.6 VDC and consumes only 24.1 mA when transmitting at +10 dBm and only 12.8 mA in receive mode with the automatic-gain-control (AGC) circuitry active. Current consumption can be cut down as far as 0.75 µA in sleep mode. The chip is supplied in a 5 x 5 mm package.



2. The Linx NT module is designed to simplify the addition of wireless communications capabilities at ISM frequencies from 902 to 928 MHz. [Photo courtesy of Linx Technologies (www.linxtechnologies.com)]

Analog Devices also took a major step towards unleashing software-defined-radio (SDR) technology on any number of medical and industrial wireless applications. The technology allows radio frequencies and characteristics to change under software control. During the recent 2012 IEEE International Microwave Symposium (IMS) in Montreal, Canada, the company announced its collaboration with Avnet Electronics Marketing Americas (www.em.avnet.com) on the Zynq™-7000 Extensible Processing Platform (EPP), along with its own SDR kit to provide a starting point for radio developers. The kit includes the FMCOMMS1-EBZ field-programmable-gate-array (FPGA) mezzanine card from Analog Devices, facilitating wireless radio design.

Silicon Labs (www.silabs.com) offers a diverse portfolio of devices for wireless portable medical products, such as its Si446x EZRadioPro® transceiver IC family for ISM-band use in medical monitoring, industrial control, and home automation applications. The low-power transceivers offer continuous coverage from 119 to 1050 MHz. The firm also strengthened its position in ISM-band products with the acquisition earlier this year of Ember Corp. (www.ember.com) and their 2.4-GHz wireless mesh networking solutions, including the EM300 series of system-on-chip (SoC) devices. Based on the ZigBee low-power 2.4-GHz protocol, these devices combine a 2.4-GHz IEEE 802.15.4 radio transceiver with a 32-b microprocessor, Flash memory, and random-access memory (RAM).


For industrial and medical wireless system developers who want a ready-to-use wireless subsystem, Linx Technologies (www.linxtechnologies.com) offers a series of transceiver modules that can simply be added to a higher-level design and integrated with some additional programming. For example, the firm's NT module uses what the company calls its True Transparency™ interface to allow users to create a "wireless wire" for use at nonstandard data rates, with custom protocols, and user-selected encoding, such as pulse-width-modulated (PWM) or Manchester encoding. The module is completely hardware-configurable. Although programming is not required, the NT Series allows for communication and microcontroller programming over a UART connection.

The Linx NT module **(Fig. 2)** operates at ISM frequencies from 902 to 928 MHz with transmit power levels from –15.5 to +12.5 dBm and receiver sensitivity from –102 to –113 dBm, depending on bit rate. The transceiver, which can be used with frequency-shift-keying (FSK) or Gaussian FSK modulation, provides data rates from 1 to 300 kb/s. It operates on supplies of +2.5 to +5.5 VDC, and consumes 15 mA current at 0-dBm transmit power and 19.2 mA current in receive mode, with less than 1 µA current in power-down mode. It is designed for operating frequencies from –40 to +85°C. To aid developers, the module is part of a master development system complete with two boards—each populated with a transceiver module.

Anaren Integrated Radio (AIR) modules from Anaren (www.anaren.com) are designed for use as embedded or stand-alone radio transceivers for industrial control, meter reading, and building automation applications. They are based on low-power transceiver ICs from Texas Instruments (ww.ti.com) and available for ISM frequency bands of 433 MHz, 915 MHz, 2.4 GHz, as well as dual-band operation at 868 and 915 MHz. For example, model A1101R04C is an AIR module based on the model CC1101 transceiver IC from Texas Instruments. The radio module measures just 9 x 12 mm and operates from 433.05 to 434.79 MHz. It offers receiver sensitivity of –112 dBm at a data rate of 1.2 kb/s and is certified to ETSI EN 300 220 for use in European applications. It operates from a supply at +1.8 to +3.6 VDC and draws only 15 mA current in receive mode and 200 nA in sleep mode. It includes a simple-to-use serial peripheral interface (SPI) bus.

For any wireless solutions to be effective in medical environments or in long-term factory-automation applications, they must operate at low power levels. The most recent version of Bluetooth (Version 4.0) is aimed at low-power consumption, such as in medical applications. Operating in the band from 2400 to 2480 MHz, this version of Bluetooth, also known as Bluetooth Smart and Bluetooth low energy (BLE), employs a new protocol stack designed to conserve power and to provide various power-saving modes.

The official Bluetooth website (www.bluetooth.com) has declared the new standard to be the future of medical wireless applications. The research firm IMS Research (www.imsresearch.com) has projected that Bluetooth Smart will be the most dominant wireless technology for medical devices in the years to come, with more than 4.7 million medical devices shipped in 2016 with Bluetooth Smart wireless capability. Regardless of approach, it is clear that the use of wireless technology for medical and industrial applications is growing rapidly. MWRF



VERY LOW DISTORTION

MIXERS

+36 dBm IP3 2 to 3100 MHz

from $9.95 ea. qty. 1000

Mini-Circuits shielded LAVI frequency mixers deliver the breakthrough combination of very high IP3 and IP2, ultra-wideband operation, and outstanding electrical performance. By combining our advanced ceramic, core & wire, and semi-conductor technologies, we've created these evolutionary patented broadband mixers that are specially designed to help improve overall dynamic range.

With a wide selection of models, you'll find a LAVI mixer optimized for your down converter and up converter requirements. Visit the Mini-Circuits website at www.minicircuits.com for comprehensive performance data, circuit layouts, and environmental specifications. Price & availability for on-line ordering is provided for your convenience.

Check these LAVI Mixer outstanding features!

- Very wide band, 2 to 3100 MHz
- Ultra high IP2 (+60 dBm) and IP3 (+36 dBm)
- -73 dBc harmonic rejection 2LO-2RF, 2RF-LO
- Super high isolation, up to 52 dB
- High 1dB compression, up to +23 dBm
- Extremely low conversion loss, from 6.3 dB

RoHS compliant **U.S. Patent Number 6,807,407**

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

YoniQ® **The Design Engineers Search Engine** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

U.S. Patents 7739260, 7761442

IF/RF MICROWAVE COMPONENTS

451 Rev J

JACK BROWNE | Technical Contributor

Transceivers Trim Power In WPANs

These highly integrated circuits and modules are designed to provide short-range wireless networking functions, all the while using low-power sleep modes for long-term operation.

WIRELESS TECHNOLOGY, according to its basic definition, is a way to use radio waves to replace wires. For many, the premiere wireless example is cellular communications. But wireless technology also has many shorter-distance, lower-power applications; the markets are vast for short-range wireless modules and integrated circuits (ICs) for such things as monitoring, remote control, and telemetry.

Standards developed for low-power wireless use include Wi-Fi (IEEE 802.11) and ZigBee (IEEE 802.15.4), both of which can operate in the unlicensed 2.4-GHz Industrial-Scientific-Medical (ISM) band. ZigBee also makes use of other available unlicensed bands, such as 868 MHz in Europe and 915 MHz in the United States. Both standards operate by establishing simple low-power wireless personal area networks (WPANs) whether indoors or outdoors, with typically coverage distances of about 5 to 10 m and low data rates.

Industry groups have grown large around these standards, including the WiFi Alliance (www.wi-fi.org); the ZigBee Alliance (www.zigbee.org), and more specialized manufacturer organizations, such as the HomePlug Powerline Alliance (www.homeplug.org).

Although these are typically very low-power devices, they tend to be highly integrated. For example, the model ZiC2410 transceiver IC from California Eastern Labs (www.cel.com) was developed to run on a +1.5-VDC (battery) supply for automatic meter reading, medical patient monitoring, energy management, and home automation. This device is part of the company's MeshConnect lines of ZigBee low-power wireless products, which also includes larger modules. The ZiC2410 transceiver IC can transmit as much as +8 dBm power at 2.4 GHz, requiring about 45 mA current, but it uses only about 4.6 mA in typical transmit/receive operation.

The chip is compliant with ZigBee IEEE 802.15.4 specifications and contains an RF transceiver with baseband modem, hardwired medium access controller (MAC), and embedded 8051 microcontroller. It is available in a 7 x 7 mm QFN or 5 x 5 mm VFBGA package. The transceiver circuitry includes a receiver low-noise amplifier (LNA), frequency synthesizer with phase-lock loop (PLL) and voltage-controlled oscillator, crystal reference oscillator, and transmit power amplifier. The receiver can provide –98 dBm sensitivity and supports ZigBee data rates to 250 kb/s; The IC can also push data rates to 1 Mb/s for custom applications.

Although these are typically very low-power devices, they tend to be highly integrated.

The on-board synthesizer exhibits typical phase noise of –81.9 dBc/Hz offset 100 kHz from the carrier and –108.6 offset 1 MHz from the carrier. The 16-MHz crystal reference oscillator has ±10 ppm crystal frequency accuracy. The chip employs offset-quadrature-phase-shift-keying (OQPSK) modulation for reliability and only requires 0.3 µA current in sleep mode.

This is impressive integration for a device that is intended for extremely low-cost applications, such as remote control light switches as part of the wireless automated home, or for patient-monitoring applications in hospitals. But it is only one of many such ICs designed for these applications, with performance requirements differing for other parts of the world depending upon availability of unlicensed frequency bands.

The model SX1231J transceiver from Semtech (www.semtech.com), for example, is designed to meet ARIB STD-T67 (426 to 470 MHz) and ARIB STD-T108 (915 to 930 MHz) requirements for use in Japan. It is suitable for remote-keyless-entry (RKE), active radio-frequency-identification (RFID), wireless sensor networks, and industrial monitoring and control. The ARIB STD-T67 standard specifies narrow 12.5-kHz channel spacing at about 426, 449, and 469 MHz, GFSK modulation, with power output limited to +10 dBm. The ARIB STD-T108 standard defines 200-kHz channels in the 915-to-930-MHz band.

Based on the firm's TrueRF™ technology, the SX1231J transceiver features a complete frequency-synthesized ultra-high-frequency (UHF) transceiver capable of data rates to 300 kb/s using frequency-shift-keying (FSK) modulation. It includes a bit synchronizer for clock recovery and built-in temperature sensor and low battery indicator. It achieves receiver sensitivity of –120 dBm with only 16 mA cur-


When Medicine Meets Microwaves Good Things Happen

There is no room for error when people's lives and well-being depend on the reliability, accuracy and performance of the electronic medical devices you design and manufacture.

That is why manufacturers prefer MAURY Device Characterization solutions for their test and measurement needs.

MAURY is an ISO: 9001:2008/AS9100:2009 Rev C registered company for design, manufacture and service of microwave measurement and test equipment.

Amplifier performance and stability testing for wireless implanted medical devices.



Agilent Technologies
Global Solutions Partner

maurymw.com/MW_RF/index.php

Maury Microwave

Your Calibration, Measurement & Modeling Solutions Partner!

Maury Microwave Corporation • 2900 Inland Empire Blvd., Ontario, California 91764
Tel: 909-987-4715 • Fax: 909-987-1112 • Email: maury@maurymw.com

rent consumption in receive mode and about 100 nA in sleep mode.

The IC includes a fractional-N frequency synthesizer with 61-Hz resolution and 32-MHz crystal oscillator; the synthesizer requires only 80-µs wakeup time from sleep mode to achieve a locked signal. The chip runs on voltages from +1.8 to +3.6 VDC and generates typical transmit power of +13 dBm, and as much as +17 dBm. Transmitter output power can be programmed in 1-dB steps from –18 to +17 dBm. The transmitter's phase noise is typically better than –95 dBc offset 50 kHz from any carrier.

BUILT FOR THE LONG HAUL

Silicon Labs (www.silabs.com) has developed a number of low-power RF transceivers for long battery life, including the new Si446x EZRadioPro® transceiver IC family for smart meters, security and home automation systems, industrial control systems, sensor networks, and electronic shelf labels. The devices offer continuous coverage from 119 to 1050 MHz using a variety of modulation formats, including frequency-shift-keying (FSK), Gaussian-minimum-shift-keying (GMSK), and on-off-keying (OOK) modulation.

The transceivers employ a patented antenna diversity algorithm developed to counteract the effects of multipath and fading, effectively doubling the wireless range in a multipath/fading environment. They comply with Federal Communications Commission (FCC) requirements for use in the US but also meet ARIB specifications for Japan and ETSI requirements for Europe. The extended frequency coverage of the transceivers enables them to serve emerging narrowband applications such as the 151-MHz multiuse-radio-service (MURS) band in the US and the 138- and 169-MHz bands in Europe.

Designed for coin-cell battery-powered operation, the transceivers draw only 17 mA current at +10-dBm transmit power and about 13 mA current in high-performance receive mode. The transceivers have a selling price starting at $1.57 in 10,000 piece quantities.

Analog Devices (www.analog.com) supports a range of low-power wireless applications, including in home automation and health-care monitoring. For example, its model ADF7023-J transceiver operates at ISM frequencies from 902 to 958 MHz with various modulation types. These include 2FSK, GFSK, MSK, and GMSK. The model can channel data rates from 1 to 300 kb/s. As with many of these highly integrated low-power RF transceiver ICs, it uses a fractional-N PLL/VCO-based frequency synthesizer with output channel frequency resolution of 400 Hz. To reduce spurious emissions, the synthesizer's VCO operates at twice the fundamental frequency. The synthesizer is locked to an on-board 26-MHz crystal oscillator.

The unique transceiver includes both single-ended and differential transmit power amplifiers, the better to accommodate transmit antenna diversity applications. The transmit output power can be programmed from –20 to +13.5 dBm. The programmable receiver provides IF bandwidths of 100, 150, 200, and 300 kHz. The ADF7023-J transceiver is designed for supplies from +2.2 to +3.6 VDC. It has only 12.8 mA current consumption in receive mode and 24.1 mA current consumption in transmit mode, with +10 dBm transmit output power. The transceiver, which is supplied in a 5 x 5 mm LFCSP package, is ideal for applications including smart metering and wireless sensor networks.

Infineon (www.infineon.com) also addresses sub-1-GHz low-power wireless markets with several IC product families, including its PMA 71xx SmartLEWIS™ MCU line of ADK/FSK transmitters with embedded microcontroller units (MCUs). Like the CEL transceivers, these highly integrated transmitters combine an on-board 8051 microcontroller with a high-efficiency power amplifier and advanced power control system, so as to minimize power consumption when using low-voltage battery power from +1.9 to +3.6 VDC. The device operates in the 315, 434, 868, and 915 MHz frequency bands using a PLL frequency synthesizer for tuning and ASK/FSK modulator for data rates to 32 kb/s. The transmitters, which include 128-b AES encryption, draw less than 0.6 µA in power-down mode. The firm offers a separate receiver IC for use in a transceiver system.

Texas Instruments (www.ti.com) offers its model C2500 transceiver for low-power wireless applications at 2.4 GHz. In a typical system, the CC2500 is used with a microcontroller and a few additional passive components. It operates from 2400 to 2483.5 MHz with a number of different modulation schemes, including OOK, GFSK, MSK, and 2FSK modulation, for data rates of 1.2 to 500.0 kb/s. It boasts –104 dBm receiver sensitivity with only 13.3 mA current consumption from a +3-VDC supply in receive mode and 250-kb/s data rate. The chip provides programmable output power to +1 dBm and features a PLL frequency synthesizer with 90-µs settling time and phase noise of –78 dBc/Hz offset 50 kHz from any carrier and –100 dBc/Hz offset 1 MHz from any carrier.


THE PROPRIETARY PATH

In addition to devices developed for low-power wireless ZigBee and Wi-Fi applications, the ANT™ and ANT+™ specifications are proprietary wireless network protocols developed for use in the 2.4-GHz ISM band. Developed by Dynastream Innovations, Inc. [a wholly owned subsidiary of GPS receiver supplier Garmin (www.garmin.com)] as a higher-speed (to 1 Mb/s) variation of ZigBee, ANT is aimed at providing wireless functionality for sports products (such as fitness monitors).

The ANT standard is supported by semiconductor suppliers like Nordic Semiconductor (www.nordicsemi.com) and Texas Instruments with low-power transceiver ICs. Nordic's nRF24AP2-8CH device provides eight-channel ANT connectivity at 2.4 GHz. It includes the transceiver and a fully embedded ANT protocol stack for flexible serial interface with a wide range of external microcontrollers. The chip is designed for use with coin-cell batteries from +1.9 to +3.6 VDC and draws only 11 µA average current and less than 17 mA peak current during transmit mode. The firm also supplies an older, single-channel version of the chip, as well as several developer's kits. MWRF

Directional / Bi-Directional

COUPLERS



5 kHz to 12 GHz **up to 250 W** from $1.69 ea. (qty. 1000)

Looking for couplers or power taps? Mini-Circuits has 236 models in stock, and we're adding even more! Our versatile, low-cost solutions include surface-mount models down to 1 MHz, and highly evolved LTCC designs as small as 0.12 x 0.06", with minimal insertion loss and high directivity. Other SMT models are designed for up to 100W RF power, and selected core-and-wire models feature our exclusive Top Hat™, for faster pick-and-place throughput.

At the other end of the scale, our new connectorized air-line couplers can handle up to 250W and frequencies as high as 12 GHz, with low insertion loss (0.2 dB @ 9 GHz, 1 dB @ 12 GHz) and exceptional coupling flatness! All of our couplers are RoHS compliant. So if you need a 50 or 75 Ω, directional or bi-directional, DC pass or DC block coupler, for military, industrial, or commercial applications, you can probably find it at minicircuits.com, and have it shipped today!

See minicircuits.com for specifications, performance data, and surprisingly low prices!
Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

YoniQ® 2 U.S. Patents 7739260, 7761442 *The Design Engineers Search Engine finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

495 rev org

JACK BROWNE | Technical Contributor


Assemblies Combine Multiple Components

Integrated microwave assemblies allow system designers to combine multiple component functions in a single compact package, avoiding crosstalk degradation.

MICROWAVE COMPONENT MANUFACTURERS take many approaches to what are commonly known as integrated microwave assemblies (IMAs). Some tie analog components together exclusively, with others adding digital control, signal processing, and even microprocessors. But while the design philosophies applied to IMAs may vary, the intent of these multifunction modules is the same: to save space in a larger system. IMA designers typically achieve that goal with some clever architectures and packaging—in the process, shaving some of the real estate that would have been occupied by the separate components.

By their nature, most IMAs are custom designs, aimed at the needs of a specific system. By integrating multiple functions into a common housing, microwave component designers can use internal switching, integrated circuits (ICs) instead of discrete components, and monolithic microwave integrated circuits (MMICs) instead of microwave integrated circuits (MICs). This allows them to fit three or more typical component functions into one package.

Design and manufacturing of IMAs typically requires broad expertise in a range of circuit technologies, circuit-board materials, and packaging approaches. Anaren (www.anaren.com), for example, cites its experience with many different circuit technologies. These include stripline, microstrip, and printed-wire board (PWB) circuits; soft and hard circuit substrate materials over a span of dielectric-constant values; and the skills to use the appropriate software design tools, including linear circuit simulators, electromagnetic (EM) simulators, and digital design tools. The firm has designed multilayer circuits on low-temperature-cofired-ceramic (LTCC) circuit materials, featuring as many as 30 circuit layers, to economize space in a system. The design and manufacturing capabilities are backed by a full complement of electrical and environmental test systems.



Model A20-MH205 is a digital frequency discriminator that can detect the frequency of pulses as narrow as 50 ns from 6 to 18 GHz. It measures 9.17 x 5.90 x 1.00 in. [Photo courtesy of Akon (www.akon.com)]

Aethercomm (www.aethercomm.com) shows its capabilities at achieving relative high transmit powers from a small volume. Its model TR 0.24-0.39-75 transmit/receive assembly measures just 3.70 x 8.125 x 1.00 in. with SMA connectors, but delivers transmitter output power to 100 W at frequencies from 290 to 390 MHz. It includes a receiver for use from 240 to 270 MHz with 18-dB gain and 3-dB noise figure. It is designed for use with nominal input power level of 2 W, but can handle a wide range of signal levels. The rugged unit is built for harsh environments, and is equipped with DC switching circuitry that enables and disables the transmitter and receiver functions in less than 10 µs. It can operate in both continuous-wave (CW) and pulsed signal modes, handling baseplate temperatures from –40 to +71°C. DC and logic connections are accessible via a DSUB connector.

Microwave Concepts (www.microcon.com), a division of Micronetics, squeezes a number of X-band components in a hermetic phase control unit measuring just 2.35 x 1.50 x 0.38 in. with extended multipin connector. Model A228001-1 is a multifunction assembly that amplifies and divides a single X-band input signal into two phase-controlled output signals. The phase of the two output signals are independently controlled by means of both analog and digital phase shifters in each output channel. The digital phase shifters control a change of 180 deg. while the analog phase shifters control as much as 400 deg. Differential interfaces are used to control the output signal phase at high speed.

The assembly operates from 9.5 to 12.0 GHz and even provides 3 dB small-signal gain with gain flatness within 1.5 dB. The unit achieves better than 12 dB return loss with better than 5-deg. accuracy for the digital phase shifters. In addition, it has a 1-dB compression point of better than +10 dBm and draws 120 mA at +15 VDC and 20 mA at –15 VDC. It was designed for clock phase control in high-capacity data com-

FLAT GAIN AMPLIFIERS



NF *as low as* **2.5 dB, Pout** *up to* **+20.5 dBm, 800 MHz** *to* **3.8 GHz** *from* **$1.79** *ea. (qty. 1000)*

Ultra flat gain, as low as ±0.2 dB across the entire frequency range, paves the way to all kinds of applications for our new YSF amplifiers. Together, these 7 models cover the 800-3200 MHz spectrum, from cellular and satellite L bands to GPS, PCS, UMTS, and WiMAX. Whenever gain flatness and repeatability are critical, and high dynamic range (low NF and high IP3) are required, Mini-Circuits YSF amplifiers are an ideal solution.

Model No.	Freq. (MHz)	Gain (dB)	Gain Flatness (±dB)	Pout (dBm) @ Comp		Dynamic Range NF	IP3	Price $ ea.
				1dB	3dB	dB	dBm	Qty. 10
	fL-fU	Typ.		Typ.	Typ.	Typ.	Typ.	
YSF-122+	800-1200	20.4	0.2	20.5	21.3	3.4	36	2.69
YSF-2151+	900-2150	20.0	0.4	20.0	21.0	3.1	35	2.95
YSF-162+	1200-1600	20.1	0.2	20.0	21.0	3.2	35	2.69
YSF-232+	1700-2300	20.0	0.2	20.0	21.0	2.8	35	2.69
YSF-272+	2300-2700	19.0	0.7	20.0	21.0	2.5	35	2.59
YSF-382+	3300-3800	14.5	0.9	20.0	21.0	2.5	36	2.59
YSF-322+	900-3200	17.0	2.2	20.0	21.0	2.5	35	2.85

DC PWR. Voltage (nom.) 5v Current (max.) 145 mA RoHS compliant

Excellent combination of gain, noise, and distortion parameters. These amplifiers meet or exceed other key performance criteria with 20 dB gains, noise figures as low as 2.5, a 20 dBm P1dB, and a 35 dBm IP3.

They even simplify PCB configuration, with a small footprint (5 x 6 mm) and no external matching requirements. Our MSiP™ design provides the internal feedback, matching, bias, and DC blocking that make it all possible. So why wait? Place your order today, and we'll have them in your hands as early as tomorrow.



MSiP™ Mini-Circuits System In Package

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

The Design Engineers Search Engine *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

U.S. Patents 7739260, 7761442

IF/RF MICROWAVE COMPONENTS

486 rev C

munication applications such as optical long-haul data networks.

TRAK Microwave Corp. (www.trak.com) specializes in combining switches and filters in compact assemblies for harsh environments. Model SWF002 is a prime illustration of that capability—a five-channel switched C-band filter assembly in a low-profile laser-welded hermetic housing for airborne use. The compact assembly includes a TTL driver for control. It incorporates five filter spaced 500 MHz apart, with stopband rejection of 60 dB ± 500 MHz from the channel and passband insertion loss minimized to 6 to 10 dB.

This is an extremely compact unit measuring just 2.29 x 1.40 x 0.265 in. and weighing only 0.8 oz. It uses hermetic SMP connectors and EMI filtered solder pins for DC connections, and handles RF power levels to +15 dBm. Power requirements are 80 mA at +5 VDC and 30 mA at –5 VDC.

Akon (www.akonic.com) provides custom IMAs for ground-based and airborne applications, with numerous examples of its integration capabilities in standard designs such as the model A20-MH205 digital frequency discriminator **(see figure)**. It covers 6 to 18 GHz and can process CW signals as well as pulses as narrow as 50 ns. It has a dynamic range of –63 to +7 dBm and 3 MHz RMS frequency accuracy. The externally triggered frequency discriminator provides 14-b resolution of measured frequency with fast 100-ns recovery time and only 200-ns shadow time. The broadband IMA draws 200 mA at +12 VDC, 1.3 A at +8 VDC, and 250 mA at –8 VDC. It operates at temperatures from –20 to +71°C.

K&L Microwave (www.klmicrowave.com) leverages its experience in filters to design and manufacture compact filter-based IMAs, including a TTL-controlled four-channel switched filter bank in a compact aluminum housing. As one would expect from K&L, the filter performance is outstanding. With four channels centered at 2975.0, 3132.5, 3332.5, and 3527.5 MHz, the maximum passband insertion loss is only 4 dB, with maximum amplitude ripple of only 0.4 dB. Phase deviation in any channel is within 1.5 deg. The out-of-band rejection for any of the channels ranges from a minimum of 50 dB to a maximum of 80 dB. The switching speed to select a channel under TTL control is less than 1 µs.

The firm has also developed the model 4SFB-00021 switched filter bank. Designed for military and airborne applications, it handles center frequencies of 698, 730, 762, and 794 MHz using lumped-component filter designs and surface-mount component technology. Each channel provides 35-MHz bandwidth with passband insertion loss of 7.5-dB or less and out-of-band rejection of typically 60 dB.

RAISING THE STAKES

MITEQ (www.miteq.com) has leveraged its successful component designs into more complex IMAs, typically for applications in satellite communications (satcom). Because weight and size are so critical in such systems, many of MITEQ's designs attempt to integrate multiple subsystems within a single package. Among these is the model 131724 frequency downconverter, which covers three separate bands in an aluminum housing measuring 5.58 x 2.850 x 0.67 in. with SMA female connectors. It covers S-, C-, and X-band frequencies of 3.62 to 4.20 GHz, 7.25 to 7.75 GHz, 10.95 to 11.90 GHz, and 11.70 to 12.75 GHz, providing an IF output at 2 GHz. It uses local oscillator (LO) frequencies of 5.62 to 6.20 GHz at +15 dBm power level and 9.25 to 12.75 GHz at +10 to +11 dBm power level, and restricts LO leakage to –80 dBm. The downconverter achieves linear group delay of 0.01 ns/MHz maximum for any 40-MHz band, suffering 16-dB maximum conversion loss.

For upconversion, the IF-driven model SME0618LI1MD* single-sideband upconverter transforms input signals across an IF bandwidth of DC to 500 MHz to an RF output range of 6 to 18 GHz, all in a package measuring 2.50 x 2.00 x 0.50 in. The upconverter, with 9-dB typical conversion loss, works with IF input power of +10 to +16 dBm and delivers RF power of 0 to +5 dBm. Sideband suppression is typically 35 dB while carrier suppression is typically 30 dB. The upconverter is designed to handle operating temperatures from –54 to +85°C. The firm also caters to those requiring complete receivers in IMA form. The model DC-50305091-12-0 C-band receiver has an RF input range of 5031.0 to 5090.7 MHz, an LO range of 5030.94 to 5090.64 MHz, and provides an IF output of 60 kHz for further processing. The receiver supplies at least 8 dB gain with a 5.8-dB noise figure and input 1-dB compression point of –14 dBm.

The input third-order intercept point is –4 dBm. The high-speed design consists of a single-pole, four-throw (SP4T) switch to select the input band, followed by a bandpass filter, limiter, two stages of amplification, isolator, and RF mixer fed by an external LO. The receiver has settling time of only 75 µs and the time to a readable signal of only 175 µs. It draws 120 mA at +12 VDC and 60 mA at +5 VDC.

Another company with a long history in designing multifunction IMAs is Narda Microwave (www.nardamicrowave.com), with assemblies operating in the frequency range from 500 MHz to 50 GHz. As with MITEQ, many of their assemblies are for satcom applications. They may include oscillators, frequency synthesizers, mixers, switches, filters, and limiters within component-sized housings.

The firm combines different technologies—such as MICs, MMICs, and surface-mount components—within a single housing to save space without limiting performance. More recently, the company coined the terms Ultimate MIC™ and Ultimate SMT™ The former describes IMAs that combine microwave hybrid manufacturing with multilayer printed circuit boards (PCBs) using analog and digital devices and components. The latter refers to IMAs based on the integration of surface-mount components on MICs.

Additional suppliers of microwave IMAs include Aeroflex (www.aeroflex.com), Microphase (www.microphase.com), Microsemi (www.microsemi), Phase Matrix (www.phasematrix.com), Planar Monolithics Industries (PMI; www.pmi-rf.com), Shireen, Inc. (www.shireen-inc.com), Sivers IMA (www.siversima.com), and Teledyne Cougar (www.teledyne-cougar.com). MWRF


Connect Here.

For Precision, Performance & Excellence.



ROHS Compliant

Vertical Integration



Global Manufacturing


AS9100

Certified "Woman Owned"

ISO 9001-2008

LEAN Manufacturing

At Delta Electronics Manufacturing, these aren't trendy buzz words and phrases, this is our core, our culture, it's who and what we are. These concepts permeate everything we do from product inception through final inspection. But don't just take our word for it, give us a call, and experience the Delta Difference for yourself.





Connect Here.

With Delta Electronics

deltarf.com

DELTA
ELECTRONICS MFG. CORP.

Connect Here.

Delta Electronics Mfg. Corp.
Tel: (978) 927-1060 • Fax: (978) 922-6430
P.O. Box 53 • 416 Cabot St.
Beverly, MA 01915 USA


6 GHz Signal Generators

... the choice is yours !

Choosing the right signal generator is now easy — the SG386 RF Signal Generator from SRS performs like the Agilent N5181A, but sells for a fraction of the price!

The SG386 is loaded with features including a rich suite of modulation functions, computer interfaces, and optional square wave clock outputs and analog I/Q inputs.

It comes with a standard OCXO timebase that has very low aging characteristics and excellent frequency stability. And the SG386 has extremely low phase noise making it ideal in the most challenging applications.



SRS SG386

- DC to 6 GHz range
- ±0.002 ppm stability
- –116 dBc/Hz phase noise
  (1 GHz, 20 kHz offset)


$5,900



Agilent N5181A-506

- 100 kHz to 6 GHz range
- ±1 ppm stability
- –118 dBc/Hz phase noise
  (1 GHz, 20 kHz offset)

$16,373



- *2 GHz, 4 GHz & 6 GHz models*
- *AM, FM, ΦM, PM & sweeps*
- *Excellent phase noise*
- *Standard OCXO timebase*
- *Rubidium timebase (opt.)*
- *Square wave clock outputs (opt.)*
- *I/Q modulation inputs (opt.)*
- *GPIB, Ethernet & RS-232*

SG386 ... DC to 6 GHz

$5,900

DemoDirect
Free 30 day evaluation
Call (408)744-9040

SRS Stanford Research Systems

Tel: 408-744-9040
www.thinkSRS.com

XIAODONG CAO, Researcher
LEI CHEN, Researcher
CHUNHUA WANG, Professor, Doctoral Supervisor (Hunan University)
ZHANGBIN WU, Master's Degree Candidate

College of Information Science and Engineering, Hunan University, Changsha-410082, Hunan Province, People's Republic of China, wzb212808@163.com, wch1227164@sina.com


Mixer Translates Multiple Standards

This broadband frequency-upconversion mixer, which has been simulated with and without a novel linearity-enhancement circuit, is suitable for multiple-standard wireless applications from 1.0 to 10.6 GHz.

WIRELESS COMMUNICATIONS products continue to support multiple communications standards, pushing designers to develop components that can work across as many bands and standards as possible. Ideally, a single device would handle all wireless communications standards and bands. But before that day comes, it is necessary to develop components—such as upconversion mixers—that can operate with several wireless standards. By employing a cross-coupling post-distortion technique (CCPFT), it was possible to design an upconversion mixer with outstanding linearity for multiple wireless communications standards.


The mixer was simulated with commercial software, based on fabrication with a CHRT 0.18-µm silicon CMOS mixed-signal/RF semiconductor process. As will be shown, the mixer consumes only 5 mW power from a +1.2-VDC supply. It achieves a maximum input third-order intercept point (IIP3) of +16.56 dBm with 3.5 dB conversion gain (flat to within ±0.5 dB), with 10.7-dB noise figure (flat to within ±0.5 dB) across a frequency range of 1.0 to 10.6 GHz. This makes it ideally suited for software-defined radios (SDRs), as well as multiple-band ultrawideband (UWB) communications systems.[1]

An upconversion mixer should provide low noise figure with reasonable gain and high linearity while consuming low power to be effective in modern multiple-standard wireless transmitters. Such mixers have been developed, including the 3.0-to-5.1-GHz upconversion mixer of ref. 2 designed with a current-reuse technique to minimize power consumption. It delivers 3.8-dB gain and 8.4-dB noise figure, but only –7.6-dBm IIP3. In ref. 3, a 1.0-to-11.0-GHz upconversion mixer was proposed, with an adopted fold structure and inductor-free matching network. Although its IIP3 reaches +12 dBm, the conversion gain is below 0 dB (–6 dB).




1. This schematic circuit diagram shows the proposed upconversion mixer for use from 1.0 to 10.6 GHz.

In ref. 4, a 3.0-to-5.0-GHz upconversion mixer with current-reuse bleeding technique was presented. It achieves 6.5-dB conversion gain and IIP3 of +11.6 dBm. However, its power dissipation is 11.0 mW, and the mixer has a very complicated structure. In ref. 5, a 6.0-to-8.0-GHz upconversion mixer was proposed which uses a feedback loop in its transconductance stage. It achieves 0-dB conversion gain and 7.0 dB noise figure, but its



2. This simple diagram provides the conceptual idea of the mixer's linearization technique.



3. This is a small-signal equivalent circuit diagram of the proposed upconversion mixer.


linearity is not mentioned. From these reference examples, it is apparent that tradeoffs were made between linearity and other performance parameters.

For high upconversion-mixer linearity without sacrificing the other key mixer performance parameters, it is necessary to apply some linearization techniques. Numerous circuit linearization techniques have been developed for low-noise amplifiers (LNAs). One commonly used method is the derivative superposition technique.[6,7] It employs auxiliary transistors biased via weak inversion, which produces a nonlinear current to cancel out the third-order intermodulation generated by the main transistors. This approach is mainly effective at lower frequencies and can induce additional gate noise. Recently, a post-distortion technique[8] and a cross-coupling post-distortion technique[9,10] were implemented for LNA linearization. Both methods yielded IIP3 performance levels exceeding +10 dBm without seriously degrading the other key LNA parameters.

For multiple-standard wireless communications applications, a low-voltage upconversion mixer was developed using a pseudodifferential double-balanced structure, allowing for high isolation between ports while operating with low supply voltage. It also employs a current-bleeding topology for improved noise and linearity performance.[11] A cross-coupling post-distortion technique was also adopted to further improve IIP3. The added linearization circuitry does not increase the size of the mixer, nor does it degrade conversion gain, noise figure, or power consumption.

Figure 1 shows a schematic circuit diagram for the UWB multiple-standard mixer, with a structure that is an improvement over a Gilbert-cell double-balanced mixer. Transistors M1 and M2 comprise the input pseudo-differential transconductance pairs. Transistors M1a and M2a employ weak inversion biasing. They form the cross-coupled post-distortion structure, which generates the nonlinear current needed to cancel the third-order intermodulation distortion generated by M1 and M2. Capacitors C1 and C2 are coupling capacitors, while transistors M3, M4, M5, and M6 work as switches. Transistors M7 and M8 serve as current sources to improve the noise and linearity performance of the whole circuit by adjusting the bias current. Resistors R1 and R2 are load resistors, while inductors L1 and L2 are useful for increasing the conversion gain at the upper edge of the desired frequency range.


The linearity of a Gilbert-cell mixer is determined mainly by its transconductance stage.[12] As a result, post-distortion linearization is implemented on the pseudo-differential transconductance stage (**Fig. 2**). To explain the basic operating principle of this approach, reactive components must be ignored in this analysis and all device pairs considered to be without mismatches. Then the drain current of each transistor can be represented as a power-series expression, with a gated-source voltage provided by transistors. For simplicity, the output current, i_{out+} of the left half-circuit composed of transistors M1 and M1a is considered first. The drain currents of those two transistors can



4. This chip layout is based on a commercial 0.18-μm silicon CMOS mixed-signal/RF process.



Get Connected...



Emerson Network Power Connectivity Solutions has a wide range of cable assemblies and connectors suited for RF, Microwave and Fiber Optic signal transmission. Connectivity Solutions is a vertically integrated supplier of custom, fixed length and semi rigid cable assemblies from DC to 50 GHz. Our product lines deliver custom-engineered products and solutions to satisfy the most demanding and complex requirements.


Emerson Connectivity Solutions products support wire line and wireless communications, data networking, test and measurement, telecomm, broadcast, medical, military, aerospace and industrial applications.

EmersonConnectivity.com
Toll free: 800-247-8256
Phone: 507-833-8822


Connectivity Solutions

EMERSON
Network Power

EMERSON. CONSIDER IT SOLVED.™



5. These traces show the simulated conversion gain of the upconversion mixer, with and without linearization.



6. These plots show the simulated noise figure of the upconversion mixer, with and without linearization.

be modeled as Eqs. 1-4:

$$i_1 = g_1 v_1 + g_2 v_1^2 + g_3 v_1^3 \quad (1)$$

$$i_{1a} = g_{a1} v_4 + g_{a2} v_4^2 + g_{a3} v_4^3 \quad (2)$$

$$i_2 = -g_1 v_1 + g_2 v_1^2 - g_3 v_1^3 \quad (3)$$

$$v_4 = -i_2 R_{ON} = a v_1 + b v_1^2 + c v_1^3 \quad (4)$$

where:

R_{ON} = the switch on resistance of the switch pair;

$a = R_{ON} g_1$;

$b = R^{ON} g^2$; and

$c = R^{ON} g^3$;

The two nonlinear currents i_1 and i_{1a} add at node v_3, yielding output current i_{out+}:

$$i_{out+} = i_1 + i_{1a} = (g_1 + a g_{a1}) v_1 + (g_2 + a^2 g_{a2} + b g_{a1}) v_1^2 + (g_3 + c g_{a1} + 2ab g_{a2} + a^3 g_{a3}) v_1^3 \quad (5)$$

The third-order derivative g_3 in Eq. 1 is a dominant source of third-order intermodulation distortion, which limits the linearity of a mixer. To improve the linearity, g_3 should be minimized without reducing the fundamental transconductance, g_1. The differential transistor pair M1 and M2 is biased in strong inversion, which has a negative third-order derivative g_3. Therefore, the third-order nonlinearity provided by the cross-coupling post-distortion canceller FET should be positive, which requires biasing FETs M1a and M2a in the weak inversion region. From Eq. 5, it can be seen that current i_{1a} partially cancels both the second- and third-order terms of current i_1.

A time-varying Volterra series can be used at high frequencies to analyze the high-frequency inter-modulation performance of the proposed mixer. The mixer's distortion is induced by the switching and transconductance stages. Reference 12 provides a detailed analysis of the intermodulation distortion of the switching pairs. The effectiveness of the applied linearization is determined mainly by the transconductance stage. For simplicity in this analysis of the mixer, distortion due to the switch pairs has been neglected. The parasitic capacitance and resistance of two auxiliary transistors, except the gate-source capacitance, have also been ignored in the analysis. **Figure 3** shows a version of the mixer schematic diagram for use in high-frequency distortion analysis. This is limited to a third-order analysis, assuming a weakly nonlinear circuit. The expression for IIP3 is given by a Volterra series analysis as follows[13]:

$$IIP3 = \frac{1}{6R_s \cdot |H(\omega)| \cdot |A_1(\omega)|^3 \cdot |\varepsilon(\Delta\omega, \omega_1 + \omega_2)|} \quad (6)$$

where:

$$H(\omega) = \frac{1 + j w C_{gs}(R_s + R_p) + j\omega C_{gd} R_s}{g_1' - j\omega C_{gd}[1 + R_p(g_1' + j\omega C_{gs})]} \quad (7)$$

$$A_1(\omega) = \frac{1}{g_1' + g(\omega)} \cdot \frac{1 + j\omega C_{gd} Z_1(\omega)}{Z_2(\omega)} \quad (8)$$

$$\varepsilon(\Delta\omega, \omega_1 + \omega_2) = g_3' - g_{OB} \quad (9)$$

$$g_1' = g_1 - a g_{a1} \quad (10)$$

$$g_3' = g_3 - c g_{a1} - 2ab g_{a2} - a^3 g_{a3} \quad (11)$$

$$g_{OB} = \frac{2(g_2')^2}{3}\left[\frac{2}{g_1' + g(\Delta\omega)} + \frac{1}{g_1' + g(\omega_1 + \omega_2)}\right] \quad (12)$$

$$g_2' = g_2 + b g_{a1} + a^2 g_{a2} \quad (13)$$

$$g(\omega) = \frac{1 + j\omega C_{gd}[R_s + Z_1(\omega)] + j\omega C_{gs}[R_s + Z_2(\omega)]}{Z_2(\omega)} \quad (14)$$

$$Z_1(\omega) = \frac{1}{j\omega C_{db}} // \{[(Z_M + Z_L) // \frac{1}{j\omega C_{gsa}}] + R_a\} \quad (15)$$

See Eqs. 16 and 17, p. 57.

where:

Z_M = the equivalent impedance of the switch transistor and

Z_L = the equivalent impedance of the load.

Equations 9 through 16 imply that the mixer's linearity (IIP3 or OIP3) is determined by g_1', g_3', and g_{OB}. Parameter g_{OB} represents the combined effect of the second-order nonlinearity generating the second-order intermodulation product,

HI-REL LIMITERS

BLOCK HIGH LEVEL RF INTERFERENCE ... PROTECT YOUR LOW NOISE RECEIVERS.



500 kHz to 7GHz from $9.95 qty.10-49

Need to protect a low-noise receiver that will be operating in a hostile environment? These limiters offer excellent protection against ESD, power surges and unwanted high-level signals—without the tradeoff of high insertion loss. And these limiters react nearly instantaneously (as fast as 2 ns response time, 10 ns recovery time) and work over a very broad band.

With an insertion loss as low as 0.23 dB typical, these hi-rel, wide-band limiters provide protection against high level signals from +5 dBm to +36 dBm input. The power out of the limiter is as low as 0 dBm typical, thus protecting the sensitive devices connected to the limiter output. *The surface mount RLM series* is housed in a miniature plastic case, 0.25" x 0.31" x 0.17", while the *VLM SMA connectorized series* is housed in a rugged, patented unibody package for easy connection to sensitive devices following the limiter.

Data sheets, performance curves, measurement data, and environmental specifications are available on our website, *minicircuits.com.* So why wait, order on our website and get delivery as quickly as the next day.

Unibody patent 6,943,646 ***RoHS compliant.***

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®


ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661


YoniQ® U.S. Patents 7739260, 7761442 ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

480 rev C



7. These curves show the simulated IIP3 versus RF output, where the RF output is fixed at 10.61 GHz.



8. These curves plot the simulated IIP3 of the upconversion mixer across the full RF range, with and without linearization.

which is then mixed with the fundamental tones, yielding the third-order products.[13] This self-interaction is due to the multiple feedback in the circuit mainly by the gate-drain capacitance.[13]

From Eqs. 12-15 it can be shown that the values of $|H(\omega)|$, $|A_1(\omega)|$, and $|\varepsilon(\Delta\omega, \omega_1 + \omega_2)|$ decrease when the cross-coupling post-distortion technique is implemented in the Gilbert-cell mixer. For this reason, the proposed mixer achieves higher linearity than a double-balanced mixer using a traditional current-bleeding technique. The analysis for the proposed mixer can be confirmed by simulation results shown in **Figs. 7 and 8**.

Noise at the output of the upconversion mixer is caused mainly by the channel thermal noise and the flicker noise of the transconductance stage, and the thermal noise generated in the switching pair and the load.

Because the noise from a transistor is proportional to its transconductance, the noise contribution from the auxiliary transistor is very small and can be neglected in an analysis. The noise figure of the proposed upconversion mixer can be calculated by Eq. 17[14]:

See Eq. 17, next column.

where the quantities α, c, G, and G^2 are evaluated with the bias current of each switch pair and symbols γ_1 and γ_5 represent noise factor γ for transistors M1 and M5, respectively. Parameter K is a coefficient used in the analysis.

Computer simulations on the upconversion mixer were performed with the aid of the Cadence Spectre program from Cadence Design Systems (www.cadence.com) and using the CHRT 0.18-µm mixed-signal/RF CMOS process from Singapore's Chartered Semiconductor Manufacturing Ltd. **Figure 4** shows a layout of the upconversion mixer, which occupies an area of 0.75 × 0.5 mm.

It was evaluated with local-oscillator (LO) input power of +1 dBm, intermediate-frequency (IF) input power of –30 dBm, with the IF fixed at 10 MHz and the LO frequency swept from 1.0 to 10/.6 GHz. The simulated conversion gain was found to be within ±0.5 dB of 3.5 dB, as shown in **Fig. 5**. For the noise figure shown in **Fig. 6**, the IF was also fixed at 10 MHz and the LO frequency swept from 1.0 to 10/.6 GHz, with the simulated results showing noise figure of better than 10 dB across most of the frequency range.


Figure 7 shows simulated IIP3 versus RF output frequency. At 10.61 GHz, the simulated IIP3 performance is +16.56 dBm. For **Fig. 8**, the IIP3 is shown across the full RF range, with the LO frequency swept from 1.0 to 10.6 GHz. The table summarizes the performance of the proposed upconversion mixer,

$$Z_2(\omega) = R_p + j\omega C_{gd}[R_s R_P + R_s Z_1(\omega) + R_p Z_1(\omega)] \quad (16)$$

$$NF = \frac{\alpha}{c^2} + \frac{2\left(\gamma_1 + \gamma_{g1} g_{m1} + \frac{K}{\alpha f g_{m1}^2}\right) g_{m1}\alpha + 4\gamma_5 \overline{G} + 4\gamma_{g5}\overline{G^2} + \frac{1}{R_L}}{c^2 g_{m3}^2 R_5} \quad (17)$$

Comparing recent developments in upconversion mixers

Reference	This work	2	3	4	5
Bandwidth GHz)	1.0 to 10.6	3.1 to 5.0	1.0 to 11.0	3.1 to 5.0	6.0 to 8.0
Noise figure (dB)	10.2 to 11.1	8.4	N/A	12.0 to 13.0	7.0
Gain (dB)	3.0 to 4.0	3.8	-6.0	6.5	0.03
IIP3 (dBm)	+2.5 to +16.56	-7.6	12.0	11.6 to 13.8	N/A
Supply (V)	1.2	1.5	1.8	1.0	1.8
Power (mW)	5.0	1.95	25.0	11.0	4.2
Size (mm)	0.75 x 5.00	0.6 x 0.6	0.5 x 0.6	0.86 x 0.6	0.64 x 0.64



HYBRID FINITE ELEMENT – INTEGRAL EQUATION

- Ideal combination of FE and IE solvers
- Provides ideal, open truncation
- Efficient solution for large radiating and scattering problems



HIGH-PERFORMANCE COMPUTING

- Distributed Solve for fast, parallel parametric analysis
- HFSS HPC for large scale, 3D EM field simulation
- Multiprocessing for faster simulation throughput

HFSS®


THE GOLD STANDARD FOR 3D FULL-WAVE ELECTROMAGNETIC FIELD SIMULATION


HFSS SOLVER ON DEMAND

- Streamlined, quick and easy HFSS model setup
- Links to popular EDA layout for package and board simulations
- Add HFSS accuracy to circuit and system simulations

HFSS TRANSIENT

- Conformal Finite Element Transient solver
- Higher and mixed order mesh elements
- Local time-stepping scheme
- Innovative implicit/explicit scheme for fine geometric detail





ANSYS delivers accuracy, productivity and computational power with HFSS 13.0, the industry leading 3D full-wave electromagnetic field simulation software. With HFSS' new Hybrid Finite Element - Integral Equation solver users can achieve unparalleled accuracy for large radiated and scattering far-field problems such as antenna platform integration. HFSS' new finite-element based Transient solver is ideal for ground-penetrating radar, electro-static discharge, EMI and time domain reflectometry studies. The new Solver on Demand capability allows users to quickly create models directly for chip, package and board designs, simplifying model creation and bringing the accuracy and power of HFSS to a layout design environment.

To learn more about HFSS 13.0 and how ANSYS can help you outdistance yourself from your RF, microwave and high speed electronics competitors visit www.ansys.com.

ANSYS®

comparing it to other reported mixers. The mixer proposed here achieves higher linearity than these other mixers, with lower operating voltage.

In summary, the simulations for an upconversion mixer based on a commercial 0.18-µm CMOS process show good results when applying a post-linearization technique to enhance linearity at low voltage levels. The mixer, which draws only 5 mW power from a +1.2-VDC supply achieves peak IIP3 of +16.56 dBm while also providing conversion gain of 3.5 dB. It is designed for use from 1.0 to 10.6 GHz and is suitable for multiple-standard wireless and UWB communications applications. MWRF

ACKNOWLEDGMENTS

The authors would like to thank the Science and Technology Planning Project of Hunan Province No.2010FJ4246 and the Fundamental Research Funds for the Central Universities NO.531107040269 for financially supporting this research.

REFERENCES


1. S.S.K. Ho and C.E. Saavedra, "A CMOS Broadband Low-Noise Mixer With Noise Cancellation," IEEE Transactions on Microwave Theory and Techniques, Vol. 58, No. 5, May 2010, pp. 1126-1132.
2. Giuseppia Sapone and Giuseppe Palmisano, "A 0.25-µm CMOS Low-Power Up-Conversion Mixer for 3.1-5 GHz Ultra-Wideband Applications," Research in Microelectronics and Electronics, Ph.D. disseration, September 2006, pp. 457-460.
3. Pin-Cheng Huang, Fong-Cheng, et al., "A Miniature, Folded-Switching, Up-conversion Mixer for UWB Applications Using 0.18-µm CMOS Process," 2007 IEEE Radio Frequency Integrated Circuits Symposium, September 2007, pp. 501-504.
4. Wen-Shan Hxiao and Zhi-Ming Lin, "A 1-V, 11.6-dBm IIP3 Up-Conversion Mixer for UWB Wireless System," 52nd IEEE International Midwest Symposium on Circuits and Systems, August 2009, pp. 1042-1046.
5. Dalenda Ben Issa, Abdennaceur Kachouri, and Mournir Samet, "Design And Optimization of Up-Conversion CMOS Mixer For UWB Application. 6th International Multi-conference on Systems, Signals and Devices, March 2009, pp. 1-4.
6. Jiming Jiang and D. M. Holburn, "Design and analysis of a low-power highly linear mixer," European Conference on IEEE Circuit Theory and Design 2009 (ECCTD 2009), August 2009, pp. 675-678.
7. Tae Hwan Jin and Tae Wook Kim, "A 5.5-mW 9.4-dBm IIP3 1.8-dB NF CMOS LNA Employing Multiple Gated Transistors With Capacitance Desensitization," IEEE Transactions on Microwave Theory and Techniques, Vol. 58, 2010, pp. 2529-2538.
8. Heng Zhang, Xiaohua Fan, and E.S. Sinencio, "A Low-Power, Linearized, Ultra-Wideband LNA Design Technique," IEEE Journal of Solid-State Circuits, Vol. 44, No. 2, February 2009, pp. 320-330.
9. Tae-Sung Kim and Byung-Sung Kim, "Linearization of Differential CMOS Low Noise Amplifier Using Cross-Coupled Post Distortion Canceller," 2008 IEEE Radio Frequency Integrated Circuits Symposium, June, 2008, pp. 83-86.
10. Gholamreza Zare Fatin, Ziaddin Daei Koozehkanani, and Henrik Sjoland, "A 90-nm CMOS +11 dBm IIP3 4 mW Dual-Band LNA for Cellular Handsets," IEEE Microwave and Wireless Components Letters, Vol. 20, No. 9, September 2010, pp. 513-515.
11. Farid Touai, Skandar Douss, and Mourad Loulou, "A 0.35-µm CMOS Mixer for 3.1-4.8 GHz UWB MB-OFDM Receivers," 14th IEEE International Conference on Electronics, Circuits and Systems, December 2007, pp. 1220-1223.
12. Manolis T. Terrovitis and Robert G. Meyer, "Inter-modulation Distortion in Current-Commutating CMOS Mixers," IEEE Journal of Solid-State Circuits, Vol. 35, No. 10, October 2000, pp. 1461-1473.
13. Bonkee Kim, Junb-Su Ko, and Kwyro Lee, "Highly Linear CMOS RF MMIC Amplifier Using Multiple Gated Transistors and its Volterra Series Analysis," 2001 IEEE MTT-S International Microwave Symposium Digest, Vol. 1, pp. 515-518.
14. Manolis T. Terrovitis and Robert G. Meyer, "Noise in current-commutating CMOS mixers," IEEE Journal of Solid-State Circuits, Vol. 34, No. 6, June 1999, pp. 772-783.

TTE® America's Filter Specialist Since 1956 www.tte.com



315P series of **Combline Bandpass Filters ship 3 weeks ARO!**

Specify any Center Frequency (Fo) from 900MHz to 6000MHz
Insertion Loss at Fo 1.8dB maximum
1dBc minimum passband bandwidth is 1.5% of Fo
-50dBc minimum at 0.937*Fo and at 1.058*Fo
SMA female connectors standard
Overall size varies with Fo
1 unit less than $600



www.tte.com • 310.478.8224 • AMERICAN EXPRESS MasterCard VISA

NASREDDINE BENAHMED
Professor of Microwaves

ABDELKADER BENKADDOUR
Assistant Professor of Electronics


FETHI TARIK BENDIMERAD
Professor of Communications Systems

NADIA BENABDALLAH
Assistant Professor of Physics

Create UWB Filters With Coaxial Cables

With the aid of a commercial EM simulator, sliced coaxial cables can be used to design and fabricate a bandpass filter with performance suitable for high-power UWB communications applications.

ULTRAWIDEBAND (UWB) communications offers great promise for voice, video, and high-data-rate transmissions, although key components will be needed for such systems. One of those components is the bandpass filter. Although traditional bandpass filters are designed and fabricated in planar form, it is also possible to create a UWB version using coaxial cables and coupled structures. The design approach is straightforward and the filter design can be readily analyzed by means of commercial electromagnetic (EM) simulation software.



1. This is a cross-sectional view of the coupled line with sliced coaxial cables used to form the UWB bandpass filter.


Coaxial cables, of course, vary widely in electrical and mechanical properties, with some cables capable of excellent phase stability with temperature and flexure and some being more sensitive to variations in amplitude and phase performance with temperature. The use of coaxial cable for constructing a bandpass filter requires an understanding of the mechanical requirements for an antenna as well as the electrical charactertics of the cable, such as the power-handling capabilities and the relative dielectric constant, in order to achieve a desired characteristic impedance for the filter.

Although they differ from traditional planar circuits, coupled sliced coaxial cables are high-frequency transmission lines that can support a variety of compact circuits, including directional couplers and RF/microwave power dividers. For example, they have been used to build a microwave directional coupler.[1] This kind of coupler has excellent performance in terms of high directivity, low VSWR, good isolation, excellent electromagnetic-interference (EMI) shielding, and high power-handling capability. Furthermore, since it is based on commercial semi-rigid coaxial cables and eliminates a mechanical housing, it is low in cost.[2,3]

Figure 1 shows the cross-section of a coupled line with sliced coaxial cables. The cable is assumed to be lossless with an inner conductor of radius r_c and an outer conductor of radius r_b. Dielectric material with relative dielectric constant ε_r fills the inside of the cable. A portion of each cable is cut out and two cut cables are used to form a coupled line (**Fig. 2**). The cut depth, u, as represented by h on the cross-sectional diagram can be found by the following equation:

$$u = \cos^{-1}(h/r_b)/\cos^{-1}(r_c)/r_b)$$

In ref. 4, a numerical tool under the FreeFEM (www.FreeFEM.org) environment[5] was used to analyze the electromagnetic (EM) parameters for sliced coaxial cables. This numeri-




2. These views depict (a) a three-dimensional schematic representation and (b) a longitudinal section of the proposed UWB bandpass filter.

Although they differ from traditional planar circuits, coupled sliced coaxial cables are high-frequency transmission lines that can support a variety of compact circuits, including directional couplers and power dividers.


cal tool can be easily adapted to study any other transverse-electromagnetic (TEM) or quasi-TEM structures.[6] Also, the authors proposed rigorous analytical expressions for the primary parameters, including the inductance (L) and capacitance (C) matrices and the impedances of the even and odd modes for sliced coaxial cables, Z_{0e} and Z_{0o}, respectively.[7]

The analytical expressions—deduced from rigorous analyses by means of finite-element-method (FEM) and method-of-moments (MoM) approaches under the FreeFEM and LINPAR[8] environments, respectively—are convenient for all coupled sliced coaxial cables with a wide range of cut depths and outer-to-inner conductor radius ratios between 1.4 and 15. The authors proposed other analytical expressions[9] to calculate the dimensions of sliced coaxial cables used to form compact microwave couplers at the characteristic impedances of 50 and 75 Ω typically used for low-loss transmissions in RF/microwave and cable-television (CATV) systems, respectively. Using these analytical expressions, an analysis can be readily implemented in modern commercial CAE software tools for the design of microwave and wireless components.

Since the release of the frequency band from 3.1 to 10.6 GHz for commercial purposes by the US Federal Communications Commission (FCC),[10] UWB technology has sparked a great deal of interest for its potential in that band. Compact bandpass filters are essential components for UWB systems, but so far only planar structures have been reported for use in low power applications.[11-15] As an alternative approach, the authors propose a novel and a simple compact UWB bandpass filter using sliced coaxial cables, convenient for high power applications requiring a small filter footprint. The filter can be easily designed and fabricated using the Transient Solver[16] contained in CST MICROWAVE STUDIO® (CST MWS) from Computer Simulation Technology (www.cst.com) or other commercial EM software.



3. This sliced coaxial coupler is used to build the UWB filter.



4. This curve reveals the effect of the frequency on the coupling coefficient of the coupler of Fig.3.


The design of the UWB filter is based on the use of impedance steps and coupled-line sections. A center frequency of around 6.85 GHz was selected, with bandwidth between 3.1 and 10 GHz. The insertion loss amounts to around 0.33 dB with better than 11.25 dB return loss across a wide frequency range (4.0 to 9.5 GHz). Simulated results show better than 20-dB stopband rejection performance to 12.5 GHz. For this bandpass filter with center frequency of 6.85 GHz and with a substrate with relative dielectric constant, ε_r, of 2.03, the sliced coaxial-cable filter is extremely compact, measuring only 6 × 8.04 × 33.4 mm.

Figures 2(a) and 2(b) show a three-dimensional (3D) schematic representation and longitudinal section, respectively, of the proposed UWB bandpass filter, assuming 50-Ω external feed lines. The filter structure includes an isolated sliced coaxial cable in the middle and a coupled line with sliced coaxial cables at the two ends.[17] To achieve the UWB passband, the three sections of this filter are arranged with lengths of one-quarter, one-half, and one-quarter wavelength (λ/4, λ/2, and λ/4) as indicated in **Fig. 2(b)**.

As part of this study on UWB coaxial-cable bandpass filters, the authors examined the design of an UWB filter with characteristic impedance of 50 Ω having an inner conductor of radius r_c = 1 mm, outer conductor of radius r_b = 3 mm, and relative dielectric constant of ε_r = 2.03. The cut depth, u, was varied from 0.90 to 0.99 to achieve a coupling coefficient of less than 5 dB for the sliced coaxial coupler **(Fig. 3)**.

FILTER SOLUTIONS

DC to 15 GHz



Over 300 Models IN STOCK ...Immediate Delivery! from $1.99 ea. 10-49

Different needs demand different technologies, and the Mini-Circuits RF/microwave filter lineup delivers. Over 300 proven solutions, from DC to 15 GHz, are standing by, ready to ship. High-pass or low-pass, band-pass or band-stop, in coaxial, surface-mount, or plug-in packages. Across the board, our filters achieve low insertion loss and low VSWR in the passband and high attenuation in the rejection band. Just go to minicircuits.com for more information. If you need a specific performance and want to search our entire model database, including engineering models, click on Yoni2, our exclusive search engine.

In Yoni2, you can enter the response type, connection option, frequency, insertion loss, or any other specifications you have. If a model cannot be found, we understand the sense of urgency. So contact us, and our engineers will find a quick, cost-effective, custom solution and deliver simulation results within a few days.

Yoni2® U.S. Patent 7739260, 7761442 ***The Design Engineers Search Engine...*** *finds the model you need, Instantly.*

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

Yoni2® U.S. Patents 7739260, 7761442 ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

484 Rev B


Building upon previous works based on FEM analysis, a coupling coefficient of 2 dB was obtained for a coaxial cable cut depth, h, of 1.02 mm. It yielded a characteristic impedance of approximately $(Z_{0e} \times Z_{0o})^{0.5} = 23.4\ \Omega$ and the following primary EM parameters:

$$[L] = \begin{bmatrix} 182.0 & 143.7 \\ 143.7 & 182.0 \end{bmatrix} \text{ (nH/m)}$$

$$[C] = \begin{bmatrix} 330.5 & -261.1 \\ -261.1 & 330.5 \end{bmatrix} \text{ (pF/m)}$$

For a length of one quarter wavelength, i.e., $l = \lambda/4$, and to verify that the designed coupler has a coupling coefficient of less than 5 dB from 3.1 to 10.6 GHz, the coupling coefficient of the sliced coaxial coupler of **Fig. 3** was plotted versus frequency in **Fig. 4**, using the CST MWS Transient Solver. From these results, it appears that the coupling coefficient varies between 3.4 to 6.15 dB for that frequency range.

For the middle line of the UWB bandpass filter represented in **Fig. 5**, the outer conductor radius, r_b, the cut depth, h, and the dielectric constant, ε_r, were kept constant, with values of 3 mm, 1.02 mm, and 2.03, respectively, while the inner conductor radius, r_c, was varied to achieve a characteristic impedance, Z_0, of 18 Ω, for the middle line. This value of Z_0 was obtained for $r_c = 2.1$ mm, yielding inductance and capacitance per unit length of 85.55 nH/m and 263.67 pF/m, respectively.[4,6]




5. The middle line of the proposed UWB bandpass filter shows the energy distribution through the surrounding dielectric material, with the goal of achieving a characteristic impedance of 18 Ω.

The CST MWS Transient Solver was applied to check the predicted electrical performance of the proposed filter characterized by the features marked in **Fig. 6. Figure 7** provides plots of the simulated scattering parameters (S-parameters) for the filter from 1.0 to 12.5 GHz. These simulated responses are in reasonable agreement with measured and simulated results of planar bandpass filter structures. They also meet the requirements for high-power UWB applications per the FCC. The simulated results indicate passband insertion loss of about 0.33 dB with return loss of better than 11.25 dB from 4.0 to 9.5 GHz. The stopband rejection is better than 20 dB for frequencies to 12.5 GHz.


There are no numerical or experimental results in the scientific literature for this type of UWB filter based on the use of sliced coaxial cables. To check the results obtained by the CST MWS Transient Solver, it was necessary to "calibrate" those results by comparison with simulation results generated by other commercial software simulation tools. To accomplish this task, the authors performed simulations for the same geometrical and physical parameters using previous works and estimating the resulting scattering parameters of the UWB filter using MATPAR software.[18] MATPAR is a software package that allows a use of MATLAB software from MathWorks (www.mathworks.com) to enlist paralallel computers for large analysis problems. Such extensions provide a dramatic increase in processing speed, sometimes as much as 30 times faster than running MATLAB on a single computer.

The results for coefficients S_{11} and S_{12} as functions of frequency for the proposed UWB filter structure are provided in **Fig. 8. Figures 7 and 8** show that the responses obtained by the two numerical models (the CST and MATPAR software simulations) are in a good agreement. Although this comparison of simulations from two different software programs is not as valid as comparing the modeled simulation results to the measured results obtained from the analysis of a prototype filter, it does indicate that the basic design parameters for the filter are sound and should yield actual performance that is relatively close to either of the simulated performance plots.


In summary, sliced coaxial cables can be used to form a wideband bandpass filter capable of handling high power levels



6. This longitudinal section shows the geometrical characteristics of the designed UWB bandpass filter.



7. These plots show how simulation software can help in the study of an UWB bandpass filter using sliced coaxial cables.



8. These scattering parameters of the designed UWB BPF were obtained using commercial math analysis software.


in a relatively small footprint. The filter, which measures just 6.00 x 8.04 x 33.40 mm, was fabricated by means of impedance steps and coupled-line sections. It was designed with the aid of the CST Transient Solver software, although other commercial EM simulation software programs can also be used with similar success. The compact bandpass filter features a broad bandwidth ranging from 3.1 to 10.0 GHz with better than 11.25 dB return loss and about 0.33 dB insertion loss over a large portion of its total passband. The design is inherently low in cost due to its humble material requirements and realtively simple to fabricate once dimensions are calculated. MWRF

ABDELKADER BENKADDOUR, Assistant Professor of Electronics, *(e-mail: abd1ben@yahoo.fr)* **NASREDDINE BENAHMED**, Professor of Microwaves, *(e-mail: n_benahmed@yahoo.fr)* **NADIA BENABDALLAH**, Assistant Professor of Physics, *(e-mail: n_benabdallah@yahoo.fr)* **FETHI TARIK BENDIMERAD**, Professor of Communications Systems, *(e-mail: ftbendimerad@gmail.com)* University of Tlemcen, Laboratory of Telecommunications (LTT), P.O. Box 119, (13000) Tlemcen, Algeria

REFERENCES

1. H. An, O. Monti, R.G. Bossio, and K. Wu, "A novel type of low cost high performance coaxial cable coupler," 25th European Microwave Conference (EuMG'95), 1995.
2. H. An, R.G. Bossio, and K. Wu, "Ultra wide band directional couplers with coaxial cable," Canadian Conference on Electronics And Computer Engineering, 1995.
3. H. An, T. Wang, R.G. Bossio, and K. Wu, "Accurate closed form expression for characteristic impedance of coupled line with sliced coaxial cable," IEE 1995.
4. N. Benahmed and M. Feham, "Finite element analysis of RF couplers with sliced coaxial cable," Microwave Journal, Vol. 43, No. 11, November 2000, pp. 106-120.
5. www.Freefem.org.
6. N. Benahmed, M. Feham, and M. Kameche, "Finite element analysis of planar couplers," Applied Microwave & Wireless, Vol.12, No. 10, October 2000, pp. 28-38.
7. N. Benahmed and M. Feham, "Rigorous analytical expressions for electromagnetic parameters of transmission lines: Coupled sliced coaxial cable," Microwave Journal, Vol. 44, No. 11, November 2001, pp. 130-138.
8. A.R. Djordjevic, M.B. Bazdar, and T.K. Sarkan, LINPAR for windows: Matrix parameters of multiconductor transmission lines, Software and user's manual, Artech House, Norwood, MA, 1999.
9. N. Benabdallah, N. Benahmed, S. Seghier and R. Bouhmidi, "Sliced coaxial cables form compact couplers," Microwaves and RF, Vol. 46, No. 7, July 2007, pp. 90-94.
10. FCC, "Revision of Part 15 of the Commission's Rules Regarding Ultra-Wideband Transmission System," Technical Report ET-Docket 98-153, 14 February 2002.
11. A. Saito, H. Harada, and A. Nishikata, "Development of bandpass filter for ultra wideband (UWB) communication," in Proceedings of the IEEE Conference on Ultra Wideband System Technology, 2003, pp.76-80.
12. L. Zhu, S. Sun, and W. Menzel, "Ultra-wideband (UWB) bandpass filters using multiple-mode resonator," IEEE Microwaves and Wireless Components Letters, Vol. 15, No. 11, Nov. 2005, pp. 796-798.
13. J. Gao, L. Zhu, W. Menzel and F. Bögelsack, "Short-Circuited CPW Multiple-Mode Resonator for Ultra-Wideband (UWB) Bandpass Filter," IEEE Microwave and Wireless Components Letters, Vol. 16, No. 3, March 2006, pp. 104-106.
14. M. Meeloon, S. Chaimool, and P. Akkaraekthalin, "Broadband bandpass filters using slotted resonators fed by interdigital coupled lines for improved upper stopband performances," International Journal of Electronic Communications (AEU) (2008).
15. D. Kaddour, J.D. Arnould, and P. Ferrari, "Miniaturized semi-lumped UWB bandpass filter with improved out-of-band performances," Microwave Journal, Vol. 53, No. 10, October 2010.
16. www.CST.com.
17. W. Menzel, L. Zhu, K. Wu, and F. Bogelsack, "On the design of novel compact broadband planar filters," IEEE Transactions on Microwave Theory & Techniques, Vol. 51, No. 2, 2003, pp. 364-370.
18. A.R. Djordjevic, M. Bazdar, G. Vitosevic, T. Sarkar, and R.F. Harrington, Scattering parameters of microwave networks with multiconductor transmission lines, Artech House, Norwood, MA, 1990.


ANGLES
"UNLIMITED"
Right Angles
Bulkhead Cable Jacks
(1=2)



	N Right Angle Jack	N rev Pol Angle Jack	TNC Right Angle Jack	TNC rev Pol Agle Jack	N Right Angle SS 18GHz
RG 55	#	#	#	#	–
RG 58	#	#	#	#	–
RG 141	#	#	#	#	–
RG 142	#	#	#	#	–
RG 223	#	#	#	#	–
Sig 195*	#	#	#	#	–
Sig 240*	Δ	Δ	Δ	Δ	–
LMR 195*	#	#	#	#	–
LMR 240*	Δ	Δ	Δ	Δ	–
HP 450	–	–	–	–	#
HP 500	–	–	–	–	#
LA 190	–	–	–	–	Δ
LA 290	–	–	–	–	Δ
RFD 190	–	–	–	–	Δ
RFD 191	–	–	–	–	Δ
RFD 290	–	–	–	–	Δ

#, in stock or in production
Δ, in current development

45 deg Angle



SMA JxSMA (ss)
RFD 3186-3536 (Stock)

*Registered trademarks of respective owners

RF Depot.com Inc.
7850 Browning Road • Pennsauken NJ 08109
Tel. 856-488-2000
Toll Free 877-RF Depot

ZHE CHEN Ph.D. Candidate
WEI HONG Professor
JIANYI ZHOU Professor
JIXIN CHEN Professor

State Key Laboratory of Millimeter Waves, School of Information Science and Engineering, Southeast University, Nanjing 210096, People's Republic of China; (86)15062259338, e-mail: zhechen@emfield.org (Zhe Chen)

Transmitter/Receiver Manages MIMO

This high-performance, low-cost two-way transmitter and receiver design employs MIMO techniques to achieve high-data-rate transmissions at 8 GHz.


FAST DATA transfers usually require large bandwidths. But the use of multiple-input, multiple-output (MIMO) antenna techniques can also boost data rates for available bandwidths, as shown with this high-performance two-way transmitter and receiver design operating with a 100-MHz bandwidth at 8.05 GHz. It boasts excellent performance, with a receiver noise figure of 2.7 dB and transmitter output power of +17 dBm at 8.05 GHz and associated third-order intermodulation (IM3) level of –41.4 dBc. In addition, the MIMO-based system achieves measured error-vector-magnitude (EVM) performance of 9.07% for an 83.3-MSymbol/s quadrature-phase-shift-keying (QPSK) signal and 6.24% for an 83.3-MSymbol/s 16-state quadrature-amplitude-modulated (16QAM) signal.

Expectations are high for fast data access in both fixed and mobile wireless applications. According to the International Telecommunications Union (ITU), fourth-generation (4G) wireless communications networks should support data rates to 1 Gb/s for low-mobility applications and 100 Mb/s for high-mobility applications.[1] To meet these requirements, advanced technologies are needed, including high-level modulation schemes, orthogonal frequency division multiplexing (OFDM), and MIMO techniques, and the channel bandwidth should be at least 100 MHz.[2-5] However, most existing communications standards employ no more than 20 MHz bandwidth.[6] The most desirable RF/microwave bandwidths, below 6 GHz, are already well occupied, so that next-generation wireless applications are expected to operate in the next higher-frequency available bands from 6 to 15 GHz,[7] where continuous multiple 100-MHz channel bandwidths are available.

To explore the possibilities for high-data-rate wireless communications in that 6-to-15-GHz band, a two-way transmitter and receiver for use with MIMO wireless techniques at 8.05 GHz were designed and implemented.

Figures 1(a) and (b) show block diagrams of the two-way MIMO transmitter and receiver, respectively. The subsystems employ a classic superheterodyne transceiver architecture. The center frequency of the transmitting and receiving IF signal is set at 850 MHz, with a bandwidth of 100 MHz. The required RF specifications for the transmitter and receiver are listed in **Tables 1(a) and (b),** respectively.

For the two-way transmitter and receiver, the local oscillator (LO) is comprised of a phase-lock-loop (PLL) frequency synthesizer. To meet the high linearity requirement listed in **Table 1(a)**,



1. These block diagrams show (a) the two-way transmitter and (b) the two-way RF receiver.



Smart RF SWITCH MATRIX

DC to 18 GHz from $385.00

Increased efficiency for almost any electronics lab.
Nothing beats a Mini-Circuits Switch Matrix for quick production or design lab setups. Our innovative, stand-alone GUI is so user-friendly, you'll put it to work within minutes! Highly portable, and compatible with most lab software,* these models also add capabilities to legacy systems with ease—for full automation, step-by-step control, or remote operation via the internet.

To meet different needs, we offer different models containing up to four 50 Ω SPDT switches, all of which are absorptive in the "off" state. Whichever model you choose, and wherever you use it, you'll enjoy the quick expansion of multi-unit and multi-parameter capabilities, and easily configured test automation that simply helps you get more done more quickly, and at a lower cost, than ever before.

Outstanding performance, unmatched reliability.
Very low insertion loss (≤0.3 dB typ.), excellent isolation (>66 dB typ.), and low VSWR (1.2:1 typ.) across the full DC-18 GHz frequency range mean accurate data, with fewer false rejects and less retesting. The rugged aluminum cases house our patented mechanical switches—the only ones available anywhere, at any price, that offer up to 10 years and 100 million cycles of guaranteed performance.† Just go to minicircuits.com for technical specifications, performance data, pricing, and real-time availability, and ***consider how much time and money you'll save*** with faster setup, quick automation, and results you can rely on, day after day and year after year!

*See data sheet for an extensive list of compatible software.

†The mechanical switches internal to each model are offered with an optional 10 year extended warranty. Agreement required, see data sheets on our website for terms and conditions. Switches protected by patents 5,272,458 6,650,210 6,414,577 7,633,361 7,843,289 and additional patents pending.

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

YoniQ® 2 *The Design Engineers Search Engine finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com


U.S. Patents 7739260, 7761442

IF/RF MICROWAVE COMPONENTS

a passive mixer, which requires +17 dBm LO drive power, is used for the receiver, and an LO drive amplifier is used with each mixer. To meet the conversion gain requirement of the two-way transmitter, an intermediate-frequency (IF) amplifier and two RF power amplifiers cascaded together are also used.

For the two-way receiver, a low-noise amplifier (LNA) with adequate gain helps meet the noise-figure requirements for the downconversion signal chain listed in **Table 1(b)**. Following downconversion, a low-noise IF amplifier is added to provide suitable conversion gain, and to minimize the impact of the following stage on the noise figure of the receiver.

System-level simulations were carried out for the RF transmitter and receiver using Advanced Design System (ADS) software from Agilent Technologies (www.agilent.com). All the RF bandpass filters in the two-way transmitter and receiver were based on substrate-integrated-waveguide (SIW) techniques,[8-10] for suppressing image signals, LO signals, and other interference. The SIW filters are low in cost and compatible with standard printed-circuit-board (PCB) fabrication methods. The SIW filters are designed and simulated with the help of the full-wave High-Frequency Structure Simulator (HFSS) electromagnetic (EM) simulation software from Ansoft Corp. (www.ansys.com). Simulation results are shown in **Fig. 2**.



2. These simulation results show the performance of a SIW bandpass filter, such as those used in the two-way transmitter and receiver.

Table 1(a): Specifications for the two-way transmitter

Parameter	Specification
Operating band	8.0 to 8.1 GHz
Channel bandwidth	100 MHz
Conversion gain	≥22 dB
Gain flatness	≤2.5 dB
Amplitude unbalance	≤1 dB
Transmit third-order intermodulation (at +17-dBm output power)	≤–40 dBc

Table 1(b): Specifications for the two-way receiver

Parameter	Specification
Operating band	8.0 to 8.1 GHz
Channel bandwidth	100 MHz
Conversion gain	≥26 dB
Gain flatness	≤2.5 dB
Amplitude unbalance	≤1 dB
Noise figure	≤3 dB




Following the simulations, the two-way RF transmitter and receiver designs were fabricated and integrated on PCBs. A frequency-control module was also included, to control the PLL frequency. **Figure 3** shows photographs of the fabricated prototypes.

The measured performance of the two-way transmitter and receiver (RF = 8.0 to 8.1 GHz, LO = 7.2 GHz, IF = 800 to 900 MHz) includes the output power of the transmitter (when the IF input power = –5 dBm), the conversion gain of the receiver, and the IM3 product of the transmitter (when the output power = +17 dBm). Detailed measured results are listed in the **Tables 2(a) and (b)**.

To measure the overall performance of the transmitter and receiver as a communications system, a test system consisting

of the prototype transmitter and receiver was constructed to measure the EVM performance. **Figure 4** shows a schematic diagram for the EVM measurement setup. The frequency-conversion plan was: RF = 8.0 to 8.1 GHz, LO = 7.2 GHz, IF = 800 to 900 MHz. In the test setup, a model SMBV100A vector signal generator from Rohde & Schwarz (www.rohde-schwarz.com) was modulated with in-phase/quadrature (I/Q) signal generated by an N8241A arbitrary waveform generator (AWG) from Agilent Technologies.



3. These prototype circuits show (a) the two-way transmitter and (b) the two-way receiver.

The modulated IF signal is first upconverted by the transmitter, then sent through an appropriate attenuator (to simulate path loss), and then downconverted by the receiver. The resultant IF signal is demodulated and analyzed by a model 89600 vector signal analyzer (VSA) from Agi-

Table 2(a): RF measurement results for the two-way transmitter

Parameter	Specification
Center frequency	8.05 GHz
Conversion gain	24.6 dB
Gain flatness	1.8 dB
Amplitude unbalance	0.3 dB
Transmit third-order intermodulation (at +17-dBm output power)	–41.4 dBc

Table 2(b): Specifications for the two-way receiver

Parameter	Specification
IF center frequency	850 MHz
Conversion gain	28.6 dB
Gain flatness	0.6 dB
Amplitude unbalance	0.8 dB
Noise figure	2.7 dB

DaisyRS
Remote Solutions
PORTABLE POWER METER
Innovative. Convenient. Practical



The RS2026 Portable Power Meter is the first of its kind.
Featuring a wireless interface between the remote power unit and the handheld display, the RS2026 is an innovative solution for any portable power meter application

- Portable, lightweight and self-contained operation requiring no computer or other hardware.
- Easy and convenient to use
- Quick measurement and exceptional performance
- Wireless interface with 2.4 GHz iSM band and a range of up to 100 meters
- HandHeld and Remote units are battery powered or by Micro USB cable.


The RS2026 is designed with a patent pending algorithm that provides exceptional performance and accuracy. Unlike large or bulky laboratory instruments with troublesome cables, the RS2026 employs wireless technology making it lightweight, fast and convenient with an intuitive GUI interface for quick setup and measurement. The RS2026 is convenient and practical for outdoor field use by installation and maintenance engineers yet equally suited for laboratory or manufacturing applications.

DaisyRS, Inc. 2095-60 Ringwood Ave., San Jose, CA 95131 (408) 273-3735 **www.daisyrsi.com**

lent Technologies to determine the EVM. During the measurement process, several baseband signals with different modulation types and symbol rates were applied.

Figure 5 shows measured EVM results for a 20-MSymbol/s baseband signal applied with modulation of (a) QPSK, (b) 16QAM, and (c) 256-state quadrature amplitude modulation (256QAM). Under those three modulation conditions, the measured EVM values were 2.02%, 1.16%, and 1.06%, respectively. To test the wideband performance of the transmitter and receiver, an 83.3-MSymbol/s (with occupied bandwidth of 92.5 MHz) baseband signal was applied with the following modulation formats: (a) QPSK and (b) 16QAM, with resulting EVM of 9.07% and 6.24%, respectively. The measured EVM results are shown in **Fig. 6.** The measured results show that the two-way MIMO communication system can support high spectrum efficiency and high data rate communications with low EVM.

In summary, low-cost, high-performance two-way transmitter and receiver designs were developed for use at 8.05 GHz. They support high data rates over a 100-MHz bandwidth using MIMO techniques. Measurements reveal low EVM for reliable high-data-rate performance with high spectral efficiency. MWRF



4. This diagram shows key instruments in the EVM test setup.


ACKNOWLEDGMENTS

This work was supported in part by the NSFC under Grant No. 60921063, and in part by the National Science and Technology Major Project of China under grants No. 2010ZX030007-02-01 and 2011ZX03004-003.


REFERENCES

1. Z. Yu, J. Zhou, J. Zhao, and W. Hong, "Design of a Wideband RF Receiver for the Next-Generation Wireless Communication System," 2009 Asia-Pacific Microwave Conference, Singapore, December 2009, pp. 465-468.
2. A.J. Paulraj, D.A. Gore, R.U. Nabar, and H. Boelcskei, "An Overview of MIMO Communications—A Key to Gigabit Wireless," Proceedings of the IEEE, Vol. 92, No. 2, 2004, pp. 198-218.
3. T. Kaiser, A. Wilzeck, M. Berentsen, and M. Rupp, "Prototyping for MIMO systems: an Overview," in Proceedings of the 12th European Signal Processing Conference (EUSIPCO '04), Vienna, Austria, September 2004.
4. J. Thanysen and K. B. Jakobsen, "Checking capacity for MIMO configurations," Microwaves & RF, Vol. 46, No. 6, 2007, pp. 74-82.
5. J. Browne, "Measuring MIMO Performance Levels," Microwaves & RF, Vol. 49, No. 7, 2010, p. 102.
6. M. Sauter, Beyond 3G – Bring Networks, Terminals and the Web Together: LTE, WiMAX,





5. Test system EVM was measured with 20-MSymbols/s signals with the following modulation: (a) QPSK, (b) 16QAM, and (c) 256QAM.



6. The experimental system EVM was measured with 83.3 MSymbols/s and baseband signals with: (a) QPSK and (b) 16QAM.

IMS, 4G Devices and the Mobile Web 2.0, Wiley, New York, 2009.
7. J. Walko, "Mobile Operators Under Pressure in Barcelona-3GSM report," Picochip EETimes Europe, February 1-March 4, 2007.
8. D. Deslande, and K. Wu, "Integrated microstrip and rectangular waveguide in planar form," IEEE Microwave Component Letters, Vol. 11, No. 2, 2001, pp. 68-70.
9. Z.C. Hao, W. Hong, J.X. Chen, X.P. Chen, and K. Wu, "Compact Super-Wide Bandpass Substrate Integrated Waveguide (SiW) Filters," IEEE Transactions on Microwave Theory and Techniques, Vol. 53, No. 9, 2005, pp. 2968-2977.
10. H.J. Tang, W. Hong, et al., "Development of millimeter-wave planar diplexers based on complementary characters of dual-mode substrate integrated waveguide filters with circular and elliptic cavities," IEEE Transactions on Microwave Theory and Techniques, Vol. 55, No. 4, 2007, pp. 776-782.

CUSTOMIZED DESIGN QUOTES IN 24 HOURS
www.pulsarmicrowave.com
DC-85 GHz
PULSAR
MICROWAVE CORPORATION
25 Years of Service
Power Dividers, DC-60 GHz
2-32 Way
Directional Couplers
Single and Dual, to 60 GHz
High Power, to 2500 watts
Hybrids, to 40 GHz
90° & 180°
Attenuators, to 18 GHz
Digital, Analog, Linearized
Bias Tees, to 85 GHz
30 KHz to 85 GHz
Switches, to 18 GHz
SP1T-SP8T
High Power Combiners
to 500 watts
Also Available
Phase Shifters, DC Blocks, Mixers, Modulators, and Image Reject Mixers
RoHS Compliant
48 Industrial West, Clifton, NJ 07012 | Tel: 973-779-6262 | Fax: 973-779-2727 | sales@pulsarmicrowave.com


WANG YAWEI Doctor
WANG GUANGMING Professor
LIANG JIANGANG Associate Professor

Microwave Laboratory, Mailbox No. 25, Sanyuan Shaanxi Province, 713800, People's Republic of China; corresponding author: Wang Yawei, e-mail: wywafeu@163.com

Tiny Spiral Spans 1.4 To 10.0 GHz

This miniature arm-width-tapered ATARSA features tapered antenna arms, enabling excellent broadband axial ratio and reflection coefficient, as well as a significant reduction in size.

ANTENNAS FOR BROADBAND and multiple-standard communications must provide excellent performance in a small area. While a spiral antenna can provide consistent radiation patterns, the size reduction is often a problem, since the antenna's design is related to the physical wavelengths of the operating frequencies. Fortunately, a miniaturized arm-width-tapered Archimedean spiral antenna (ATARSA) has been designed that delivers outstanding performance in a size that is dramatically reduced compared to conventional spiral antennas.




1. This photograph shows a prototype of the ATARSA.

The arms of the antenna are tapered to maintain self-complementarity, helping to achieve that good performance in a small size. Comparing the results of computer simulations and measurements (which agree closely), the ATARSA offers reflection coefficient and axial ratio of –10 dB and 3 dB, respectively, from 1.4 to 10.0 GHz. It features a 73.1% reduction in area compared to a typical Archimedean spiral antenna designed for the same frequency band.


Spiral antennas have long been appreciated for their stable input impedance and radiation characteristics (excellent gain, axial ratio, and radiation patterns) over several octaves. The tradeoff has been their large size when designed for low-frequency operation. As a result, a variety of techniques have been developed to reduce the size of a spiral antenna. One of the most efficient methods is to add loads to the ends of the antenna.[1-10] Reactance loading can greatly decrease the phase velocity along the arms of the antenna, helping to reduce the size of the antenna by 50%.[1]

Resistance loading[2,3] and the use of microwave absorber materials[4-6] have also been used for size reductions in spiral antennas, but they weaken the current at the ends of the antenna arms—helping to achieve lower-frequency operation in a smaller antenna size, but with a sacrifice in gain performance. Tapered spiral lines have been used, as detailed in refs. 7-10, in order to improve the low-frequency response of a spiral antenna by reflecting the current from the ends of the antenna arms. As ref. 7 explains, making a tapered line thinner and with more windings on a fixed radius helps to miniaturize a spiral antenna with enhanced performance at low frequencies.

Up until now, tapered spiral lines have been applied mainly to the ends of equiangular spi-



2. This schematic diagram shows the basic construction of the ATARSA with its precisely defined spiral curves.



3. The ATARSA's width tapered antenna arm can be modeled with these parameters.



Smart SYNTHESIZED SIGNAL GENERATORS 250-4000 MHz

WOW! only $1995.00 ea.


Rugged, portable, production test workhorses

Sweep or hop across wide frequency and power bands, use a pair for third-order intercept tests, or slip one into your laptop case and take it on the road! Our easy-to-use GUI will have you up and running in minutes. Compatible with most test software,* they add capabilities and increase efficiency, all without busting your budget!


*See data sheets for an extensive list of compatible software.

Accurate, reliable results at high speed

Signals within 1 ppm for frequency and 0.25 dBm for power, low harmonics, a resolution of 5 kHz, and 5-msec settling times help you get the data you need from complex, high-speed testing plans. Just go to minicircuits.com for specifications, performance data, and everything you need to make your choice — and get it in your hands as soon as tomorrow!



Frequency and power hopping.



Low spurious.

Model	Frequency (MHz)	Power (dBm)	Harmonics (dBc typ.)	Price ($ ea.)
SSG-4000HP	250-4000	-50 to +20	-40	1995.00
SSG-4000LH	250-4000	-60 to +10	-66	2395.00

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

YoniQ2® U.S. Patents 7739260, 7761442
The Design Engineers Search Engine *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com
IF/RF MICROWAVE COMPONENTS

ral antennas rather than Archimedean spiral antennas (ARSAs)[8-10] in attempts to achieve size reductions. The tapered lines have typically degraded or destroyed the self-complementarity of the antennas, limiting the amount of impedance matching possible at the cost of low-frequency performance.


To overcome these limitations, a new method was developed for tapering the arms of an ARSA while also preserving the self-complementarity of the design. **Figure 1** shows an ATARSA, designed for an operating frequency range of 1.58 to 10.00 GHz; it has an outer diameter of only 53 mm. The small size is achieved by a combination of thin tapers and increased number of windings. The antenna is backed by an absorber-loaded cavity to enhance its unidirectional operation. This eliminates back-side radiation without decreasing the frequency band of operation, although at some loss of efficiency. An exponentially tapered microstrip balun is employed as a balanced feed for the antenna.

When an ATARSA is designed, the self-complementarity of an ARSA is maintained in a transition area **(Fig. 2)**. Archimedean spiral curves are defined by the function $r = r_0 + a\phi$ where r_0 is the original radius of the spiral line, a is the spiral constant, and ϕ is the winding angle (derived from the starting angle, ϕ_{st} and the ending angle, ϕ_{end}). The width of the Archimedean spiral lines must be $a\pi/2$ when a two-arm self-complementary ARSA is built.


In **Fig. 2**, the inner area is fully filled without any overlap by duplicating a self-complementary Archimedean spiral line (called ARSL1) at every 90-deg. rotation. The second self-complementary Archimedean spiral line, ARSL2, begins at the ϕ_{end} of ARSL1. Its outer boundary curve is flush with that of the inner area and its inner boundary curve is flush with the outer boundary curve of the inner winding area after a 90-deg. winding. In this way, it can fill the outer area. The width of ARSL2 (w_2) is smaller than the width of ARSL1 (w_1), so the arm width is tapered and the self-complementary structure of the ATARSA is preserved.

The miniature ATARSA was modeled by understanding its mechanical construction. Its antenna arms consisted of ARSLs with four different widths **(Fig. 3)**. If these four ARSL "subantennas" are considered as ARSL1, ARSL2, ARSL3, and ARSL4, then ARSL1 was formed with four windings with width of 1 mm, ARSL2 was constructed with three windings 0.5 mm wide, ARSL3 with two windings each 0.25 mm wide, and ARSL4 with two windings each 0.125 mm wide. There were 11 windings in the antenna aperture, the outer diameter of which is 53 mm. To achieve good matching behavior, the original radius of ARSL1 was chosed as 1 mm. The ATARSA was fabricated from a circular substrate with relative dielectric constant of 4.3 in the z direction at 10 GHz and thickness of 1 mm.


Continued on p. 73.



4. These plots reveal (a) the impedances of the ATARSA and a typical ARSA and (b) the S_{11} behavior of the ATARSA with and without a balun.




5. These plots compare the axial ratios of the ATARSA with a typical ARSA.



6. The measured S_{11} performance of the ATARSA is plotted here.

The characteristic impedance of a two-arm ATARSA simulated alone is shown in **Fig. 4(a)**, together with the characteristic impedance of a typical self-complementary ARSA with arm width and outer diameter of are 1 mm and 53 mm, respectively. According to basic ARSA design principles, the wavelength of the lowest frequency of operation will be determined by the formula $C \geq 1.5\lambda$, where C is the circumference of the antenna aperture and λ is the wavelength of the lowest operating frequency. By this formula, the lowest frequency of operation for the miniature ATARSA is 2.7 GHz. But from **Fig. 4**, it is possible to find that real and imaginary parts of the ATARSA's impedance change more gradually over frequency than those of an ARSA. The imaginary part of the ATARSA's impedance changes more approximately to zero, likely because of the better self-complementary structure of the ATARSA than the ARSA. As a result, the ATARSA provides excellent reflection coefficient characteristics with impedance chose for 100Ω across the full operating band **[Fig. 4(b)]**. An exponentially tapered microstrip balun was used as the feed for the ATARSA. **Figure 4(b)** shows the simulated results for S_{11} when the ATARSA is fed by that balun, with S_{11} better than –10 dB from 1.3 to 10.0 GHz.




7. The measured axial ratio of the ATARSA is shown here.

The performance of the spiral antenna was evaluated by simulating and measuring its axial ratio, a parameter that assigns a value to the ratio of an antenna's electric field strength in its two major axes. For an antenna with radiating field that is perpendicular to the direction of propagation, the electric field magnitude is generally reprsented by an ellipse which can be characterized by the axial ratio. An antenna's polarization can be linear, circular, or elliptical where, in the first two cases, a plot of the antenna's electric field appears as a straight line or a circle, respectively. The polarization in turn can be characterized as rotating in a clockwise direction, and being designated as right-hand polarization, or rotating in a counterclockwise direction, and being called left-hand polarization.

Figure 5 offers another comparison between the axial-ratio performance of a typical ARSA and the novel ATARSA. The ATARSA shows excellent performance in terms of circular polarization. According to the simulations of axial ratio, the ATARSA works well with circularly polarized signals in the frequency range from 1.4 to 10.0 GHz.

For the prototype, the ATARSA was etched onto a 1-mm-thick, copper-laminated dielectric substrate with permittivity of 4.3. The antenna was backed by a cavity full of microwave absorber material to improve directivity. Measurements were performed with a commercial microwave vector network analyzer (VNA), with results shown in **Fig. 6**. The measured results show good antenna performance from 1.4 to 10.0 GHz, correlating well with the simulated results.

Figure 7 shows the axial ratio of the ATARSA in the main direction of radiation. The plot reveals the excellent broadband characteristics of the antenna. The VNA-measured results, while not exactly matching the simulated data




8. These plots show radiation patterns at several frequencies: (a) 1.4 GHz, (b) 3.0 GHz, (c) 6.0 GHz, (d) 9.0 GHz.

of **Fig. 5,** do track the broadband axial-ratio behavior of the simulations, indicating stable performance from 1.4 to 10.0 GHz. **Figure 8** shows radiation patterns for four different frequencies (1.4, 3.0, 6.0, and 9.0 GHz). The antenna design appears to do well with circular polarization, with reasonable performance at the low-frequency operating limit of 1.4 GHz. This compares to the lowest frequency of operation for a typical ARSA of about 2.7 GHz. The ATARSA essentially achieves a 73.1% reduction in antenna aperture area in contrast with a typical ARSA working in the same frequency band.

In conclusion, by tapering the arm width of the antenna along an increasing winding angle, it was possible to design a self-complementary Archimedean spiral antenna with miniature dimensions but with good low-frequency performance. This difficult-to-achieve low-frequency response combines with the antenna's high-frequency capability for a continuous, wideband radiation pattern. The simulations and measurements of a prototype ATARSA shows excellent performance from 1.4 to 10.0 GHz, with significantly more effective miniaturization than reported in refs. 8-10.

Virtual VNA

Real Performance. Real Value.



PLANAR 804/1
Vector Network Analyzer
300 KHz - 8.0 GHz

Frequency and time domain measurements, fixture simulation, gating, and mixer testing capabilities – all standard.

Other models available at
www.coppermountaintech.com

COPPER MOUNTAIN
TECHNOLOGIES


ACKNOWLEDGMENTS

The authors would like to thank the support from National Natural Science Foundation of China under Grant No. 60971118. Thanks are also due to the reviewers for their valuable comments. MWRF

REFERENCES

1. B.A. Kramer, C.-C. Chen, and J.L. Volakis, "Size reduction of a low-profile spiral antenna using inductive and dielectric loading," IEEE Antennas and Wireless Propagation Letters, Vol. 7, 2008, pp. 22-25.
2. Zhu Yu-xiao, Zhong Shun-shi, and Xu Sai-qing, "Miniaturized compound spiral slot antenna." Microwave and Optical Technology Letters, Vol. 50, No. 11, 2008, pp. 2799-2801.
3. M.W. Numberger and J.L. Volakis, "New termination for ultra-wideband slot spirals," IEEE Transactions on Antennas and Propagation, Vol. 50, No. 1, 2002, pp. 82-85.
4. H. Nakano, S. Sasaki, H. Oyanagi, et al., "Cavity-backed Archimedean spiral antenna with strip absorber," IET Microwaves Antennas & Propagation, Vol. 2, No. 7, 2008, pp. 725-730.
5. H. Nakano, K. Kikkawa, Y. Iitsuka, et al., "Equangular spiral antenna backed by a shallow cavity with absorbing strips," IEEE Transactions on Antennas and Propagation, Vol. 56, No. 8, 2008, pp. 2742-2747.
6. Hisamatsu Nakano, Tatsuya Igarashi, Hiroshi Oyanagi, et al., "Unbalanced-mode spiral antenna backed by an extremely shallow cavity," IEEE Transactions on Antennas and Propagation, Vol. 57, No. 6, 2009, pp. 1625-1633.
7. J.A. Kaiser, "The Archimedean two-wire spiral antenna," IRE Transactions on Antennas and Propagation, Vol. 8, No. 3, 1960, pp. 312-323.
8. Song Zhao-hui, Qiu Jing-hui, and Li Hong-mei, "Novel planar complex spiral ultra-wideband antenna," 2004 4th International Conference on Microwave and Millimeter Wave Technology Proceedings. Beijing, 2004, pp. 35-38.
9. Zhu Yu-xiao, Zhong Shun-shi, Xu Sai-qing, and Zhang Li-na, "Design of miniaturized planar spiral antenna and its wideband balun," Journal of Shanghai U., Vol. 14, No. 6, 2008, pp. 581-584.
10. Ya-wei Wang, Guang-ming Wang, and Zhong-wu Yu, "Design of a highly miniaturized compound spiral antenna," 2010 ISSSE. Nanjing, pp. 494-496.

If You Can't Find The Power You Need Here, It Doesn't Exist.



Traveling Wave Tube Amplifiers

"T" Series–CW TWTA's from 1 to 45 GHz. 15 to 2000 watts.
"TP" Series–Pulsed TWTA's from 1 to 18 GHz. 1000 to 10,000 watts.

When it comes to the largest selection of Traveling Wave Tube (TWT) Amplifiers, AR has no equal. We cover a wider range of high-power, broadband amplifiers for your specific test application than any other brand.

CW models also have the capability to faithfully reproduce AM, FM, and pulse modulation input signals. Features that are included at no extra cost are our "Sleep mode" which prolongs the tube life, rugged construction for the rigorous treatment in test labs, modular supplies to reduce repair turn-around, and well thought out digital displays to help you monitor essential amplifier conditions.

So before you choose a look-alike traveling wave tube amplifier, examine all the features and benefits that come along at no extra charge with an AR amplifier. If you want a TWTA that will take you farther, you'll choose the one with the AR logo on it ... the company that stands behind our products with the global service and support that you demand.

To learn more, visit www.arworld.us or call us at 215-723-8181.

www.arworld.us/twta

ISO 9001:2008
Certified

rf/microwave instrumentation

Other ar divisions: modular rf • receiver systems • ar europe

USA 215-723-8181. For an applications engineer, call 800-933-8181.
In Europe, call ar United Kingdom 441-908-282766 • ar France 33-1-47-91-75-30 • emv GmbH 89-614-1710 • ar Benelux 31-172-423-000

www.arworld.us

Copyright © 2012 AR. The orange stripe on AR products is Reg. U.S. Pat. & TM. Off.

YUE AISHUAI Master
ZHAI DAILIANG Master
LIANG JIANGANG Associate Professor
YANG ZIMU Master

Microwave Laboratory, Mailbox No. 24, Sanyuan Shaanxi Province, 713800, People's Republic of China; corresponding author: Yang Zimu, e-mail: yzmmmmmm@126.com

Compact Monopole Sleeve Antenna Reaches 11.8 GHz


The use of a sleeve and ladder-shaped ground-plane structures helps to widen the impedance bandwidth of a planar monopole antenna, while also reducing the dimensions of the low-cost circuit.

ANTENNAS FOR ultrawideband (UWB) must exhibit wide operating bandwidth, but also small size for use in a variety of electronic devices. A monopole planar sleeve antenna may meet those requirements with a broad frequency range extending almost to 12 GHz. It consists of symmetrical strips and a ground plane on the same side, using a coplanar-waveguide (CPW) structure on low-cost FR-4 dielectric substrate material with relative dielectric constant of 2.95 and thickness of 1.6 mm. This antenna is suitable for worldwide interoperability for microwave access (WiMAX) applications.


Numerous types of antennas have been proposed for UWB applications.[1,2] Among the various types of UWB antenna designs proposed, the planar monopole antenna is particularly promising: It can provide uniform radiation fields and be integrated seamlessly with other electronic devices.[3,4]

Ground-plane effects play strong roles in the characteristics of a planar monopole antenna, including its impedance bandwidth and radiation pattern. The dual-sleeve tuning technique has been successfully applied to create antennas with wideband characteristic impedance,[5] while the technique of forming slots on the ground plane has been adopted for use in many kinds of antennas.[6-9]


The proposed planar monopole sleeve antenna exhibits the desired return-loss characteristics for UWB communications. Its 10-dB bandwidth covers the UWB spectrum from 3.1 to 10.6 GHz and more, provided by using a trapezoid conductor and L-shaped slots in the ground plane. The use of such a structure enhances the impedance bandwidth.[10]



1. This diagram shows the geometry of the proposed printed planar monopole antenna.




2. This plot shows the S_{11} behavior of the monopole antenna as simulated by the HFSS EM software.



3. These plots show S_{11} responses for different antenna structures, as simulated by the HFSS EM software: (a) the monopole antenna with the sleeve and ladder-shaped structure, (b) the monopole antenna with just the ladder-shaped structure, (c) the monopole antenna with just the sleeve, and (d) just the monopole antenna without the two structures.

Figure 1 shows a layout for the proposed antenna. It consists of a trapezoid and a ladder-shaped patch fed by a 50-Ω transmission line. L-shaped slots are cut from the edge of the ground plane and a 4.7-mm-long sleeve is attached to each side of the ground plane. Two patches



SKYWORKS®

High Performance RF Solutions

Handsets and Mobile Devices

Part Number	Description	Frequency (GHz)	Package (mm)
SKY65534	WLAN / Bluetooth® Front-End Module with Integrated PA, Filter, LNA, and T/R Switch	2.4	QFN 20L 2.5 x 2.5 x 0.45
SKY65535	WLAN Front-End Module with Integrated PA with Filter, LNA, and SPDT Switch	5.0	QFN 16L 2.5 x 2.5 x 0.45
SKY77701-16	High PAE Power Amplifier Module for CDMA / WCDMA / HSPA+ / LTE – Band I	1.92–1.98	10-pin MCM 3 x 3 x 0.9

WiFi Connectivity

SE5516A	802.11ac Dual-Band Front-End Module with PA, LNA, and SP2T Switch	2.4, 5.0	LGA 4 x 4 x 1
SE5003L1	802.11ac Matched Power Amplifier with Harmonic Filter	5.0	QFN 20L 4 x 4 x 0.9
SKY13317-373LF	pHEMT GaAs IC SP3T Switch	0.02–6.0	MLP 8L 1.5 x 1.5 x 0.45
SKY13351-375LF	GaAs SPDT Switch	0.2–6.0	QFN 6L 1 x 1 x 0.45
TT20P6-0709P0-1825E	High Power Infrastructure Filter can be Configured in a Pass Band Design	0.7–2.1	5" x 1.9" x 1"

Wireless Infrastructure

SKY12210-478LF	High Power (100 W) T/R SPDT Switch, 44 dB Isolation @ 2.6 GHz	0.9–4.0	QFN 16L 4 x 4 x 1.5
SKY13419-365LF	CMOS DBS Switch Matrix with Tone/Voltage Detector High Isolation 40 dB @ 900 MHz	0.25–2.15	QFN 20L 4 x 4 x 0.9
SKY65185	Dual-Channel Variable Gain Amplifier Front-End Module with 31.5 dB Control Range	1.7–2.7	32-pin MCM 7 x 7 x 1.35
SKY65373-11	Variable Gain Low Noise Amplifier with High Linearity @ 35 dB and Low NF @ 1 dB	1.7	16-pin MCM 8 x 8 x 1.3
SKY67001-396LF, SKY67002-396LF, SKY67003-396LF	High Linearity, Active Bias Low Noise Amplifiers	0.6–1.2 1.6–2.1 2.0–3.0	DFN 6L 1.5 x 1.5 x 0.45
SKY67130-396LF	High Linearity Amplifier Driver with +16 dBm $OP_{1\ dB}$ and 39.5 dBm OIP3 @ 22 mA	0.7–2.7	DFN 8L 2 x 2 x 0.75
SKY73208	Wideband Rx Mixer with Integrated Integer-N PLL and VCO	0.35–5.0	36-pin MCM 6 x 6 x 1.35
SKYFR-000782	Single Junction Circulator with Very Low Insertion Loss of 0.08 dB Typical	2.11–2.17	Drop-in 19 mm
SKYFR-000827	Single Junction Circulator with Very Low Insertion Loss of 0.10 dB Typical	2.3–2.4	SMT – Robust Lead, 23 mm

Smart Energy—Connected Home and Automation 802.15.4, ISM, and ZigBee®

SE2435L	High Power RF Front-End Module, 1 W High Efficiency with Integrated PA, LNA, and Diversity Switch	0.86–0.93	QFN 24L 4 x 4 x 0.9
SE2436L	High Power 0.5 W Front-End Module for ISM Band Applications, with PA, LNA, Bypass and Antenna Diversity	2.4	QFN 24L 4 x 4 x 0.9
SE2438T	Ultra Low Power ZigBee® Front-End IC with PA, LNA, Tx/Rx Bypass	2.4	QFN 20L 3 x 3 x 0.5
SKY13370-374LF	SPDT Switch, 50 Ohm Terminated	0.5–6.0	DFN 6L 1.5 x 1.5 x 0.45
SKY65367-11	High Power / High Efficiency Tx/Rx Front-End Module with Integrated PA and Bypass	0.17	16-pin MCM 4 x 4 x 0.9
SKY67012-396LF	Low Noise Amplifier with < 0.85 dB NF and < 5 mA Current @ 3.3 V	0.3–0.6	DFN 8L 2 x 2 x 0.75


Receive Skyworks Product News

New products (indicated in **blue, bold**). Join our customer email program today to start receiving information on new product releases, literature, upcoming tradeshow events, and more!

Skyworks Green™ products are compliant to all applicable materials legislation and are halogen-free. For additional information, refer to Skyworks Definition of Green™, document number SQ04-0074.

For more information, please visit our Web site at www.skyworksinc.com.

USA: 781-376-3000 • Asia: 886-2-2735 0399 • Europe: 33 (0)1 43548540 • Email: sales@skyworksinc.com
www.skyworksinc.com • NASDAQ: SWKS




4. These plots show the simulated radiation patterns of the monopole antenna at (a) 3.4 GHz, (b) 6.0 GHz, (c) 8.0 GHz, and (d) 10.0 GHz.

form a 38.5-deg. angle. The trapezoidal structure improves the impedance bandwidth. The lower-frequency resonant point can be adjusted by changing the size of the ladder-shaped patch; the higher-frequency resonant point links tightly to the dual-sleeve structure to broaden the impedance bandwidth. To achieve a compact structure, the slots on the ground plane are chosen to be L-shaped configurations.

The antenna is printed on a standard, low-cost FR-4 copper-clad substrate with thickness of 1.6 mm and relative permittivity of 2.95. The overall size of the antenna is 32 x 20 x 1.6 mm. Its performance and behavior were analyzed with the aid of the Ansoft High-Frequency Structure Simulator (HFSS) software (www.ansys.com).

Figure 2 shows the simulated reflection coefficient (dB) as a function of frequency (GHz). The 10-dB bandwidth reaches from 2.39 GHz to 11.8 GHz, meeting the UWB application. Also, the reflection coefficient from 3.3 to 3.7 GHz (for WiMAX applications) is better than –17.5 dB. At 3.39 GHz, it reaches nearly –40 dB.


Figure 3 shows the effects of the ladder-shaped conductor and the sleeve on the monopole antenna's reflection-coefficient performance. As can be seen from the curves of **Figs. 3(b) and 3(d)**, the lower resonant frequency has been adjusted to 3.39 GHz by the use of the ladder-shaped conductor. **Figures 3(c) and 3(d)** show how the sleeve tuning method produces a new higher resonant frequency, while also expanding the impedance bandwidth.




5. This photograph shows the prototype monopole antenna, fabricated on FR-4 substrate.

The far-field radiation patterns in the x-y E and H planes were computed at four frequency points: 3.4, 5.0, 8.0, and 10.0 GHz. **Figure 4** shows that nearly omnidirectional radiation patterns were obtained at all four frequencies. With the increase in frequency, however, the symmetry of the radiation patterns was lost, with pronounced sidelobes appearing. **Figure 5** shows a prototype of the proposed antenna; its dimensions are listed in the **table**. Measurements of return loss agree well with the simulations provided in **Fig. 6**. **Figure 7** shows that the measured peak antenna gain as a function of frequency varied approximately from 2.4 to 4.4 dBi.

In conclusion, the use of the sleeve and ladder-shaped structures can help shrink the dimensions of a planar monopole antenna while also providing the wide impedance bandwidth needed for UWB communications applications. MWRF



6. These plots compare the simulated and measured S_{11} responses for the planar monopole antenna.



7. This plot shows the measured gain of the compact planar monopole antenna.

ACKNOWLEDGMENTS

The authors would like to thank the National Natural Science Foundation of China for its support under Grant No. 60971118. The authors also thank the reviewers of this article for their invaluable comments.

REFERENCES

1. Kin-Lu Wong, "Compact and broadband microstrip antennas," unpublished.
2. Y. Lu, Y. Huang, H.-T. Chattha, and P. Cao, "Reducing ground-plane effects on UWB monopole antennas," IEEE Antennas and Wireless Propagation Letters, Vol. 10, 2011, pp. 147-150.
3. A. Elsherbini and K. Sarabandi, "Dual-polarized coupled sectorial loop antennas for UWB applications," IEEE Antennas and Wireless Propagation Letters, Vol. 10, 2011, pp. 75-78.
4. Z.-Y. Zhang, G. Fu, W.-J. Wu, J. Lei, and S.-X. Gong, "A wideband dual-sleeve monopole antenna for indoor base station application," IEEE Antennas and Wireless Propagation Letters, Vol. 10, 2011, pp. 45-48.
5. V. Zachou, C.G. Christodoulou, M.T. Chryssomallis, D. Anagnostou, and S. Barbin, "Planar monopole antenna with attached sleeves," IEEE Antennas and Wireless Propagation Letters,

WORLD'S WIDEST SELECTION

VCOs




RoHS COMPLIANT

RoHS models available, consult factory.

12 to 6840 MHz *from* $11.95 ea. (qty. 5)

Want a miniature surface mount, shielded plug-in, or rugged coaxial voltage controlled oscillator with the right stuff for your project? Go to minicircuits.com! You'll find over 800 standard catalog models, ***always in stock***. They're optimized to meet specific requirements, from narrow, broad, or octave bandwidths to linear tuning, low phase noise, dual output, 5V PLL/synthesizer implementation, or size, as small as 0.30 x 0.30 x 0.07". Selection is a snap, even with so many models to choose from! Just enter your requirements, and our patented search engine, Yoni2, searches *actual test data* to find the models that meet your needs. And if you need a custom design, challenge us with a phone call or email! We constantly design new models to meet new needs—so you'll get a quick response, fast turnaround times, and all at a surprisingly low price. Give your competition *real competition*...specify a Mini-Circuits VCO!



All SMT components are glued, as well as soldered, in place for long-term, reliable performance even after multiple reflow operations.

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®

ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

Yoni2® U.S. Patents 7739260, 7761442 ***The Design Engineers Search Engine*** *finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

359 rev T

Lark Engineering Co.
sales@larkengineering.com

THE FILTER SOURCE

NEW
LOW PROFILE, LEADLESS CAVITY FILTERS



0.2" Height

Features

- Frequency Range: Up to 20 GHz
- Bandwidths: Up to 60%
- Low Insertion Loss
- Meets Mil-Std-202
- Leadless SMT Package
- Available on Tape & Reel
- Custom Designed to your Specifications

Lark is a leading (OEM) supplier of RF and Microwave Filters, Multiplexers and Multifunction Assemblies for the Military, Aerospace and Commercial markets. The company began operations in 1986 with the goal to design and manufacture quality products that satisfy the customer's needs and requirements. Our products can be found in today's military radar systems, aircraft, shipboard, hand held radios, GPS, ISM, PCN, PCS and many other military and commercial applications. Our commitment to quality and customer service has been a cornerstone of the company since its inception.

Military • Aerospace • Commercial

sales@larkengineering.com • 949.240.1233

www.larkengineering.com

ISO 9001:2008 Certified ISO 14001:2004 Certified

Dimensions of the proposed antenna

Parameter	Value (in mm)
W	20
L	32
S	0.5
T	0.5
w_L	1.3
w_1	15.5
w_2	13.8
w_3	9.4
w_4	3.6
w_t	2
l_1	6
l_2	4
l_3	2
l_4	8
l_5	6.5
l_6	4.7

Vol. 5, 2006, pp. 286-289.
6. L. Dang, Z.Y. Lei, G.L. Ning, and J. Fan, "A Compact Microstrip Slot Triple-Band Antenna for WLAN/WiMAX Applications," IEEE Antennas and Wireless Propagation Letters, Vol. 9, 2010, pp. 1178-1181.
7. Lev Pazin, and Yehuda Leviatan, "Inverted-F laptop antenna with enhanced bandwidth for Wi-Fi/WiMAX applications," IEEE Transactions on Antennas and Propagation, Vol. 59, No. 3, 2011, pp. 1065-1068.
8. B. Zhou, G.-Z. Lu, and Q. Yang, "Triple-band planar monopole antenna design," Journal of Microwaves, Vol. 4, 2010, pp. 219-222.
9. Tenigeer, N. Zhang, J.-H. Qiu, S. Lin, and G.-L. Lu, "Wide slot UWB antenna with band rejection character analysis," Chinese Journal of Radio Science, Vol. 26 , No. 1, February 2011, pp. 164-169.
10. T. Zhang, G. Fu, Z.-Y. Zhang, X. Chen, and Z. Mei, "Design of a printed sleeve antenna with broadband," Journal of Microwaves, Vol. 4, August 2010, pp. 197-199.
11. C.-Y. Pan, T.-S. Horng, W.-S. Chen, and C.-H. Huang, "Dual wideband printed monopole antenna for WLAN/WiMAX applications," IEEE Antennas and Wireless Propagation Letters , Vol. 6, 2007, pp. 149-151.
12. J. Chen, G. Fu, G.-D. Wu, L. Yang, S.-X. Gong, and X. Chen, "CPW-fed sleeve antenna for multiband applications," Chinese Journal of Radio Science, Vol. 26, No. 1, February 2011, pp. 140-144.
13. S. Gai, Y.-C. Jiao, P. Zhu, and Y.-B. Yang, "A novel compact monopole antenna for WLAN applications," Journal of Microwaves, Vol. 4, 2010, pp. 172-174.
14. J.-S. Li, "An omnidirectional microstrip antenna for WiMAX applications," IEEE Antennas and Wireless Propagation Letters, Vol. 10, 2011, pp. 167-169.
15. S.-G. Zhou, B.-H. Sun, and Q.-Z. Liu, "Analysis and design of a novel omni-directional broadband biconical antenna for mobile communication," Chinese Journal of Radio Science, Vol. 24, No. 2, April 2009, pp. 224-227.

ULTRA WIDE BANDWIDTH VCO

Model	Frequency Range (MHz)	Tuning Voltage (VDC)	DC Bias (VDC)	Typical Phase Noise @10kHz (dBc/Hz)
DCMO25-5	20 -50	0.5 - 24	+5 @ 30 mA	-114
DCMO514-5	50 -140	0.5 - 24	+5 @ 29 mA	-110
DCMO616-5	65 -160	0.5 - 24	+5 @ 28 mA	-108
DCMO1027	100 -270	0.5 - 24	+5 - 12 @ 20 mA	-112
DCMO1129	110 -330	0.5 - 24	+5 - 12 @ 22 mA	-112
DCMO1545	150 -450	0.5 - 24	+5 - 12 @ 22 mA	-108
DCMO1857	180 -560	0.5 - 24	+5 - 12 @ 26 mA	-108
DCYR2060-5	200 -600	0.5 - 28	+5 @ 60 mA	-119
DCMO2260-5	220 -600	0.5 - 24	+5 @ 28 mA	-108
DCMO2476	240 -760	0.5 - 24	+5 - 12 @ 27 mA	-108
DCMO2550-12	250 -500	0.5 - 20	+12 @ 30 mA	-112
DCYR3097-5	300 -970	0.5 - 28	+5 @ 38 mA	-112
DCMO3288-5	320 -880	0.5 - 24	+5 @ 21 mA	-109
DCMO3288-12	320 -880	0.5 - 24	+12 @ 32 mA	-105
DCFO35105-5	350 -1050	0.5 - 25	+5 @ 53 mA	-110
DCMO40110-5	400 -1100	0.5 - 24	+5 @ 37 mA	-103
DCMO40110-8	400 -1100	0.5 - 24	+8 @ 39 mA	-104
DCMO40110-12	400 -1100	0.5 - 24	+12 @ 38 mA	-105
DCMO50120-5	500 -1200	0.5 - 24	+5 @ 37 mA	-102
DCMO50120-12	500 -1200	0.5 - 24	+12 @ 28 mA	-103
DCYR50125-10	500 -1250	0.5 - 24	+10 @ 37 mA	-110
DCMO60170-5	600 -1700	0.5 - 25	+5 @ 35 mA	-100
DCMO60170-12	600 -1700	0.5 - 24	+12 @ 29 mA	-102
DCMO80210-5	800 -2100	0.5 - 24	+5 @ 28 mA	-96
DCMO80210-10	800 -2100	0.5 - 24	+10 @ 25 mA	-100
DCMO90220-5	900 -2200	0.5 - 24	+5 @ 28 mA	-98
DCMO90220-12	900 -2200	0.5 - 24	+12 @ 29 mA	-99
DCMO92200-12	925 -2000	0.5 - 18	+12 @ 35 mA	-101
DCMO100230-5	1000 -2300	0.5 - 24	+5 @ 35 mA	-98
DCMO100230-12	1000 -2300	0.5 - 24	+12 @ 33 mA	-101
DCYS100200-12	1000 -2000	0.5 - 28	+12 @ 33 mA	-105
DCMO110250-5	1100 -2500	0.5 - 28	+5 @ 25 mA	-100
DCMO110250-8	1100 -2500	0.5 - 28	+8 @ 30 mA	-102
DCMO130275-5	1300 -2750	0.5 - 24	+5 @ 20 mA	-93
DCMO135270-8	1350 -2700	0.5 - 20	+8 @ 36 mA	-93
DCMO150318-10	1500 -3100	0.5 - 22	+10 @ 32 mA	-96
DCMO150318-5	1500 -3200	0.5 - 20	+5 @ 24 mA	-93
DCMO150320-5	1500 -3200	0.5 - 18	+5 @ 33 mA	-92
DCYS160360-5	1600 -3600	0.5 - 20	+5 @ 47 mA	-94
DCMO170340-3	1700 -3400	0.5 - 20	+3.5 @ 18 mA	-85
DCMO170345-5	1700 -3450	0.5 - 16	+5 @ 43 mA	-88
DCMO172332-5	1720 -3320	0.5 - 24	+5 @ 22 mA	-94
DCMO190410-5	1900 -4100	0.5 - 18	+5 @ 45 mA	-90
DCMO200420-5	2000 -4200	0.5 - 17	+5 @ 50 mA	-89
DCYS200400-5	2000 -4000	0.5 - 16	+5 @ 45 mA	-90
DCYS200400P-5	2000 -3900	0.5 - 22	+5 @ 50 mA	-95
DCMO250512-5	2500 -5125	0.5 - 14	+5 @ 51 mA	-76
DCYS250500-5	2500 -5000	0.5 - 14	+5 @ 45 mA	-78
DCYS250510-5	2500 -5100	0.5 - 16	+5 @ 45 mA	-78
DCYS275550-5	2750 -5550	0.5 - 22	+5 @ 43 mA	-77
DCYS300600-5	3000 -6000	0.3 - 17	+5 @ 43 mA	-77

Patented Technology

SYNERGY® MICROWAVE CORPORATION

Phone: (973) 881-8800 | Fax: (973) 881-8361
E-mail: sales@synergymwave.com
Web: WWW.SYNERGYMWAVE.COM
Mail: 201 McLean Boulevard, Paterson, NJ 07504

CONQUER PHASE NOISE AND JITTER IN FREQUENCY STANDARDS

TO MEASURE A signal's noise level, phase noise or jitter can be used. The choice depends largely on the application, although jitter can be calculated from phase noise if the phase-noise characteristic is known. In a five-page white paper titled, "Designing for Exceptional Phase Noise and Jitter Performance in Precision GPS Frequency Standards," Precision Time and Frequency, Inc. provides a concise overview of the steps and considerations needed to design a high-performance, low-noise, precision-frequency standard.

The first step is to select the right crystal oscillator. A "good" oven-controlled crystal oscillator (OCXO) will have a phase-noise characteristic of at least –125 dBc/Hz at 10 Hz offset from a 10-MHz carrier. At higher offsets, phase noise will generally fall linearly to a noise floor of less than –160 dBc/Hz at 10 kHz offset from a 10-MHz carrier. In evaluating phase-noise specifications, it is critical to keep in mind the carrier frequency at which the measurement is quoted, as there is a direct mathematical relationship between carrier frequency and measured phase noise.

Precise Time and Frequency, Inc., 50L Audubon Rd., Wakefield, MA 01880; (781) 245-9090, FAX: (781) 245-9099, www.ptfinc.com.

The next task is to preserve the attained low phase noise when buffering and distributing. In addition to filtering the power supply at the input to the printed-circuit board (PCB), filtering should be placed at the supply pins to the buffer amplifiers. When it comes to amplifying and distributing low-phase-noise RF signals, current feedback amplifiers are sufficient. However, the layout must be correct to ensure desired performance. For this application, bandwidth limiting is required. Capacitance to ground at the inputs and outputs also must be minimized as much as possible to avoid instability. With these tips, the white paper provides a solid foundation for designers working in this segment.

GET A SOLID GRASP OF IEEE 802.11ad



WIRELESS LOCAL-AREA NETWORKING (WLAN) was birthed to support computers in the home and office as well as on the road. Today, however, the usage models have moved far beyond such basic functionality. They now incorporate wireless display, high-definition-television (HDTV) distribution, rapid upload/download, backhaul, outdoor campus/auditorium, and the manufacturing floor. Two new IEEE project groups have emerged to provide very high-throughput capabilities: Working Groups TGac (focused on IEEE 802.11ac) and TGad (proposing IEEE 802.11ad). The standard that is the focus of the latter is detailed at length in a newly available application note from Agilent Technologies titled, "Wireless LAN at 60 GHz—IEEE 802.11ad Explained."

The 28-page application note explains that IEEE 802.11ad is being jointly proposed by its working group and the Wireless Gigabit Alliance (WiGig; http://wirelessgigabitalliance.org). The goal of the standard, which is expected to be finalized by the end of this year, is to provide throughput to 7 Gb/s using roughly 2 GHz of spectrum at 60 GHz over a short range. All of the IEEE 802.11 standards are tasked with backward compatibility. Thus, IEEE 802.11ac and 802.11ad are compatible at the medium-access-control (MAC) or data-link layer. They differ only in their physical-layer (PHY) characteristics. As a result, devices could have three radios: a 2.4-GHz radio for general use, which may suffer from interference; a 5-GHz radio for more robust, higher-speed applications; and a 60-GHz radio for ultra-high speed within a room. Session switching between all three radios would be supported.

Agilent Technologies, Inc., 5301 Stevens Creek Blvd., Santa Clara, CA 95051; (408) 345-8886, FAX: (408) 345-8474, www.agilent.com.


The application note provides in-depth information on various facets of the standard. For example, a discussion of the choice of 60 GHz explains that transmission at that frequency covers less distance for a given power. For the most part, this is due to the increased free-space path loss (68 dB over 1 m at 60 GHz, which is 21.6 dB worse than at 5 GHz). It is compounded by propagation losses through materials and human-body shadowing (losses from, say, 3 to 30+ dB).

Another concern raised about the 60-GHz band is the range limitation caused by the substantial RF absorption peak, which is due to a resonance of atmospheric oxygen molecules. Yet this absorption effect only begins to grow significant beyond 100 m. As a result, it does not impact low-power transmissions. With IEEE 802.11ad, it is considered an advantage that low-power transmissions will not propagate very far. In addition to reducing the likelihood of co-channel interference, such limited propagation increases the possible frequency re-use density.

Among other benefits are reduced opportunities for protected content to be stolen by eavesdropping on nearby transmissions; the emergence of low-cost microwave-component fabrication techniques; and the fact that high path loss can be mitigated by increasing antenna gain. In-depth information also is provided on topics like a regulatory overview, the standard's PHY, and testing. By covering so many aspects surrounding IEEE 802.11ad, the note succeeds in addressing both the requirements and challenges of supporting today's unwired world.

TINY

Wideband Transformers



0.15-6200 MHz as low as 99¢ each (qty. 1000) RoHS compliant.

Rugged, repeatable performance.
At Mini-Circuits, we're passionate about transformers. We even make own transmission line wire under tight manufacturing control, and utilize all-welded connections to maximize performance, reliability, and repeatability. And for signals up to 6 GHz, our rugged LTCC ceramic models feature wrap-around terminations for your visual solder inspection, and they are even offered in packages as small as 0805!

Continued innovation: Top Hat.
A Mini-Circuits exclusive, this new feature is now available on every open-core transformer we sell. Top Hat speeds customer pick-and-place throughput in four distinct ways: (1) faster set-up times, (2) fewer missed components, (3) better placement accuracy and consistency, and (4) high-visibility markings for quicker visual identification and inspection.

More models, to meet more needs
Mini-Circuits has over 200 different SMT models in stock. So for RF or microwave baluns and transformers, with or without center taps or DC isolation, you can probably find what you need at minicircuits.com. Enter your requirements, and Yoni2, our patented search engine, can identify a match in seconds. And new custom designs are just a phone call away, with surprisingly quick turnaround times gained from over 40 years of manufacturing and design experience!

See minicircuits.com for technical specifications, performance data, pricing, and real-time, in-stock availability!
Mini-Circuits...we're redefining what Value is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

Yoni2® U.S. Patents 7739260, 7761442 *The Design Engineers Search Engine finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

377 rev Y

ANRITSU CO.
490 Jarvis Dr., Morgan Hill, CA 95037-2809; (408) 778-2000,
FAX: (408) 776-1744, www.anritsu.com

VNAs Measure Noise From 70 kHz to 125 GHz


Two new options arm an established line of microwave vector network analyzers for making accurate noise figure measurements, along with the capability to make those measurements up to 125 GHz.

NOISE FIGURE IS A PARAMETER well-known to receiver designers, and a key measure of determining a receiver's ultimate signal sensitivity. Measurements of noise figure have often been reserved for specialized test systems. But this needn't be the case, thanks to the new noise-figure measurement capability (option MS-4640A-041) that can be built into the VectorStar MS4640A and ME7838A series vector network analyzers (VNAs) from Anritsu Co. (www.anritsu.com). These workhorses can now make noise-figure measurements from 70 kHz to 70 GHz. And by adding the optional broadband receiver (model SM6609) the frequency range can be extended to 125 GHz **(Fig. 1)**.

The SM6609 broadband receiver equips an ME7838A VNA for continuous broadband frequency coverage from 70 kHz to 125 GHz via a small-dimensioned coaxial connector. Back in 1983, Anritsu (then Wiltron Co.) introduced the K-connector with 2.92-mm dimensions for frequency coverage to 40 GHz, in support of its line of scalar network analyzers. Over the years, the firm's Bill Oldfield has been instrumental in developing smaller coaxial connector configurations for higher-frequency use. The 1-mm connector, for example, is specified to 110 GHz, but can operate up to 125 GHz. Anritsu plans to support the new architecture with coaxial as well as waveguide adapters for those making noise-figure measurements on waveguide DUTs.

The new millimeter-wave noise-figure measurement systems are suitable for both research and production tasks, with

1. The VectorStar MS4640A series and ME7838A series (not shown) VNAs are eligible for two new options that add noise-figure measurement capability and extend the coaxial frequency coverage to 125 GHz.



S-parameter measurement speed of 55 ms for 201 data points using an intermediate-frequency (IF) bandwidth of 10 kHz. They offer noise-figure measurement resolution of < 0.1 dB, backed by calibration and measurement stability of 0.1 dB over 24 h. The system dynamic range for S-parameter measurements is 108 dB at 65 GHz and 107 dB at 110 GHz.

The SM6609 receiver uses the same nonlinear-transmission-line (NLTL) technology employed in the firm's model 3743A VectorStar frequency extension modules (see the September 2011 issue of *Microwaves & RF*, p. 98). The compact size of those frequency-extension units, which are a fraction of the size and weight of conventional frequency-converter modules, enabled ease of positioning on wafer probe stations when making on-wafer measurements. The firm will offer additional optional frequency-conversion modules for waveguide-based millimeter-wave coverage through 750 GHz and beyond for higher-millimeter-wave and quasi-optical measurements.

Noise-figure measurements on the VectorStar MS4640A and ME7838A series VNAs equipped with the optional SM6609 receiver are supported by optional measurement software. The analyzers run under simple graphical user interfaces (GUI) that offer various other active-device measurements related to noise figure—including gain and compression point—as either standard or optional capabilities.

Accurate noise-figure measurements, of course, are aided by some understanding of how these measurements are made and why. Noise figure essentially describes the degradation of a system or component's signal-to-noise ratio (SNR) due to the output noise power (N_o) added by a device under test (DUT), usually an active device such as an amplifier. Measuring the noise figure of the DUT can help determine the impact it will have on a system's SNR.

Noise figure (NF) in decibels can be calculated as a function of noise factor, F:

$$NF = 10\log F$$

where:

$$F = (S_i/N_i)/(S_o/N_o)$$

and:

S_i = the input signal power;


N_i = the input noise power;

S_o = the output signal power; and

N_o = the output noise power.

Over the years, noise-figure measurements have improved due to better understanding of how to make the measurements,[1-6] more sensitive receivers, and more accurate noise-power measurements. Option MS-4640A-041 (which equips a VectorStar MS4640A or ME7838A VNA) and a model SM6609 receiver (with noise-figure capability through 70 to 125 GHz) incorporates many of these noise-figure advances, including the use of the cold-source measurement method rather than the hot-cold or Y-factor measurement approach.

The Y-factor (hot-cold) measurement technique uses a noise source capable of producing a low-temperature (cold) noise power (N_c) and a hot noise power (N_h). Such a noise source is the Input Noise Signal in **Fig. 2**. The Y factor is simply the ratio of hot to cold noise powers, $Y = N_h/N_c$.[2] The Y factor was useful for a quick calculation of noise figure using Eq. 1:



2. This block diagram shows a simple representation of the VNA-based noise figure measurement system.

$$F = [(T_h/T_c) - 1]/(Y - 1) \quad (1)$$

where:

T_h = the equivalent hot temperature of the noise source; and

T_c = the equivalent cold temperature of the noise source, which is often assumed to be equal to 290 K per IEEE definition.

By making noise-figure measurements of the receiver alone, and then the receiver with the device under test (DUT), it is possible to deconvolve the noise figure of the DUT using the Friis equation[1]:

$$F_{DUT} = F_{SYS} - (F_{rcvr} - 1)/G \quad (2)$$

where:

F_{DUT} = the noise factor of the DUT;

F_{SYS} = the noise factor of the whole system (receiver + DUT);

F_{rcvr} = the noise factor of the receiver alone; and

G = the gain of the DUT.

The DUT gain, G, can be measured separately, such as by means of scattering (S) parameters; it can also be determined from the change in measured noise powers during calibration and measurement. The hot-cold noise-figure measurement approach is based totally on ratios and therefore does not require absolute power calibrations. This was important when the available measurement dynamic range over broad bandwidths was limited.

Calibration of the equivalent hot temperture, T_h, for a noise source is difficult and usually left to a handful or qualified laboratories. Another problem with the hot/cold noise-figure measurement approach is related to minimizing impedance match changes when the noise source changes between its hot and cold states.[4] Match changes result in large measurement errors, which can be partially overcome by source correction methods.[3]

The cold-source noise-figure measurement method was developed to eliminate the need for the hot/cold noise source. In

the cold-source method, the noise factor can be found from Eq. 3:

$$F = (kT_0B + N)/(kT_0BG) \quad (3)$$

where:
k = Boltzmann's constant (~1.3807 × 10^{-23} J/°K);
N = the noise power added by the DUT;
G = the gain of the DUT; and
B = the measurement bandwidth.

This method requires an accurate measurement of absolute noise power, implying the need for an effective measurement receiver calibration. It also calls for an accurate measurement of bandwidth which, in the case of using a VNA with a digital IF system, can be readily determined. The bandwidth can also be found when measuring absolute power, provided a noise source is used. Isolating the noise factor of the DUT using this method, the noise contributions of the receiver must be known, which can be performed with only a cold source attached to the receiver's input port. Once receiver noise is known, Eq. 3 can be rewritten as Eq. 4:

$$F = (1/G) + (N_{DUT} + rcvr - N_{rcvr})/kT_0BG \quad (4)$$

This method places great import on gain measurements, with errors in measuring gain or noise power transferred almost on a dB-for-dB basis to the noise-figure results. Again, impedance matching is also important for maintaining good measurement accuracy, and the receiver noise power may be affected by the source impedance. By considering that the response of a DUT can be represented by its minimum noise factor (F_{min}), its resistive noise (R_n, and its optimum impedance (Γ_{opt}),[7] the net noise figure of the DUT can be found from Eq. 5:

$$F = F_{min} + (4R_n|\Gamma_S - \Gamma_{opt}|^2)/[Z_0(1 - |\Gamma_S|^2)|1 + \Gamma_{opt}|^2] \quad (5)$$

where:
Z_0 = the system characteristic impedance.

If R_n is small relative to Z_0, the net noise figure will be relatively insensitive to changes in source reflection coefficient, Γ_S. Typically, measurement receiver effective R_n is small. When examining typical noise circles for a measurement receiver at 50 GHz (not shown), even if the DUT's output port is poorly matched, the effective receiver noise figure only changes by about 0.65 dB from F_{min}. For a DUT with 10-dB gain and 2-dB noise figure, this would only add 0.1-dB uncertainty, and only 0.01-dB uncertainty for a DUT with 20-dB gain and 2-dB noise figure.

Measurements of noise figures have often been reserved for specialized test systems, but this needn't be the case.

A number of factors affect noise-factor measurement uncertainty, $\tilde{F}$, arising from deviations (Δ) that can occur during measurements or calibrations:

$$\tilde{F} = 1 + (G + \Delta G) + (N_{DUT + rcvr} - N_{rcvr}) + (\Delta N_{DUT + rcvr} - \Delta N_{rcvr})](1 + \Delta R)/[kT_0B(G + \Delta G)] \quad (6)$$

Equation 6 does not list all possible uncertainty sources—just the dominant ones. Gain variation (ΔG) is usually associated with S-parameter measurements. Other variations are related to measurements of noise power, including ΔR terms related to a user's power calibration and receiver calibration, and ΔN terms related to impedance match interactions.

To help understand different uncertainty scenarios, the VectorStar Noise Figure Uncertainty Calculator, based on Monte Carlo methods,[8] was created as a companion to the new 125-GHz noise-figure measurement capability. The program runs on an external personal computer (PC) or on the desktop of a VectorStar VNA and is helpful in determining the optimum measurement setup for achieving a desired measurement uncertainty target. The program takes into account receiver parameters, DUT parameter, power measurement parameters, source parameters, and the cold source temperature. It can provide plots of noise figure uncertainty versus frequency and versus gain as well as the receiver gain required to achieve a desired noise-figure uncertainty.


Option MS4640A-041, which adds noise-figure-measurement capability to Anritsu's VectorStar MS4640A and ME7838A series VNAs, is priced at $15,000 (plus the cost of the analyzer). VectorStar MS4640A series VNAs are available in standard frequency ranges from 10 MHz to 20, 40, 50, or 70 GHz (with frequency extension option to 70 kHz), while the ME7838A series VNAs offer single-sweep capability from 70 kHz to 110 GHz through a 1-mm connector.

The SM6609 receiver option extends the overall frequency range of the VNAs to 125 GHz through the same type of 1.0-mm coaxial connector. P&A: $15,000 (noise-figure capability); 8 wks, and $30,250 (SM6609 receiver for 125-GHz coverage); 16 wks. MWRF

ANRITSU CO., 490 Jarvis Dr., Morgan Hill, CA 95037-2809; (408) 778-2000, FAX: (408) 776-1744, *www.anritsu.com*.

REFERENCES

1. H.T. Friis, "Noise figure of radio receivers," Proceedings of the IRE, Vol. 32, July 1944, pp. 419-422.
2. "Noise Figure," Anritsu Co. (www.anritsu.com), Application Note 11410-00210, August 2000.
3. David Vondran, "Noise figure measurement: corrections related to match and gain," Microwave Journal, March 1999, pp. 22-38.
4. N. Otegi, J.M. Collantes, and M. Sayed, "Cold-source measurements for noise figure calculation in spectrum analyzers," 67th ARFTG Conference Digest, June 2006, pp. 223-228.
5. N. Otegi, J.M. Collantes, and M. Sayed, "Receiver noise calibration for vector network analyzer," 76th ARFTG Conference Digest, December 2010, pp. 1-5.
6. J.M. Collantes, R.D. Pollard, and M. Sayed, "Effects of DUT mismatch on the noise figure characterization: A comparative analysis of two Y-factor techniques," IEEE Transactions on Instrumentation & Measurements, Vol. 51, December 2002, pp. 1150-1156.
7. L. Escotte, R. Plana, and J. Graffeuil, "Evaluation of noise parameter extraction methods," IEEE Transactions on Microwave Theory & Techniques, Vol. 41, March 1993, pp. 382-387.
8. "Supplement 1 to the "Guide to the expression of uncertainty in measurement," Propagation of distributions using a Monte Carlo method," Joint Committee for Guides in Metrology, 2008.



Turn USB Power Sensors into

Smart RF POWER METERS

-30 to +20 dBm 9 kHz to 8 GHz

• Lightning-fast measurement, as quick as 30ms • Averaging of measurement • 50 dB dynamic range
*• Linux® support • Compatible with LabVIEW®, Delphi®, C++, C#, Visual Basic®, and .NET software**

Don't break your bank with expensive conventional power meters. Mini-Circuits USB Power Sensors turn almost any Linux® or Windows® based computer into a low-cost testing platform for all kinds of RF components. Reference calibration is built in, and your USB port supplies required power. Our GUI offers a full range of watt or dB measurements, including averaging, frequency sweeps, and multi-sensor support.

Our power sensors can be carried in your pocket, or mounted remotely for manual or automated system monitoring (internet connectivity required). Data can be viewed on-screen or exported to Excel® spreadsheets for reporting and analytic tools. Mini-Circuits Power Sensors cost half as much as you might expect, so why do without? Place an order today, and we can have it in your hands as early as tomorrow.

All Power Sensor models include:

- *Power Sensor Unit*
- *Power Data Analysis Software*
- *SMA Adaptor (50Ω only)*
- *USB Cable*



** Linux is a registered trademark of Linus Torvalds. LabVIEW is a registered trademark of National Instruments Corporation. Delphi is a registered trademark of Codegear LLC. Visual Basic, Excel, and Windows are registered trademarks of Microsoft Corporation. Neither Mini-Circuits nor the Mini-Circuits USB Power Sensor are affiliated with or endorsed by the owners of the above referenced trademarks. Mini-Circuits and the Mini-Circuits logo are registered trademarks of Scientific Components Corporation.*

Model	Frequency	Speed	Ω	Price $ ea. qty. 1-4
PWR-8 FS	1MHz-8 GHz	10 ms	50	969.00
PWR-8 GHS	1MHz-8 GHz	30 ms	50	869.00
PWR-6 GHS	1MHz-6 GHz	30 ms	50	795.00
PWR-6 G	1MHz-6 GHz	30 ms	50	695.00
PWR-4 GHS	9kHz-4 GHz	30 ms	50	795.00
PWR-2 GHS-75	100kHz-2 GHz	30 ms	75	795.00
PWR-2.5 GHS-75	100kHz-2.5 GHz	30 ms	75	895.00

RoHS compliant

Mini-Circuits...we're redefining what VALUE is all about!

Mini-Circuits®
ISO 9001 ISO 14001 AS9100

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

U.S. Patents 7739260, 7761442

***The Design Engineers Search Engine** finds the model you need, Instantly* • For detailed performance specs & shopping online see minicircuits.com

IF/RF MICROWAVE COMPONENTS

JACK BROWNE | Technical Contributor


Making Microwave Measurements Modular

An increasing number of RF/microwave measurement functions are now available in modular form, making it possible to shrink the size and reduce the power of automated test systems.

TEST INSTRUMENT modules once represented a small, specialized area among high-frequency measurement products. But more and more manufacturers are now supporting established module standards—such as PCI eXtensions for Instrumentation (PXI)—with a growing number of measurement functions. As a result, engineers are discovering that they can benefit from the versatility of modular test instruments without sacrificing performance.

Since National Instruments (www.ni.com) created the specifications for PXI instrumentation in the late 1990s, the open PXI standard has gained momentum. Much of the credit for this goes to the PXI Systems Alliance industry group (PXISA; www.pxisa.org), now with more than 50 member companies. PXI Instruments use the Peripheral Component Interconnect (PCI) bus together with modular Eurocard mechanical packaging, in contrast to more traditional rack-mount instruments using the General Purpose Interface Bus (GPIB) for control and data communications.

PXI instruments are built into either 3U or 6U Eurocards, where each U is 1.75 in. (44.45 mm) high and represents a rack unit or slot in a mainframe or chassis. Common PXI chassis sizes range from 4 to 18 slots, with some of the slots occupied by essential functions such as power supplies and system controllers. The chassis contains the PXI backplane with the PCI, triggering, and timing buses, and uses a dedicated 10-MHz system reference clock. Because the PXI backplane was defined with a somewhat limited bandwidth of 132 MB/s, the PXI standard evolved into a higher-speed standard (PXI Express) with a backplane bandwidth to 6 GB/s. PXI Express also adopted a higher-speed differential 100-MHz reference clock for enhanced synchronization capabilities, using the differential interface for improved immunity to noise.



1. A modular test system consists of a mainframe chassis and a number of plug-in function modules, along with an external monitor. [Photo courtesy of National Instruments (www.ni.com)]


Software for PXI instruments is managed by the PXI Systems Alliance—with PXI software defining the frameworks for PXI systems, which are based on 32-b Microsoft Windows® operating systems. The software is designed for compatibility with most popular development environments. The goal for all PXI software and hardware is universal interoperability.

Assembling a PXI or other modular measurement system starts with a mainframe/chassis designed to hold the modules. Next, modules are added to define desired measurement functions, such as signal generation and signal analysis. Control functions and measurements results are shown on a computer display screen in a PXI system **(Fig. 1)**.

National Instruments offers both PXI and higher-speed PXI Express (PXIe) modules for a variety of functions, including chassis, system controllers, switches, signal sources, and digitizers/analyzers. Examples include the recently introduced PXI/PXIe-2543 multiplexer, the PXIe-5185/5186 digitizers, and the PXIe-5665 vector signal analyzer (VSA). The PXI/PXI-2543 is a 4 x 1 50-Ω multiplexer for high-density switching applications. It consists of dual single-pole, four-throw (SP4T) FET switches capable of operating from 10 MHz to 6.6 GHz with input power levels to +30 dBm. The insertion loss is typically less than 3.4 dB to 2.4 GHz and typically less than 6.1 dB through 6.6 GHz. VSWR is typically less than 1.50:1 through 2.4 GHz and less than 1.60:1 through 6.6 GHz. The isolation is better than 70 dB through 2.4 GHz and better than 59 dB through 6.6 GHz. Propagation delays are minimized to 1720 ps.

The PXIe-5185 and PXIe-5186 digitizers were co-developed by National Instruments and Tektronix (www.tek.com). The dual-channel PXIe digitizers operate with sampling rates of 6.25 GSamples/s for two channels and 12.50 GSamples/s for one channel, with 8-b vertical resolution. The

Why Settle for <80dBm IIP2?




True Zero-IF with >530MHz I/Q Demodulation Bandwidth, IIP2 and Offset Tuning

Achieve a high performance true ZIF receiver using the LTC®5585 I/Q demodulator with integrated adjustable IIP2 to >80dBm and DC offset nulling. With tuning, its 530MHz demodulation bandwidth can be extended to over 600MHz at gain flatness of ±0.5dB.

Features

Features	LTC5584	LTC5585
Frequency Range	30MHz to 1.4GHz	700MHz to 3GHz
I/Q Demodulation BW	>530MHz	>530MHz
IIP3	31dBm@450MHz	25.7dBm@1.9GHz
Adjustable IIP2	>80dBm	>80dBm
DC Offset Cancellation	Yes	Yes


IIP2 Optimization vs Trim Voltage



Info & Free Samples

www.linear.com/IQdemod


1-800-4-LINEAR



www.linear.com/dn1027

LT, LTC, LTM, Linear Technology and the Linear logo are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners.

LINEAR TECHNOLOGY



2. This 18-slot PXIe chassis holds the modules that comprise the M9392A dual-channel VSA with bandwidth of 50 MHz to 26.5 GHz. [Photo courtesy of Agilent Technologies (www.agilent.com)]

PXIe-5185 captures signals from DC to 3 GHz, while the PXIe-5186 operates from DC to 5 GHz across an input range of 110 to 1000 mV. The VSWR is typically 1.25:1 at 1 GHz and 1.80:1 at 5 GHz.


The PXIe-5665 VSA consists of a PXIe-5653 frequency synthesizer as the local oscillator (LO), a PXIe-5603 RF downconverter, and a PXIe-5622 IF digitizer. The modules combine for a low-frequency path that covers 20 Hz to 3.6 GHz and a high-frequency path that extends to 14 GHz. The trio of modules provides instantaneous bandwidths of 25 and 50 MHz with 16-b resolution and better than –165 dBm/Hz typical displayed average noise level (DANL) at 1 GHz. The amplitude accuracy is typically ±0.1 dB with ±0.35 dB typical amplitude flatness within a 20-MHz bandwidth. The typical phase noise is –129 dBc/Hz offset 10 kHz from an 800-MHz carrier.

Phase Matrix (www.phasematrix.com) offers a full line of PXI modular instruments, including tunable preselector filters, frequency downconverters, and microwave LOs, in 3U sizes occupying from one to three slots in a PXI chassis. For example, model PXI-1450B is a two-slot PXI LO module with frequency range of 3 to 9 GHz and 1-Hz tuning resolution. It has 500-µs frequency switching speed and as much as +16 dBm output power with ±2 dB amplitude accuracy.

ZTEC Instruments (www.ztechinstruments.com) produces a 6-GHz VSA in both PXI and PXIe formats. Models ZT 8651 PXI and ZT 8651 PXIe both feature frequency spans of DC to 6 GHz with amplitude capture ranges of –120 to +20 dBm. They operate at 400 MSamples/s with 16-b resolution and use a high-speed FPGA for real-time signal processing. The VSAs provide 1-Hz frequency resolution and phase noise of better than –125 dBc/Hz offset 100 kHz from a 1-GHz carrier. Low-level signals benefit from an 80-dB SFDR and DANL of –163.5 dBm/Hz at 6 GHz.

GuideTech (www.guidetech.com) offers a number of PXI chassis products, as well as its continuous-time-interval-counter (CTIA) line of PXI instruments through 2.7 GHz. The latest model, the GT210PXI-8, offers automatic measurements of time interval, frequency, period, totalize, ratio, time interval delay, and pulse width across eight channels. It provides 0.01 ppm frequency resolution and 8-ps time resolution, and can perform 2300 measurements/s. It is supplied in a 3U PXI module form factor.

Aeroflex (www.aeroflex.com) has developed a variety of PXI instruments, including its models 3010 and 3011 frequency synthesizers, each fitting into single-width 3U PXI cards. They tune from 12.50 to 3.0 GHz with 1-Hz frequency resolution and typical phase noise of –116 dBc/Hz offset 20 kHz from the carrier. The phase noise for both units is –114 dBc/Hz offset 10 kHz from the carrier and typically –140 dBc/Hz offset 1 MHz from the carrier. The 3010 derives its stability from an internal voltage-controlled crystal oscillator (VCXO) or external 10-MHz reference oscillator, while the 3011 operates with an internal 10-MHz oven-controlled crystal oscillator (VOCXO) reference.



3. This model M9703A AXIe eight-channel digitizer shows the similarity with PXI. This single-slot digitizer provides 12-b resolution for an analog bandwidth of DC to 1 GHz. [Photo courtesy of Agilent Technologies (www.agilent.com)]

Agilent Technologies (www.agilent.com) supplies numerous instruments in the PXI format, but is also one of a growing number of companies to offer instruments in the emerging AdvancedTCA Extensions for Instrumentation and Test (AXIe) modular instrumentation standard. Agilent's model M9392A is the industry's most broadband PXIe VSA with a bandwidth of 50 MHz to 26.5 GHz. Available in a two-channel version that fits neatly in the firm's M9018A 18-slot PXIe chassis **(Fig. 2)** and works under the command of the 89600 VSA software, the PXI VSA boasts an instantaneous bandwidth of 250 MHz. The VSA incorporates an internal 10-MHz reference oscillator with ±1 ppm/year aging rate and achieves ±0.5 dB amplitude accuracy to 26.5 GHz. It has a DANL of –158 dBm/Hz to 9.5 GHz and –147 dBm/Hz to 26.5 GHz, with phase noise of –115 dBc/Hz offset 10 kHz from a 10-GHz carrier.

In addition to instruments, Agilent offers chassis products, such as the model M9703A AXIe eight-channel digitizer **(Fig. 3)**. The single-slot 12-b digitizer has an analog bandwidth of DC to 1 GHz and operates at sampling rates to 3.2 GSamples/s. The compact AXIe module includes four Virtex-6 FPGAs from Xilinx (www.xilinx.com) and 4 GB internal memory for robust signal analysis and processing.

The firm is not alone in offering AXIe modules, with companies such as Aeroflex also producing AXIe test equipment products. Guzik (www.guzik.com) is also one of an increasing number of computers to support the newest instrument module format, with its ADC 6000 series of AXIe digitizer modules. With one- to four-channel models with sampling rates to 40 GSamples/s (for one channel) and bandwidths to 13 GHz, these modules offer deep memories for complex signal capture.

Those accustomed to traditional instruments may doubt the capabilities of modular test equipment. Nonetheless, they can provide excellent results while passing test data at high speeds. MWRF


TO-8 YIGs Tune 3 To 13 GHz

These compact microwave oscillators can tune across customer-specified bands with generous output power, featuring low levels of spurious and SSB phase noise.

OSCILLATORS can be built from many different types of resonators. Perhaps one of the most reliable for high-frequency applications is the yttrium-iron-garnet (YIG) sphere, the heart of YIG-tuned oscillators. At one time, such tunable sources were relatively large and heavy. But with new models such as the second-generation MLTO-Series of permanent-magnet YIG oscillators from Micro Lambda Wireless (www.microlambdawireless.com), these microwave oscillators take up no more space than a small coin on a printed-circuit board (PCB). Diminutive oscillators in the MLTO Series are supplied in tiny TO-8 housings and are available in selected tuning ranges from 3 to 13 GHz.

These oscillators can be constructed with pin or coaxial connectors **(see figure)**. They are designed for operating voltages of +8 and –5 VDC and deliver consistent performance across operating (case) temperatures from 0 to +65°C. The oscillator series currently includes models MLTO-50365 for use from 3.0 to 6.5 GHz, MLTO-50409 for use from 4.0 to 9.0 GHz, and MLTO-50613 with a tuning range of 6.5 to 13.0 GHz. Each oscillator has a free-running frequency, which is varied as current is applied to the permanent-magnet resonant cavity with its YIG sphere.

Each model provides at least +10 dBm output power across its tuning range, with worst-case power variations contained within a 3-dB window. Frequency drift over temperature is a maximum of ±25 MHz in the two lower-frequency oscillators and ±20 MHz in the MLTO-50613.



MLTO-Series oscillators can be supplied in 0.875-in.-diameter TO-8 housings with pin or coaxial connectors and operating frequencies to 13 GHz.

MLTO-50365 exhibits harmonics of –12 dBc or better and spurious levels of –70 dBc or better from 3.0 to 6.5 GHz. It has phase noise of –100 dBc/Hz or better offset 10 kHz from the carrier, improving to –128 dBc/Hz or better offset 100 kHz from the carrier, and typically –130 dBc/Hz offset 100 kHz from the carrier. It suffers typical pulling of frequency of a mere 2 MHz into a load with 12-dB return loss, and typical pushing with power supply of 2 MHz/V at +8 VDC.

As with the other oscillators in the series, the MLTO-50365 has a main tuning coil and a frequency-modulation (FM) coil for modulation and phase-locking purposes when used in a frequency synthesizer design. The main coil sensitivity is typically 9 MHz/mA while the FM coil sensitivity is 150 kHz/mA. The MLTO-50365 YIG oscillator draws a maximum of 60 mA from +8 VDC and 20 mA from –5 VDC.

Moving up in frequency, model MLTO-50409 tunes from 4.0 to 9.0 GHz, with harmonic and spurious levels that meet or exceed –12 and –70 dBc, respectively. The phase noise is –100 dBc/Hz or better offset 10 kHz from the carrier and –128 dBc/Hz or better offset 100 kHz from the carrier, with typical phase noise of –130 dBc/Hz offset 100 kHz from the carrier. Frequency pulling is typically 2 MHz into a 12-dB-return-loss load while frequency pushing is typically 2 MHz/V with supply variations centered at +8 VDC. The main tuning coil sensitivity is typically 15 MHz/mA while the FM tuning coil sensitivity is typically 150 kHz/mA. Model MLTO-50409 draws maximum power of 60 mA from a +8-VDC supply and 20 mA from a –5-VDC supply.

The MLTO-5613 operates from 6.5 to 13.0 GHz, with similar tuning characteristics as the others. It also exhibits harmonics of –12 dBc or better and spurious performance of –70 dBc or better. The phase noise is at least –98 dBc/Hz offset 10 kHz from the carrier and at least –123 dBc/Hz offset 100 kHz from the carrier, with typical phase noise of –125 dBc/Hz offset 100 kHz from the carrier. The MLTO-5613 operates on 60 mA at +8 VDC and 15 mA at –5 VDC.


The TO-8 packages are only 0.5 in. tall with 0.675-in. diameter, facilitating attachment to tight spots on PCBs. Extended temperature versions to +85°C are available for all models. P&A: 6 wks. ARO.—*JB*

MICRO LAMBDA WIRELESS, INC., 46515 Landing Pkwy., Fremont, CA 94538; (510) 770-9221, FAX: (510) 770-9213; *www.microlambdawireless.com.*

Envelope Tracking Makes Phones Smarter

Using envelope-tracking techniques, the efficiency of the power amplifiers found in cellular telephones can be improved.

POWER AMPLIFIER DESIGNERS supporting wireless communications aim for high efficiency, often through innovative biasing schemes. These schemes typically use only as much energy as needed by the active devices to meet transmit power requirements. Now, however, there is an easier way to boost the power-added efficiency (PAE) of a power amplifier: through the addition of a Coolteq.L envelope-tracking integrated circuit (IC) from Nujira Ltd. (www.nujira.com). The firm's recently announced model NCT-L1100 power-supply-modulator chip closely tracks an amplifier's amplitude or power envelope, dynamically adjusting the supply voltage as needed to consume less power and raise PAE.



Model NCT-L1100 is an envelope-tracking power-supply modulator designed to improve the efficiency of power amplifiers in 3G/4G cellular telephones. The IC is supplied in a low-profile WLCSP housing.

Traditional power amplifiers operate with a fixed voltage supply, working with a wide range of input power levels. The peak-to-average-power ratio (PAPR) of these signals can be large, with optimum efficiency occurring when the power amplifier is operating in compression when driving peak level signals. For lower-level signals, the amplifier is still supplied with a fixed voltage and current, although it may not require as much supply power.

Nujira's Coolteq.L employs the company's envelope-tracking (ET) technology, which tracks the signal envelope of a wireless handset transceiver and dynamically modulates the supply feeding the power amplifier. The technology is embodied within the company's lines of handset and base-station power-supply modulators, offering a high-efficiency alternative to conventional buck-boost DC/DC converters. In addition to tracking the signal envelope, the firm's ISOGAIN™ envelope-shaping technology enhances the linearity of the power amplifier, all the while maintaining its compressed operation for maximum PAE.

The model NCT-L1100 is the first of Nujira's Coolteq.L line of power-supply modulators designed for use in small, portable devices. It can operate with voltage supplies from 2.50 to 5.25 V, such as cellular telephone handsets. It can also handle peak current to 1 A and provide average power levels to 1.2 W in support of efficiency as high as 80%. The integrated circuit (IC) features a wide-bandwidth, three-stage current supply, control, and ripple-elimination circuitry within a low-profile WLCSP housing **(see photo)**, allowing for ease of integration within an RF front end or power-amplifier module.

The Coolteq.L family is suitable for use in third-generation (3G) and fourth-generation (4G) cellular handsets. The firm also offers its Coolteq.h line of power-supply modulators for base-station applications. Power-supply modulators are available for bandwidths of 5, 10, and 20 MHz, in support of all cellular communications Long-Term-Evolution (LTE) frequency bands; they also include fast disable/enable functionality for use in time-division LTE (TD-LTE) systems. Side benefits of the reduction in amplifier power consumption include longer battery operating life and less heat produced by the amplifier within a handheld telephone.

As Nujira's Chief Executive Officer Tim Haynes notes, "The industry consensus is that Envelope Tracking will become the standard PA architecture for the next generation of handsets, because it is the only power optimization technology which delivers high efficiency over the entire spectrum used for 3G and 4G standards. As a result we see the launch of our first commercial chip for mobile handsets as a significant milestone—not just for Nujira, but for the mobile handset sector."

The Coolteq.L model NCT-L1100 uses the industry-standard OpenET analog envelope interface. The IC conforms to Mobile Industry Processor Interface (MIPI) alliance RF front-end (RFFE) specifications to enable a number of different operating modes, including for ET, average power tracking, bypass, and standby. The power-supply modulator, which can supply outputs from 0.5 to 5.0 V with buck-boost capability, is designed for operating temperatures from −40 to +85°C.—*JB*

NUJIRA LTD., Building 1010, Cambourne Business Park, Cambourne, Cambridge CB23 6DP, United Kingdom; (44) 1223-597900, e-mail: info@nujira.com, *www.nujira.com.*

USB Steers Digital Pads



Digital attenuators in the LDA series of compact Lab Brick® products are powered and controlled by a Universal Serial Bus (USB) connection to a laptop or personal computer (PC). These step attenuators are available for use through 6 GHz and are easily programmed to provide fixed attenuation or attenuation ramps, using a simple graphical user interface (GUI). Units range in capability from model LDA-102, which provides 63-dB attenuation in 0.5-dB steps from 0.1 to 1000.0 MHz to model LDA-602, which offers 63-dB attenuation in 0.5-dB steps from 6 to 6000 MHz. The compact units measure just 3.86 x 2.52 x 1.35 in. (98 x 54 x 34 mm) and weigh just 0.5 lb. (0.23 kg). They are supplied with a USB flash drive containing the GUI software and a digital version of the programming guide, along with a 6-ft.-long USB cable. The digital attenuators are compatible with computers running Microsoft Windows™ standard operating systems for personal computers, including Windows 2000, XP, Vista, and 7.

VAUNIX TECHNOLOGY CORP., 242 Neck Rd., Haverhill, MA 01835; (978) 662-7839, FAX: (978) 662-7842, ***www.vaunix.com.***

USB Meter Reads Power To 8 GHz


RFMW Ltd. has announced that it is offering applications and sales support for the model TED8000-40 Universal Serial Bus (USB) power sensor from Telemakus (www.telemakus.com). Designed for power measurements from 50 to 8000 MHz, the USB sensor uses a laptop or personal computer (PC) as the control and display; this enables it to replace a full-sized power meter. It can also be used with the company's low-cost USB signal sources to form a cost-effective, USB-controlled microwave scalar network analyzer. The power sensor achieves true root-mean-square (RMS) measurement accuracy over its frequency and power ranges, detecting power levels over a 50-dB dynamic range with 0.5-dB accuracy. No zeroing or cal standards are required for operation as factory calibration data is stored within the on-board flash memory. Installation files for the custom Graphical User Interface (GUI) are also resident in Flash.



RFMW, LTD., 90 Great Oaks Blvd., Ste. 107, San Jose, CA 95119; (408) 414-1450, e-mail: info@rfmw.com, ***www.rfmw.com.***

Amplifier Boosts 71 To 76 GHz

Model HHPAE-459 is a millimeter-wave power amplifier designed for use from 71 to 76 GHz. It provides small-signal gain of 29 dB over that frequency range, with +18-dBm output power at 1-dB compression. Based on monolithic-microwave-integrated-circuit (MMIC) technology, the amplifier operates from a single +6.5-VDC bias supply with an internal voltage regulator and bias sequencer. The amplifier is ideal for transmitters in E-band radio communications systems.



RENAISSANCE ELECTRONICS CORP., 12 Lancaster County Rd., Harvard, MA 01451; (978) 772-7774, FAX: (978) 772-7775, e-mail: sales@rec-usa.com, ***www.rec-usa.com.***

Conductive Foams Shield Cell Phones

Condux Plus™ electrically conductive foams provide excellent electrical conductivity, consistent mechanical properties, and outstanding electromagnetic (EM) shielding capabilities. These attributes enhance conductivity and improve shielding performance in small wireless devices, such as cellular telephones. The materials are available in different thicknesses (0.33, 0.53, and 0.73 mm) to serve a variety of circuit and package configurations. They feature consistent and reliable connectivity while also offering excellent mechanical stability over time and temperature. The typical compression set for 0.021-in.-thick (0.53-mm-thick) Condux Plus foam is only 2.5%. Condux Plus foam can also be used as an electromagnetic-interference (EMI) shielding material, with superb shielding effectiveness (SE) over a wide operating frequency range of 200 MHz to 10 GHz. Condux Plus materials are RoHS and REACH compliant, and will not deform with processing.

ROGERS CORP., One Technology Dr., Rogers, CT 06263; (860) 774-9605, FAX: (860) 779-5509, ***www.rogerscorp.com/hpf.***


Tiny Caps Feature Tight Tolerances

The Accu-P® line of RF capacitors has been augmented by some of the industry's smallest, tightest-tolerance capacitors available, with subminiature 01005-size chips now available with capacitance values from 0.05 to 2.40 pF. The capacitors, which are ideal for applications at VHF, UHF, and microwave frequencies, boast tolerances to within ±0.01 pF. The capacitors, which are fabricated with high-thermal-conductivity materials, incorporate high-purity electrodes for low effective series resistance (ESR). They achieve high breakdown voltages, high insulation resistance, and low loss at frequencies through 40 GHz. The Accu-P series capacitors are available in standard 01005, 0201, 0402, 0603, 0805, and 1210 chip sizes for use at temperatures from –55 to +125°C. They undergo inspection, test, and quality-control procedures in accordance with ISO9001 and MIL standards.

AVX CORP., One AVX Blvd., Fountain Inn, SC 29644; (864) 967-9304, ***www.avx.com.***

Switch Controls 0.1 To 2.7 GHz

Model SKY13388-465LF is a symmetrical, single-pole, four-throw (SP4T) switch designed for applications from 100 MHz to 2.7 GHz. Built with a silicon-on-insulator (SOI) process, the switch requires only two control lines for operation. The high-performance SP4T switch features typical isolation of better than 30 dB at 1.0 GHz and more than 23 dB at 2.7 GHz. The insertion loss is typically 0.60 dB at 2.2 GHz and 0.65 dB at 2.7 GHz. The switch, which runs on



supplies of +2.5 to +5.5 VDC, is rated for +37 dBm maximum input power. It exhibits an input 1-dB compression point of typically +36 dBm from 0.8 to 2.7 GHz, and an input third-order intercept point of typically +65 dBm. The switch is supplied in a compact quad flat no lead (QFN) housing measuring just 2 x 2 mm.

SKYWORKS SOLUTIONS, INC., 20 Sylvan Rd., Woburn, MA 01801; (781) 376-3000, FAX: (781) 376-3100, e-mail: sales@skyworksinc.com, ***www.skyworksinc.com.***


Mod/Demod Unit Spans 20 to 300 MHz

Model CMX973 is a combination of an IF/RF quadrature demodulator and quadrature IF/RF modulator, supplied in a 32-lead VQFN package. It operates from 20 to 300 MHz with in-phase/quadrature (I/Q) receive bandwidth of 10 MHz and I/Q transmit bandwidth of 25 MHz. The demodulator is suitable for superheterodyne architectures with IF frequencies up to 300 MHz and may be used in low IF systems or those converting to baseband. The modulator converts directly from baseband to the desired transmit frequency and features quadrature phase correction to minimize unwanted spectral components. It provides a 0-dBm modulator output level with better than 1-deg. I/Q phase matching and better than 0.5-dB gain matching. It operates from supplies of +3.0 to +3.6 VDC and consumes low current. The circuit, which is controlled by serial bus, is ideal for avionics radios, wireless data terminals, and software-defined radios (SDRs).

CML MICROCIRCUITS, Oval Park, Hatfield Rd., Langford, Maldon, England CM9 6WG; 44 (0)1621 875500, FAX: 44 (0)1621 875600, ***www.cmlmicro.com.***

VCO Maintains 3200 MHz Output

Model CVCO55CCQ-3200-3200 is a voltage-controlled oscillator (VCO) that operates at a center frequency of 3200 MHz. Its frequency is adjusted by a control voltage range of 0.5 to 4.5 V. The oscillator has typical phase noise of –115 dBc/Hz offset 10 kHz from the carrier. It delivers typical output power of +6 dBm with second-harmonic suppression of typically –12 dBc. Pushing and pulling are minimized to 0.3 MHz and 0.1 MHz/V, respectively. The VCO, which is supplied in a 0.5 x 0.5 in. SMD surface-mount package, draws maximum current of 27 mA from a +6-VDC




supply. It is ideal for use in digital radios, fixed wireless access, cellular base stations, and in satellite-communications (satcom) systems.

CRYSTEK CORP., 12730 Commonwealth Dr., Ft. Myers, FL 33913; (800) 237-3061, (239) 561-3311, FAX: (239) 561-1025, e-mail: sales@crystek.com, ***www.crystek.com.***

Amp/Attenuator Combo Covers 0.45 To 2.40 GHz

Model DVGA1-242+ is a digitally controlled variable gain amplifier; it combines a high-gain E-PHEMT amplifier with a wide-dynamic-range step attenuator, and is fabricated using CMOS on silicon. The end result is a variable gain amplifier with 30-dB nominal gain at 0-dB attenuation that features a 31.5-dB gain control range from 0.45 to 2.40 GHz. The digitally controlled attenuator includes a 6-b serial interface for fast switching and 0.5-dB step resolution. The attenuation accuracy is typically 0.1 dB. The amplifier achieves +23 dBm output power at 1-dB compression, with an output third-order intercept point of typically +35.2 dBm at 450 MHz and +37 dBm at 2.40 GHz. The amplifier and attenuator combination, which is supplied in a 5 x 5 mm surface-mount MCLP package, runs on supplies of +3 and +5 VDC. It is suitable for cellular communications and Global Positioning



System (GPS) receivers, among many other applications.

MINI-CIRCUITS, P.O. Box 350166, Brooklyn, NY 11235-0003; (718) 934-4500, FAX: (718) 332-4661, ***www.minicircuits.com.***

LNAs Limit Noise In Cellular Stations

A pair of low-noise amplifiers (LNAs) leverage GaAs E-pHEMT technology to achieve low noise figures through 2.7 GHz. Model TQP3M9036 operates from 400 to 1500 MHz with a noise figure of 0.45 dB at 900 MHz and the model TQP3M9037 runs from 1500 to 2700 MHz with a noise figure of 0.40 dB at 1900 MHz. Model TQP3M9036 features 19-dB gain at 900 MHz with +20-dBm output power at 1-dB compression and an output third-order intercept point of +35 dBm. Model TQP3M9037 offers 20-dB gain at 1900 MHz with +21-dBm output power at 1-dB compression and an output third-order intercept point of +36 dBm. Both LNAs include a biasing network that maintains stability over temperature through a current mirror and resistive feedback, and also provides a switching circuit for digital power-down capability. The amplifiers operate on bias voltages from +3 to +5 VDC and are housed in 2 x 2 mm DFN packages.

TRIQUINT SEMICONDUCTOR, INC., 2300 NE Brookwood Pkwy., Hillsboro, OR 97124; (503) 615-9000, FAX: (503) 615-8900, ***www.triquint.com.***

Advertiser	Website, E-Mail Address	Page
A		
Advanced Switch Technology	www.astswitch.com, email: info@astswitch.com	96
Agilent Technologies	www.metrictest.com/agilent/specan.jsp	17
Ansys Inc. Electronics Business Unit.	www.ansys.com	57
Applied Interconnect	www.onlinecables.com , email: sales@onlinecables.com	96
AR Worldwide	www.arworld.us	75
ARRA INC.	www.arra.com, email: sales@arra.com	IBC
AWR	www.awrcorp.com	4
C		
CIAO Wireless, Inc	www.ciaowireless.com, email: sales@ciaowireless.com	8
Coilcraft	www.coilcraft.com, email: info@coilcraft.com	10
Copper Mountain Technologies	www.coppermountaintech.com	74
D		
dBm, LLC.	www.dbmcorp.com.	22
Delta Electronics Manufacturing	www.deltarf.com, email: sales@deltarf.com	49
Dudley Labs	www.dudleylab.com/surplus.html, email: hdudley@dudleylab.com	96
E		
Eclipse Microwave	www.eclipsemicrowave.com, email: sales@eclipsemicrowave.com	67
Emerson Network Power	www.emersonconnectivity.com	53
F		
Fairview Microwave.	www.fairviewmicrowave.com, email: sales@fairviewmicrowave.com	18
H		
Herotek Inc	www.herotek.com, email: sales@herotek.com	13
Hittite Microwave Corporation	www.hittite.com	27
I		
International Manufacturing Services.	www.ims-resistors.com	66
L		
Lark Engineering Company	www.larkengineering.com, email: sales@larkengineering.com	80
Linear Technology Corporation	www.linear.com	89
M		
M/A-COM INC	www.macomtech.com	IFC
Maury Microwave, Inc	www.maurymw.com, email: maury@maurymw.com.	43
Meese Munich	www.electronica.de	68
Mini Circuits/Sci Components	www.minicircuits.com.	12
Mini Circuits/Sci Components	www.minicircuits.com.	23
Mini Circuits/Sci Components	www.minicircuits.com.	41
Mini Circuits/Sci Components	www.minicircuits.com.	55
Mini Circuits/Sci Components	www.minicircuits.com.	61
Mini Circuits/Sci Components	www.minicircuits.com.	65
Mini Circuits/Sci Components	www.minicircuits.com.	29
Mini Circuits/Sci Components	www.minicircuits.com.	35
Mini Circuits/Sci Components	www.minicircuits.com.	45
Mini Circuits/Sci Components	www.minicircuits.com.	47
Mini Circuits/Sci Components	www.minicircuits.com.	71
Mini Circuits/Sci Components	www.minicircuits.com.	79
Mini Circuits/Sci Components	www.minicircuits.com.	83
Mini Circuits/Sci Components	www.minicircuits.com.	87
Mini Circuits/Sci Components	www.minicircuits.com.	14-15
Mini Circuits/Sci Components	www.minicircuits.com.	30-31
MITEQ	www.miteq.com	1
MITEQ	www.miteq.com	11
N		
Narda An L-3 Communications	www.nardamicrowave.com.	3
National Instruments	www.ni.com/redefine	25
P		
Panasonic Corporation	www.panasonic.com/rfmodules	2
Phase Matrix.	www.phasematrix.com, email: sales@phasematrix.com	24
Planar Monolithics Industries	www.pmi-rf.com, email: sales@pmi-rf.com	BC
Polyfet RF Devices	www.polyfet.com	96
Pulsar Microwave Corp.	www.pulsarmicrowave.com, email: sales@pulsarmicrowave.com	69
R		
RF Depot.	www.rfdepot.com	63
RFMW Ltd.	www.rfmw.com.	6
S		
Sector Microwaves Inc Inc.	www.sectormicrowave.com	96
Skyworks Solutions, Inc.	www.skyworksinc.com	77
Stanford Research Systems	www.thinksrs.com	50
Synergy Microwave	www.synergymwave.com, email: sales@synergymwave.com.	7
Synergy Microwave	www.synergymwave.com, email: sales@synergymwave.com.	37
Synergy Microwave	www.synergymwave.com, email: sales@synergymwave.com.	81
T		
Tecdia	www.tecdia.com.	16
TTE Incorporated.	www.tte.com	58
W		
Wenteq Microwave Corporation	www.wenteq.com, email: sales@wenteq.com	96
Wright Technologies	www.wrighttec.com	96

*Domestic Edition only **International Edition only This index is provided as an additional service by the publisher, who assumes no responsibility for errors or omissions.

MARKETING & ADVERTISING STAFF

VICE PRESIDENT & MARKET LEADER
BILL BAUMANN
T: (201) 845-2403
F: (201)845-2484
bill.baumann@penton.com

BRAND DIRECTOR, e|DESIGN
TRACY SMITH
T: (913) 967.1324
F: (913) 514.6881
E: tracy.smith@penton.com

BRAND CHAMPION
DAVID MADONIA
T: (212)-204-4331
E: dave.madonia@penton.com

SOUTH
BILL YARBOROUGH
T: (713) 636-3809
T: (713) 523-8384
E: bill.yarborough@penton.com

NORTHERN CALIFORNIA, NEVADA, NORTHWEST
JAMIE ALLEN
T: (415) 608-1959
F: (913) 514-3667
E: jamie.allen@penton.com

ONLINE SALES DEVELOPMENT DIRECTOR
STEPHANIE CAMPANA
T: (312) 840-2403-8437
stephanie.campana@penton.com

WEB PRODUCTION & SALES COORDINATOR
JACKIE CROSS
T: (212) 204-4379
jackie.cross@penton.com

DIRECT CONNECTION ADS CLASSIFIED ADVERTISING
PHYLLIS L. SCHRODER
E: phyllis.schroder@penton.com
KEVIN DERN
E: kevin.dern@penton.com

EUROPEAN SALES REP
MARK DURHAM
T: +44 (0)7958 564137
E:mark.durham@penton.com

TAIWAN, R.O.C.
CHARLES C.Y. LIU
T: (886)-2-2727-7799
F: (886)-2-2728-3686

JAPAN
HIRO MORITA
T: 81-3-3261-4591
F: 81-3-3261-6126

KOREA
JO YOUNG SANG
T: 011-82-2-739-7840
F: 011-82-732-3662

CUSTOMER SERVICE - SUBSCRIPTIONS
New/Renew/Cancel/Change Address/Missing and Back Issues
T: 866-505-7173 F: 847-763-9673
E: microwaves&rf@halldata.com

Penton
Design Engineering & Sourcing Group

Subscription Assistance and Information: Microwaves & RF (ISSN 0745-2993) is published monthly, except semi-monthly in December. **Microwaves & RF** is sent free to individuals actively engaged in high-frequency electronics engineering. In addition, paid subscriptions are available. Subscription rates for U.S. are $95 for 1 year ($120 in Canada, $150 for International). Published by Penton Media, Inc., 9800 Metcalfe Ave., Overland Park, KS 66212-2216. Periodicals Postage Paid at Shawnee Mission, KS and at additional mailing offices.


POSTMASTER: Send change of address to Microwaves & RF, Penton Media Inc., P.O. Box 2095, Skokie, IL 60076-7995. For paid subscription requests, please contact: Penton Media Inc., P.O. Box 2100, Skokie, IL 60076-7800. Canadian Post Publications Mail agreement No. 40612608. Canadian GST# R126431964. Canada return address: Bleuchip International, P.O Box 25542,London, ON N6C6B2.

Back issues of **MicroWaves** and **Microwaves & RF** are available on microfilm and can be purchased from National Archive Publishing Company (NAPC). For more information, call NAPC at 734-302-6500 or 800-420-NAPC (6272) x 6578. Copying: Permission is granted to users registered with the Copyright Clearance Center, Inc. (CCC) to photocopy any article, with the exception of those for which separate copyright ownership is indicated on the first page of the article, provided that a base fee of $1.25 per copy of the article plus 60 cents per page is paid directly to the CCC, 222 Rosewood Dr., Danvers, MA 01923. (Code 0745–2993/02 $1.25 +.60) Copying done for other than personal or internal reference use without the expressed permission of Penton Media, Inc., is prohibited. Requests for special permission or bulk orders should be addressed in writing to the publisher.

Copyright © 2012 by Penton Media, Inc. All rights reserved. Printed in the U.S.

DAVE MADONIA (e) dave.madonia@penton.com, 212-204-4331 • **TRACY SMITH** (e) tracy.smith@penton.com, 913-967-1324

GaN Demo Amp
25W - 48Vdc - 11dB
TB222: 1-1000MHz




RF polyfet rf devices
Your Power MOSFET People
www.polyfet.com
TEL (805)484-4210

Polyfet RF Devices

AST Advanced Switch Technology
754 Fortune Cr, Kingston, ON
K7P 2T3, Canada.
613 384 3939
info@astswitch.com

Our line of Waveguide, Coaxial and Dual Switches are the most reliable in the industry, but don't just take our word for it. Join the hundreds of satisfied customers who use our switches every day.

www.astswitch.com



When only the best will do

Advanced Switch Technology


SECTOR MICROWAVE
Don't sweat over your switching needs.
Our Waveguide and Coaxial switches are COOL!!



(631)242-2300 PHONE (631)242-8158 FAX
WWW.SECTORMICROWAVE.COM

Sector

Cable Assemblies
1,000,000 RF Cables
@ OnlineCables.com



Applied Interconnect™
Phone: (408) 749-9900 Fax: (408) 734-9770
Sales@OnlineCables.com

Applied Interconnect

Dudley Lab





RF Amplifiers .01 to 40 GHz
+10dBm to 2,000 Watts
Hughes TWTA 1.0 to 40 GHz
Varian /CPI TWTA 1.0 to 18 GHz
MCL Klystron 12.7 to 14.5 GHz
Solid State 0.01 to 18 GHz
www.dudleylab.com/surplus.html
e-mail: hdudley@dudleylab.com
732-240-6895 NJ

Dudley Lab

RF Amplifiers, Isolators and Circulators from 20MHz to 40GHz

- Super low noise RF amplifiers
- Broadband low noise amplifiers
- Input PIN diode protected low noise amplifiers
- General purpose gain block amplifiers
- High power RF amplifiers and broadband power amplifiers





- RF isolators and circulators
- High power coaxial and waveguide terminations
- High power coaxial attenuators
- PIN diode power limiters
- Active up and down converters

Wenteq Microwave Corporation
1070 Hamilton Road, Suite A, Duarte, CA 91010
Phone: (626) 305-6666, Fax: (626) 602-3101
Email: sales@wenteq.com, Website: www.wenteq.com

Wenteq Microwave Corp.

Our switches are so COOL They're HOT HOT




SECTOR MICROWAVE
(631) 242-2300 PHONE
(631)242-8158 FAX
WWW.SECTORMICROWAVE.COM

Sector Microwave Industries, Inc.

Attention Advertisers:
For digital ad specifications and requirements, please visit the AD PRODUCTION web site:
www.pentondigitalads.com

Get a piece of the ARRA pie...



100 dB Variable Attenuators

100 dB Attenuators
Mmmm....

Freq Range	Atten vs Freq dB	Model #
500 - 1000 MHz	1.5	2952 - 100
900 - 1300 MHz	0.75	2-3952 - 100
1000 - 2000 MHz	1.5	3952 - 100X
2000 - 4000 MHz	1.5	4952 - 100 X
4000 - 8000 MHz	1.5	5952 - 100X

Insertion loss - 6 dB
VSWR - 1.5
Power - 15 cw
Temperature -30 to +120 C

Now, you can have your pie and eat it too! Only from ARRA! Four models that cover the 500 to 8000 MHz frequency range! Available in lower attenuation ranges. *Customerized to your requirements with little or no additonal charge.* Top performance. Super dial accuracy.

- Direct reading dial
- Extremely high reliability
- Non-contacting movable parts (our special recipe)
- High power version available (up to 200 W)
- Usage will not change calibration
- Attenuation will not vary with temperature
- Excellent phase characteristics
- Type N standard SMA connectors available

Applications include:
•TACAN •DME/IFF •Lab standards •Altimeter
Or any other requirements needing high attenuation and accurate dial reading.

Visit our website at www.arra.com
E-Mail: sales@arra.com

Some of the best attenuator recipes you can find are cooking at ARRA right now! Send for your copy today and get a piece of the ARRA pie.

... the last word in variable attenuators


ARRA INC.
15 Harold Court • Bay Shore NY 11706-2296
Tel 631-231-8400 Fax 631-434-1116

Efficient High Power Solid State Switches


- Amplifiers
- Attenuators - Variable
- DLVA & ERDLVA & SDLVA's
- DTO's
- Filters
- Form, Fit & Function Products
- Hybrids, Dividers & Couplers
- IFM's & Frequency Discriminators
- Integrated MIC/MMIC Modules
- I/Q Vector Modulators
- Limiters & Detectors
- Log Amplifiers
- Pulse & Bi-Phase Modulators
- Phase Shifters
- Rack & Chassis Mount Products
- Receiver Front Ends
- Single Sideband Modulators
- SMT & QFN Products
- Solid-State Switches
- Switch Matrices
- Switch Filter Banks
- Threshold Detectors
- USB Products

PIN Diode & FET High Efficiency Designs


- SPST thru SP16T
- Reflective and Absorptive
- Input Power up to 2kW Peak, 200W Average
- Custom Packages and Designs
- Form, Fit & Function Replacements



Model Number	Style	Frequency Range (GHz)	Insertion Loss (dB)	Isolation (dB)	Reflective / Absorptive	Switching Speed (nSec)	Operating Input Power	DC Voltage & Current
P1T-0R310R0G-60-R-SFF-20W	SPST	0.3 – 18.0	2.5	60	Reflective	250	20 Watt Peak 7 Watt Average	+5vdc@100mA -12vdc@50mA
P1T-1R0G18R0G-80-R-SFF-75W	SPST	1.0 – 18.0	2.5	80	Reflective	25	75 Watt Peak 2 Watt Average	+5vdc@65mA -12vdc@20mA
P1T-0R5G2R0G-80-R-SFF-LVT-10W	SPST	0.5 – 2.0	1.0	80	Reflective	25	10 Watt Peak 2 Watt CW	+5vdc@50mA -5vdc@5mA
P1T-0R6G1R3G-70-SFF-4W	SPST	0.6 – 1.3	1.5	70	Absorptive	30	4 Watts	+5vdc@100mA -5vdc@100mA
P2T-335M535M-30-R-SFF-20W	SPDT	0.335 – 0.535	0.9	45	Reflective	100	20 Watts	+5vdc@31mA
P2T-1G18G-10-R-528-SFF-HIP10W	SPDT	1.0 – 18.0	3.0	25	Reflective	40	10 Watts	+5vdc@5mA -28vdc@5mA
P2T-0R1G2R0G-40-SFF-100W	SPDT	1.0 – 2.0	1.5	40	Reflective	<1µSec	100 Watts CW	+5vdc@150mA -15vdc@70mA
PEC-9R510R7-100W-SFF-120W	SPDT	9.5 – 10.7	1.5	40	Reflective	400	120 Watts	+5vdc@160mA -28vdc@15mA
P2T-0R5G18G-60-SFF-10W	SPDT	0.5 – 18.0	1.5	60	Reflective	150	10 Watts	+5vdc@100mA -15vdc@75mA
P2T-14D415D4-15-SMT-20W Surface Mount, Driverless	SPDT	14.4 – 15.4	0.5	15	Reflective	50	20 Watts	Bias 50mA
P3T-0R1G2R0G-40-SFF-100W	SP3T	0.1 – 2.0	1.5	40	Reflective	<1µSec	100 Watts CW	+5vdc@150mA -15vdc@70mA
P3T-0R5G18G-70-SFF-200W	SP3T	0.5 – 18.0	3.75	70	Absorptive	100	200 Watts Peak 12 Watts CW	+5vdc@150mA -15vdc@100mA
P4T-2G18G-45-TFF-100W	SP4T	2.0 - 18.0	3.1	45	Reflective	200	100 Watts Peak 1 Watt CW	+5vdc@105mA -15vdc@70mA
P4T-0R1G2R0G-40-SFF-100W	SP4T	0.1 – 2.0	1.5	40	Reflective	<1µSec	100 Watts CW	+5vdc@150mA -15vdc@70mA
P4T-0R1G18G-65-SFF-75W	SP4T	0.1 – 18.0	2.6	65	Reflective	50	75 Watts Peak 1 Watt CW	+5vdc@150mA -15vdc@50mA
P4T-900M1300M-35-SFF-50W	SP4T	0.9 – 1.3	2.0	35	Absorptive	<5µSec	50 Watts	28vdc
P8T-2R37G2R39G-60-SFF-10W	SP8T	2.37 – 2.39	2.5	60	Reflective	<2µSec	10 Watts	+5vdc@500mA -27vdc@10mA
P8T-8G18G-50-SFF-10W	SP8T	8.0 – 18.0	4.0	50	Reflective	75	10 Watts Peak 4 Watts CW	+5vdc@450mA -15vdc@150mA







14.4 to 15.4 GHz
20 Watt, SPDT, SMT,
PIN DIODE SWITCH

PMI

PLANAR MONOLITHICS INDUSTRIES, INC.

7311-F Grove Road, Frederick, Maryland 21704 USA
Tel: 301-662-5019 | Fax: 301-662-1731
Email: sales@pmi-rf.com | www.pmi-rf.com

ISO9001:2008 Certified