

Mounting InstructionSHV Cable Jack + Cable RG58

1) Remove the cable sheath 25 mm → 2) Push back the braided shield and strip the isolation from the center conductor 3,5 mm 3) Push back the screen to the front end and twist it together 4) Put on the cable the srews, metal washer, clamping rubber and taper washer Push back the brained shield and cut it 5) along the outside of the taper washer 6) Solder the center contact 7) Push the parts together and screw them together