

Reissued: 30-Apr-99

Model: F401/411/421/C-Bird	Date: 15-Apr-99	No.: RA175012a
----------------------------	-----------------	----------------

RTB Correction

The items (cut-in serial number) in bold italics have been corrected.

Subject: DJF Software Modification History		Prepared by: F. Noguchi	
From: Technical Service Dept., GTS Division			
Classification:	<input checked="" type="checkbox"/> Troubleshooting	<input type="checkbox"/> Part information	<input type="checkbox"/> Action required
	<input type="checkbox"/> Mechanical	<input type="checkbox"/> Electrical	<input type="checkbox"/> Service manual revision
	<input type="checkbox"/> Paper path	<input type="checkbox"/> Transmit/receive	<input type="checkbox"/> Retrofit information
	<input type="checkbox"/> Other ()		

DJF modifications and history are as follows.

Main ROM(A6105820) modification history

Suffix	Description	Cut-in Serial Number
C	This ROM was used from the first production run.	A610-15: A16060001 A610-17: A7146060001 A610-22: AB86060001 A610-26: J90660001
D	To prevent original jams: In the limitless mode, if a new original is fed while the paper trays are being switched, a jam will occur.	Not implemented
E	This version is the same as that of "C". Notes A software change will not prevent original jams in the limitless mode if a new original is fed while the paper trays are being switched. Since the occurrence rate of this problem is extremely low, this is being treated as a product limitation.	A610-15: 6A16120001 A610-17: A7146110001 A610-22: AB87010001 A610-26: 3J90170001
F	Standardization with the Penguin series	A610-15: 6A18030001 A610-17: A714803000 A610-22: AB88030001 A610-26: 3J90680001
G	To prevent the following problems when the 2 in 1 mode is used: ● The machine stops (but the print key remains red) after the job if the number of originals and the number input on the main unit differ. ● After an odd number of originals is used, the image in the next copy job is elongated or a paper jam occurs.	A610-15: 6A18060001 A610-17: A7148060001 A610-22: AB88060001 A610-26: 3J90680001
H	To prevent original non-feed out in European version main frame machines: Due to the difference in the feed-in and feed-out timing for the B6Y size paper, three originals will be set on the exposure glass at the same time as opposed to two.	A610-15: 6A18100001 A610-17: A7148100001 A610-22: AB88100001 A610-26: 3J91080001