

Universal Automobile Adapter for Mobile Office Equipment

The ideal mobile office companion from Xantrex, XPower Micro Inverter 175 is the smallest 175-watt power inverter on the market today. It incorporates high-frequency technology to convert power from a vehicle's battery (12-volt DC) into standard utility power (115-volt AC, 60 Hz). By plugging the XPower Micro Inverter 175 into a vehicle's lighter socket, users can conveniently recharge and run electronic devices such as cell phones, camcorders, laptop computers, PDAs, 13" TV/VCRs and computer games - without the need for multiple adaptors.

Product Features

- Converts DC power from vehicle battery into 115 VAC power
- Three-prong AC outlet to handle all chargers and adapters for mobile electronics: cellular, telephones, laptops, computers, camcorders, game consoles and 13" TV/VCRs
- LED indicator notification of power availbility
- Stylish plastic case with molded-in lighter connector
- Compact and lightweight
- One year warranty

Protection Features

- Over-temperature shutdown
- Low battery voltage shutdown (10.5 VDC and automatic reset)
- Overload shutdown
- Internal fuse 20 A (user changeable)



Xantrex Technology Inc.

Headquarters 8999 Nelson Way Burnaby, British Columbia Canada V5A 4B5 800 670 0707 Toll Free 604 420 1591 Fax

5916 195th Street NE Arlington, Washington USA 98223 800 446 6180 Toll Free 360 925 5144 Fax

www.xantrex.com

| Electrical Specifications | |
|-----------------------------------|-------------------------------------|
| AC output power (max. continuous) | 140 W |
| AC output power (5 min.) | 175 W |
| AC output voltage | 115 +/- 10 volts AC RMS |
| AC output frequency | 60 +/- 4 Hz |
| AC output waveform | Modified sine wave |
| DC input voltage range | 10.5-15.5 volts DC |
| Battery drain with no AC load | <0.35 amps DC (at 12 V input) |
| Dimensions (H x W x L) | 1.9 x 2.9 x 4.8" (49 x 73 x 141 mm) |
| Weight | 0.38 lb (175 g) |
| Warranty | One year |
| Part Number | 851-0178 |

Note: Specifications subject to change without



| XPower Micro Inverter 175 Packaging Sp | | | |
|--|------------------------|--|--|
| FGA / Part # | 851-0178 | | |
| UPC | 7 15535 11164 9 | | |
| Pallet Count | 330 | | |
| Pallet Dimensions (LxWxH) | 40" x 48" x 48" | | |
| Pallet Weight | 575 lbs | | |
| Master Carton Count | 20 | | |
| Master Carton Size (LxWxH) | 22.65" x 15.5" x 9.05" | | |
| Master Carton Weight | 18.85 lbs | | |
| Master Carton Volume | 3,177 | | |
| Inner Carton Count | 10 | | |
| Inner Carton Size (LxWxH) | 14.9" x 11.03" x 7.95" | | |

| ci | cifications | | | |
|----|--|-----------------------|--|--|
| | Inner Carton Weight | 8.32 lbs | | |
| _ | Retail Package Type | Blister Inside Box | | |
| _ | Retail Package Size (LxWxH) | 7.25" x 2.13" x 7.25" | | |
| _ | Retail Package Weight | 0.73 lb | | |
| | Unit Weight | 0.35 lbs | | |
| | Unit Dimensions (LxWxH) | 4.8" x 2.76" x 1.77" | | |
| - | Container Quantities: assume 8 pallets per | | | |
| | 20' container and 18 per 40' container. | | | |
| _ | 20' Container | 2, 640 | | |
| _ | 40' Container | 5,940 | | |
| - | | | | |

